Neural Stochastic Control

Jingdong Zhang[1]   **Qunxi Zhu**[2,*]   **Wei Lin**[1,2,3,4,5*]

[1] School of Mathematical Sciences, SCMS, SCAM, and CCSB, Fudan University
[2] Research Institute of Intelligent Complex Systems
and MOE Frontiers Center for Brain Science, Fudan University
[3] Key Laboratory of Computational Neuroscience
and Brain-Inspired Intelligence, Fudan University
[4] State Key Laboratory of Medical Neurobiology, Institutes of Brain Science, Fudan University
[5]Shanghai Artificial Intelligence Laboratory

{zhangjd20,qxzhu16,wlin}@fudan.edu.cn

Abstract

Control problems are always challenging since they arise from the real-world systems where stochasticity and randomness are of ubiquitous presence. This naturally and urgently calls for developing efficient neural control policies for stabilizing not only the deterministic equations but the stochastic systems as well. Here, in order to meet this paramount call, we propose two types of controllers, viz., the exponential stabilizer (ES) based on the stochastic Lyapunov theory and the asymptotic stabilizer (AS) based on the stochastic asymptotic stability theory. The ES can render the controlled systems exponentially convergent but it requires a long computational time; conversely, the AS makes the training much faster but it can only assure the asymptotic (not the exponential) attractiveness of the control targets. These two stochastic controllers thus are complementary in applications. We also investigate rigorously the linear controller and the proposed neural stochastic controllers in both convergence time and energy cost and numerically compare them in these two indexes. More significantly, we use several representative physical systems to illustrate the usefulness of the proposed controllers in stabilization of dynamical systems.

1 Introduction

In the field of controlling dynamical systems, one of the major missions is to find efficient control policies for stabilizing ordinary differential equations (ODEs) to targeted equilibriums. The policies for stabilizing linear or polynomial dynamical systems have been fully developed using the standard Lyapunov stability theory, e.g., the linear quadratic regulator (LQR) Khalil (2002) and the sum-of-squares (SOS) polynomials through the semi-definite planning (SDP) Parrilo (2000). As for stabilizing more general and nonlinear dynamical systems, linearization technique around the targeted states is often utilized and thus the existing control policies are effective in the vicinity of the targeted states (Sastry & Isidori, 1989) but likely lose efficacy in the region far away from those states. Moreover, in real applications, the explicit forms of the controlled nonlinear systems are often partially or completely unknown, so it is very difficult to directly design controllers only using the Lyapunov stability theory. To overcome these difficulties, designing the controllers via training neural networks (NNs) become one of the mainstream approaches in the community of cybernetics (Polycarpou, 1996). Recent outstanding developments using NNs include enlarging the safe region

---

*To whom correspondence should be addressed: Q.Z. and W.L,
https://faculty.fudan.edu.cn/wlin/zh_CN/index.htm.

(Richards et al., 2018), learning the stable dynamics (Takeishi & Kawahara, 2021), and constructing the Lyapunov function and the control function simultaneously (Chang et al., 2019). In Kolter & Manek (2019) a projected NN has been constructed to directely learn a stable dynamical system and fits the observed time series data well, but it did not focus on learning a control policy to stabilize the original dynamics. All these existing developments are formulated only for deterministic systems but inapplicable directly to the dynamical systems described by stochastic differential equations (SDEs), requiring us to include the stochasticity appropriately into the use of neural controls to different types of dynamical systems.

The stability theory for stochastic systems has been systematically developed in the past several decades. Representative contributions in the literature include the Lyapunov-like stability theory for SDEs Mao (2007), stabilization of unstable states in ODEs only using noise perturbations Mao (1994b), and the stability induced by randomly switching structures Guo et al. (2018). Generally, for any SDEs governed by $\mathrm{d}\boldsymbol{x} = f(\boldsymbol{x})\mathrm{d}t + g(\boldsymbol{x})\mathrm{d}B_t$, control policies as $\boldsymbol{u} = (\boldsymbol{u}_f, \boldsymbol{u}_g)$ are introduced, which transforms the original equations into the controlled system $\mathrm{d}\boldsymbol{x} = [f(\boldsymbol{x}) + \boldsymbol{u}_f(\boldsymbol{x})]\mathrm{d}t + [g(\boldsymbol{x}) + \boldsymbol{u}_g(\boldsymbol{x})]\mathrm{d}B_t$. Appropriate forms of control policies are able to steer the controlled system to the equilibriums that are unstable in the original SDEs. Traditional control methods focus on designing deterministic control $\boldsymbol{u}_f$ and regard noise as negative part. Innovatively, we treat noise as a beneficial part and design stochastic control $\boldsymbol{u}_g$ to achieve the stabilization.

Figure 1: Sketches of the two frameworks of neural stochastic controller. Both the ES and AS find control function $\boldsymbol{u}$ with fully connected feedforward NN (FNN).

In this article, we articulate two frameworks of neural stochastic control which can complement each other in terms of convergence rate and the computational time of training NNs. Additionally, we analytically investigate the convergence time and the energy cost for the classic linear control and the proposed neural stochastic control and numerically compare them. We further extend our frameworks to model-free case with existing data reconstruction methods. The major contributions of this article are multi-folded, including:

- designing two frameworks of neural stochastic control, viz., the ES and the AS, and presenting their advantages in the stochastic control,
- providing theoretical estimation for ES/AS and classic linear control in terms of convergence time and the energy cost,
- computing the convergence time and the energy cost of particular stochastic neural control,
- demonstrating the efficacy of the proposed stochastic neural control in important control problems arising from representative physical systems, and we make our code available at `https://github.com/jingddong-zhang/Neural-Stochastic-Control`.

1.1 Related Works

● **Lyapunov Method in Machine Learning** The recent work Chang et al. (2019) proposed an NN framework of learning the Lyapunov function and the linear control function simultaneously for stabilizing ODEs. In comparison, we select several specific types of NNs which have typical properties of the Lyapunov function. For instance, we use the input convex neural network (ICNN) Amos et al. (2017), constructing a positively definite convex function as a neural Lyapunov function (Kolter & Manek, 2019; Takeishi & Kawahara, 2021), and we construct the NN in a quadratic form (Richards et al., 2018; Gallieri et al., 2019) for linear or sublinear systems where the SDP method is often used to find the SOS-type Lyapunov function (Henrion & Garulli, 2005; Jarvis-Wloszek et al., 2003; Parrilo, 2000).

● **Stochastic Stability Theory of SDEs** Stochastic stability theory for SDEs have been systematically and fruitfully achieved in the past several decades (Kushner, 1967; Arnold, 2007; Mao, 1991, 1994a). The positive effects of stochasticity have also been cultivated in control fields (Mao

et al., 2002; Deng et al., 2008; Caraballo et al., 2003; Appleby et al., 2008; Mao et al., 2007). These, therefore, motivate us to develop *only* neural stochastic control to stabilize different sorts of dynamical systems in this article. More stochastic stability theory for different kinds of systems are included in Appleby et al. (2006); Appleby (2003); Caraballo & Robinson (2004); Wang & Zhu (2017).

2   Preliminaries

To begin with, we consider the SDE which is written in a general form as:

$$d\boldsymbol{x}(t) = F(\boldsymbol{x}(t))dt + G(\boldsymbol{x}(t))dB_t, \ \ t \geq 0, \ \boldsymbol{x}(0) = \boldsymbol{x}_0 \in \mathbb{R}^d, \tag{1}$$

where $F : \mathbb{R}^d \to \mathbb{R}^d$ is the drift function, and $G : \mathbb{R}^d \to \mathbb{R}^{d \times r}$ is the diffusion function with $\mathbb{R}^{d \times r}$, a space of $d \times r$ matrices with real entries, and $B_t \in \mathbb{R}^r$, a r-dimensional (r-D) Brownian motion. Without loss of generality, we set $F(\mathbf{0}) = \mathbf{0}$ and $G(\mathbf{0}) = \mathbf{0}$ so that $\boldsymbol{x}_0 = \mathbf{0}$ is a zero solution Eq. (1).

Notations. Denote by $\|\cdot\|$ the L^2-norm for any given vector in $\mathbb{R}^d$. Denote by $|\cdot|$ the absolute value of a scalar number or the modulus length of a complex number number. For $A = (a_{ij})$, a matrix of dimension $d \times r$, denote by $\|A\|_{\mathrm{F}}^2 = \sum_{i=1}^d \sum_{j=1}^r a_{ij}^2$ the Frobenius norm.

Assumption 2.1 *(Locally Lipschitzian Continuity) For every integer $n \geq 1$, there is a number $K_n > 0$ such that*

$$\|F(\boldsymbol{x}) - F(\boldsymbol{y})\| \leq K_n \|\boldsymbol{x} - \boldsymbol{y}\|, \ \|G(\boldsymbol{x}) - G(\boldsymbol{y})\|_{\mathrm{F}} \leq K_n \|\boldsymbol{x} - \boldsymbol{y}\|,$$

for any $\boldsymbol{x}, \boldsymbol{y} \in \mathbb{R}^d$ with $\|\boldsymbol{x}\| \vee \|\boldsymbol{y}\| \leq n$.

Definition 2.1 *(Derivative Operator) Define the differential operator $\mathcal{L}$ associated with Eq. (1) by*

$$\mathcal{L} \triangleq \sum_{i=1}^d F_i(\boldsymbol{x}) \frac{\partial}{\partial x_i} + \frac{1}{2} \sum_{i,j=1}^d [G(\boldsymbol{x})G^\top(\boldsymbol{x})]_{ij} \frac{\partial^2}{\partial x_i \partial x_j}.$$

Definition 2.2 *(Exponential Stability) The zero solution of Eq. (1) is said to be almost surely exponentially stable, if $\limsup_{t \to \infty} \frac{1}{t} \log \|\boldsymbol{x}(t; \boldsymbol{x}_0)\| < 0$ a.s. for all $\boldsymbol{x}_0 \in \mathbb{R}^d$. Here and throughout, a.s. stands for the abbreviation of almost surely.*

Then, the following Lyapunov stability theorem will be used in the establishment of our main results.

Theorem 2.2 *Mao (2007) Suppose that Assumptions 2.1 holds. Suppose further that there exist a function $V \in C^2(\mathbb{R}^d; \mathbb{R}_+)$ with $V(\mathbf{0}) = 0$, constants $p > 0$, $c_1 > 0$, $c_2 \in \mathbb{R}$ and $c_3 \geq 0$, such that (i) $c_1 \|\boldsymbol{x}\|^p \leq V(\boldsymbol{x})$, (ii) $\mathcal{L}V(\boldsymbol{x}) \leq c_2 V(\boldsymbol{x})$, and (iii) $|\nabla V^\top(\boldsymbol{x})G(\boldsymbol{x})|^2 \geq c_3 V^2(\boldsymbol{x})$ for all $\boldsymbol{x} \neq 0$ and $t \geq 0$. Then,*

$$\limsup_{t \to \infty} \frac{1}{t} \log \|\boldsymbol{x}(t; t_0, \boldsymbol{x}_0)\| \leq -\frac{c_3 - 2c_2}{2p} \ \ a.s.. \tag{2}$$

In particular, if $c_3 - 2c_2 > 0$, the zero solution of Eq. (1) is exponentially stable almost surely.

The following asymptotic theorem also will be used in the establishment of our main results.

Theorem 2.3 *Appleby et al. (2008) Suppose that Assumptions 2.1 holds. Suppose further $\min_{\|\boldsymbol{x}\|=M} \|\boldsymbol{x}^\top G(\boldsymbol{x})\| > 0$ for any $M > 0$ and there exists a number $\alpha \in (0, 1)$ such that*

$$\|\boldsymbol{x}\|^2 (2\langle \boldsymbol{x}, F(\boldsymbol{x})\rangle + \|G(\boldsymbol{x})\|_{\mathrm{F}}^2) - (2 - \alpha)\|\boldsymbol{x}^\top G(\boldsymbol{x})\|^2 \leq 0, \ \ \forall \boldsymbol{x} \in \mathbb{R}^d. \tag{3}$$

Then, the unique and global solution of Eq. (1) satisfies $\lim_{t \to \infty} \boldsymbol{x}(t, \boldsymbol{x}_0) = \mathbf{0}$ a.s., and we call this property as asymptotic attractiveness.

3   Designing Stable Stochastic Controller

Here, we assume that the zero solution of the following SDE:

$$d\boldsymbol{x} = f(\boldsymbol{x})dt + g(\boldsymbol{x})dB_t \tag{4}$$

is unstable. Note that, for any nontrivial targeted equilibrium $\boldsymbol{x}^*$, a direct transformation $\boldsymbol{y} = \boldsymbol{x} - \boldsymbol{x}^*$ can make the zero solution as the equilibrium of the transformed system. Thus, our mission is to

stabilize the zero solution only. As such, we are to use the NNs to design the control $\boldsymbol{u} : \mathbb{R}^d \to \mathbb{R}^{d \times r}$ with $\boldsymbol{u}(\mathbf{0}) = \mathbf{0}$ and apply it to Eq. (4) as

$$\mathrm{d}\boldsymbol{x} = f(\boldsymbol{x})\mathrm{d}t + [g(\boldsymbol{x}) + \boldsymbol{u}(\boldsymbol{x})]\mathrm{d}B_t. \tag{5}$$

Since $\boldsymbol{u}$ is integrated with $\mathrm{d}B_t$ in the controlled system (5), we regard it as a stochastic controller. In what follows, two frameworks of neural stochastic control, the exponential stabilizer (ES) and the asymptotic stabilizer (AS), are articulated, respectively, in Sections 3.1 and 3.2. All these control policies are intuitively depicted in Figure 1.

3.1 Exponential Stabilizer

Once we find the Lyapunov function V and the neural controller $\boldsymbol{u}$, making the controlled system (5) meet all the conditions assumed in Theorem 2.2, the equilibrium $\mathbf{0}$ can be exponentially stabilized. To this end, we first provide two different types of functions for constructing V, which actually could be complementary in applications. Then, we design the explicit forms of control function and loss function.

ICNN V Function. We use the ICNN (Amos et al., 2017) to represent the candidate Lyapunov function V. This guarantees V as a convex function with respect to the input $\boldsymbol{x}$. In order to further make V as a true Lyapunov function, we use the following form:

$$\begin{aligned}
&\boldsymbol{z}_1 = \sigma_0(W_0\boldsymbol{x} + b_0), \ \ \boldsymbol{z}_{i+1} = \sigma_i(U_i\boldsymbol{z}_i + W_i\boldsymbol{x} + b_i), \\
&g(\boldsymbol{x}) \equiv \boldsymbol{z}_k, \ \ i = 1, \cdots, k-1, \\
&V(\boldsymbol{x}) = \sigma_{k+1}(g(\mathcal{F}(\boldsymbol{x})) - g(\mathcal{F}(\mathbf{0}))) + \varepsilon\|\boldsymbol{x}\|^2,
\end{aligned} \tag{6}$$

as introduced in Manek & Kolter (2020). Here, W_i, b_i are real-valued weights, U_i are positive weights, σ_i are convex, monotonically non-decreasing activation functions in the i-th layer, ε is a small positive constant, and $\mathcal{F}$ is a continuously differentiable and invertible function. In our framework, we require $V \in C^2(\mathbb{R}^d; \mathbb{R}_+)$ according to Definition 2.1; however, each activation function $\sigma_i \equiv \sigma$ in Manek & Kolter (2020) is C^1 only. Thus, we modify the original function as:

$$\sigma(x) = \begin{cases} 0, & \text{if } x \leq 0, \\ (2dx^3 - x^4)/2d^3, & \text{if } 0 < x \leq d, \\ x - d/2, & \text{otherwise} \end{cases} \tag{7}$$

Figure 2: The smoothed **ReLU** $\sigma(\cdot)$.

which not only approximates the typical **ReLU** activation but also becomes continuously differentiable to the second order (see Figure 2).

Quadratic V Function. For any $\boldsymbol{x} \in \mathbb{R}^d$, let $V_{\boldsymbol{\theta}} \in \mathbb{R}^d$ be a multilayered feedforward NN of the input $\boldsymbol{x}$ and with $\tanh(\cdot)$ as the activation functions, where $\boldsymbol{\theta}$ is the parameter vector. To meet the condition used in Definition 2.1, we cannot use the **ReLU**, a non-smooth function, as the activation function. Hence, we use the candidate Lyapunov function as:

$$V(\boldsymbol{x}) = \boldsymbol{x}^\top \left[\varepsilon I + V_{\boldsymbol{\theta}}(\boldsymbol{x})^\top V_{\boldsymbol{\theta}}(\boldsymbol{x})\right] \boldsymbol{x}, \tag{8}$$

which was introduced in Gallieri et al. (2019). Here, ε is a small positive constant.

Control Function. We introduce a multi-layer feedforward NN (FNN), denoted by $\mathbf{NN}(\boldsymbol{x}) \in \mathbb{R}^r$, to design the controller $\boldsymbol{u}$. Since we require $\boldsymbol{u}(\mathbf{0}) = \mathbf{0}$, we set $\boldsymbol{u}(\boldsymbol{x}) \triangleq \mathbf{NN}(\boldsymbol{x}) - \mathbf{NN}(\mathbf{0})$ or $\boldsymbol{u}(\boldsymbol{x}) \triangleq \mathrm{diag}(\boldsymbol{x})\mathbf{NN}(\boldsymbol{x})$ with $r = d$. Here, $\mathrm{diag}(\boldsymbol{x})$ is a diagonal matrix with its i-th diagonal element as x_i.

Remark 3.1 *As reported in Chang et al. (2019), a single-layer NN without the bias constants in its arguments, which degenerates as linear control, could sufficiently take effect in the stabilization of many deterministic systems. However, this is NOT always the case for achieving the stabilization of highly nonlinear systems or even SDEs. The following proposition with Figure 3 provides an example, where neither the classic linear controller nor the stochastic linear controller can stabilize the unstable equilibrium in a particular SDE. The proof of this proposition is included in Appendix A.1.*

Proposition 3.2 *Consider the following* 1-D *SDE:*

$$\mathrm{d}x(t) = x(t) \log |x(t)| \mathrm{d}t + u(x(t)) \mathrm{d}B_t, \qquad (9)$$

with a zero solution $x^* = 0$. *Then, for* $u(x) = kx$ *with any* k *and* $x_0 \neq 0$, $x^* = 0$ *is neither exponentially stable nor of globally asymptotic attractiveness almost surely. For* $u(x) = 2x^2$, $x^* = 0$ *is of globally asymptotic attractiveness. For* $u(x) \equiv 0$, *the deterministic system cannot be stabilized by any classic linear controller.*

Loss Function. When the learning procedure updates the parameters in the NNs such that the constructed V and $\boldsymbol{u}$ with the coefficient functions, f and $g_{\boldsymbol{u}} \triangleq g + \boldsymbol{u}$, in the controlled system (5) meet all the conditions assumed in Theorem 2.2, the exponential stability of the controlled system is assured. Thus, we demand

Figure 3: (a) $u(x) = kx$, (b) $u(x) = 2x^2$.

a suitable loss function to evaluate the likelihood that those conditions are satisfied. First, from Theorem 2.2, it follows that $V(\boldsymbol{x}) \geq \varepsilon \|\boldsymbol{x}\|^2$ for all $\boldsymbol{x} \in \mathbb{R}^d$. Thus, Conditions (ii)-(iii) together with $c_3 - 2c_2 > 0$ in Theorem 2.2 equivalently become

$$\inf_{\boldsymbol{x} \neq 0} \frac{(\nabla V(\boldsymbol{x})^\top g_{\boldsymbol{u}}(\boldsymbol{x}))^2}{V(\boldsymbol{x})^2} \geq b \cdot \sup_{\boldsymbol{x} \neq 0} \frac{\mathcal{L}V(\boldsymbol{x})}{V(\boldsymbol{x})}, \quad b > 2. \qquad (10)$$

These conditions further imply that

$$\frac{(\nabla V(\boldsymbol{x})^\top g_{\boldsymbol{u}}(\boldsymbol{x}))^2}{V(\boldsymbol{x})^2} - b \cdot \frac{\mathcal{L}V(\boldsymbol{x})}{V(\boldsymbol{x})} \geq 0, \quad b > 2, \ \boldsymbol{x} \neq 0. \qquad (11)$$

With these reduced conditions, we design the ES loss function for the controlled system (5) as follows.

Definition 3.1 *(ES loss)* Consider a candidate Lyapunov function V and a controller $\boldsymbol{u}$ for the controlled system (5). Then, the ES loss is defined as

$$L_{\mu,b,\varepsilon}(\boldsymbol{\theta}, \boldsymbol{u}) = \mathbb{E}_{\boldsymbol{x} \sim \mu} \Big[\max \Big(0, \frac{b \cdot \mathcal{L}V(\boldsymbol{x})}{V(\boldsymbol{x})} - \frac{(\nabla V(\boldsymbol{x})^\top g_{\boldsymbol{u}}(\boldsymbol{x}))^2}{V(\boldsymbol{x})^2} \Big) \Big],$$

where the state variable $\boldsymbol{x}$ obeys the distribution μ. In practice, we consider the following empirical loss function:

$$L_{N,b,\varepsilon}(\boldsymbol{\theta}, \boldsymbol{u}) = \frac{1}{N} \sum_{i=1}^{N} \max \Big(0, \frac{b \cdot \mathcal{L}V(\boldsymbol{x}_i)}{V(\boldsymbol{x}_i)} - \frac{(\nabla V(\boldsymbol{x}_i)^\top g_{\boldsymbol{u}}(\boldsymbol{x}_i))^2}{V(\boldsymbol{x}_i)^2} \Big), \qquad (12)$$

where $\{\boldsymbol{x}_i\}_{i=1}^{N}$ are sampled from the distribution $\mu = \mu(\Omega)$ and Ω is some closed domain in $\mathbb{R}^d$.

For convenience, we summarize the developed framework in Algorithm 1. Here, b is a hyperparameter that can be adjusted as required by solving a specific problem.

Remark 3.3 *In Section 5, we show numerically that the conditions reduced in* (11) *are sufficiently effective for designing the ES loss. Actually, it is not necessary to design the loss function using the conditions in* (10).

Now, for controlling any nonlinear ODEs or SDEs, we design the ES according to Algorithm 1. As such, using the ES framework can not only stabilize those unstable equilibriums (constant states) of the given systems, but also can stabilize those unstable oscillators, e.g., the limit cycle. This is because the solution corresponding to the oscillator can be regarded as a zero solution of the controlled system after appropriate transformations are implemented.

Another point needs attention. During the construction of V in (6), $\varepsilon \|\boldsymbol{x}\|^2$, the L^2-regularization, is used to guarantee the positive definiteness of V. However, often in the application of the Lyapunov stability theory, the form of $\|\boldsymbol{x}\|^2$ is not always a suitable candidate for the Lyapunov function. It may restrict the generalizability of using our framework, so it needs necessary adjustments. The following example illustrates this point.

Example 3.4 *Consider a 2-D SDE as follows:*

$$\begin{cases} \mathrm{d}x_1(t) = x_2(t)\mathrm{d}t, \\ \mathrm{d}x_2(t) = [-2x_1(t) - x_2(t)]\mathrm{d}t + x_1(t)\mathrm{d}B_t. \end{cases}$$

In Appendix A.2, the zero solution of this system is validated to be exponentially stable almost surely; however, $k\|\boldsymbol{x}\|^2$ for any $k \in \mathbb{R}$ cannot be a useful auxiliary function to identify the exact stability of the zero solution.

To be candid, using the current framework takes a longer time for training and constructing the neural Lyapunov function. In the next subsection, we thus establish an alternative control framework that can reduce the training time.

3.2 Asymptotic Stabilizer

Here, in light of Theorem 2.3, we are to establish the second framework, the AS, for stabilizing the unstable equilibrium of system (5). This framework only makes the equilibrium asymptotically attractive almost surely. Its control function is designed in the same way as the one used in the ES framework, whereas the loss function is differently designed.

Definition 3.2 *(AS loss) Utilization of the notations used in Definition 3.1, the loss function for the controlled system (5) with the controller $\boldsymbol{u}$ is defined as:*

$$L_{\mu,\alpha}(\boldsymbol{u}) = \mathbb{E}_{\boldsymbol{x} \sim \mu}\big[\max\big(0, (\alpha - 2)\|\boldsymbol{x}^\top g_{\boldsymbol{u}}(\boldsymbol{x})\|^2 + \|\boldsymbol{x}\|^2(\langle \boldsymbol{x}, f(\boldsymbol{x})\rangle + \|g_{\boldsymbol{u}}(\boldsymbol{x})\|_{\mathrm{F}}^2)\big)\big].$$

Akin to Definition 3.1, we set the empirical loss function as:

$$L_{N,\alpha}(\boldsymbol{u}) = \frac{1}{N}\sum_{i=1}^{N}\big[\max\big(0, (\alpha - 2)\|\boldsymbol{x}_i^\top g_{\boldsymbol{u}}(\boldsymbol{x}_i)\|^2 + \|\boldsymbol{x}_i\|^2(\langle \boldsymbol{x}_i, f(\boldsymbol{x}_i)\rangle + \|g_{\boldsymbol{u}}(\boldsymbol{x}_i)\|_{\mathrm{F}}^2)\big)\big]. \quad (13)$$

Here, α is an adjustable parameter, which is related to the convergence time and the energy cost using the controller $\boldsymbol{u}$. We show in Appendix A.8 the influence of selecting different α. For convenience, we summarize the AS framework in Algorithm 2.

4 Convergence Time and Energy Cost

The convergence time and the energy cost are the crucial factors to measure the quality of a controller (Yan et al., 2012; Li et al., 2017; Sun et al., 2017). In this section, we provide a comparative study between the traditional stochastic linear control and the ES/AS, the above-articulated neural stochastic control.

To this end, we first present a theorem on the estimations of the convergence time and the energy cost for the stochastic linear control on a general SDE.

Theorem 4.1 *Consider the SDE with a stochastic linear controller as:*

$$\mathrm{d}\boldsymbol{x} = f(\boldsymbol{x})\mathrm{d}t + u(\boldsymbol{x})\mathrm{d}B_t, \quad \boldsymbol{x}(0) = \boldsymbol{x}_0 \in \mathbb{R}^d, \quad (14)$$

where $\langle \boldsymbol{x}, f(\boldsymbol{x})\rangle \leq L\|\boldsymbol{x}\|^2$ and $u(\boldsymbol{x}) = k\boldsymbol{x}$ with $|k| > \sqrt{2L}$. Then, for $\epsilon < \|\boldsymbol{x}_0\|$, we have

$$\begin{cases} \mathbb{E}[\tau_\epsilon] \leq T_\epsilon = \dfrac{2\log\left(\|\boldsymbol{x}_0\|/\epsilon\right)}{k^2 - 2L}, \\ \mathcal{E}(\tau_\epsilon, T_\epsilon) \leq \dfrac{k^2\|\boldsymbol{x}_0\|^2}{k^2 + 2L}\left[\exp\left(\dfrac{2(k^2 + 2L)\log\left(\|\boldsymbol{x}_0\|/\epsilon\right)}{k^2 - 2L}\right) - 1\right], \end{cases}$$

where, for a sufficiently small $\epsilon > 0$, we denote the stopping time by $\tau_\epsilon \triangleq \inf\{t > 0 : \|\boldsymbol{x}(t)\| = \epsilon\}$ and denote the energy cost by

$$\mathcal{E}(\tau_\epsilon, T_\epsilon) \triangleq \mathbb{E}\big(\int_0^{\tau_\epsilon \wedge T_\epsilon}\|\boldsymbol{u}\|^2\mathrm{d}t\big) = \mathbb{E}\big(\int_0^{T_\epsilon}\|\boldsymbol{u}\|^2\mathbb{1}_{\{t < \tau_\epsilon\}}\mathrm{d}t\big).$$

The proof of this theorem is provided in Appendix A.3.1.

We further consider the case for NN controller $u(x)$. In general, the $u(x)$ is Lipschitz continuous with Lipschitz constant k_u under a suitable activation function such as **ReLU** in NN (Fazlyab et al., 2019; Pauli et al., 2021). Then we have the following upper bound estimation of the convergence time and the energy cost for ES and AS, whose proofs are provided in Appendix A.3.2, A.3.3.

Theorem 4.2 *(Estimation for ES)* For ES stabilizer $u(x)$ in (14) with $\langle x, f(x) \rangle \leq L\|x\|^2$, $\varepsilon < \|x_0\|$, under the same notations and conditions in Theorem 2.2 with $c_3 - 2c_2 > 0$, we have

$$\begin{cases} \mathbb{E}[\tau_\epsilon] \leq T_\epsilon = \dfrac{2 \log \left(V(x_0)/c_1\varepsilon^p \right)}{c_3 - 2c_2}, \\ \mathcal{E}(\tau_\epsilon, T_\epsilon) \leq \dfrac{k_u^2\|x_0\|^2}{k_u^2 + 2L} \left[\exp\left(\dfrac{2(k_u^2 + 2L)\log\left(V(x_0)/c_1\varepsilon^p \right)}{c_3 - 2c_2} \right) - 1 \right]. \end{cases}$$

Theorem 4.3 *(Estimation for AS)* For (14) with $\langle x, f(x) \rangle \leq L\|x\|^2$, $\varepsilon < \|x_0\|$, under the same notations and conditions in Theorem 2.3, if the left term in (3) further satisfies $\max_{\|x\|\geq\varepsilon} \|x\|^{\alpha-4}(\|x\|^2(2\langle x, f(x) \rangle + \|u(x)\|_F^2) - (2-\alpha)\|x^\top u(x)\|^2) = -\delta_\varepsilon < 0$, then for NN controller $u(x)$ with Lipschizt constant k_u, we have

$$\begin{cases} \mathbb{E}[\tau_\epsilon] \leq T_\epsilon = \dfrac{2\left(\|x_0\|^\alpha - \varepsilon^\alpha \right)}{\delta_\varepsilon \cdot \alpha}, \\ \mathcal{E}(\tau_\epsilon, T_\epsilon) \leq \dfrac{k_u^2\|x_0\|^2}{k_u^2 + 2L} \left[\exp\left(\dfrac{2(k_u^2 + 2L)\left(\|x_0\|^\alpha - \varepsilon^\alpha \right)}{\delta_\varepsilon \cdot \alpha} \right) - 1 \right]. \end{cases}$$

Based on the theoretical results for ES and AS, we can further analyze the effects of hyperparameters b, α and neural network structures on the convergence time and energy cost in the control process. There are some interesting phenomena such as the monotonicity of T_ε along α for AS change with the relative relationships of $\|x_0\|$ and ε, this inspires us to select suitable α according to the specific problems. We leave more discussions in Appendix A.3.4.

Now, we numerically compare the performances of the linear controller $u(x) = kx$ and the AS on the convergence time and the energy cost of the controls applied to system (14) with specific configurations (see Figure 4). We numerically find that $u(x) = kx$ can efficiently stabilize the equilibrium for $k > k_c = 5.6$. Without loss of generality, we fix $k = 6.0$, and compare the corresponding performances. As clearly shown in Figure 4, the AS outperforms $u(x) = kx$ from both perspectives, the convergence speed and the energy cost. In the simulations, the energy cost $\mathcal{E}(\tau_\epsilon, T_\epsilon)$ defined above is computed in a finite-time duration as $\mathcal{E}(\tau_\epsilon, T \wedge T_\epsilon)$, where $T < \infty$ is selected to be appropriately large. We leave more results of the comparison study in Appendix A.5.5.

Figure 4: The performances of system (14) with specific configurations: $f(x) = x\log(1+x)$. (a) $u(x) = kx, k = 0.2 \cdot j, j = 1, \cdots, 50$, plot $\log(1 + x(1))$ against k. (b) Linear controller with $k = 6.0$, $\mathcal{E}(\tau_{0.1}, 1) = 38,388$. (c) AS control with $\mathcal{E}(\tau_{0.1}, 1) = 1438$

5 Experiments

In this section, we demonstrate the efficacy of the above-articulated frameworks of stochastic neural control, the ES and the AS, on several representative physical systems. We also compare these two frameworks, highlighting their advantages and weaknesses. The detailed configurations for these experiments are included in Appendix A.5. Additional illustrative experiments are included in Appendix A.6.

5.1 Harmonic Linear Oscillator

First, consider the harmonic linear oscillator $\ddot{y} + 2\beta\dot{y} + w^2 y = 0$, where w is the natural frequency and $\beta > 0$ is the damping coefficient representing the strength of the external force on the vibrator (Dekker, 1981). Although this system is exponentially stable, the system with stochastic perturbations $\ddot{y} + (2\beta + \xi_2)\dot{y} + (w^2 + \xi_1)y = 0$ becomes unstable even if $\mathbb{E}[\xi_1(t)] = \mathbb{E}[\xi_2(t)] = 0$ (Arnold et al., 1983). Now, we apply the nonlinear ES(+ICNN), the linear ES(+Quadratic), and the nonlinear AS, respectively, to stabilizing this unstable dynamics (A.5.1) with $w^2 = 1$, $\beta = 0.5$, $\zeta_1 = -3$, and $\zeta_2 = 2.15$, the results are shown in Figure 5. Indeed, we find that

Figure 5: The solid lines are obtained through averaging the 20 sampled trajectories, while the shaded areas stand for the variance regions.

the two nonlinear stochastic neural controls are more robust than the linear control, and that the ES(+ICNN), rather than the AS, makes the controlled system more stable.

In Table 1 we compute the training time (Tt) used for the loss function converging to 0, the number of iterations (Ni), the distance (Di) between the trajectory and the targeted equilibrium at time $T = 4$, and the convergence time (Ct) when the distance between the trajectory and the targeted equilibrium is less than 0.05. The re-

Table 1: Performance on Harmonic Linear Oscillator

	Tt	Ni	Di	Ct
ES(+ICNN)	276.385s	121	**1e-9**	**0.459**
ES(+Quadratic)	78.071s	**107**	0.049	3.683
AS	**4.839**s	184	0.027	2.027

sults are obtained through averaging the corresponding quantities produced by 20 randomly-sampled trajectories and the detailed training configurations are shown in Appendix A.5.1.

We further provide a comparison study of our newly proposed ES(+ICNN) with HDSCLF in (Sarkar et al., 2020), BALSA in (Fan et al., 2020) and classic LQR controller in controlling the harmonic linear oscillator. Both HDSCLF and BALSA are based on the Quadratic Program(QP), and they seek the control policy dynamically for each state in the control process. By contrast, our proposed learning control policy is directly

Figure 6: Comparison with existing methods.

used in the control process. Hence, our method is more efficient in the practical control problems. The results are shown in Figure. 6 (Please see more details in Appendix A.5.1). As can be seen that our learning control methods outperforms all others.

5.2 Stuart-Landau Equations

In this subsection, we show that our frameworks are beneficial to realizing the control and the synchronization of complex networks. To this end, we consider the single Stuart–Landau oscillator which is governed by the following complex-valued ODE:

$$\dot{Z} = (\beta + \mathrm{i}\gamma + \mu|Z|^2)Z, \;\; Z \in \mathbb{C}. \tag{15}$$

This equation is a paradigmatic model undergoing the so-called Andronov bifurcation (Kuznetsov, 2013): Stability of the equilibrium changes and the limit cycle emerges as the parameter passes some critical value. In what follows, we consider two cases based on system (15).

● **Case 1** We set $\beta = -25$, $\gamma = 1$, and $\mu = 1$, so that system (15) has a stable equilibrium $\rho = 0$ and an unstable limit cycle $\rho = 5$. Here, $Z = x + \mathrm{i}y = \rho e^{\mathrm{i}\theta}$. Now, the AS steers the dynamics to the unstable limit cycle, as successfully shown in Figure 7. The trajectories (the left column) and the phase orbits (the right column) of system (15), initiated from 30 randomly-selected initial states, without control (the upper panels) and with control of the AS (the lower panels). The initial values inside (resp., outside) the limit cycle $\rho = 5$ are indicated by the blue (resp., purple) pentagrams.

● **Case 2** Next, we consider the synchronization problem of the coupled Stuart-Landau equations. Successful deterministic methods have been systematically developed for realizing synchronization, including the adaptive control with time delay Selivanov et al. (2012) and the open-loop temporal network controller Zhang & Strogatz (2021). These methods majorly depend on the technique

Figure 7: The trajectories (the left column) and the phase orbits (the right column) of system (15).

Figure 8: The dynamics of the first (resp., second) component of the coupled oscillators are shown in the panels in the left (resp., middle) column. The dynamics in the phase space (the right column).

of linearization in the vicinity of the synchronization manifold. Here, we show how to apply our framework to achieving the synchronization in the coupled system. We set the corresponding Laplace matrix $L = (L_{jk})_{n \times n}$ as $\sum_{k=1}^{n} L_{jk} = 0$, which guarantees the synchronization manifold is an invariant manifold of the coupled system (Pecora & Carroll, 1998). Specifically, we select as $n = 20$, $\sigma = 0.01$, $c_1 = -1.8$, $c_2 = 4$, and $L_{jk} = \delta_{jk} - \frac{1}{n}$, where δ_{jk} is the Kronecker function. Then, we apply the AS to this system and realize the stabilization of the synchronous manifold, as shown in Figure 8.

5.3 Data-Driven Pinning Control for Cell Fate Dynamics

Indeed, our frameworks can be extended to the model-free version via a combination with existing data reconstruction method. To be concrete, we show that our framework can combine with Neural ODEs (NODEs) (Chen et al., 2018) to learn the control policy from time series data for the Cell Fate system (Sun et al., 2017; Laslo et al., 2006), which describes the interaction be-

Figure 9: Pinning control for cell fate dynamics.

tween two suppressors during cellular differentiation for neutrophil and macrophage cell fate choices. The system $\dot{\boldsymbol{x}} = f(\boldsymbol{x})$, $\boldsymbol{x} = (x_1, ..., x_6)$ has three steady states: $P_{1,2,3}$, where $P_{2,3}$ correspond to different cell fates and are stable and P_1 represents a critical expression level connecting the two fates and is unstable. The network structure of this 6-D system is a treemap, where one root node x_1 can stabilize itself under the original dynamic. Hence, we choose root node x_2 with maximum our degree and add pinning control on it to stabilize the system to unstable state P_1. The original trajectory that converges to P_2 (left) and the controlled trajectory that converges to P_1 (right) are shown in Figure 17. The original trajectory is used to train the NODE to reconstruct the vector field $\hat{f}$, then we use the sample of $\hat{f}$ as training data to learn our stochastic pinning control. We provide experimental details in Appendix A.5.6.

In addition to the above controlled systems, we include the other illustrative examples, the controlled inverted pendulum, reservoir computing and the controlled Lorenz system, in Appendix A.5,A.6.

6 Conclusion and Future Works

In this article, we have proposed two frameworks of neural stochastic control for stabilizing different types of dynamical systems, including the SDEs. We have shown that the neural stochastic control outperforms the classic stochastic linear control in both the convergence time and the energy cost for typical systems. More importantly, using several representative physical systems, we have demonstrated the advantages of our frameworks and showed part of their weaknesses possibly emergent in real applications. Also, we present some limitations of the proposed frameworks in Appendix A.9. Moreover, we suggest several directions for further investigations: (i) acceleration of the training process of the ES, (ii) the basin stability of the neural stochastic control (Menck et al., 2013), (iii) the trade-off between the deterministic controller $\boldsymbol{u}_g$ using the NNs and the stochastic controller $\boldsymbol{u}_f$ using the NNs, (iv) the safe learning in Robotic control with small disturbances (Berkenkamp et al., 2017), and (v) the design of the purely data-driven stochastic neural control.

7 Acknowledgments

We thank the anonymous reviewers for their valuable and constructive comments that helped us to improve the work. Q.Z is supported by the Shanghai Postdoctoral Excellence Program (No. 2021091) and by the STCSM (Nos. 21511100200 and 22ZR1407300). W.L. is supported by the National Natural Science Foundation of China (No. 11925103) and by the STCSM (Nos. 19511101404, 22JC1402500, 22JC1401402, and 2021SHZDZX0103).

References

Amos, B., Xu, L., and Kolter, J. Z. Input convex neural networks. In *International Conference on Machine Learning*, pp. 146–155. PMLR, 2017.

Anderson, C. W. Learning to control an inverted pendulum using neural networks. *IEEE Control Systems Magazine*, 9(3):31–37, 1989.

Appleby, J. A. Stabilisation of functional differential equations by noise. *Systems & Control Letters*, 2003.

Appleby, J. A., Mao, X., and Rodkina, A. On stochastic stabilization of difference equations. *Discrete & Continuous Dynamical Systems*, 15(3):843, 2006.

Appleby, J. A., Mao, X., and Rodkina, A. Stabilization and destabilization of nonlinear differential equations by noise. *IEEE Transactions on Automatic Control*, 53(3):683–691, 2008.

Arnold, L. *Stochastic Differential Equations: Theory and Applications*. Stochastic Differential Equations: Theory and Applications, 2007.

Arnold, L., Crauel, H., and Wihstutz, V. Stabilization of linear systems by noise. *SIAM Journal on Control and Optimization*, 21(3):451–461, 1983.

Berkenkamp, F., Turchetta, M., Schoellig, A. P., and Krause, A. Safe model-based reinforcement learning with stability guarantees. *arXiv preprint arXiv:1705.08551*, 2017.

Caraballo, T. and Robinson, J. C. Stabilisation of linear pdes by stratonovich noise. *Systems & Control Letters*, 53(1):41–50, 2004.

Caraballo, T., Garrido-Atienza, M. J., and Real, J. Stochastic stabilization of differential systems with general decay rate. *Systems & Control Letters*, 48(5):397–406, 2003.

Chang, Y.-C., Roohi, N., and Gao, S. Neural lyapunov control. In *Proceedings of the 33rd International Conference on Neural Information Processing Systems*, pp. 3245–3254, 2019.

Chen, R. T., Rubanova, Y., Bettencourt, J., and Duvenaud, D. Neural ordinary differential equations. *arXiv preprint arXiv:1806.07366*, 2018.

Dekker, H. Classical and quantum mechanics of the damped harmonic oscillator. *Physics Reports*, 80(1):1–110, 1981.

Deng, F., Luo, Q., Mao, X., and Pang, S. Noise suppresses or expresses exponential growth. *Systems & Control Letters*, 57(3):262–270, 2008.

Fan, D. D., Nguyen, J., Thakker, R., Alatur, N., Agha-mohammadi, A.-a., and Theodorou, E. A. Bayesian learning-based adaptive control for safety critical systems. In *2020 IEEE international conference on robotics and automation (ICRA)*, pp. 4093–4099. IEEE, 2020.

Fazlyab, M., Robey, A., Hassani, H., Morari, M., and Pappas, G. Efficient and accurate estimation of lipschitz constants for deep neural networks. *Advances in Neural Information Processing Systems*, 32, 2019.

Gallieri, M., Salehian, S. S. M., Toklu, N. E., Quaglino, A., Masci, J., Koutník, J., and Gomez, F. Safe interactive model-based learning. *arXiv preprint arXiv:1911.06556*, 2019.

Guo, Y., Lin, W., and Chen, G. Stability of switched systems on randomly switching durations with random interaction matrices. *IEEE Transactions on Automatic Control*, 63(1):21–36, 2018.

He, K., Zhang, X., Ren, S., and Sun, J. Deep residual learning for image recognition. In *Proceedings of the IEEE conference on computer vision and pattern recognition*, pp. 770–778, 2016.

Henrion, D. and Garulli, A. *Positive Polynomials in Control*, volume 312. Springer Science & Business Media, 2005.

Huang, S.-J. and Huang, C.-L. Control of an inverted pendulum using grey prediction model. *IEEE Transactions on Industry Applications*, 36(2):452–458, 2000.

Jaeger, H. The "echo state" approach to analysing and training recurrent neural networks-with an erratum note. *Bonn, Germany: German National Research Center for Information Technology GMD Technical Report*, 148(34):13, 2001.

Jaeger, H. Echo state network. *Scholarpedia*, 2(9):2330, 2007.

Jaeger, H. and Haas, H. Harnessing nonlinearity: Predicting chaotic systems and saving energy in wireless communication. *Science*, 304(5667):78–80, 2004.

Jarvis-Wloszek, Z., Feeley, R., Tan, W., Sun, K., and Packard, A. Some controls applications of sum of squares programming. In *42nd IEEE International Conference on Decision and Control (IEEE Cat. No. 03CH37475)*, volume 5, pp. 4676–4681. IEEE, 2003.

Khalil, H. K. Nonlinear systems third edition. *Patience Hall*, 115, 2002.

Kolter, J. Z. and Manek, G. Learning stable deep dynamics models. *Advances in Neural Information Processing Systems*, 32:11128–11136, 2019.

Kushner, H. J. Stochastic stability and control. Technical report, Brown Univ Providence RI, 1967.

Kuznetsov, Y. A. *Elements of applied bifurcation theory*, volume 112. Springer Science & Business Media, 2013.

Laslo, P., Spooner, C. J., Warmflash, A., Lancki, D. W., Lee, H.-J., Sciammas, R., Gantner, B. N., Dinner, A. R., and Singh, H. Multilineage transcriptional priming and determination of alternate hematopoietic cell fates. *Cell*, 126(4):755–766, 2006.

Leong, Y. P., Horowitz, M. B., and Burdick, J. W. Linearly solvable stochastic control lyapunov functions. *SIAM Journal on Control and Optimization*, 54(6):3106–3125, 2016.

Li, A., Cornelius, S. P., Liu, Y.-Y., Wang, L., and Barabási, A.-L. The fundamental advantages of temporal networks. *Science*, 358(6366):1042–1046, 2017.

Liptser, R. and Shiryayev, A. N. *Theory of martingales*, volume 49. Springer Science & Business Media, 2012.

Lukoševičius, M. and Jaeger, H. Reservoir computing approaches to recurrent neural network training. *Computer Science Review*, 3(3):127–149, 2009.

Ma, H., Ho, D. W., Lai, Y.-C., and Lin, W. Detection meeting control: Unstable steady states in high-dimensional nonlinear dynamical systems. *Physical Review E*, 92(4):042902, 2015.

Manek, G. and Kolter, J. Z. Learning stable deep dynamics models. *arXiv preprint arXiv:2001.06116*, 2020.

Mao, X. *Stability of Stochastic Differential Equations with Respect to Semimartingales*. Longman, 1991.

Mao, X. *Exponential Stability of Stochastic Differential Equations*. Marcel Dekker, 1994a.

Mao, X. Stochastic stabilization and destabilization. *Systems & Control Letters*, 23(4):279–290, 1994b.

Mao, X. *Stochastic differential equations and applications*. Elsevier, 2007.

Mao, X., Marion, G., and Renshaw, E. Environmental brownian noise suppresses explosions in population dynamics. *Stochastic Processes and Their Applications*, 97(1):95–110, 2002.

Mao, X., Yin, G. G., and Yuan, C. Stabilization and destabilization of hybrid systems of stochastic differential equations. *Automatica*, 43(2):264–273, 2007.

Menck, P. J., Heitzig, J., Marwan, N., and Kurths, J. How basin stability complements the linear-stability paradigm. *Nature Physics*, 9(2):89–92, 2013.

Parrilo, P. A. *Structured Semidefinite Programs and Semialgebraic Geometry Methods in Robustness and Optimization*. California Institute of Technology, 2000.

Pauli, P., Koch, A., Berberich, J., Kohler, P., and Allgöwer, F. Training robust neural networks using lipschitz bounds. *IEEE Control Systems Letters*, 6:121–126, 2021.

Pecora, L. M. and Carroll, T. L. Master stability functions for synchronized coupled systems. *Physical Review Letters*, 80(10):2109, 1998.

Polycarpou, M. Stable adaptive neural control scheme for nonlinear systems. *IEEE Transactions on Automatic Control*, 41(3):447–451, 1996. doi: 10.1109/9.486648.

Richards, S. M., Berkenkamp, F., and Krause, A. The lyapunov neural network: Adaptive stability certification for safe learning of dynamical systems. In *Conference on Robot Learning*, pp. 466–476. PMLR, 2018.

Sarkar, M., Ghose, D., and Theodorou, E. A. High-relative degree stochastic control lyapunov and barrier functions. *arXiv preprint arXiv:2004.03856*, 2020.

Sastry, S. and Isidori, A. Adaptive control of linearizable systems. *IEEE Transactions on Automatic Control*, 34(11):1123–1131, 1989. doi: 10.1109/9.40741.

Selivanov, A. A., Lehnert, J., Dahms, T., Hövel, P., Fradkov, A. L., and Schöll, E. Adaptive synchronization in delay-coupled networks of stuart-landau oscillators. *Physical Review E*, 85(1): 016201, 2012.

Sparrow, C. *The Lorenz Equations: Bifurcations, Chaos, and Strange Attractors*, volume 41. Springer Science & Business Media, 2012.

Sun, Y.-Z., Leng, S.-Y., Lai, Y.-C., Grebogi, C., and Lin, W. Closed-loop control of complex networks: A trade-off between time and energy. *Physical Review Letters*, 119(19):198301, 2017.

Takeishi, N. and Kawahara, Y. Learning dynamics models with stable invariant sets. In *Proceedings of the AAAI Conference on Artificial Intelligence*, volume 35, pp. 9782–9790, 2021.

Tan, W. and Packard, A. Searching for control lyapunov functions using sums of squares programming. *sibi*, 1(1), 2004.

Wang, B. and Zhu, Q. Stability analysis of markov switched stochastic differential equations with both stable and unstable subsystems. *Systems & Control Letters*, 105:55–61, 2017.

Xie, C., Wu, Y., Maaten, L. v. d., Yuille, A. L., and He, K. Feature denoising for improving adversarial robustness. In *Proceedings of the IEEE/CVF conference on computer vision and pattern recognition*, pp. 501–509, 2019.

Yan, G., Ren, J., Lai, Y.-C., Lai, C.-H., and Li, B. Controlling complex networks: How much energy is needed? *Physical Review Letters*, 108(21):218703, 2012.

Yan, H., Du, J., Tan, V. Y., and Feng, J. On robustness of neural ordinary differential equations. *arXiv preprint arXiv:1910.05513*, 2019.

Yang, S.-K., Chen, C.-L., and Yau, H.-T. Control of chaos in lorenz system. *Chaos, Solitons & Fractals*, 13(4):767–780, 2002.

Yang, T., Yang, L.-B., and Yang, C.-M. Impulsive control of lorenz system. *Physica D: Nonlinear Phenomena*, 110(1-2):18–24, 1997.

Zhang, Y. and Strogatz, S. H. Designing temporal networks that synchronize under resource constraints. *Nature Communications*, 12(1):1–8, 2021.

Zhu, Q., Ma, H., and Lin, W. Detecting unstable periodic orbits based only on time series: When adaptive delayed feedback control meets reservoir computing. *Chaos: An Interdisciplinary Journal of Nonlinear Science*, 29(9):093125, 2019.

A Appendix

A.1 Proof of Proposition 3.2

First, we consider the solution of Eq. (9) for $u(x) = kx$. Applying Itô's formula to $\log |x|$ yields:

$$\mathrm{d}\log|x| = \frac{1}{|x|} \cdot \frac{x}{|x|}\mathrm{d}x - \frac{1}{2}\frac{1}{x^2}\mathrm{d}x \cdot \mathrm{d}x$$

$$= \left(\log|x| - \frac{k^2}{2}\right)dt + k\mathrm{d}B_t.$$

By letting $y = \log|x| - \frac{1}{2}k^2$, we obtain $\mathrm{d}y = y\mathrm{d}t + k\mathrm{d}B_t$. Through applying Itô's formula of two dimensions to $e^{-t}y$, we get

$$\mathrm{d}(e^{-t}y) = \mathrm{d}(e^{-t})y + e^{-t}\mathrm{d}y + \mathrm{d}e^{-t}\mathrm{d}y$$

$$= -e^{-t}y\mathrm{d}t + e^{-t}\mathrm{d}y - e^{-t}\mathrm{d}t\mathrm{d}y$$

$$= ke^{-t}\mathrm{d}B_t,$$

which further implies

$$y(t) = e^t\left(y(0) + k\int_0^t e^{-s}\mathrm{d}B_s\right)$$

$$\triangleq y(0)e^{-t} + ke^t\eta(t).$$

Here, the Gaussian process $\{\eta(t) = \int_0^t e^{-s}\mathrm{d}B_s,\ t \geq 0\}$ is a martingale. Thus, from the property of the martingale and Itô's isometry formula, it follows that

$$\begin{cases} \mathbb{E}\eta(t) = \mathbb{E}\eta(0) = 0, \\ \mathbb{E}\eta(t)^2 = \mathbb{E}\int_0^t e^{-2s}\mathrm{d}s = \dfrac{1 - e^{-2t}}{2}. \end{cases}$$

Hence, we have $y(t) \sim \mathcal{N}\left(y(0)e^t, \frac{k^2}{2}(e^{2t} - 1)\right)$, which further indicates that

$$\log|\boldsymbol{x}(t)| \sim \mathcal{N}\left(\left(\log|x(0)| - \frac{k^2}{2}\right)e^t + \frac{k^2}{2}, \frac{k^2}{2}\left(e^{2t} - 1\right)\right).$$

For any $k \in \mathbb{R}$, we choose $x(0)$ such that $\log|x(0)| - \frac{k^2}{2} > 0$. Thus, we have $\mathbb{P}(\log|x(t)| > 0) > 0$, which contradicts the asymptotic stability condition:

$$\lim_{t\to\infty} x(t) = 0\ a.s. \iff \lim_{t\to\infty}\log|x(t)| = -\infty\ a.s..$$

Second, for $u(x) = 2x^2$, it is direct to validate that

$$x^2[2x^2\log x + u(x)^2] - \frac{3}{2}x^2u(x)^2 \leq 0.$$

This thus meets the conditions with $\alpha = \frac{1}{2}$ in Theorem 2.3. Then, in light of this theorem, the zero solution is of asymptotic attractiveness almost surely. Finally, for $u(x) \equiv 0$, direct calculations give a result that the classic linear controller cannot globally stabilize the deterministic system. Therefore, the proof is complete.

A.2 Validation of Example 3.4

On one hand, we select as $V(\boldsymbol{x}) = k\|\boldsymbol{x}\|^2 \equiv k(x_1^2 + x_2^2)$ with $k > 0$, an undetermined coefficient. We thus get $\mathcal{L}V(\boldsymbol{x}) = k(x_1^2 - 2x_1x_2 - 2x_2^2)$ and $\nabla V^\top(\boldsymbol{x})g(\boldsymbol{x}) = 2kx_1x_2$. Notice that

$$\liminf_{(x_1^2+x_2^2)\neq 0} \frac{x_1^2 x_2^2}{(x_1^2 + x_2^2)^2} = 0.$$

So, to satisfy Condition (iii) in Theorem 2.2, we have to set $c_3 = 0$. As for meeting Condition (ii), letting $\boldsymbol{x} = (x, 0)$ gives $\mathcal{L}V = kx^2 > 0$, which indicates that, if there exists a number c_2 such that

$\mathcal{L}V(\boldsymbol{x}) \le c_2 V(\boldsymbol{x})$, c_2 is positive. Hence, $c_3 - 2c_2 < 0$, so the above form of V cannot guarantee the exponential stability of the zero solution.

On the other hand, we set as $\hat{V}(\boldsymbol{x}) \equiv \frac{5}{2}x_1^2 + x_1 x_2 + x_2^2$, and then we obtain

$$\mathcal{L}\hat{V}(\boldsymbol{x}) \le -2\left[2x_1^2 + \frac{1}{2}x_2^2 + \frac{1}{2}(x_1 + x_2)^2\right] = -2\hat{V}(\boldsymbol{x}).$$

As we choose $c_2 = -2$ and $c_3 = 0$, all the conditions in Theorem 2.2 are satisfied. Therefore, the exponential stability of the zero solution is assured. This example particularly indicates that regularization terms need delicate design and fine-tune in applications.

A.3 Proofs for Theorems

A.3.1 Proof of Theorem 4.1

We first present an estimation for the upper bound of $\mathbb{E}[\tau_\epsilon]$. Applying Itô's formula to $\log\|\boldsymbol{x}\|$ yields:

$$\begin{aligned}
\log\|\boldsymbol{x}\| &- \log\|\boldsymbol{x}(0)\| \\
&= \int_0^t \left(\frac{\langle \boldsymbol{x}(s), f(\boldsymbol{x}(s))\rangle}{\|\boldsymbol{x}\|^2} - \frac{k^2}{2}\right)\mathrm{d}s + \int_0^t k\,\mathrm{d}B_s \\
&\le \int_0^t \left(L - \frac{k^2}{2}\right)\mathrm{d}s + \int_0^t k\,\mathrm{d}B_s \\
&= \left(L - \frac{k^2}{2}\right)t + kB_t.
\end{aligned}$$

Substitution of t with a stopping time τ gives

$$\log\|\boldsymbol{x}(\tau)\| - \log\|\boldsymbol{x}_0\| \le \left(L - \frac{k^2}{2}\right)\tau + kB_\tau,$$

which, after taking the expectation on both sides, yields:

$$\mathbb{E}\left[\log\frac{\|\boldsymbol{x}(\tau)\|}{\|\boldsymbol{x}_0\|}\right] \le \mathbb{E}\left[\int_0^\tau \left(L - \frac{k^2}{2}\right)\mathrm{d}s\right].$$

Notice that $\boldsymbol{x}(\tau_\epsilon) = \epsilon$. Then, we have

$$\log\frac{\epsilon}{\|\boldsymbol{x}_0\|} = \mathbb{E}\left[\log\frac{\|\boldsymbol{x}(\tau_\epsilon)\|}{\|\boldsymbol{x}_0\|}\right] \le \left(L - \frac{k^2}{2}\right)\mathbb{E}[\tau_\epsilon].$$

From $L - \frac{k^2}{2} < 0$ and $\log\frac{\epsilon}{\|\boldsymbol{x}_0\|} < 0$, it follows that

$$\mathbb{E}[\tau_\epsilon] \le \frac{2\log\left(\frac{\|\boldsymbol{x}_0\|}{\epsilon}\right)}{k^2 - 2L} \triangleq T_\epsilon.$$

Next, by using the above results, we are in a position to provide an estimation of the energy $\mathcal{E}(\tau_\epsilon, T_\epsilon)$. To this end, an application of Itô's formula yields:

$$\begin{aligned}
\|\boldsymbol{x}(t)\|^2 &- \|\boldsymbol{x}(0)\|^2 \\
&= \int_0^t \left(2\langle\boldsymbol{x}(s), f(\boldsymbol{x}(s))\rangle + k^2\|\boldsymbol{x}(s)\|^2\right)\mathrm{d}s \\
&\quad + \int_0^t 2k^2\|\boldsymbol{x}(s)\|^2\mathrm{d}B_s \\
&\le \int_0^t (2L + k^2)\|\boldsymbol{x}(s)\|^2\mathrm{d}s + \int_0^t 2k^2\|\boldsymbol{x}(s)\|^2\mathrm{d}B_s.
\end{aligned}$$

Thus, taking the expectation on both sides along the time interval $[0, t \wedge \tau_\epsilon]$ gives

$$\begin{aligned}
\mathbb{E}[\|\boldsymbol{x}(t \wedge \tau_\epsilon)\|^2] &\le \|\boldsymbol{x}_0\|^2 + \mathbb{E}\int_0^{t\wedge\tau_\epsilon} (2L + k^2)\|\boldsymbol{x}(s)\|^2\mathrm{d}s \\
&= \|\boldsymbol{x}_0\|^2 + (2L + k^2)\int_0^t \mathbb{E}[\|\boldsymbol{x}(s)\|^2 \mathbb{1}_{\{s<\tau_\epsilon\}}]\mathrm{d}s,
\end{aligned}$$

which further implies

$$\mathbb{E}[\|\boldsymbol{x}(t)\|^2 \mathbb{1}_{\{t < \tau_\epsilon\}}] \leq \mathbb{E}[\|\boldsymbol{x}(t \wedge \tau_\epsilon)\|^2]$$

$$\leq \|\boldsymbol{x}_0\|^2 + (2L + k^2) \int_0^t \mathbb{E}[\|\boldsymbol{x}(s)\|^2 \mathbb{1}_{\{s < \tau_\epsilon\}}]\mathrm{d}s.$$

Now, applying Gronwall's inequality, we get

$$\mathbb{E}[\|\boldsymbol{x}(t)\|^2 \mathbb{1}_{\{t < \tau_\epsilon\}}] \leq \|\boldsymbol{x}_0\|^2 e^{(2L+k^2)t}.$$

Finally, the energy is computed and estimated as follows:

$$\mathcal{E}(\tau_\epsilon, T_\epsilon) = \mathbb{E}\left(\int_0^{\tau_\epsilon \wedge T_\epsilon} k^2 \|\boldsymbol{x}(s)\|^2 \mathrm{d}s\right)$$

$$= k^2 \int_0^{T_\epsilon} \mathbb{E}[\|\boldsymbol{x}(t)\|^2 \mathbb{1}_{\{t < \tau_\epsilon\}}]\mathrm{d}s$$

$$\leq k^2 \|\boldsymbol{x}_0\|^2 \int_0^{T_\epsilon} e^{(2L+k^2)s}\mathrm{d}s$$

$$= \frac{k^2 \|\boldsymbol{x}_0\|^2}{2L + k^2} \left[\exp(2L + k^2)T_\epsilon - 1\right]$$

$$= \frac{k^2 \|\boldsymbol{x}_0\|^2}{k^2 + 2L} \Big[\exp\Big(\frac{2(k^2 + 2L)\log\left(\frac{\|\boldsymbol{x}_0\|_2^2}{\epsilon}\right)}{k^2 - 2L}\Big) - 1\Big].$$

This therefore completes the proof of the whole theorem.

A.3.2 Proof of Theorem 4.2

First we prove the estimation for $\mathbb{E}[\tau_\varepsilon]$. Applying Itô's formula to $\log V(\boldsymbol{x})$ yields:

$$\log V(\boldsymbol{x}(t)) = \log V(\boldsymbol{x}_0) + \int_0^t \frac{\mathcal{L}V(\boldsymbol{x}(s))}{V(\boldsymbol{x}(s))}\mathrm{d}s + \int_0^t \frac{\nabla V(\boldsymbol{x}(s)) \cdot \boldsymbol{u}(\boldsymbol{x}(s))}{V(\boldsymbol{x}(s))}\mathrm{d}B_s$$

$$- \frac{1}{2} \int_0^t \frac{\|\nabla V \cdot \boldsymbol{u}\|^2}{V^2}ds$$

$$\leq \log(V(\boldsymbol{x}_0)) + c_2 t + \int_0^t \frac{\nabla V(\boldsymbol{x}(s)) \cdot \boldsymbol{u}(\boldsymbol{x}(s))}{V(\boldsymbol{x}(s))}\mathrm{d}B_s - \frac{c_3 t}{2},$$

Substitution of t with a stopping time τ and taking expectation on both sides, we have

$$\mathbb{E}[\log V(\boldsymbol{x}(\tau))] \leq \mathbb{E}[\log V(\boldsymbol{x}_0)] + \frac{2c_2 - c_3}{2}\tau.$$

From $\|\boldsymbol{x}(\tau_\varepsilon)\| = \varepsilon < \|\boldsymbol{x}_0\|$ and $c_3 - 2c_2 > 0$, it follows that

$$\mathbb{E}[\tau_\varepsilon] \leq \frac{2\log(V(\boldsymbol{x}_0)/V(\boldsymbol{x}_{\tau_\varepsilon}))}{c_3 - 2c_2} \leq \min_{\|\boldsymbol{x}\|=\varepsilon} \frac{2\log(V(\boldsymbol{x}_0)/V(\boldsymbol{x}))}{c_3 - 2c_2} \leq \frac{2\log(V(\boldsymbol{x}_0)/c_1\varepsilon^p)}{c_3 - 2c_2} \triangleq T_\varepsilon.$$

Notice that NN control satisfies $\boldsymbol{u}(\boldsymbol{0}) = \boldsymbol{0}$, under the Lipschitz condition, we have $\|\boldsymbol{u}(\boldsymbol{x})\| \leq k_{\boldsymbol{u}}\|\boldsymbol{x}\|$. Then, similar to the procedure for the energy cost in A.3.1, we can get that

$$\mathbb{E}[\|\boldsymbol{x}(t)\|^2 \mathbb{1}_{\{t < \tau_\epsilon\}}] \leq \|\boldsymbol{x}_0\|^2 e^{(2L+k_{\boldsymbol{u}}^2)t},$$

$$\mathcal{E}(\tau_\varepsilon, T_\varepsilon) = \mathbb{E}\left(\int_0^{\tau_\varepsilon \wedge T_\varepsilon} \|\boldsymbol{u}(\boldsymbol{x}(s))\|^2 \mathrm{d}s\right)$$

$$\leq k_{\boldsymbol{u}}^2 \int_0^{T_\varepsilon} \mathbb{E}[\|\boldsymbol{x}(s)\|^2 \mathbb{1}_{\{s < \tau_\epsilon\}}]\mathrm{d}s$$

$$\leq \frac{k_{\boldsymbol{u}}^2 \|\boldsymbol{x}_0\|^2}{k_{\boldsymbol{u}}^2 + 2L} \left[\exp\left(\frac{2(k_{\boldsymbol{u}}^2 + 2L)\log(V(\boldsymbol{x}_0)/c_1\varepsilon^p))}{c_3 - 2c_2}\right) - 1\right],$$

which completes the proof.

A.3.3 Proof of Theorem 4.3

First we prove the estimation for $\mathbb{E}[\tau_\varepsilon]$. Applying Itô's formula to $\|\boldsymbol{x}\|^2$ we have

$$\|\boldsymbol{x}(t)\|^2 = \|\boldsymbol{x}(0)\|^2 + \int_0^t (2\langle \boldsymbol{x}, f(\boldsymbol{x})\rangle + \|\boldsymbol{u}(\boldsymbol{x})\|^2)\mathrm{d}s + \int_0^t 2\langle \boldsymbol{x}, \boldsymbol{u}(\boldsymbol{x})\mathrm{d}B_s\rangle.$$

For $\alpha \in (0,1)$, further using the fact that $\|\boldsymbol{x}\|^\alpha = (\|\boldsymbol{x}\|^2)^{\alpha/2}$ we have

$$\|\boldsymbol{x}(t)\|^\alpha = \|\boldsymbol{x}(0)\|^\alpha + \int_0^t \frac{\alpha}{2}\|\boldsymbol{x}\|^{\alpha-4}q(\boldsymbol{x})\mathrm{d}s + \int_0^t \alpha\|\boldsymbol{x}\|^{\alpha-2}\langle \boldsymbol{x}, \boldsymbol{u}(\boldsymbol{x})\mathrm{d}B_s\rangle,$$

$$q(\boldsymbol{x}) = \|\boldsymbol{x}\|^2(2\langle \boldsymbol{x}, F(\boldsymbol{x})\rangle + \|\boldsymbol{u}(\boldsymbol{x})\|_{\mathrm{F}}^2) - (2-\alpha)\|\boldsymbol{x}^\top \boldsymbol{u}(\boldsymbol{x})\|^2 \leq 0,$$

$$\max_{\|\boldsymbol{x}\|\geq\varepsilon} \frac{q(\boldsymbol{x})}{\|\boldsymbol{x}\|^{4-\alpha}} \leq -\delta_\varepsilon.$$

Notice that $\|\boldsymbol{x}(t)\| \geq \varepsilon$, $t \leq \tau_\varepsilon$, setting t as τ_ε and taking expectation we have

$$\varepsilon^\alpha \leq \|\boldsymbol{x}_0\|^\alpha - \frac{\alpha}{2}\delta_\varepsilon \mathbb{E}[\tau_\varepsilon]$$

Then we have

$$\mathbb{E}[\tau_\varepsilon] \leq \frac{2(\|\boldsymbol{x}_0\|^\alpha - \varepsilon^\alpha)}{\alpha \cdot \delta_\varepsilon} \triangleq T_\varepsilon.$$

The estimation of the energy cost is just the same as that in A.3.2, and here we omit it.

A.3.4 Discussions for Theorem 4.2,4.3

Convergence Time for ES From the conditions in Theorem 2.2 and the equivalent condition (10),(11), the hyperparameter b for ES can be substantially regarded as $\frac{c_3}{c_2}$. Hence, when $b > 2$ we have $c_3 - 2c_2 > 0$, which corresponds to the exponential stability condition. This can be also confirmed by the upper bound estimation $\frac{2\log(V(\boldsymbol{x}_0)/c_1\varepsilon^p)}{c_3 - 2c_2} \triangleq T_\varepsilon$ in our Theorem 4.2, the convergence time T_ε decreases as $c_3 - 2c_2$ get larger than zero, which means we should choose larger b in the training. The T_ε also decreases as the c_1 and p increase, from the condition $V(\boldsymbol{x}) \geq c_1\|\boldsymbol{x}\|^p$ in Theorem 2.2 and the truth that $\nabla(c_1\|\boldsymbol{x}\|^p) = c_1 p\|\boldsymbol{x}\|^{p-1}\nabla(\|\boldsymbol{x}\|)$, we can summarize that the slope of $V(\boldsymbol{x})$ can affect the convergence rate for ES. This inspire that we can design more steep neural networks structure for V, such as multiply $\|\boldsymbol{x}\|^\lambda$, $\lambda > 0$ to V or increase ε in V in ES(+Quad).

Convergence Time for AS From the upper bound estimation $\frac{2(\|\boldsymbol{x}_0\|^\alpha - \varepsilon^\alpha)}{\alpha \cdot \delta_\varepsilon} \triangleq T_\varepsilon$ in Theorem 4.3, the convergence time is indeed related to α. This parameter is not covered in the learning parameters, so we can adjust it according to the practical requirements. Here, we study the influence of α with fixed ε, that is, we consider the function $h(\alpha) = \frac{a^\alpha - b^\alpha}{\alpha}$, $a > b$, $\alpha \in (0,1)$. The interesting thing is that monotonicity of $h(\alpha)$ changes with the parameters a, b, as shown in Figure 10. This phenomenon indicates that the minimal point for convergence time in AS should be selected according to the parameter region of $(\|\boldsymbol{x}_0\|, \varepsilon)$. The analytical or numerical forms of critical curve in this region need further research in future work.

A.3.5 More Discussion of AS/ES

Understanding AS Loss We utilize the formula $\|\boldsymbol{x}\|^2(2\langle \boldsymbol{x}, F(\boldsymbol{x})\rangle + \|G(\boldsymbol{x})\|_{\mathrm{F}}^2) - (2-\alpha)\|\boldsymbol{x}^\top G(\boldsymbol{x})\|^2 \triangleq q(\boldsymbol{x})$ in (3) to construct the AS loss. Here we explain this term in more detail. The $q(\boldsymbol{x})$ is derived from the chain derivative of $\|\boldsymbol{x}\|^\alpha = (\|\boldsymbol{x}\|^2)^{\alpha/2}$ according to Itô's formula, we then have $\mathrm{d}\|\boldsymbol{x}\|^\alpha = \alpha/2\|\boldsymbol{x}\|^{\alpha-4}q(\boldsymbol{x})\mathrm{d}t + \alpha\|\boldsymbol{x}\|^{\alpha-2}\|\boldsymbol{x}^\top G(\boldsymbol{x})\|\mathrm{d}B_t$. The drift term is less than zero when $q(\boldsymbol{x}) \leq 0$, which can guarantee the bounded existence and asymptotic stability of $\|\boldsymbol{x}\|^\alpha$ from the semi-martingale convergence theorem (Liptser & Shiryayev, 2012) .

Figure 10: Plot for $h(\alpha)$ with different parameters combinations.

Computational Complexity   The AS framework is computationally efficient because we only need the tensor operation in the training process. The computational complexity of this procedure is $\mathcal{O}(mn)$ for m data on n-D dynamics. The training for ES framework is not as efficient as AS. The major reason is that we should compute the Hessian matrix of V to get $\mathcal{L}V$ and the computational complexity of this operator is $\mathcal{O}(mn^2)$.

A.4 Algorithms

We summarize the Algorithms of ES and AS as follows:

Algorithm 1: Exponential Stabilizer

Input: Data $\{\boldsymbol{x}_i\}_{i=1}^n$ sampled from $\mu(\Omega)$, iteration step m, learning rate γ, training error δ, coefficient samples $f(\boldsymbol{x}_i)$ and $g(\boldsymbol{x}_i)$, initial parameters $\boldsymbol{\theta}_V(0), \boldsymbol{\theta}_{\boldsymbol{u}}(0)$, and parameters ε used in (6) and b used in (11).

Output: Controller $\boldsymbol{u}_{\theta_{\boldsymbol{u}}}(\boldsymbol{x}_i)$ and Lyapunov function $V_{\theta_V}(\boldsymbol{x}_i)$ in the form of (6) or (8).

for $r = 0$ **to** $m - 1$ **do**

    Compute $\nabla V(\boldsymbol{x}_i), HV(\boldsymbol{x}_i), \; i = 1, \cdots, n$

    Compute ES loss: $L(\boldsymbol{\theta}_V(r), \boldsymbol{\theta}_{\boldsymbol{u}}(r))$ from (12)

    $\boldsymbol{\theta}_u(r+1) = \boldsymbol{\theta}_u(r) - \gamma \cdot \nabla_{\boldsymbol{\theta}_u} L(\boldsymbol{\theta}_V(r), \boldsymbol{\theta}_u(r)), \; \boldsymbol{\theta}_V(r+1) = \boldsymbol{\theta}_V(r) - \gamma \cdot \nabla_{\boldsymbol{\theta}_V} L(\boldsymbol{\theta}_V(r), \boldsymbol{\theta}_{\boldsymbol{u}}(r))$

    ▷ Update parameters

    if $L(\boldsymbol{\theta}_V(r+1), \theta_{\boldsymbol{u}}(r+1)) \leq \delta$ **then**

        break

Algorithm 2: Asymptotic Stabilizer

Input: Data $\{\boldsymbol{x}_i\}_{i=1}^n$ sampled from $\mu(\Omega)$, parameter $\alpha \in (0, 1)$ used in (13), and all other parameters, $m, \gamma, \delta, f(\boldsymbol{x}_i)$, and $g(\boldsymbol{x}_i)$, defined in the same manner as those in Algorithm 1.

Output: Controller $\boldsymbol{u}_{\theta_{\boldsymbol{u}}}(\boldsymbol{x}_i)$.

for $r = 0$ **to** $m - 1$ **do**

    Compute loss function: $L(\boldsymbol{\theta}_u(r))$ from (13)

    $\theta_{\boldsymbol{u}}(r+1) = \boldsymbol{\theta}_{\boldsymbol{u}}(r) - \gamma \cdot \nabla_{\boldsymbol{\theta}_{\boldsymbol{u}}} L(\boldsymbol{\theta}_{\boldsymbol{u}}(r))$ ▷ Update parameters

    if $L(\boldsymbol{\theta}_{\boldsymbol{u}}(r+1)) \leq \delta$ **then**

        break

A.5 Experimental Configurations

In this section, we provide the detailed descriptions for the experimental configurations of the physical examples in the main text. The computing device that we use for calculating our examples includes a single i7-10870 CPU with 16GB memory, while the computational frameworks for our neural stochastic control contain three typical NNs.

1. The ICNN V function is constructed as:

$$z_1 = \sigma(W_0 \boldsymbol{x} + b_0),$$
$$z_{i+1} = \sigma(U_i z_i + W_i \boldsymbol{x} + b_i), \ i = 1, \cdots, k-1,$$
$$p(\boldsymbol{x}) \equiv z_k,$$
$$V(\boldsymbol{x}) = \sigma(p(\boldsymbol{x}) - p(\boldsymbol{0})) + \varepsilon\|\boldsymbol{x}\|^2,$$

where σ is the smoothed **ReLU** function as defined in the main text, $W_i \in \mathbb{R}^{h_i \times d}$, $U_i \in (\mathbb{R}_+ \cup \{0\})^{h_i \times h_{i-1}}$, $\boldsymbol{x} \in \mathbb{R}^d$, and, for simplicity, this ICNN function is denoted by $\mathrm{ICNN}(h_0, h_1, \cdots, h_{k-1})$;

2. The quadratic form V function is constructed as:

$$z_1 = \tanh(W_0 \boldsymbol{x} + B_1),$$
$$z_{i+1} = \tanh(W_i z_i + b_i), \ i = 1, \cdots, k-1,$$
$$V_{\boldsymbol{\theta}}(\boldsymbol{x}) \equiv W_k z_k,$$
$$V(\boldsymbol{x}) = \boldsymbol{x}^\top (\varepsilon I + V_{\boldsymbol{\theta}}(\boldsymbol{x})^\top V_{\boldsymbol{\theta}}(\boldsymbol{x})) \boldsymbol{x}.$$

where $W_i \in \mathbb{R}^{h_{i+1} \times h_i}$, and this quadratic function is denoted by $\mathrm{Quadratic}(h_0, h_1, \cdots, h_{k+1})$;

3. The neural control function (nonlinear version) is constructed as:

$$z_1 = \mathcal{F}(W_0 \boldsymbol{x} + B_1),$$
$$z_{i+1} = \mathcal{F}(W_i z_i + b_i), \ i = 1, \cdots, k-1,$$
$$\mathbf{NN}(\boldsymbol{x}) \equiv W_k z_k,$$
$$\boldsymbol{u}(\boldsymbol{x}) = \mathrm{diag}(\boldsymbol{x})\mathbf{NN}(\boldsymbol{x}),$$

where $\mathcal{F}(\cdot)$ is the activation function, $W_i \in \mathbb{R}^{h_{i+1} \times h_i}$, and this control function is denoted by $\mathrm{Control}(h_0, h_1, \cdots, h_{k+1})$;
The neural control function (linear version) is set as $\boldsymbol{u}(\boldsymbol{x}) = W_1 \boldsymbol{x}$.

A.5.1 Controlling Harmonic Linear Oscillator

Mathematically, the perturbed harmonic oscillator is written as:

$$\begin{cases} \mathrm{d}x_1 = x_2 \mathrm{d}t, \\ \mathrm{d}x_2 = \left(-w^2 x_1 - 2\beta x_2\right)\mathrm{d}t + \left(\zeta_1 x_1 + \zeta_2 x_2\right)\mathrm{d}B_t. \end{cases}$$

The controlled harmonic linear oscillator with the random damping and the random restoring force is written as:

$$\mathrm{d}x_1 = x_2 \mathrm{d}t + u_1(x_1, x_2)\mathrm{d}B(t),$$
$$\mathrm{d}x_2 = -\left(x_1 + x_2\right)\mathrm{d}t + \left[-3x_1 + 2.15x_2 + u_2(x_1, x_2)\right]\mathrm{d}B(t).$$

As introduced in the main text, we use three combinations of our neural control frameworks:

1. ES(+ICNN): $\varepsilon = 10^{-3}$, $\mathrm{ICNN}(6, 6, 1)$, and $\mathrm{Control}(2, 6, 6, 2)$ with $\mathcal{F}(\cdot) = \mathbf{ReLU}$ and $b = 2.1$,

2. ES(+Quadratic): $\varepsilon = 10^{-2}$, $\mathrm{Quadratic}(2, 6, 2)$, and the controller is set as $\boldsymbol{u}(\boldsymbol{x}) = W_1 \boldsymbol{x}$ with $W_1 \in \mathbb{R}^{2 \times 2}$ and $b = 2.1$, and

3. AS: $\mathrm{Control}(2, 6, 6, 2)$ with $\mathcal{F}(\cdot) = \mathbf{ReLU}$ and $\alpha = 0.75$.

We train these NNs, respectively, for 500 iterations using the 500 data that are sampled from $\mathcal{U}([-6, 6]^2)$, and we depict their loss functions in Figure 11, respectively.

In the main text, we compare the performance of the three learning control functions using the same initial value $(0.3, 0.5)$ along the time interval $[0, 4]$. In Figure 12, we display the results along the interval $[0, 3]$, where we randomly select the initial values from $\mathcal{U}([-2, 2]^2)$ and sample the corresponding 20 trajectories using different neural controllers.
In comparison with existing methods, we use the above ES(+ICNN) control. For LQR controller, we select $Q = 20I_2$, $R = I_2$ to stabilize the state to zero, the corresponding feedback control matrix

Figure 11: The Loss functions in the training processes, respectively, for using the ES(+ICNN) (left), the ES(+Quadratic) (middle), and the AS (right), respectively.

solved from the Riccati equation is $K = ((4.45, 0.09)^\top, (0.09, 3.6)^\top)$. For both the HDSCLF and BALSA method, there are three variables u_1, u_2, d to be solved by Quadratic Program (QP), where u_1, u_2 are the control to be found and d is the relaxation parameter. We pick the objective function as $u_1^2 + u_2^2 + 10d^2$, and select control Lyapunov function V as the LQR solution K in HDSCLF, $V = \frac{1}{2}\boldsymbol{x}^\top P\boldsymbol{x}$ with $A^\top P + PA = -N$ for some $N > 0$ as required in BALSA (Fan et al., 2020), where A is the drift matrix. The solution of this Lyapunov function with $N = ((2, 1)^\top, (1, 4)^\top)$ is $P = ((3, 1)^\top, (1, 3)^\top)$.

Figure 12: The 20 trajectories with the initial values sampled from $\mathcal{U}([-2, 2]^2)$. The trajectories of the controlled system are displayed along the two time intervals: $[0, 3.0]$ (bottom) and $[2.4, 3.0]$ (top middle & right). Here, the solid line and the shaded areas are the same as those defined in Figure 5.

A.5.2 Controlling Inverted Pendulum

Controlling the inverted pendulum is one of the classic nonlinear control problems (Anderson, 1989; Huang & Huang, 2000), which is governed by $ml^2\ddot{\theta} = mgl\sin\theta - \beta\dot{\theta}$. Here, m is the mass of the pendulum, g is the gravitational acceleration, l is the pole length, and β is the friction coefficient. Mathematically, the pendulum can be written as a system with two state variables: θ, the angle deviating from the vertical position $x = 0$, and $\dot{\theta}$, the angular velocity. Denote the 2-D state variable by $\boldsymbol{x} = (\theta, \dot{\theta})$. Then, we apply the AS articulated in Algorithm 2 to steer the system to the equilibrium

Figure 13: A schematic diagram of the inverted pendulum system (left), the sampled trajectories of the angle θ (middle), and the corresponding orbits in the phase space (right).

$x = 0$ (sustaining the pendulum inverted). The schematic diagram of the inverted pendulum system and successful control results are shown in Figure 13. The sampled trajectories are initiated from different angles and angular velocities [i.e., $(\theta(0), \dot{\theta}(0)) = (-5,\ 5),\ (-1,\ 3),\ (3,\ -4)$].

The controlled inverted pendulum equation is written as:

$$
\begin{aligned}
\mathrm{d}x &= y\mathrm{d}t + u_1(x, y)\mathrm{d}B_t, \\
\mathrm{d}y &= \frac{g}{l}\sin x - \frac{\beta}{ml^2}y + u_2(x, y)\mathrm{d}B_t.
\end{aligned}
\tag{16}
$$

Here, we use the AS to design the neural stochastic controllers $u_{1,2}$ to stabilize the system to the inverted position. As such, we select $\alpha = 0.5$ and Control$(2, 6, 2)$ with $\mathcal{F}(\cdot) = \textbf{ReLU}$. We train the NNs using the $1,000$ data sampled from $\mathcal{U}([-10, 10]^2)$. A successful control has been shown in the main text (Figure 13). We perform further specific experiments on this system in Appendix A.8.

A.5.3 Controlling Stuart-Landau Equation

The underlying system is written as $\dot{Z} = (-25 + \mathrm{i} + |Z|^2)Z$. Let $Z = \rho e^{\mathrm{i}\theta}$. Then, the original system is transformed into $\dot{\rho} = (\rho^2 - 25)\rho$ and $\dot{\theta} = 1$. Since $\rho = 5$ corresponds to the unstable limit cycle, we use the transformation $\tilde{\rho} = \rho - 5$ to shift it to the zero equilibrium, and then consider the following controlled system:

$$
\mathrm{d}\tilde{\rho} = \tilde{\rho}(\tilde{\rho} + 5)(\tilde{\rho} + 10)\mathrm{d}t + u(\tilde{\rho})\mathrm{d}B(t).
$$

Here, for constructing the AS, we use the nonlinear control function as Control$(1, 10, 1)$ with $\mathcal{F}(\cdot) = \textbf{Tanh}$ and $\alpha = 0.5$. Particularly, we train the NNs using the $3,000$ data sampled from $\mathcal{U}([-30, 30])$. We also sample 30 initial values from $(\rho, \theta) \sim \mathcal{U}([3, 10]) \times \mathcal{U}([0, 6.28])$ and numerically get their solutions without and with neural stochastic control along the time interval $[0, 0.2]$. Then, we use the constructed AS to stabilize the system successfully, as shown in the main text (Figure 7).

A.5.4 Synchronization of Stuart-Landau Equations

Here, we consider the n Stuart-Landau oscillators coupled in the form of

$$
\dot{Z}_j = Z_j - (1 + \mathrm{i}c_2)|Z_j|^2 Z_j - \sigma(1 + \mathrm{i}c_1) \sum_{k=1}^{n} L_{jk} Z_k,
$$

where $\sum_{k=1}^{n} L_{jk} = 0$ for all $j = 1, \cdots, n$. Using the coordinates $Z_j = \rho_j e^{i\theta_j}$, we have

$$
\begin{aligned}
\dot{\rho}_j =& \rho_j - \rho_j^3 - \sigma \sum_{k=1}^{n} L_{jk}\rho_k \left[\cos(\theta_k - \theta_j) - c_1 \sin(\theta_k - \theta_j)\right], \\
\dot{\theta}_j =& - c_2\rho_j^2 - \sigma \sum_{k=1}^{n} L_{jk}\frac{\rho_k}{\rho_j}\left[c_1 \cos(\theta_k - \theta_j) + \sin(\theta_k - \theta_j)\right].
\end{aligned}
\tag{17}
$$

Let $\tilde{\rho}_j = \rho_j - 1$ and notice that system (17) only depends on $\theta_k - \theta_j$ for $j, k = 1, \cdots, n$. Thus, letting $\tilde{\theta}_j = \theta_j - \theta_{j+1}$ yields:

$$
\begin{aligned}
\dot{\tilde{\rho}}_j =& (\tilde{\rho}_j + 1) - (\tilde{\rho}_j + 1)^3 - \sigma \sum_{k=1}^{n} L_{jk}(\tilde{\rho}_k + 1)p(\theta_k - \theta_j), \\
\dot{\tilde{\theta}}_j =& -c_2 \left[(\tilde{\rho}_j + 1)^2 - (\tilde{\rho}_{j+1} + 1)^2\right] \\
& - \sigma \sum_{k=1}^{n} \left[L_{jk}\frac{\tilde{\rho}_k + 1}{\tilde{\rho}_j + 1}q(\theta_k - \theta_j) - L_{j+1,k}\frac{\tilde{\rho}_k + 1}{\tilde{\rho}_{j+1} + 1}q(\theta_k - \theta_j)\right],
\end{aligned}
\tag{18}
$$

where

$$
p(\theta) = \cos\theta - c_1 \sin\theta, \quad q(\theta) = c_1 \cos\theta + \sin\theta,
\tag{19}
$$

$$
\theta_k - \theta_j = \begin{cases} -\tilde{\theta}_j - \cdots - \tilde{\theta_{k-1}}, \ k > j, \\ 0, \ k = j, \\ \tilde{\theta}_k + \cdots + \tilde{\theta_{j-1}}. \end{cases}
\tag{20}
$$

Hence, we successfully transform the original coupled system (17) with the states $\{\rho_j, \theta_j, \ j = 1, \cdots, n\}$ into a new coupled system (18) with (18)-(20) and the states $\{\tilde{\rho}_i, \ i = 1, \cdots, n; \ \tilde{\theta}_j, \ j = 1, \cdots, n-1\}$. In particular, the synchronous manifold $\{\rho_j = 1, \ \theta_1 = \cdots = \theta_n\}$ in the original system (17) becomes the equilibrium of the transformed system (18), i.e., $\{\tilde{\rho}_i = 0, \ \tilde{\theta}_j = 0\}$.

Now, we use the AS, the neural stochastic control, to stabilize this equilibrium of system (18) and equivalently realize the synchronization in the original coupled system. For implementing numerical experiment, we set $c_1 = -1.8$, $c_2 = 4$, $\sigma = 0.01$, and $n = 20$. We further set the Laplace matrix $L = (L_{jk})_{n\times n}$ as

$$
L_{jk} = \begin{cases} 1 - \dfrac{1}{n}, \ j = k, \\ -\dfrac{1}{n}, \ j \neq k. \end{cases}
\tag{21}
$$

We construct the AS as Control$(39, 80, 39)$ with $\mathcal{F}(\cdot) = \textbf{ReLU}$ and $\alpha = 0.75$. Particularly, we sample $5,000$ points from

$$
(\tilde{\rho}_1, \cdots, \tilde{\rho}_{20}) \times (\tilde{\theta}_1, \cdots, \tilde{\theta}_{19}) \sim \mathcal{U}([0,5]^{20}) \times \mathcal{U}([-5,5]^{19}),
$$

and get the information of the dynamics based on system (18) with (19) and (20). The training process for the AS seems to be pretty efficient, as shown in Figure 14.

Figure 14: The Loss function for training the AS, dropping to 1.23e-5 within only 30 iterations.

As for generating the controlled trajectories for ρ, θ, we make the following descriptions.

First, we randomly select the initial values for $\{\tilde{\rho}_i, \tilde{\theta}_j\}_{n=20}$ (we denote $\tilde{\theta}_{20}$ as θ_{20}) from $(\mathcal{U}[0,5])^{20} \times (\mathcal{U}[-1,1])^{20}$, and thus obtain the initial values for $\{\rho_j, \theta_j\}_{n=20}$ based on (20). Secondly, without any control, we generate the trajectories using (17) and (18), respectively. Finally, after the neural stochastic control is implemented, we use $\rho = \tilde{\rho} + 1$ and $(\theta_1, \cdots, \theta_{20})^\top = \mathcal{A}(\tilde{\theta}_1, \cdots, \tilde{\theta}_{19}, \theta_{20})^\top$ to get the controlled trajectories for ρ and θ, where

$$\mathcal{A} = \begin{pmatrix} 1 & 1 & \cdots & 1 \\ 0 & 1 & \cdots & 1 \\ \vdots & \vdots & \vdots & \vdots \\ 0 & 0 & \cdots & 1 \end{pmatrix}_{20 \times 20} .$$

A.5.5 Energy Cost of Control

Figure 15: The convergence performance of different k selected from $\{2, 4, 6, 8, 10\}$ and AS control. The mean energy(ME) $\mathcal{E}(\tau_{0.1}, 1.0)$ are computed from 20 random seeds $\{4r + 1, r = 0, \cdots, 19\}$

For the controlled nearly-linear SDE: $\mathrm{d}x = x \log(1 + x)\mathrm{d}t + u(x)\mathrm{d}B_t$, $x \in \mathbb{R}$. We construct the AS as Control$(1, 6, 1)$ with $\mathcal{F}(\cdot) = \mathbf{ReLU}$ and $\alpha = 0.9$. Particularly, we sample $4,000$ points from $\mathcal{U}([0, 50])$ as the training data. For computing the energy cost, we sample 20 trajectories initiating from the initial value $x(0) = 20$, using the linear control and the neural stochastic control of the AS along the time interval $[0, 1]$. The random seeds are set as $\{4i + 1, i = 0, \cdots, 19\}$. We compute numerically the stopping time τ_ϵ, as defined in Theorem 4.1 and with $\epsilon = 0.1$, for each trajectory, and further compute the integration of $\int_0^{\tau_\epsilon \wedge 1} [u(x(t))]^2 \mathrm{d}t$ along each trajectory. Finally, we set the average of these integrations as an estimation of the energy cost for the respective control processes. We further conduct comprehensive experiments for many different values of k and compare their numerical performance to the proposed AS control method. The results are shown in Figure 15. We can see that AS control significantly outperforms linear control in terms of energy cost and convergence stability.

A.5.6 Data-Driven Pinning Control for Cell Fate Dynamics

Indeed, our frameworks can be extended to the model-free version via a combination with existing data reconstruction method. It should be noted that the proposed methods only depend on the samples of vector field in the learning stage instead of the explicit formula of systems (see Algorithm 1,2), implying that our frameworks inherently include the model-free situation. To

Figure 17: Pinning control for cell fate dynamics.

be concrete, we show that our framework can combine with Neural ODEs (NODEs) (Chen et al., 2018) to learn the control policy from time series data for the Cell Fate system (Sun et al., 2017; Laslo et al., 2006), which describes the interaction between two suppressors during cellular differentiation for neutrophil and macrophage cell fate choices. The system $\dot{\boldsymbol{x}} = f(\boldsymbol{x})$, $\boldsymbol{x} = (x_1, ..., x_6)$ has three steady states: $P_{1,2,3}$, where $P_{2,3}$ correspond to different cell fates and are stable and P_1 represents a critical expression level connecting the two fates and is unstable. The network structure of this 6-D system is a treemap, where one root node x_1 can stabilize itself under the original dynamic. Hence, we choose root node x_2 with maximum our degree and add pinning control on it to stabilize the system to unstable state P_1. The original trajectory that converges to P_2 (left) and the controlled

Figure 16: The sampled trajectories of the ESN (22) without and with the neural stochastic control of the AS. The 50-D ESN (22) is component-wisely displayed along the time interval $[0, 4]$ (the most left column) and the controlled ESN is component-wisely displayed along $[0, 0.05]$ (the second column from the left). The remaining panels depict the controlled dynamics of $x_{10, 20, \cdots, 50}$, a part of the components. Here, the solid line represents the average of the 10 realizations and the shaded area corresponds to the region which the trajectories in all the realizations sweep through. The initial values are set as $x_i^0 = -2 + \frac{i-1}{49}$ for $i = 1, \cdots, 50$.

trajectory that converges to P_1 (right) are shown in Figure 17. The original trajectory is used to train the NODE to reconstruct the vector field $\hat{f}$, then we use the sample of $\hat{f}$ as training data to learn our stochastic pinning control. We provide experimental details in Appendix A.5.6. The results in this section do not conflict with those in the Appendix A.9 because the 3-link pendulum does not has the similar treemap structure and self-stabilizing nodes as the cell fate system.

The stem cell fate dynamic is written as:

$$
\begin{aligned}
\dot{x_1} &= 0.5 - ax_1, \\
\dot{x_2} &= 5x_1/((1+x_1)(1+x_3^4)) - bx_2, \\
\dot{x_3} &= 5x_4/((1+x_4)(1+x_2^4)) - cx_3, \\
\dot{x_4} &= 0.5/(1+x_2^4) - ax_4, \\
\dot{x_5} &= (x_1x_4/(1+x_1x_4) + 4x_3/(1+x_3))/(1+x_2^4) - ax_5, \\
\dot{x_6} &= (x_1x_4/(1+x_1x_4) + 4x_2/(1+x_2))/(1+x_3^4) - ax_6.
\end{aligned}
$$

We set $a = b = c = 1$, then this system has 3 equilibrium points P_1, P_2, P_3, where only P_1 is unstable. Now we use data-driven method to find pinning control to stabilize P_1. We use coordinate transformations first to transform P_1 to zero for simplicity.

The connection graph structure of this model is a treemap, where x_1, x_2 directly affect all the other nodes. From the dynamic, x_1 is exponential stable in itself, hence we can pin control the root node x_2 to stabilize the whole system.

For model reconstruction stage, we use NODE with $(6, 50, 6)$ NN structure with $\mathcal{F}(\cdot) = $ **Tanh** to fit time series data $\mathcal{D}$ on interval $[0, 15]$ initiated from $(0.5, -0.9, 0.6, -0.6, -0.9, 0.5)$. We use standard NODE method at `https://github.com/rtqichen/torchdiffeq/tree/master/examples`. We sample the dynamic learned by NODE along $\mathcal{D}$ as the training data for AS. We learn pinning control for this dynamic that only add control to x_2, thus, we focus on stabilizing the sub-model for x_2 and treat other variables as parameters. We construct AS as Control$(1, 6, 6, 1)$ with $\mathcal{F}(\cdot) = $ **ReLU** and $\alpha = 0.9$.

A.6 Additional Experiments

A.6.1 Controlling the Echo State Network

Here, we show that our proposed frameworks of neural stochastic control can perform well in controlling high-dimensional dynamics. As such, we consider the Echo State Network (ESN), one of the pioneering reservoir computing methods (Lukoševičius & Jaeger, 2009; Jaeger & Haas, 2004) and having an appealing property of dynamical short-term memory capacity (Jaeger, 2007). The reservoir states in the ESN are formulated as (Zhu et al., 2019):

$$\dot{\boldsymbol{x}} = f_{\textbf{res}}(A\boldsymbol{x} + \boldsymbol{b}), \ \boldsymbol{x} \in \mathbb{R}^n, \tag{22}$$

where the connection weight matrix A is a random matrix representing the reservoir. The ESN is asymptotically stable if the spectrum radius satisfies $\rho(A) < 1$; otherwise, it is unstable for $\rho(A) > 1$ (Jaeger, 2001).

Now, we use our stochastic neural control to stabilize the unstable equilibrium for the case where $n = 50$ and $f_{\textbf{res}} = \textbf{Tanh}$ or $\textbf{ReLU}$, and $\boldsymbol{b} = \textbf{0}$. Particularly, the AS is constructed as $\text{Control}(50, 200, 50)$ with $\mathcal{F}(\cdot) = \textbf{ReLU}$ and $\alpha = 0.8$. We train the parameters using the $5,000$ data sampled from $\mathcal{U}([-10, 10]^{50})$. Also we sample 10 trajectories along time interval $[0, 0.2]$ using the correspondingly trained neural stochastic control, respectively. The controlling results are shown in Figure 16.

A.6.2 Controlling the Lorenz System

Figure 18: The chaotic dynamics of the Lorenz system (23), initiating from $(3, 5, 6)$ on the time interval $[0, 40]$. The 3-D orbits in the phase space (left) and the trajectories component-wisely displayed (right).

Here, we consider the chaotic Lorenz system (Sparrow, 2012):

$$\dot{x} = 10(y - x), \quad \dot{y} = x(28 - z) - y,$$
$$\dot{z} = xy - \frac{8}{3}z, \tag{23}$$

which has three unstable equilibriums: $P_1 = (0, 0, 0)$, $P_2 = (6\sqrt{2}, 6\sqrt{2}, 27)$ and $P_3 = (-6\sqrt{2}, -6\sqrt{2}, 27)$, as shown in Figure 18. Controlling chaos is always validated by using this paradigmatic system and its controlled system (Yang et al., 1997, 2002; Ma et al., 2015). It is noted that the equilibriums $P_{2,3}$ are of the same type. So, a successful stabilization of P_2 implies a successful stabilization of P_3. Thus, in what follows, we stabilize $P_{1,2}$ using the neural stochastic control of the ES in different configurations. Precisely, we apply, respectively,

1. ES(+ICNN): $\varepsilon = 0.001$, ICNN(12, 12, 12, 1), and Control(3, 10, 10, 3) with $\mathcal{F}(\cdot) = \textbf{ReLU}$ and $b = 2.1$, and

2. ES(+Quadratic): $\varepsilon = 0.001$, Quadratic(3, 12, 12, 3), and Control(3, 10, 10, 3) with $\mathcal{F}(\cdot) = \textbf{ReLU}$ and $b = 2.1$.

For stabilizing P_1, we train these NNs for 200 epochs with the batch size 100 and the iterations $2,000$, using the $10,000$ data sampled from $\mathcal{U}([0, 10]^3)$ along the vector field produced by system

Figure 19: Controlling the Lorenz system (23) by using the neural stochastic control of the ES(+ICNN) and the ES(+Quadratic), respectively. The system, initiating from either one of the three positions $Q_{1,2,3}$, is stabilized to P_1 or P_2.

(23). For stabilizing P_2, we first use $\tilde{x} = x - 6\sqrt{2}$, $\tilde{y} = y - 6\sqrt{2}$, and $\tilde{z} = z - 27$ to transform P_2 to the zero solution of a new system, denoted by $(\tilde{x}, \tilde{y}, \tilde{z})$. Then, we train the NNs for controlling $(\tilde{x}, \tilde{y}, \tilde{z})$ in the same manner as the training procedure for stabilizing P_1. As for the initial values, we select as $Q_1 = (9, 6, 8)$, $Q_2 = (3, 5, 6)$, and $Q_3 = (1, 9, 2)$. The controlling results using different neural stochastic controllers are shown in Figure 19 and Table 2, respectively.

Table 2: The results, using the ES(+ICNN) and the ES(+Quadratic), are obtained through averaging the corresponding quantities produced by 20 randomly-sampled trajectories. The quantities are defined in the same manner as those in Table 1, where $T = 20$ and the thresholds for computing Ct are set as 1e-10 (for P_1) and 0.02 (for P_2), respectively.

	Tt	Di	Ct
ES(+ICNN): P_1	283.251s	**2.43e-45**	**1.776**
ES(+Quadratic): P_1	**124.623**s	4.77e-45	4.082
ES(+ICNN): P_2	190.464s	**1.16e-5**	**2.600**
ES(+Quadratic): P_2	**44.196**s	0.017	14.823

A.7 Combination with Deterministic Control

In this section, we consider different control combinations for the controlled dynamics $d\boldsymbol{x} = [f(\boldsymbol{x}) + \boldsymbol{u}_f(\boldsymbol{x})]dt + [g(\boldsymbol{x}) + \boldsymbol{u}_g(\boldsymbol{x})]dB_t$, that is, the deterministic control $\boldsymbol{u} = (\boldsymbol{u}_f, \boldsymbol{0})$, the mixed control $\boldsymbol{u} = (\boldsymbol{u}_f, \boldsymbol{u}_g)$, the proposed stochastic control $\boldsymbol{u} = (\boldsymbol{0}, \boldsymbol{u}_g)$. Similar to the proposed neural stochastic control, we can find the neural deterministic control and mixed control with the same loss functions in ES and AS. the results are shown in Figure 20. We can see that both mixed control and stochastic control outperform deterministic control in terms of convergence rate and energy cost, this illustrates the benefits of introducing the stochastic term in control. The mixed control may be more efficient because it uses both stochastic and deterministic control simultaneously. By contrast, our method allows using the stochastic term only to realize the stochastic stability while all the traditional

methods merely use the deterministic control for stabilizing the stochastic systems. This difference indicates that noise is regarded a positive factor in our stabilization, contrary to the common sense. To the best of our knowledge, there are no existing methods integrating the pure noise control with the neural networks. Therefore, our work indeed extends the existing methods non-trivially, which can be seen as a solid step for treating noise as a beneficial part with provable stability guarantee using neural networks.

Here, for all three kinds of neural controllers, we use AS Control(2,6,6,2) with $\alpha = 0.8$ and $\mathcal{F}(\cdot) = \mathbf{ReLU}$, we train the NNs using the $1,000$ data sampled from $\mathcal{U}([-10, 10]^2)$. We sample 10 trajectories along time interval $[0, 0.5]$ using the correspondingly trained neural controllers, respectively.

Figure 20: Numerical performance of different control combinations in the inverted pendulum experiment: deterministic control(Left), mixed control(Middle), stochastic control(Right), the mean energy for control process $\mathcal{E}(\tau_{0.1}, 0.5)$ is computed from 10 random seeds $\{2i + 1, i = 0, \cdots, 9\}$.

A.8 Roles of Hyperparameters

Here, we investigate the role of the hyperparameter b in using the ES and the role of the hyperparameter α in using the AS. The investigations are performed on the physical example, the inverted pendulum system (16).

● **The role of** b. We test the performances of the ES(+Quadratic) in the stabilization of system (16) for different values of b. Here, the values of b are equally spaced in $[1.0, 3.0]$. We configure the ES(+Qadratic) as Quadratic$(2, 6, 2)$ with $\mathcal{F}(\cdot) = \mathbf{Tanh}$ and Control$(2, 6, 6, 2)$ with $\mathcal{F}(\cdot) = \mathbf{ReLU}$. We train the NNs using 500 data sampled from $\mathcal{U}([-10, 10])$. Furthermore, for each b and the corresponding ES(+Qadratic), we sample 5 controlled trajectories along the time interval $[0, 2]$.

In Figure 21, we show the average convergence position of the variable $\theta(t)$ over the 5 sampled trajectories for a given b. The closer the position to zero, the better the neural stochastic controller performs. Clearly, the controller does not perform very well as b is either large or small. Actually, b can be regarded as an upper bound for the exponential decay rate of the solution. A smaller b corresponds to a lower convergence rate, while a larger b, theoretically, can speed up the convergence. However, in applications, it is hard to treat the case of the larger b because it requires more complex structures of the NNs and more training data for finding the effective Lyapunov function and the useful stochastic control function.

Through the simulations, we select five optimal values, $\{1.9, 2.0, 2.1, 2.2, 2.3\}$, for b and compare their performances in training process and control process in details. The corresponding results are displayed in Figure 22. Clearly, the best value for b is 2.1, and, at this value, the correspondingly-constructed Lyapunov function V and the control function u have a property of the stronger convexity.

Figure 21: The convergence positions of $\theta(t)$ in the controlled system (16) for different values of b selected from $\{1.0, 1.1, \cdots, 2.9\}$. Here in the simulations, the time for the convergence position is set at $t = 2$, and the position for each b is obtained through averaging the quantities of the 5 sampled trajectories.

Figure 22: Training and control results of the controlled system (16) for the hyperparameter b in the ES taking values from $\in \{1.9, 2.0, 2.1, 2.2, 2.3\}$, respectively. Here, depicted are the training losses (top row), the averages of the variable θ on the 5 sample trajectories initiating from $(3, 5)$ along the time interval (second row), the constructed Lyapunov functions V (third row), and the constructed control functions u (bottom row). The dashed lines in the panels in the third row correspond to the contour lines of $\{V \leq 0.05\}$.

● **The role of α.** Next, we test the performances of the AS in the stabilization of system (16) for different values of α, where the values of α are equally spaced in $[0, 1]$. To this end, we construct the AS as Control$(2, 6, 6, 2)$ with $\mathcal{F}(\cdot) = $ **ReLU**. We sample 500 points from $\mathcal{U}([-10, 10])$ as the training data. For each α and the corresponding AS, we sample 10 controlled trajectories along the time interval $[0, 0.6]$. We depict the average final position of the variable $\theta(t)$ over the 10 sampled trajectories in Figure 23. Clearly, the control efficacy becomes better and better with an increase of α.

Moreover, through the simulations, we select seven optimal values, $\{0.65, 0.7, 0.75, 0.8, 0.85, 0.9, 0.95\}$, for α. As clearly shown in Figure 24, the convexity of the correspondingly-constructed control function u becomes stronger as the value of α increases.

Figure 23: The convergence positions of $\theta(t)$ in the controlled system (16) for different values of α selected from $\{0.05, 0.1, 0.15, \cdots, 0.95\}$. Here in the simulations, the time for the convergence position is set at $t = 0.6$, and the convergence position for each α is obtained through averaging the quantities of the 10 sampled trajectories.

Figure 24: Training and control results of the controlled system (16) for the hyperparameter α in the AS taking values from $\{0.65, 0.7, 0.75, 0.8, 0.85, 0.9, 0.95\}$, respectively. Here, depicted are the training losses (top row), the averages of the variables θ and $\dot{\theta}$ on the 10 sample trajectories initiating from $(3, 5)$ along the time interval (two middle rows), and the correspondingly-constructed control functions u (bottom row).

A.9   Limitations

Here, we point out some limitations of the proposed frameworks. As we stabilize an n-D system with its state as $\boldsymbol{x} = (x_1, \cdots, x_n)$, the proposed controller requires each component x_j $(j = 1, \cdots, n)$ to be accessible for control. In fact, our Algorithms 1 and 2 sometimes could be successfully in stabilization when taken into account is the complete control but the partial control (i.e., $x_{i_1}, \cdots, x_{i_k}$ with $1 \leq i_1 < \cdots < i_k < n$ or $i_k = 1$, some components of the state, are accessible for control). However, we cannot guarantee the descent of the loss because of a lack of the stochastic stability theory for the partial control.

To illustrate it, we consider the 3-link planar pendulum. The 3-link pendulum system possesses 6 state variables $(\theta_1, \theta_2, \theta_3, \dot\theta_1, \dot\theta_2, \dot\theta_3)$, which represent the 3 link angles and the 3 angle velocities. Suppose that, for $i = 1, 2, 3$, each link has mass m_i, length l_i, moments of inertia i_i, and relative position l_{ci} of the center of gravity. Thus, the controlled dynamics becomes:

$$\mathrm{d}\boldsymbol{x} = \boldsymbol{y}\mathrm{d}t + \boldsymbol{u}_1\mathrm{d}B_1(t),$$
$$\mathrm{d}\boldsymbol{y} = M(\boldsymbol{x})^{-1}[-N(\boldsymbol{x},\boldsymbol{y})\boldsymbol{y} - Q(\boldsymbol{x})]\mathrm{d}t + M(\boldsymbol{x})^{-1}\boldsymbol{u}_2\mathrm{d}B_2(t),$$

where $\boldsymbol{x} = (\theta_1, \theta_2, \theta_3)^\top$, $\boldsymbol{y} = (\dot\theta_1, \dot\theta_2, \dot\theta_3)^\top$, $M, N \in \mathbb{R}^{3\times 3}$, $Q \in \mathbb{R}^3$ with

$$M_{ij} = a_{ij}\cos(x_j - x_i), \ \ N_{ij} = -a_{ij}y_j\sin(x_j - x_i), \ \ Q_i = -b_i\sin(x_i),$$
$$a_{ii} = I_i + m_i l_{ci}^2 + l_i^2 \sum_{k=i+1}^{3} m_k, \ \ a_{ij} = a_{ji} = m_j l_i l_{cj} + l_i l_j \sum_{k=j+1}^{3} m_k,$$
$$b_i = m_i l_{ci} + l_i \sum_{k=i+1}^{3} m_k.$$

Here, we, respectively, investigate the complete control (case 1) $\boldsymbol{u} = (\boldsymbol{u}_1, \boldsymbol{u}_2)$ and the partial control (case 2) $\boldsymbol{u} = (\boldsymbol{0}, \boldsymbol{u}_2)$ with AS control. We construct the AS as $\mathrm{Control}(6, 24, 24, 6)$ and $\mathrm{Control}(6, 24, 24, 3)$ with $\mathcal{F}(\cdot) = \mathbf{ReLU}$. We sample 1000 points from $\mathcal{U}([-6, 6]^6)$ as the training data. We present the results in Figure 25. We can see that the complete control performs well in stabilizing 3-link pendulum systems, as guaranteed by the stochastic stability theory; nevertheless, the loss using the partial control cannot converge to zero. Generally, the partial control is more practical for utilization. Therefore, the stochastic theory assuring the efficacy of the partial control is urgently needed.

Figure 25: Dynamics of the state variables in the uncontrolled system (a) and in the controlled system using the complete control (b), initiating from $(\theta_1, \theta_2, \theta_3, \dot\theta_1, \dot\theta_2, \dot\theta_3)|_{t=0} \sim \mathcal{N}(0, I_{6\times 6})$. Logarithm of the training loss in case 1 using the complete control (c) and in case 2 using the partial control (d).

Furthermore, the neural auxiliary functions can easily satisfy the soft constraint/constraints in Theorems 2.2,2.3 due to the flexible structures of NNs and large amounts of adjustable parameters. However, we cannot guarantee the sufficient conditions are totally satisfied in the whole space because we have not solved the hard constraints optimization directly as opposed to the other existing QP or SOS based methods (Sarkar et al., 2020; Fan et al., 2020; Tan & Packard, 2004). Although we pay strictness for flexibility, our neural controller can be efficient in the control process due to the trained feedback form in advance, while the other methods solve the hard constrained optimization for each state at each time step in the control process. Hence, we can trade off between practicability and strictness according to the specific problems.

A.10 More Details on Related Work

Benefits of Stochastic Component The stochastic stability theory have been systematically and fruitfully achieved in the past several decades Mao (1991, 1994a). The stochastic stability criteria often use the Lyapunov-like conditions Mao (2007), which even includes the degenerated case of the stability in ODEs. Most of the established criteria regard the noise as a negative effect impacting the stability; however, there are still some advances on the positive effect of stochasticity in the stabilization of the dynamical systems. For example, the environmental Brownian noise can suppress the explosion of the population dynamics Mao et al. (2002), a certain amount of noise can suppress the exponential growth of SDEs to the polynomial growth or more general growth form Deng et al. (2008); Caraballo et al. (2003), and the multiplicative noise can stabilize and destabilize nonlinear or hybrid differential equations (Appleby et al., 2008; Mao et al., 2007). These, therefore, motivate us to

develop *only* neural stochastic control to stabilize different sorts of dynamical systems in this article. Moreover, the stochastic stability theory has been further generalized to the other systems, such as the stochastic difference equations Appleby et al. (2006), the stochastic functional differential equations Appleby (2003), the linear PDEs with Stratonovich's noise Caraballo & Robinson (2004), and the Markov switched stochastic differential equations Wang & Zhu (2017). All these generalizations could provide the directions for further investigations on neural stochastic control policies.

Robustness of NODE   Inspired by the residual neural networks (He et al., 2016), the neural ODE (Chen et al., 2018) method was established to model the continuous-time dynamical system by approximating the original dynamics of this system with trainable layers. Recently, many researchers have conducted studies on robustness and adaptability of neural ODEs. In (Yan et al., 2019), the authors explored the intrinsic robustness of neural ODEs via the translation invariance of time-invariant system, and propose TisODE to improve the robustness of deep networks. In (Xie et al., 2019), the authors designed a special filter with feature denoising property that can remove the perturbation's pattern from feature maps, which can also be combined the NODE method to improve the robustness.

Generate CLFs   In this paper, we use neural networks to find the auxiliary functions with soft stability guarantee, while the existing work just use the hard constrained optimization to generate the auxiliary functions, i.e. CLFs. In (Tan & Packard, 2004), the authors propose to use the sum of squares optimization to generate a polynomial CLF for deterministic controls. This process is not using gradient descent with a soft loss function but is rather solving a constrained optimization (SDP) to generate the CLF itself. In (Parrilo, 2000), the method of polynomial approximations for the dynamics and the search of SOS as Lyapunov functions through SDP is given systematically. Further, (Leong et al., 2016) provides some methods for generating a CLF for stochastic systems using the Hamilton-Jacobi-Bellman formulation.