Correlative Information Maximization Based Biologically Plausible Neural Networks for Correlated Source Separation

Abstract

The brain effortlessly extracts latent causes of stimuli, but how it does this at the network level remains unknown. Most prior attempts at this problem proposed neural networks that implement independent component analysis which works under the limitation that latent causes are mutually independent. Here, we relax this limitation and propose a biologically plausible neural network that extracts correlated latent sources by exploiting information about their domains. To derive this network, we choose maximum correlative information transfer from inputs to outputs as the separation objective under the constraint that the outputs are restricted to their presumed sets. The online formulation of this optimization problem naturally leads to neural networks with local learning rules. Our framework incorporates infinitely many source domain choices and flexibly models complex latent structures. Choices of simplex or polytopic source domains result in networks with piecewise-linear activation functions. We provide numerical examples to demonstrate the superior correlated source separation capability for both synthetic and natural sources.

1 Introduction

Extraction of latent causes, or sources, of complex stimuli sensed by sensory organs is essential for survival. Due to absence of any supervision in most circumstances, this extraction must be performed in an unsupervised manner, a process which has been named blind source separation (BSS) (Comon & Jutten, 2010; Cichocki et al., 2009).

How BSS may be achieved in visual, auditory, or olfactory cortical circuits has attracted the attention of many researchers, e.g. (Bell & Sejnowski, 1995; Olshausen & Field, 1996; Bronkhorst, 2000; Lewicki, 2002; Asari et al., 2006; Narayan et al., 2007; Bee & Micheyl, 2008; McDermott, 2009; Mesgarani & Chang, 2012; Golumbic et al., 2013; Isomura et al., 2015). Influential papers showed that visual and auditory cortical receptive fields could arise from performing BSS on natural scenes (Bell & Sejnowski, 1995; Olshausen & Field, 1996) and sounds (Lewicki, 2002). The potential ubiquity of BSS in the brain suggests that there exists generic neural circuit motifs for BSS (Sharma et al., 2000). Motivated by this observation, here, we present a set of novel biologically plausible neural network algorithms for BSS.

BSS algorithms typically derive from normative principles. The most important one is the information maximization principle, which aims to maximize the information transferred from input mixtures to separator outputs under the restriction that the outputs satisfy a specific generative assumption about sources. However, Shannon mutual information is a challenging choice for quantifying information transfer, especially for data-driven adaptive applications, due to its reliance on the joint and conditional densities of the input and output components. This challenge is eased by the independent component analysis (ICA) framework by inducing joint densities into separable forms based on the assumption of source independence, which is called the ICA-InfoMax approach (Bell & Sejnowski, 1995). As an alternative, Erdogan (2022) recently proposed the use of the second-order statistics-based *correlative (log-determinant) mutual information* maximization for BSS to eliminate the need for the independence assumption, allowing for correlated source separation.

In this article, we propose an online correlative information maximization-based biologically plausible neural network framework (CorInfoMax) for the BSS problem. Our motivations for the proposed framework are as follows:

- The correlative mutual information objective function is only dependent on the second-order statistics of the inputs and outputs. Therefore, its use avoids the need for costly higher-order statistics or joint pdf estimates,
- The corresponding optimization is equivalent to maximization of correlation, or linear dependence, between input and output, a natural fit for the linear inverse problem,
- The framework relies only on the source domain information, eliminating the need for the source independence assumption. Therefore, neural networks constructed with this framework are capable of separating correlated sources. Furthermore, the CorInfoMax framework can be used to generate neural networks for infinitely many source domains corresponding to the combination of different attributes such as sparsity, nonnegativity etc.,
- The optimization of the proposed objective inherently leads to learning with local update rules.
- CorInfoMax acts as a unifying framework to generate biologically plausible neural networks for various unsupervised data decomposition methods to obtain structured latent representations, such as nonnegative matrix factorization (NMF) (Fu et al., 2019), sparse component analysis (SCA) (Babatas & Erdogan, 2018), bounded component analysis (BCA) (Erdogan, 2013; Inan & Erdogan, 2014) and polytopic matrix factorization (PMF) (Tatli & Erdogan, 2021).

(a) (b)

Figure 1: CorInfoMax BSS neural networks for two different canonical source domain representations.

Figure 1 illustrates CorInfoMax neural networks for two different source domain representation choices, which are three-layer neural networks with piecewise linear activation functions. Lateral connections at the output neurons are based on the inverse of the correlation matrix of the outputs. We note that the proposed CorInfoMax framework, beyond solving the BSS problem, can be used to learn structured representations from data through the maximum correlative information transfer from inputs to the choice of the structured domain at the output.

1.1 RELATED WORK AND CONTRIBUTIONS

1.1.1 BIOLOGICALLY PLAUSIBLE NEURAL NETWORKS FOR BLIND SOURCE SEPARATION

There are different methods to solve the BSS problem through neural networks with local learning rules. These methods are differentiated on the basis of the observation models they assume and the normative approach they propose. We can list biologically plausible ICA networks as an example category, which are based on the exploitation of the presumed mutual independence of sources (Isomura & Toyoizumi, 2018; Bahroun et al., 2021). There exist alternative approaches which exploit different properties of the data model to replace the independence assumption with a weaker one. As an example, Pehlevan et al. (2017a) uses the nonnegativeness property along with the biologically inspired similarity matching (SM) framework (Pehlevan et al., 2017b) to derive biologically plausible neural networks that are capable of separating uncorrelated but potentially

dependent sources. Similarly, Erdogan & Pehlevan (2020) proposes bounded similarity matching (BSM) as an alternative approach that takes advantage of the magnitude boundedness property for uncorrelated source separation. More recently, Bozkurt et al. (2022) introduced a generic biologically plausible neural network framework based on weighted similarity matching (WSM) introduced in Erdogan & Pehlevan (2020) and maximization of the output correlation determinant criterion used in the NMF, SCA, BCA and PMF methods. This new framework exploits the domain structure of sources to generate two- / three-layer biologically plausible networks that have the ability to separate potentially correlated sources. Another example of biologically plausible neural networks with correlated source separation capability is offered in Simsek & Erdogan (2019), which also uses the determinant maximization criterion for the separation of antisparse sources.

Similarly to Bozkurt et al. (2022), the framework proposed in this article is a general framework for the separation of potentially correlated sources. However, it does not use similarity matching; therefore, the resulting network structure and update rules are completely different from Bozkurt et al. (2022). For example, the lateral connections of the outputs in Bozkurt et al. (2022) are based on the output autocorrelation matrix, while they are based on the inverse of the output autocorrelatin matrix. Compared to the approach in Simsek & Erdogan (2019), the proposed framework is derived from information-theoretic grounds, and its scope is not limited to antisparse sources, but to infinitely many different source domains.

1.1.2 INFORMATION MAXIMIZATION FOR UNSUPERVISED LEARNING

The use of Shannon's mutual information maximization for various unsupervised learning tasks dates back to a couple of decades. As one of the pioneering applications, we can list Linsker's work on self-organizing networks, which proposes maximizing mutual information between input and its latent representation as a normative approach (Linsker, 1988). Under the Gaussian assumption, the corresponding objective simplifies to determinant maximization for the output covariance matrix. Becker & Hinton (1992) suggested maximizing mutual information between alternative latent vectors derived from the same input source as a self-supervised method for learning representations. The most well-known application of the information maximization criterion to the BSS problem is the ICA-Infomax approach by Bell & Sejnowski (1995). The corresponding algorithm maximizes the information transferred from the input to the output under the constraint that the output components are mutually independent. For potentially correlated sources, Erdogan (2022) proposed the use of a second-order statistics-based correlative (or log-determinant) mutual information measure for the BSS problem. This approach replaces the mutual independence assumption in the ICA framework with the source domain information, enabling the separation of both independent and dependent sources. Furthermore, it provides an information-theoretic interpretation for the determinant maximization criterion used in several unsupervised structured matrix factorization frameworks such as NMF (or simplex structured matrix factorization (SSMF)) (Chan et al., 2011; Lin et al., 2015; Fu et al., 2018; 2019), SCA, BCA, and PMF. More recently, Ozsoy et al. (2022) proposed maximization of the correlative information among latent representations corresponding to different augmentations of the same input as a self-supervised learning method.

The current article offers an online optimization formulation for the batch correlative information maximization method of Erdogan (2022) that leads to a general biologically plausible neural network generation framework for the unsupervised unmixing of potentially dependent/correlated sources.

2 PRELIMINARIES

This section aims to provide background information for the CorInfoMax-based neural network framework introduced in Section 3. For this purpose, we first describe the BSS setting assumed throughout the article in Section 2.1. Then, in Section 2.2, we provide an essential summary of the batch CorInfoMax-based BSS approach introduced in (Erdogan, 2022).

2.1 BLIND SOURCE SEPARATION SETTING

SOURCES: We assume a BSS setting with a finite number of n-dimensional source vectors, represented by the set $\mathbb{S} = \{s(1), s(2), \ldots, s(N)\} \subset \mathcal{P}$, where $\mathcal{P}$ is a particular subset of $\mathbb{R}^n$. The choice of source domain $\mathcal{P}$ determines the identifiability of the sources from their mixtures, the properties

of the individual sources and their mutual relations. Structured unsupervised matrix factorization methods are usually defined by the source/latent domain, such as

i. *Normalized nonnegative sources in the NMF(SSMF) framework*: $\Delta = \{s \mid s \geq 0, \mathbf{1}^T s = 1\}$. Signal processing and machine learning applications such as hyperspectral unmixing and text mining (Abdolali & Gillis, 2021), (Fu et al., 2016).

ii. *Bounded antisparse sources in the BCA framework*: $\mathcal{B}_{\ell_\infty} = \{s \mid \|s\|_\infty \leq 1\}$. Applications include digital communication signals Erdogan (2013).

iii. *Bounded sparse sources in the SCA framework*: $\mathcal{B}_{\ell_1} = \{s \mid \|s\|_1 \leq 1\}$. Applications: modeling efficient representations of stimulus such as vision Olshausen & Field (1997) and sound Smith & Lewicki (2006). ·

iv *Nonnegative bounded antiparse sources in the nonnegative-BCA framework*: $\mathcal{B}_{\ell_\infty,+} = \mathcal{B}_{\ell_\infty} \cap \mathbb{R}^n_+$. Applications include natural images Erdogan (2013).

v. *Nonnegative bounded sparse sources in the nonnegative-SCA framework*: $\mathcal{B}_{\ell_1,+} = \mathcal{B}_{\ell_1} \cap \mathbb{R}^n_+$. Potential applications similar to Δ in (i).

Note that the sets in (ii)-(v) of the above list are the special cases of (convex) polytopes. Recently, Tatli & Erdogan (2021) showed that infinitely many polytopes with a certain symmetry restriction enable identifiability for the BSS problem. Each "identifiable" polytope choice corresponds to different structural assumptions on the source components. A common canonical form to describe polytopes is to use the H-representation Grünbaum et al. (1967):

$$\mathcal{P} = \{\boldsymbol{y} \in \mathbb{R}^n | \boldsymbol{A}_{\mathcal{P}} \boldsymbol{y} \preccurlyeq \boldsymbol{b}_{\mathcal{P}}\}, \tag{1}$$

which corresponds to the intersection of half-spaces. Alternatively, similar to Bozkurt et al. (2022), we can consider a subset of polytopes, which we refer to as "feature-based" polytopes, defined in terms of attributes (such as non-negativity and sparseness) assigned to the subsets of components:

$$\mathcal{P} = \left\{\boldsymbol{s} \in \mathbb{R}^n \mid s_i \in [-1,1] \, \forall i \in \mathcal{I}_s, \, s_i \in [0,1] \, \forall i \in \mathcal{I}_+, \, \|\boldsymbol{s}_{\mathcal{J}_l}\|_1 \leq 1, \, \mathcal{J}_l \subseteq \mathbb{Z}_n^+, \, l \in \mathbb{Z}_L^+\right\}, \tag{2}$$

where $\mathcal{I}_s \subseteq \mathbb{Z}_n^+$ is the set of indexes for signed sources, and $\mathcal{I}_+$ is its complement, $\boldsymbol{s}_{\mathcal{J}_l}$ is the sub-vector constructed from the elements with indices in $\mathcal{J}_l$, and L is the number of sparsity constraints imposed on the sub-vector level. In this article, we consider both polytope representations above.

MIXING: We assume a linear generative model, that is, the source vectors are mixed through an unknown matrix $\boldsymbol{A} \in \mathbb{R}^{m \times n}$, $\boldsymbol{x}(i) = \boldsymbol{A}\boldsymbol{s}(i)$, $\forall i = 1, \ldots, N$, where we consider the overdetermined case, that is, $m \geq n$ and $rank(\boldsymbol{A}) = n$.

SEPARATION: The purpose of the source separation setting is to recover the original source matrix $\boldsymbol{S}$ from the mixture matrix $\boldsymbol{X}$ up to some scaling and/or permutation ambiguities, that is, the separator output vectors $\{\boldsymbol{y}(i)\}$ satisfy $\boldsymbol{y}(i) = \boldsymbol{W}\boldsymbol{x}(i) = \boldsymbol{\Pi}\boldsymbol{\Lambda}\boldsymbol{s}(i)$, for all $i = 1, \ldots, N$, where $\boldsymbol{W} \in \mathbb{R}^{n \times m}$ is the learned separator matrix, $\boldsymbol{\Pi}$ is a permutation matrix, $\boldsymbol{\Lambda}$ is a full-rank diagonal matrix and $\boldsymbol{y}(i)$ refers to the estimate of the source of the sample index i.

2.2 CORRELATIVE MUTUAL INFORMATION MAXIMIZATION FOR BLIND SOURCE SEPARATION

Erdogan (2022) proposes maximizing the (correlative) information flow from the mixtures to the separator outputs, while the outputs are restricted to lie in their presumed domain $\mathcal{P}$. The corresponding batch optimization problem is given by

$$\underset{\boldsymbol{Y} \in \mathbb{R}^{n \times N}}{\text{maximize}} \quad I_{\text{LD}}^{(\epsilon)}(\boldsymbol{X}, \boldsymbol{Y}) = \frac{1}{2} \log \det(\hat{\boldsymbol{R}}_{\boldsymbol{y}} + \epsilon \boldsymbol{I}) - \frac{1}{2} \log \det(\hat{\boldsymbol{R}}_{\boldsymbol{e}} + \epsilon \boldsymbol{I}) \tag{3a}$$

$$\text{subject to} \quad \boldsymbol{Y}_{:,i} \in \mathcal{P}, i = 1, \ldots, N, \tag{3b}$$

where the objective function $I_{\text{LD}}^{(\epsilon)}(\boldsymbol{X}, \boldsymbol{Y})$ is the log-determinant (LD) mutual information[1] between the mixture and the separator output vectors (see Appendix A.1 and Erdogan (2022) for more information), $\hat{\boldsymbol{R}}_{\boldsymbol{y}}$ is the sample autocorrelation (or autocovariance) matrix for the separator output vector, $\hat{\boldsymbol{R}}_{\boldsymbol{e}}$ equals $\hat{\boldsymbol{R}}_{\boldsymbol{y}} - \hat{\boldsymbol{R}}_{\boldsymbol{xy}}^T (\hat{\boldsymbol{R}}_{\boldsymbol{x}} + \epsilon \boldsymbol{I})^{-1} \hat{\boldsymbol{R}}_{\boldsymbol{yx}}$ where $\hat{\boldsymbol{R}}_{\boldsymbol{xy}}$ is the sample cross-correlation (or

---

[1]In this article, we use "correlative mutual information" and "LD-mutual information" interchangeably.

cross-covariance) matrix between mixture and output vectors, and $\hat{\boldsymbol{R}}_{\boldsymbol{x}}$ is the sample autocorrelation (or covariance) matrix for the mixtures. As discussed in Appendix A.1, for sufficiently small ϵ, $\hat{\boldsymbol{R}}_{\boldsymbol{e}}$ is the sample autocorrelation (covariance) matrix of the error vector corresponding to the best linear (affine) minimum mean square error (MMSE) estimate of the separator output vector $\boldsymbol{y}$, from the mixture vector $\boldsymbol{x}$. Under the assumption that the original source samples are sufficiently scattered in $\mathcal{P}$, (Fu et al., 2019; Tatli & Erdogan, 2021), i.e., they form a maximal LD-entropy subset of $\mathcal{P}$, (Erdogan, 2022), then the optimal solution of (3) recovers the original sources up to some permutation and sign ambiguities, for sufficiently small ϵ.

The biologically plausible CorInfoMax BSS neural network framework proposed in this article is obtained by replacing batch optimization in (3) with its online counterpart, as described in Section 3.

3 METHOD: BIOLOGICALLY PLAUSIBLE NEURAL NETWORKS FOR CORRELATIVE INFORMATION MAXIMIZATION

3.1 ONLINE OPTIMIZATION SETTING FOR LD-MUTUAL INFORMATION MAXIMIZATION

We start our online optimization formulation for CorInfoMax by replacing the output and error sample autocorrelation matrices in (3a) with their weighted versions

$$\hat{\boldsymbol{R}}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(k) = \frac{1-\zeta_{\boldsymbol{y}}}{1-\zeta_{\boldsymbol{y}}^k} \sum_{i=1}^{k} \zeta_{\boldsymbol{y}}^{k-i} \boldsymbol{y}(i)\boldsymbol{y}(i)^T \quad \hat{\boldsymbol{R}}_{\boldsymbol{e}}^{\zeta_e}(k) = \frac{1-\zeta_e}{1-\zeta_e^k} \sum_{i=1}^{k} \zeta_e^{k-i} \boldsymbol{e}(i)\boldsymbol{e}(i)^T, \quad (4)$$

where $0 \ll \zeta_{\boldsymbol{y}} < 1$ is the forgetting factor, $\boldsymbol{W}(i)$ is the best linear MMSE estimator matrix (to estimate $\boldsymbol{y}$ from $\boldsymbol{x}$), and $\boldsymbol{e}(k) = \boldsymbol{y}(i) - \boldsymbol{W}(i)\boldsymbol{x}(i)$ is the corresponding error vector. Therefore, we can define the corresponding online CorInfoMax optimization problem as

$$\underset{\boldsymbol{y}(k) \in \mathbb{R}^n}{\text{maximize}} \quad \mathcal{J}(\boldsymbol{y}(k)) = \frac{1}{2} \log \det(\hat{\boldsymbol{R}}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(k) + \epsilon \boldsymbol{I}) - \frac{1}{2} \log \det(\hat{\boldsymbol{R}}_{\boldsymbol{e}}^{\zeta_e}(k) + \epsilon \boldsymbol{I}) \quad (5a)$$

$$\text{subject to} \quad \boldsymbol{y}_k \in \mathcal{P}. \quad (5b)$$

When $\mathcal{P}$ is a polytope with a half-space representation in (1), the optimization in (5) takes the form

$$\underset{\boldsymbol{y}(k) \in \mathbb{R}^n}{\text{maximize}} \quad \mathcal{J}(\boldsymbol{y}(k)) \quad (6a)$$

$$\text{subject to} \quad \boldsymbol{A}_{\mathcal{P}}\boldsymbol{y}(k) \preccurlyeq \boldsymbol{b}_{\mathcal{P}}. \quad (6b)$$

Note that the above formulation assumes knowledge of the best linear MMSE matrix $\boldsymbol{W}(i)$, whose update is formulated as a solution to an online regularized least squares problem,

$$\underset{\boldsymbol{W}(i) \in \mathbb{R}^{m \times n}}{\text{maximize}} \quad \mu_{\boldsymbol{W}} \|\boldsymbol{y}(i) - \boldsymbol{W}(i)\boldsymbol{x}(i)\|_2^2 + \|\boldsymbol{W}(i) - \boldsymbol{W}(i-1)\|_F^2. \quad (7a)$$

3.2 DESCRIPTION OF THE NETWORK DYNAMICS FOR SPARSE SOURCES

We now show that the gradient-ascent-based maximization of the online CorInfoMax objective in (5) corresponds to the neural dynamics of a multilayer recurrent neural network with local learning rules. Furthermore, the presumed source domain $\mathcal{P}$ determines the output activation functions and additional inhibitory neurons. For an illustrative example, in this section, we concentrate on the sparse special case in Section 2.1, that is, $\mathcal{P} = \mathcal{B}_{\ell_1}$. We can write the corresponding Lagrangian optimization setting as

$$\underset{\lambda \geq 0}{\text{minimize}} \underset{\boldsymbol{y}(k) \in \mathbb{R}^n}{\text{maximize}} \quad \mathcal{L}(\boldsymbol{y}(k), \lambda(k)) = \mathcal{J}(\boldsymbol{y}(k)) - \lambda(k)(\|\boldsymbol{y}(k)\|_1 - 1). \quad (8)$$

To derive network dynamics, we use the proximal gradient update (Parikh et al., 2014) for $\boldsymbol{y}(k)$ with the expression (A.14) for $\frac{d\mathcal{J}(\boldsymbol{y}(k))}{d\boldsymbol{y}(k)}\Big|_{\boldsymbol{y}(k)}$, derived in Appendix B, and the projected gradient descent update for $\lambda(k)$ using $\frac{d\mathcal{L}(\boldsymbol{y}(k),\lambda(k))}{d\lambda(k)}\Big|_{\boldsymbol{y}(k;\nu)} = \|\boldsymbol{y}(k;\nu+1)\|_1 - 1$, which leads to the following

iterations:

$$\boldsymbol{e}(k; \nu) = \boldsymbol{y}(k; \nu) - \boldsymbol{W}(k)\boldsymbol{x}(k) \tag{9}$$

$$\frac{d\mathcal{J}(\boldsymbol{y}(k))}{d\boldsymbol{y}(k)}\Big|_{\boldsymbol{y}(k;\nu)} = \gamma_{\boldsymbol{y}}(k)\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(k-1)\boldsymbol{y}(k;\nu) - \gamma_{\boldsymbol{e}}(k)\boldsymbol{B}_{\boldsymbol{e}}^{\zeta_{\boldsymbol{e}}}(k-1)\boldsymbol{e}(k;\nu), \tag{10}$$

$$\boldsymbol{y}(k; \nu + 1) = ST_{\lambda(k;\nu)}\left(\boldsymbol{y}(k;\nu) + \eta_{\boldsymbol{y}}(\nu)\frac{d\mathcal{J}(\boldsymbol{y}(k);)}{d\boldsymbol{y}(k)}\Big|_{\boldsymbol{y}(k;\nu)}\right) \tag{11}$$

$$\lambda(k; \nu + 1) = \text{ReLU}\left(\lambda(k;\nu) + \eta_\lambda(\nu)(\|\boldsymbol{y}(k;\nu+1)\|_1 - 1)\right), \tag{12}$$

where $\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(k)$ and $\boldsymbol{B}_{\boldsymbol{e}}^{\zeta_{\boldsymbol{e}}}(k)$ are inverses of $\boldsymbol{R}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(k-1)$ and $\boldsymbol{R}_{\boldsymbol{e}}^{\zeta_{\boldsymbol{e}}}(k-1)$ respectively, $\gamma_{\boldsymbol{y}}(k)$ and $\gamma_{\boldsymbol{e}}(k)$ are provided in (A.11) and (A.13), $\nu \in \mathbb{N}$ is the iteration index, $\eta_{\boldsymbol{y}}(\nu)$ and $\eta_\lambda(\nu)$ are the learning rates for the output and λ, respectively, at iteration ν, ReLU$(\cdot)$ is the rectified linear unit, and $ST_\lambda(.)$ is the soft-thresholding nonlinearity defined as $ST_\lambda(\boldsymbol{y})_i = \begin{cases} 0 & |y_i| \leq \lambda, \\ y_i - sign(y_i)\lambda & \text{otherwise} \end{cases}$. We represent the values in the final iteration ν_{final}, with some abuse of notation, with $\boldsymbol{y}(k) = \boldsymbol{y}(k;\nu_{final})$ and $\boldsymbol{e}(k) = \boldsymbol{e}(k;\nu_{final})$.

The neural dynamic iterations in (9)-(12) define a recurrent neural network, where $\boldsymbol{W}(k)$ represents feedforward synaptic connections from the input $\boldsymbol{x}(k)$ to the error $\boldsymbol{e}(k)$, $\boldsymbol{B}_{\boldsymbol{e}}^{\zeta_{\boldsymbol{e}}}(k)$ represents feedforward connections from the error $\boldsymbol{e}(k)$ to the output $\boldsymbol{y}(k)$, and $\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(k)$ corresponds to lateral synaptic connections among the output components. Next, we examine the learning rules for this network.

Update of inverse correlation matrices $\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(k)$ and $\boldsymbol{B}_{\boldsymbol{e}}^{\zeta_{\boldsymbol{e}}}(k)$: We can obtain the update expressions by applying matrix inversion lemma to $(\hat{\boldsymbol{R}}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(k) + \epsilon\boldsymbol{I})^{-1}$ and $(\hat{\boldsymbol{R}}_{\boldsymbol{e}}^{\zeta_{\boldsymbol{e}}}(k) + \epsilon\boldsymbol{I})^{-1}$, as derived in Appendix B to obtain (A.10) and (A.12)

$$\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(k+1) = \frac{1 - \zeta_{\boldsymbol{y}}^k}{\zeta_{\boldsymbol{y}} - \zeta_{\boldsymbol{y}}^k}(\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(k) - \gamma_{\boldsymbol{y}}(k)\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(k)\boldsymbol{y}(k)\boldsymbol{y}(k)^T\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(k)), \tag{13}$$

$$\boldsymbol{B}_{\boldsymbol{e}}^{\zeta_{\boldsymbol{e}}}(k+1) = \frac{1 - \zeta_{\boldsymbol{e}}^k}{\zeta_{\boldsymbol{e}} - \zeta_{\boldsymbol{e}}^k}(\boldsymbol{B}_{\boldsymbol{e}}^{\zeta_{\boldsymbol{e}}}(k) - \gamma_{\boldsymbol{e}}(k)\boldsymbol{B}_{\boldsymbol{e}}^{\zeta_{\boldsymbol{e}}}(k)\boldsymbol{e}(k)\boldsymbol{e}(k)^T\boldsymbol{B}_{\boldsymbol{e}}^{\zeta_{\boldsymbol{e}}}(k)). \tag{14}$$

However, note that (13), and (14) violate biological plausibility, since the multiplier $\gamma_{\boldsymbol{y}}$ and $\gamma_{\boldsymbol{e}}$ depend on all output and error components contrasting the locality. Furthermore, the update in (14) is not local since it is only a function of the feedforward signal $\boldsymbol{z}_e(k) = \boldsymbol{B}_{\boldsymbol{e}}^{\zeta_{\boldsymbol{e}}}(k)\boldsymbol{e}(k)$ entering into output neurons: the update of $[\boldsymbol{B}_{\boldsymbol{e}}^{\zeta_{\boldsymbol{e}}}]_{ij}$, the synaptic connection between the output neuron i and the error neuron j requires $[\boldsymbol{z}_e]_j$ which is a signal input to the output neuron j. To modify the updates (13) and (14) into a biologically plausible form, we make the following observations and assumptions:

- If $\zeta_{\boldsymbol{y}}$ is close enough to 1, and the time step k is large enough, $\gamma_{\boldsymbol{y}}(k)$ is approximately $\frac{1 - \zeta_{\boldsymbol{y}}}{\zeta_{\boldsymbol{y}}}$,

- $\hat{\boldsymbol{R}}_{\boldsymbol{e}}^{\zeta_{\boldsymbol{e}}}(k) + \epsilon\boldsymbol{I} \approx \epsilon\boldsymbol{I} \Rightarrow \boldsymbol{B}_{\boldsymbol{e}}^{\zeta_{\boldsymbol{e}}}(k+1) \approx \frac{1}{\epsilon}\boldsymbol{I}$, which is a reasonable assumption, as we expect the error $\boldsymbol{e}(k)$ to converge near zero in the noiseless linear observation model.

Therefore, we modify the update equation of $\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(k+1)$ as

$$\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(k+1) = \frac{1}{\zeta_{\boldsymbol{y}}}(\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(k) - \frac{1 - \zeta_{\boldsymbol{y}}}{\zeta_{\boldsymbol{y}}}\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(k)\boldsymbol{y}(k)\boldsymbol{y}(k)^T\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(k)), \tag{15}$$

and approximate $\boldsymbol{B}_{\boldsymbol{e}}^{\zeta_{\boldsymbol{e}}}(k+1)$ with $\epsilon^{-1}\boldsymbol{I}$.

Feed-forward synaptic connections $\boldsymbol{W}(k)$: The solution of online optimization in (7) is given by

$$\boldsymbol{W}(k+1) = \boldsymbol{W}(k) + \mu_{\boldsymbol{W}}(k)\boldsymbol{e}(k)\boldsymbol{x}(k)^T, \tag{16}$$

where $\mu_{\boldsymbol{W}}(k)$ is the step size, which corresponds to the adaptive least-mean-squares (LMS) update based on the MMSE criterion (Sayed, 2003).

Neural Network Realizations: Figure 2a shows the three-layer realization of the sparse CorInfo-Max neural network based on the network dynamics expressions in (9)-(12) and the approximation

Figure 2: Sparse CorInfoMax Network: (a) three-layer (b) two-layer.

$\boldsymbol{B}_{\boldsymbol{e}}^{\zeta_e}(k) \approx \frac{1}{\epsilon}\boldsymbol{I}$. The first layer corresponds to the error ($\boldsymbol{e}(k)$) neurons, and the second layer corresponds to the output ($\boldsymbol{y}(k)$) neurons with soft thresholding activation functions. If we substitute (9) and $\boldsymbol{B}_{\boldsymbol{e}}^{\zeta_e}(k+1) = \frac{1}{\epsilon}\boldsymbol{I}$ in (10), we obtain $\left.\frac{d\mathcal{J}(\boldsymbol{y}(k))}{d\boldsymbol{y}(k)}\right|_{\boldsymbol{y}(k;\nu)} = \boldsymbol{M}_{\boldsymbol{y}}^{\zeta_y}(k)\boldsymbol{y}(k;\nu) + \frac{\gamma_e}{\epsilon}\boldsymbol{W}(k)\boldsymbol{x}(k)$ where $\boldsymbol{M}_{\boldsymbol{y}}^{\zeta_y}(k) = \gamma_{\boldsymbol{y}}\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_y}(k) - \frac{\gamma_e}{\epsilon}\boldsymbol{I}$. Therefore, this gradient expression and (11)-(12) correspond to the two-layer network shown in Figure 2b.

3.3 Description of the Network Dynamics for other special source domains

We can generalize the procedure for obtaining CorInfoMax BSS networks in Section 3.2 for other source domains. The choice of source domain would affect the structure of the output layer and the potential inclusion of additional interneurons. Table 1 summarizes the output dynamics for special source domains provided in Section 2.1, for which the derivations are provided in Appendix C.

Table 1: Example source domains and the corresponding CorInfoMax network dynamics.

Source Domain	Output Dynamics	Output Activation
$\mathcal{P} = \Delta$	$\left.\frac{d\mathcal{J}(\boldsymbol{y}(k))}{d\boldsymbol{y}(k)}\right	_{\boldsymbol{y}(k;\nu)} = \gamma_{\boldsymbol{y}}\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_y}(k-1)\boldsymbol{y}(k;\nu) - \gamma_e\boldsymbol{B}_{\boldsymbol{e}}^{\zeta_e}(k-1)\boldsymbol{e}(k;\nu),$
$\boldsymbol{y}(k;\nu+1) = \text{ReLU}\left(\boldsymbol{y}(k;\nu) + \eta_{\boldsymbol{y}}(\nu)\left.\frac{d\mathcal{J}(\boldsymbol{y}(k))}{d\boldsymbol{y}(k)}\right|_{\boldsymbol{y}(k;\nu)} - \lambda(\nu)\right),$
$\lambda(k;\nu+1) = \lambda(k;\nu) + \eta_{\lambda}(\nu)\left(\left(\sum_{i=1}^n y_i(k;\nu+1)\right) - 1\right).$	ReLU(x)
$\mathcal{P} = \mathcal{B}_{\ell_\infty}$	$\left.\frac{d\mathcal{J}(\boldsymbol{y}(k))}{d\boldsymbol{y}(k)}\right	_{\boldsymbol{y}(k;\nu)} = \gamma_{\boldsymbol{y}}\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_y}(k-1)\boldsymbol{y}(k;\nu) - \gamma_e\boldsymbol{B}_{\boldsymbol{e}}^{\zeta_e}(k-1)\boldsymbol{e}(k;\nu),$
$\boldsymbol{y}(k;\nu+1) = \sigma_1\left(\boldsymbol{y}(k;\nu) + \eta_{\boldsymbol{y}}(\nu)\left.\frac{d\mathcal{J}(\boldsymbol{y}(k))}{d\boldsymbol{y}(k)}\right	_{\boldsymbol{y}(k;\nu)}\right),$	$\sigma_1(x)$
$\mathcal{P} = \mathcal{B}_{\ell_\infty,+}$	$\left.\frac{d\mathcal{J}(\boldsymbol{y}(k))}{d\boldsymbol{y}(k)}\right	_{\boldsymbol{y}(k;\nu)} = \gamma_{\boldsymbol{y}}\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_y}(k)\boldsymbol{y}(k;\nu) - \gamma_e\boldsymbol{B}_{\boldsymbol{e}}^{\zeta_e}(k)\boldsymbol{e}(k;\nu),$
$\boldsymbol{y}(k;\nu+1) = \sigma_+\left(\boldsymbol{y}(k;\nu) + \eta_{\boldsymbol{y}}(\nu)\left.\frac{d\mathcal{J}(\boldsymbol{y}(k))}{d\boldsymbol{y}(k)}\right	_{\boldsymbol{y}(k;\nu)}\right),$	$\sigma_+(x)$
$\mathcal{P} = \mathcal{B}_{\ell_1,+}$	$\left.\frac{d\mathcal{J}(\boldsymbol{y}(k))}{d\boldsymbol{y}(k)}\right	_{\boldsymbol{y}(k;\nu)} = \gamma_{\boldsymbol{y}}\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_y}(k-1)\boldsymbol{y}(k;\nu) - \gamma_e\boldsymbol{B}_{\boldsymbol{e}}^{\zeta_e}(k-1)\boldsymbol{e}(k;\nu),$
$\boldsymbol{y}(k;\nu+1) = \text{ReLU}\left(\boldsymbol{y}(k;\nu) + \eta_{\boldsymbol{y}}(\nu)\left.\frac{d\mathcal{J}(\boldsymbol{y}(k))}{d\boldsymbol{y}(k)}\right|_{\boldsymbol{y}(k;\nu)} - \lambda(\nu)\right),$
$\lambda(k;\nu+1) = \text{ReLU}\left(\lambda(k;\nu) + \eta_{\lambda}(\nu)\left(\left(\sum_{i=1}^n y_i(k;\nu+1)\right) - 1\right)\right).$	ReLU(x)

3.4 Description of the Network Dynamics for a Canonical Polytope Representation

In this section, we consider the optimization problem specified in (6) for a generic polytope with H-representation in (1). We can rewrite the online optimization setting in Lagrangian form as

$$\underset{\boldsymbol{\lambda}\succcurlyeq 0}{\text{minimize}}\,\underset{\boldsymbol{y}(k)\in\mathbb{R}^n}{\text{maximize}}\quad \overbrace{\mathcal{J}(\boldsymbol{y}(k)) - \boldsymbol{\lambda}(k)^T(\boldsymbol{A}_{\mathcal{P}}\boldsymbol{y}(k) - \boldsymbol{b}_{\mathcal{P}})}^{\mathcal{L}(\boldsymbol{y}(k),\boldsymbol{\lambda}(k))}, \qquad (17)$$

which is a Min-Max problem. For the recursive update dynamics of the network output and the Lagrangian variable, we obtain the derivative of the objective in (17) with respect to $\boldsymbol{y}(k)$ and $\boldsymbol{\lambda}(k)$ as

$$\frac{d\mathcal{L}(\boldsymbol{y}(k),\boldsymbol{\lambda}(k))}{d\boldsymbol{y}(k)}\bigg|_{\substack{\boldsymbol{y}(k;\nu)\\\boldsymbol{\lambda}(k;\nu)}} = \gamma_{\boldsymbol{y}}\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(k-1)\boldsymbol{y}(k;\nu) - \gamma_{\boldsymbol{e}}\boldsymbol{B}_{\boldsymbol{e}}^{\zeta_{e}}(k-1)\boldsymbol{e}(k;\nu) - \boldsymbol{A}_{\mathcal{P}}^{T}\boldsymbol{\lambda}(k;\nu), \quad (18)$$

$$\frac{d\mathcal{L}(\boldsymbol{y}(k),\boldsymbol{\lambda}(k))}{d\boldsymbol{\lambda}(k)}\bigg|_{\boldsymbol{y}(k;\nu)} = \boldsymbol{A}_{\mathcal{P}}\boldsymbol{y}(k;\nu) - \boldsymbol{b}_{\mathcal{P}}. \quad (19)$$

Recursive update dynamics for $\boldsymbol{y}(k)$ and $\boldsymbol{\lambda}(k)$: To solve the optimization problem in (17), the projected gradient updates on the $\boldsymbol{y}(k)$ and $\boldsymbol{\lambda}(k)$ lead to the following neural dynamic iterations:

$$\boldsymbol{y}(k;\nu+1) = \boldsymbol{y}(k;\nu) + \eta_{\boldsymbol{y}}(\nu)\frac{d\mathcal{L}(\boldsymbol{y}(k),\boldsymbol{\lambda}(k))}{d\boldsymbol{y}(k)}\bigg|_{\substack{\boldsymbol{y}(k;\nu)\\\boldsymbol{\lambda}(k;\nu)}}, \quad (20)$$

$$\boldsymbol{\lambda}(k,\nu+1) = \text{ReLU}\left(\boldsymbol{\lambda}(k,\nu) + \eta_{\boldsymbol{\lambda}}(\nu)\frac{d\mathcal{L}(\boldsymbol{y}(k),\boldsymbol{\lambda}(k))}{d\boldsymbol{y}(k)}\bigg|_{\boldsymbol{\lambda}(k;\nu)}\right), \quad (21)$$

where $\eta_{\boldsymbol{\lambda}}(\nu)$ denotes the learning rate for $\boldsymbol{\lambda}$ at iteration ν. These iterations correspond to a recurrent neural network for which we can make the following observations: i) output neurons use linear activation functions since $\boldsymbol{y}(k)$ is unconstrained in (17), ii) the network contains f interneurons corresponding to the Lagrangian vector $\boldsymbol{\lambda}$, where f is the number of rows of $\boldsymbol{A}_{\mathcal{P}}$ in (17), or the number of $(n-1)$-faces of the corresponding polytope, iii) the nonnegativity of $\boldsymbol{\lambda}$ implies ReLU activation functions for interneurons. The neural network architecture corresponding to the neural dynamics in (20)-(21) is shown in Figure 1a, which has a layer of f interneurons to impose the polytopic constraint in (6b). The updates of $\boldsymbol{W}(k)$ and $\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(k)$ follow the equations provided in Section 3.2. Although the architecture in Figure 1a allows implementation of arbitrary polytopic source domains; f can be a large number. Alternatively, it is possible to consider the subset of polytopes in (2), which are described by individual properties and the relations of source components. Appendix C.5 derives the network dynamics for this "feature-based" polytope representation, and Figure 1b illustrates its particular realization. The number of interneurons in this case is equivalent to the number of sparsity constraints in (2), which can be much less than the number of faces of the polytope.

4 NUMERICAL EXPERIMENTS

In this section, we illustrate different domain selections for sources and compare the proposed CorInfoMax framework with existing batch algorithms and online biologically plausible neural network approaches. We demonstrate the correlated source separation capability of the proposed framework for both synthetic and natural sources. Additional experiments and details about their implementations are available in Appendix D.

4.1 SYNTHETICALLY CORRELATED SOURCE SEPARATION WITH ANTISPARSE SOURCES

Figure 3: The SINR performances of CorInfoMax, LD-InfoMax, PMF, ICA-InfoMax, NSM, and BSM (averaged over 100 realizations): (a) SINR results for nonnegative antisparse, (b) antisparse.

To illustrate the correlated source separation capability of the online CorInfoMax framework for both nonnegative and signed antisparse sources, i.e. $\boldsymbol{s}(i) \in \mathcal{B}_{\ell_{\infty,+}} \; \forall i$ and $\boldsymbol{s}(i) \in \mathcal{B}_{\ell_{\infty}} \; \forall i$, respectively, we consider a BSS setting with $n = 5$ sources and $m = 10$ mixtures. The 5-dimensional sources are generated using the Copula-T distribution with 4 degrees of freedom. We control the correlation level of the sources by adjusting a Toeplitz distribution parameter matrix with a first row of $[1 \quad \rho \quad \rho \quad \rho \quad \rho]$ for $\rho \in [0, 0.8]$. In each realization, we generate $N = 5 \times 10^5$ samples for each source and mix them through a random matrix $\boldsymbol{A} \in \mathbb{R}^{10 \times 5}$ whose entries are drawn from an i.i.d. standard normal distribution. Furthermore, we use an i.i.d. white Gaussian noise (WGN) corresponding to the signal-to-noise ratio (SNR) level of 30dB to corrupt the mixture signals. We use antisparse CorInfoMax network in Section C.1 and nonnegative CorInfoMax network in Appendix C.2 for these experiments. To compare, we also performed these experiments with biologically plausible algorithms: online BCA (Simsek & Erdogan, 2019), WSM (Bozkurt et al., 2022), ICA-Infomax (Bell & Sejnowski, 1995), NSM (Pehlevan et al., 2017a), BSM (Erdogan & Pehlevan, 2020), and batch altgorithms LD-InfoMax (Erdogan, 2022) and PMF (Tatli & Erdogan, 2021).

Figure 3 shows the signal-to-interference-plus-noise ratio (SINR) versus correlation level ρ curves of different algorithms for nonnegative antisparse and antisparse source separation experiments. We observe that the proposed CorInfoMax approach achieves relatively high SINR results despite increasing ρ in both cases. Although the WSM curve has a similar characteristic, its performance falls behind that of CorInfoMax. Moreover, the LD-InfoMax and PMF algorithms typically achieve the best results, as expected, due to their batch learning settings. Furthermore, the performance of NSM, BSM, and ICA-InfoMax degrades with increasing source correlation because these approaches assume uncorrelated or independent sources.

4.2 Video Separation

To provide a visual example and illustrate a real source scenario, we consider the following video separation setup: 3 videos of 10 seconds are mixed to generate 5 mixture videos. We use a random mixing matrix $\boldsymbol{A} \in \mathbb{R}^{5 \times 3}$ with positive entries (to exclude the negative frame effect), which is provided in the Appendix D.3.3. Since the image pixels are in the set $[0, 1]$, we use the nonnegative antisparse CorInfoMax network to separate the original videos. The demo video (which is available in supplementary files and whose link is provided in the footnote [2]) visually demonstrates the separation process by the proposed approach over time. The first and second rows of the demo are the 3 source videos and 3 of the 5 mixture videos, respectively. The last row contains the source estimates obtained by the CorInfoMax network during its unsupervised learning process. We observe that the output frames become visually better as time progresses and start to represent individual sources. In the end, the CorInfoMax network is trained to a stage of near-perfect separation, with peak signal-to-noise ratio (PSNR) levels of 35.60dB, 48.07dB, and 44.58dB for each source, respectively. Further details for this experiment can be found in the Appendix D.3.3.

5 Conclusion

In this article, we propose an information-theoretic framework for generating biologically plausible neural networks that are capable of separating both independent and correlated sources. The proposed CorInfoMax framework can be applied to infinitely many source domains, enabling a diverse set of source characterizations. In addition to solving unsupervised linear inverse problems, CorInfoMax networks have the potential to generate structured embeddings from observations based on the choice of source domains. In fact, as a future extension, we consider representation frameworks that learn desirable source domain representations by adapting the output-interneuron connections in Figure 1a.

In terms of limitations, we can list the computational complexity for simulating such networks in conventional computers, mainly due to the loop-based recurrent output computation. However, as described in Appendix D.6, the neural networks generated by the proposed framework have computational loads similar to the existing biologically plausible BSS neural networks.

---

[2]https://figshare.com/s/a3fb926f273235068053

6 REPRODUCIBILITY

To ensure the reproducibility of our results, we provide

i. Detailed mathematical description of the algorithms for different source domains and their neural network implementations in Section 3.2, Appendix C.1, Appendix C.2, Appendix C.3, Appendix C.4 and Appendix C.5,

ii. Detailed information on the simulation settings of the experiments in Section 4 in the main article, and Appendix D,

iii. Full list of hyperparameter sets used in these experiments in Table 3, Table 4 in Appendix D.4,

iv. Ablation studies on hyperparameters in Appendix D.5,

v. Algorithm descriptions for special source domains in pseudo-code format in Appendix D.1,

vi. Python scripts and notebooks for individual experiments to replicate the reported results in the supplementary zip file.

7 ETHICS STATEMENT

Related to the algorithmic framework we propose in this article, we see no immediate ethical concerns. In addition, the datasets that we use have no known or reported ethical issues, to the best of our knowledge.

REFERENCES

Maryam Abdolali and Nicolas Gillis. Simplex-structured matrix factorization: Sparsity-based identifiability and provably correct algorithms. *SIAM Journal on Mathematics of Data Science*, 3(2):593–623, 2021. doi: 10.1137/20M1354982. URL https://doi.org/10.1137/20M1354982.

Hiroki Asari, Barak A Pearlmutter, and Anthony M Zador. Sparse representations for the cocktail party problem. *Journal of Neuroscience*, 26(28):7477–7490, 2006.

Eren Babatas and Alper T Erdogan. An algorithmic framework for sparse bounded component analysis. *IEEE Transactions on Signal Processing*, 66(19):5194–5205, August 2018.

Yanis Bahroun, Dmitri Chklovskii, and Anirvan Sengupta. A normative and biologically plausible algorithm for independent component analysis. *Advances in Neural Information Processing Systems*, 34:7368–7384, 2021.

Suzanna Becker and Geoffrey E Hinton. Self-organizing neural network that discovers surfaces in random-dot stereograms. *Nature*, 355(6356):161–163, 1992.

Mark A Bee and Christophe Micheyl. The cocktail party problem: what is it? how can it be solved? and why should animal behaviorists study it? *Journal of comparative psychology*, 122(3):235, 2008.

Anthony J Bell and Terrence J Sejnowski. An information-maximization approach to blind separation and blind deconvolution. *Neural computation*, 7(6):1129–1159, 1995.

Bariscan Bozkurt and Alper T Erdogan. On identifiable polytope characterization for polytopic matrix factorization. *2022 IEEE International Conference on Acoustics, Speech, and Signal Processing (ICASSP)*, May 2022.

Bariscan Bozkurt, Cengiz Pehlevan, and Alper T Erdogan. Biologically-plausible determinant maximization neural networks for blind separation of correlated sources. In *Advances in Neural Information Processing Systems (NeurIPS), to appear*, 2022. preprint on webpage at https://arxiv.org/abs/2209.12894.

Adelbert W Bronkhorst. The cocktail party phenomenon: A review of research on speech intelligibility in multiple-talker conditions. *Acta Acustica united with Acustica*, 86(1):117–128, 2000.

Tsung-Han Chan, Wing-Kin Ma, ArulMurugan Ambikapathi, and Chong-Yung Chi. A simplex volume maximization framework for hyperspectral endmember extraction. *IEEE Transactions on Geoscience and Remote Sensing*, 49(11):4177–4193, May 2011.

Andrzej Cichocki, Rafal Zdunek, Anh Huy Phan, and Shun-ichi Amari. *Nonnegative matrix and tensor factorizations: applications to exploratory multi-way data analysis and blind source separation*. John Wiley & Sons, 2009.

Pierre Comon and Christian Jutten. *Handbook of Blind Source Separation: Independent component analysis and applications*. Academic press, 2010.

Sergio Cruces. Bounded component analysis of linear mixtures: A criterion of minimum convex perimeter. *IEEE Transactions on Signal Processing*, 58(4):2141–2154, 2010.

Alper T Erdogan. A class of bounded component analysis algorithms for the separation of both independent and dependent sources. *IEEE Transactions on Signal Processing*, 61(22):5730–5743, August 2013.

Alper T Erdogan. An information maximization based blind source separation approach for dependent and independent sources. In *ICASSP 2022 - 2022 IEEE International Conference on Acoustics, Speech and Signal Processing (ICASSP)*, pp. 4378–4382, 2022. doi: 10.1109/ICASSP43922.2022.9746099.

Alper T Erdogan and Cengiz Pehlevan. Blind bounded source separation using neural networks with local learning rules. In *ICASSP 2020 - 2020 IEEE International Conference on Acoustics, Speech and Signal Processing (ICASSP)*, pp. 3812–3816, 2020. doi: 10.1109/ICASSP40776.2020.9053114.

Xiao Fu, Kejun Huang, Bo Yang, and N.D. Sidiropoulos. Robust volume minimization-based matrix factorization for remote sensing and document clustering. *IEEE Transactions on Signal Processing*, 64, 08 2016. doi: 10.1109/TSP.2016.2602800.

Xiao Fu, Kejun Huang, and Nicholas D Sidiropoulos. On identifiability of nonnegative matrix factorization. *IEEE Signal Processing Letters*, 25(3):328–332, January 2018.

Xiao Fu, Kejun Huang, Nicholas D Sidiropoulos, and Wing-Kin Ma. Nonnegative matrix factorization for signal and data analytics: Identifiability, algorithms, and applications. *IEEE Signal Process. Mag.*, 36(2):59–80, March 2019.

Elana M Zion Golumbic, Nai Ding, Stephan Bickel, Peter Lakatos, Catherine A Schevon, Guy M McKhann, Robert R Goodman, Ronald Emerson, Ashesh D Mehta, Jonathan Z Simon, et al. Mechanisms underlying selective neuronal tracking of attended speech at a "cocktail party". *Neuron*, 77(5):980–991, 2013.

Branko Grünbaum, Victor Klee, Micha A Perles, and Geoffrey Colin Shephard. *Convex polytopes*, volume 16. Springer, 1967.

Huseyin A Inan and Alper T Erdogan. Convolutive bounded component analysis algorithms for independent and dependent source separation. *IEEE transactions on neural networks and learning systems*, 26(4):697–708, 2014.

Takuya Isomura and Taro Toyoizumi. Error-gated hebbian rule: A local learning rule for principal and independent component analysis. *Scientific reports*, 8(1):1–11, 2018.

Takuya Isomura, Kiyoshi Kotani, and Yasuhiko Jimbo. Cultured cortical neurons can perform blind source separation according to the free-energy principle. *PLoS Comput Biol*, 11(12):e1004643, 2015.

Thomas Kailath, Ali H Sayed, and Babak Hassibi. *Linear estimation*. Prentice-Hall information and system sciences series. Prentice Hall, 2000. ISBN 9780130224644.

Michael S Lewicki. Efficient coding of natural sounds. *Nature neuroscience*, 5(4):356–363, 2002.

Chia-Hsiang Lin, Wing-Kin Ma, Wei-Chiang Li, Chong-Yung Chi, and ArulMurugan Ambikapathi. Identifiability of the simplex volume minimization criterion for blind hyperspectral unmixing: The no-pure-pixel case. *IEEE Transactions on Geoscience and Remote Sensing*, 53(10):5530–5546, May 2015.

Ralph Linsker. Self-organization in a perceptual network. *Computer*, 21(3):105–117, 1988.

Josh H McDermott. The cocktail party problem. *Current Biology*, 19(22):R1024–R1027, 2009.

Nima Mesgarani and Edward F Chang. Selective cortical representation of attended speaker in multi-talker speech perception. *Nature*, 485(7397):233–236, 2012.

Rajiv Narayan, Virginia Best, Erol Ozmeral, Elizabeth McClaine, Micheal Dent, Barbara Shinn-Cunningham, and Kamal Sen. Cortical interference effects in the cocktail party problem. *Nature neuroscience*, 10(12):1601–1607, 2007.

Bruno A Olshausen and David J Field. Emergence of simple-cell receptive field properties by learning a sparse code for natural images. *Nature*, 381(6583):607–609, 1996.

Bruno A Olshausen and David J Field. Sparse coding with an overcomplete basis set: A strategy employed by v1? *Vision research*, 37(23):3311–3325, 1997.

Serdar Ozsoy, Shadi Hamdan, Sercan Ö. Arik, Deniz Yuret, and Alper T Erdogan. Self-supervised learning with an information maximization criterion. *Advances in Neural Information Processing Systems (NeurIPS), to appear*, 2022. preprint on webpage at `https://arxiv.org/abs/2209.07999`.

Neal Parikh, Stephen Boyd, et al. Proximal algorithms. *Foundations and trends® in Optimization*, 1(3):127–239, 2014.

Cengiz Pehlevan, Sreyas Mohan, and Dmitri B Chklovskii. Blind nonnegative source separation using biological neural networks. *Neural computation*, 29(11):2925–2954, 2017a.

Cengiz Pehlevan, Anirvan M Sengupta, and Dmitri B Chklovskii. Why do similarity matching objectives lead to hebbian/anti-hebbian networks? *Neural computation*, 30(1):84–124, 2017b.

Ali H Sayed. *Fundamentals of adaptive filtering*. John Wiley & Sons, 2003.

Jitendra Sharma, Alessandra Angelucci, and Mriganka Sur. Induction of visual orientation modules in auditory cortex. *Nature*, 404(6780):841–847, 2000.

Berfin Simsek and Alper T Erdogan. Online bounded component analysis: A simple recurrent neural network with local update rule for unsupervised separation of dependent and independent sources. In *2019 53rd Asilomar Conference on Signals, Systems, and Computers*, pp. 1639–1643, 2019. doi: 10.1109/IEEECONF44664.2019.9048916.

Evan C Smith and Michael S Lewicki. Efficient auditory coding. *Nature*, 439(7079):978–982, 2006.

Gokcan Tatli and Alper T Erdogan. Polytopic matrix factorization: Determinant maximization based criterion and identifiability. *IEEE Transactions on Signal Processing*, 69:5431–5447, 2021. doi: 10.1109/TSP.2021.3112918.

A APPENDIX

A.1 INFORMATION THEORETIC DEFINITIONS

In this section, we review the logarithm-determinant (LD) entropy measure and mutual information for the BSS setting introduced in Section 2.1 based on Erdogan (2022). Note that in this article, we refer to LD-mutual information synonymously as correlative mutual information. For a finite set of vectors $\mathbb{X} = \{\boldsymbol{x}(1), \boldsymbol{x}(2), \ldots, \boldsymbol{x}(N)\} \subset \mathbb{R}^m$ with a sample covariance matrix $\hat{\boldsymbol{R}}_{\boldsymbol{x}} = \frac{1}{N}\boldsymbol{X}\boldsymbol{X}^T - \frac{1}{N^2}\boldsymbol{X}\boldsymbol{1}\boldsymbol{1}^T\boldsymbol{X}^T$, where $\boldsymbol{X}$ is defined as $\boldsymbol{X} = [\ \boldsymbol{x}(1)\quad \boldsymbol{x}(2)\quad \ldots\quad \boldsymbol{x}(N)\ ]$, the deterministic LD-entropy is defined in Erdogan (2022) as

$$H(\boldsymbol{X})_{\text{LD}}^{(\epsilon)} = \frac{1}{2}\log\det(\hat{\boldsymbol{R}}_{\boldsymbol{x}} + \epsilon\boldsymbol{I}) + \frac{m}{2}\log(2\pi e) \tag{A.1}$$

where $\epsilon > 0$ is a small number to keep the expression away from $-\infty$. If the sample covariance $\hat{\boldsymbol{R}}_{\boldsymbol{x}}$ in this expression is replaced with the true covariance, then $H(\boldsymbol{x})_{\text{LD}}^{(0)}$ coincides with the Shannon differential entropy for a Gaussian vector $\boldsymbol{x}$. Moreover, a deterministic joint LD-entropy of two sets of vectors $\mathbb{X} \subset \mathbb{R}^m$ and $\mathbb{Y} \subset \mathbb{R}^n$ can be defined as

$$\begin{aligned}
H(\boldsymbol{X}, \boldsymbol{Y})_{\text{LD}}^{(\epsilon)} &= \frac{1}{2}\log\det(\hat{\boldsymbol{R}}_{\begin{bmatrix}\boldsymbol{x}\\\boldsymbol{y}\end{bmatrix}} + \epsilon\boldsymbol{I}) + \frac{m+n}{2}\log\det(2\pi e) \\
&= \frac{1}{2}\log\det\left(\begin{bmatrix}\hat{\boldsymbol{R}}_{\boldsymbol{x}} + \epsilon\boldsymbol{I} & \hat{\boldsymbol{R}}_{\boldsymbol{xy}} \\ \hat{\boldsymbol{R}}_{\boldsymbol{yx}} & \hat{\boldsymbol{R}}_{\boldsymbol{y}} + \epsilon\boldsymbol{I}\end{bmatrix}\right) + \frac{m+n}{2}\log\det(2\pi e) \\
&= \frac{1}{2}\log\left(\det(\hat{\boldsymbol{R}}_{\boldsymbol{x}} + \epsilon\boldsymbol{I})\det(\hat{\boldsymbol{R}}_{\boldsymbol{y}} + \epsilon\boldsymbol{I} - \hat{\boldsymbol{R}}_{\boldsymbol{xy}}^T(\hat{\boldsymbol{R}}_{\boldsymbol{x}} + \epsilon\boldsymbol{I})^{-1}\hat{\boldsymbol{R}}_{\boldsymbol{yx}})\right) \\
&\quad + \frac{m+n}{2}\log\det(2\pi e) \\
&= \frac{1}{2}\log\det(\hat{\boldsymbol{R}}_{\boldsymbol{x}} + \epsilon\boldsymbol{I}) + \frac{m}{2}\log(2\pi e) + \frac{1}{2}\log\det(\hat{\boldsymbol{R}}_{\boldsymbol{e}} + \epsilon\boldsymbol{I}) + \frac{n}{2}\log(2\pi e) \\
&= H(\boldsymbol{X})_{\text{LD}}^{(\epsilon)} + H(\boldsymbol{Y}|_L\boldsymbol{X})_{\text{LD}}^{(\epsilon)}
\end{aligned} \tag{A.2}$$

where $\hat{\boldsymbol{R}}_{\boldsymbol{e}} = \hat{\boldsymbol{R}}_{\boldsymbol{y}} - \hat{\boldsymbol{R}}_{\boldsymbol{xy}}^T(\hat{\boldsymbol{R}}_{\boldsymbol{x}} + \epsilon\boldsymbol{I})^{-1}\hat{\boldsymbol{R}}_{\boldsymbol{yx}}$, and $\hat{\boldsymbol{R}}_{\boldsymbol{xy}} = \frac{1}{N}\boldsymbol{X}\boldsymbol{Y}^T = \hat{\boldsymbol{R}}_{\boldsymbol{yx}}^T$. In (A.2), the notation $\boldsymbol{Y}|_L\boldsymbol{X}$ is used to signify $H(\boldsymbol{Y}|_L\boldsymbol{X})_{\text{LD}}^{(\epsilon)} \neq H(\boldsymbol{Y}|\boldsymbol{X})_{\text{LD}}^{(\epsilon)}$ as the latter requires the use of $\hat{\boldsymbol{R}}_{\boldsymbol{y}|\boldsymbol{x}}$ instead of $\hat{\boldsymbol{R}}_{\boldsymbol{e}}$. Moreover, $H(\boldsymbol{Y}|_L\boldsymbol{X})_{\text{LD}}^{(\epsilon)}$ corresponds to the log-determinant of the error sample covariance of the best linear minimum mean squared estimate (MMSE) of $\boldsymbol{y}$ from $\boldsymbol{x}$. To verify that in the zero-mean and noiseless case, consider the MMSE estimate $\hat{\boldsymbol{y}} = \boldsymbol{W}\boldsymbol{x}$ for which the solution is given by $\boldsymbol{W} = \boldsymbol{R}_{\boldsymbol{yx}}\boldsymbol{R}_{\boldsymbol{x}}^{-1} = \boldsymbol{R}_{\boldsymbol{xy}}^T\boldsymbol{R}_{\boldsymbol{x}}^{-1}$ (Kailath et al., 2000). Then $\boldsymbol{R}_{\hat{\boldsymbol{y}}} = \mathbb{E}[\hat{\boldsymbol{y}}\hat{\boldsymbol{y}}^T] = \mathbb{E}[\boldsymbol{R}_{\boldsymbol{xy}}^T\boldsymbol{R}_{\boldsymbol{x}}^{-1}\boldsymbol{x}\boldsymbol{x}^T\boldsymbol{R}_{\boldsymbol{x}}^{-1}\boldsymbol{R}_{\boldsymbol{xy}}] = \boldsymbol{R}_{\boldsymbol{xy}}^T\boldsymbol{R}_{\boldsymbol{x}}^{-1}\boldsymbol{R}_{\boldsymbol{xy}}$. Therefore, if the error is defined as $\boldsymbol{e} = \boldsymbol{y} - \hat{\boldsymbol{y}}$, its covariance matrix can be found as desired, i.e., $\boldsymbol{R}_{\boldsymbol{e}} = \boldsymbol{R}_{\boldsymbol{y}} - \boldsymbol{R}_{\hat{\boldsymbol{y}}} = \boldsymbol{R}_{\boldsymbol{y}} - \boldsymbol{R}_{\boldsymbol{xy}}^T\boldsymbol{R}_{\boldsymbol{x}}^{-1}\boldsymbol{R}_{\boldsymbol{xy}}$.

The LD-mutual information for $\boldsymbol{X}$ and $\boldsymbol{Y}$ can be defined based on the equations (A.1) and (A.2) as

$$\begin{aligned}
I^{(\epsilon)}(\boldsymbol{X}, \boldsymbol{Y}) &= H_{\text{LD}}^{(\epsilon)}(\boldsymbol{Y}) - H_{\text{LD}}^{(\epsilon)}(\boldsymbol{Y}|_L\boldsymbol{X}) = H_{\text{LD}}^{(\epsilon)}(\boldsymbol{X}) - H_{\text{LD}}^{(\epsilon)}(\boldsymbol{X}|_L\boldsymbol{Y}) \\
&= \frac{1}{2}\log\det(\hat{\boldsymbol{R}}_{\boldsymbol{y}} + \epsilon\boldsymbol{I}) - \frac{1}{2}\log\det(\hat{\boldsymbol{R}}_{\boldsymbol{y}} - \hat{\boldsymbol{R}}_{\boldsymbol{xy}}^T(\hat{\boldsymbol{R}}_{\boldsymbol{x}} + \epsilon\boldsymbol{I})^{-1}\hat{\boldsymbol{R}}_{\boldsymbol{yx}} + \epsilon\boldsymbol{I}) + C \\
&= \frac{1}{2}\log\det(\hat{\boldsymbol{R}}_{\boldsymbol{x}} + \epsilon\boldsymbol{I}) - \frac{1}{2}\log\det(\hat{\boldsymbol{R}}_{\boldsymbol{x}} - \hat{\boldsymbol{R}}_{\boldsymbol{yx}}^T(\hat{\boldsymbol{R}}_{\boldsymbol{y}} + \epsilon\boldsymbol{I})^{-1}\hat{\boldsymbol{R}}_{\boldsymbol{xy}} + \epsilon\boldsymbol{I}) + C,
\end{aligned} \tag{A.3}$$

where $C = \frac{m}{2}\log(2\pi e) + \frac{n}{2}\log(2\pi e)$ is a constant.

B GRADIENT DERIVATIONS FOR ONLINE OPTIMIZATION OBJECTIVE

Assuming that the mapping $\boldsymbol{W}(k)$ changes slowly over time, the current output $\boldsymbol{y}(k)$ can be implicitly defined by the projected gradient ascent with neural dynamics. To derive the corresponding neural dynamics for the output $\boldsymbol{y}(k)$, we need to calculate the gradient of the objective 5a with respect

to $\boldsymbol{y}(k)$. First, we consider the derivative of both $\log \det(\hat{\boldsymbol{R}}_{\boldsymbol{y}}^{\zeta_y}(k) + \epsilon \boldsymbol{I})$ and $\log \det(\hat{\boldsymbol{R}}_{\boldsymbol{e}}^{\zeta_e}(k) + \epsilon \boldsymbol{I})$ with respect to $\boldsymbol{y}(k)$.

$$\frac{\partial \log \det(\hat{\boldsymbol{R}}_{\boldsymbol{y}}^{\zeta_y}(k) + \epsilon \boldsymbol{I})}{\partial y_i(k)} = Tr\left(\frac{\partial \log \det(\hat{\boldsymbol{R}}_{\boldsymbol{y}}^{\zeta_y}(k) + \epsilon \boldsymbol{I})}{\partial(\hat{\boldsymbol{R}}_{\boldsymbol{y}}^{\zeta_y}(k) + \epsilon \boldsymbol{I})} \frac{\partial \hat{\boldsymbol{R}}_{\boldsymbol{y}}^{\zeta_y}(k)}{\partial y_i(k)}\right),$$

where $y_i(k)$ is the i-th element of the vector $\boldsymbol{y}(k)$, and

$$\frac{\partial \log \det(\hat{\boldsymbol{R}}_{\boldsymbol{y}}^{\zeta_y}(k) + \epsilon \boldsymbol{I})}{\partial(\hat{\boldsymbol{R}}_{\boldsymbol{y}}^{\zeta_y}(k) + \epsilon \boldsymbol{I})} = (\hat{\boldsymbol{R}}_{\boldsymbol{y}}^{\zeta_y}(k) + \epsilon \boldsymbol{I})^{-1}, \tag{A.4}$$

$$\frac{\partial \hat{\boldsymbol{R}}_{\boldsymbol{y}}^{\zeta_y}(k)}{\partial y_i(k)} = \frac{1 - \zeta_y}{1 - \zeta_y^k}(\boldsymbol{y}(k)\boldsymbol{e}^{(i)T} + \boldsymbol{e}^{(i)}\boldsymbol{y}(k)^T). \tag{A.5}$$

In (A.5), $\boldsymbol{e}^{(i)}$ denotes the standard basis vector with a 1 at position i and should not be confused with the error vector $\boldsymbol{e}(k)$. Combining (A.4) and (A.5), we obtain the following result:

$$\frac{\partial \log \det(\hat{\boldsymbol{R}}_{\boldsymbol{y}}^{\zeta_y}(k) + \epsilon \boldsymbol{I})}{\partial y_i(k)} = 2\frac{1 - \zeta_y}{1 - \zeta_y^k}\boldsymbol{e}^{(i)T}(\hat{\boldsymbol{R}}_{\boldsymbol{y}}^{\zeta_y}(k) + \epsilon \boldsymbol{I})^{-1}\boldsymbol{y}(k),$$

which leads to

$$\frac{\partial \log \det(\hat{\boldsymbol{R}}_{\boldsymbol{y}}^{\zeta_y}(k) + \epsilon \boldsymbol{I})}{\partial \boldsymbol{y}(k)} = 2\frac{1 - \zeta_y}{1 - \zeta_y^k}(\hat{\boldsymbol{R}}_{\boldsymbol{y}}^{\zeta_y}(k) + \epsilon \boldsymbol{I})^{-1}\boldsymbol{y}(k). \tag{A.6}$$

If we apply the same procedure to obtain the derivative of $\log \det(\hat{\boldsymbol{R}}_{\boldsymbol{e}}^{\zeta_e}(k) + \epsilon \boldsymbol{I})$ with respect to $\boldsymbol{e}(k)$, we obtain

$$\frac{\partial \log \det(\hat{\boldsymbol{R}}_{\boldsymbol{e}}^{\zeta_e}(k) + \epsilon \boldsymbol{I})}{\partial \boldsymbol{e}(k)} = 2\frac{1 - \zeta_e}{1 - \zeta_e^k}(\hat{\boldsymbol{R}}_{\boldsymbol{e}}^{\zeta_e}(k) + \epsilon \boldsymbol{I})^{-1}\boldsymbol{e}(k).$$

Using the composition rule, we can obtain the derivative of $\log \det(\hat{\boldsymbol{R}}_{\boldsymbol{e}}^{\zeta_e}(k) + \epsilon \boldsymbol{I})$ with respect to $\boldsymbol{y}(k)$ as follows:

$$\frac{\partial \log \det(\hat{\boldsymbol{R}}_{\boldsymbol{e}}^{\zeta_e}(k) + \epsilon \boldsymbol{I})}{\partial \boldsymbol{y}(k)} = \underbrace{\frac{\partial \boldsymbol{e}(k)}{\partial \boldsymbol{y}(k)}}_{\boldsymbol{I}_n}\frac{\partial \log \det(\hat{\boldsymbol{R}}_{\boldsymbol{e}}^{\zeta_e}(k) + \epsilon \boldsymbol{I})}{\partial \boldsymbol{e}(k)}$$

$$= 2\frac{1 - \zeta_e}{1 - \zeta_e^k}(\hat{\boldsymbol{R}}_{\boldsymbol{e}}^{\zeta_e}(k) + \epsilon \boldsymbol{I})^{-1}\boldsymbol{e}(k). \tag{A.7}$$

Finally, combining the results from (A.6) and (A.7), we obtain the derivative of the objective function $\mathcal{J}(\boldsymbol{y}(k))$ with respect to $\boldsymbol{y}(k)$

$$\nabla_{\boldsymbol{y}(k)}\mathcal{J}(\boldsymbol{y}(k)) = \frac{1}{2}\nabla_{\boldsymbol{y}(k)}\log \det(\hat{\boldsymbol{R}}_{\boldsymbol{y}}^{\zeta_y}(k) + \epsilon \boldsymbol{I}) - \frac{1}{2}\nabla_{\boldsymbol{y}(k)}\log \det(\hat{\boldsymbol{R}}_{\boldsymbol{e}}^{\zeta_e}(k) + \epsilon \boldsymbol{I})$$

$$= \frac{1 - \zeta_y}{1 - \zeta_y^k}(\hat{\boldsymbol{R}}_{\boldsymbol{y}}^{\zeta_y}(k) + \epsilon \boldsymbol{I})^{-1}\boldsymbol{y}(k) - \frac{1 - \zeta_e}{1 - \zeta_e^k}(\hat{\boldsymbol{R}}_{\boldsymbol{e}}^{\zeta_e}(k) + \epsilon \boldsymbol{I})^{-1}\boldsymbol{e}(k) \tag{A.8}$$

For further simplification of (A.8), we define the recursions for $\hat{\boldsymbol{R}}_{\boldsymbol{y}}^{\zeta_y}(k)^{-1}$ and $\hat{\boldsymbol{R}}_{\boldsymbol{e}}^{\zeta_e}(k)^{-1}$ based on the recursive definitions of the corresponding correlation matrices. Based on the definition in (4), we can write

$$\hat{\boldsymbol{R}}_{\boldsymbol{y}}^{\zeta_y}(k) + \epsilon \boldsymbol{I} = \frac{1 - \zeta_y^{k-1}}{1 - \zeta_y^k}\zeta_y(\hat{\boldsymbol{R}}_{\boldsymbol{y}}^{\zeta_y}(k-1) + \epsilon \boldsymbol{I}) + \frac{1 - \zeta_y}{1 - \zeta_y^k}\boldsymbol{y}(k)\boldsymbol{y}(k)^T + \frac{1 - \zeta_y}{1 - \zeta_y^k}\epsilon \boldsymbol{I}$$

$$\approx \frac{1 - \zeta_y^{k-1}}{1 - \zeta_y^k}\zeta_y(\hat{\boldsymbol{R}}_{\boldsymbol{y}}^{\zeta_y}(k-1) + \epsilon \boldsymbol{I}) + \frac{1 - \zeta_y}{1 - \zeta_y^k}\boldsymbol{y}(k)\boldsymbol{y}(k)^T \tag{A.9}$$

Using the assumption in (A.9), we take the inverse of both sides and apply the matrix inversion lemma to obtain

$$
(\hat{\boldsymbol{R}}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(k) + \epsilon\boldsymbol{I})^{-1} = \frac{1 - \zeta_{\boldsymbol{y}}^k}{\zeta_{\boldsymbol{y}} - \zeta_{\boldsymbol{y}}^k}\Big((\hat{\boldsymbol{R}}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(k-1) + \epsilon\boldsymbol{I})^{-1}
$$
$$
- \gamma_{\boldsymbol{y}}(k)(\hat{\boldsymbol{R}}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(k-1) + \epsilon\boldsymbol{I})^{-1}\boldsymbol{y}(k)\boldsymbol{y}(k)^T(\hat{\boldsymbol{R}}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(k-1) + \epsilon\boldsymbol{I})^{-1}\Big), \quad \text{(A.10)}
$$

where

$$
\gamma_{\boldsymbol{y}}(k) = \left(\frac{\zeta_{\boldsymbol{y}} - \zeta_{\boldsymbol{y}}^k}{1 - \zeta_{\boldsymbol{y}}} + \boldsymbol{y}(k)^T(\hat{\boldsymbol{R}}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(k-1) + \epsilon\boldsymbol{I})^{-1}\boldsymbol{y}(k)\right)^{-1}. \quad \text{(A.11)}
$$

We apply the same procedure to obtain the inverse of $(\hat{\boldsymbol{R}}_{\boldsymbol{e}}^{\zeta_{\boldsymbol{e}}}(k) + \epsilon\boldsymbol{I})^{-1}$:

$$
(\hat{\boldsymbol{R}}_{\boldsymbol{e}}^{\zeta_{\boldsymbol{e}}}(k) + \epsilon\boldsymbol{I})^{-1} = \frac{1 - \zeta_{\boldsymbol{e}}^k}{\zeta_{\boldsymbol{e}} - \zeta_{\boldsymbol{e}}^k}\Big((\hat{\boldsymbol{R}}_{\boldsymbol{e}}^{\zeta_{\boldsymbol{e}}}(k-1) + \epsilon\boldsymbol{I})^{-1}
$$
$$
- \gamma_{\boldsymbol{e}}(k)(\hat{\boldsymbol{R}}_{\boldsymbol{e}}^{\zeta_{\boldsymbol{e}}}(k-1) + \epsilon\boldsymbol{I})^{-1}\boldsymbol{e}(k)\boldsymbol{e}(k)^T(\hat{\boldsymbol{R}}_{\boldsymbol{e}}^{\zeta_{\boldsymbol{e}}}(k-1) + \epsilon\boldsymbol{I})^{-1}\Big), \quad \text{(A.12)}
$$

where

$$
\gamma_{\boldsymbol{e}}(k) = \left(\frac{\zeta_{\boldsymbol{e}} - \zeta_{\boldsymbol{e}}^k}{1 - \zeta_{\boldsymbol{e}}} + \boldsymbol{e}(k)^T(\hat{\boldsymbol{R}}_{\boldsymbol{e}}^{\zeta_{\boldsymbol{e}}}(k-1) + \epsilon\boldsymbol{I})^{-1}\boldsymbol{e}(k)\right)^{-1}. \quad \text{(A.13)}
$$

Note that plugging (A.10) into the first part of (A.8) yields the following simplification:

$$
\frac{1 - \zeta_{\boldsymbol{y}}}{1 - \zeta_{\boldsymbol{y}}^k}(\hat{\boldsymbol{R}}(k) + \epsilon\boldsymbol{I})^{-1}\boldsymbol{y}(k) = \frac{1 - \zeta_{\boldsymbol{y}}}{1 - \zeta_{\boldsymbol{y}}^k}\frac{1 - \zeta_{\boldsymbol{y}}^k}{\zeta_{\boldsymbol{y}} - \zeta_{\boldsymbol{y}}^k}\Big((\hat{\boldsymbol{R}}(k-1) + \epsilon\boldsymbol{I})^{-1}
$$
$$
- \gamma_{\boldsymbol{y}}(k)(\hat{\boldsymbol{R}}(k-1) + \epsilon\boldsymbol{I})^{-1}\boldsymbol{y}(k)\boldsymbol{y}(k)^T(\hat{\boldsymbol{R}}(k-1) + \epsilon\boldsymbol{I})^{-1}\Big)\boldsymbol{y}(k)
$$
$$
= \frac{1 - \zeta_{\boldsymbol{y}}}{\zeta_{\boldsymbol{y}} - \zeta_{\boldsymbol{y}}^k}\Bigg((\hat{\boldsymbol{R}}(k-1) + \epsilon\boldsymbol{I})^{-1}
$$
$$
- \frac{(\hat{\boldsymbol{R}}(k-1) + \epsilon\boldsymbol{I})^{-1}\boldsymbol{y}(k)\boldsymbol{y}(k)^T(\hat{\boldsymbol{R}}(k-1) + \epsilon\boldsymbol{I})^{-1}}{\frac{\zeta_{\boldsymbol{y}} - \zeta_{\boldsymbol{y}}^k}{1 - \zeta_{\boldsymbol{y}}} + \boldsymbol{y}(k)^T(\hat{\boldsymbol{R}}(k-1) + \epsilon\boldsymbol{I})^{-1}\boldsymbol{y}(k)}\Bigg)\boldsymbol{y}(k)
$$
$$
= \frac{1 - \zeta_{\boldsymbol{y}}}{\zeta_{\boldsymbol{y}} - \zeta_{\boldsymbol{y}}^k}\left(\frac{\frac{\zeta_{\boldsymbol{y}} - \zeta_{\boldsymbol{y}}^k}{1 - \zeta_{\boldsymbol{y}}}(\hat{\boldsymbol{R}}(k-1) + \epsilon\boldsymbol{I})^{-1}\boldsymbol{y}(k)}{\frac{\zeta_{\boldsymbol{y}} - \zeta_{\boldsymbol{y}}^k}{1 - \zeta_{\boldsymbol{y}}} + \boldsymbol{y}(k)^T(\hat{\boldsymbol{R}}(k-1) + \epsilon\boldsymbol{I})^{-1}\boldsymbol{y}(k)}\right)
$$
$$
+ \frac{1 - \zeta_{\boldsymbol{y}}}{\zeta_{\boldsymbol{y}} - \zeta_{\boldsymbol{y}}^k}\left(\frac{(\hat{\boldsymbol{R}}(k-1) + \epsilon\boldsymbol{I})^{-1}\boldsymbol{y}(k)\boldsymbol{y}(k)^T(\hat{\boldsymbol{R}}(k-1) + \epsilon\boldsymbol{I})^{-1}\boldsymbol{y}(k)}{\frac{\zeta_{\boldsymbol{y}} - \zeta_{\boldsymbol{y}}^k}{1 - \zeta_{\boldsymbol{y}}} + \boldsymbol{y}(k)^T(\hat{\boldsymbol{R}}(k-1) + \epsilon\boldsymbol{I})^{-1}\boldsymbol{y}(k)}\right)
$$
$$
- \frac{1 - \zeta_{\boldsymbol{y}}}{\zeta_{\boldsymbol{y}} - \zeta_{\boldsymbol{y}}^k}\left(\frac{(\hat{\boldsymbol{R}}(k-1) + \epsilon\boldsymbol{I})^{-1}\boldsymbol{y}(k)\boldsymbol{y}(k)^T(\hat{\boldsymbol{R}}(k-1) + \epsilon\boldsymbol{I})^{-1}\boldsymbol{y}(k)}{\frac{\zeta_{\boldsymbol{y}} - \zeta_{\boldsymbol{y}}^k}{1 - \zeta_{\boldsymbol{y}}} + \boldsymbol{y}(k)^T(\hat{\boldsymbol{R}}(k-1) + \epsilon\boldsymbol{I})^{-1}\boldsymbol{y}(k)}\right)
$$
$$
= \gamma_{\boldsymbol{y}}(k)(\hat{\boldsymbol{R}}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(k-1) + \epsilon\boldsymbol{I})^{-1}\boldsymbol{y}(k).
$$

A similar simplification can be obtained for (A.12), and incorporating these simplifications into (A.8) yields

$$
\nabla_{\boldsymbol{y}(k)}\mathcal{J}(\boldsymbol{y}(k)) = \gamma_{\boldsymbol{y}}(k)\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(k)\boldsymbol{y}(k) - \gamma_{\boldsymbol{e}}(k)\boldsymbol{B}_{\boldsymbol{e}}^{\zeta_{\boldsymbol{e}}}(k)\boldsymbol{e}(k), \quad \text{(A.14)}
$$

where we denote $(\hat{\boldsymbol{R}}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(k) + \epsilon\boldsymbol{I})^{-1}$ and $(\hat{\boldsymbol{R}}_{\boldsymbol{e}}^{\zeta_{\boldsymbol{e}}}(k) + \epsilon\boldsymbol{I})^{-1}$ by $\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(k+1)$ and $\boldsymbol{B}_{\boldsymbol{e}}^{\zeta_{\boldsymbol{e}}}(k+1)$ for simplicity, respectively.

C SUPPLEMENTARY ON THE NETWORK STRUCTURES FOR THE EXAMPLE DOMAINS

C.1 DESCRIPTION OF THE NETWORK DYNAMICS FOR ANTISPARSE SOURCES

We consider the source domain $\mathcal{P} = \mathcal{B}_{\ell_\infty}$ which corresponds to antisparse sources. Similar to the sparse CorInfoMax example in Section 3.2, we derive the network corresponding to the antisparse CorInfoMax network through the projected gradient ascent method. Since projection onto the $\mathcal{P} = \mathcal{B}_{\ell_\infty}$ is an elementwise clipping operation, unlike the sparse CorInfoMax case, we do not require any interneurons related to the projection operation.

Recursive update dynamics for $\boldsymbol{y}(k)$: Based on the gradient of (5a) with respect to $\boldsymbol{y}(k)$ in (A.14), derived in Appendix B, we can write the corresponding projected gradient ascent iterations for (5) as

$$\boldsymbol{e}(k;\nu) = \boldsymbol{y}(k;\nu) - \boldsymbol{W}(k)\boldsymbol{x}(k),$$

$$\frac{d\mathcal{J}(\boldsymbol{y}(k))}{d\boldsymbol{y}(k)}\bigg|_{\boldsymbol{y}(k;\nu)} = \gamma_{\boldsymbol{y}}\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_y}(k)\boldsymbol{y}(k;\nu) - \gamma_{\boldsymbol{e}}\boldsymbol{B}_{\boldsymbol{e}}^{\zeta_e}(k)\boldsymbol{e}(k;\nu),$$

$$\boldsymbol{y}(k;\nu+1) = \sigma_1\left(\boldsymbol{y}(k;\nu) + \eta_{\boldsymbol{y}}(\nu)\frac{d\mathcal{J}(\boldsymbol{y}(k))}{d\boldsymbol{y}(k)}\bigg|_{\boldsymbol{y}(k;\nu)}\right),$$

where $\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_y}(k)$ and $\boldsymbol{B}_{\boldsymbol{e}}^{\zeta_e}(k)$ are inverses of $\boldsymbol{R}_{\boldsymbol{y}}^{\zeta_y}(k-1)$ and $\boldsymbol{R}_{\boldsymbol{e}}^{\zeta_e}(k-1)$ respectively, $\nu \in \mathbb{N}$ is the index of neural dynamic iterations, $\sigma_1(.)$ is the projection onto the selected domain $\mathcal{B}_{\ell_\infty}$, which is the elementwise clipping function defined as $\sigma_1(\boldsymbol{y})_i = \begin{cases} y_i & -1 \le y_i \le 1, \\ \text{sign}(y_i) & \text{otherwise.} \end{cases}$.

The corresponding realization of the neural network is shown in Figure 4.

Figure 4: Two-Layer antisparse CorInfoMax Network.

C.2 DESCRIPTION OF THE NETWORK DYNAMICS FOR NONNEGATIVE ANTISPARSE SOURCES

We consider the source domain $\mathcal{P} = \mathcal{B}_{\ell_\infty,+}$. The treatment for this case is almost the same as the signed antisparse case in Appendix C.1. The only difference is that the projection to the source domain is performed by applying elementwise nonnegative clipping function to individual outputs. Therefore, we can write the neural network dynamics for the nonnegative antisparse case as

$$\boldsymbol{e}(k;\nu) = \boldsymbol{y}(k;\nu) - \boldsymbol{W}(k)\boldsymbol{x}(k),$$

$$\frac{d\mathcal{J}(\boldsymbol{y}(k))}{d\boldsymbol{y}(k)}\bigg|_{\boldsymbol{y}(k;\nu)} = \gamma_{\boldsymbol{y}}\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_y}(k)\boldsymbol{y}(k;\nu) - \gamma_{\boldsymbol{e}}\boldsymbol{B}_{\boldsymbol{e}}^{\zeta_e}(k)\boldsymbol{e}(k;\nu),$$

$$\boldsymbol{y}(k;\nu+1) = \sigma_+\left(\boldsymbol{y}(k;\nu) + \eta_{\boldsymbol{y}}(\nu)\frac{d\mathcal{J}(\boldsymbol{y}(k))}{d\boldsymbol{y}(k)}\bigg|_{\boldsymbol{y}(k;\nu)}\right),$$

where the nonnegative clipping function is defined as

$$
\sigma_+(\boldsymbol{y})_i = \left\{ \begin{array}{ll} 0 & y_i \leq 0, \\ y_i & 0 \leq y_i \leq 1, \\ 1 & y_i \geq 1. \end{array} \right.
$$

The corresponding neural network realization is shown in Figure 5.

Figure 5: Two-Layer nonnegative antisparse CorInfoMax Network.

C.3 DESCRIPTION OF THE NETWORK DYNAMICS FOR NONNEGATIVE SPARSE SOURCES

For the nonnegative sparse CorInfoMax network in Section 3.2, the only change compared to its sparse counterpart is the replacement of the soft-thresholding activation functions at the output layer with the rectified linear unit. Accordingly, we can state the dynamics of output and inhibitory neurons as

$$
\frac{d\mathcal{J}(\boldsymbol{y}(k))}{d\boldsymbol{y}(k)}\bigg|_{\boldsymbol{y}(k;\nu)} = \gamma_{\boldsymbol{y}} \boldsymbol{B}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(k-1)\boldsymbol{y}(k;\nu) - \gamma_{\boldsymbol{e}} \boldsymbol{B}_{\boldsymbol{e}}^{\zeta_{e}}(k-1)\boldsymbol{e}(k;\nu),
$$

$$
\boldsymbol{y}(k;\nu+1) = \text{ReLU}\left(\boldsymbol{y}(k;\nu) + \eta_{\boldsymbol{y}}(\nu)\frac{d\mathcal{J}(\boldsymbol{y}(k))}{d\boldsymbol{y}(k)}\bigg|_{\boldsymbol{y}(k;\nu)} - \lambda(k;\nu)\right),
$$

$$
\frac{d\mathcal{L}(\boldsymbol{y}(k),\lambda(k))}{d\lambda(k)}\bigg|_{\boldsymbol{y}(k;\nu)} = \left(\sum_{i=1}^{n} y_i(k;\nu+1)\right) - 1,
$$

$$
\lambda(k;\nu+1) = \text{ReLU}\left(\lambda(k;\nu) + \eta_{\lambda}(\nu)\frac{d\mathcal{L}(\boldsymbol{y}(k),\lambda(k))}{d\lambda(k)}\bigg|_{\boldsymbol{y}(k;\nu)}\right).
$$

The corresponding network structure is illustrated in Figure 6.

Figure 6: Three-Layer nonnegative sparse CorInfoMax Network.

C.4 Description of the Network Dynamics for Unit Simplex Sources

For the BSS setting for the unit simplex set Δ, which is used for nonnegative matrix factorization, we consider the following optimization problem,

$$\underset{\boldsymbol{y}(k) \in \mathbb{R}^n}{\text{maximize}} \quad \mathcal{J}(\boldsymbol{y}(k)) \tag{A.15a}$$

$$\text{subject to} \quad ||\boldsymbol{y}(k)||_1 = 1, \quad \boldsymbol{y}(k) \succcurlyeq 0 \tag{A.15b}$$

for which the Lagrangian-based Min-Max problem can be stated as

$$\underset{\lambda}{\text{minimize}} \underset{\boldsymbol{y}(k) \in \mathbb{R}^n}{\text{maximize}} \quad \overbrace{\mathcal{J}(\boldsymbol{y}(k)) - \lambda(k)(||\boldsymbol{y}(k)||_1 - 1)}^{\mathcal{L}(\boldsymbol{y}(k),\lambda(k))}.$$

In this context, contrary to the optimization problem defined in (8), we do not require that the Lagrangian variable λ be nonnegative, due to the equality constraint in (A.15b). Hence, we write the network dynamics for a simplex source as

$$\frac{d\mathcal{J}(\boldsymbol{y}(k))}{d\boldsymbol{y}(k)}\bigg|_{\boldsymbol{y}(k;\nu)} = \gamma_{\boldsymbol{y}} \boldsymbol{B}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(k-1)\boldsymbol{y}(k;\nu) - \gamma_{\boldsymbol{e}} \boldsymbol{B}_{\boldsymbol{e}}^{\zeta_{\boldsymbol{e}}}(k-1)\boldsymbol{e}(k;\nu),$$

$$\boldsymbol{y}(k;\nu+1) = \text{ReLU}\left(\boldsymbol{y}(k;\nu) + \eta_{\boldsymbol{y}}(\nu)\frac{d\mathcal{J}(\boldsymbol{y}(k))}{d\boldsymbol{y}(k)}\bigg|_{\boldsymbol{y}(k;\nu)} - \lambda(k;\nu)\right),$$

$$\frac{d\mathcal{L}(\boldsymbol{y}(k),\lambda(k))}{d\lambda(k)}\bigg|_{\lambda(k;\nu)} = \left(\sum_{i=1}^n y_i(k;\nu+1)\right) - 1,$$

$$\lambda(k;\nu+1) = \lambda(k;\nu) + \eta_{\lambda}(\nu)\frac{d\mathcal{L}(\boldsymbol{y}(k),\lambda(k))}{d\lambda(k)}\bigg|_{\lambda(k;\nu)}.$$

Figure 7 demonstrates the network structure for simplex sources, which is identical to nonnegative sparse CorInfoMax network except that the linear activation replaces the ReLU activation of the inhibitory neuron.

Figure 7: Three-Layer CorInfoMax Network for unit simplex sources.

C.5 Description of the Network Dynamics for Feature Based Specified Polytopes

In this section, we consider the source separation setting where source samples are from a polytope represented in the form of (2). We expand the derivation in Bozkurt et al. (2022) (see Appendix D.6 in the reference) to obtain a neural network solution to the BSS problem for any identifiable polytope

that can be expressed in the form of (2). Accordingly, we consider the following optimization problem

$$
\begin{align}
\underset{\boldsymbol{y}(k) \in \mathbb{R}^n}{\text{maximize}} \quad & \mathcal{J}(\boldsymbol{y}(k)) \tag{A.16a}\\
\text{subject to} \quad & -\mathbf{1} \preccurlyeq \boldsymbol{y}(k)_{\mathcal{I}_s} \preccurlyeq \mathbf{1}, \tag{A.16b}\\
& \mathbf{0} \preccurlyeq \boldsymbol{y}(k)_{\mathcal{I}_+} \preccurlyeq \mathbf{1}, \tag{A.16c}\\
& \|\boldsymbol{y}(k)_{\mathcal{J}_l}\|_1 \leq 1 \quad \forall l = 1, \ldots, L \tag{A.16d}
\end{align}
$$

We write the online optimization setting in a Lagrangian Min-Max setting as follows:

$$
\underset{\lambda_l(k) \geq 0}{\text{minimize}} \quad \underset{\substack{\boldsymbol{y}(k) \in \mathbb{R}^n \\ -\mathbf{1} \preccurlyeq \boldsymbol{y}(k)_{\mathcal{I}_s} \preccurlyeq \mathbf{1} \\ \mathbf{0} \preccurlyeq \boldsymbol{y}(k)_{\mathcal{I}_+} \preccurlyeq \mathbf{1}}}{\text{maximize}} \quad \overbrace{\mathcal{J}(\boldsymbol{y}(k)) - \sum_{l=1}^{L} \lambda_l(k)(\|\boldsymbol{y}(k)_{\mathcal{J}_l}\|_1 - 1)}^{\mathcal{L}(\boldsymbol{y}(k), \lambda_1(k), \ldots, \lambda_L(k))}.
$$

The proximal operator corresponding to the Lagrangian term can be written as

$$
\text{prox}_\lambda(\boldsymbol{y}) = \underset{\boldsymbol{q} \text{ s.t. } \boldsymbol{q}_{\mathcal{I}_+} \succcurlyeq \mathbf{0}}{\text{argmin}} \left(\frac{1}{2}\|\boldsymbol{y} - \boldsymbol{q}\|_2^2 + \sum_{l=1}^{L} \lambda_l \|\boldsymbol{q}_{\mathcal{J}_l}\|_1 \right). \tag{A.17}
$$

Let $\boldsymbol{q}^*$ be the output of the proximal operator defined in (A.17). From the first order optimality condition,

- If $j \notin \mathcal{I}_+$, then $q_j^* - y_j + \sum_{\substack{l \in \mathcal{J}_l \\ \text{s.t. } j \in \mathcal{J}_l}} \lambda_l sign(y_j) = 0$. Therefore, $q_j^* = y_j - \sum_{\substack{l \in \mathcal{J}_l \\ \text{s.t. } j \in \mathcal{J}_l}} \lambda_l sign(y_j)$.

- If $j \in \mathcal{I}_+$, then $q_j^* = y_j - \sum_{\substack{l \in \mathcal{J}_l \\ \text{s.t. } j \in \mathcal{J}_l}} \lambda_l$.

As a result, defining $\mathcal{I}_a = (\cap_l \mathcal{J}_l)^{\complement}$ as the set of dimension indices which do not appear in the sparsity constraints, we can write the corresponding output dynamics as

$$
\begin{align}
\frac{d\mathcal{J}(\boldsymbol{y}(k))}{d\boldsymbol{y}(k)} \bigg|_{\boldsymbol{y}(k;\nu)} &= \gamma_{\boldsymbol{y}} \boldsymbol{B}_{\boldsymbol{y}}^{\zeta_y}(k-1)\boldsymbol{y}(k;\nu) - \gamma_{\boldsymbol{e}} \boldsymbol{B}_{\boldsymbol{e}}^{\zeta_e}(k-1)\boldsymbol{e}(k;\nu), \notag\\
\bar{\boldsymbol{y}}(k;\nu+1) &= \boldsymbol{y}(k;\nu) + \eta_{\boldsymbol{y}}(\nu)\frac{d\mathcal{J}(\boldsymbol{y}(k;\nu))}{d\boldsymbol{y}(k)}\bigg|_{\boldsymbol{y}(k;\nu)} \tag{A.18}\\
y_j(k;\nu+1) &= ST_{\alpha_j(k,\nu)}(\bar{y}_j(k;\nu+1)) \text{ where } \alpha_j(k;\nu) = \sum_{\substack{l \in \mathcal{J}_l \\ \text{s.t. } j \in \mathcal{J}_l}} \lambda_l(k;\nu) \quad \forall j \in \mathcal{I}_s \cap \mathcal{I}_a^{\complement} \notag\\
y_j(k;\nu+1) &= \text{ReLU}\left(\bar{y}_j(k;\nu+1) - \sum_{\substack{l \in \mathcal{J}_l \\ \text{s.t. } j \in \mathcal{J}_l}} \lambda_l(k;\nu)\right) \quad \forall j \in \mathcal{I}_+ \cap \mathcal{I}_a^{\complement} \notag\\
y_j(k;\nu+1) &= \sigma_1(\bar{y}_j(k;\nu)) \quad \forall j \in \mathcal{I}_s \cap \mathcal{I}_a, \notag\\
y_j(k;\nu+1) &= \sigma_+(\bar{y}_j(k;\nu)) \quad \forall j \in \mathcal{I}_+ \cap \mathcal{I}_a \notag
\end{align}
$$

For inhibitory neurons corresponding to Lagrangian variables $\lambda_1, \ldots, \lambda_L$, we obtain the update dynamics based on the derivative of $\mathcal{L}(\boldsymbol{y}(k;\nu), \lambda_1(k;\nu), \ldots, \lambda_L(k;\nu))$ as

$$
\left.\frac{d\mathcal{L}(\boldsymbol{y}(k), \lambda_1(k), \ldots, \lambda_L(k))}{d\lambda_l(k)}\right|_{\lambda_l(k;\nu)} = \|[\boldsymbol{y}(k;\nu+1)]_{\mathcal{J}_l}\|_1 - 1 \quad \forall l,
$$

$$
\bar{\lambda}_l(k;\nu+1) = \lambda_l(k;\nu)
$$
$$
+ \eta_{\lambda_l}(\nu)\left.\frac{d\mathcal{L}(\boldsymbol{y}(k), \lambda_1(k), \ldots, \lambda_L(k))}{d\lambda_l(k)}\right|_{\lambda_l(k;\nu)},
$$

$$
\lambda_l(k,\nu+1) = \text{ReLU}\Big(\bar{\lambda}_l(k;\nu+1)\Big).
$$

In Appendix D.2.4, we demonstrate an example setting in which the underlying domain is defined as

$$
\mathcal{P}_{ex} = \left\{ \boldsymbol{s} \in \mathbb{R}^5 \,\middle|\, \begin{array}{l} s_1, s_2, s_4 \in [-1,1], s_3, s_5 \in [0,1], \\ \left\| \begin{bmatrix} s_1 \\ s_2 \\ s_5 \end{bmatrix} \right\|_1 \leq 1, \left\| \begin{bmatrix} s_2 \\ s_3 \\ s_4 \end{bmatrix} \right\|_1 \leq 1 \end{array} \right\}.
$$

We summarize the neural dynamics for this specific example:

$$
y_1(k;\nu+1) = ST_{\lambda_1(k,\nu)}\left(\bar{y}_1(k;\nu+1)\right),
$$
$$
y_2(k;\nu+1) = ST_{\lambda_1(k,\nu)+\lambda_2(k,\nu)}\left(\bar{y}_2(k;\nu+1)\right),
$$
$$
y_3(k;\nu+1) = \text{ReLU}\left(\bar{y}_3(k;\nu+1) - \lambda_2(k;\nu)\right),
$$
$$
y_4(k;\nu+1) = ST_{\lambda_2(k,\nu)}\left(\bar{y}_4(k;\nu+1)\right),
$$
$$
y_5(k;\nu+1) = \text{ReLU}\left(\bar{y}_5(k;\nu+1) - \lambda_1(k;\nu)\right),
$$
$$
\lambda_1(k;\nu+1) = \lambda_1(k;\nu) + \eta_{\lambda_1}(\nu)\big(|y_1(k;\nu+1)| + |y_2(k;\nu+1)| + y_5(k;\nu+1)\big),
$$
$$
\lambda_2(k;\nu+1) = \lambda_2(k;\nu) + \eta_{\lambda_1}(\nu)\big(|y_2(k;\nu+1)| + y_3(k;\nu+1) + |y_4(k;\nu+1)|\big),
$$

where $\bar{\boldsymbol{y}}(k;\nu)$ is defined as in (A.18).

D   SUPPLEMENTARY ON NUMERICAL EXPERIMENTS

In this section, we provide more details on the algorithmic view of the proposed approach and the numerical experiments presented. In addition, we provide more examples.

D.1   ONLINE CORINFOMAX ALGORITHM IMPLEMENTATIONS FOR SPECIAL SOURCE DOMAINS

Algorithm 1 summarizes the dynamics of the CorInfoMax network and learning rules. For each of the domain choices, the recurrent and feedforward weight updates follow (14) and (16), respectively, and the learning step is indicated in the 4$^{\text{th}}$ and 5$^{\text{th}}$ lines in the pseudo-code. The line 3$^{\text{rd}}$ expresses the recursive neural dynamics to obtain the output of the network, and its implementation differs for different domain choices. Based on the derivations in Section 3 and Appendix C, Algorithm 2, 3, 4, and 5 summarizes the neural dynamic iterations for some example domains. For example, Algorithm 4 indicates the procedure to obtain the output $\boldsymbol{y}(k)$ of the antisparse CorInfoMax network at time step k corresponding to the mixture vector $\boldsymbol{x}(k)$. As it is an optimization process, we introduce two variables for implementation in digital hardware: 1) numerical convergence tolerance ϵ_t, and 2) maximum number of (neural dynamic) iterations $\nu_{\max}$. We run the proposed neural dynamic iterations until either a convergence happens, i.e., $\|\boldsymbol{y}(k;\nu) - \boldsymbol{y}(k;\nu-1)\|/\|\boldsymbol{y}(k;\nu)\| > \epsilon_t$, or the loop counter reaches a predetermined maximum number of iterations, that is, $\nu = \nu_{\max}$. Differently from the antisparse and nonnegative antisparse networks, the other CorInfoMax neural networks include additional inhibitory neurons due to the Lagrangian Min-Max settings, and the activation of these neurons are coupled with the network's output. Therefore, inhibitory neurons are updated in neural dynamics based on the gradient of the Lagrangian objective.

Algorithm 1 Online CorInfoMax pseudo-code

Input: A streaming data of $\{\boldsymbol{x}(k)\}_{k=1}^{N} \in \mathbb{R}^m$.
Output: $\{\boldsymbol{y}(k)\}_{k=1}^{N} \in \mathbb{R}^n$.
1: Initialize $\zeta_{\boldsymbol{y}}, \zeta_{\boldsymbol{e}}, \mu(1)_{\boldsymbol{W}}, \boldsymbol{W}(1), \boldsymbol{B}_{\boldsymbol{y}}^{\zeta_y}(1), \boldsymbol{B}_{\boldsymbol{e}}^{\zeta_e}(1)$, and select $\mathcal{P}$.
2: **for** k = 1, 2, ..., N **do**
3:    **run neural dynamics until convergence**:

$$\frac{d\mathcal{J}(\boldsymbol{y}(k;\nu))}{d\boldsymbol{y}(k)}\bigg|_{\boldsymbol{y}(k;\nu)} = \gamma_{\boldsymbol{y}}\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_y}(k)\boldsymbol{y}(k;\nu) - \gamma_{\boldsymbol{e}}\boldsymbol{B}_{\boldsymbol{e}}^{\zeta_e}(k)\boldsymbol{e}(k;\nu) \text{ s.t. } \boldsymbol{y}(k) \in \mathcal{P}$$

4:    $\boldsymbol{W}(k+1) = \boldsymbol{W}(k) + \mu_{\boldsymbol{W}}(k)\boldsymbol{e}(k)\boldsymbol{x}(k)^T$
5:    $\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_y}(k+1) = \frac{1}{\zeta_{\boldsymbol{y}}}(\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_y}(k) - \frac{1-\zeta_{\boldsymbol{y}}}{\zeta_{\boldsymbol{y}}}\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_y}(k)\boldsymbol{y}(k)\boldsymbol{y}(k)^T\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_y}(k))$
6:    Adjust $\mu_{\boldsymbol{W}}(k+1)$ if necessary.
7: **end for**

Algorithm 2 Online CorInfoMax neural dynamic iterations: sources in unit simplex

---

1: Initialize $\nu_{\max}, \epsilon_t, \eta_{\boldsymbol{y}}(1), \eta_\lambda(1), \lambda(1)(= 0$ in general$)$ and $\nu = 1$
2: **while** $(\|\boldsymbol{y}(k;\nu) - \boldsymbol{y}(k;\nu-1)\|/\|\boldsymbol{y}(k;\nu)\| > \epsilon_t)$ and $\nu < \nu_{\max}$ **do**
3:    $\frac{d\mathcal{J}(\boldsymbol{y}(k;\nu))}{d\boldsymbol{y}(k)}\bigg|_{\boldsymbol{y}(k;\nu)} = \gamma_{\boldsymbol{y}}\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_y}(k)\boldsymbol{y}(k;\nu) - \gamma_{\boldsymbol{e}}\boldsymbol{B}_{\boldsymbol{e}}^{\zeta_e}(k)\boldsymbol{e}(k;\nu)$
4:    $\boldsymbol{y}(k;\nu+1) = \text{ReLU}\left(\boldsymbol{y}(k;\nu) + \eta_{\boldsymbol{y}}(\nu)\frac{d\mathcal{J}(\boldsymbol{y}(k;\nu))}{d\boldsymbol{y}(k)}\bigg|_{\boldsymbol{y}(k;\nu)} - \lambda(\nu)\right)$
5:    $\frac{d\mathcal{L}(\boldsymbol{y}(k;\nu),\lambda(k;\nu))}{d\lambda(k)}\bigg|_{\lambda(k;\nu)} = \|\boldsymbol{y}(k;\nu+1)\|_1 - 1$
6:    $\lambda(k;\nu+1) = \lambda(k;\nu) + \eta_\lambda(\nu)\frac{d\mathcal{L}(\boldsymbol{y}(k;\nu),\lambda(k;\nu))}{d\lambda(k)}\bigg|_{\lambda(k;\nu)}$
7:    $\nu = \nu + 1$, and adjust $\eta_{\boldsymbol{y}}(\nu), \eta_\lambda(\nu)$ if necessary.
8: **end while**

Algorithm 3 Online CorInfoMax neural dynamic iterations: sparse sources

---

1: Initialize $\nu_{\max}, \epsilon_t, \eta_{\boldsymbol{y}}(1), \eta_\lambda(1), \lambda(1)(= 0$ in general$)$ and $\nu = 1$
2: **while** $(\|\boldsymbol{y}(k;\nu) - \boldsymbol{y}(k;\nu-1)\|/\|\boldsymbol{y}(k;\nu)\| > \epsilon_t)$ and $\nu < \nu_{\max}$ **do**
3:    $\frac{d\mathcal{J}(\boldsymbol{y}(k;\nu))}{d\boldsymbol{y}(k)}\bigg|_{\boldsymbol{y}(k;\nu)} = \gamma_{\boldsymbol{y}}\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_y}(k)\boldsymbol{y}(k;\nu) - \gamma_{\boldsymbol{e}}\boldsymbol{B}_{\boldsymbol{e}}^{\zeta_e}(k)\boldsymbol{e}(k;\nu)$
4:    $\boldsymbol{y}(k;\nu+1) = ST_{\lambda(\nu)}\left(\boldsymbol{y}(k;\nu) + \eta_{\boldsymbol{y}}(\nu)\frac{d\mathcal{J}(\boldsymbol{y}(k;\nu))}{d\boldsymbol{y}(k)}\bigg|_{\boldsymbol{y}(k;\nu)} - \lambda(\nu)\right)$
5:    $\frac{d\mathcal{L}(\boldsymbol{y}(k;\nu),\lambda(k;\nu))}{d\lambda(k)}\bigg|_{\lambda(k;\nu)} = \|\boldsymbol{y}(k;\nu+1)\|_1 - 1$
6:    $\lambda(k;\nu+1) = \text{ReLU}\left(\lambda(k;\nu) + \eta_\lambda(\nu)\frac{d\mathcal{L}(\boldsymbol{y}(k;\nu),\lambda(k;\nu))}{d\lambda(k)}\bigg|_{\lambda(k;\nu)}\right)$
7:    $\nu = \nu + 1$, and adjust $\eta_{\boldsymbol{y}}(\nu), \eta_\lambda(\nu)$ if necessary.
8: **end while**

Algorithm 4 Online CorInfoMax neural dynamic iterations: antisparse sources

---

1: Initialize $\nu_{\max}$, ϵ_t, $\eta_{\boldsymbol{y}}(1)$ and $\nu = 1$
2: **while** $(\|\boldsymbol{y}(k;\nu) - \boldsymbol{y}(k;\nu - 1)\|/\|\boldsymbol{y}(k;\nu)\| > \epsilon_t)$ and $\nu < \nu_{\max}$ **do**
3: $\quad \dfrac{d\mathcal{J}(\boldsymbol{y}(k;\nu))}{d\boldsymbol{y}(k)}\bigg|_{\boldsymbol{y}(k;\nu)} = \gamma_{\boldsymbol{y}} \boldsymbol{B}_{\boldsymbol{y}}^{\zeta_y}(k)\boldsymbol{y}(k;\nu) - \gamma_{\boldsymbol{e}} \boldsymbol{B}_{\boldsymbol{e}}^{\zeta_e}(k)\boldsymbol{e}(k;\nu)$
4: $\quad \boldsymbol{y}(k;\nu + 1) = \sigma_1\left(\boldsymbol{y}(k;\nu) + \eta_{\boldsymbol{y}}(\nu)\dfrac{d\mathcal{J}(\boldsymbol{y}(k;\nu))}{d\boldsymbol{y}(k)}\bigg|_{\boldsymbol{y}(k;\nu)}\right)$
5: $\quad \nu = \nu + 1$, and adjust $\eta_{\boldsymbol{y}}(\nu)$ if necessary.
6: **end while**

Algorithm 5 Online CorInfoMax neural dynamic iterations for Canonical Form

---

1: Initialize $\nu_{\max}$, ϵ_t, $\eta_{\boldsymbol{y}}(1)$, $\eta_{\boldsymbol{\lambda}}(1)$, $\boldsymbol{\lambda}(1)(=\boldsymbol{0}$ in general$)$ and $\nu = 1$
2: **while** $(\|\boldsymbol{y}(k;\nu) - \boldsymbol{y}(k;\nu - 1)\|/\|\boldsymbol{y}(k;\nu)\| > \epsilon_t)$ and $\nu < \nu_{\max}$ **do**
3: $\quad \dfrac{d\mathcal{J}(\boldsymbol{y}(k;\nu))}{d\boldsymbol{y}(k)}\bigg|_{\boldsymbol{y}(k;\nu)} = \gamma_{\boldsymbol{y}} \boldsymbol{B}_{\boldsymbol{y}}^{\zeta_y}(k)\boldsymbol{y}(k;\nu) - \gamma_{\boldsymbol{e}} \boldsymbol{B}_{\boldsymbol{e}}^{\zeta_e}(k)\boldsymbol{e}(k;\nu) - \boldsymbol{A}_{\mathcal{P}}^T\boldsymbol{\lambda}(\nu)$
4: $\quad \boldsymbol{y}(k;\nu + 1) = \boldsymbol{y}(k;\nu) + \eta_{\boldsymbol{y}}(\nu)\dfrac{d\mathcal{J}(\boldsymbol{y}(k;\nu))}{d\boldsymbol{y}(k)}\bigg|_{\boldsymbol{y}(k;\nu)}$
5: $\quad \dfrac{d\mathcal{L}(\boldsymbol{y}(k;\nu), \boldsymbol{\lambda}(k;\nu))}{d\boldsymbol{\lambda}(k)}\bigg|_{\boldsymbol{\lambda}(k;\nu)} = \boldsymbol{A}_{\mathcal{P}}\boldsymbol{y}(k;\nu) - \boldsymbol{b}_{\mathcal{P}}$
6: $\quad \boldsymbol{\lambda}(k;\nu + 1) = \mathrm{ReLU}\left(\boldsymbol{\lambda}(k;\nu) + \eta_{\boldsymbol{\lambda}}(\nu)\dfrac{d\mathcal{L}(\boldsymbol{y}(k;\nu),\boldsymbol{\lambda}(k;\nu))}{d\boldsymbol{\lambda}(k)}\bigg|_{\boldsymbol{\lambda}(k;\nu)}\right)$
7: $\quad \nu = \nu + 1$, and adjust $\eta_{\boldsymbol{y}}(\nu), \eta_{\boldsymbol{\lambda}}(\nu)$ if necessary.
8: **end while**

D.2 Additional Numerical Experiments for Special Source Domains

D.2.1 Sparse Source Separation

In this section, we illustrate blind separation of sparse sources, i.e. $\boldsymbol{s}(i) \in \mathcal{B}_{\ell_1} \forall i$. We consider $n = 5$ sources and $m = 10$ mixtures. For each source, we generate 5×10^5 samples in each realization of the experiments. We examine two different experimental factors: 1) output SINR performance as a function of mixture SNR levels, and 2) output SINR performance for different distribution selections for the entries of the mixing matrix.

For the first scenario with different mixture SNR levels: the sources are mixed through a random matrix $\boldsymbol{A} \in \mathbb{R}^{10 \times 5}$ whose entries are drawn from i.i.d. standard normal distribution, and the mixtures are corrupted by WGN with 30 dB SNR. We compare our approach with the WSM (Bozkurt et al., 2022), LD-InfoMax (Erdogan, 2022) and PMF (Tatli & Erdogan, 2021) algorithms and visualize the results in Figure 8. We also use the portion of the mixtures to train batch LD-InfoMax and PMF algorithms. Figure 8a illustrates the SINR performances of these algorithms for different input noise levels. The SINR results of CorInfoMax, LD-InfoMax, and PMF are noticeably close to each other, which is almost equal to the input SNR. Figure 8b illustrates the SINR convergence of the sparse CorInfoMax network for the 30 dB mixture SNR level as a function of update iterations. Based on this figure, we can conclude that the proposed CorInfoMax network converges robustly and smoothly.

Figure 8: SINR performances of CorInfoMax, LD-InfoMax, PMF, and WSM (averaged over 50 realizations): (a) output SINR results with respect to the input SNR level, (b) SINR convergence plot of sparse CorInfoMax for 30 dB SNR level (mean solid line and standard deviation envelopes).

In the second experimental setting, we examine the effect of the distribution choice for generating the random mixing matrix. Figure 9 illustrates the box plots of SINR results for CorInfoMax, LD-InfoMax, and PMF for different distribution selections to generate the mixing matrix, which are $\mathcal{N}(0,1)$, $\mathcal{U}[-1,1]$, $\mathcal{U}[-2,2]$, $L(0,1)$. where $\mathcal{N}$ is normal distribution, $\mathcal{U}$ is uniform distribution, and L is the Laplace distribution. It is observable that the performance of CorInfoMax is robust against the different distribution selections of the unknown mixing matrix, while its performance is on par with the batch algorithms LD-InfoMax and PMF.

Figure 9: SINR performances of CorInfoMax, LD-InfoMax, and PMF with different distribution selections for the mixing matrix entries.

D.2.2 NONNEGATIVE SPARSE SOURCE SEPARATION

We replicate the first experimental setup in Appendix D.2.1 for the nonnegative sparse source separation: evaluate the SINR performance of the nonnegative sparse CorInfoMax network for different levels of mixture SNR, compared to the batch LD-InfoMax algorithm and the biologically plausible WSM neural network. In these experiments, $n = 5$ uniform sources in $\mathcal{B}_{\ell_1,+}$ are randomly mixed to generate $m = 10$ mixtures. Figure 10a illustrates the averaged output SINR performances of each algorithm with a standard deviation envelope for different input noise levels. In Figure 10b, we observe the SINR convergence behavior of nonnegative sparse CorInfoMax as a function of update iterations. Note that CorInfoMax outperforms the biologically plausible neural network WSM for all input SNR levels, and its convergence is noticeably stable.

Figure 10: SINR performances of CorInfoMax, LD-InfoMax, and WSM: (a) the output SINR results with respect to the input SNR level, (b) SINR convergence plot of nonnegative sparse CorInfoMax for 30 dB SNR level (mean solid line and standard deviation envelopes).

D.2.3 SIMPLEX SOURCE SEPARATION

We repeat both the experimental settings in Appendix D.2.1 for the blind separation of simplex sources using the CorInfoMax network in Figure 7. Figure 11a shows the output SINR results of both the online CorInfoMax and the batch LD-InfoMax approaches for different mixture SNR levels. Even though simplex CorInfoMax is not as successful as the other examples (e.g., sparse CorInfo-Max), in terms of the closeness of its performance to the batch algorithms, it has still satisfactory source separation capability. Similar to the sparse network examples, its SINR convergence is fast and smooth, as illustrated in Figure 11b.

Figure 11: SINR performances of CorInfoMax and LD-InfoMax (averaged over 50 realizations): (a) the output SINR results with respect to the input SNR level, (b) SINR convergence plot of simplex-CorInfoMax for 30 dB SNR level (mean solid line and standard deviation envelopes).

Figure 12 shows the box plots of the SINR performances for both CorInfoMax and LD-InfoMax approaches with respect to different distribution selections for generating the random mixing matrix. Based on this figure, we can conclude that the simplex CorInfoMax network significantly maintains its performance for different distributions for the entries of the mixing matrix.

Figure 12: SINR performances of CorInfoMax and LD-InfoMax with different distribution selections for the mixing matrix entries (averaged over 50 realizations).

D.2.4 SOURCE SEPARATION FOR POLYTOPES WITH MIXED LATENT ATTRIBUTES

In this section, we demonstrate the source separation capability of CorInfoMax on an identifiable polytope with mixed features, which is a special case of "feature-based" polytopes in (2). We focus on the polytope

$$\mathcal{P}_{ex} = \left\{ \boldsymbol{s} \in \mathbb{R}^5 \ \middle| \ \begin{array}{l} s_1, s_2, s_4 \in [-1, 1], s_3, s_5 \in [0, 1], \\ \left\| \begin{bmatrix} s_1 \\ s_2 \\ s_5 \end{bmatrix} \right\|_1 \le 1, \left\| \begin{bmatrix} s_2 \\ s_3 \\ s_4 \end{bmatrix} \right\|_1 \le 1 \end{array} \right\}, \tag{A.19}$$

whose identifiability property is verified by the identifiable polytope characterization algorithm presented in Bozkurt & Erdogan (2022). We experiment with both approaches discussed in Section 3.4 and Appendix C.5. For the feature-based polytope setting introduced in Appendix C.5, the output dynamics corresponding to $\mathcal{P}_{ex}$ is also summarized as an example. This polytope can also be represented as the intersection of 10 half-spaces, that is, $\mathcal{P}_{ex} = \{\boldsymbol{s} \in \mathbb{R}^n | \boldsymbol{A}_{\mathcal{P}} \boldsymbol{s} \preccurlyeq \boldsymbol{b}_{\mathcal{P}}\}$ where $\boldsymbol{A}_{\mathcal{P}} \in \mathbb{R}^{10 \times 5}$ and $\boldsymbol{b}_{\mathcal{P}} \in \mathbb{R}^{10}$. Therefore, using $\boldsymbol{A}_{\mathcal{P}}$ and $\boldsymbol{b}_{\mathcal{P}}$, we can also employ the neural network illustrated in Figure 1a with 10 inhibitory neurons.

For this BSS setting, we generated the sources uniformly within this 5 dimensional polytope $\mathcal{P}_{ex}$ where the sample size is 5×10^5. The source vectors are mixed through a random matrix $\boldsymbol{A} \in \mathbb{R}^{10 \times 5}$ with standard normal entries. Figure 13a and 13b show the SINR convergence of CorInfoMax networks based on the feature-based polytope representation in (2) and the H-representation in (1) respectively, for the mixture SNR level of 30 dB. Moreover, Figure 13c and 13d illustrate their SINR convergence curves for the SNR level of 40 dB. In Table 2, we compare both approaches with the batch algorithms LD-InfoMax and PMF.

Figure 13: SINR performances of CorInfoMax networks on $\mathcal{P}_{ex}$ with mean-solid line with standard deviation envelope (averaged over 50 realization): (a) SINR convergence curve for CorInfoMax feature-based polytope formulation with $30\ dB$ mixture SNR, (b) SINR convergence curve for CorInfoMax canonical formulation with $30\ dB$ mixture SNR, (c) SINR convergence curve for CorInfoMax feature-based polytope formulation with $40\ dB$ mixture SNR, (d) SINR convergence curve for CorInfoMax canonical formulation with $40\ dB$ mixture SNR.

Table 2: Source separation averaged SINR results on $\mathcal{P}_{ex}$ for the CorInfoMax, CorInfoMax Canonical, LD-InfoMax, and PMF algorithms (averaged for 50 realizations).

Algorithm	CorInfoMax	CorInfoMax Canonical	LD-InfoMax	PMF
SINR (\w $30\ dB$ SNR)	26.55	24.85	30.28	27.68
SINR (\w $40\ dB$ SNR)	30.93	26.19	38.50	31.48

D.3 APPLICATIONS

We present several potential applications of the proposed approach, for which we illustrate the usage of antisparse, nonnegative antisparse and sparse CorInfoMax neural networks. This section demonstrates sparse dictionary learning, source separation for digital communication signals with 4-PAM modulation scheme, and video separation.

Online CorInfoMax 4-PAM SINR Convergence

(a)

(b)

Figure 14: (a) Sparse Dictionary, (b) The SINR convergence curve for the 4-PAM digital communication example (averaged over 100 realizations): mean-solid line with standard deviation envelope

D.3.1 Sparse Dictionary Learning

We consider sparse dictionary learning for natural images, to model receptive fields in the early stages of visual processing (Olshausen & Field, 1997). In this experiment, we used 12×12 pre-whitened image patches as input to the sparse CorInfoMax network. The image patches are obtained from the website http://www.rctn.org/bruno/sparsenet. The inputs are vectorized to the shape 144×1 before feeding to the neural network illustrated in Figure 2. Figure 14a illustrates the dictionary learned by the sparse CorInfoMax network.

D.3.2 Digital communication example: 4-PAM modulation scheme

One successful application of antisparse source modeling to solve BSS problems is digital communication systems Cruces (2010); Erdogan (2013). In this section, we verify that the antisparse CorInfoMax network in Figure 4 can separate 4-pulse-amplitude-modulation (4-PAM) signals with domain $\{-3, -1, 1, 3\}$ (with a uniform probability distribution). We consider that 5 digital communication (4-PAM) sources with 10^5 samples are transmitted and then mixed through a Gaussian channel to produce 10 mixtures. The mixtures can represent signals received at some base station antennas in a multipath propagation environment. Furthermore, the mixtures are corrupted by WGN that corresponds to SNR level of 30 dB. We feed the mixtures to the antisparse CorInfoMax network illustrated as input. For 100 different realization of the experimental setup, Figure 14b illustrates the SINR convergence as a function of update iterations. We note that the proposed approach distinguishably converges fast and each realization of the experiments resulted in a zero symbol error rate.

D.3.3 Video Separation

We provide more details on the video separation experiment discussed in Section 4.2. Three source videos we used in this experiment are from the website https://www.pexels.com/, which are free to download and use. Videos are mixed linearly through a randomly selected nonnegative 5×3 matrix

$$A = \begin{bmatrix} 1.198 & 1.020 & 1.273 \\ 0.367 & 1.364 & 0.901 \\ 0.100 & 0.869 & 0.627 \\ 1.257 & 0.859 & 0.015 \\ 0.957 & 0.789 & 0.592 \end{bmatrix},$$

to generate 5 mixture videos. Figures 15a and 15b illustrate the last RGB frames of the original and mixture videos, respectively. To train the nonnegative antisparse CorInfoMax network in Figure 5 for the separation of the videos, we followed the procedure below.

- In each iteration of the algorithm, we randomly choose a pixel location and select pixels from one of the color channels of all mixture videos to form a mixture vector of size 5×1,
- We sample 20 mixture vectors from each frame and perform 20 algorithm iterations per frame using these samples.

The demonstration video contains three rows of frames: the first row contains the source frames, the second row contains three of the five mixture frames, and the last row contains the network outputs for these mixture frames. Demo video is located at (https://figshare.com/s/a3fb926f273235068053). It is also included in supplementary files. If we use the separator matrix of the CorInfoMax network, which is an estimate for the left inverse of $\boldsymbol{A}$, to predict the original videos after training, we obtain PSNR values of $35.60\ dB$, $48.07\ dB$, and $44.58\ dB$ for the videos, which are calculated as the average PSNR levels of the frames. Figure 15c illustrates the final output frames of the CorInfoMax.

Figure 15: The final frames of (a) sources, (b) mixtures, and (c) the outputs of the nonnegative antisparse CorInfoMax network.

D.4 HYPERPARAMETER SELECTIONS

Hyperparameter selection has a critical impact on the performance of the neural networks offered in this article. In this section, we provide the list of our hyperparameter selections for the experiments provided in the article. These parameters are selected through ablation studies and some trials, which are discussed in Appendix D.5.

Table 3 summarizes the hyperparameter selections for the special domain choices provided in Section 2.1. Based on this table, we can observe that the hyperparameter sets for different special source domains generally resemble each other. However, there are some noticable domain-specific changes in some parameters, such as the starting learning rate for neural dynamics ($\eta_{\boldsymbol{y}}(1)$) and the learning rate for the Lagrangian variable ($\eta_\lambda(\nu)$).

Table 3: CorInfoMax network hyperparameter selections for special source domains in 2.1.

Source Domain	Hyperparameters
$\mathcal{P} = \mathcal{B}_{\ell_\infty}$	$\boldsymbol{W}(1) = \boldsymbol{I}, \quad \boldsymbol{B}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(1) = 5\boldsymbol{I}, \quad \boldsymbol{B}_{\boldsymbol{e}}^{\zeta_{\boldsymbol{e}}}(1) = 5000\boldsymbol{I}$
$\zeta_{\boldsymbol{y}} = 1 - 10^{-2}, \quad \zeta_{\boldsymbol{e}} = 1 - 2 \times 10^{-2}, \quad \mu_{\boldsymbol{W}} = 3 \times 10^{-2}$
$\nu_{\max} = 500, \quad \eta_{\boldsymbol{y}}(\nu) = 0.9/\nu, \quad \epsilon_t = 10^{-6}$
$\mathcal{P} = \mathcal{B}_{\ell_\infty,+}$	$\boldsymbol{W}(1) = \boldsymbol{I}, \quad \boldsymbol{B}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(1) = 5\boldsymbol{I}, \quad \boldsymbol{B}_{\boldsymbol{e}}^{\zeta_{\boldsymbol{e}}}(1) = 2000\boldsymbol{I}$
$\zeta_{\boldsymbol{y}} = 1 - 10^{-2}, \quad \zeta_{\boldsymbol{e}} = 1 - 10^{-1}/3, \quad \mu_{\boldsymbol{W}} = 3 \times 10^{-2}$
$\nu_{\max} = 500, \quad \eta_{\boldsymbol{y}}(\nu) = \max\{0.9/\nu, 10^{-3}\}, \quad \epsilon_t = 10^{-6}$
$\mathcal{P} = \mathcal{B}_1$	$\boldsymbol{W}(1) = \boldsymbol{I}, \quad \boldsymbol{B}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(1) = \boldsymbol{I}, \quad \boldsymbol{B}_{\boldsymbol{e}}^{\zeta_{\boldsymbol{e}}}(1) = 1000\boldsymbol{I}$
$\zeta_{\boldsymbol{y}} = 1 - 10^{-2}, \quad \zeta_{\boldsymbol{e}} = 1 - 10^{-2}, \quad \mu_{\boldsymbol{W}} = 3 \times 10^{-2}$
$\nu_{\max} = 500, \quad \eta_{\boldsymbol{y}}(\nu) = \max\{0.1/\nu, 10^{-3}\},$
$\eta_\lambda(\nu) = 1, \quad \epsilon_t = 10^{-6}$
$\mathcal{P} = \mathcal{B}_{1,+}$	$\boldsymbol{W}(1) = \boldsymbol{I}, \quad \boldsymbol{B}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(1) = 5\boldsymbol{I}, \quad \boldsymbol{B}_{\boldsymbol{e}}^{\zeta_{\boldsymbol{e}}}(1) = 1000\boldsymbol{I}$
$\zeta_{\boldsymbol{y}} = 1 - 10^{-2}, \quad \zeta_{\boldsymbol{e}} = 1 - 10^{-2}, \quad \mu_{\boldsymbol{W}} = 3 \times 10^{-2}$
$\nu_{\max} = 500, \quad \eta_{\boldsymbol{y}}(\nu) = \max\{0.1/\nu, 10^{-3}\},$
$\eta_\lambda(\nu) = 1, \quad \epsilon_t = 10^{-6}$
$\mathcal{P} = \Delta$	$\boldsymbol{W}(1) = \boldsymbol{I}, \quad \boldsymbol{B}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(1) = 5\boldsymbol{I}, \quad \boldsymbol{B}_{\boldsymbol{e}}^{\zeta_{\boldsymbol{e}}}(1) = 1000\boldsymbol{I}$
$\zeta_{\boldsymbol{y}} = 1 - 10^{-2}, \quad \zeta_{\boldsymbol{e}} = 1 - 10^{-2}, \quad \mu_{\boldsymbol{W}} = 3 \times 10^{-2}$
$\nu_{\max} = 500, \quad \eta_{\boldsymbol{y}}(\nu) = \max\{0.1/\nu, 10^{-3}\},$
$\eta_\lambda(\nu) = 0.05, \quad \epsilon_t = 10^{-6}$

For the other experiments presented in the Appendices D.2.4 and D.3, Table 4 summarizes the corresponding hyperparameter selections.

Table 4: CorInfoMax network hyperparameter selections for the polytope with mixed latent attributes in (A.19) and application examples in Appendix D.3.

Experiment	Hyperparameters
Polytope in (A.19) with Mixed Attributes (Canonical)	$\boldsymbol{W}(1) = \boldsymbol{I}, \quad \boldsymbol{B}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(1) = \boldsymbol{I}, \quad \boldsymbol{B}_{\boldsymbol{e}}^{\zeta_{\boldsymbol{e}}}(1) = 1000\boldsymbol{I}$
$\zeta_{\boldsymbol{y}} = 1 - 10^{-2}, \quad \zeta_{\boldsymbol{e}} = 1 - 10^{-2}, \quad \mu_{\boldsymbol{W}} = 5 \times 10^{-2}$
$\nu_{\max} = 500, \quad \eta_{\boldsymbol{y}}(\nu) = \max\{0.25/\nu, 10^{-4}\},$
$\eta_{\boldsymbol{\lambda}}(\nu) = 0.1, \quad \epsilon_t = 10^{-6}$
Polytope in (A.19) with Mixed Attributes (Feature-based)	$\boldsymbol{W}(1) = \boldsymbol{I}, \quad \boldsymbol{B}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(1) = 5\boldsymbol{I}, \quad \boldsymbol{B}_{\boldsymbol{e}}^{\zeta_{\boldsymbol{e}}}(1) = 2500\boldsymbol{I}$
$\zeta_{\boldsymbol{y}} = 1 - 10^{-2}, \quad \zeta_{\boldsymbol{e}} = 1 - 10^{-2}, \quad \mu_{\boldsymbol{W}} = 5 \times 10^{-2}$
$\nu_{\max} = 500, \quad \eta_{\boldsymbol{y}}(\nu) = \max\{0.1/\nu, 10^{-10}\},$
$\eta_{\lambda_1}(\nu) = \eta_{\lambda_2}(\nu) = 1, \quad \epsilon_t = 10^{-6}$
Sparse Dictionary Learning	$\boldsymbol{W}(1) = \boldsymbol{I}, \quad \boldsymbol{B}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(1) = \boldsymbol{I}, \quad \boldsymbol{B}_{\boldsymbol{e}}^{\zeta_{\boldsymbol{e}}}(1) = 20000\boldsymbol{I}$
$\zeta_{\boldsymbol{y}} = 1 - 10^{-3}/7, \quad \zeta_{\boldsymbol{e}} = 1 - 10^{-3}/7, \quad \mu_{\boldsymbol{W}} = 0.25 \times 10^{-3}$
$\nu_{\max} = 500, \quad \eta_{\boldsymbol{y}}(\nu) = \max\{1.5/(\nu \times 0.01), 10^{-8}\},$
$\eta_\lambda(\nu) = 3 \times 10^{-2}, \quad \epsilon_t = 10^{-6}$
Digital Communications	$\boldsymbol{W}(1) = \boldsymbol{I}, \quad \boldsymbol{B}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(1) = 5\boldsymbol{I}, \quad \boldsymbol{B}_{\boldsymbol{e}}^{\zeta_{\boldsymbol{e}}}(1) = 1000\boldsymbol{I}$
$\zeta_{\boldsymbol{y}} = 1 - 10^{-2}, \quad \zeta_{\boldsymbol{e}} = 1 - 10^{-2}, \quad \mu_{\boldsymbol{W}} = 3 \times 10^{-2}$
$\nu_{\max} = 500, \quad \eta_{\boldsymbol{y}}(\nu) = \max\{0.9/\nu, 10^{-3}\}, \quad \epsilon_t = 10^{-6}$
Video Separation	$\boldsymbol{W}(1) = \boldsymbol{I}, \quad \boldsymbol{B}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(1) = \boldsymbol{I}, \quad \boldsymbol{B}_{\boldsymbol{e}}^{\zeta_{\boldsymbol{e}}}(1) = 65\boldsymbol{I}$
$\zeta_{\boldsymbol{y}} = 1 - 10^{-1}/5, \quad \zeta_{\boldsymbol{e}} = 0.3, \quad \mu_{\boldsymbol{W}} = 6 \times 10^{-2}$
$\nu_{\max} = 500, \quad \eta_{\boldsymbol{y}}(\nu) = \max\{0.5/\nu, 10^{-3}\}, \quad \epsilon_t = 10^{-6}$

D.5 ABLATION STUDIES ON HYPERPARAMETER SELECTIONS

In this section, we illustrate an ablation study on selection of two hyperparameters for the non-negative antisparse CorInfoMax network: we experiment with selection for the learning rate of the

feedforward weights $\mu_{\boldsymbol{W}}$ and the initialization of the inverse error correlation matrix $\boldsymbol{B}_e^{\zeta_e}$. For these hyperparameters, we consider the following selections:

- $\mu_{\boldsymbol{W}} \in \{5 \times 10^{-3}, 10^{-2}, 3 \times 10^{-2}, 5 \times 10^{-2}\}$,
- $\boldsymbol{B}_e^{\zeta_e} \in \{10^3, 2 \times 10^3, 5 \times 10^3, 10^4\}$.

We consider the experimental setup in Section 4.1 for both uncorrelated sources and correlated sources with correlation parameter $\rho = 0.6$. For the ablation study for $\mu_{\boldsymbol{W}}$, we used fixed $\boldsymbol{B}_e^{\zeta_e}$ as indicated in Table 3, and vice versa.

Figures 16a and 16b illustrate the mean SINR with standard deviation envelope results with respect to $\mu_{\boldsymbol{W}}$ for uncorrelated and correlated source separation settings, respectively. Note that although selection $\mu_{\boldsymbol{W}} = 5 \times 10^{-2}$ seems to be better for uncorrelated sources, its performance degrades for correlated sources as for some of the realizations, the algorithm diverges. We conclude that the selection $\mu_{\boldsymbol{W}} = 3 \times 10^{-2}$ is near optimal in this setting and obtains good SINR results for both correlated and uncorrelated sources. For the initialization of $\boldsymbol{B}_e^{\zeta_e}$, Figures 16c and 16d illustrate the SINR performances of CorInfoMax for uncorrelated and correlated source separation experiments, respectively. Note that the selections $\boldsymbol{B}_e^{\zeta_e} = 2000\boldsymbol{I}$ and $\boldsymbol{B}_e^{\zeta_e} = 5000\boldsymbol{I}$ are suitable considering both settings.

Figure 16: CorInfoMax ablation studies on the hyperparameter selections of $\mu_{\boldsymbol{W}}$ and $\boldsymbol{B}_e^{\zeta_e}$: mean SINR with standard deviation envelopes corresponding to 50 realizations. (a) ablation study of $\mu_{\boldsymbol{W}}$ on uncorrelated nonnegative antisparse sources, (b) ablation study of $\mu_{\boldsymbol{W}}$ on correlated (with $\rho = 0.6$) nonnegative antisparse sources, (c) ablation study of $\boldsymbol{B}_e^{\zeta_e}$ on uncorrelated nonnegative antisparse sources, (d) ablation study of $\boldsymbol{B}_e^{\zeta_e}$ on correlated (with $\rho = 0.6$) nonnegative antisparse sources,

D.6 COMPUTATIONAL COMPLEXITY OF THE PROPOSED APPROACH

The complexity of the proposed approach can be characterized based on the analysis of output dynamics and weight updates. For simplicity, we consider the complexity of the antisparse CorInfoMax network in Figure 4: Let ν_{max} represent the maximum count for the neural dynamic iterations.

Neural Dynamics' Complexity: For one neural dynamic iteration, we observe the following number of operations

- Error calculation $\boldsymbol{e}(k; \nu) = \boldsymbol{y}(k; \nu) - \boldsymbol{W}(k)\boldsymbol{x}(k)$ requires nm multiplications,
- $\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(k)\boldsymbol{y}(k; \nu)$ requires n^2 multiplications,
- $\boldsymbol{B}_{\boldsymbol{e}}^{\zeta_e}(k)\boldsymbol{e}(k; \nu)$ requires n multiplications as $\boldsymbol{B}_{\boldsymbol{e}}^{\zeta_e}(k) = \dfrac{1}{\epsilon}\boldsymbol{I}$.

As a result, ν_{max} neural dynamics iterations require $\nu_{max}(mn + n^2 + n) \approx \nu_{max}mn$ multiplications per output computation.

Weight Updates' Complexity: For the weight updates, we note the following number of operations

- $\boldsymbol{W}(k+1) = \boldsymbol{W}(k) + \mu_{\boldsymbol{W}}(k)\boldsymbol{e}(k)\boldsymbol{x}(k)^T$ requires $2mn$ multiplication,
- $\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(k+1) = \dfrac{1}{\zeta_{\boldsymbol{y}}}(\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(k) - \dfrac{1 - \zeta_{\boldsymbol{y}}}{\zeta_{\boldsymbol{y}}}\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(k)\boldsymbol{y}(k)\boldsymbol{y}(k)^T\boldsymbol{B}_{\boldsymbol{y}}^{\zeta_{\boldsymbol{y}}}(k))$ requires $n^2 + n^2 + n^2 + 1 + \dfrac{n(n+1)}{2} = \dfrac{7n^2 + n + 2}{2}$ multiplications.

Therefore, weight updates for learning require $2mn + \frac{7n^2+n+2}{2}$ multiplications per input sample.

Taking into account both components of the computations, complexity is dominated by the neural dynamics iterations which require approximately $\mathcal{O}(\nu_{max}mn)$ operations. This is in the same order as the complexity reported in Bozkurt et al. (2022) for biologically plausible WSM, NSM, and BSM networks.