Exploiting Spatial Separability for Deep Learning Multichannel Speech Enhancement with an Align-and-Filter Network

Abstract

Multichannel speech enhancement (SE) systems separate the target speech from background noise by performing spatial and spectral filtering. The development of multichannel SE has a long history in the signal processing field, where one crucial step is to exploit spatial separability of sound sources by aligning the microphone signals in response to the target speech source prior to further filtering processes. However, most existing deep learning based multichannel SE works have yet to effectively incorporate or emphasize this spatial alignment aspect in the network design – we postulate that it is owing to the lack of suitable datasets with sufficient spatial diversity of the speech sources. In this paper, we highlight this important but often overlooked step in deep learning based multichannel SE, i.e., signal alignment, by introducing an Align-and-Filter network (AFnet) featuring a two-stage sequential masking design. The AFnet estimates two sets of masks, the alignment masks and filtering masks, and multiplies the estimated masks with the respective input signals to each stage sequentially, while leveraging the relative transfer functions (RTFs) for guiding the model to align signals with various speech source locations during training. For exploration purposes, we argue that the popular CHiME-3 multichannel dataset has its own limitation in representing spatially diverse speech data as the speakers were mostly located at the front side, and thereby adopt simulated and real-world measured room impulse responses to generate multichannel recordings where the target speech sources might come from arbitrary directions. Our findings suggest that for spatially diverse speaker scenarios, careful consideration of exploiting spatial characteristics is of great importance for deep learning based multichannel SE especially when the number of microphone gets increased. We show that utilizing the RTFs for signal alignment purposes in the two-stage, sequential masking framework consistently improves the capability of the network to separate the target speech from the noise signals, supporting that spatial separability is being effectively exploited by the proposed model. Our studies advocate for the advantages and significance of considering the signal alignment aspect, a wisdom coming from conventional signal processing, for developing future deep based multichannel SE algorithms to improve enhancement outcomes with positional diverse target speech scenarios.

1 Introduction

Signal quality could significantly deteriorate in the presence of noise and interference. Information carried by the signal, e.g., speech, could be severely lost at the receiver side (the human ear or smart assistants) in a very noisy environment, causing difficulty of communication. Speech enhancement (SE) techniques aim to resolve such issues, which had been majorly developed based on model-based, signal processing approaches that utilize mathematical modeling of signal statistics (Loizou, 2007). In the past decade, the advent of deep learning has demonstrated the potential of advancing the development of SE systems to a higher level, making SE a topic of great interest in the machine learning field (Wang & Chen, 2018; Haeb-Umbach et al., 2019).

SE systems can be categorized into *single-channel* (single microphone) and *multichannel* (multiple microphones) schemes. An important aspect of multichannel SE against single-channel SE is the *exploitation of spatial separability*, as known as *spatial filtering* or *beamforming*, enabled by the *difference* between the amplitudes and times of arrival of the received microphone signals due to the different acoustic paths the sound waveform travels to the microphones. In many signal processing

beamforming methods, a key step is to *align* the microphone signals in response to the target signal source before any further filtering processes. This step, by *steering* the array toward the location of the target signal, aims to compensate for the difference of the amplitudes and time delays (or correspondingly the magnitudes and phases in the frequency domain) of the microphone signals with respect to the target source. Ideally, after the alignment step, each microphone should contain the same target speech component with no difference in amplitude and time delay (or magnitude and phase) which makes the speech extraction easier in the later filtering process. Thus, an efficient SE system can first align its microphone signals in response to the target speech, followed by spectral processing for fine-tuning and enhancement. This is similar to the human ear which can do both delay estimation and frequency analysis. Surprisingly, though well-known in signal processing approaches, there are only few deep learning SE systems designed mainly based on this observation.

In this paper, we revisit this important but often overlooked alignment aspect from conventional signal processing algorithms for deep learning based multichannel SE network design. The main contributions of this paper are summarized as follows:

- We propose a deep learning framework, namely Align-and-Filter network (AFnet) (Figure 1), for studying the importance of spatial separability in deep learning based multichannel SE. The framework features a two-stage design, i.e., Align Net and Filter Net, where two sets of masks, alignment and filtering masks, are sequentially estimated and multiplied with their respective input signals, while leveraging the *relative transfer function (RTF)* information for facilitating signal alignment during the learning stage. The incorporation of RTF supervision along with the sequential masking mechanism are shown to assist the network in effectively exploiting spatial characteristics of the target speech source for improved SE outcomes.

- The proposed AFnet framework is utilized to analyze the spatial diversity of speech sources in different datasets. Based on our study, we point out that some existing dataset such as CHiME-3 (Barker et al., 2015) lacks sufficient positional variety of target speech (mostly from the front side) and thus has its own limitation of representing broader SE scenarios, which could in turn downgrade the importance of the signal alignment aspect. On the other hand, on more spatially diverse data that we have gathered, our results indicate that remarkable improvements can be achieved by exploiting spatial separability via RTF alignment and sequential masking, while simply stacking neural network models might not work well when the number of microphones gets increased.

- Through our exploration on the spatial characteristics of multichannel data with the AFnet, we highlight the wisdom of conventional signal processing methods – *the importance of signal alignment* – and advocate for incorporating the concept into the development of deep learning based multichannel SE systems, especially when the target speech may locate in arbitrary positions.

Figure 1: The proposed AFnet for exploiting spatial separability for multichannel SE. X_i: input noisy STFTs, A_i: alignment masks, F_i: filtering masks, $\hat{S}$: enhanced STFT. $X_i, A_i, F_i, \hat{S} \in \mathbb{C}^{F \times T}$.

2 RELATED WORK

Multichannel SE has been a well known topic in signal processing for decades. Aside from leveraging spectral characteristics, multichannel SE can exploit positional information to perform *spatial filtering*, or *beamforming*, that allows extracting the target speech from noise based on spatial separability. Conventional beamforming approaches rely on the so-called "steering vector" which carries positional information about the target speech (Doclo et al., 2015; Trees, 2004), e.g., the minimum-variance-distortionless-response (MVDR) beamformer (Capon, 1969) and its variants (Frost, 1972; Griffiths & Jim, 1982). It is an important step in beamforming that the microphone array is steered toward the target signal location prior to further filtering processes. To this end, certain knowledge about the acoustic paths (either impulse responses or transfer functions) between the target signal and the microphones have to be known. Many signal processing based multichannel SE systems utilize the ratio of the acoustic transfer functions, i.e., the *relative transfer function (RTF)*, that represents the coupling between sensors in response to a desired source (Cohen, 2004; Gannot et al., 2001; Krueger et al., 2010; Koldovský et al., 2015) for improving the denoising process.

In the past decade, supervised learning approaches, especially deep learning, have remarkably changed the way of developing SE systems. Along with the success of deep neural networks (DNNs) on single-channel SE (Lu et al., 2013; Williamson et al., 2015; Pascual et al., 2017; Luo & Mesgarani, 2019; Kim et al., 2020; Zheng et al., 2021), several multichannel SE systems have also been proposed, e.g., Erdogan et al. (2016); Variani et al. (2016); Sainath et al. (2017); Bu et al. (2019); Luo et al. (2020); Tolooshams et al. (2020). However, the utilization of such important RTF information is often overlooked in the model design of DNN-based multichannel SE. To the best of our knowledge, the only work that incorporates RTFs for SE is by Wang & Wang (2018), in which, however, the RTF estimation is used as an intermediate step to assist the conventional MVDR beamformer only. We postulate that the overlook may be due to the lack of sufficient spatial variety of the speech sources in the popular dataset such as CHiME-3, where the benefit of utilizing RTFs could be only marginal. However, many practical situations can have the target speech coming from arbitrary directions and thus a deep dive into the RTF spatial alignment aspect is still of great importance.

3 PROPOSED METHOD

We consider an acoustic scenario with one desired speech source and several interfering noise signals in a reverberant environment. The SE system will be developed in the time-frequency domain using the short-time Fourier transform (STFT) (Parchami et al., 2016) where the time-domain waveforms are transformed to complex-valued STFT representations. Let f, t stand for the frequency index and time frame index (with a total of F frequency bins and T time frames), we consider an additive noise model where the i-th microphone noisy signal $X_i \in \mathbb{C}^{F \times T}$ of an N-element local microphone array can be written in the STFT domain as (Doclo et al., 2015): $X_i(f, t) = S_i(f, t) + V_i(f, t)$, $\forall i = 1, \ldots, N$, with $S_i(f, t) = H_i(f, t)S_0(f, t)$ being the speech component received by microphone i, where $H_i(f, t)$ is the acoustic transfer function between microphone i and the location of the far-field speech source signal $S_0(f, t)$, and $V_i(f, t)$ is the noise component captured by microphone i. Typically, the goal of multichannel SE is to recover the speech component $S(f, t) = S_r(f, t)$ of a selected reference microphone $r \in \{1, \ldots, N\}$ given the noisy microphone signals $X_1(f, t), \ldots, X_N(f, t)$. Multichannel SE systems typically perform the "filter-and-sum" operation, or more generally known as "beamforming" – linearly combining the signals of different microphone channels to extract the target signal from background noise. In the STFT domain, the estimation process can be expressed as: $\hat{S}(f, t) = \sum_{i=1}^{N} W_i(f, t)X_i(f, t)$, where $W_i(f, t)$ is the corresponding filter weight for microphone i and $\hat{S}(f, t)$ is the enhanced signal.

3.1 TWO-STAGE ALIGN-AND-FILTER FRAMEWORK WITH SEQUENTIAL MASKING

Inspired by the alignment concept in signal processing based algorithms, we introduce a two-stage Align-and-Filter framework for deep learning multichannel SE in Figure 1, where two modules are utilized to carry out alignment and filtering purposes respectively. The first module (Align Net) aims at estimating a set *alignment masks* for steering the input microphone signals toward the target speech location. Subsequently, the second module (Filter Net) focuses on cleaning up the interference in the aligned signals by estimating another set of *filtering masks* and linearly combines all channel outputs into the enhanced signal. Overall, the enhancement process can be expressed as: $\hat{S}(f, t) = \sum_{i=1}^{N} F_i(f, t)A_i(f, t)X_i(f, t)$, where $A_i \in \mathbb{C}^{F \times T}$ is the alignment mask and $F_i \in \mathbb{C}^{F \times T}$ is the filtering mask of the i-th microphone. This sequential masking scheme at the same time introduces signal level skip connections on top of the two modules for improved optimization.

3.2 RTF-AWARE TRAINING

The spatial relationship between the far-field target source and the microphones along with the acoustic environment characteristics determine the inter-channel level difference (ILD) and inter-channel time difference (ITD) of the microphone signals, which are important cues for sound source localization. In the STFT domain, the ILD and ITD correspond to the magnitude and phase of the RTF respectively, which is the ratio between the acoustic transfer functions of two microphones with regards to the sound source (Li et al., 2016). Formally, we can express the RTF $\tilde{H}_i \in \mathbb{C}^{F \times T}$ as:

$$\tilde{H}_i(f,t) \triangleq \frac{H_r(f,t)}{H_i(f,t)} = \frac{H_r(f,t)S_0(f,t)}{H_i(f,t)S_0(f,t)} = \frac{S_r(f,t)}{S_i(f,t)}, \tag{1}$$

$\forall i = 1, \ldots, N$, where $H_r(f,t)$ denotes the acoustic transfer function of the selected reference microphone $r \in \{1, \ldots, N\}$. From (1) we can see that the RTFs can be inferred from the ratios of the clean microphone signals which are often available in supervised learning SE schemes, and thus can be collected without knowing or simulating the noise. Note that the RTF information is only needed for training and is not required during inference.

Element-wise multiplying the RTF $\tilde{H}_i(f,t)$ with the microphone signal $X_i(f,t)$ we obtain:

$$Z_i(f,t) = \tilde{H}_i(f,t)X_i(f,t) = \frac{H_r(f,t)}{H_i(f,t)}[H_i(f,t)S_0(f,t) + V_i(f,t)] = S_r(f,t) + \tilde{V}_i(f,t), \tag{2}$$

$\forall i = 1, \ldots, N$, where $S_r(f,t)$ is the speech component of the reference microphone and $\tilde{V}_i(f,t) = [H_r(f,t)/H_i(f,t)]V_i(f,t)$ is the noise component. It can be seen that multiplying the RTFs with the microphone signals leads to aligning all the microphone channels with respect to the clean speech component at the reference microphone as each $Z_i(f,t)$ contains $S_r(f,t)$. In the case of far-field, anechoic setting, this means the microphone array has steered to the direction of the signal source.

We implicitly incorporate RTFs during the model learning phase via an RTF-aware training protocol consisting of two phases: first adjusting only the Align Net parameters so that the alignment masks A_i approximate the RTFs $\tilde{H}_i$ by minimizing the following RTF alignment loss: $\mathcal{L}_{rtf} = \sum_{i,f,t} |A_i(f,t) - \tilde{H}_i(f,t)|^2$, where we have chosen to use the mean squared error (MSE) loss. Note that truncation of the magnitude of the ground-truth RTF $\tilde{H}_i(f,t)$ to a maximum value of, e.g., 10, can be applied for avoiding training instability. Optimizing for this loss function guides the network to learn to steer the microphone signals toward the target speech, making the model aware of the spatial information of the target source. The second phase performs parameter learning of the whole model (i.e., jointly adjusting both Align Net and Filter Net parameters) to reconstruct the clean speech. To this end, we minimize the signal reconstruction loss $\mathcal{L}_{rec} = \sum_{f,t} 0.7(|\hat{S}(f,t)|^{0.3} - |S(f,t)|^{0.3})^2 + 0.3||\hat{S}(f,t)|^{0.3}e^{j\angle\hat{S}(f,t)} - |S(f,t)|^{0.3}e^{j\angle S(f,t)}|^2$, i.e., the combined power-law compressed MSE loss in Wilson et al. (2018); Braun & Tashev (2021).

3.3 AFNET BASED ON COMPLEX W-NET ARCHITECTURE

We introduce the AFnet (Figure 1) for multichannel SE based on implementing a W-Net architecture suitable for realizing the two-stage framework. Originally, the W-Net (Xia & Kulis, 2017) is an improved version of the U-Net structure (Ronneberger et al., 2015). For the SE application here, extension to complex operations can be more suitable when working in the STFT domain. Choi et al. (2018) have proposed to utilize complex-valued U-Net for the single-channel SE task. In our work, we follow this idea and extend the W-Net by incorporating complex operations for the multichannel SE task. Note that Koyama & Raj (2019) also adopt a W-Net architecture for beamforming. However, they do not utilize complex-valued network layers. In addition, the first U-Net in their work aims to predict a single-channel enhanced output, while in our AFnet it estimates multiple masks for predicting aligned multichannel signals to exploit spatial information.

In the current work, main modifications to the W-Net include: Convolutional layers of W-Net are all replaced to complex convolutional layers. For the activation function, complex leaky ReLU, i.e., an activation function which applies leaky ReLU on both real and imaginary values, are utilized. The number of feature maps in each layer are also modified. Note that in Figure 1, "dConv (C_{in}, C_{out})" stands for "double Convolutions" with C_{in} input channels and C_{out} output channels. Each dConv unit consists of two stacks of "(complex) 3×3 convolution→batch normalization→leaky ReLU". The convolution layer of the first stack takes C_{in} channels and outputs C_{out} channels; the convolution layer of the second takes C_{out} channels and outputs C_{out} channels.

4 EXPERIMENTS

4.1 DATASETS AND EXPERIMENTAL SETUP

4.1.1 PRIMARY DATASET

Speech corpus: We leverage the AVSpeech dataset which is a large collection of video clips of single speakers talking with no audio background interference introduced in Ephrat et al. (2018). The dataset is based on public instructional YouTube videos, from which short, 3-10 second clips were automatically extracted, where the only audible sound in the soundtrack belongs to a single speaking person. We downloaded 8308 clips from the training set and another 1199 clips from the test set for our experiments, using only the audio portion (converted to 16 kHz .wav files).

Room impulse response data: We mix the speech files with noise files of several types also downloaded from YouTube and consider different reverberation conditions for generating the noisy data using simulated impulse responses via Pyroomacoustics (Scheibler et al., 2018), which is a Python-based acoustic simulator for generating different acoustic scenes. We create a room of size $8 \times 8 \times 3$ (length×width×height in meters). Reverberation time is randomly chosen from {0.16, 0.32, 0.48, 0.64} second. The simulating approach for estimating room impulse responses is based on the image source method. Speech and noise signals are randomly positioned at a distance of {1, 2, 3, 4} meters from the microphone array with arbitrary directions of arrival. The microphones form a 2-by-4 planar array placed vertically at the center of the room, and the spacing between two adjacent microphones is 5 cm. 4 types of commonly seen interference (blender, vacuum, washer, baby cry) are used for training and another 4 types (dog barking, kids playing sound, hair dryer, food sizzling) are used for testing. Each type of noise is multiplied with a scale randomly chosen from {0, 0.5, 1, 1.5, 2} before added up, and the combined noise is then added to the clean speech according to a specific SNR level randomly selected from {-10, -6, -3, 0, 3, 6, 10} dB. In this way, we are adopting the supervised learning SE scheme of mix-and-separate, where the clean and noise signals are separately collected and subsequently mixed together to become the noisy signals for training purposes. This mix-and-separate scheme by assuming additive noise model is still being used in the majority of SE works (not only signal processing but also deep learning based approaches). To apply it to real data, one may collect the clean and noise recordings using the target device in real-world environments and mix them up to generate noisy mixtures for training.

The main reason why we have chosen to use the simulated multichannel data as the primary dataset for exploration purposes is to have sufficient spatial diversity of the target speech and also be able to label the speech source location for visualization of the intermediate variables learned by the AFnet (i.e., the alignment masks) and other in-depth study. The acoustic room simulator provides the flexibility of modifying several factors for generating representative multichannel data, which has also been a common practice in many multichannel audio processing works.

4.1.2 AUXILIARY DATASET:

The CHiME-3 dataset (Barker et al., 2015), made available as part of a speech separation and recognition challenge, is used for training and evaluating SE performance. The dataset is a 6-channel microphone recording of talkers speaking in a noisy environment, sampled at 16 kHz. It consists of 7,138 and 1,320 simulated utterances with an average length of 3 seconds for training and testing, respectively. We take this dataset only as auxiliary due to limited positional variety of the target speech – most of the speakers have been speaking from the front side with respect to the microphones. As such, the dataset is less ideal for exploration of spatial characteristics and signal alignment purposes.

4.1.3 MODEL SETTINGS AND EVALUATION METRICS

In this paper, we set the number of channels of the AFnet (Figure 1) as: $C_1, C_2, C_3, C_4 = 32, 64, 64, 64$, resulting in a model size of approximately 2.6M parameters. Regarding the STFT processing of the input signal, for the primary dataset we use the Hann window with 512-point fast Fourier transform (FFT) and for CHiME-3 with 1024-point FFT, both using a hop size of 256. During training, 4-second long segments are randomly cropped from the training data samples while during testing the whole utterances are used. The RTFs are obtained by computing the ratios between the clean speech signals at all microphones according to (1). We use the following three commonly seen speech enhancement metrics for evaluation purposes. **PESQ:** Perceptual Evaluation of Speech Quality (ITU-T Recommendation P.862.2, 2005). **STOI:** Short-Time Objective Intelligibility (Taal et al., 2011). **SSNR:** Segmental Signal-to-Noise Ratio (Hansen & Pellom, 1998). For all the metrics, the higher the score, the better the performance.

4.2 RESULTS

4.2.1 ALIGNED VS. UNALIGNED SIGNAL ENHANCEMENT

To get an understanding of the importance of alignment, we first conduct an experiment to compare the difference between enhancement outcomes of aligned and unaligned input signals with the primary dataset. To this end, two schemes are considered, where in the first scheme we manually align the noisy microphone signals by multiplying them with the corresponding ground truth speech RTFs, while in the other

Table 1: Speech enhancement performance comparison between aligned (A) and unaligned (U) signals.

# Mic	PESQ		STOI		SSNR	
	A	U	A	U	A	U
2	2.68	1.68	0.842	0.697	7.86	4.66
4	2.89	1.67	0.862	0.696	8.28	4.56
8	3.04	1.76	0.879	0.719	8.66	4.68
CHiME-3	2.62	2.42	0.973	0.963	10.32	9.13

scheme we directly use the original unaligned signals. In each scheme, a single U-Net model, or equivalently, the Filter Net (the second half of AFnet), is trained for the signal reconstruction loss $\mathcal{L}_{rec}$ and tested on the corresponding aligned or unaligned data. The performance numbers of the two cases are presented in Table 1. It can be seen that when the signals are aligned, the Filter Net model can do a much better job of separating the target signal from background noise and achieves significantly better scores than unaligned results in all three metrics. This observation is consistent across all three number of microphone settings. The results suggest that for a spatially diverse dataset where the target speech may come from various locations, having a signal alignment module in front of the signal filtering module can be beneficial.

We also present the results for the CHiME-3 dataset in Table 1. We can see that the margin between the results of using the aligned and unalinged signals is much smaller here. It could be attributed to that most of the CHiME-3 recording data samples have the speaker almost speaking from the front side with respect to the microphones which results in less variety in directional angles (the common situation when the speaker was asked for holding a tablet to speak the sentence listed in the tablet, and the speech data were recorded through 6 embedded microphones in the same tablet. See the recording setup and recording demonstration picture in CHiME-3 official website) and thus the less spatial diversity. Moreover, as the speech sources mostly come from the front side, they are in a sense already roughly aligned. Thus, there is the less benefit brought by performing the alignment, meaning that the requirement of aligning signals is bypassed to some extend.

4.2.2 EXPLOITING SPATIAL SEPARABILITY WITH AFNET

Having the above insight, we move on to studying the proposed AFnet for exploitation of spatial separability on the primary dataset with different model/training settings and comparing with typical one-stage deep learning framework approaches. For detailed analysis, we consider four cases below:

i) **U-Net for filter weights:** using only a single U-Net (same model as the Filter Net of AFnet) to estimate the filter weights W_i in typical (one-stage) multichannel SE

ii) **W-Net for filter weights:** using a W-Net (same model as the AFnet, but the output of the first U-Net block goes directly to the next U-Net block without multiplying the input signals) to estimate the filter weights W_i in typical (one-stage) multichannel SE

iii) **AFnet w/o RTF loss:** the two-stage sequential masking AFnet model trained by normal training scheme without incorporating RTFs

iv) **AFnet:** the two-stage sequential masking AFnet model trained with RTF-aware scheme

Cases i) and ii) represent the typical one-stage approach which uses a DNN to estimate the filter weights for beamforming purposes, serving as baseline methods here. Cases iii) and iv) are considered to observe the role of RTF alignment in the proposed AFnet.

Figure 2 presents the enhancement results. One can see that the AFnet with RTF supervision achieves the best performance overall. More importantly, the performance improves as the number of microphone increases, indicating that AFnet indeed exploits the spatial characteristics of sound sources within the multichannel data for enhancement purposes. In contrast, the typical one-stage approaches of U-Net and W-Net do not seem to actually benefit from the multichannel input data, as the performance is not necessarily improving with increased number of microphones. In fact, the W-Net even performs worse than the single U-Net model for the cases with more microphones (4-mic, 8-mic) though doubling the model size, with its best result surprisingly reached for the 2-mic

case. This observation implies that to further take advantage of audio data with more microphone channels, simply stacking U-Net models may not straightforwardly work well. This might be due to the potential optimization difficulty of having a deeper model and more complicated multichannel input data to extract useful information. On the other hand, the AFnet seems to mitigate these issues by introducing the sequential masking mechanism which also provides certain input signal level skip connections, as we can see that even without RTF supervision it is able to perform much better than the W-Net. With the RTF loss incorporated for leveraging spatial separability more easily, the AFnet is able to achieve even better performance. From these observations, we can conclude that the positional variety of the target speaker can be an important factor to consider in multichannel SE, and careful consideration of the spatial alignment for model design, e.g., the RTF loss within the sequential masking scheme, is critical for deep learning based multichannel SE systems for diverse speaker position scenarios.

Figure 2: Enhancement performance of different networks and training settings.

4.2.3 VISUALIZING THE ALIGNMENT OUTCOMES AND DATASET SPATIAL DIVERSITY

To further observe the effect of RTF supervision, we visualize the distributions of the alignment masks in Figure 3 from AFnet trained with RTF loss and that without RTF loss. To obtain these plots, we take noisy signal samples from the test set in which the speech source in each sample is located at one of three pre-defined positions in the room. We feed the taken noisy samples to the trained AFnet models (both with and without RTF supervision) and obtain the alignment masks for each sample. The distribution of the principal components (PCs) of the obtained masks are plotted. It can be seen that with RTF-aware training, the distributions show clearer clusters of speech sources corresponding to the three different positions than with normal training. In addition, with increased number of microphones the clusters also become more separate. The results together with improved enhanced speech quality provide evidence of the fact that the system is actually exploiting spatial separability of the audio sources for achieving better enhancement performance.

Another angle to inspect the spatial diversity of the dataset can also be provided by observing the alignment masks of the data points. In Figure 4 we compare the distributions of the intermediate alignment masks learned by the AFnet models trained on the primary dataset (high spatial diversity) and the CHiME-3 dataset (low spatial variety). Here, we plot the distributions of the alignment masks estimated by the trained models for all the test data samples of the two datasets. It can be seen that for the primary dataset, the RTF-aware training leads to a more widespread distribution than that of the normal training case, corresponding to the greater spatial diversity of the target speech source positions. In contrast, in the CHiME-3 dataset the RTF-aware training actually results in a more aggregated cluster than the normal training scheme, indicating that the target speech sources are coming from similar directions. This visualization of the alignment masks provides another angle to inspect the data properties from the spatial diversity aspect for exploring SE performance.

4.2.4 COMPARISON TO SOTA METHODS

To demonstrate the superiority of our method, we compare the AFnet with several SOTA architectures, including: **Conv-TasNet** (Luo & Mesgarani, 2019): a single-channel SE system performing masking based separation method in the learned transform domain via learnable encoder and decoder. **DCUnet** (Choi et al., 2018): a phase-aware single-channel SE approach utilizing complex-valued operations with the U-Net architecture. **FaSNet** (Luo et al., 2020): a time-domain, multi-channel SE system exploiting cross-channel correlation based on filter-and-sum method.

We train the SOTA models by ourselves. For fairness, all models are trained by minimizing the reconstruction loss $\mathcal{L}_{rec}$ of the power-law compressed MSE, using 512-point FFT with a hop size of

Figure 3: Visualization of the distributions of alignment masks. The RTF-aware training cases (Upper Row) show obvious clusters of signals coming from the three different locations (loc 1, loc 2, loc 3) as the number of microphone increases, while the normal training cases (Lower Row) do not present clear boundaries.

Figure 4: Visualization of the distributions of alignment masks. (Left): the estimated masks for the primary dataset using AVSpeech audio with Pyroomacoustics. (Right): the estimated masks for the CHiME-3 dataset.

256 via the Hann window. The results are presented in Table 2. It can be seen that the single-channel methods do not perform well even with a larger model size. The FaSNet, with a lighter model, performs slightly better than the two single-channel approaches when the number of microphones is larger. Finally, our proposed AFnet outperforms all the SOTA approaches by significant amount in all the metrics used, while being of the smallest model size. The results demonstrate the superiority of the AFnet for enhancing speech in noisy environments.

Although a less ideal dataset for our study on spatial characteristics, we still benchmark the AFnet with several SOTAs on the CHiME-3 dataset: **Nerual BF** (Erdogan et al., 2016), **MVDR**$_{GC}$ (Bu et al., 2019), **rSDFCN** (Liu et al., 2020), **CA Dense U-Net** (Tolooshams et al., 2020), and **IC Conv-TasNet** (Lee et al., 2021). In Table 3 we report the PESQ and STOI taken from the corresponding papers and the missing entries in the table indicate that the metric is not reported in the reference paper (we do not report SSNR as most papers do not report it). We present both results of the AFnet trained with and without RTF supervision (with the 5-th channel selected as the reference microphone). One can see that the two-stage, sequential masking design of the AFnet is efficient in that it achieves comparable or better performance to other SOTA approaches while maintaining a small model size. Notably, the RTF supervision helps improve the AFnet performance, while the gains are minor in this case due to the less spatial diversity of the speech data. Nevertheless, the results still show the benefit of incorporating signal alignment into the network design, even though on a dataset with limited positional variety of the speech target.

Table 2: SE comparison with SOTA methods on the primary dataset.

Methods	# Params	PESQ	STOI	SSNR
Noisy	-	1.21	0.577	-1.70
Conv-TasNet	8.7M	1.47	0.636	3.00
DCUnet	7.6M	1.49	0.660	2.91
FaSNet (2-mic)		1.55	0.663	3.70
FaSNet (4-mic)	2.8M	1.57	0.667	3.64
FaSNet (8-mic)		1.64	0.683	3.66
AFnet (2-mic)		1.84	0.728	5.06
AFnet (4-mic)	2.6M	1.92	0.739	5.26
AFnet (8-mic)		1.99	0.753	5.35

Table 3: SE comparison with SOTA methods on the CHiME-3 dataset.

Methods	# Params	PESQ	STOI
Noisy	-	1.27	0.870
Neural BF	-	2.29	-
$MVDR_{GC}$	0.5M	-	0.952
rSDFCN	2.1M	2.15	0.937
CA Dense U-Net	>20M	2.44	-
IC Conv-TasNet	1.7M	2.67	0.973
AFnet w/o RTF Loss (ours)	2.6M	2.68	0.972
AFnet (ours)		2.72	0.972

4.2.5 RESULTS ON REAL-WORLD MEASURED ROOM IMPULSE RESPONSE GENERATED DATA

The results presented in previous sections on the primary dataset are based on the multichannel audio data synthesized by using the image source method via the Pyroomacoustics library, which is useful for methodological study but also has its limitation to represent real data. To further validate the proposed approach's generalization capabilities to more realistic scenarios, we also conduct experiments on multichannel audio data generated using real-world measured acoustic room impulse responses taken from the work of Hadad et al. (2014), where the impulse responses of several 8-channel linear microphone arrays with respect to various target source directions of arrival (DoAs) (from -90 to 90 degrees) are provided. We utilize the 3-3-3-8-3-3-3 array impulse responses of the dataset including reverberation time of 0.16, 0.36, and 0.61 second cases, together with the AVSpeech utterances and the YouTube noise profiles to generate the multichannel noisy data for experiments. To observe the relation of the AFnet performance with the speech source spatial diversity, we generate a spatially diverse dataset where the speech DoA ranges from -90 to 90 degrees, and another spatially constant dataset where the speech comes from only one direction.

Table 4 and Table 5 present the results for the two datasets respectively. One can see that for for the spatially diverse dataset of Table 4, the AFnet clearly benefits from the sequentially masking mechanism and the RTF loss supervision, while for the spatially constant dataset of Table 5 the three models perform comparably with the RTF loss marginally improves AFnet. These results show that a model (such as the W-Net) that performs well on a dataset lacking spatial variety of the target speech may not generalize well to a spatially diverse dataset, unless further attention is paid to exploiting spatial characteristics of the speech sources. The RTF information leveraged by the two-stage sequential masking design of the AFnet is shown to take advantage of the spatial separability for enhanced SE performance on spatially diverse datasets.

Table 4: Results on spatially diverse multichannel data generated using measured acoustic room impulse responses where the target speech DoA range is $[-90, 90]$ degrees.

Methods	PESQ	STOI	SSNR
Noisy	1.40	0.598	-0.91
W-Net for filter weights	1.89	0.693	3.20
AFnet w/o RTF Loss	2.06	0.728	3.83
AFnet	2.22	0.759	4.16

Table 5: Results on spatially constant multichannel data generated using measured acoustic room impulse responses where the target speech DoA is fixed to one direction.

Methods	PESQ	STOI	SSNR
Noisy	1.42	0.609	-0.51
W-Net for filter weights	1.93	0.708	3.81
AFnet w/o RTF Loss	1.93	0.702	3.95
AFnet	1.99	0.717	3.40

5 CONCLUSION

In this paper, we presented the AFnet, a deep learning based multichannel SE approach featuring a two-stage, sequential masking design, that leverages spatial information inherent in the RTFs for signal alignment, an essential factor in many conventional signal processing SE algorithms. The effect of target speech spatial diversity of the dataset and the importance of spatial alignment on deep learning based methods were analyzed and discussed. Our findings suggest that signal alignment plays a crucial role in deep learning based multichannel SE approaches when the target speech may come from arbitrary locations, especially when there are more microphones, and that it would be beneficial to consider such alignment aspect when developing future multichannel SE systems.

REFERENCES

J. Barker, R. Marxer, E. Vincent, and S. Watanabe. The third 'CHiME' speech separation and recognition challenge: Dataset, task and baselines. In *Proceedings of IEEE Workshop on Automatic Speech Recognition and Understanding (ASRU)*, pp. 504–511, 2015.

A. Benichoux, L. S. R. Simon, E. Vincent, and R. Gribonval. Convex regularizations for the simultaneous recording of room impulse responses. *IEEE Transactions on Signal Processing*, 62(8): 1976–1986, 2014.

S. Braun and I. Tashev. A consolidated view of loss functions for supervised deep learning-based speech enhancement. In *Proceedings of International Conference on Telecommunications and Signal Processing (TSP)*, pp. 72–76, 2021.

S. Bu, Y. Zhao, and M.-Y. Hwang. A novel method to correct steering vectors in MVDR beamformer for noise robust ASR. In *Proceedings of the Annual Conference of the International Speech Communication Association (Interspeech)*, pp. 4280–4284, 2019.

J. Capon. High-resolution frequency-wavenumber spectrum analysis. *Proceedings of the IEEE*, 57 (8):1408–1418, 1969.

H.-S. Choi, J.-H. Kim, J. Huh, A. Kim, J.-W. Ha, and K. Lee. Phase-aware speech enhancement with deep complex U-Net. In *Proceedings of International Conference on Learning Representations (ICLR)*, 2018.

I. Cohen. Relative transfer function identification using speech signals. *IEEE Transactions on Speech and Audio Processing*, 12(5):451–459, 2004.

S. Doclo, W. Kellermann, S. Makino, and S. E. Nordholm. Multichannel signal enhancement algorithms for assisted listening devices: Exploiting spatial diversity using multiple microphones. *IEEE Signal Processing Magazine*, 32(2):18–30, 2015.

A. Ephrat, I. Mosseri, O. Lang, T. Dekel, K. Wilson, A. Hassidim, W. T. Freeman, and M. Rubinstein. Looking to listen at the cocktail party: A speaker-independent audio-visual model for speech separation. *ACM Transactions on Graphics*, 37(4):109:1–109:11, 2018.

H. Erdogan, J. R. Hershey, S. Watanabe, M. Mandel, and J. Le Roux. Improved MVDR beamforming using single-channel mask prediction networks. In *Proceedings of the Annual Conference of the International Speech Communication Association (Interspeech)*, pp. 1981–1985, 2016.

O. L. Frost. An algorithm for linearly constrained adaptive array processing. *Proceedings of the IEEE*, 60(8):926–935, 1972.

S. Gannot and I. Cohen. Speech enhancement based on the general transfer function GSC and postfiltering. *IEEE Transactions on Speech and Audio Processing*, 12(6):561–571, 2004.

S. Gannot, D. Burshtein, and E. Weinstein. Signal enhancement using beamforming and nonstationarity with applications to speech. *IEEE Transactions on Signal Processing*, 49(8):1614–1626, 2001.

R. Giri, B. D. Rao, F. Mustiere, and T. Zhang. Dynamic relative impulse response estimation using structured sparse Bayesian learning. In *IEEE International Conference on Acoustics, Speech, and Signal Processing (ICASSP)*, pp. 514–518, 2016.

R. Giri, T. A. Srikrishnan, B. D. Rao, and T. Zhang. Empirical bayes based relative impulse response estimation. *The Journal of the Acoustical Society of America*, 143(6):3922–3933, 2018.

L. Griffiths and C. Jim. An alternative approach to linearly constrained adaptive beamforming. *IEEE Transactions on Antennas and Propagation*, 30(1):27–34, 1982.

E. Hadad, F. Heese, P. Vary, and S. Gannot. Multichannel audio database in various acoustic environments. In *International Workshop on Acoustic Signal Enhancement (IWAENC)*, pp. 313–317, 2014.

R. Haeb-Umbach, S. Watanabe, T. Nakatani, M. Bacchiani, B. Hoffmeister, M. L. Seltzer, H. Zen, and M. Souden. Speech processing for digital home assistants: Combining signal processing with deep-learning techniques. *IEEE Signal Processing Magazine*, 36(6):111–124, 2019.

J. H. L. Hansen and B. L. Pellom. An effective quality evaluation protocol for speech enhancement algorithms. In *Proceedings of International Conference on Speech and Language Processing (ICSLP)*, volume 7, pp. 2819–2822, 1998.

ITU-T Recommendation P.862.2. Wideband extension to recommendation P.862 for the assessment of wideband telephone networks and speech codecs. *International Telecommunication Union*, 2005.

J. Kim, M. El-Khamy, and J. Lee. T-GSA: Transformer with Gaussian-weighted self-attention for speech enhancement. In *Proceedings of IEEE International Conference on Acoustics, Speech, and Signal Processing (ICASSP)*, pp. 6649–6653, 2020.

Z. Koldovskỳ, P. Tichavskỳ, and D. Botka. Noise reduction in dual-microphone mobile phones using a bank of pre-measured target-cancellation filters. In *IEEE International Conference on Acoustics, Speech, and Signal Processing (ICASSP)*, pp. 679–683, 2013.

Z. Koldovskỳ, J. Málek, and S. Gannot. Spatial source subtraction based on incomplete measurements of relative transfer function. *IEEE/ACM Transactions on Audio, Speech, and Language Processing*, 23(8):1335–1347, 2015.

Y. Koyama and B. Raj. W-Net BF: DNN-based beamformer using joint training approach. *arXiv preprint arXiv:1910.14262*, 2019.

A. Krueger, E. Warsitz, and R. Haeb-Umbach. Speech enhancement with a GSC-like structure employing eigenvector-based transfer function ratios estimation. *IEEE Transactions on Audio, Speech, and Language Processing*, 19(1):206–219, 2010.

B. Laufer, R. Talmon, and S. Gannot. Relative transfer function modeling for supervised source localization. In *IEEE Workshop on Applications of Signal Processing to Audio and Acoustics (WASPAA)*, pp. 1–4, 2013.

D. Lee, S. Kim, and J.-W. Choi. Inter-channel Conv-TasNet for multichannel speech enhancement. *arXiv preprint arXiv:2111.04312*, 2021.

X. Li, L. Girin, R. Horaud, and S. Gannot. Estimation of the direct-path relative transfer function for supervised sound-source localization. *IEEE/ACM Transactions on Audio, Speech, and Language Processing*, 24(11):2171–2186, 2016.

Y. Lin, J. Chen, Y. Kim, and D. D. Lee. Blind channel identification for speech dereverberation using l_1-norm sparse learning. *Advances in Neural Information Processing Systems (NIPS)*, 20, 2007.

C.-L. Liu, S.-W. Fu, Y.-J. Li, J.-W. Huang, H.-M. Wang, and Y. Tsao. Multichannel speech enhancement by raw waveform-mapping using fully convolutional networks. *IEEE/ACM Transactions on Audio, Speech, and Language Processing*, 28:1888–1900, 2020.

P. C. Loizou. *Speech Enhancement: Theory and Practice*. Boca Raton, FL, USA: CRC Press, 2007.

X. Lu, Y. Tsao, S. Matsuda, and C. Hori. Speech enhancement based on deep denoising autoencoder. In *Proceedings of the Annual Conference of the International Speech Communication Association (Interspeech)*, volume 2013, pp. 436–440, 2013.

Y. Luo and N. Mesgarani. Conv-TasNet: Surpassing ideal time-frequency magnitude masking for speech separation. *IEEE/ACM Transactions on Audio, Speech, and Language Processing*, 27(8):1256–1266, 2019.

Y. Luo, Z. Chen, N. Mesgarani, and T. Yoshioka. End-to-end microphone permutation and number invariant multi-channel speech separation. In *Proceedings of IEEE International Conference on Acoustics, Speech, and Signal Processing (ICASSP)*, pp. 6394–6398, 2020.

M. Parchami, W.-P. Zhu, B. Champagne, and E. Plourde. Recent developments in speech enhancement in the short-time Fourier transform domain. *IEEE Circuits and Systems Magazine*, 16(3): 45–77, 2016.

S. Pascual, A. Bonafonte, and J. Serra. SEGAN: Speech enhancement generative adversarial network. In *Proceedings of the Annual Conference of the International Speech Communication Association (Interspeech)*, pp. 3642–3646, 2017.

O. Ronneberger, P. Fischer, and T. Brox. U-Net: Convolutional networks for biomedical image segmentation. In *Proceedings of International Conference on Medical image computing and computer-assisted intervention (MICCAI)*, pp. 234–241. Springer, 2015.

T. N. Sainath, R. J. Weiss, K. W. Wilson, B. Li, A. Narayanan, E. Variani, M. Bacchiani, I. Shafran, A. Senior, K. Chin, A. Misra, and C. Kim. Multichannel signal processing with deep neural networks for automatic speech recognition. *IEEE/ACM Transactions on Audio, Speech, and Language Processing*, 25(5):965–979, 2017.

R. Scheibler, E. Bezzam, and I. Dokmanić. Pyroomacoustics: A python package for audio room simulation and array processing algorithms. In *Proceedings of IEEE International Conference on Acoustics, Speech, and Signal Processing (ICASSP)*, pp. 351–355, 2018.

T. A. Srikrishnan, B. D. Rao, R. Giri, and T. Zhang. Improved noise characterization for relative impulse response estimation. In *IEEE International Conference on Acoustics, Speech, and Signal Processing (ICASSP)*, pp. 411–415, 2018.

C. H. Taal, R. C. Hendriks, R. Heusdens, and J. Jensen. An algorithm for intelligibility prediction of time-frequency weighted noisy speech. *IEEE Transactions on Audio, Speech, and Language Processing*, 19(7):2125–2136, 2011.

B. Tolooshams, R. Giri, A. H. Song, U. Isik, and A. Krishnaswamy. Channel-attention dense U-Net for multichannel speech enhancement. In *Proceedings of IEEE International Conference on Acoustics, Speech, and Signal Processing (ICASSP)*, pp. 836–840, 2020.

H. L. Van Trees. *Optimum Array Processing: Part IV of Detection, Estimation, and Modulation Theory*. Honoken, NJ, USA: John Wiley & Sons, 2004.

E. Variani, T. N Sainath, I. Shafran, and M. Bacchiani. Complex linear projection (CLP): A discriminative approach to joint feature extraction and acoustic modeling. In *Proceedings of the Annual Conference of the International Speech Communication Association (Interspeech)*, pp. 808–812, 2016.

D. Wang and J. Chen. Supervised speech separation based on deep learning: An overview. *IEEE/ACM Transactions on Audio, Speech, and Language Processing*, 26(10):1702–1726, 2018.

Z.-Q. Wang and D. Wang. Mask weighted STFT ratios for relative transfer function estimation and its application to robust ASR. In *Proceedings of IEEE International Conference on Acoustics, Speech, and Signal Processing (ICASSP)*, pp. 5619–5623. IEEE, 2018.

D. S. Williamson, Y. Wang, and D. Wang. Complex ratio masking for monaural speech separation. *IEEE/ACM Transactions on Audio, Speech, and Language Processing*, 24(3):483–492, 2015.

K. Wilson, M. Chinen, J. Thorpe, B. Patton, J. Hershey, R. A. Saurous, J. Skoglund, and R. F. Lyon. Exploring tradeoffs in models for low-latency speech enhancement. In *Proceedings of International Workshop on Acoustic Signal Enhancement (IWAENC)*, pp. 366–370, 2018.

X. Xia and B. Kulis. W-Net: A deep model for fully unsupervised image segmentation. *arXiv preprint arXiv:1711.08506*, 2017.

C. Zheng, X. Peng, Y. Zhang, S. Srinivasan, and Y. Lu. Interactive speech and noise modeling for speech enhancement. In *Proceedings of the AAAI Conference on Artificial Intelligence (AAAI)*, pp. 14549–14557, 2021.

A IMPLEMENTATION DETAILS

A.1 PRIMARY DATASET

Corpus: We use Audio-Visual Speech Dataset (AVSpeech) (Ephrat et al., 2018) available online. AVSpeech is a large collection of video clips of single speakers talking with no audio background interference. The audio files of the AVSpeech dataset serve as proper target speech files due to their variety (diversity of language, gender, age, etc.) The dataset can be found at: https://looking-to-listen.github.io/avspeech/.

Noise data: We collected 8 types of noise profiles from YouTube which are commonly seen sound sources in daily life. The noise types include blender, vacuum, washer, baby cry (for training) and dog barking, kids playing sound, hair dryer, food sizzling (for testing). Each type of noise profile contains recordings from different sound sources of the same type.

Data pre-processing: All the raw audio data are first converted to 16 kHz mono .wav files before feeding to the room acoustic simulator to generate the multichannel data samples for experimentation (the AVSpeech audio originally may contains 1 or 2 channels of audio). For spectral processing, we use the Hann window with 512-point FFT and a hop size of 256 for the STFT. By conjugate symmetry of the FFT, only half of the frequency bins (i.e., 257) are actually needed for the network to process the spectrograms.

Room acoustic simulator: Pyroomacoustics is utilized to generate multichannel audio which can be found at https://github.com/LCAV/pyroomacoustics/tree/pypi-release. We create a room of size $8 \times 8 \times 3$ (length×width×height in meters). Reverberation time is randomly chosen from $\{0.16, 0.32, 0.48, 0.64\}$ second. The room impulse responses are estimated based on the image source method. 8 microphones are placed to form a planar array (4 columns, 2 rows) vertically, where the distance between adjacent microphones is set to 5 cm. The microphone array center is placed at the center of the room. Speech and noise signals are randomly positioned at a distance of $\{1, 2, 3, 4\}$ meters from the microphone array center. In the experiments, the upper leftmost and rightmost microphones are used for the 2-mic scheme, the microphones at the four corners are used for the 4-mic scheme, and all microphones are used for the 8-mic scheme.

Measured room impulse responses: To further validate the proposed approach's generalization capabilities to more realistic scenarios, we also conduct experiments on multichannel audio data generated using real-world measured acoustic room impulse responses. A popular multichannel impulse response dataset is from the work by Hadad et al. (2014), where the impulse responses of several 8-channel microphone arrays with respect to various target source directions (from -90 to 90 degrees) are provided. We utilize the 3-3-3-8-3-3-3 array impulse responses of the dataset including reverberation time of 0.16, 0.36, and 0.61 second cases (https://www.iks.rwth-aachen.de/en/research/tools-downloads/databases/multi-channel-impulse-response-database/), together with the AVSpeech utterances and the YouTube noise profiles to generate the multichannel noisy data for experiments.

Network architectures:

- **AFnet:** the implementation of AFnet (Figure 1) is based on the deep complex U-Net model at: https://github.com/sweetcocoa/DeepComplexUNetPyTorch, for both the Align Net and Filter Net parts. The number of layers and the number of features in each layer are modified to the one shown in Figure 1, where $C_1, C_2, C_3, C_4 = 32, 64, 64, 64$.

- **Conv-TasNet**: the experimental results of Conv-TasNet is based on the implementation from https://github.com/kaituoxu/Conv-TasNet using their own model settings instead of the original Conv-TasNet paper. Note that although the model hyperparameters were designed based on 8 kHz sampling rate, we directly use them for 16 kHz sampling rate of our data without further modifications.

- **DCUnet**: the experimental results of DCUnet is based on the implementation of the code at https://github.com/mhlevgen/DCUNetTorchSound. We choose the Large-DCUnet-20 model which realizes the 20-layer model in the original DCUnet paper. Note that although in the original system a 1024-point FFT was used, here we use 512-point FFT instead.

- **FaSNet**: the experimental results of FaSNet is based on the implementation of the code at: https://github.com/yluo42/TAC. We choose to use the FaSNet_TAC model where TAC stands for transform-average-concatenate.

Model optimization: All experiments were run on one NVIDIA Tesla V100 GPU of 32 GB CUDA memory.

- **AFnet training:** the AFnet is trained via the RTF-aware training scheme. The Adam optimizer is used for minimizing $\mathcal{L}_{rtf}$ with a total of 80 epochs, where for the first 50 epochs a learning rate of 0.001 is used and for the rest 30 epochs it is decreased to 0.0001. For minimizing $\mathcal{L}_{rec}$ we train the network for another 55 epochs with Adam, where for the first 50 epochs a learning rate of 0.001 is used and for the rest 5 epochs it is decreased to 0.0001. The total number of epochs is 80+55=135.

- **AFnet training (w/o RTF supervision):** the AFnet trained without RTF loss is just minimizing $\mathcal{L}_{rec}$. In this case, the Adam optimizer with a learning rate of 0.001 is used, which is decreased to 0.0001 at the 50-th epoch, and with a total of 80 epochs.

- **Conv-TasNet, DCUnet, and FaSNet training:** for fair comparison purposes, the training of the SOTA methods is same by minimizing the reconstruction loss $\mathcal{L}_{rec}$ using 512-point FFT with a hop size of 256 via the Hann window (same STFT setting as AFnet). For the time-domain approaches (Conv-TasNet and FaSnet), the waveform of the model output is converted to STFTs for computing the loss. In all cases, the Adam optimizer with a learning rate of 0.001 is used, which is decreased to 0.0001 at the 50-th epoch, and with a total of 80 epochs.

A.2 CHIME-3 DATASET

Dataset: The publicly available CHiME-3 dataset (Barker et al., 2015), made available as part of a speech separation and recognition challenge, is used for training and evaluating SE performance. The dataset is a 6-channel microphone recording of talkers speaking in a noisy environment, sampled at 16 kHz. It consists of 7,138 and 1,320 simulated utterances with an average length of 3 seconds for training and testing, respectively.

SOTAs to compare:

- **Nerual BF** (Erdogan et al., 2016): An MVDR beamforming with mask estimation through bidirectional-LSTM.

- **MVDR$_{GC}$** (Bu et al., 2019): An MVDR beamforming using a neural network based method to identify and correct phase errors in the steering vector.

- **rSDFCN** (Liu et al., 2020): A time-domain, fully convolutional network (FCN) with sinc and dilated convolutional layers for multichannel SE.

- **CA Dense U-Net** (Tolooshams et al., 2020): A time-frequnecy domain multichannel SE model that combines the merits of DenseNet, U-Net, and channel attention (CA) mechanism.

- **IC Conv-TasNet** (Lee et al., 2021): The Inter-Channel (IC) Conv-TasNet is the extension of the time-domain Conv-TasNet for single-channel SE to the multichannel SE case.

Spectral processing: We use the Hann window with 1024-point FFT and a hop size of 256 for the STFT. By conjugate symmetry of the FFT, only half of the frequency bins (i.e., 513) are actually needed for the network to process the spectrograms.

Model optimization: The AFnet training was run on one NVIDIA Tesla V100 GPU of 32 GB CUDA memory using the same model optimization scheme discussed in Section A.1.

A.3 EVALUATION METRICS

PESQ: a speech quality measure using the wide-band version recommended in ITU-T P.862.2. It basically models the mean opinion scores (MOS) that cover a scale from 1 (bad) to 5 (excellent). We use the Python-based PESQ implementation from: https://github.com/ludlows/python-pesq.

STOI: a function that well represents the average intelligibility of the degraded speech. It provides a value from 0 to 1, which can be interpreted as the percentage of correctly recognized words by normal-hearing people. We use the Python-based STOI implementation from: https://github.com/mpariente/pystoi.

SSNR: an SNR measure, instead of working on the whole signal, that calculates the average of the SNR values of short segments. We use the Python-based SSNR implementation from: https://github.com/schmiph2/pysepm.

B ADDITIONAL EXPERIMENTAL RESULTS

B.1 IMPORTANCE OF MAGNITUDE AND PHASE ESTIMATION IN RTF ALIGNMENT

It would be interesting to look at how the magnitude and phase components of the RTFs, which correspond to ILD and ITD in time domain, affect the enhancement performance of the AFnet. In Figure 5 we compare four different RTF alignment schemes – no alignment, aligning RTF magnitude only, aligning RTF phase only, and aligning everything for the RTF loss $\mathcal{L}_{rtf}$. From the results it can be seen that phase alignment is the key to obtaining improved performance over the alignment-agnostic system. This is reasonable as aligning phase in the frequency domain corresponds to compensating the delay in the time domain, which is crucial for any beamforming algorithms that rely on spatial separability. The results suggest that the AFnet indeed exploits spatial information for improved enhancement performance.

Figure 5: Comparison of different RTF alignment schemes for AFnet training. It can be seen that aligning the phase is the key factor for obtaining significant improvement over the alignment-agnostic system.

B.2 ENHANCEMENT PERFORMANCE VS. INPUT SNR CONDITION COMPARISON

To look more into the testing results, we present the PESQ, STOI, and SSNR performance numbers vs. input SNR conditions in Figure 6 for the three schemes:

  i) **AFnet:** the two-stage AFnet model trained with the RTF-aware training scheme
  ii) **AFnet w/o RTF loss:** the two-stage AFnet model trained with normal training scheme without incorporating RTFs
  iii) **W-Net for filter weights:** using a W-Net (same model as the AFnet, but the output of the first U-Net block goes directly to the next U-Net block without multiplying the input signals) to estimate the filter weights W_i in typical (one-stage) multichannel SE

We take 160 utterances for each specified input SNR value from the test set and obtain the corresponding performance number of each input SNR value. The results for the 8-mic systems are presented. From the results we can see that the proposed AFnet consistently improves the baseline method over a wide range of input SNR conditions.

Figure 6: Speech enhancement performance vs. input SNR conditions.

C ALIGN NET VS. CONVENTIONAL SIGNAL PROCESSING APPROACHES FOR RTF ESTIMATION

In this section, we study how effective the deep leaning based Align Net for estimating the RTFs compared to conventional model-based signal processing methods in the presence of noise. We show that the Align Net performs reasonably well in the low SNR regime where signal processing approaches fail to, justifying its usage of alignment purposes for later enhancement processing in AFnet. To our best knowledge, it is the first work that utilizes the neural network for direct RTF estimation in the SE task[1].

C.1 RTF ESTIMATION PROBLEM

RTFs or their time-domain counterparts, relative impulse responses (ReIRs) are important tools in several multichannel audio processing tasks (Gannot & Cohen, 2004; Laufer et al., 2013). The estimation of RTFs has been studied for a while in the audio signal processing field (Gannot et al., 2001; Koldovský et al., 2015; Giri et al., 2016; 2018; Srikrishnan et al., 2018), where the task is to estimate the correlation between the target source components received by the two microphones, either in terms of RTFs or ReIRs, given the noisy recordings. Following the previous works, we will discuss the scenario with two microphones (i.e., left and right microphones) while the idea may be generalized to more microphones.

Consider a two-channel noisy recording of a target speech in a noisy environment, whose position is fixed for a certain time interval. This situation can be represented as:

$$x_L(n) = \underbrace{h_L(n) * s(n)}_{s_L(n)} + v_L(n),$$
$$x_R(n) = \underbrace{h_R(n) * s(n)}_{s_R(n)} + v_R(n), \tag{3}$$

where n is the time sample index taking values $1, \ldots, N$; $*$ denotes the convolution; x_L and x_R are, respectively, the signals from the left (L) and right (R) microphones; h_L and h_R are the impulse responses between the target and the two microphones; s is the far-field target speech; and v_L and v_R are the noise components.

Let h_{rel} represent the ReIR between the speech signal components arriving at the two microphones, we have following relation:

$$x_L(n) = h_{rel}(n) * x_R(n) + \underbrace{[v_L(n) - h_{rel}(n) * v_R(n)]}_{v}. \tag{4}$$

The main goal is to estimate h_{rel} given x_L and x_R. The issue is in the presence of noise v the estimation becomes challenging. The oracle ReIR is given as $h_{rel} = h_L * h_R^{-1}$, where h_R^{-1} denotes the filter inverse to h_R. To ensure that the solution is causal, a fixed delay of a few milliseconds can be introduced (Lin et al., 2007; Koldovský et al., 2013), i.e., $h_{rel} = h_L * h_R^{-1} * \delta(n - D)$, where

---

[1]The work of Wang & Wang (2018) also uses neural networks to estimate RTFs, but in an indirect manner, where an intermediate time-frequency mask is first estimated and then used for computing RTFs.

$\delta(\cdot)$ is the unit impulse function and D is the delay in samples. In the STFT domain, (4) can be equivalent to:

$$X_L(f,t) = H_{rel}(f)X_R(f,t) + V(f,t), \tag{5}$$

where the oracle RTF is given by:

$$H_{rel}(f) = \frac{H_L(f)}{H_R(f)}. \tag{6}$$

The goal again is to estimate H_{rel} given the microphone signals X_L and X_R. Note that under the assumption that the source position is fixed, we have the transfer functions independent of the time (thus omitting the index t).

C.2 METHODS

Signal processing based methods

- **Frequency-domain approaches:** The RTF estimation problem can be addressed in the frequency domain by utilizing signal and noise statistics, i.e., using the power spectral density (PSD) entities. To deal with noise, Gannot et al. (2001) propose the non-stationarity based frequency domain (NSFD) method relying on the assumption that noise signals are stationary, or less dynamic, when compared to the target speech signal. To be more exact, let $\Phi_{AB}(f,t)$ denote the (cross)-PSD between A and B during the t-th frame, we have:

$$\Phi_{X_L X_R}(f,t) = H_{rel}(f)\Phi_{X_R X_R}(f,t) + \Phi_{V X_R}(f,t). \tag{7}$$

  Assuming over $t = 1, \ldots, P$ frames the the noise is stationary, we can write $\Phi_{V X_R}(f,t) = \Phi_{V X_R}(f)$ and solve the overdetermined set of equations:

$$\begin{bmatrix} \Phi_{X_L X_R}(f,1) \\ \vdots \\ \Phi_{X_L X_R}(f,P) \end{bmatrix} = \begin{bmatrix} \Phi_{X_R X_R}(f,1) & 1 \\ \vdots & \\ \Phi_{X_R X_R}(f,P) & 1 \end{bmatrix} \begin{bmatrix} H_{rel}(f) \\ \Phi_{V X_R}(f) \end{bmatrix}. \tag{8}$$

  In practice the PSDs in the above set of equations are replaced by their sample estimates.

- **Time-domain approaches:** The ReIR estimation problem can be formulated in the time domain as: $\mathbf{h}_{rel} = \arg\min_{\mathbf{h} \in \mathbb{R}^M} \mathcal{L}(\mathbf{x}_L, \mathbf{X}_R \mathbf{h})$, where $\mathbf{x}_L = [x_L(1-D), \ldots, x_L(N-D)]^T$ and D is an integer delay for causality, and $\mathbf{X}_R$ is the convolution matrix of dimensions $N \times M$ constructed from $\mathbf{x}_R$. When the cost function $\mathcal{L}(\cdot, \cdot)$ is the squared Euclidean distance, the problem can be solved by least squares (noise-free) or regularized least squares (noisy) methods. To better handle the noise, prior knowledge about the ReIR can be leveraged to improve the estimation, e.g., utilizing the structural sparsity of ReIRs. One popular approach is the weighted ℓ_1 approach (Benichoux et al., 2014; Koldovský et al., 2015; Giri et al., 2018):

$$\mathbf{h}_{rel} = \arg\min_{\mathbf{h} \in \mathbb{R}^M} \|\mathbf{x}_L - \mathbf{X}_R \mathbf{h}\|_2^2 + \lambda \|\mathbf{w} \odot \mathbf{h}\|_1, \tag{9}$$

  where $\mathbf{w} = [w_1, \ldots, w_M]^T$ is a vector of non-negative weights and $\odot$ denotes the Hadamard product. To mimic the expected structure of a ReIR, the weights are chosen as follows:

$$w_i = k_1 e^{k_2|i-D|^{k_3}}, i = 1, \ldots, M, \tag{10}$$

  where k_1, k_2, and k_3 are positive constants and D is the integer delay.

Deep learning based approach (proposed Align Net): In the proposed AFnet, the first half Align Net is utilized to perform signal alignment by estimating RTFs, which can be viewed as a deep learning based RTF estimation method. By exploiting the power of complex-valued deep networks for predicting the RTFs, the data-driven approach Align Net can be shown to outperform conventional model-based signal processing approaches under noisy environments.

C.3 EXPERIMENTS

Settings: We generate 2-mic noisy data using Pyroomacoustics library for conducting the RTF estimation experiments. We create a room of size $8 \times 8 \times 3$ (length$\times$width$\times$height in meters). Reverberation time is randomly chosen from $\{0.16, 0.32, 0.48, 0.64\}$ second. The simulating approach for estimating room impulse responses is based on the image source method. The two microphones are placed with a distance of 15 cm in between, where the center is placed at a distance of 1 meter to one of the walls, with a height of 1.525 meters, and the array is positioned horizontally to the wall with equal distance to the two sides. Speech and noise signals are randomly positioned at a distance of $\{1, 2, 3, 4\}$ meters from the microphone array. 649 files from the training set of AVSpeech dataset are used for training the Align Net and 160 files from the testing set are used for evaluating the competing algorithms (i.e., Align Net, time-domain weighted ℓ_1 approach, and NSFD approach). 4 types of commonly seen interference (blender, vacuum, washer, baby cry) are used for training and another 4 types (dog barking, kids playing sound, hair dryer, food sizzling) are used for testing. Each type of noise is multiplied with a scale randomly chosen from $\{0, 0.5, 1, 1.5, 2\}$ before added up, and the combined noise is then added to the clean speech according to a specific SNR level randomly selected from $\{-10, -6, -3, 0, 3, 6, 10\}$ dB for training and $\{0, 5, 10, 15\}$ dB for testing.

For the freqency-domain approaches (Align Net and NSFD) we use the Hann window with 512-point FFT and a hop size of 256 for the STFT. For Align Net we use $C_1, C_2, C_3, C_4 = 32, 64, 64, 64$ and train for the RTF loss $\mathcal{L}_{rtf}$. For NSDF we use 250 frames as a processing block and smoothing over 5 frames for computing the PSD entities. For the time-domain weighted ℓ_1 we use $k_1 = 0.1$, $k_2 = 0.11$ and $k_3 = 0.3$ with $\lambda = 0.0001$; and a ReIR length of $M = 1024$ for each processing block of 2048 samples.

Evaluation metric: To quantitatively evaluate the competing algorithms, we use a well-known and widely used performance metric called the Attenuation Rate (ATR) (Koldovskỳ et al., 2015), which can be evaluated as the ratio between SNR_{out} and SNR_{in} in dB scale, where:

$$SNR_{in} = \frac{\sum_{i \in \{L,R\}} \sum_n [h_i(n) * s(n))]^2}{\sum_{i \in \{L,R\}} \sum_n [v_i(n)]^2} \tag{11}$$

and

$$SNR_{out} = \frac{\sum_n [h_{rel}(n) * s_R(n) - s_L(n)]^2}{\sum_n [h_{rel}(n) * v_R(n) - v_L(n)]^2} \tag{12}$$

The numerator of SNR_{out} measures the leakage of the target signal whereas the denominator measures the attenuation of the noise signal. The more negative the value (in dB) of ATR is, the better the evaluated algorithm performs.

Results: The ATR results are presented in Table 6. It can be seen that for all the methods the performance degrades as SNR decreases, since it becomes more challenging to estimate the RTF when noise is stronger. However, the proposed Align Net significantly outperforms the conventional model-based approaches over all SNR settings, indicating the effectiveness of the data-driven approach for the RTF estimation task against existing methods. In future study, improving the design of Align Net for better RTF estimation as well as its applications to other audio processing tasks (e.g., sound localization, speech separation, etc.) can be interesting topics to explore.

Table 6: Comparison of ATR results (in dB) of proposed Align Net vs. conventional signal processing based methods. The Align Net gives much better estimation outcomes for all the SNR settings.

Methods	Input SNR			
	0 dB	5 dB	10 dB	15 dB
Unprocessed	-1.33	-1.34	-1.20	-1.64
NSFD	-2.79	-3.79	-5.14	-5.78
Weighted ℓ_1	-2.15	-3.99	-5.86	-6.64
Align Net (proposed)	-5.00	-6.27	-7.79	-8.63