ENERGY-EFFICIENT SAMPLING USING STOCHASTIC MAGNETIC TUNNEL JUNCTIONS

ABSTRACT

(Pseudo)random sampling, a costly yet widely used method in (probabilistic) machine learning and Markov Chain Monte Carlo algorithms, remains unfeasible on a truly large scale due to unmet computational requirements. We introduce an energy-efficient algorithm for uniform Float16 sampling, utilizing a room-temperature stochastic magnetic tunnel junction device to generate truly random floating-point numbers. By avoiding expensive symbolic computation and mapping physical phenomena directly to the statistical properties of the floating-point format and uniform distribution, our approach achieves a higher level of energy efficiency than the state-of-the-art Mersenne-Twister algorithm by a minimum factor of 9721 and an improvement factor of 5649 compared to the more energy-efficient PCG algorithm. Building on this sampling technique and hardware framework, we decompose arbitrary distributions into many non-overlapping approximative uniform distributions along with convolution and prior-likelihood operations, which allows us to sample from any 1D distribution without closed-form solutions. We provide measurements of the potential accumulated approximation errors, demonstrating the effectiveness of our method.

1 INTRODUCTION

The widespread implementation of artificial intelligence (AI) incurs significant energy use, financial costs, and CO_2 emissions. This not only increases the cost of products, but also presents obstacles in addressing climate change. Traditional AI methods like deep learning lack the ability to quantify uncertainties, which is crucial to address issues such as hallucinations or ensuring safety in critical tasks. Probabilistic machine learning, while providing a theoretical framework for achieving much-needed uncertainty quantification, also suffers from high energy consumption and is unviable on a truly large scale due to insufficient computational resources (Izmailov et al., 2021). At the heart of probabilistic machine learning and Bayesian inference is Markov Chain Monte Carlo (MCMC) sampling (Kass et al., 1998; Murphy, 2012; Hoffman & Gelman, 2014). Although effective in generating samples from complex distributions, MCMC is known for its substantial computational and energy requirements, making it unsuitable for large-scale deployment for applications such as Bayesian neural networks (Izmailov et al., 2021). In general, random number generation is an expensive task that is required in many machine learning algorithms.

To address these challenges, this paper proposes a novel hardware framework aimed at improving energy efficiency, in particular tailored for probabilistic machine learning methods. Our framework builds on uniform floating-point format sampling utilizing stochastically switching magnetic tunnel junction (s-MTJ) devices as a foundation, achieving significant gains in both computational resources and energy consumption compared to current pseudorandom number generators. In contrast to existing generators, this device-focused strategy not only enhances sampling efficiency but also incorporates genuine randomness originating from the thermal noise in our devices. Simultaneously, this noise is crucial for the probabilistic functioning of the s-MTJs and is associated with low energy costs during operation.

We present an acceleration approach for efficiently handling probability distributions. Our experiments confirm its effectiveness by quantifying potential approximation errors. This work does not seek to create a one-size-fits-all setting for all possible probabilistic algorithms that manage proba-

bility distributions. Rather, we offer a solution approach that researchers can customize and utilize based on individual required sampling resolution dependent on a specific algorithm.

Our contributions can summarized as follows:

1. We present a novel, highly energy-efficient stochastically switching magnetic tunnel junction device which is designed to improve both the energy efficiency and precision of our sampling approach. The device is capable of generating samples from a Bernoulli distribution whose parameter p can be controlled using a current bias.

2. We present a closed-form solution that defines the parameters for a collection of Bernoulli distributions applied to the bit positions of the floating-point format, leading to samples that adhere to a distribution without the need for symbolic calculations. Our simulations indicate that this hardware configuration surpasses existing random number generators in terms of energy efficiency by a factor of 5649 when using Float16. Additionally, our method achieves genuine randomness through the use of thermal noise in our hardware devices. In general, this approach is suitable for any entropy source device or even (pseudo)random number generator that can produce bits in a reliable (and efficient) Bernoulli fashion.

3. We propose the representation of arbitrary one-dimensional distributions using a mixture of uniforms model. This approach utilizes our highly efficient hardware-supported uniform sampling approach to enable sampling from arbitrary 1D distributions. We introduce convolution and prior-likelihood transformations for this model to learn and sample from such distributions without closed-form solutions. Our experimental evaluation shows that this method is effective, as evidenced by the small approximation error in KL-divergence when compared to sampling results from known closed-form solutions (0.0343 ± 0.1473 for the convolution and 0.0141 ± 0.1073 for prior-likelihood) for basic usage scenarios.

All code of our experiments is available at www.github.com/TBA.

The structure of this paper begins by reviewing relevant work on random number generation and Markov-Chain-Monte-Carlo algorithms for probabilistic machine learning in Section 2. Section 3 provides an introduction to the floating-point format, which is the format utilized for generating samples. In the Approach Section 4, we introduce the stochastically switching magneto-tunneling junction device being utilized in our approach. Following this, we outline a configuration for these devices to generate uniform floating-point samples, addressing the statistical challenge of mapping Bernoulli distributions to specific bitstring positions within the floating-point format. Additionally, we propose our approach for representing, sampling, and converting arbitrary 1D-distributions using a mixture of uniforms as representation. Section 5 illustrates our approach through particular instances and assesses potential approximation errors arising from both the devices and our theoretical framework in the Float16 format. The paper concludes with Section 6, where we summarize our findings and outline further research directions. We used LLM-based tools to improve the writing style and code generation. All reported experiments and simulations can be performed on consumer-grade computers.

2 RELATED WORK

A majority of artificial intelligence algorithms rely on random number generators. Random number generators (RNG) are employed for weight initialization or dropout in deep learning or taking random actions in reinforcement learning. In probabilistic machine learning, Markov-Chain-Monte-Carlo (MCMC) algorithms utilize them for sampling from proposal distributions or for making decisions on whether to accept or reject samples based on random draws.

Hence, the research community focused on the development of efficient random number generators (L'Ecuyer, 1994) and their infrastructure (Tan et al., 2021; Nagasaka et al., 2018) shares similarities to this work. Physical (true) random number generators (TRNG) using physical devices is an active research field since the 1950s (L'Ecuyer, 2017). Currently used random number generators are often feasability-motivated free-running oscillators with randomness from electronic noise (Stipcevic & Koç, 2014). A very recent subfield are Quantum Based Random Number generators (QRNG) (Mannalatha et al., 2023; Józwiak et al., 2024; Stipcevic & Koç, 2014; Herrero-Collantes & Garcia-Escartin, 2017). However, it should be noted that our conceptual approach can in principle

be applied with any RNG that generates parametrizable Bernoulli distributions, given that they are sufficiently (energy-)efficient. The concept of employing stochastic magnetic tunnel junctions for random number generation has been investigated in recent years. Although these methods generally outperform traditional algorithmic random number generators in terms of energy efficiency, they lack three crucial features for machine learning applications that our approach addresses. First, they lack the ability to directly produce results using the floating-point format (Zhang et al., 2024; Chen et al., 2022; Oosawa et al., 2015; Perach et al., 2019), which is critical for machine learning applications. Converting results to floating-point format later (Fu et al., 2023) introduces unnecessary overhead, reducing energy efficiency. In general, the unequal spacing characteristic of the floating-point format complicates the transition from integers, making it non-trivial to maintain all possible floating-point number candidates within a specific distribution. Second, most works lack the flexibility to generate arbitrary distributions. Zhang et al. (2024) propose using a conditional probability table for this purpose. However, their method involves adjusting the current bias for each bit in a sample and repeating this process for every required sample, which substantially increases energy consumption. In addition, sequential operations that scale with the number of bits reduce the achievable sampling speed. Furthermore, they address integer generation only, making their work unsuitable for machine learning applications. Finally, none of the works addresses directly sampling from a product of likelihoods (distributions) as often encountered in probabilistic machine learning.

MCMC methods like Metropolis-Hastings (Hastings, 1970; Metropolis et al., 1953) and the state-of-the-art Hamiltonian Monte Carlo (HMC) (Neal et al., 2011) algorithm are crucial for this research. The use of MCMC for Bayesian inference and probabilistic machine learning represents the core application area of this paper, aiming to achieve computational and energy-efficient deployment at a large scale. Furthermore, (pseudo)random number generation is often discussed in the context of Monte Carlo approaches as they are closely intertwined and take advantage of efficient random number sampling as proposed by us. On the other hand, we propose an alternative hardware-supported approach to the MCMC algorithms themselves with our mixture model. In general, our approach differs from traditional pseudorandom number generation of MCMC algorithms as we employ a genuinely random sampling method, making it less suitable for scenarios requiring reproducibility (L'Ecuyer, 2017; Holohan, 2023; Hill, 2015) or reversability (Yoginath & Perumalla, 2018), our objectives align in efficient random number generation and genuine statistical independence.

Antunes & Hill (2024) accurately measured the energy usage of random number generators (Mersenne-Twister, PCG, and Philox) in programming languages and frameworks such as Python, C, Numpy, Tensorflow, and PyTorch, thus providing a quantification of energy consumption in tools relevant to AI. The energy measurements of this benchmark serve as baseline against our approach.

3 Preliminaries

We use the floating-point format as the number representation of interest as this is also the format that machine learning algorithms use. We define a generic floating-point number as follows:

$$x = \pm 2^{e-b} \cdot d_1.d_2 \ldots d_t, \tag{1}$$

where e is the exponent adjusted by a bias b, $d_1.d_2 \ldots d_t$ represent the mantissa, $d_i \in \{0, 1\}$, and $d_1 = 1$ indicates an implicit leading bit for normalized numbers.

While our approach is generally applicable to any floating-point format, we demonstrate the approach for the Float16 format in this paper. The use of the Float16 format compared to formats with more precision bits is advantageous in a real-world setting as it demands less rigor in setting the current bias for the s-MTJ devices, which is especially relevant for higher-order exponent bits.

In the following, we describe a Float16 number by its 16-bit organization

$$B = (b_0, b_1, \ldots, b_{15}), \tag{2}$$

where b_{15} is the sign bit, b_{14} to b_{10} are the exponent bits with a bias of 15, and b_9 to b_0 are the mantissa bits. The implicit bit remains unexpressed. This arrangement represents the actual storage format of the bits in memory. By expressing the floating-point format in terms of its bit structure, we can directly map an s-MTJ device's output bit to its equivalent position in the Float16 format.

4 APPROACH

4.1 PROBABILISTIC SPINTRONIC DEVICES

Spintronic devices are a class of computing (logic and memory) devices that harness the spin of electrons (in addition to their charge) for computation (Žutić et al., 2004). This contrasts with traditional electronic devices which only use electron charges for computation. In essence, we interpret the upwards and downwards electronic spin as binary states instead of their charge. Changing state corresponds to changing the direction of the spin. The field of spintronics holds potential for lowering energy consumption in comparison to conventional electronics. Applying insufficient current results in the electronic spin states exhibiting probabilistic behavior due to ambient temperature. In this research, we utilize this probabilistic behavior by aligning it directly with algorithmic requirements.

Spintronic devices are built using magnetic materials, as the magnetization (magnetic moment per unit volume) of a magnet is a macroscopic manifestation of its correlated electron spins. The prototypical spintronic device, called the magnetic tunnel junction (MTJ), is a three-layer device which can act both as a memory unit and a switch (Moodera et al., 1995). It consists of two ferromagnetic layers separated by a thin, insulating non-magnetic layer. When the magnetization of the two ferromagnetic layers is aligned parallel to each other, the MTJ exhibits a low resistance (R_P). Conversely, when the two magnetizations are aligned anti-parallel, the MTJ exhibits a high resistance (R_{AP}). By virtue of the two discrete resistance states, an MTJ can act as a memory bit as well as a switch. In practice, the MTJs are constructed such that one of the ferromagnetic layers stays fixed, while the other layer's magnetization can be easily toggled (free layer, FL). Thus, by toggling the FL, using a magnetic field or electric currents, the MTJ can be switched between its '0' and '1' state.

An MTJ can serve as a natural source of randomness upon aggressive scaling, i.e. when the FL of the MTJ is shrunk to such a small volume that it toggles randomly just due to thermal energy in the vicinity. It is worth noting that the s-MTJ can produce a Bernoulli distribution like probability density function (PDF), with $p = 0.5$, without any external stimulus, by virtue of only the ambient temperature. However, applying a bias current across the s-MTJ can allow tuning of the PDF through the spin transfer torque mechanism. As shown in Figure 5c-f of Appendix A, applying a positive bias current across the device makes the high resistance state more favorable, while applying a negative current has the opposite effect. In fact, by applying an appropriate bias current across the s-MTJ, using a simple current-mode digital to analog converter as shown in Figure 6a of Appendix A, we can achieve precise control over the Bernoulli parameter (p) exhibited by the s-MTJ. The p-value of the s-MTJ responds to the bias current through a sigmoidal dependence. A more detailed version of this section on the physical principles, device structure and simulations of the s-MTJ device can be found in Appendix A.

4.2 RANDOM NUMBER SAMPLING

This section describes the configuration of s-MTJ devices representing Bernoulli distributions for generating uniform random numbers in floating-point formats, particularly Float16. To apply this method to other floating-point formats, modify the number of total bits in Equation equation 3, equation 5 and equation 6 as well as the number of exponent bits in equation 8 and their positions in the format in variable e of equation 6.

The configuration C for a set of s-MTJ devices is defined as follows:

$$C = \{(b_i, p_i) \mid p_i \in [0, 1], b_i \in \{b_0, \ldots, b_{15}\}\}, \tag{3}$$

where each p_i is the parameter of a Bernoulli distribution representing the probability of the corresponding Float16 format bit being '1' in the output.

The goal is to configure C so that, with infinite resampling, the sequence B_n of Float16 values converges to a uniform distribution D over the full format. Formally, we seek C such that:

$$\lim_{n \to \infty} P(B_n = b \mid C) = D(b), \text{ where } D = \text{Uniform}(-65504, 65504) \tag{4}$$

In order to meet this condition, we need to assign each bit position b_i of the Float16 format a probability p_i, representing the frequency of each bit's occurrence in a uniform Float16 distribution

Table 1: Required 1-bit occurrences in a 3-bit exponent representation

	1-Bit Count							
e_3	0	0	0	0	2^4	2^5	2^6	2^7
e_2	0	0	2^2	2^3	0	0	2^6	2^7
e_1	0	2^1	0	2^3	0	2^5	0	2^7

(Equations equation 5-equation 8). The mantissa bits are assigned a value of 0.5, as detailed in line equation 6, ensuring uniformity across the range they cover. This method extends to the sign bit, whose equal likelihood of toggling maintains the format's symmetry.

In floating-point formats, increasing the exponent doubles the range covered by the mantissa due to the base 2 system. Higher exponent ranges need more frequent sampling to maintain uniform coverage, as simply doubling sample occurrence from one range to the next does not preserve uniformity. Table 2 shows the number of 1-bits for each exponent in a 3-bit example. In general, one can see a specific overall pattern. Specifically, e_1 has four groups of size 1, e_2 has two groups of size 2, and e_3 has one group of size 1. More generally, the first count of any exponent group is always $2^{2^{i-1}}$. For the first exponent, groups are size 1 (excludable by $\mathbf{1}_{\{i>1\}}$). For other exponents, remaining 1-Bit counts in the first group are $\sum_{k=1}^{c-1} 2^{2^{i-1}+k}$, where $c = 2^{i-1}$ is the group size, depending on the position i in the floating-point format. The count of groups based on bit position i and total bits e is $z = 2^{-i+e}$. The count sums for remaining groups are given by $\sum_{k=1}^{z-1} \sum_{g=1}^{c-1} 2^{2^{i-1}+2^i \cdot k+g}$, where z is the number of groups and c their size. The highest exponent bit e_3 with one group is excluded using $\mathbf{1}_{\{z>1\}}$. To find the probability of 1-Bit occurrences for each exponent e_i, divide by the total bits $2^{(2^e)} - 1$, which depends on the exponent bits e.

Combining everything, we derive the equation for the configuration C as follows:

$$C = \{(b_i, p_i) \mid p_i \in [0, 1], b_i \in \{b_0, \ldots, b_{15}\}, \text{ where} \tag{5}$$

$$p_i = \begin{cases} \frac{o_{i-9}}{2^{(2^e)}-1} & \text{if } i \in \{10, \ldots, 14\}, \\ 0.5 & \text{otherwise} \end{cases}, \text{ and} \tag{6}$$

$$o_i = 2^{2^{i-1}} + \sum_{k=1}^{c-1} 2^{2^{i-1}+k} \cdot \mathbf{1}_{\{i>1\}} + \sum_{k=1}^{z-1} 2^{2^{i-1}+2^i \cdot k} + \sum_{k=1}^{z-1} \sum_{g=1}^{c-1} 2^{2^{i-1}+2^i \cdot k+g} \cdot \mathbf{1}_{\{z>1\}}, \text{ and} \tag{7}$$

$$z = 2^{-i+e}, c = 2^{i-1}, e = 5. \tag{8}$$

After obtaining a sample s, min-max normalization can be applied to linearly transform it into a sample s' that adheres to any specified uniform distribution within the Float16 range:

$$s' \sim \text{Uniform}(a, b) = a + \frac{(s + 65504) \cdot (b - a)}{131008}. \tag{9}$$

The transformation must be performed in a format exceeding Float16, like Float32 or a specialized circuit, to maintain numerical stability and precision, due to exceeding Float16 limits in the denominator of Equation equation 9. We assume special cases like NaNs or Infinities are discarded.

4.3 SAMPLING AND LEARNING ARBITRARY 1D-DISTRIBUTIONS

This section addresses how to represent and sample from any arbitrary one-dimensional distribution, aiming for random and energy-efficient non-parametric sampling without closed-form solutions.

Sampling from a uniform distribution within the Float16 range is an energy-efficient method. Given that hardware representations of continuous distributions are inherently discretized during real computations, we use a mixture model of uniform distributions as distributional representation. This approach (Gao et al., 2022) is well-established for handling real-world data that standard distributions do not adequately represent. In general, mixture models of all forms are used in probabilistic machine learning to approximate multimodal and complex distributions (Murphy, 2012). We break down a distribution into several non-overlapping uniform distributions, where the approximation

error depends on the interval size. The weights of these components indicate the relative probability density of each interval within the overall distribution.

Let D be the distribution to be represented, $\mathbf{F}_{16}$ the set of Float16 values, and $U_i \sim \text{Uniform}(a_i, b_i)$ for $i = 1, 2, \ldots, k$ non-overlapping interval components of our mixture model, where each U_i is uniform on $[a_i, b_i)$ with $a_i, b_i \in \mathbf{F}_{16}$. The mixture probability density function f_U is defined by

$$D(x) = f_U(x) = \sum_{i=1}^{k} w_i f_{U_i}(x) \tag{10}$$

such that $\sum_{x \in X} w_i f_{U_i}(x) = 1$ and $w_i f_{U_i}(x)$ is the probability density function of component U_i:

$$f_{U_i}(x) = \begin{cases} \frac{1}{b_i - a_i} & \text{if } x \in [a_i, b_i) \\ 0 & \text{otherwise.} \end{cases}$$

To draw a sample from the distribution D, we first perform a uniform sampling within the interval $[0, 1]$, which is assigned to the intervals of the components according to their respective weights. From the selected component interval, we then perform another uniform sampling within that specific range. Therefore, obtaining a sample from D requires two uniform sampling steps.

Our approach is particularly suited for the concentration of statistical distributions in ranges (e.g., near zero due to data normalization). Using a high component resolution in this range ensures precise sampling, though it may cause inaccuracies further afield. We propose using a balanced number of s-MTJ devices to manage errors, offering a viable and energy-efficient solution. More research is needed to tailor distribution resolutions to specific algorithms. The effectiveness of our method is demonstrated through the analysis of cumulative approximation errors in Section 5.3.

Probabilistic machine learning relies heavily on thorough sampling from the posterior distribution. We have introduced an efficient sampling method, but operations involving two arbitrary distributions are necessary to derive a posterior distribution. Modern probabilistic machine learning mainly uses distributions that have closed-form solutions and methods for approximating unknown distributions to familiar ones. We introduce both the sum (convolution) and the computation of prior-likelihood (pointwise multiplication) as methods to facilitate the learning of posterior distributions in a non-parametric manner, bypassing the need for closed-form solutions.

In all definitions, it is assumed that the intervals $\{[a_i, b_i]\}$ in our mixture models are consistent across all represented distributions. Variations in notation (e.g., $\{[c_i, d_i]\}$) highlight different distributions.

The convolution $Z = X + Y$ for two independent random variables X and Y is defined as $f_Z(z) = \int_{-\infty}^{\infty} f_X(x) f_Y(z - x) \, dx$. For approximating the convolution using interval sets with weights, we calculate the mean of sums of interval bounds for each combination (Cartesian product). Let $\{X_i = ([a_i, b_i), w_i)\}_{i=1}^{n}$ and $\{Y_j = ([c_j, d_j), v_j)\}_{j=1}^{n}$ represent the mixture models for X and Y respectively, covering the entire Float16 range.

Calculating the means results in

$$m_{ij} = \frac{a_i + b_i}{2} + \frac{c_j + d_j}{2}, \tag{11}$$

with a combined weight:

$$u_{ij} = w_i \cdot v_j. \tag{12}$$

This intermediate set $\{(m_{ij}, u_{ij})\}_{i,j=1}^{n}$ contains pairs of mean and weight. Define $\{Z_l = ([g_l, h_l), r_l)\}_{l=1}^{n}$ as the desired distribution. Update the weights for Z_l by

$$r_l = \sum_{l=1}^{n} u_{ij} \cdot \mathbf{1}_{[g_l, h_l)}(m_{ij}), \tag{13}$$

where $\mathbf{1}_{[g_l, h_l)}(x)$ is the indicator function that is 1 if $x \in [g_l, h_l)$ and 0 otherwise. Lastly, the weights are normalized

$$r_l' = \frac{r_l}{\sum_{s=1}^{n} r_s}. \tag{14}$$

Figure 1: Hardware setup for sampling one value from a uniform Float16 distribution.

It should be noted that sampling from both normalized and unnormalized distributions yields equivalent results since normalization maintains the relative proportions within our distributions. However, it keeps the weights bounded and manageable for storage purposes.

Intermediate pairs of mean and weight for the prior-likelihood computation is obtained by

$$m_{ii} = \frac{a_i + b_i}{2} = \frac{c_i + d_i}{2}, \text{ where } a_i = c_i \text{ and } b_i = d_i \tag{15}$$

and

$$u_{ii} = w_i \cdot v_i. \tag{16}$$

Aside from above equations, the remaining algorithm is that of convolution. Note that the joint distribution is derived by simultaneously sampling from two mixture models. The components of the models remain unchanged during sampling.

5 EVALUATION

5.1 ENERGY CONSUMPTION OF THE S-MTJ APPROACH

Figure 1 depicts our hardware configuration for sampling a single Float16 value. Each d_i is an s-MTJ device. The devices $d_{10}, \cdots, d_{14}$ for the exponent are equipped with 4 control bits to adjust the current bias c_i, which corresponds to the Bernoulli probability. The other devices are set to a fixed current bias equivalent to a Bernoulli of 0.5. The resolution, which determines how accurately we can set the Bernoulli distributions for a device, is dependent on the number of control bits and is visualized in Figure 2. This Figure displays the specific Bernoulli values achievable with 4 control bits. Although additional control bits could allow for more precise settings, we restrict this number to 4 due to physical limitations in setting current biases in hardware with higher resolution while keeping the bias circuit simple (and hence energy-efficient). Our approach focuses on achieving high accuracy around a probability of 1 (cf. configuration in Section 5.2) by taking advantage of the characteristics of the sigmoid function, thus making 4 bits sufficient for achieving the required probability density function.

For our specific case, where the s-MTJs are being configured to generate a uniform distribution of Float16 samples, the p for each s-MTJ is predetermined and fixed. All the mantissa and sign bits require $p = 0.5$, which is exhibited by the s-MTJ without any current bias (cf. 4.1 and 4.2). Thus, these eleven s-MTJs do not require a current biasing circuit. The predetermined p-values for the five exponent bits correspond to specific current biases as shown in Figure 2, which amount to a total power consumption of $20.86\,\text{W}$, as determined through SPICE simulations (see Appendix C). For a sampling rate of $1\,\text{MHz}$, this corresponds to $20.86\,\text{pJ}$ biasing energy per Float16 sample. Reading the state of all sixteen s-MTJs, assuming a nominal resistance of $1\,\text{k}\Omega$ and $10\,\text{ns}$ readout with $10\,\mu\text{A}$ probe current, amounts to an additional readout energy dissipation of $16\,\text{fJ}$ per Float16 sample.

Given a hardware accelerator-style architecture, our system is designed with an embarrassingly parallel structure, capable of producing samples every $1\,\mu\text{s}$. Energy-wise, there is no difference between parallel and sequential setups. Using min-max normalization, sampled intervals can be transformed efficiently into other intervals. It is reasonable that each of the five floating point operations mentioned in Equation 9 within a normalization circuit consumes about $150\,\text{fJ}$ on modern microprocessors (Ho et al., 2023), leading to an extra energy cost of $750\,\text{fJ}$ per sample.

Consequently, generating 2^{30} samples without linear transformation yields an energy consumption

$$(16 \cdot 1\,\text{fJ} + 20.862\,\text{pJ}) \cdot 2^{30} = 22.42\,\text{mJ}. \tag{17}$$

Figure 2: Possible Bernoulli resolutions for s-MTJ device with 4 control bits.

(a) First Moment (Mean) (b) Second Moment (Variance) (c) Third Moment (Kurtosis)

Figure 3: Physical approximation error comparison for the first three moments of the uniform distribution (s-MTJ-based approach vs. closed-form solution sampling). Second moment standard deviation omitted due to equivalence to the means.

Applying the transformation yields

$$(16 \cdot 1\,\text{fJ} + 20.862\,\text{pJ} + 750\,\text{fJ}) \cdot 2^{30} = 23.22\,\text{mJ}. \tag{18}$$

Our method's energy usage is compared to actual energy measurements taken by Antunes & Hill (2024). They benchmarked advanced pseudorandom number generators like Mersenne Twister, PCG, and Philox. This includes evaluations across original C versions (O2 and O3 suffixes refer to C flags) and adaptations in Python, NumPy, TensorFlow, and PyTorch, relevant platforms and languages for AI. Each measurement reports the total energy used to produce 2^{30} pseudorandom 32-bit integers or 64-bit doubles, which are common outputs from these generators. Often, specific algorithms and implementations are limited to producing only certain numeric formats (like integers or doubles), particular bit sizes, or specific stochastic properties. As such, comparing different implementations and floating-point formats is somewhat limited. However, given that all implementations serve the same machine learning algorithms and that our energy consumption estimates show vast differences, this comparison is deemed both reasonable and significant.

Although our method introduces considerable energy costs due to transformations, the overall energy usage, when including linear transformations, is reduced by factor 5649 (pcg32integer) compared to the most efficient pseudorandom number generator currently available. Compared to the double-generating Mersenne-Twister (mt19937arO2), we obtain an improvement by factor 9721. We provide a full comparison against all benchmarked generators in Figure 7 of Appendix D.

5.2 PHYSICAL APPROXIMATION ERROR: IMPACT OF CONTROL BITS RESOLUTION

The number of control bits in an s-MTJ device impacts both energy consumption and the precision of setting the energy bias, which in turn affects the available probabilities of obtaining bit samples. Figure 2 illustrates this relationship. This section evaluates the approximation error caused by imprecision in achieving a desired Bernoulli distribution.

Four control bits allow 16 distinct, uniformly spaced current biases for an s-MTJ device. The stability of reading a '1' or '0' from the device follows a sigmoid function, enhancing resolution near 0 and 1, but reducing it around 0.5.

This effect is beneficial as it yields the configurations $c_{10}, c_{11}, \cdots, c_{14} = \{(10, 0.6666\overline{6}), (11, 0.80000), (12, 0.94118), (13, 0.99611), (14, 0.99998)\}$ for our hardware

Table 2: Approximation error comparison (mixture-based approach vs. closed-form solution)

Approach for Distribution P	$D_{\text{KL}}(P \parallel Q_{\text{closed-form}})$	$\Delta Q_{\text{closed-form}}$
Sampling $Q_{\text{closed-form}}$ Convolution	1.6932 ± 0.1032	-
Mixture-based Convolution	1.7274 ± 0.1033	0.0343 ± 0.1473
Sampling $Q_{\text{closed-form}}$ Prior-Likelihood	0.7959 ± 0.0859	-
Mixture-based Prior-Likelihood	0.8099 ± 0.0845	0.0141 ± 0.1073

setup shown in Figure 1, as derived from Equations equation 5-equation 8. Higher exponent bits demand greater precision than lower ones, highlighting the advantages of the Float16 format over larger formats due to the physical constraints in setting the energy bias.

Figure 8 of Appendix E plots samples using perfect resolution sampling and sampling that considers physical control bit boundaries. Control Bits Sampling v1 uses the closest distance, assigning equal probabilities of 0.9933 to c_{13} and c_{14}. Control Bits Sampling v2 assigns probabilities of 0.9911 to c_{13} and 0.9933 to c_{14}, testing whether a having a difference is more effective than the closest distance method (see Figure 2). All versions yield a uniform distribution without noticeable discrepancies.

To precisely analyze distribution shifts, we compared the first three moments (mean, variance, kurtosis) of the uniform Float16 distribution in Figures 3a, 3b, and 3c. We evaluated the empirical moments of these distributions against theoretical expectations using closed-form solutions. We generated $100\,000$ samples per measurement, repeating each measurement 100 times, and report the results as mean and standard deviations.

The mean values over all three moments are consistent for all bit resolutions. The observed deviations are primarily attributed to variations within the extensive Float16 scale, rather than impacts from individual approximation errors. Furthermore, the deviation in the second moment is relatively minor given its high absolute value in the closed-form expression. Based on these observations, it is evident that all versions show negligible effects of major approximation errors due to physical inaccuracies.

5.3 Conceptual Approximation Error: Impact of Mixture Model Components

This section discusses approximation errors induced by our conceptual approach due to interval resolution and transformation errors. It examines the convolution and prior-likelihood transformation of two distributions. The convolution analysis spans the interval $[-1, 1)$ with a 0.0005 resolution, comprising 4000 elements. Similarly, the prior-likelihood transformation is analyzed over the interval $[-0.5, 1.5)$ using the same resolution.

The approximation error is quantified by setting up transformations as described in Section 4.3. Control bit errors are not considered, attributing the error solely to the theoretical approach. We set up input distributions and their closed-form probability density functions. We convolved two Gaussian distributions $\mathcal{N}(0.2, 0.1^2)$ to get $\mathcal{N}(0.4, 0.1^2 + 0.1^2)$. Using a Beta$(2, 5)$ prior and a $\mathcal{N}(0.1, 0.1^2)$ likelihood, we derived the final distribution by multiplying their densities.

We evaluated the difference in outcomes between our mixture-based approach and the closed-form solution using Kullback-Leibler (KL) divergence. We used kernel density estimation with a uniform kernel and a bandwidth of 0.0005 for density estimation. To assess the inherent offset between closed-form densities and sampling-based ones due to limited sample sizes, we sampled $50\,000$ times from the Gaussian closed-form distribution. We also used rejection sampling with a uniform proposal distribution, allowing us to obtain samples from the prior-likelihood multiplication. Remaining KL discrepancies can be attributed to the approximation errors of our mixture model. We repeated these sampling-based evaluations 100 times, recording the mean and standard deviation.

Table 2 shows the approximation errors observed. As shown in Table 2, each method aligns well with the closed-form probability densities. The approximation errors due to sample size are 0.0141 ± 0.1073 for prior-likelihood transformations and 0.0343 ± 0.1473 for convolutions. The slightly higher error in convolutions is likely due to more frequent recalculations of means and weights (Cartesian product), while prior-likelihood transformations are linear (pointwise multiplication). Appendix 9 illustrates the sampled distributions for these calculations.

6 CONCLUSION AND FUTURE WORK

We introduced a hardware-driven highly energy-efficient acceleration method for transforming and sampling one-dimensional probability distributions, using stochastically switching magnetic tunnel junctions. This method includes a precise initialization for these devices for uniform random number sampling that beats current state-of-the-art Mersenne-Twister by a factor of 5649, a uniform mixture model for distribution sampling, and convolution and prior-likelihood computations to enhance learning and sampling efficiency.

We assessed the approximation error associated with the s-MTJ devices and our theoretical framework. Findings show that the physical approximation error is negligible when sampling uniform random numbers. Furthermore, the KL-divergence showed only minor variations compared to sampling from the closed-form solution, noting deviations of 0.0343 ± 0.1473 in convolution and 0.0141 ± 0.1073 in prior-likelihood operations. Our approach improves existing machine learning algorithms directly by generating random numbers with high efficiency. It also allows the development of specialized solutions designed for specific algorithms and tasks in the future. Further studies will explore specific algorithms in (probabilistic) machine learning currently unsuitable for MCMC methods and validate the s-MTJ method by building a prototype including statistical randomness testing of the device (Martínez et al., 2018; L'Ecuyer, 2017).

REFERENCES

Benjamin Antunes and David R. C. Hill. Reproducibility, energy efficiency and performance of pseudorandom number generators in machine learning: a comparative study of python, numpy, tensorflow, and pytorch implementations. *CoRR*, abs/2401.17345, 2024.

Kerem Y. Camsari, Brian M. Sutton, and Supriyo Datta. p-bits for probabilistic spin logic. *Applied Physics Reviews*, 6(1):011305, 03 2019.

Xiheng Chen, Jiabin Zhang, and Jiang Xiao. Magnetic-tunnel-junction-based true random-number generator with enhanced generation rate. *Physical Review Applied*, 18(2):L021002, 2022.

Siqing Fu, Tiejun Li, Chunyuan Zhang, Hanqing Li, Sheng Ma, Jianmin Zhang, Ruiyi Zhang, and Lizhou Wu. Rhs-trng: A resilient high-speed true random number generator based on stt-mtj device. *IEEE Transactions on Very Large Scale Integration (VLSI) Systems*, 2023.

Jianxiong Gao, Zongwen An, and Xuezong Bai. A new representation method for probability distributions of multimodal and irregular data based on uniform mixture model. *Ann. Oper. Res.*, 311 (1):81–97, 2022.

Keith Hastings. Monte carlo sampling methods using markov chains and their applications. *Biometrika*, 57(1):97–109, 1970.

Miguel Herrero-Collantes and Juan Carlos Garcia-Escartin. Quantum random number generators. *Reviews of Modern Physics*, 89(1):015004, 2017.

David R. C. Hill. Parallel random numbers, simulation, and reproducible research. *Computing in Science & Engineering*, 17(4):66–71, 2015.

Anson Ho, Ege Erdil, and Tamay Besiroglu. Limits to the energy efficiency of CMOS microprocessors. In *IEEE International Conference on Rebooting Computing, ICRC 2023, San Diego, CA, USA, December 5-6, 2023*, pp. 1–10. IEEE, 2023.

Matthew Hoffman and Andrew Gelman. The no-u-turn sampler: adaptively setting path lengths in hamiltonian monte carlo. *Journal of Machine Learning Research*, 15(1):1593–1623, 2014.

Naoise Holohan. Random number generators and seeding for differential privacy. *CoRR*, abs/2307.03543, 2023.

Igor Žutić, Jaroslav Fabian, and S. Das Sarma. Spintronics: Fundamentals and applications. *Reviews of Modern Physics*, 76:323–410, Apr 2004.

Pavel Izmailov, Sharad Vikram, Matthew D. Hoffman, and Andrew Gordon Wilson. What are bayesian neural network posteriors really like? In Marina Meila and Tong Zhang (eds.), *Proceedings of the 38th International Conference on Machine Learning, ICML 2021, 18-24 July 2021, Virtual Event*, volume 139 of *Proceedings of Machine Learning Research*, pp. 4629–4640. PMLR, 2021.

Piotr Józwiak, Janusz Jacak, and Witold Jacak. New concepts and construction of quantum random number generators. *Quantum Inf. Process.*, 23(4):132, 2024.

Shivam N. Kajale, Thanh Nguyen, Corson A. Chao, David C. Bono, Artittaya Boonkird, Mingda Li, and Deblina Sarkar. Current-induced switching of a van der waals ferromagnet at room temperature. *Nature Communications*, 15(1):1485, Feb 2024.

Robert Kass, Bradley Carlin, Andrew Gelman, and Radford Neal. Markov chain monte carlo in practice: a roundtable discussion. *The American Statistician*, 52(2):93–100, 1998.

Pierre L'Ecuyer. Uniform random number generation. *Annals of Operations Research*, 53(1):77–120, 1994.

Pierre L'Ecuyer. History of uniform random number generation. In *2017 Winter Simulation Conference, WSC 2017, Las Vegas, NV, USA, December 3-6, 2017*, pp. 202–230. IEEE, 2017.

Vaisakh Mannalatha, Sandeep Mishra, and Anirban Pathak. A comprehensive review of quantum random number generators: concepts, classification and the origin of randomness. *Quantum Inf. Process.*, 22(12):439, 2023.

Aldo C. Martínez, Aldo Solís, Rafael Díaz Hernández Rojas, Alfred B. U'Ren, Jorge G. Hirsch, and Isaac Pérez Castillo. Advanced statistical testing of quantum random number generators. *Entropy*, 20(11):886, 2018.

Nicholas Metropolis, Arianna Rosenbluth, Marshall Rosenbluth, Augusta Teller, and Edward Teller. Equation of state calculations by fast computing machines. *The journal of chemical physics*, 21 (6):1087–1092, 1953.

J. S. Moodera, Lisa R. Kinder, Terrilyn M. Wong, and R. Meservey. Large magnetoresistance at room temperature in ferromagnetic thin film tunnel junctions. *Phys. Rev. Lett.*, 74:3273–3276, Apr 1995.

Kevin Murphy. *Machine learning - a probabilistic perspective*. Adaptive computation and machine learning series. MIT Press, 2012. ISBN 0262018020.

Yusuke Nagasaka, Akira Nukada, Satoshi Matsuoka, Kenichi Miura, and John Shalf. MRG8: random number generation for the exascale era. In *Proceedings of the Platform for Advanced Scientific Computing Conference, PASC 2018, Basel, Switzerland, July 02-04, 2018*, pp. 6:1–6:11. ACM, 2018.

Radford Neal et al. Mcmc using hamiltonian dynamics. *Handbook of markov chain monte carlo*, 2 (11):2, 2011.

Satoshi Oosawa, Takayuki Konishi, Naoya Onizawa, and Takahiro Hanyu. Design of an stt-mtj based true random number generator using digitally controlled probability-locked loop. In *2015 IEEE 13th International New Circuits and Systems Conference (NEWCAS)*, pp. 1–4. IEEE, 2015.

Ben Perach et al. An asynchronous and low-power true random number generator using stt-mtj. *IEEE Transactions on Very Large Scale Integration (VLSI) Systems*, 27(11):2473–2484, 2019.

M. D. Stiles and A. Zangwill. Anatomy of spin-transfer torque. *Physical Review B*, 66:014407, Jun 2002.

Mario Stipcevic and Çetin Kaya Koç. True random number generators. In Çetin Kaya Koç (ed.), *Open Problems in Mathematics and Computational Science*, pp. 275–315. Springer, 2014.

Hongshi Tan, Xinyu Chen, Yao Chen, Bingsheng He, and Weng-Fai Wong. Thundering: generating multiple independent random number sequences on fpgas. In Huiyang Zhou, Jose Moreira, Frank Mueller, and Yoav Etsion (eds.), *ICS '21: 2021 International Conference on Supercomputing, Virtual Event, USA, June 14-17, 2021*, pp. 115–126. ACM, 2021.

Arne Vansteenkiste, Jonathan Leliaert, Mykola Dvornik, Mathias Helsen, Felipe Garcia-Sanchez, and Bartel Van Waeyenberge. The design and verification of MuMax3. *AIP Advances*, 4(10): 107133, 10 2014.

Srikanth Yoginath and Kalyan Perumalla. Efficient reversible uniform and non-uniform random number generation in UNU.RAN. In Erika Frydenlund, Shafagh Jafer, and Hamdi Kavak (eds.), *Proceedings of the Annual Simulation Symposium, SpringSim (ANSS) 2018, Baltimore, MD, USA, April 15-18, 2018*, pp. 2:1–2:10. ACM, 2018.

Gaojie Zhang, Fei Guo, Hao Wu, Xiaokun Wen, Li Yang, Wen Jin, Wenfeng Zhang, and Haixin Chang. Above-room-temperature strong intrinsic ferromagnetism in 2d van der waals fe3gate2 with large perpendicular magnetic anisotropy. *Nature Communications*, 13(1):5067, Aug 2022.

Ran Zhang, Xiaohan Li, Mingkun Zhao, Caihua Wan, Xuming Luo, Shiqiang Liu, Yu Zhang, Yizhan Wang, Guoqiang Yu, and Xiufeng Han. Probability-distribution-configurable true random number generators based on spin-orbit torque magnetic tunnel junctions. *Advanced Science*, pp. 2402182, 2024.

A ADDITIONAL INFORMATION ON THE SPINTRONIC DEVICE

Spintronic devices are a class of computing (logic and memory) devices that harness the spin of electrons (in addition to their charge) for computation. This contrasts with traditional electronic devices which only use electron charges for computation. Spintronic devices are built using magnetic materials, as the magnetization (magnetic moment per unit volume) of a magnet is a macroscopic manifestation of its correlated electron spins. The prototypical spintronic device, called the magnetic tunnel junction (MTJ), is a three-layer device which can act both as a memory unit and a switch (Žutić et al., 2004; Moodera et al., 1995). It consists of two ferromagnetic layers separated by a thin, insulating non-magnetic layer. When the magnetization of the two ferromagnetic layers is aligned parallel to each other, the MTJ exhibits a low resistance (R_P). Conversely, when the two magnetizations are aligned anti-parallel, the MTJ exhibits a high resistance (R_{AP}). By virtue of the two discrete resistance states, an MTJ can act as a memory bit as well as a switch. In practice, the MTJs are constructed such that one of the ferromagnetic layers stays fixed, while the other layer's magnetization can be easily toggled (free layer, FL). Thus, by toggling the FL, using a magnetic field or electric currents, the MTJ can be switched between its '0' and '1' state.

An MTJ can serve as a natural source of randomness upon aggressive scaling, i.e. when the FL of the MTJ is shrunk to such a small volume that it toggles randomly just due to thermal energy in the vicinity. As schematically illustrated in Figure 4a, the self-energy of the magnetic layer is minimum and equal for the magnetization pointing vertically up or down, i.e. polar angle $\theta_M = 0^o$ or 180^o, respectively. The self-energy is maximum for the horizontal orientation ($\theta_M = 90^o$). The corresponding energy barrier, ΔE dictates the time scale at which the magnet can toggle between the up and down oriented states owing to thermal energy. This time scale follows an Arrhenius law dependence (Camsari et al., 2019), i.e.

$$\tau_{\uparrow\downarrow} = \tau_0 e^{\frac{\Delta E}{kT}}, \tag{19}$$

where, τ_0 is the inverse of attempt frequency, typically of the order of 1 ns, k is the Boltzmann constant and T is the ambient temperature. The energy barrier for a magnet is $\Delta E = K_U V = \mu_0 H_K M_S V/2$, where K_U, V, H_K and M_S are the magnet's uniaxial anisotropy energy, volume, effective magnetic anisotropy field and saturation magnetization, respectively. μ_0 is the magnetic permeability of free space. Thus, it can be observed that by reducing the volume V of the magnetic free layer, we can make its ΔE comparable to kT and achieve natural toggling frequencies of computational relevance, as shown in Figure 4b. Figure 5a shows a time-domain plot of the normalized state of such an s-MTJ, calculated using micromagnetic simulations with the MuMax3 package (Vansteenkiste et al., 2014). Further details on the micromagnetic simulations are included in Appendix B. A histogram of the resistance state of this s-MTJ is presented in Figure 5b. It is worth noting that the s-MTJ can produce such a Bernoulli distribution like probability density function (PDF), with $p = 0.5$, without any external stimulus, by virtue of only the ambient temperature. However, applying a bias current across the s-MTJ can allow tuning of the PDF through the spin transfer torque mechanism (Stiles & Zangwill, 2002). As shown in Figure 5c-f, applying a positive bias current across the device makes the high resistance state more favorable, while applying a negative current has the opposite effect. In fact, by applying an appropriate bias current across the s-MTJ, using a simple current-mode digital to analog converter as shown in Figure 6a, we can achieve precise control over the Bernoulli parameter (p) exhibited by the s-MTJ. Details on the current-biasing circuit are included in Appendix C. The p-value of the s-MTJ responds to the bias current through a sigmoidal dependence, as shown in Figure 6b.

Figure 4: (a) Schematic illustration of the self-energy (E) of a nanomagnet with respect to the polar angle (θ_M) of its magnetization (indicated by thick arrows). (b) Natural frequency of stochastic switching for a nanomagnet of a particular diameter at different temperatures.

Figure 5: Dynamics of the normalized resistance of a stochastic MTJ for different bias current densities. (a) $I_{\text{bias}} = 0$ produces equal probability of observing the high or low state. (b) Histogram of the observed resistance state for $I_{\text{bias}} = 0$. (c, d) Trace and histogram of the observed resistance for a bias current of 2×10^{11} A/m^2. (e, f) Trace and histogram of the observed resistance for a bias current of -2 $\times 10^{11}$ A/m^2.

Figure 6: (a) Schematic diagram of a current-mode digital to analog converter for providing the biasing current to a stochastic MTJ. (b) Variation of the Bernoulli parameter of the stochastic MTJ with bias current. Red triangles are data point obtained from micromagnetic simulations, while the grey dotted line is a theoretical fit (sigmoid function).

B   MICROMAGNETIC SIMULATIONS

Dynamics of a ferromagnet's magnetization in response to external stimuli, like magnetic fields, currents or heat can be modelled using micromagnetic simulations. The magnetization dynamics can be described using a differential equation, known as the Landau-Lifshitz-Gilbert-Slonczewski (LLGS) equation:

$$\frac{d\vec{m}}{dt} = -\gamma \vec{m} \times \vec{H}_{\text{eff}} + \alpha \vec{m} \times \frac{d\vec{m}}{dt} + \tau_{\parallel} \frac{\vec{m} \times (\vec{x} \times \vec{m})}{|\vec{x} \times \vec{m}|} + \tau_{\perp} \frac{\vec{x} \times \vec{m}}{|\vec{x} \times \vec{m}|} \tag{20}$$

where, $\vec{m}$ is the normalized magnetization ($\vec{M}/|\vec{M}|$), and are the gyromagnetic ratio and damping constant for the ferromagnet, x is a unit vector along the direction of applied electric current and, $\tau_{\parallel}$ and $\tau_{\perp}$ are current-induced torque magnitudes acting parallel and perpendicular to the current. $\vec{H}_{\text{eff}}$ is the effective magnetic field acting on the ferromagnet, which contains contributions from externally applied magnetic fields, exchange interactions, magneto-crystalline anisotropy, shape anisotropy, thermal fields, and demagnetization, among others.

The simulations results presented here are performed for a van der Waals (vdW) magnetic material, Fe_3GaTe_2 (FGaT) (Zhang et al., 2022; Kajale et al., 2024). Being a vdW material, FGaT has a layered structure which makes it an ideal candidate for building ultra-thin (monolayer) magnetic thin films of high quality needed for achieving stochasticity. FGaT also exhibits perpendicular magnetic anisotropy, which means its self-energy is lower for magnetization pointing out of plane as compared to the magnetization pointing in-plane. This property is crucial for building compact, nanoscale spintronic devices. The simulations are performed using the MuMax3 program (Vansteenkiste et al., 2014), for devices shaped as circular discs. The values of different physical parameters used in the micromagnetic simulations are compiled in Table 3. Certain parameters, whose experimental values are not determined, are set to typical values for similar materials and are indicated as such. All simulations can be replicated using standard consumer-grade computers without requiring extensive resources.

Table 3: Parameters Used in Micromagnetic Simulations With the MuMax3 Code.

Parameter	Value
Saturation magnetization (M_S)	3.95×10^4 A/m (Kajale et al., 2024)
Effective anisotropy field (K_U)	3.02×10^6 A/m (Kajale et al., 2024)
Permeability of free space (μ_0)	1.26×10^{-6} kg·m/s^2·A^2
Temperature (T)	300 K
Gilbert damping constant (α)	0.02 (typical)
Exchange stiffness (A_{ex})	1.3×10^{13} J/m
Thickness	1 nm
Diameter	2 nm

C POWER ESTIMATION OF THE CURRENT BIASING CIRCUIT

The current biasing circuit was simulated using Cadence Virtuoso using the Global Foundries 22FDX (22 nm FDSOI) process design kit. The circuit has been designed for a maximum bias current of 20 μA to attain an s-MTJ with Bernoulli parameter $p = 0.99$. The current levels corresponding to $p = 0.67$ and $p = 0.99$ are divided into 4-bit resolution (Figure 2). The four bias bits (B0-B3) are fed to the transistors P0, P1, P2, P3 (LSB to MSB), which are sized to produce currents I_0, $2I_0$, $4I_0$ and $8I_0$, respectively, when the corresponding bias bit it '1'. A constant current $I_{\text{base}} = 2.82\ \mu$A is additionally supplied through P4 to create a baseline of $p = 0.67$ for the s-MTJs. The transistors are operated at a low supply voltage of 0.35 V to achieve a small $I_0 = 1.14\ \mu$A. Thus, each exponent bit can be set to its requisite Bernoulli parameter by appropriately setting the 4-bit bias word, and the power dissipation in the biasing circuit can be estimated for each of the exponent bits. Lengths of all the transistors are set to 20 nm. Width of P4 is set to 260 nm, while the widths of P0, P1, P2 and P3 are 100 nm, 200 nm, 400 nm, and 800 nm, respectively. As discussed in the main text, our proposed method requires only positive current biases for the stochastic MTJs. Thus, the unipolar current mode DAC proposed here suffices for our application. For more general use cases where both positive and negative bias currents may be needed, a bipolar current-steering DAC can be utilized.

D ENERGY CONSUMPTION OF RANDOM NUMBER GENERATORS

Figure 7: Power consumption analysis in Joules (logarithmic scale) for 2^{30} random numbers. Benchmarks were performed by Antunes & Hill (2024).

E   ADDITIONAL FIGURES ON PHYSICAL APPROXIMATION ERROR

Figure 8: Visualization of samples obtained with three different assumptions. Perfect Resolution Sampling assumes the precise values obtained from Equations $equation$ 5-$equation$ 8 in Section 4.2. Control Bits Sampling v1 assumes the closest distance measure to actual obtainable control bits. Control Bits Sampling v2 assumes that each exponent bit should actually be different over closest distance, even if the physically closest distance would imply redundant values.

F ADDITIONAL FIGURES FOR CONCEPTUAL APPROXIMATION ERROR

Figure 9: Sampling from the convolution of two Gaussian distributions, $\mathcal{N}(0.2, 0.1^2)$ and $\mathcal{N}(0.2, 0.1^2)$, resulting in $\mathcal{N}(0.4, \sqrt{0.1^2 + 0.1^2})$.

Figure 10: Sampling after Prior-Likelihood Transformation: Using a Beta$(2, 5)$ prior and a $\mathcal{N}(0.1, 0.1^2)$ likelihood, the final distribution is derived by multiplying their densities.