# FAST PARTIAL FOURIER TRANSFORM

## ABSTRACT

Given a time-series vector, how can we efficiently compute a specified part of Fourier coefficients? Fast Fourier transform (FFT) is a widely used algorithm that computes the discrete Fourier transform in many machine learning applications. Despite its pervasive use, all known FFT algorithms do not provide a fine-tuning option for the user to specify one's demand, that is, the output size (the number of Fourier coefficients to be computed) is algorithmically determined by the input size. Such a lack of flexibility is often followed by just discarding the unused coefficients because many applications do not require the whole spectrum of the frequency domain, resulting in an inefficiency due to the extra computation.

In this paper, we propose a fast Partial Fourier Transform (PFT), an efficient algorithm for computing only a part of Fourier coefficients. PFT approximates a part of twiddle factors (trigonometric constants) using polynomials, thereby reducing the computational complexity due to the mixture of many twiddle factors. We derive the asymptotic time complexity of PFT with respect to input and output sizes, as well as its numerical accuracy. Experimental results show that our algorithm outperforms the state-of-the-art FFT algorithms, with an order of magnitude of speedup for sufficiently small output sizes without sacrificing accuracy.

## 1 INTRODUCTION

How can we efficiently compute a specified part of Fourier coefficients of a given time-series vector? Discrete Fourier transform (DFT) is a crucial task in several application areas, including anomaly detection (Hou & Zhang (2007); Rasheed et al. (2009); Ren et al. (2019)), data center monitoring (Mueen et al. (2010)), and image processing (Shi et al. (2017)). Notably, in many such applications, it is well known that the DFT results in strong "energy-compaction" or "sparsity" in the frequency domain. That is, the Fourier coefficients of data are mostly small or equal to zero, having a much smaller support compared to the input size. Moreover, the support can often be specified in practice (e.g., a few low-frequency coefficients around the origin). These observations arouse a great interest in an efficient algorithm capable of computing only a specified part of Fourier coefficients.

Fast Fourier transform (FFT) is an algorithm that rapidly computes the DFT of a vector, which reduces the arithmetic complexity from naïve $O(N^2)$ to $O(N \log N)$, where $N$ is data size. Nevertheless, all known FFT algorithms do not provide the aforementioned fine-tuning option for the user, i.e., the output size (the number of Fourier coefficients to be computed) is algorithmically determined by the input size. Such a lack of flexibility is often followed by just discarding many unused coefficients, not to mention the inefficiency due to the extra computation.

In this paper, we propose a fast Partial Fourier Transform (PFT), an efficient algorithm for computing a part of Fourier coefficients. Specifically, we consider the following problem: *given a complex-valued vector $\boldsymbol{a}$ of size $N$, a non-negative integer $M$, and an integer $\mu$, estimate the Fourier coefficients of $\boldsymbol{a}$ for the interval $[\mu - M, \mu + M]$*. The resulting algorithm is of remarkably simple structure, composed of several "smaller" FFTs combined with linear pre- and post-processing steps; consequently, we achieve $O(N + M \log M)$ complexity of PFT. When $M \ll N$, this is a significant improvement compared to the conventional FFT which never benefits from the information of $M$, resulting in $O(N \log N)$ complexity, consistently.

To the best of our knowledge, PFT is the first DFT algorithm that enables one to control the output interval, providing great versatility and efficiency on the computation. There have been studies for estimating the top-$k$ (the $k$ largest in magnitude) Fourier coefficients (Hassanieh et al. (2012); Iwen et al. (2007)), yet none of them grants a "freedom" of specifying the output interval. Furthermore,

PFT does not require the input size to be a power of 2, unlike many other variants of FFT. This is because the idea of PFT derives from a modification of the Cooley-Tukey algorithm (Cooley & Tukey, 1965), which also makes it straightforward to extend the idea to a higher dimensionality.

Through experiments, we show that PFT outperforms the state-of-the-art FFT libraries, FFTW by Frigo & Johnson (2005) and Intel Math Kernel Library (MKL), with an order of magnitude of speedup for sufficiently small output sizes without sacrificing accuracy.

## 2  RELATED WORK

We describe related works on Fast Fourier transform (FFT), as well as its applications.

**Fast Fourier Transform.** Cooley and Tukey proposed by far the most commonly used FFT algorithm (Cooley & Tukey, 1965), in which a DFT is recursively broken down into several smaller DFTs provided that the original data is of composite size. Johnson & Frigo (2006) reduced the arithmetic complexity of FFT to the state-of-the-art $\sim \frac{34}{9}N \log N$, where $N$ is data size. Meanwhile, a great interest in an algorithm that efficiently computes only a small number of Fourier coefficients has grown because of the frequently observed energy-compaction property. A few techniques have been proposed by Hassanieh et al. (2012) and Iwen et al. (2007), which estimate the top-$k$ Fourier coefficients of a given vector. However, all known FFT algorithms lack the ability to efficiently compute only a specified part of Fourier coefficients.

**Applications of FFT.** Fast Fourier transform has been widely used for anomaly detection (Hou & Zhang (2007); Rasheed et al. (2009); Ren et al. (2019)). Hou & Zhang (2007) and Ren et al. (2019) detect anomalous points of a given data by extracting a compact representation with FFT. Rasheed et al. (2009) use FFT to detect local spatial outliers which have similar patterns within a region but different patterns from the outside. Several works (Pagh (2013); Pham & Pagh (2013); Malik & Becker (2018)) exploit FFT for efficient operations. Pagh (2013) leverages FFT to efficiently compute a polynomial kernel used with support vector machines (SVMs). Malik & Becker (2018) propose an efficient tucker decomposition method using FFT. In addition, FFT has been used for fast training of convolutional neural networks (Mathieu et al. (2014); Rippel et al. (2015)) and an efficient recommendation model on a heterogeneous graph (Jin et al. (2020)).

## 3  PROPOSED METHOD

### 3.1  OVERVIEW

We propose PFT, an efficient algorithm for computing a specified part of Fourier coefficients. The main challenges and our approaches are as follows:

1. **How can we extract essential information for a specified output?** Considering that only a specified part of Fourier coefficients should be computed, we need to find an algorithm requiring fewer operations than the direct use of conventional FFT. This is achievable by carefully modifying the Cooley-Tukey algorithm, finding *twiddle factors* (trigonometric factors) with small oscillations, and approximating them via polynomials (Section 3.2.1).
2. **How can we reduce approximation cost?** The approach given above involves an approximating process, which would be computationally demanding. We propose using a *base exponential function*, by which all data-independent factors can be precomputed, enabling one to bypass the approximation problem during the run-time (Sections 3.2.2 and 3.3).
3. **How can we further reduce numerical computation?** We carefully reorder operations and factorize terms in order to alleviate the complexity of PFT. Such techniques separate all data-independent factors from data-dependent factors, allowing further precomputation. The arithmetic cost of the resulting algorithm is $O(N + M \log M)$, where $N$ and $M$ are input and output size descriptors, respectively (Sections 3.4 and 3.5.1).

### 3.2  APPROXIMATION OF TWIDDLE FACTORS

The key of our algorithm is to approximate a part of twiddle factors with small oscillations by using polynomial functions, reducing the computational complexity of DFT due to the mixture of many twiddle factors. Using polynomial approximation also allows one to carefully control the degree of polynomial (or the number of approximating terms), enabling fine-tuning the output range and the approximation bound of the estimation. Our first goal is to find a collection of twiddle factors with small oscillations. This can be achieved by slightly adjusting the summand of DFT and splitting the

summation as in the Cooley-Tukey algorithm (Section 3.2.1). Next, using a proper base exponential function, we give an explicit form of approximation to the twiddle factors (Section 3.2.2).

### 3.2.1 TWIDDLE FACTORS WITH SMALL OSCILLATIONS

Recall that the DFT of a complex-valued vector $\boldsymbol{a}$ of size $N$ is defined as follows:

$$\hat{a}_m = \sum_{n \in [N]} a_n e^{-2\pi i m n / N}, \tag{1}$$

where $[\nu]$ denotes $\{0, 1, \cdots, \nu - 1\}$ for a positive integer $\nu$ (in this paper, we follow the convention of viewing a vector $\boldsymbol{v} = (v_0, v_1, \cdots, v_{\nu-1})$ of size $\nu$ as a finite sequence defined on $[\nu]$). Assume that $N = pq$ for two integers $p, q > 1$. The Cooley-Tukey algorithm re-expresses (1) as

$$\hat{a}_m = \sum_{k \in [p]} \sum_{l \in [q]} a_{qk+l} e^{-2\pi i m (qk+l)/N} = \sum_{k \in [p]} \sum_{l \in [q]} a_{qk+l} e^{-2\pi i m l / N} \cdot e^{-2\pi i m k / p}, \tag{2}$$

yielding two collections of twiddle factors, namely $\{e^{-2\pi i m l / N}\}_{l \in [q]}$ and $\{e^{-2\pi i m k / p}\}_{k \in [p]}$. Consider the problem of computing $\hat{a}_m$ for $-M \leq m \leq M$, where $M \leq N/2$ is a non-negative integer. In this case, note that the exponent of $e^{-2\pi i m l / N}$ ranges from $-2\pi i M (q-1)/N$ to $+2\pi i M (q-1)/N$ and that the exponent of $e^{-2\pi i m k / p}$ ranges from $-2\pi i M (p-1)/p$ to $+2\pi i M (p-1)/p$. Here $\frac{(q-1)/N}{(p-1)/p} \sim \frac{1}{p}$, meaning that the first collection contains twiddle factors with smaller oscillations compared to the second one. Typically, a function with smaller oscillation results in a better approximation via polynomials. In this sense, it is reasonable to approximate the first collection of twiddle factors in (2) with polynomial functions, thereby reducing the complexity of the computation due to the mixture of two collections of twiddle factors. Indeed, one can further reduce the complexity of approximation: we slightly adjust the summand in (2) as follows.

$$\hat{a}_m = e^{-\pi i m / p} \sum_{k \in [p]} \sum_{l \in [q]} a_{qk+l} e^{-2\pi i m (l - q/2)/N} \cdot e^{-2\pi i m k / p}. \tag{3}$$

In (3), we observe that the range of exponents of the first collection $\{e^{-2\pi i m (l - q/2)/N}\}_{l \in [q]}$ of twiddle factors is $[-\pi i M / p, +\pi i M / p]$, a contraction by a factor of around 2 when compared with $[-2\pi i M (q-1)/N, +2\pi i M (q-1)/N]$, hence the twiddle factors with even smaller oscillations. There is an extra twiddle factor $e^{-\pi i m / p}$ in (3). Note that, however, it depends on neither $k$ nor $l$, so the amount of the additional computation is relatively small.

### 3.2.2 BASE EXPONENTIAL FUNCTION

The first collection of twiddle factors in (3) consists of $q$ distinct exponential functions. One can apply approximation process for each function in the collection; however, this would be time-consuming. A more plausible approach is to 1) choose a base exponential function $e^{uix}$ for a fixed $u \in \mathbb{R}$, 2) approximate $e^{uix}$ using a polynomial, and 3) exploit a property of exponential functions: the laws of exponents. Specifically, suppose that we obtained a polynomial $\mathcal{P}(x)$ that approximates $e^{uix}$ on $|x| \leq |\xi|$, where $u, \xi \in \mathbb{R} \setminus \{0\}$. Consider another exponential function $e^{vix}$, where $v \neq 0$. Since $e^{vix} = e^{ui(vx/u)}$, the re-scaled polynomial $\mathcal{P}(vx/u)$ approximates $e^{vix}$ on $|x| \leq |u\xi/v|$. This observation indicates that once we find an approximation $\mathcal{P}$ to $e^{uix}$ on $|x| \leq |\xi|$ for properly selected $u$ and $\xi$, all elements belonging to $\{e^{-2\pi i m (l - q/2)/N}\}_{l \in [q]}$ can be approximated by re-scaling $\mathcal{P}$. Fixing a base exponential function also enables precomputing a polynomial that approximates it, so that one can bypass the approximation problem during the run-time. We further elaborate this idea in a rigorous manner after giving a few definitions (see Definitions 3.1 and 3.2).

Let $\| \cdot \|_R$ be the uniform norm (or supremum norm) restricted to a set $R \subseteq \mathbb{R}$, that is, $\|f\|_R = \sup\{|f(x)| : x \in R\}$ and $P_\alpha$ be the set of polynomials on $\mathbb{R}$ of degree at most $\alpha$.

**Definition 3.1.** Given a non-negative integer $\alpha$ and non-zero real numbers $\xi, u$, we define a polynomial $\mathcal{P}_{\alpha, \xi, u}$ as the best approximation to $e^{uix}$ out of the space $P_\alpha$ under the restriction $|x| \leq |\xi|$:

$$\mathcal{P}_{\alpha, \xi, u} := \arg\min_{P \in P_\alpha} \|P(x) - e^{uix}\|_{|x| \leq |\xi|},$$

and $\mathcal{P}_{\alpha, \xi, u} = 1$ when $\xi = 0$ or $u = 0$. $\qquad \square$

Smirnov & Smirnov (1999) proved the unique existence of $\mathcal{P}_{\alpha, \xi, u}$. A few techniques called *minimax approximation algorithms* for computing the polynomial are reviewed in Fraser (1965).

**Definition 3.2.** Given a tolerance $\epsilon > 0$ and a positive integer $r \geq 1$, we define $\xi(\epsilon, r)$ to be the scope about the origin such that the exponential function $e^{\pi i x}$ can be approximated by a polynomial

of degree less than $r$ with approximation bound $\epsilon$:
$$\xi(\epsilon, r) := \sup\{\xi \geq 0 : \|\mathcal{P}_{r-1,\xi,\pi}(x) - e^{\pi i x}\|_{|x| \leq \xi} \leq \epsilon\}.$$
We express the corresponding polynomial as $\mathcal{P}_{r-1,\xi(\epsilon,r),\pi}(x) = \sum_{j \in [r]} w_{\epsilon,r-1,j} \cdot x^j$. $\qquad\square$

In Definition 3.2, we choose $e^{\pi i x}$ as a base exponential function. The rationale behind is as follows. First, using a minimax approximation algorithm, we precompute $\xi(\epsilon, r)$ and $\{w_{\epsilon,r-1,j}\}_{j \in [r]}$ for several tolerance $\epsilon$'s (e.g. $10^{-1}, 10^{-2}, \cdots$) and positive integer $r$'s (typically $1 \leq r \leq 25$). When $N, M, p$ and $\epsilon$ are given, we find the minimum $r$ satisfying $\xi(\epsilon, r) \geq M/p$. Then, by the preceding argument, it follows that the re-scaled polynomial function $\mathcal{P}_{r-1,\xi(\epsilon,r),\pi}(-2x(l-q/2)/N)$ approximates $e^{-2\pi i x(l-q/2)/N}$ on $|x| \leq |\frac{N}{2(l-q/2)} \cdot \frac{M}{p}|$ for each $l \in [q]$ (note that if $l - q/2 = 0$, we have $|\frac{N}{2(l-q/2)} \cdot \frac{M}{p}| = \infty$). Here $|\frac{N}{2(l-q/2)} \cdot \frac{M}{p}| = |\frac{q}{2l-q} \cdot M| \geq M$ for all $l \in [q]$. Therefore, we obtain a polynomial approximation on $|m| \leq M$ for each twiddle factor in $\{e^{-2\pi i m(l-q/2)/N}\}_{l \in [q]}$, namely $\{\mathcal{P}_{r-1,\xi(\epsilon,r),\pi}(-2m(l-q/2)/N)\}_{l \in [q]}$. Then, it follows from (3) that
$$\hat{a}_m \approx e^{-\pi i m/p} \sum_{k \in [p]} \sum_{l \in [q]} a_{qk+l} \, \mathcal{P}_{r-1,\xi(\epsilon,r),\pi}(-2m(l-q/2)/N) \cdot e^{-2\pi i m k/p}, \tag{4}$$
which gives an estimation of the coefficient $\hat{a}_m$ for $-M \leq m \leq M$.

### 3.3 Arbitrarily centered target ranges

In the previous section, we have focused on the problem of calculating $\hat{a}_m$ for $m$ belonging to $[-M, M]$. We now consider a more general case: let us use the term **target range** to indicate the range where the Fourier coefficients should be calculated, and $R_{\mu,M}$ to denote $[\mu - M, \mu + M] \cap \mathbb{Z}$, where $\mu \in \mathbb{Z}$. Note that the previously given method works only when our target range is centered at $\mu = 0$. A slight modification of the algorithm allows the target range to be arbitrarily centered. One possible approach is as follows: given a complex-valued vector $\boldsymbol{x}$ of size $N$, we define $\boldsymbol{y}$ as $y_n = x_n \cdot e^{-2\pi i \mu n/N}$. Then, the Fourier coefficients of $\boldsymbol{x}$ and $\boldsymbol{y}$ satisfy the following relationship:
$$\hat{y}_m = \sum_{n \in [N]} x_n \cdot e^{-2\pi i \mu n/N} \cdot e^{-2\pi i m n/N} = \sum_{n \in [N]} x_n \cdot e^{-2\pi i(m+\mu)n/N} = \hat{x}_{m+\mu}.$$
Thus, the problem of calculating $\hat{x}_m$ for $m \in R_{\mu,M}$ is equivalent to calculating $\hat{y}_m$ for $m \in R_{0,M}$, to which our previous method can be applied. This technique, however, requires extra $N$ multiplications due to the computation of $\boldsymbol{y}$. A better approach, where one can bypass the extra process during the run-time, is to exploit the following lemma (see Appendix A.1 for the proof).

**Lemma 1.** *Given a non-negative integer $\alpha$, non-zero real numbers $\xi, u$, and a real number $\mu$, the following equality holds:*
$$e^{u i \mu} \cdot \mathcal{P}_{\alpha,\xi,u}(x - \mu) = \operatorname*{arg\,min}_{P \in P_\alpha} \|P(x) - e^{u i x}\|_{|x-\mu| \leq |\xi|}. \qquad\square$$

This observation implies that, in order to obtain a polynomial approximating $e^{u i x}$ on $|x - \mu| \leq |\xi|$, we first find a polynomial $\mathcal{P}$ approximating $e^{u i x}$ on $|x| \leq |\xi|$, then translate $\mathcal{P}$ by $-\mu$ and multiply it with the scalar $e^{u i \mu}$. Applying this process to the previously obtained approximation polynomials (see Section 3.2.2) yields $\{e^{-2\pi i \mu(l-q/2)/N} \cdot \mathcal{P}_{r-1,\xi(\epsilon,r),\pi}(-2(m-\mu)(l-q/2)/N)\}_{l \in [q]}$. We substitute these polynomials for the twiddle factors $\{e^{-2\pi i m(l-q/2)/N}\}_{l \in [q]}$ in (3), which gives the following estimation of $\hat{a}_m$ for $m \in R_{\mu,M}$, where $k \in [p], l \in [q]$, and $j \in [r]$:
$$e^{-\pi i m/p} \sum_{k,l} a_{qk+l} \, e^{-2\pi i \mu(l-q/2)/N} \cdot \mathcal{P}_{r-1,\xi(\epsilon,r),\pi}(-2(m-\mu)(l-q/2)/N) \cdot e^{-2\pi i m k/p}$$
$$= e^{-\pi i m/p} \sum_{k,l} a_{qk+l} \, e^{-2\pi i \mu(l-q/2)/N} \sum_j w_{\epsilon,r-1,j} \, (-2(m-\mu)(l-q/2)/N)^j \cdot e^{-2\pi i m k/p} \tag{5}$$
$$= e^{-\pi i m/p} \sum_j \sum_{k,l} a_{qk+l} \, e^{-2\pi i \mu(l-q/2)/N} \, w_{\epsilon,r-1,j} \, ((m-\mu)/p)^j (1 - 2l/q)^j \cdot e^{-2\pi i m k/p}.$$

### 3.4 Efficient Summations

We have found that three main summation steps (each being over $j, k$ and $l$) take place when computing the partial Fourier coefficients. Note that in (5), the innermost summation $\sum_j$ is moved to the outermost position, and the term $-2(m-\mu)(l-q/2)/N$ is factorized into two independent terms, $(m-\mu)/p$ and $1 - 2l/q$. Interchanging the order of summations and factorizing the term

---

**Algorithm 1:** Configuration phase of PFT

    **input** : Input size $N$, output descriptors $M$ and $\mu$, divisor $p$, and tolerance $\epsilon$
    **output:** Matrix $B$, divisor $p$, and numbers of rows and columns, $q$ and $r$

1  $q \leftarrow N/p$
2  $r \leftarrow \min\{r \in \mathbb{N} : \xi(\epsilon, r) \geq M/p\}$               `// Use precomputed` $\xi(\epsilon, r)$
3  **for** $(l, j) \in [q] \times [r]$ **do**
4     $B[l, j] \leftarrow e^{-2\pi i \mu (l - q/2)/N} \cdot w_{\epsilon, r-1, j} \cdot (1 - 2l/q)^j$ `// Use precomputed` $w_{\epsilon, r-1, j}$
5  **end**

---

**Algorithm 2:** Computation phase of PFT

    **input** : Vector $\boldsymbol{a}$ of size $N$, output descriptors $M$ and $\mu$, and configuration results $B, p, q, r$
    **output:** Vector $\mathcal{E}(\hat{\boldsymbol{a}})$ of estimated Fourier coefficients of $\boldsymbol{a}$ for $[\mu - M, \mu + M]$

1  $A[k, l] \leftarrow a_{qk+l}$ for $k \in [p]$ and $l \in [q]$
2  $C \leftarrow A \times B$
3  **for** $j \in [r]$ **do**
4     $\hat{C}[\cdot, j] \leftarrow \text{FFT}(C[\cdot, j])$               `// FFT of` $j$`-th column of` $C$
5  **end**
6  **for** $m \in [\mu - M, \mu + M]$ **do**
7     $\mathcal{E}(\hat{\boldsymbol{a}})[m] \leftarrow e^{-\pi i m/p} \sum_{j=0}^{r-1} ((m - \mu)/p)^j \cdot \hat{C}[m\%p, j]$
8  **end**

---

result in a significant computational benefit; we elucidate what operator we should utilize for each summation and how we can save the arithmetic costs from it. As we will see, the innermost sum over $l$ corresponds to a matrix multiplication, the second sum over $k$ can be viewed as multiple DFTs, and the outermost sum over $j$ is an inner product. For the first sum, let $A = (a_{k,l}) = a_{qk+l}$ and $B = (b_{l,j}) = e^{-2\pi i \mu (l - q/2)/N} \, w_{\epsilon, r-1, j} \, (1 - 2l/q)^j$, so that (5) can be written as follows:

$$e^{-\pi i m/p} \sum_{j \in [r]} ((m - \mu)/p)^j \sum_{k \in [p]} e^{-2\pi i m k/p} \sum_{l \in [q]} a_{k,l} b_{l,j}.$$

Here, note that the matrix $B$ is data-independent (not dependent on $\boldsymbol{a}$), and thus can be precomputed. Indeed, we have already seen that $\{w_{\epsilon, r-1, j}\}_{j \in [r]}$ can be precomputed. The other factors $e^{-2\pi i \mu (l - q/2)/N}$ and $(1 - 2l/q)^j$ composing the elements of $B$ can also be precomputed if $(N, M, \mu, p, \epsilon)$ is known in advance. Thus, as long as the setting $(N, M, \mu, p, \epsilon)$ is unchanged, we can reuse the matrix $B$ for any input data $\boldsymbol{a}$ once the configuration phase of PFT is completed (Algorithm 1). We shall denote the multiplication $A \times B$ as $C = (c_{k,j})$:

$$e^{-\pi i m/p} \sum_{j \in [r]} ((m - \mu)/p)^j \sum_{k \in [p]} c_{k,j} \cdot e^{-2\pi i m k/p}. \tag{6}$$

For each $j \in [r]$, the summation $\hat{c}_{m,j} = \sum_{k \in [p]} c_{k,j} \cdot e^{-2\pi i m k/p}$ is a DFT of size $p$. We perform FFT $r$ times for this computation, which yields the following estimation of $\hat{a}_m$ for $m \in R_{\mu, M}$:

$$e^{-\pi i m/p} \sum_{j \in [r]} ((m - \mu)/p)^j \cdot \hat{c}_{m,j}. \tag{7}$$

Note that $\hat{c}_{m,j}$ is a periodic function of period $p$ with respect to $m$, so we use the coefficient at $m$ modulo $p$ if $m < 0$ or $m \geq p$. Thus, the $m^{th}$ Fourier coefficient of $\boldsymbol{a}$ can be estimated by the inner product of $((m - \mu)/p)^j$ and $\hat{c}_{m,j}$ with respect to $j$, followed by a multiplication with the extra twiddle factor $e^{-\pi i m/p}$ (we also precompute $((m - \mu)/p)^j$ and $e^{-\pi i m/p}$). The full computation is outlined in Algorithm 2. By these summation techniques, the arithmetic complexity is reduced to $O(N + M \log M)$ from naïve $O(MN)$, as described in Section 3.5.

## 3.5 THEORETICAL ANALYSIS

We present theoretical analysis on the time complexity of PFT and its approximation bound.

### 3.5.1 TIME COMPLEXITY

We analyze the time complexity of PFT. Theorem 2 (see Appendix A.2 for the proof) shows that the time cost $T(N, M)$ of PFT, where $N$ and $M$ are input and output size descriptors, respectively, is bounded by $O(N + M \log M)$. Note that the theorem presumes that all prime factors of $N$ have

Table 1: Detailed information of datasets.

| Dataset | Type | Size | Description |
|---|---|---|---|
| $\{S_n\}_{n=12}^{22}$ | Synthetic | $2^n$ | Vectors of random real numbers between 0 and 1 |
| Urban Sound[1] | Real-world | 32000 | Various sound recordings in urban environment |
| Air Condition[2] | Real-world | 19735 | Time-series vectors of air condition information |

a fixed upper bound. Yet, in practice, this necessity is not a big concern because one can readily control the input size with basic techniques such as zero-padding or re-sampling. Moreover, we empirically find that even if $N$ has a large prime factor, PFT still shows a promising performance (see Section 4.2). In Theorem 2, note that a positive integer is called $b$-**smooth** if none of its prime factors is greater than $b$. For example, the 2-smooth integers are equivalent to the powers of 2.

**Theorem 2.** *Fix a tolerance $\epsilon > 0$ and an integer $b \geq 2$. If $N$ is $b$-smooth, then the time complexity $T(N, M)$ of PFT has an asymptotic upper bound $O(N + M \log M)$.* $\square$

### 3.5.2 APPROXIMATION BOUND

We now give a theoretical approximation bound of the estimation via the polynomial $\mathcal{P}$. We denote the estimated Fourier coefficient of $\boldsymbol{a}$ as $\mathcal{E}(\hat{\boldsymbol{a}})$. Theorem 3 (see Appendix A.3 for the proof) states that the approximation bound over the target range is data-dependent of the total weight $\|\boldsymbol{a}\|_1$ of the original vector and the given tolerance $\epsilon$, where $\|\cdot\|_1$ denotes the $\ell_1$ norm.

**Theorem 3.** *Given a tolerance $\epsilon > 0$, the following inequality holds for PFT:*
$$\|\hat{\boldsymbol{a}} - \mathcal{E}(\hat{\boldsymbol{a}})\|_{R_{\mu,M}} \leq \|\boldsymbol{a}\|_1 \cdot \epsilon. \qquad \square$$

## 4 EXPERIMENTS

Through experiments, the following questions should be answered:

- **Q1. Run-time cost (Section 4.2).** How quickly does PFT compute a part of Fourier coefficients compared to other competitors without sacrificing accuracy?
- **Q2. Effect of hyper-parameter $p$ (Section 4.3).** How do the different choices of divisor $p$ of input size $N$ affect the overall performance of PFT?
- **Q3. Anomaly detection (Section 4.4).** How well does PFT work for a practical application employing FFT (anomaly detection)?

### 4.1 EXPERIMENTAL SETUP

**Machine.** A machine with Intel Core i7-6700HQ @ 2.60GHz and 8GB of RAM is used.

**Datasets.** We use both synthetic and real-world datasets listed in Table 1.

**Competitors.** We compare PFT with two state-of-the-art FFT algorithms, FFTW and MKL. All of them including PFT are implemented in C++.

1. **FFTW**: FFTW[3] is one of the fastest public implementation for FFT, offering a hardware-specific optimization. We use the optimized version of FFTW 3.3.5, and do not include the pre-processing for the optimization as the run-time cost.
2. **MKL**: Intel Math Kernel Library[4] (MKL) is a library of optimized math routines including FFT, and often shows a better run time result than the FFTW. All the experiments are conducted with an Intel processor for the best performance.
3. **PFT (proposed)**: we use MKL BLAS routines for the matrix multiplication, MKL DFTI functions for the batch FFT computation, and Intel Integrated Performance Primitives (IPP) library for the post-processing steps such as inner product and element-wise multiplication.

**Measure.** In all experiments, we use single-precision floating-point format, and the parameters $p$ and $\epsilon$ are chosen so that the relative $\ell_2$ error is strictly less than $10^{-6}$, which ensures that the overall estimated coefficients have at least 6 significant figures. Explicitly,

$$\text{Relative } \ell_2 \text{ Error} = \sqrt{\frac{\sum_{m \in \mathcal{R}} |\hat{a}_m - \mathcal{E}(\hat{a})_m|^2}{\sum_{m \in \mathcal{R}} |\hat{a}_m|^2}} < 10^{-6},$$

where $\hat{\boldsymbol{a}}$ is the actual coefficient, $\mathcal{E}(\hat{\boldsymbol{a}})$ is the estimated coefficient, and $\mathcal{R}$ is the target range.

---

[1] https://urbansounddataset.weebly.com/urbansound8k.html

[2] https://archive.ics.uci.edu/ml/datasets/Appliances+energy+prediction

[3] http://www.fftw.org/index.html

[4] http://software.intel.com/mkl

Figure 1: **(a) Run time vs. input size** for target range $R_{0,2^9}$ with $\{S_n\}_{n=12}^{22}$ datasets, and **(b) run time vs. output size** for $S_{22}$. We observe that PFT outperforms both FFTW and MKL if the output size is small enough ($< 10\%$) compared to the input size. When the output is sufficiently smaller than the input, the performance gain is significant: an order of magnitude of speedup.

Figure 2: Run time vs. output size results for **(a) Urban Sound** dataset and **(b) Air Condition** dataset. PFT outperforms both FFTW and MKL regardless of the fact that the input size is not a power of 2 ($N = 2^8 \times 5^3$) or even it has a large prime factor ($N = 5 \times 3947$).

### 4.2 RUN-TIME COST

**Run time vs. input size.** We fix the target range to $R_{0,2^9}$ and evaluate the run time of PFT vs. input sizes $N : 2^{12}, 2^{13}, \cdots, 2^{22}$. Figure 1a shows how the three competitive algorithms scale with varying input size, wherein PFT outperforms both FFTW and MKL if the output size is sufficiently smaller ($< 10\%$) than the input size. Consequently, PFT achieves up to $21\times$ speedup compared to its competitors. Due to the overhead of the $O(N)$ pre- and $O(M)$ post-processing steps, PFT runs slower than FFT when $M$ is close to $N$ so the time complexity tends to $O(N + N \log N)$.

**Run time vs. output size.** We fix the input size to $N = 2^{22}$ and evaluate the run time of PFT vs. target ranges $R_{0,2^9}, R_{0,2^{10}}, \cdots, R_{0,2^{18}}$. The result is illustrated as a run time vs. output size plot (recall that $|R_{0,M}| \simeq 2M$) in Figure 1b. Note that the run times of FFTW and MKL are consistent because they do not benefit from the information of the output size. When the output size is sufficiently smaller than the input size, PFT is up to $13.8\times$ faster than the other competitors.

**Real-world data.** When it comes to real-world data, it is not generally the case that the size of an input vector is a power of 2. Notably, PFT still shows a promising performance regardless of the fact that the input size is not a power of 2 or even it has a large prime factor: a strong indication that our proposed technique is robust for many different applications in real-world. *Urban Sound* dataset contains various sound recording vectors of size $N = 32000 = 2^8 \times 5^3$. We evaluate the run time of PFT vs. output size ranging from 100 to 6400. Figure 2a illustrates the result, wherein PFT outperforms both FFTW and MKL if the output size is small enough compared to the input size. On the other hand, *Air Condition* dataset is composed of time-series vectors of size $N = 19735 = 5 \times 3947$. Note that $N$ has only two non-trivial divisors, namely 5 and 3947, forcing one to choose $p = 3947$ in any practical settings; if we choose $p = 5$, the ratio $M/p$ often turns out to be *too large*, which results in a poor performance (see Section 4.3 for more discussion of the optimal choice of $p$). The run time of PFT vs. output size ranging from 125 to 16000 is evaluated in Figure 2b. It is noteworthy that PFT still outperforms its competitors even in such pathological examples, implying the robustness of our algorithm for various real-world situations.

Table 2: Average run time (ms) of PFT for $N = 2^{22}$ with different settings of $M/p$ and $M$.

| $M/p$ | $M$ | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|
| | $2^9$ | $2^{10}$ | $2^{11}$ | $2^{12}$ | $2^{13}$ | $2^{14}$ | $2^{15}$ | $2^{16}$ | $2^{17}$ | $2^{18}$ |
| 1/32 | **1.273** | **1.394** | 1.634 | 2.303 | 5.659 | 14.121 | - | - | - | - |
| 1/8 | 2.674 | 1.608 | **1.332** | **1.491** | 1.860 | 3.020 | 7.711 | - | - | - |
| 1/2 | 2.627 | 3.738 | 2.717 | 1.678 | **1.526** | 1.881 | 2.707 | 5.740 | 14.715 | - |
| 1 | 2.677 | 2.685 | 3.805 | 2.808 | 1.687 | **1.692** | 2.164 | 3.530 | 7.749 | - |
| 2 | 4.005 | 2.723 | 2.731 | 3.533 | 2.878 | 1.949 | **1.940** | **2.821** | 5.556 | 12.534 |
| 4 | 4.090 | 4.295 | 2.986 | 2.983 | 4.108 | 3.275 | 2.365 | 2.929 | **5.411** | **11.924** |

Figure 3: Top-20 anomalous points detected in Air Condition time-series data, where each red dot denotes a detected anomaly position. Note that replacing FFT with PFT does not change the result of the detection, still reducing the overall time complexity.

### 4.3 EFFECT OF HYPER-PARAMETER $p$

To investigate the effect of different choices of $p$, we fix $N = 2^{22}$ and vary the ratio $M/p$ from $1/32$ to $4$ for target ranges $R_{0,2^9}, R_{0,2^{10}}, \cdots, R_{0,2^{18}}$. Table 2 shows the resulting run times, where the bold highlights the best choice of $M/p$ for each $M$, and the missing entries are due to worse performance than FFT. One crucial observation is as follows: with the increase of output size, the best choice of $M/p$ also increases or, equivalently, the optimal value of $p$ tends to remain stable. Intuitively, this is the consequence of "balancing" the three summation steps (Section 3.4): when $M \ll N$, the most computationally expensive operation is the matrix multiplication with $O(rN)$ time cost, and thus, $M/p$ should be small so that the $r$ decreases, despite a sacrifice in the batch FFT step requiring $O(rp \log p)$ operations (Appendix A.2). As the $M$ becomes larger, however, more concern is needed regarding the batch FFT and post-processing steps, so the parameter $p$ should not change rapidly. This observation indicates the possibility that the optimal value of $p$ can be algorithmically auto-selected given a setting $(N, M, \mu, \epsilon)$, which we leave as a future work.

### 4.4 ANOMALY DETECTION

We demonstrate an example of how PFT is applied to practical applications. Here is one simple but fundamental principle: *replace the "perform FFT and discard unused coefficients" procedure with "just perform PFT"*. Considering the anomaly detection method proposed in Rasheed et al. (2009), where one first performs FFT and then inverse FFT with only a few low-frequency coefficients to obtain an estimated fitted curve, we can directly apply the principle to the method. To verify this experimentally, we use a time-series vector from Air Condition dataset, and set the target range as $R_{0,125}$ ($\simeq 250$ low-frequency coefficients). Note that, in this setting, PFT results in around $8\times$ speedup compared to the conventional FFT (see Figure 2b). The top-20 anomalous points detected from the data are presented in Figure 3. In particular, we found that replacing FFT with PFT does not change the result of top-20 anomaly detection, with all its computational benefits.

## 5 CONCLUSIONS

In this paper, we propose PFT (fast Partial Fourier Transform), an efficient algorithm for computing a part of Fourier coefficients. PFT approximates some of twiddle factors with relatively small oscillations using polynomials, reducing the computational complexity of DFT due to the mixture of many twiddle factors. Experimental results show that our algorithm outperforms the state-of-the-art FFT algorithms, FFTW and MKL, with an order of magnitude of speedup without sacrificing accuracy. Future works include optimizing the implementation of PFT; for example, the optimal divisor $p$ of input size $N$ might can be algorithmically auto-selected. We also believe that hardware-specific optimizations (similar to FFTW or MKL) would further increase the performance of PFT.

REFERENCES

James W Cooley and John W Tukey. An algorithm for the machine calculation of complex fourier series. *Mathematics of computation*, 19(90):297–301, 1965.

W. Fraser. A survey of methods of computing minimax and near-minimax polynomial approximations for functions of a single independent variable. *J. ACM*, 12(3):295–314, 1965. doi: 10.1145/321281.321282. URL https://doi.org/10.1145/321281.321282.

M. Frigo and S. G. Johnson. The design and implementation of fftw3. *Proceedings of the IEEE*, 93 (2):216–231, 2005.

Haitham Hassanieh, Piotr Indyk, Dina Katabi, and Eric Price. Simple and practical algorithm for sparse fourier transform. In *Proceedings of the twenty-third annual ACM-SIAM symposium on Discrete Algorithms*, pp. 1183–1194. SIAM, 2012.

Xiaodi Hou and Liqing Zhang. Saliency detection: A spectral residual approach. In *CVPR*. IEEE Computer Society, 2007.

MA Iwen, A Gilbert, M Strauss, et al. Empirical evaluation of a sub-linear time sparse dft algorithm. *Communications in Mathematical Sciences*, 5(4):981–998, 2007.

Jiarui Jin, Jiarui Qin, Yuchen Fang, Kounianhua Du, Weinan Zhang, Yong Yu, Zheng Zhang, and Alexander J. Smola. An efficient neighborhood-based interaction model for recommendation on heterogeneous graph. *CoRR*, abs/2007.00216, 2020.

Steven G Johnson and Matteo Frigo. A modified split-radix fft with fewer arithmetic operations. *IEEE Transactions on Signal Processing*, 55(1):111–119, 2006.

Osman Asif Malik and Stephen Becker. Low-rank tucker decomposition of large tensors using tensorsketch. In *NeurIPS*, pp. 10117–10127, 2018.

Michaël Mathieu, Mikael Henaff, and Yann LeCun. Fast training of convolutional networks through ffts. In *2nd International Conference on Learning Representations, ICLR 2014, Banff, AB, Canada, April 14-16, 2014, Conference Track Proceedings*, 2014.

Abdullah Mueen, Suman Nath, and Jie Liu. Fast approximate correlation for massive time-series data. In *SIGMOD*, pp. 171–182. ACM, 2010.

Rasmus Pagh. Compressed matrix multiplication. *ACM Trans. Comput. Theory*, 5(3):9:1–9:17, 2013.

Ninh Pham and Rasmus Pagh. Fast and scalable polynomial kernels via explicit feature maps. In *KDD*, pp. 239–247. ACM, 2013.

Faraz Rasheed, Peter Peng, Reda Alhajj, and Jon G. Rokne. Fourier transform based spatial outlier mining. In *Intelligent Data Engineering and Automated Learning - IDEAL 2009, 10th International Conference, Burgos, Spain, September 23-26, 2009. Proceedings*, volume 5788 of *Lecture Notes in Computer Science*, pp. 317–324. Springer, 2009.

Hansheng Ren, Bixiong Xu, Yujing Wang, Chao Yi, Congrui Huang, Xiaoyu Kou, Tony Xing, Mao Yang, Jie Tong, and Qi Zhang. Time-series anomaly detection service at microsoft. In *KDD*, pp. 3009–3017. ACM, 2019.

Oren Rippel, Jasper Snoek, and Ryan P Adams. Spectral representations for convolutional neural networks. In *Advances in neural information processing systems*, pp. 2449–2457, 2015.

Sheng Shi, Runkai Yang, and Haihang You. A new two-dimensional fourier transform algorithm based on image sparsity. In *2017 IEEE International Conference on Acoustics, Speech and Signal Processing, ICASSP 2017, New Orleans, LA, USA, March 5-9, 2017*, pp. 1373–1377. IEEE, 2017.

Georgey S Smirnov and Roman G Smirnov. Best uniform approximation of complex-valued functions by generalized polynomials having restricted ranges. *Journal of approximation theory*, 100 (2):284–303, 1999.

# A PROOFS

## A.1 PROOF OF LEMMA 1

*Proof.* Let $Q = \arg\min_{P \in P_\alpha} \|P(x) - e^{uix}\|_{|x-\mu| \le |\xi|}$. We first observe the following equation:

$$
\begin{aligned}
Q &= \arg\min_{P \in P_\alpha} \|P(x) - e^{uix}\|_{|x-\mu| \le |\xi|} \\
&= \arg\min_{P \in P_\alpha} \|P(x + \mu) - e^{ui(x+\mu)}\|_{|x| \le |\xi|} \\
&= \arg\min_{P \in P_\alpha} \|e^{-ui\mu} \cdot P(x + \mu) - e^{uix}\|_{|x| \le |\xi|},
\end{aligned}
$$

where the third equality holds since $|e^{-ui\mu}| = 1$. Recall that the polynomial $\mathcal{P}_{\alpha,\xi,u}$ is defined by $\arg\min_{P \in P_\alpha} \|P(x) - e^{uix}\|_{|x| \le |\xi|}$. If $Q(x) \in P_\alpha$, it is clear that $e^{-ui\mu} \cdot Q(x + \mu) \in P_\alpha$ because translation and non-zero scalar multiplication on a polynomial do not change its degree. Therefore, by the uniqueness of the best approximation (Smirnov & Smirnov, 1999), we have

$$
e^{-ui\mu} \cdot Q(x + \mu) = \mathcal{P}_{\alpha,\xi,u}(x),
$$

which yields $Q(x) = e^{ui\mu} \cdot \mathcal{P}_{\alpha,\xi,u}(x - \mu)$, and hence the proof. $\square$

## A.2 PROOF OF THEOREM 2

*Proof.* We first claim that the following statement holds: *let $b \ge 2$; if $N$ is b-smooth and $M \le N$ is a positive integer, then there exists a positive divisor $p$ of $N$ satisfying $M/\sqrt{b} \le p < \sqrt{b}M$.* Indeed, suppose that none of $N$'s divisors belongs to $[M/\sqrt{b}, \sqrt{b}M)$. Let $1 = p_1 < p_2 < \cdots < p_d = N$ be the enumeration of all positive divisors of $N$ in increasing order. It is clear that $p_1 < \sqrt{b}M$ and $M/\sqrt{b} < p_d$ since $b \ge 2$ and $1 \le M \le N$. Then, there exists an $i \in \{1, 2, \cdots, d-1\}$ so that $p_i < M/\sqrt{b}$ and $p_{i+1} \ge \sqrt{b}M$. Since $N$ is b-smooth and $p_i < N$, at least one of $2p_i, 3p_i, \cdots, bp_i$ must be a divisor of $N$. However, this is a contradiction because we have $p_{i+1}/p_i > (\sqrt{b}M)(M/\sqrt{b})^{-1} = b$, so none of $2p_i, 3p_i, \cdots, bp_i$ can be a divisor of $N$, which completes the proof.

Exploiting the above property, we manage to reduce the time complexity of PFT to a functional form dependent of only $N$ and $M$. We follow the convention in counting FFT operations, assuming that all data-independent elements such as configuration results $B, p, q, r$ and twiddle factors are precomputed, and thus not included in the run-time cost. We begin with the construction of the matrix $A$. For this, we merely interpret $\boldsymbol{a}$ as an array representation for $A$ of size $p \times q = N$ (line 1 in Algorithm 2). Also, recall that the matrix $B$ can be precomputed as described in Section 3.4. For the two matrices $A$ of size $p \times q$ and $B$ of size $q \times r$, standard matrix multiplication algorithm has running time of $O(pqr) = O(r \cdot N)$ (line 2 in Algorithm 2). Next, the expression (6) contains $r$ DFTs of size $p$, namely $\hat{c}_{m,j} = \sum_{k \in [p]} c_{k,j} \cdot e^{-2\pi imk/p}$ for each $j \in [r]$. We use FFT $r$ times for the computation, then it is easy to see that the time cost is given by $O(r \cdot p \log p)$ (lines 3-5 in Algorithm 2). Finally, there are $2M + 1$ coefficients to be calculated in (7), each requiring $O(r)$ operations, giving an upper bound $O(r \cdot M)$ for the running time (lines 6-8 in Algorithm 2). Combining the three upper bounds, we formally express the time complexity $T(N, M)$ of PFT as

$$
T(N, M) = O(r \cdot (N + p \log p + M)).
$$

Note that $r$ is only dependent of $\epsilon$ and $M/p$ by its definition (Algorithm 1). Therefore, when $\epsilon$ is fixed, $T(N, M)$ is dependent of the choice of $p$. By the preceding argument, we can always find a divisor $p$ of $N$ such that $M/\sqrt{b} \le p < \sqrt{b}M$, implying that $M/p$ is tightly bounded, and thus, so is $r$. It follows that $p = \Theta(M)$ and $r = \Theta(1)$, which leads to the following asymptotic upper bound for $T(N, M)$ with respect to $N$ and $M$:

$$
T(N, M) = O(N + M \log M),
$$

hence the proof. $\square$

### A.3 PROOF OF THEOREM 3

*Proof.* Let $v = -2(l - q/2)/N$. By the estimation in (5), the following holds:

$$\|\hat{\boldsymbol{a}} - \mathcal{E}(\hat{\boldsymbol{a}})\|_{R_{\mu,M}} = \|\sum_{k,l} a_{qk+l}\big(e^{\pi ivm} - e^{\pi iv\mu} \cdot \mathcal{P}_{r-1,\xi(\epsilon,r),\pi}(v(m-\mu))\big)e^{-2\pi imk/p}e^{-\pi im/p}\|_{m \in R_{\mu,M}}$$

$$\leq \sum_{k,l} \|a_{qk+l}\big(e^{\pi ivm} - e^{\pi iv\mu} \cdot \mathcal{P}_{r-1,\xi(\epsilon,r),\pi}(v(m-\mu))\big)e^{-2\pi imk/p}e^{-\pi im/p}\|_{m \in R_{\mu,M}}$$

$$= \sum_{k,l} |a_{qk+l}| \cdot \|e^{\pi iv(m-\mu)} - \mathcal{P}_{r-1,\xi(\epsilon,r),\pi}(v(m-\mu))\|_{m \in R_{\mu,M}},$$

since we have $|e^{-2\pi imk/p}| = |e^{-\pi im/p}| = |e^{-\pi iv\mu}| = 1$. If $l$ ranges from 0 to $q - 1$, then $|v| \leq 2(q/2)/N = 1/p$, and thus, $M|v| \leq M/p \leq \xi(\epsilon, r)$. We extend the domain of the function $e^{\pi iv(m-\mu)} - \mathcal{P}_{r-1,\xi(\epsilon,r),\pi}(v(m-\mu))$ from $m \in R_{\mu,M} = [\mu - M, \mu + M] \cap \mathbb{Z}$ to $x \in [\mu - M, \mu + M]$ (note that extending domain never decreases the uniform norm), and replace $v(x - \mu)$ with $x'$, from which it follows that

$$\|\hat{\boldsymbol{a}} - \mathcal{E}(\hat{\boldsymbol{a}})\|_{R_{\mu,M}} \leq \sum_{k,l} |a_{qk+l}| \cdot \|e^{\pi iv(x-\mu)} - \mathcal{P}_{r-1,\xi(\epsilon,r),\pi}(v(x-\mu))\|_{|x-\mu| \leq M}$$

$$= \sum_{k,l} |a_{qk+l}| \cdot \|e^{\pi ix'} - \mathcal{P}_{r-1,\xi(\epsilon,r),\pi}(x')\|_{|x'| \leq M|v|}$$

$$\leq \sum_{k,l} |a_{qk+l}| \cdot \|e^{\pi ix'} - \mathcal{P}_{r-1,\xi(\epsilon,r),\pi}(x')\|_{|x'| \leq \xi(\epsilon,r)}$$

$$\leq \sum_{k,l} |a_{qk+l}| \cdot \epsilon$$

$$= \|\boldsymbol{a}\|_1 \cdot \epsilon,$$

where the second inequality holds since $M|v| \leq \xi(\epsilon, r)$, hence the desired result. $\square$