# Subspace State-Space Identification and Model Predictive Control of Nonlinear Dynamical Systems Using Deep Neural Network with Bottleneck

## Abstract

A novel nonlinear system identification method that produces state estimator and predictor directly usable for model predictive control (MPC) is proposed in this paper. The main feature of the proposed method is that it uses a neural network with a bottleneck layer between the state estimator and predictor to represent the input-output dynamics, and it is proven that the state of the dynamical system can be extracted from the bottleneck layer based on the observability of the target system. The training of the network is shown to be a natural nonlinear extension of the subspace state-space system identification method established for linear dynamical systems. This correspondence gives interpretability to the resulting model based on linear control theory. The usefulness of the proposed method and the interpretability of the model are demonstrated through an illustrative example of MPC.

## 1 Introduction

Model predictive control (MPC) has been widely used as a practical method to control nonlinear dynamical systems (Qin & Badgwell, 2000; Vazquez et al., 2014; Karamanakos et al., 2020). As the name implies, MPC requires a prediction model, and in most cases, state-space models are used. When we want to apply MPC to a complex system whose structure and state are unknown, model construction from input-output data, i.e., system identification, is required. For linear state-space system identification, the subspace methods (Favoreel et al., 2000; Katayama, 2005; van der Veen et al., 2013) are widely used. Its fundamental idea is to reduce the dimensionality of the measured past and future input and output data, and it strongly depends on the linearity of the system. Although there have been continuous attempts to extend the subspace methods to nonlinear systems with specific structures such as Wiener and Hammerstein structures (e.g., Verhaegen & Westwick, 1996; Goethals et al., 2005; Katayama & Ase, 2016) and related research has also been conducted in the field of machine learning as spectral learning of Hidden Markov Models (Kawahara et al., 2007; Hsu et al., 2012; Kandasamy et al., 2016), there is still a lot of room for research in extending the subspace method to general nonlinear dynamical systems.

On the other hand, recent advances in machine learning techniques have had an impact on the research field of system identification (Ljung et al., 2020a;b). Among those technologies, autoencoder is a notable dimensional reduction or feature extraction technique with deep neural networks, whose traits derives from topological constraints of own bottleneck structure. Although several pieces of research apply it to state-space system identification (Masti & Bemporad, 2018; Beintema et al., 2021), these works do not provide a theoretical basis for obtaining the state sequence.

This paper aims to propose a theoretically supported and interpretable nonlinear dynamical system identification method by simply extending the subspace method with neural networks. For the proposed method, it can be shown based on the observability of the target system that when a neural network with an appropriate bottleneck is trained, the state estimator and predictor are formed across the bottleneck layer. The obtained model can be interpreted based on the knowledge from linear system identification methods, and this aspect is explained through an illustrative example.

In this paper, the set of integers and the natural numbers are denoted by $\mathbb{Z}$ and $\mathbb{N}$, respectively. The set $\{s_a, s_{a+1}, \dots, s_{b-1}, s_b\}$ is denoted as $\{s_k\}_{k=a}^{b}$ for conciseness. The $n \times m$ zero matrix is denoted as $\mathbf{0}_{n \times m}$, and $\mathbf{0}_n := \mathbf{0}_{n \times 1}$. For a matrix $\boldsymbol{M}$, $\boldsymbol{M}^\dagger$ is the Moore–Penrose inverse of $\boldsymbol{M}$.

## 2 PROBLEM FORMULATION & NOTATION

We consider the following discrete-time nonlinear dynamical system:

$$\boldsymbol{x}_{t+1} = f(\boldsymbol{x}_t, \boldsymbol{u}_t), \qquad\qquad \boldsymbol{y}_t = h(\boldsymbol{x}_t) \qquad (1)$$

with $t \in \mathbb{Z}$ the time index, $\boldsymbol{x}_t \in \mathbb{R}^{n_x}$ the state, $\boldsymbol{y}_t \in \mathbb{R}^{n_y}$ the output, $\boldsymbol{u}_t \in \mathbb{R}^{n_u}$ the input, $f : \mathbb{R}^{n_x} \times \mathbb{R}^{n_u} \to \mathbb{R}^{n_x}$ the state-transition map and $h : \mathbb{R}^{n_x} \to \mathbb{R}^{n_y}$ the output map. As in the usual setting for system identification, $\boldsymbol{x}_t$ is a latent variable and $\boldsymbol{u}_t$ and $\boldsymbol{y}_t$ are measurable with noise. Although the noise is not considered explicitly in the theoretical discussion, its effect will be discussed in a later example.

For convenience, We define the sequence of input and output signals in the past and future from a certain time $t$ as follows:

$$\boldsymbol{u}_t^{\mathrm{p}} := \begin{bmatrix} \boldsymbol{u}_{t-\mathrm{h_p}} \\ \boldsymbol{u}_{t-\mathrm{h_p}+1} \\ \vdots \\ \boldsymbol{u}_{t-1} \end{bmatrix}, \quad \boldsymbol{y}_t^{\mathrm{p}} := \begin{bmatrix} \boldsymbol{y}_{t-\mathrm{h_p}} \\ \boldsymbol{y}_{t-\mathrm{h_p}+1} \\ \vdots \\ \boldsymbol{y}_{t-1} \end{bmatrix}, \quad \boldsymbol{u}_t^{\mathrm{f}} := \begin{bmatrix} \boldsymbol{u}_t \\ \boldsymbol{u}_{t+1} \\ \vdots \\ \boldsymbol{u}_{t+\mathrm{h_f}-1} \end{bmatrix}, \quad \boldsymbol{y}_t^{\mathrm{f}} := \begin{bmatrix} \boldsymbol{y}_t \\ \boldsymbol{y}_{t+1} \\ \vdots \\ \boldsymbol{y}_{t+\mathrm{h_f}-1} \end{bmatrix} \qquad (2)$$

where the superscripts p and f indicate past and future, and $\mathrm{h_p} \in \mathbb{N}$ and $\mathrm{h_f} \in \mathbb{N}$ are horizons for corresponding directions, respectively. Using these notations, we formulate the problem as follows.

**Problem 1.** *Given the measured input-output data $\{(\boldsymbol{u}_t, \boldsymbol{y}_t)\}_{t=-\mathrm{h_p}+1}^{T+\mathrm{h_f}-1}$, and the design parameters $\mathrm{h_p}, \mathrm{h_f}, n_{\hat{x}} \in \mathbb{N}$, construct a model that consists of a state estimator $E$, which maps $(\boldsymbol{u}_t^{\mathrm{p}}, \boldsymbol{y}_t^{\mathrm{p}}) \mapsto \hat{\boldsymbol{x}}_t$, and a predictor $P$, which maps $(\hat{\boldsymbol{x}}_t, \boldsymbol{u}_t^{\mathrm{f}}) \mapsto \boldsymbol{y}_t^{\mathrm{f}}$. Here, $\hat{\boldsymbol{x}}_t \in \mathbb{R}^{n_{\hat{x}}}$ is a state equivalent to $\boldsymbol{x}_t$ but in an arbitrary coordinate system and $T \in \mathbb{N}$ indicates the size of the dataset.*

**Remark 1.** *In the usual state-space system identification, the goal is to construct a model of $f$ and $h$, i.e., a state-space model. However, in many applications, including model predictive control, the state estimator and multi-step ahead predictor are often reconstructed from the resulting state-space model. In particular, for nonlinear systems that are difficult to analyze, the merits of going through state-space models are questionable. Therefore, we focus here on the construction of the state estimator $E$ and predictor $P$ and only briefly discuss the identification of $f$ and $h$ in section A.1.*

To guarantee Problem 1 to be solvable, we make some assumptions. With the vectors defined above (2), we can write the system (1) as

$$\boldsymbol{x}_t = f^{\mathrm{h_p}}\left(\boldsymbol{x}_{t-\mathrm{h_p}}, \boldsymbol{u}_t^{\mathrm{p}}\right), \qquad\qquad \boldsymbol{y}_t^{\mathrm{p}} = h^{\mathrm{h_p}}\left(\boldsymbol{x}_{t-\mathrm{h_p}}, \boldsymbol{u}_t^{\mathrm{p}}\right) \qquad (3)$$

where

$$f^k\left(\boldsymbol{x}_t, \left[\boldsymbol{u}_t^\top, \dots, \boldsymbol{u}_{t+k}^\top\right]^\top\right) := f\left(\cdots f\left(f\left(\boldsymbol{x}_t, \boldsymbol{u}_t\right), \boldsymbol{u}_{t+1}\right)\cdots, \boldsymbol{u}_{t+k}\right) \qquad (4a)$$

$$h^k\left(\boldsymbol{x}_t, \left[\boldsymbol{u}_t^\top, \dots, \boldsymbol{u}_{t+k}^\top\right]^\top\right) := \begin{bmatrix} h(\boldsymbol{x}_t) \\ h \circ f(\boldsymbol{x}_t, \boldsymbol{u}_t) \\ \vdots \\ h \circ f^{k-1}\left(\boldsymbol{x}_t, \left[\boldsymbol{u}_t^\top, \dots, \boldsymbol{u}_{t+k-1}^\top\right]^\top\right) \end{bmatrix}. \qquad (4b)$$

And define the uniform $k$-observability as follows.

**Definition 1** (uniform $k$-observability (Moraal & Grizzle, 1995))**.** *If the mapping*

$$\mathbb{R}^{n_x} \times (\mathbb{R}^{n_u})^k \to (\mathbb{R}^{n_y})^k \times (\mathbb{R}^{n_u})^k \quad by \quad (\boldsymbol{x}, \boldsymbol{u}) \mapsto \left(h^k(\boldsymbol{x}, \boldsymbol{u}), \boldsymbol{u}\right) \qquad (5)$$

*is injective, the system (1) is said to be uniformly $k$-observable (Moraal & Grizzle, 1995).*

Then, we make the following assumptions and theorem.

**Assumption 1.** *The system (1) is uniformly $k$-observable, where $k = \min(\mathrm{h_p}, \mathrm{h_f})$.*

**Remark 2.** *According to Aeyels (1981), if the underlying dynamics of the system (1) is continuous, then the system is $k$-observable for $k \geq 2n_x + 1$.*

**Assumption 2.** *The dimension of the state estimate is large enough, that is, $n_{\hat{x}} \geq n_x$.*

**Theorem 1.** *Under Assumptions 1 and 2, Problem 1 has a solution.*

*Proof.* From Assumption 1, there exists the map

$$\Phi^{\mathrm{h_p}} : \left\{ \left( \boldsymbol{u}^{\mathrm{p}}, h^{\mathrm{h_p}}(\boldsymbol{x}^{\mathrm{p}}, \boldsymbol{u}^{\mathrm{p}}) \right) \mid \boldsymbol{x}^{\mathrm{p}} \in \mathbb{R}^{n_x}, \boldsymbol{u}^{\mathrm{p}} \in (\mathbb{R}^{n_u})^{\mathrm{h_p}} \right\} \to \mathbb{R}^{n_x} \tag{6}$$

that maps $(\boldsymbol{u}_t^{\mathrm{p}}, \boldsymbol{y}_t^{\mathrm{p}}) \mapsto \boldsymbol{x}_{t-\mathrm{h_p}}$, and the map

$$\Psi : \left\{ \left( \boldsymbol{u}^{\mathrm{p}}, h^{\mathrm{h_p}}(\boldsymbol{x}^{\mathrm{p}}, \boldsymbol{u}^{\mathrm{p}}) \right) \mid \boldsymbol{x}^{\mathrm{p}} \in \mathbb{R}^{n_x}, \boldsymbol{u}^{\mathrm{p}} \in (\mathbb{R}^{n_u})^{\mathrm{h_p}} \right\} \to \mathbb{R}^{n_x} \tag{7}$$

that maps $(\boldsymbol{u}_t^{\mathrm{p}}, \boldsymbol{y}_t^{\mathrm{p}}) \mapsto f^{\mathrm{h_p}} \left( \Phi^{\mathrm{h_p}} \left( \boldsymbol{u}_t^{\mathrm{p}}, \boldsymbol{y}_t^{\mathrm{p}} \right), \boldsymbol{u}_t^{\mathrm{p}} \right)$ also exists. Since the pair of maps $\Psi$ and $h^{\mathrm{h_f}}$ is a pair of state estimator and predictor that is a solution to Problem 1, it is guaranteed that there is a solution when $n_{\hat{x}} \geq n_x$. $\qquad\square$

## 3 PROPOSED METHOD

This section presents the proposed nonlinear system identification approach. Also, nonlinear MPC based on the obtained model is described.

### 3.1 TRAINING STATE ESTIMATOR & PREDICTOR

In the proposed method, we train the neural network which has the structure of figure 1, where the state estimator $E : (\mathbb{R}^{n_u})^{\mathrm{h_p}} \times (\mathbb{R}^{n_y})^{\mathrm{h_p}} \to \mathbb{R}^{n_{\hat{x}}}$ maps the past input and output to the current state and the predictor $P : \mathbb{R}^{n_{\hat{x}}} \times \mathbb{R}^{\mathrm{h_f} n_u} \to \mathbb{R}^{\mathrm{h_f} \times n_y}$ maps the current state and the future input to the future output.

Figure 1: Proposed network structure. The sequences of past inputs $\boldsymbol{u}_t^{\mathrm{p}}$ and outputs $\boldsymbol{y}_t^{\mathrm{p}}$ are once compressed into state variables $\hat{\boldsymbol{x}}_t$, and then reflected in the prediction of the sequence of future outputs $\boldsymbol{y}_t^{\mathrm{f}}$.

We set $n_{\hat{x}} < \mathrm{h_p} n_y$ for the bottleneck structure of the network to take a lower-dimensional state, and the training problem is formulated as the following minimization problem

$$\min_{E, P} \quad \frac{1}{T} \sum_{t=1}^{T} \left\| \boldsymbol{y}_t^{\mathrm{f}} - P\big( \underbrace{E\left(\boldsymbol{u}_t^{\mathrm{p}}, \boldsymbol{y}_t^{\mathrm{p}}\right)}_{\text{estimate of } \boldsymbol{x}_t}, \boldsymbol{u}_t^{\mathrm{f}} \big) \right\|^2. \tag{8}$$

$$\underbrace{\phantom{\min_{E, P} \quad \frac{1}{T} \sum_{t=1}^{T} \left\| \boldsymbol{y}_t^{\mathrm{f}} - P\big( E\left(\boldsymbol{u}_t^{\mathrm{p}}, \boldsymbol{y}_t^{\mathrm{p}}\right), \boldsymbol{u}_t^{\mathrm{f}} \big) \right\|^2}}_{\text{prediction of } \boldsymbol{y}_t^{\mathrm{f}}}$$

Since the state $\boldsymbol{x}_t$ cannot be measured, the state estimator $E$ and predictor $P$ are coupled in series and trained in the same way as the encoder and decoder in autoencoder. To solve (8), we can utilize modern batch optimization algorithms for deep learning (e.g. Adam by Kingma & Ba, 2014).

Here, we show that $\hat{\boldsymbol{x}}_t := E\left(\boldsymbol{u}_t^{\mathrm{p}}, \boldsymbol{y}_t^{\mathrm{p}}\right)$ is also a state of the system in the ideal situation.

**Theorem 2.** *Assume the training (8) is perfectly done, that is, for all $\boldsymbol{x}^{\mathrm{p}} \in \mathbb{R}^{n_x}$, $\boldsymbol{u}^{\mathrm{p}} \in (\mathbb{R}^{n_u})^{\mathrm{h_p}}$, $\boldsymbol{u}^{\mathrm{f}} \in (\mathbb{R}^{n_u})^{\mathrm{h_f}}$, the equation*

$$P\left(E\left(\boldsymbol{u}^{\mathrm{p}}, \boldsymbol{y}^{\mathrm{p}}\right), \boldsymbol{u}^{\mathrm{f}}\right) = \boldsymbol{y}^{\mathrm{f}}, \tag{9}$$

*where $\boldsymbol{y}^{\mathrm{f}}\left(\boldsymbol{x}^{\mathrm{p}}, \boldsymbol{u}^{\mathrm{p}}, \boldsymbol{u}^{\mathrm{f}}\right) := h^{\mathrm{h_f}}\left(\boldsymbol{x}, \boldsymbol{u}^{\mathrm{f}}\right)$, $\boldsymbol{x}\left(\boldsymbol{x}^{\mathrm{p}}, \boldsymbol{u}^{\mathrm{p}}\right) := f^{\mathrm{h_p}}\left(\boldsymbol{x}^{\mathrm{p}}, \boldsymbol{u}^{\mathrm{p}}\right)$, $\boldsymbol{y}^{\mathrm{p}}\left(\boldsymbol{x}^{\mathrm{p}}, \boldsymbol{u}^{\mathrm{p}}\right) := h^{\mathrm{h_p}}\left(\boldsymbol{x}^{\mathrm{p}}, \boldsymbol{u}^{\mathrm{p}}\right)$ and arguments are omitted for conciseness, holds. Then, for all $\boldsymbol{x}^{\mathrm{p}} \in \mathbb{R}^{n_x}$ and $\boldsymbol{u}^{\mathrm{p}} \in (\mathbb{R}^{n_u})^{\mathrm{h_p}}$, $E\left(\boldsymbol{u}^{\mathrm{p}}, h^{\mathrm{h_p}}\left(\boldsymbol{x}^{\mathrm{p}}, \boldsymbol{u}^{\mathrm{p}}\right)\right)$ is a state equivalent to $f^{\mathrm{h_p}}\left(\boldsymbol{x}^{\mathrm{p}}, \boldsymbol{u}^{\mathrm{p}}\right)$.*

*Proof.* From $\mathrm{h_f}$-observability of the system, the map

$$\Phi^{\mathrm{h_f}} : \left\{ \left(\boldsymbol{u}^{\mathrm{f}}, h^{\mathrm{h_f}}\left(\boldsymbol{x}, \boldsymbol{u}^{\mathrm{f}}\right)\right) \mid \boldsymbol{x} \in \mathbb{R}^{n_x}, \boldsymbol{u}^{\mathrm{f}} \in (\mathbb{R}^{n_u})^{\mathrm{h_f}} \right\} \to \mathbb{R}^{n_x} \text{ that maps } \left(\boldsymbol{u}^{\mathrm{f}}, \boldsymbol{y}^{\mathrm{f}}\right) \mapsto \boldsymbol{x} \tag{10}$$

exists, and the map

$$\Gamma : \mathbb{R}^{n_{\hat{x}}} \times (\mathbb{R}^{n_u})^{\mathrm{h_f}} \to \mathbb{R}^{n_x} \text{ that maps } \left(\hat{\boldsymbol{x}}, \boldsymbol{u}^{\mathrm{f}}\right) \mapsto \Phi^{\mathrm{h_f}}\left(\boldsymbol{u}^{\mathrm{f}}, P\left(\hat{\boldsymbol{x}}, \boldsymbol{u}^{\mathrm{f}}\right)\right) \tag{11}$$

also exists. Then, a map obtained by fixing the second argument of $\Gamma$, e.g.,

$$\Gamma_0(\hat{\boldsymbol{x}}) := \Gamma\left(\hat{\boldsymbol{x}}, \mathbf{0}_{\mathrm{h_f} n_u}\right) \tag{12}$$

maps $\hat{\boldsymbol{x}}$ to $\boldsymbol{x}$, and $\hat{\boldsymbol{x}}$ is proved to be a state. $\qquad\square$

**Remark 3.** *The existence of the map from $\hat{x}$ to $x$ is ensured by the predictor $P$ trained with a common input $\mathbf{0}_{\mathrm{h_f} n_u}$ for all states as in (12). Although this is just one way of constructing a map that is possible under the strong assumption of Theorem 2, this implies that to obtain an appropriate state estimator, the training data must be rich enough to include situations where common inputs are applied in diverse states.*

**Corollary 1.** *When the assumption of Theorem 2 holds, $P$ is the predictor that predicts the sequence of future output from a state and a sequence of future input.*

### 3.2 MODEL PREDICTIVE CONTROL WITH ESTIMATOR & PREDICTOR

Next, the use of the obtained model in MPC is briefly described.

Here we reuse the symbols for the past and future input/output sequences $\boldsymbol{u}_t^{\mathrm{p}}, \boldsymbol{y}_t^{\mathrm{p}}, \boldsymbol{u}_t^{\mathrm{f}}, \boldsymbol{y}_t^{\mathrm{f}}$ defined in (2), but note that the MPC is done after the training and these input-output signals are not the ones at the time of training.

In MPC, a loss function $l_t : \mathbb{R}^{n_u} \times \mathbb{R}^{n_y} \to \mathbb{R}$ that evaluates the input and output at each time $t$ is given. And, at each time step $t$, the optimization problem

$$\underset{\boldsymbol{u}^{\mathrm{f}} \in (\mathbb{R}^{n_u})^{\mathrm{h_f}}}{\text{minimize}} \quad \sum_{k=1}^{\mathrm{h_f}} l_{t+k-1}\left(\left(\boldsymbol{u}^{\mathrm{f}}\right)_{(k-1)n_u+1:kn_u}, \left(\boldsymbol{y}^{\mathrm{f}}\right)_{(k-1)n_y+1:kn_y}\right) \tag{13}$$

$$\text{s.t.} \quad \boldsymbol{y}^{\mathrm{f}} = P\left(E\left(\boldsymbol{u}_t^{\mathrm{p}}, \boldsymbol{y}_t^{\mathrm{p}}\right), \boldsymbol{u}^{\mathrm{f}}\right)$$

$$\left(\boldsymbol{u}^{\mathrm{f}}, \boldsymbol{y}^{\mathrm{f}}\right) \text{ satisfies constraints on the control system}$$

is solved to obtain $\boldsymbol{u}^{\mathrm{f}}$, which is a candidate for the future input sequence $\boldsymbol{u}_t^{\mathrm{f}}$. Then, the candidate for most immediate future input $\left[\boldsymbol{I}_{n_u}, \mathbf{0}_{n_u \times n_u(\mathrm{h_f}-1)}\right] \boldsymbol{u}^{\mathrm{f}}$ is actually applied to the system and moves to the next step $t+1$.

Usually, state-space models are used in MPC, and a state estimator like extended Kalman filter and a predictor are constructed from the models. On the other hand, the state estimator and predictor obtained by the proposed method can be directly used for MPC.

## 4 INTERPRETATION OF PROPOSED METHOD AND MODEL

The proposed method can be viewed as a natural extension of the subspace methods for linear systems, and the similarity with the subspace methods gives interpretability to the model obtained by the proposed method. In this section, we briefly explain the framework of the subspace method and describe how the model obtained by the proposed method can be interpreted based on it.

## 4.1 Relation to Subspace Methods for Linear Dynamical Systems

Here, we consider restricting the state estimator $E$ and predictor $P$ of the proposed method to linear maps and representing them by matrices $\boldsymbol{E} \in \mathbb{R}^{n_{\hat{x}} \times h_{\mathrm{p}}(n_u + n_y)}$ and $\boldsymbol{P} \in \mathbb{R}^{h_{\mathrm{f}} n_y \times (n_x + h_{\mathrm{f}} n_u)}$. When the target system is linear, the optimal state estimator and predictor are known to be linear maps, and can be represented by these matrices if $h_{\mathrm{p}}$ and $h_{\mathrm{f}}$ are sufficiently large. In this case, the training of the state estimator and predictor (8) is reduced to the following nonlinear least-squares problem:

$$\min_{\substack{\boldsymbol{E} \in \mathbb{R}^{n_{\hat{x}} \times h_{\mathrm{p}}(n_u + n_y)} \\ \boldsymbol{P}_x \in \mathbb{R}^{h_{\mathrm{f}} n_y \times n_{\hat{x}}} \\ \boldsymbol{P}_u \in \mathbb{R}^{h_{\mathrm{f}} n_y \times h_{\mathrm{f}} n_u}}} \frac{1}{T} \sum_{t=1}^{T} \left\| \boldsymbol{y}_t^{\mathrm{f}} - \boldsymbol{P}_x \boldsymbol{E} \begin{bmatrix} \boldsymbol{u}_t^{\mathrm{p}} \\ \boldsymbol{y}_t^{\mathrm{p}} \end{bmatrix} - \boldsymbol{P}_u \boldsymbol{u}_t^{\mathrm{f}} \right\|^2, \tag{14}$$

where we split $\boldsymbol{P} = [\boldsymbol{P}_x, \boldsymbol{P}_u]$ for convenience. Also, by defining the matrix $\boldsymbol{U}^{\mathrm{p}} := [\boldsymbol{u}_1^{\mathrm{p}}, \boldsymbol{u}_2^{\mathrm{p}}, \ldots, \boldsymbol{u}_T^{\mathrm{p}}]$ and the matrices $\boldsymbol{Y}^{\mathrm{p}}, \boldsymbol{U}^{\mathrm{f}}, \boldsymbol{Y}^{\mathrm{f}}$ in the same manner, we can rewrite the objective function as follows

$$\min_{\substack{\boldsymbol{E} \in \mathbb{R}^{n_{\hat{x}} \times h_{\mathrm{p}}(n_u + n_y)} \\ \boldsymbol{P}_x \in \mathbb{R}^{h_{\mathrm{f}} n_y \times n_{\hat{x}}} \\ \boldsymbol{P}_u \in \mathbb{R}^{h_{\mathrm{f}} n_y \times h_{\mathrm{f}} n_u}}} \frac{1}{T} \left\| \boldsymbol{Y}^{\mathrm{f}} - \boldsymbol{P}_x \boldsymbol{E} \begin{bmatrix} \boldsymbol{U}^{\mathrm{p}} \\ \boldsymbol{Y}^{\mathrm{p}} \end{bmatrix} - \boldsymbol{P}_u \boldsymbol{U}^{\mathrm{f}} \right\|_F^2. \tag{15}$$

On the other hand, while the actual computational procedure is more cumbersome due to the use of RQ decomposition for numerical benefits, the outline of the subspace methods can be summarized as follows (Peternell et al., 1996):

**(S1)** Solve linear least squares problem

$$\min_{\substack{\widehat{\boldsymbol{P}_x \boldsymbol{E}} \in \mathbb{R}^{h_{\mathrm{f}} n_y \times h_{\mathrm{p}}(n_u + n_y)} \\ \boldsymbol{P}_u \in \mathbb{R}^{h_{\mathrm{f}} n_y \times h_{\mathrm{f}} n_u}}} \frac{1}{T} \left\| \boldsymbol{Y}^{\mathrm{f}} - \widehat{\boldsymbol{P}_x \boldsymbol{E}} \begin{bmatrix} \boldsymbol{U}^{\mathrm{p}} \\ \boldsymbol{Y}^{\mathrm{p}} \end{bmatrix} - \boldsymbol{P}_u \boldsymbol{U}^{\mathrm{f}} \right\|_F^2 \tag{16}$$

to obtain $\widehat{\boldsymbol{P}_x \boldsymbol{E}} \in \mathbb{R}^{h_{\mathrm{f}} n_y \times h_{\mathrm{p}}(n_u + n_y)}$ and $\boldsymbol{P}_u \in \mathbb{R}^{h_{\mathrm{f}} n_y \times h_{\mathrm{f}} n_u}$.

**(S2)** Obtain $\boldsymbol{P}_x$ and $\boldsymbol{E}$ rank-$n_{\hat{x}}$ approximation of $\widehat{\boldsymbol{P}_x \boldsymbol{E}}$ via a 'weighted' SVD.

**(S3)** Calculate state-space representation based on $\boldsymbol{E}$.

As can be seen from the comparison of the two optimization problems (15) and (16), the subspace method is characterized by the fact that instead of solving the nonlinear least-squares problem involving the product of two matrix parameters $\boldsymbol{P}_x$ and $\boldsymbol{E}$, it solves the linear least-squares problem with the product $\widehat{\boldsymbol{P}_x \boldsymbol{E}}$ as the parameter, and then obtain $\boldsymbol{P}_x$ and $\boldsymbol{E}$ via the low-rank approximation in (S2).

The distinct advantage of the procedure (S1)-(S2) is that both linear least-squares and low-rank approximations by SVD yield globally optimal solutions. On the other hand, the solution obtained by (S1)-(S2) is different from the solution of the original optimization problem (15), and there are many variants that have different statistical properties for this misalignment (see e.g., Van Overschee & De Moor, 1994; Peternell et al., 1996; Favoreel et al., 2000).

Therefore, the proposed method can be regarded as a variant of the subspace methods that revert to the underlying nonlinear least-squares problem (15) and extend it to nonlinear systems by replacing linear mappings with neural networks.

## 4.2 Interpretation of Model

It is also possible to interpret the obtained model based on the knowledge in linear system identification. Only in this section, we assume that the target system is the following linear dynamical system with noise

$$\boldsymbol{x}_{t+1} = \boldsymbol{A}\boldsymbol{x}_t + \boldsymbol{B}\boldsymbol{u}_t + \boldsymbol{w}_t, \qquad\qquad \boldsymbol{y}_t = \boldsymbol{C}\boldsymbol{x}_t + \boldsymbol{v}_t, \tag{17}$$

where $\boldsymbol{A} \in \mathbb{R}^{n_x \times n_x}$, $\boldsymbol{B} \in \mathbb{R}^{n_x \times n_u}$, $\boldsymbol{C} \in \mathbb{R}^{n_y \times n_x}$ are the system matrices; $w_t \sim \mathcal{N}\left(\boldsymbol{0}_{n_u \times 1}, \boldsymbol{Q}\right)$ and $v_t \sim \mathcal{N}\left(\boldsymbol{0}_{n_y \times 1}, \boldsymbol{R}\right)$ are process noise and measurement noise, respectively. When the number

of states in the model is accurate ($n_{\hat{x}} = n_x$) and the number of data $T$ and horizons $\mathrm{h_p}, \mathrm{h_f}$ are sufficiently large, the result of steps (S1) and (S2) is consistent with the solution of (15), and what we get as a state estimator $E$ is known to be the Kalman filter for the target system. And, the matrix $\boldsymbol{E}$ becomes the Markov parameters of the Kalman filter, that is,

$$\boldsymbol{E} = \begin{bmatrix} \boldsymbol{E}_u & \boldsymbol{E}_y \end{bmatrix}, \tag{18}$$

$$\boldsymbol{E}_u = \begin{bmatrix} \bar{\boldsymbol{A}}^{\mathrm{h_p}-1}\boldsymbol{B}, \ldots, \bar{\boldsymbol{A}}^2\boldsymbol{B}, \bar{\boldsymbol{A}}\boldsymbol{B}, \boldsymbol{B} \end{bmatrix}, \quad \boldsymbol{E}_y = \begin{bmatrix} \bar{\boldsymbol{A}}^{\mathrm{h_p}-1}\boldsymbol{K}, \ldots, \bar{\boldsymbol{A}}^2\boldsymbol{K}, \bar{\boldsymbol{A}}\boldsymbol{K}, \boldsymbol{K} \end{bmatrix}, \tag{19}$$

$$\bar{\boldsymbol{A}} := \boldsymbol{A} - \boldsymbol{K}\boldsymbol{C}, \quad \boldsymbol{K} := \boldsymbol{A}\hat{\boldsymbol{\Sigma}}\boldsymbol{C}^\top \left( \boldsymbol{C}\hat{\boldsymbol{\Sigma}}\boldsymbol{C}^\top + \boldsymbol{R} \right)^{-1} \tag{20}$$

where $\boldsymbol{K} \in \mathbb{R}^{n_x \times n_y}$ is the Kalman gain and $\hat{\boldsymbol{\Sigma}}$ is the solution to the discrete-time algebraic Riccati equation

$$\hat{\boldsymbol{\Sigma}} = \boldsymbol{A}\hat{\boldsymbol{\Sigma}}\boldsymbol{A}^\top - \boldsymbol{A}\hat{\boldsymbol{\Sigma}}\boldsymbol{C}^\top \left( \boldsymbol{C}\hat{\boldsymbol{\Sigma}}\boldsymbol{C}^\top + \boldsymbol{R} \right)^{-1} \boldsymbol{C}\hat{\boldsymbol{\Sigma}}\boldsymbol{A}^\top + \boldsymbol{Q}. \tag{21}$$

From the Kalman filter designed for the target system, we can retrieve the frequency bands that are important for state estimation or the noise characteristics in the target system. Conversely, we can also evaluate whether the obtained state estimator is reasonable or not, based on the knowledge of the target system. For the state estimator $E$ implemented by a neural network, $\boldsymbol{E}_u$ and $\boldsymbol{E}_y$ correspond to $\frac{\partial E}{\partial \boldsymbol{u}^\mathrm{p}}$ and $\frac{\partial E}{\partial \boldsymbol{y}^\mathrm{p}}$ at the operating point, respectively. And by calculating these, the characteristics of the obtained state estimator can be evaluated.

On the other hand, the predictor $\boldsymbol{P}_x$ and $\boldsymbol{P}_u$ are an extended observability matrix and the Markov parameters of the target system, that is,

$$\boldsymbol{P}_x = \begin{bmatrix} \boldsymbol{C} \\ \boldsymbol{C}\boldsymbol{A} \\ \vdots \\ \boldsymbol{C}\boldsymbol{A}^{\mathrm{h_f}-1} \end{bmatrix}, \quad \boldsymbol{P}_u = \begin{bmatrix} \boldsymbol{O} & \boldsymbol{O} & \cdots & \cdots & \boldsymbol{O} \\ \boldsymbol{C}\boldsymbol{B} & \boldsymbol{O} & \cdots & & \\ \boldsymbol{C}\boldsymbol{A}\boldsymbol{B} & \boldsymbol{C}\boldsymbol{B} & \ddots & & \vdots \\ \vdots & \vdots & \ddots & & \\ \boldsymbol{C}\boldsymbol{A}^{\mathrm{h_f}-2}\boldsymbol{B} & \boldsymbol{C}\boldsymbol{A}^{\mathrm{h_f}-3}\boldsymbol{B} & \cdots & \boldsymbol{C}\boldsymbol{B} & \boldsymbol{O} \end{bmatrix}, \quad \boldsymbol{O} := \boldsymbol{0}_{n_y \times n_u}. \tag{22}$$

and characterize the unforced response and input-output characteristics of the target system. For nonlinear predictors, $\boldsymbol{P}_x$ and $\boldsymbol{P}_u$ correspond to $\frac{\partial P}{\partial \hat{\boldsymbol{x}}}$ and $\frac{\partial P}{\partial \boldsymbol{y}^\mathrm{p}}$, respectively, from which the characteristics of the target system at the operating point can be illustrated.

## 5 ILLUSTRATIVE EXAMPLE

Next, we demonstrate the proposed method through a toy example, where the identification and MPC of a cascaded tanks system (Wigren & Schoukens, 2013) is performed.

The state equation of the system is as follows:

$$\boldsymbol{x}_{t+1} = \begin{bmatrix} x_{t+1,1} \\ x_{t+1,2} \end{bmatrix} = \begin{bmatrix} \max\left( x_{t,1} - k_1\sqrt{x_{t,1}} + k_2\left(u_t + w_t\right), 0 \right) \\ \max\left( x_{t,2} + k_3\sqrt{x_{t,1}} - k_4\sqrt{x_{t,2}}, 0 \right) \end{bmatrix}, \quad y_t = x_{t,2} + v_t, \tag{23}$$

where $n_x = 2$, $n_u = n_y = 1$, $k_1 = 0.5$, $k_2 = 0.4$, $k_3 = 0.2$, $k_4 = 0.3$, $w_t \sim \mathcal{N}\left(0, 0.35^2\right)$, and $v_t \sim \mathcal{N}\left(0, 0.15^2\right)$. The state variables $x_{t,1}$ and $x_{t,2}$ are the levels of the upper and the lower tank, and $u_t$ denotes the applied voltage to the pump at $t$. To obtain the training dataset, the system is excited by a sequence of random input

$$u_t = \min\left( \max\left( u_t^0, 0 \right), 5 \right), \qquad u_t^0 \sim \mathcal{N}(2, 5^2), \tag{24}$$

and a sequence of data $\{(u_t, y_t)\}_{t=-19}^{1000019}$ is obtained.

On training the state estimator $E$ and predictor $P$, We choose the hyperparameters of $n_{\hat{x}} = 2$, $\mathrm{h_p} = \mathrm{h_f} = 20$. $E$ and $P$ are implemented by neural networks with two and three hidden layers, respectively, where each layer contains 64 ReLU neurons and every layers are fully connected. For training, we used the Adam optimizer in PyTorch (Paszke et al., 2019) with the default settings. To prevent overfitting, the $90\%$ of the samples were used for training, and the training was continued

until the fit to the remaining $10\%$ of the validation data did not improve for 1000 consecutive iterations.

Then, the MPC controller which solves the optimization problem (13) with the cost function

$$l_t(u_t, y_t) := (y_t - r_t)^2 + 0.05 (u_t - u_{t-1})^2 \tag{25}$$

and the constraint $0 \leq u_t \leq 5$ at each time $t$ is implemented with the obtained state estimator and predictor. Here, $r_t \in \mathbb{R}^{n_y}$ is the reference signal. To solve the optimization problem, and we used Levenberg-Marquardt Algorithm (Moré, 1978).

The result of the tracking control up to $t = 400$ is shown in figure 2. In the figure, the applied control input $u_t$, the measured output $y_t$ (red line), reference signal $r_t$ (dotted black line), and the true water levels in the tanks $x_{t,1}, x_{t,2}$ (blue lines) are shown. In addition, the green lines in each plot show $\boldsymbol{u}_t^{\mathrm{f}}$ and $\boldsymbol{y}_t^{\mathrm{f}}$ at $t = 400$, respectively. As can be seen from the figure, appropriate MPC is performed using the obtained state estimator and predictor.

Figure 2: Result of tracking control

Then, to support the interpretation discussed in section 4, figure 3 shows the visualization of the state estimator and predictor at the operating point at $t = 50$, where the change in water level is slow and nonlinearity is expected to be weak. The dashed lines in figures 3(a)-(c) and the bitmap on the right in figure 4(d) show the corresponding properties of the linearized system of (23) at the operating point. Since linear systems also have degrees of freedom in how they coordinate in state space, a transformation matrix $\boldsymbol{\Phi} := \boldsymbol{P}_x^\dagger \frac{\partial P}{\partial \tilde{\boldsymbol{x}}} \in \mathbb{R}^{n_x \times n_x}$ is used to align the coordinate system. From figures 3(a) and (b), the state estimator $\tilde{E}$ obtained by the proposed method agrees well with the Kalman filter for the linearized system of the true system, and it can be confirmed that the proposed method yields almost optimal state estimators as expected for subspace methods in an ideal situation with sufficient data. It can also be seen that the predictor is consistent with the true system.

Moreover, figure 4 was obtained at the operating point at $t = 380$, where the nonlinearity is considered to be more strongly observed. Although the results in this case are similar to those in the linearized system to some extent, differences in the characteristics can be seen. For example, in figure 4(d), the Toeplitz structure of linear systems is partially lost, indicating the existence of nonlinearity. In figures 4(a) and (b), it can be seen that an estimator that is less dependent on the output and more focused on the recent input than the Kalman filter for the linearized system is obtained.

(a) Markov parameters of state estimator for $\boldsymbol{u}^{\mathrm{p}}$ $\left(\text{solid} : \left(\frac{\partial E}{\partial u^{\mathrm{p}}}\right)_{:,j}, \text{dashed} : \left(\boldsymbol{\Phi}^{-\top}\boldsymbol{E}_u\right)_{:,j}\right)$

(c) Predictor unforced response $\left(\text{solid} : \left(\frac{\partial P}{\partial \tilde{\boldsymbol{x}}}\right)_{i,:}, \text{dashed} : \left(\boldsymbol{P}_x\boldsymbol{\Phi}\right)_{i,:}\right)$

(b) Markov parameters of state estimator for $\boldsymbol{y}^{\mathrm{p}}$ $\left(\text{solid} : \left(\frac{\partial E}{\partial \boldsymbol{y}^{\mathrm{p}}}\right)_{:,j}, \text{dashed} : \left(\boldsymbol{\Phi}^{-\top}\boldsymbol{E}_y\right)_{:,j}\right)$

(d) Predictor Markov parameters

Figure 3: Visualization of $E$ and $P$ at $t = 50$

(a) Markov parameters of state estimator for $\boldsymbol{u}^{\mathrm{p}}$ $\left(\text{solid} : \left(\frac{\partial E}{\partial u^{\mathrm{p}}}\right)_{:,j}, \text{dashed} : \left(\boldsymbol{\Phi}^{-\top}\boldsymbol{E}_u\right)_{:,j}\right)$

(c) Predictor unforced response $\left(\text{solid} : \left(\frac{\partial P}{\partial \tilde{\boldsymbol{x}}}\right)_{i,:}, \text{dashed} : \left(\boldsymbol{P}_x\boldsymbol{\Phi}\right)_{i,:}\right)$

(b) Markov parameters of state estimator for $\boldsymbol{y}^{\mathrm{p}}$ $\left(\text{solid} : \left(\frac{\partial E}{\partial \boldsymbol{y}^{\mathrm{p}}}\right)_{:,j}, \text{dashed} : \left(\boldsymbol{\Phi}^{-\top}\boldsymbol{E}_y\right)_{:,j}\right)$

(d) Predictor Markov parameters

Figure 4: Visualization of $E$ and $P$ at $t = 380$

To verify the validity of placing the bottleneck, we evaluated the performance with different widths of the bottleneck $n_{\hat{x}}$. All settings except $n_{\hat{x}}$ and the realized value of the stochastic noise $w_t$, $v_t$ are set to be identical to the case of $n_{\hat{x}} = 2$ and 60 trials were conducted with different realizations of the stochastic noise.

The results are summarized in figure 5. The loss for the validation dataset in figure 5(a) shows that

Figure 5: Width of bottleneck $n_{\hat{x}}$ and performance

the performance does not degrade until the width of the bottleneck $n_{\hat{x}}$ goes below the actual state dimension $n_x = 2$. Also, the performance of the MPC calculated by $\sum_{t=\text{h}_\text{p}+1}^{400} l_t(u_t, x_{t,2})$ does not show degradation until $n_{\hat{x}} < n_x = 2$ as shown in figure 5(b), and these results support the use of the bottleneck to provide interpretability.

## 6 CONCLUSION

In this paper, we proposed a new nonlinear subspace identification method that produces state estimator and predictor directly usable for nonlinear MPC. It is theoretically shown that by training a neural network with a bottleneck that performs regression on input-output sequences of a length that provides observability in both past and future directions, a state estimator and a predictor are formed across the bottleneck layer. The relationship between this method and the subspace identification method, as well as the interpretation of the obtained model using this relationship, is also explained, and its use is demonstrated through an example.

This research is still in its early stages, and there is much work to be done in the future. For example, a more precise condition for yielding a state estimator is desired. The current proof makes use of the assumption that zero-input responses from all states have been learned, and while the fact that zero-input responses constitute states is often used in this type of research (Verdult & Scherpen, 2004), more precise conditions would be useful for experiment design. It also appears that the technique of inverse optimal control (Ab Azar et al., 2020) can be applied to the interpretation of the obtained state estimator. Finally, since noise with high-order dynamics is ubiquitous (Bak et al., 1987) and the synthesis of state estimator for such a system is prone to failure, it is important to develop a mechanism to focus on useful states.

## REFERENCES

Nematollah Ab Azar, Aref Shahmansoorian, and Mohsen Davoudi. From inverse optimal control to inverse reinforcement learning: A historical review. *Annual Reviews in Control*, 50:119–138, 2020. ISSN 1367-5788. doi: https://doi.org/10.1016/j.arcontrol.2020.06.001. URL https://www.sciencedirect.com/science/article/pii/S1367578820300511.

Dirk Aeyels. Generic observability of differentiable systems. *SIAM Journal on Control and Optimization*, 19(5):595–603, 1981. doi: 10.1137/0319037. URL https://doi.org/10.1137/0319037.

Per Bak, Chao Tang, and Kurt Wiesenfeld. Self-organized criticality: An explanation of the 1/f noise. *Phys. Rev. Lett.*, 59:381–384, Jul 1987. doi: 10.1103/PhysRevLett.59.381. URL https://link.aps.org/doi/10.1103/PhysRevLett.59.381.

Gerben I. Beintema, Roland Toth, and Maarten Schoukens. Non-linear state-space model identification from video data using deep encoders. *IFAC-PapersOnLine*, 54(7):697–701, 2021. ISSN 2405-8963. doi: https://doi.org/10.1016/j.ifacol.2021.08.442. URL https://www.sciencedirect.com/science/article/pii/S2405896321012167. 19th IFAC Symposium on System Identification SYSID 2021.

Wouter Favoreel, Bart De Moor, and Peter Van Overschee. Subspace state space system identification for industrial processes. *Journal of Process Control*, 10(2):149–155, 2000. ISSN 0959-1524. doi: https://doi.org/10.1016/S0959-1524(99)00030-X. URL https://www.sciencedirect.com/science/article/pii/S095915249900030X.

I. Goethals, K. Pelckmans, L. Hoegaerts, J. Suykens, and B. De Moor. Subspace intersection identification of hammerstein-wiener systems. In *Proceedings of the 44th IEEE Conference on Decision and Control*, pp. 7108–7113, 2005. doi: 10.1109/CDC.2005.1583307.

Daniel Hsu, Sham M. Kakade, and Tong Zhang. A spectral algorithm for learning hidden markov models. *Journal of Computer and System Sciences*, 78(5):1460–1480, 2012. ISSN 0022-0000. doi: https://doi.org/10.1016/j.jcss.2011.12.025. URL https://www.sciencedirect.com/science/article/pii/S0022000012000244. JCSS Special Issue: Cloud Computing 2011.

Kirthevasan Kandasamy, Maruan Al-Shedivat, and Eric P Xing. Learning hmms with nonparametric emissions via spectral decompositions of continuous matrices. In D. Lee, M. Sugiyama, U. Luxburg, I. Guyon, and R. Garnett (eds.), *Advances in Neural Information Processing Systems*, volume 29. Curran Associates, Inc., 2016. URL https://proceedings.neurips.cc/paper/2016/file/afe434653a898da20044041262b3ac74-Paper.pdf.

Petros Karamanakos, Eyke Liegmann, Tobias Geyer, and Ralph Kennel. Model predictive control of power electronic systems: Methods, results, and challenges. *IEEE Open Journal of Industry Applications*, 1:95–114, 2020. doi: 10.1109/OJIA.2020.3020184.

Tohru Katayama. *Subspace methods for system identification*. Springer, 1 edition, 2005.

Tohru Katayama and Hajime Ase. Linear approximation and identification of mimo wiener–hammerstein systems. *Automatica*, 71:118–124, 2016. ISSN 0005-1098. doi: https://doi.org/10.1016/j.automatica.2016.04.040. URL https://www.sciencedirect.com/science/article/pii/S0005109816301650.

Yoshinobu Kawahara, Takehisa Yairi, and Kazuo Machida. A kernel subspace method by stochastic realization for learning nonlinear dynamical systems. In B. Schölkopf, J. Platt, and T. Hoffman (eds.), *Advances in Neural Information Processing Systems*, volume 19. MIT Press, 2007. URL https://proceedings.neurips.cc/paper/2006/file/96629f1aac6ddb7a7cfa82574b6722d4-Paper.pdf.

Diederik P Kingma and Jimmy Ba. Adam: A method for stochastic optimization. *arXiv preprint arXiv:1412.6980*, 2014.

Lennart Ljung, Carl Andersson, Koen Tiels, and Thomas B. Schön. Deep learning and system identification. *IFAC-PapersOnLine*, 53(2):1175–1181, 2020a. ISSN 2405-8963. doi: https://doi.org/10.1016/j.ifacol.2020.12.1329. URL https://www.sciencedirect.com/science/article/pii/S2405896320317353. 21st IFAC World Congress.

Lennart Ljung, Tianshi Chen, and Biqiang Mu. A shift in paradigm for system identification. *International Journal of Control*, 93(2):173–180, 2020b. doi: 10.1080/00207179.2019.1578407. URL https://doi.org/10.1080/00207179.2019.1578407.

Daniele Masti and Alberto Bemporad. Learning nonlinear state-space models using deep autoencoders. In *Proc. of the 57th IEEE Conference on Decision and Control (CDC 2018)*, pp. 3862–3867, 2018. doi: 10.1109/CDC.2018.8619475.

P.E. Moraal and J.W. Grizzle. Observer design for nonlinear systems with discrete-time measurements. *IEEE Transactions on Automatic Control*, 40(3):395–404, 1995. doi: 10.1109/9.376051.

Jorge J Moré. The Levenberg-Marquardt algorithm: implementation and theory. In *Numerical analysis*, pp. 105–116. Springer, 1978.

Adam Paszke, Sam Gross, Francisco Massa, Adam Lerer, James Bradbury, Gregory Chanan, Trevor Killeen, Zeming Lin, Natalia Gimelshein, Luca Antiga, Alban Desmaison, Andreas Kopf, Edward Yang, Zachary DeVito, Martin Raison, Alykhan Tejani, Sasank Chilamkurthy, Benoit Steiner, Lu Fang, Junjie Bai, and Soumith Chintala. PyTorch: An imperative style, high-performance deep learning library. In H. Wallach, H. Larochelle, A. Beygelzimer, F. d'Alché-Buc, E. Fox, and R. Garnett (eds.), *Advances in Neural Information Processing Systems 32*, pp. 8024–8035. Curran Associates, Inc., 2019.

Klaus Peternell, Wolfgang Scherrer, and Manfred Deistler. Statistical analysis of novel subspace identification methods. *Signal Processing*, 52(2):161–177, 1996.

S. Joe Qin and Thomas A. Badgwell. An overview of nonlinear model predictive control applications. In Frank Allgöwer and Alex Zheng (eds.), *Nonlinear Model Predictive Control*, volume 26 of *Progress in Systems and Control Theory*, pp. 369–392. Birkhäuser Basel, 2000. ISBN 978-3-0348-8407-5.

Gijs van der Veen, Jan-Willem van Wingerden, Marco Bergamasco, Marco Lovera, and Michel Verhaegen. Closed-loop subspace identification methods: an overview. *IET Control Theory & Applications*, 7(10):1339–1358, 2013. doi: https://doi.org/10.1049/iet-cta.2012. 0653. URL https://ietresearch.onlinelibrary.wiley.com/doi/abs/10. 1049/iet-cta.2012.0653.

Peter Van Overschee and Bart De Moor. N4SID: Subspace algorithms for the identification of combined deterministic-stochastic systems. *Automatica*, 30(1):75–93, 1994.

Sergio Vazquez, Jose I. Leon, Leopoldo G. Franquelo, Jose Rodriguez, Hector A. Young, Abraham Marquez, and Pericle Zanchetta. Model predictive control: A review of its applications in power electronics. *IEEE Industrial Electronics Magazine*, 8(1):16–31, 2014. doi: 10.1109/MIE.2013. 2290138.

Vincent Verdult and Jacquelien Scherpen. Identification of nonlinear state-space systems using zero-input responses. In *Proc. of the 16th international symposium on mathematical theory of networks and systems (MTNS 2004)*, pp. 1–11, 2004.

Michel Verhaegen and David Westwick. Identifying mimo hammerstein systems in the context of subspace model identification methods. *IFAC Proceedings Volumes*, 29(1):4092–4097, 1996. ISSN 1474-6670. doi: https://doi.org/10.1016/S1474-6670(17)58321-4. URL https://www. sciencedirect.com/science/article/pii/S1474667017583214. 13th World Congress of IFAC, 1996, San Francisco USA, 30 June - 5 July.

Torbjörn Wigren and Johan Schoukens. Three free data sets for development and benchmarking in nonlinear system identification. In *Proc. of 2013 European Control Conference (ECC)*, pp. 2933–2938. IEEE, 2013.

## A APPENDIX

### A.1 IDENTIFICATION OF $f$ AND $h$ IN STATE-SPACE EQUATION

A method of obtaining the state-space model from the state estimator and predictor is briefly explained here.

The model of the output map $h : \boldsymbol{x}_t \mapsto \boldsymbol{y}_t$, the map $\hat{h} : \mathbb{R}^{n_{\hat{x}}} \to \mathbb{R}^{n_y}$ is obtained by extracting the first prediction of the predictor $P$ as

$$\hat{h}(\hat{\boldsymbol{x}}) := \left[ \boldsymbol{I}_{n_y}, \boldsymbol{0}_{n_y \times (h_f - 1)n_y} \right] P(\hat{\boldsymbol{x}}, 0).  \tag{26}$$

As for the model of the state-transition map $\hat{f} : \mathbb{R}^{n_{\hat{x}}} \times \mathbb{R}n_u \to \mathbb{R}^{n_{\hat{x}}}$, by estimating the state sequence $\{\hat{\boldsymbol{x}}_t\}_{t=1}^T$ with $E$ as

$$\hat{\boldsymbol{x}}_t = E\left(\boldsymbol{u}_t^{\mathrm{p}}, \boldsymbol{y}_t^{\mathrm{p}}\right), \tag{27}$$

the construction of $\hat{f}$ is reduced to the fitting of a static map as

$$\underset{\hat{f}}{\text{minimize}} \, \frac{1}{T} \sum_{t=1}^T \left\| \hat{\boldsymbol{x}}_{t+1} - \hat{f}\left(\hat{\boldsymbol{x}}_t, \boldsymbol{u}_t\right) \right\|^2.$$