Differentiable Analog Quantum Computing for Optimization and Control

Abstract

We formulate the first differentiable analog quantum computing framework with specific parameterization design at the analog signal (pulse) level to better exploit near-term quantum devices via variational methods. We further propose a scalable approach to estimate the gradients of quantum dynamics using a forward pass with Monte Carlo sampling, which leads to a quantum stochastic gradient descent algorithm for scalable gradient-based training in our framework. Applying our framework to quantum optimization and control, we observe a significant advantage of differentiable analog quantum computing against SOTAs based on parameterized digital quantum circuits by *orders of magnitude*.

1 Introduction

Quantum computing has promised unprecedented improvement in our computational ability to tackle classically intractable problems. Despite of the rapid development of quantum hardware [2, 62], near-term quantum computers are still likely to have very restricted hardware resources, where the limited number of "qubits" and non-negligible machine noises would impede the implementation of large-scale quantum algorithms. Recent research results in both computer science [57] and physics [42] suggest a promising approach of designing resource-efficient *Noisy Intermediate-Scale Quantum (NISQ)* [50] applications by breaking quantum circuit abstractions and directly designing applications at the pulse-level control of quantum machines.[1] The benefits of this analog-oriented approach have been witnessed in the history of classical analog computing that predates digital computing due to relaxed hardware requirement and plays an important role in domain applications such as simulation.

One leading algorithmic paradigm on NISQ computers is the *Variational Quantum Algorithm (VQA)* with a few prominent examples like the Variational Quantum Eigensolver (VQE) [49], quantum approximate optimization algorithm (QAOA) [20], and more in [4]. Specifically, VQA uses *parametrized quantum models* to characterize loss functions, in particular those from quantum physics, which are potentially intractable for classical computing [26]. These parameters will then be optimized, usually through gradient-based approaches, to minimize the given loss function. Conventionally, parameterized quantum models are typically quantum circuits where each gate is parameterized by classical variables. Moreover, auto-differentiation techniques have been recently developed (e.g., [46, 56, 63]) for a scalable quantum gradient calculation on parameterized quantum circuits. We henceforth refer this existing framework as *differentiable digital quantum computing*.

Although parameterized quantum circuits are designed for NISQ applications, implementing (digital) quantum circuits still incurs non-negligible overheads, which significantly restricts the size of parametrized circuits that can be executed faithfully on NISQ machines. Moreover, the current parameterization in VQAs is also largely restricted by available parameterized gates and how they compose circuits, which in turn limits the expressive power of VQAs. A natural alternative to the

---

[1] Pulse-level control is available on IBMQ computers.

36 current digital parameterization is to perform VQA directly on *parametrized analog signals (pulses)*,
37 either on digital quantum machines with pulse-level controls, *or* on general analog quantum hardware.
38 Indeed, parameterized analog pulses have the potential for more efficient NISQ implementation and
39 better expressiveness as suggested in a recent perspective paper [42], which could be a more favorable
40 parameterization for NISQ applications even when digital quantum gates are available.

41 However, there is not yet a systematic study of the analog parameterization for VQAs, its scalable
42 training, and its quantitative benefits in achieving high-quality solutions in VQA applications.

43 **Contributions.** We conduct the first sys-
44 tematic study of the parameterization and
45 scalable training of analog VQAs, which
46 we call *differentiable analog quantum*
47 *computing*. We also leverage our scal-
48 able training to demonstrate the quanti-
49 tative benefits of the analog parameteri-
50 zation for specific VQA applications.

	Diff. Quantum	Neural ODE	Diff. Physics
$\frac{\mathrm{d}}{\mathrm{d}t}\mathbf{x}(t) =?$	$-iH(\mathbf{v},t)\mathbf{x}(t)$	$f(\mathbf{x}(t),\mathbf{v})$	$f(\mathbf{x}(t),\mathbf{v})$
Parametrization	Basis Function	Neural Network	Dynamics Equation
Forward	Time Evolution	Forward Pass	Time Integration
Backward	MC Integration	Autodiff	Auto/Manual Diff.
Device	Quantum	Classical	Classical

Table 1: Machine learning in different dynamical systems. A
diagram in Appendix A illustrates their connections.

51 Specifically, we formulate the general differentiable analog quantum computing as a control problem,
52 $\min_{\mathbf{v}} \mathcal{L}(\mathbf{v})$, where the loss function $\mathcal{L}(\mathbf{v})$ is calculated from the $\mathbf{v}$-parametrized quantum state
53 $\mathbf{x}(T;\mathbf{v})$ generated by quantum machines at the evolution time $t = T$. Intuitively, this control problem
54 is no different from any classical ones except that the evolution of the quantum state in $[0, T]$ is
55 governed by the Schrödinger equation

$$\frac{\mathrm{d}}{\mathrm{d}t}\mathbf{x}(t) = -iH(\mathbf{v},t)\mathbf{x}(t), \tag{1}$$

56 where the Hamiltonian operator $H(\mathbf{v}, t)$ can be much more flexibly parameterized in $\mathbf{v}$ compared
57 with parameterized quantum circuits (detailed in Section 3.2), and i is the imaginary unit.

58 We also develop a scalable Monte Carlo integration technique of computing quantum-related gradients
59 from the loss function $\mathcal{L}(\mathbf{v})$. A well-known difficulty in computing quantum-related gradients by
60 classical means is the exponential cost associated with classical simulation of the quantum system.
61 Thus, any scalable solution must leverage quantum machines to compute the gradients for themselves.
62 Existing "auto-differentiation" techniques for parameterized quantum circuits (e.g., [46, 56, 63])
63 are designed for discrete-time evolution and the basic parameterized units (i.e., gates) are described
64 by finite-dimensional matrices. Differential analog quantum computing exploits parameterization
65 of continuous-time evolution and $H(\mathbf{v}, t)$ refers to a parameterized model from a functional space.
66 Our Monte Carlo integration technique is designed to bridge this technical gap, which is later
67 integrated with the stochastic gradient descent (SGD) for the entire framework for fast convergence
68 and robustness against empirical noise. We further illustrate that our quantum stochastic gradient
69 descent could still work with approximate descriptions of $H(\mathbf{v}, t)$ for domain applications.

70 An analogy could be drawn between our approach and classical deep learning, as summarized
71 in Table 1. *Neural ODEs* [40, 10] view the structure of ResNet [27], $\mathbf{x}_{n+1} = \mathbf{x}_n + f(\mathbf{x}_n, \theta)$, as the
72 solving of an ordinary differential equation,

$$\frac{\mathrm{d}}{\mathrm{d}t}\mathbf{x}(t) = f(\mathbf{x}(t),\mathbf{v}), \tag{2}$$

73 with $f(\cdot)$ as the network layer, $\mathbf{v}$ the network parameter, and $\mathbf{x}(t)$ the hidden state. This formula
74 is similar to our system in (1), although we adopt a different parametrization than neural networks.
75 Similarly, *differentiable physics* (e.g., [31]), which incorporates physical simulation into learning
76 process, leverages existing numerical solvers and the autodiff functionality of deep learning with
77 backpropagation to compute gradients of a physical or dynamical system, then integrates them into a
78 neural network. This approach has proven to accelerate learning and generalization.

79 Differentiable analog quantum computing can be deemed as a special form of differentiable physics
80 at the quantum scale. Similar to the promise of differentiable physics or neural ODEs, we have also
81 observed the advantageous performance of differentiable analog quantum computing against the
82 conventional parameterized quantum circuits by orders of magnitude in major VQA applications
83 like optimization (Section 4) and control (Section 5). Our auto-differentiation technique in quantum
84 is however less efficient than classical ones that leverage the chain rule and the forward/backward
85 propagation. This is due to the quantum no-cloning theorem [61] which prevents us from storing
86 any arbitrary immediate state during quantum computation. So, we develop a sampling technique to
87 compute gradients. To sum up, the key contributions of this work include:

- A formulation of differentiable, resource-efficient *analog* quantum computing framework (Sec. 3),
- A scalable technique of computing gradients by Monte Carlo sampling with SGD (Sec. 3.3),
- Formal analysis on correctness, efficiency, and robustness that showcases *exponential reduction of computational complexity* and bounded errors with approximate machine description (Sec. 3.4-3.6),
- Applications of our framework on quantum optimization (Sec. 4) and control (Sec. 5), with demonstrated advantages by *orders of magnitude* against parameterized quantum circuits.

2 Related work

Learning for dynamics and control. Dynamical systems have widely been used to interpret and improve the design of machine learning algorithms. Compared to traditional discrete layers, Neural ODEs [24] demonstrate that continuous modeling of neural network can better learn the continuous structures [22, 54] with infinite depth [44] and constant memory cost [66]. Besides neural networks, differentiable physics [16] also computes analytic gradients of classical dynamical systems like rigid body [14], articulated body [23, 60, 52], soft body [19, 21], and fluids [58, 59, 29]. Those methods have made great success on design [41], control [28] and system identification [38] tasks in the macroworld. Our framework, as the first differentiable dynamics for quantum computing, could have tremendous potential in chemistry and physics applications.

Quantum machine learning & optimal control. Quantum machine learning is a fast-developing emerging field (e.g., see the survey [5]) where variational quantum algorithms (VQAs) (e.g., see the survey [4] are one of the most promising candidates for NISQ applications. Quantum optimal control (succinctly, quantum control) aims to achieve a desired response from the quantum system by controlling the system parameters [18, 6]. Quantum control theory has empowered the growth of quantum technologies and found applications in several fields, ranging from molecular chemistry to quantum computing [53, 13]. The connection between quantum control theory and VQAs has been discussed recently [42, 45]. Several optimization algorithms have been developed to solve quantum control problems, including the Krotov method [48], monotonically convergence algorithms [65], non-iterative algorithms [64], the *GRadient Ascent Pulse Engineering (GRAPE)* algorithm [34], the *Chopped RAndom-Basis (CRAB)* algorithm [8], etc. The development of quantum computing also opens up the possibility of solving quantum control problems with quantum computers [17, 9]. These proposals take the approach of hybridizing quantum simulations with classical optimization routines. Nevertheless, they either do not support gradient-based methods or compute the gradients in a non-scalable way (e.g., via classical simulation), which significantly limits their performance especially comparing to ours. Existing pulse-level variational algorithms [45, 39, 15] do not discuss their direct application to quantum analog machines and can not compute gradients analytically on quantum machines, while our paper resolves this problem.

3 Differentiable Analog Quantum Computing

Similar to classical dynamical systems, quantum systems also have states, governing equations, and observations, so there naturally exist plenty of optimization [47], control [12], and learning [5] problems for quantum computing. Inspired by the success of gradient-based approach in the classical domain, we propose a differentiable framework to compute the gradients of parametrized analog control signals on quantum computers, based on a "*forward simulation* with *stochastic sampling*" (see the workflow in Figure 1).

3.1 Quantum preliminaries

A *qubit* (or *quantum bit*) is the analogue of a classical bit in quantum computation. It is a two-level quantum-mechanical system described by the Hilbert space $\mathbb{C}^2$. We use Dirac notation $|\psi\rangle$ to denote quantum states (i.e., unit vectors) ψ in $\mathcal{H}$. For example, the classical "0" and "1" are represented by $|0\rangle = \begin{bmatrix} 1 \\ 0 \end{bmatrix}$ and $|1\rangle = \begin{bmatrix} 0 \\ 1 \end{bmatrix}$. One qubit states could be in any linear combination of $|0\rangle$ and $|1\rangle$, which is called *superposition*. An n-qubit state is a unit vector in the Kronecker tensor product $\otimes$ of n single-qubit Hilbert spaces, i.e., $\mathcal{H} = \otimes_{i=1}^{n} \mathbb{C}^2 \cong \mathbb{C}^{2^n}$, whose dimension is exponential in n. For an n by m matrix A and a p by q matrix B, their Kronecker product is an np by mq matrix where $(A \otimes B)_{pr+u,qs+v} = A_{r,s} B_{u,v}$. The **complex conjugate transpose** of $|\psi\rangle$ is denoted as $\langle\psi| = |\psi\rangle^{\dagger}$ († is the Hermitian conjugate). Therefore, the **inner product** of ϕ and ψ could be written as $\langle\phi|\psi\rangle$.

The time evolution of quantum states under Schödinger equation is specified by the (time-dependent) Hermitian matrix $H(t)$ over the corresponding Hilbert space, known as the *Hamiltonian* of the

Figure 1: **The workflow of differentiable analog quantum computing.** In this 2-qubit example, the system starts with an initial ground state ψ_0 of dimension $4 = 2^2$ and evolves through the time following the Schrödinger equation (1). We control the dynamics of this quantum system by specifying the time-dependent Hamiltonian $H(\mathbf{v}, t)$, parameterized by trainable variables $\mathbf{v}$. In the end of the process, we measure the system and get a real-valued loss value, $\mathcal{L}$. The derivatives are computed as in the right box. Quantum computers cannot store computational graphs, so we propose to sample a time t in the forward simulation and apply the parameter shift rule to compute the gradients. The derivatives are then used in the feedback loop to update $\mathbf{v}$ optimizing $\mathcal{L}$.

141 quantum system. Typical single-qubit Hamiltonians include the famous *Pauli matrices*:

$$I = \begin{bmatrix} 1 & 0 \\ 0 & 1 \end{bmatrix}, X = \begin{bmatrix} 0 & 1 \\ 1 & 0 \end{bmatrix}, Y = \begin{bmatrix} 0 & -i \\ i & 0 \end{bmatrix}, Z = \begin{bmatrix} 1 & 0 \\ 0 & -1 \end{bmatrix}. \tag{3}$$

142 Similarly, a multi-qubit Hamiltonian can be built from the Pauli group consisting of tensor products
143 of Pauli matrices. Conventionally we write X_j (Y_j, Z_j) for a multi-qubit Hamiltonian to indicate the
144 tensor product of multiple identity matrices while the j-th operand is X (Y, Z), which represents
145 operations on the j-th subsystem.

146 *Quantum measurement* refers to the procedure of extracting classical information from quantum
147 systems. It is characterized by an Hermitian matrix M called the *observable*. Measuring a quantum
148 state $|\psi\rangle$ with observable M is modelled as a random variable whose expectation value is $\langle\psi| M |\psi\rangle$.

3.2   Problem formulations

150 Most computational tasks in quantum simulation and control, like finding the ground state of a physics
151 system, can be formulated as the following optimization problem. Given a quantum observable M
152 and an initial state $|\psi(0)\rangle = |\psi_0\rangle$, we seek for a parameter vector $\mathbf{v}$ by minimizing the loss function

$$\mathcal{L} = \langle\psi(T)| M |\psi(T)\rangle, \tag{4}$$

153 where the evolution of $|\psi(t)\rangle$ from $t = 0$ to $t = T$ subject to the Schrödinger equation (1). Here,
154 $H(\mathbf{v}, t)$ is a Hamiltonian parametrized by $\mathbf{v}$ with form

$$H(\mathbf{v}, t) = H_c + \sum_{j=1}^{m} u_j(\mathbf{v}, t)H_j, \tag{5}$$

155 where m is the number of control pulses, H_c is a time-independent Hamiltonian (e.g. Pauli matrices),
156 H_j are tensor products of Pauli matrices, and the range of $u_j(\mathbf{v}, t)$ is $\mathbb{R}$. We also require $u_j(\mathbf{v}, t)$ to
157 be differentiable with respect to $\mathbf{v}$ for any $t \in [0, T]$. The loss function $\mathcal{L}$ is hence *differentiable*.
158 We can loosen the restriction of H_j to general time-independent Hamiltonians if we have powerful
159 enough quantum simulators. We keep it in this paper for the convenience of presenting our algorithm.

160 With specific M and $|\psi_0\rangle$, optimization problem $\min_{\mathbf{v}} \mathcal{L}$ with post-processing can encode many
161 essential classical and quantum problems. For example, any classical optimization of $f(x)$ over n-bit
162 integers x can be formulated as $M = \sum_x f(x) |x\rangle \langle x|$. More examples like Max-Cut problem and
163 quantum state preparation are discussed in details in Sec. 4, 5.

164 **Abstract Quantum Analog Machines (AQAMs).** We propose AQAMs as our computational model.
165 An AQAM optimizing the above loss function should be capable of consecutively: (1) evolving under
166 $H(\mathbf{v}, t)$ for any $\mathbf{v}$ and time interval $[t_1, t_2] \subset [0, T]$; (2) evolving under constant Hamiltonian H_j
167 for time duration τ (effectively applying unitary transformation $e^{-iH_j\tau}$); (3) preparing $|\psi_0\rangle$; (4)
168 measuring with observable M. For realistic quantum devices, we need to design AQAMs accordingly.

169 **Remark 3.1.** A trivial AQAM directly employs the Hamiltonian of a quantum device as $H(\mathbf{v}, t)$,
170 parameterized by tunable pulses. In most realistic quantum devices, multi-qubit interactions are not
171 tunable and weak compared to tunable single-qubit Hamiltonians. Thus H_j can be simulated with
172 high fidelity. Our method is robust against imprecise simulations of $H(\mathbf{v}, t)$ and H_j (discussed in
173 Section 3.6). Hence the trivial AQAMs are usually suitable for realistic quantum devices.

Our formulation of the problem via analog quantum computing is a generalization of the formulation via parameterized circuits. For example, a series of parameterized Pauli rotation gates $R_{P_j}(\theta_j) = \exp\{-i(\theta_j/2)P_j\}$ can be realized by $H(\mathbf{v}, t) = \sum_j \mathbf{v}_j \mathbf{1}_j(t)P_j$ with valuation $\mathbf{v}_j = \theta_j/2$, where $\mathbf{1}_j$ is the indicator function of $[j, j+1]$. However, simulating analog quantum computing via quantum circuits requires much longer time duration on nowadays devices [42], hence is unrealistic. So direct analog quantum computing can *exploit near-term quantum devices much better* than quantum circuits.

3.3 Quantum stochastic gradient descent

Our quantum SGD scheme for computing gradients on AQAMs is illustrated in this section, with its correctness, efficiency, and robustness discussed in the following sections.

We borrow the idea of mini-batches from classical SGD to deal with the gradients, and set two layers of mini-batches: (1) an integration mini-batch with size b_{int}; (2) an observation mini-batch with size b_{obs}. The integration mini-batch updates parameters according to the estimation of derivatives on the sampled time. The observation mini-batch repeats experiments to generate more precise measurement results. The scheme is displayed in Algorithm 1.

The forward and backward propagation of our SGD scheme is depicted in Figure 1. Notice that the inner loop is the only procedure on quantum machine. The difference of this procedure compared with the estimation of loss function $\mathcal{L}$ is the inserted evolution under H_j, which is beneficial in the error analysis in Section 3.6.

Algorithm 1 Estimating gradients on an AQAM

Classical inputs: $b_{\text{int}}, b_{\text{obs}}$ (batch sizes), m (number of control pulses), u_j (parametrized pulses), T (evolution duration), $\mathbf{v}$ (parameters)
Quantum inputs: $\mathcal{E}_{|\psi_0\rangle}$ (preparation of initial state), H (parametrized system Hamiltonian), H_j (pulse-controllable Hamiltonian), $\mathcal{E}_M$ (measurement procedure with observable M)
Output: a gradient estimation of $\mathcal{L}$ to $\mathbf{v}$

$\quad$ **for** $k \in \{1, ..., b_{\text{int}}\}$ **do**
$\quad\quad$ Draw $\tau \sim \text{Uniform}(0, T)$
$\quad\quad$ **for** $j \in \{1, ..., m\}, s \in \{-1, +1\}$ **do**
$\quad\quad\quad$ **for** $l \in \{1, ..., b_{\text{obs}}\}$ **do**
$\quad\quad\quad\quad$ Prepare $|\psi_0\rangle$ via $\mathcal{E}_{|\psi_0\rangle}$
$\quad\quad\quad\quad$ Evolve under $H(\mathbf{v}, t)$ for time $[0, \tau]$
$\quad\quad\quad\quad$ Evolve under H_j for duration $(1 + \frac{3}{4}s)\pi$.
$\quad\quad\quad\quad$ Evolve under $H(\mathbf{v}, t)$ for time $[\tau, T]$
$\quad\quad\quad\quad$ $x_l \leftarrow$ observation sample from $\mathcal{E}_M$.
$\quad\quad\quad$ **end for**
$\quad\quad\quad$ $\tilde{p}_j^{\text{sign}(s)} \leftarrow \frac{1}{b_{\text{obs}}} \sum_{l=1}^{b_{\text{obs}}} x_l$
$\quad\quad$ **end for**
$\quad\quad$ $\tilde{f}_k \leftarrow \sum_{j=1}^m \frac{\partial u_j}{\partial \mathbf{v}}(\mathbf{v}, \tau)(\tilde{p}_j^- - \tilde{p}_j^+)$
$\quad$ **end for**
$\quad$ $\widetilde{\frac{\partial \mathcal{L}}{\partial \mathbf{v}}} \leftarrow \frac{T}{b_{\text{int}}} \sum_{k=1}^{b_{\text{int}}} \tilde{f}_k$

With the estimation of gradients, various optimizers designed for classical stochastic gradient descent are suitable to optimize the objective function. For example, Adam [35] is used in our experiments.

3.4 Correctness of gradient estimation

We show that Algorithm 1 generates an unbiased estimation of the gradient $\frac{\partial \mathcal{L}}{\partial \mathbf{v}}$, and hence establishes its correctness. The proof of the following theorem is postponed to Appendix B.1.

Theorem 3.2. *The derivative of $\mathcal{L}$ to parameters $\mathbf{v}$ is*

$$\frac{\partial \mathcal{L}}{\partial \mathbf{v}} = \int_0^T \mathrm{d}\tau \sum_{j=1}^m \frac{\partial u_j}{\partial \mathbf{v}}(\mathbf{v}, \tau)\left(p_j^-(\tau) - p_j^+(\tau)\right). \tag{6}$$

Here, $p_j^\pm(t) = \langle\psi_0| U_{\mathbf{v}}^\dagger(T, t)e^{iH_j(1 \pm \frac{3}{4})\pi}U_{\mathbf{v}}^\dagger(T, t)MU_{\mathbf{v}}(T, t)e^{-iH_j(1 \pm \frac{3}{4})\pi}U_{\mathbf{v}}(t, 0)|\psi_0\rangle$, where $U_{\mathbf{v}}(t_2, t_1)$ denotes the time evolution operator for time interval $[t_1, t_2]$ under Hamiltonian $H(\mathbf{v}, t)$.

One can interpret the above formula as a direct application of the chain rule over functional derivatives $\frac{\delta \mathcal{L}}{\delta u_j}$ and partial derivatives $\frac{\partial u_j}{\partial \mathbf{v}}$, since $\frac{\delta \mathcal{L}}{\delta u_j}(\mathbf{v}, t) = p_j^-(t) - p_j^+(t)$ by the parameter shift rule [46, 56], which is a technique for evaluating commutators of Hermitian by quantum processes.

Algorithm 1 estimates the integral in (6) via Monte Carlo integration (MCI) technique. We prove that the sampling of MCI has finite variances in Appendix B.1 when $u_j(\mathbf{v}, t)$ has bounded derivatives to $\mathbf{v}$. Hence MCI converges of rate $O(b_{\text{int}}^{-\frac{1}{2}})$ [51]. Other numerical integral methods are also applicable here for different conditions on u_j and H_j, and may have better convergence rates than MCI. We present it here because MCI has good generalization and simplicity. We also remark that similar ideas developed in this section have also appeared in [3] in the circuit model, whereas we develop everything in the analog quantum computing model.

Overall, the forward and backward propagation of differentiation of $\mathcal{L}$ are depicted in Figure 1. Since the parameterization of u_j is arbitrary, a typical treatment is using a Fourier basis or a Legendre basis as the support of the parameterization. Neural networks are also suitable for pulse generation, whose gradients are easy to compute via backpropagation.

3.5 Scalability analysis

The resource consumption of our classical-quantum hybrid approach has two aspects: the classical and the quantum sides. The classical computation, as described in Algorithm 1, has $O(b_{\mathrm{int}}b_{\mathrm{obs}}m)$ numerical calculations. On the quantum side, the sampling process assessing the loss function and its derivatives takes $O(T)$ time each. The total running time on a quantum computer then is $O(b_{\mathrm{int}}b_{\mathrm{obs}}mT)$. Almost on every architecture of quantum devices, the number of control signals m is *at most quadratic in the number of qubits* n (see some survey papers [36, 32, 7, 55]), showing excellent scalability of our approach. We exhibit the scalability of our method for up to 11 qubits in numerical experiments in Section 4.2. Our approach could in principle be readily applied to the most advanced existing quantum systems (e.g., [1] with $n \sim 60$). This is in sharp contrast to the case of GRAPE and CRAB algorithms, which rely on classical simulation of quantum systems with an exponential cost in n. For instance, the associated classical computation cost for $n \sim 60$ (i.e. at least 2^{60}) is prohibitively high, almost reaching the limit of supercomputers today. *Our approach makes it feasible with only $O(n^2)$ complexity.*

3.6 Robustness analysis

In this section, we analyze systematic errors of gradient estimation produced of Algorithm 1. Our goal is to optimize the loss function assessed on a realistic and noisy quantum machine, whose capabilities of evolving under $H(\mathbf{v}, t)$ and H_j are imperfect.

As a concrete example, when using the trivial AQAMs in Remark 3.1, the actual Hamiltonian of the quantum device may deviate from the description $H(\mathbf{v}, t)$ in our understanding, and the simulation of H_j may be imprecise due to weak non-tunable terms in H_c. We show that our algorithm well approximates the gradient of loss function of the actual devices.

One major advantage of Algorithm 1 is that even though we have imperfect realization of Hamiltonian $H(\mathbf{v}, t)$ built in the AQAM, the quantum part is executed on the actual quantum machine following the accurate Hamiltonian $\widehat{H}(\mathbf{v}, t)$. As a result, the output of our algorithm well approximates the gradient for the actual quantum machine.

Lemma 3.3. *Let $\widehat{\frac{\partial \mathcal{L}}{\partial \mathbf{v}}}$ denote the accurate gradient of the loss function of the quantum machine, $\frac{\partial \mathcal{L}}{\partial \mathbf{v}}$ denote the estimated gradient via Algorithm 1, and $\|\cdot\|$ represents the matrix spectral norm [30], then*
$$\left| \frac{\partial \mathcal{L}}{\partial \mathbf{v}} - \widehat{\frac{\partial \mathcal{L}}{\partial \mathbf{v}}} \right| \leq 2\|M\|T \max_{\tau \in [0,T]} \left\| \frac{\partial H}{\partial \mathbf{v}}(\mathbf{v}, \tau) - \frac{\partial \widehat{H}}{\partial \mathbf{v}}(\mathbf{v}, \tau) \right\|.$$

The proof of this lemma is detailed in Appendix B.2. In other words, one can use Algorithm 1 to *optimize the control pulses without a precise understanding of the machine Hamiltonian*, if the difference $H(\mathbf{v}, t) - \widehat{H}(\mathbf{v}, t)$ varies slowly w.r.t. $\mathbf{v}$ (a rather mild condition to satisfy).

On the contrary, if one relies solely on the Hamiltonian $H(\mathbf{v}, t)$ built in the abstract quantum analog machine (e.g., the classical simulation of quantum systems in GRAPE or CRAB), the approximation error could be as large as the difference $H(\mathbf{v}, t) - \widehat{H}(\mathbf{v}, t)$ itself, a potentially large term compared with its derivative w.r.t. $\mathbf{v}$. An example is illustrated in Appendix B.3. This particular advantage of Algorithm 1 exists exactly because of its execution on the real machine, which *is potentially applicable in general scenarios where only approximate machine descriptions are obtainable*.

Similar to the circuit case, the systematic error caused by the imprecise evolution under H_j is bounded by the error sum in each evolution under H_j for duration $(1 \pm \frac{3}{4})\pi$, which is usually small.

4 Quantum optimization

Many important optimization problems in both physics and combinatorics that allow variational solutions can be formulated easily in our framework. For example, finding the ground state of physics

systems can be solved by variational quantum eigensolver (VQE) (e.g. [49, 33]), and searching for the max-cut of graphs can be approximated by quantum approximate optimization algorithms (QAOA) [20]. Replacing parameterized circuits to AQAMs in existing variational quantum algorithms leads to significantly improved convergence based on numerical experiments on a classical simulator.

4.1 Variational quantum eigensolver

We exhibit our approach via an AQAM comparable to existing circuit VQE in terms of the pulse duration, with significantly better convergence and hardware efficiency in identifying the ground state of the H_2 molecule.

(a) Ground energy search   (b) Cut size maximization

Figure 2: **Experiments on quantum optimization problems.** (a) Experiment results on the H_2 ground energy search. Loss function is the difference of the evaluated energy to the ground energy of H_2, and the lower is the better. Our method with the same (720dt) or less (360dt) pulse duration converges more than 10 times faster than the circuit model [33]. (b) Experiment results on finding the max cut for 4 vertices circular graph. Loss function is the difference of the evaluated cut size to the maximal cut size, the lower the better. Our method outperforms the others by orders of magnitude.

Problem setting. The Hamiltonian of H_2 molecule is expanded with Pauli matrices in the form $H_{H_2} = \alpha_0 \mathbb{I} + \alpha_1 Z_1 Z_2 + \alpha_2 X_1 X_2 + \alpha_3 Z_1 + \alpha_4 Z_2$, where α_i is a scalar weight calculated in [33]. The ground state $|\psi\rangle$ has the minimal energy, defined by $\mathrm{argmin}_{|\psi\rangle} \langle \psi | H_{H_2} | \psi \rangle$. This energy function is computed on real machines by Pauli measurements and linearity.

AQAM design. We propose an IBM-AQAM mimicking IBM transmon system [43] (a detailed introduction in Appendix C), and realizable on IBM's machines. The IBM-AQAM contains 2 qubits and 4 input pulses $u_{jk}(t)$, and can evolve under

$$H(t) = H_{\mathrm{sys}} + \sum_{j,k \in \{0,1\}} \mathcal{M}_{jk}(u_{jk}, t) X_j. \tag{7}$$

Here H_{sys} is a constant Hamiltonian. The input pulses to IBM quantum devices are $u_{jk}(t)$ which are complex values with norm less than 1. These pulses are modulated by the built-in modulation procedure $\mathcal{M}_{jk}$ of the IBM's quantum devices when executed on the real machine. Since the tunable terms have Hamiltonian X_j, we require the IBM-AQAM to be able to evolve under X_j. This is realizable on IBM's machines because in (7), H_{sys} is much weaker than the microwave input pulses for each qubit in form X_j, ensuring a high fidelity simulation of Hamiltonian X_j on real machines. We also require the IBM-AQAM to support initializing in state $|00\rangle$ and measuring with $M = H_{H_2}$, and these procedures are easy to implement for IBM's machines. We adopt the parameterization

$$u_{jk}(\mathbf{v}, t) = \mathcal{N}\left(\sum_{l=0}^{d} (\mathbf{v}_{jkl0} + i\mathbf{v}_{jkl1}) \cdot P_l \left(\frac{2t}{T} - 1 \right) \right) \tag{8}$$

to make the pulse norms less than 1, where $\mathcal{N}(0) = 0, \mathcal{N}(z) = \frac{S(|z|)}{|z|} z$ for $z \neq 0$ is a differentiable normalization function restricting the norm, $S(x) = \frac{1-e^{-x}}{1+e^{-x}}$ is the shifted sigmoid function, T is the duration, and P_l is the l-th Legendre polynomial.

In [33], a parameterized circuit is proposed as layered tunable single qubit rotations and fixed cross-resonance gates, which are compiled to pulses fitting in (7) and sent to the IBM quantum devices. Their one-layer experiments over two qubits have cross resonance gates compiled to pulses with duration around 720dt where dt=0.22ns. We match it in our experiments, setting $T = 720$dt. Additionally, we test our approach with only half the duration, $T = 360$dt.

Comparisons. We compare our approach to circuit VQE, finite difference method, simultaneous perturbation stochastic approximation (SPSA), and derivative-free methods (CMAES [25] and SLSQP [37]) with the IBM-AQAM on a classical simulator. The experiment results are displayed in Figure 2a with a detailed hyper-parameter settings in Appendix D.1.1.

The circuit VQE converges to $\mathcal{L} = 0.02$, while our approach decreases lower: at 400 epoch, with 720dt it decreases to less than 0.002, and with 360dt it decreses to 0.01. In general, our approach is over 10 times more accurate than the circuit VQE, and 100 times more accurate than the derivative-free methods. The finite difference method and SPSA do not converge because of the intrinsic randomness of quantum measurements at relatively small observation mini-batch ($b_{\mathrm{obs}} = 100$), which would be

amplified by the small difference length. With a large enough observation mini-batch, the gradients evaluated by finite difference method has $\sim 3\%$ relative difference to the gradients evaluated by our approach. These results exhibit the advantages of our differentiable analog framework compared to circuit model and derivative-free analog models.[2]

4.2 Quantum approximate optimization algorithm

We also investigate the application of QAOA to approximate solutions for the MaxCut problem, an NP-complete problem. With a corresponding AQAM, we achieve a significantly better convergence.

Problem setting. Given a graph $G = \{E, V\}$ where V is the vertex set and $E = \{(i, j)\}$ contains all the edges, our goal is to partition the vertices into two sets (V_0, V_1) so that the number of edges between the two sets is maximized. A cut of an n-node graph G is represented by an n-bit string $s = b_1 b_2 ... b_n$, with $b_j \in \{0, 1\}$ representing in which set the j-th vertex is. We use the computational basis $|s\rangle$ in an n-qubit register to represent the cut s. A maximum cut $|s\rangle$ maximizes the expected cut size $\langle s | C | s \rangle$, where $C = \frac{1}{2} \sum_{(j,k) \in E} C_{j,k}$, $C_{j,k} = \mathbb{I} - Z_j Z_k$. We test the performance on the circular graph shown in the leftmost of Figure 6.

AQAM design. Farhi et al. [20] optimizes a p-layer circuit ansatz $U(\beta, \gamma) = \Pi_{j=1}^{p} e^{-i\beta_j B} e^{-i\gamma_j C}$, where $B = \sum_{j=1}^{n} X_j$. We set $p = 2$ as a baseline. To have a fair comparison, we design a Cut-AQAM corresponding to the above circuit: $H(t) = \frac{1}{2\pi} \sum_{j=1}^{4} (u_{j0}(t) C_{j,j+1} + u_{j1}(t) X_j)$. The input pulses are real functions $u_{jk}(t)$, where we restrict the energy input by requiring $|u_{jk}| \leq 1$. Cut-AQAM natively supports evolving merely under $C_{j,j+1}$ or X_j by setting u_{jk} as indicator functions. We also require it to support initializing in state $|0\rangle$ and measuring with observable C. In our experiment, we set the duration $T = 4$ within which the circuit QAOA can be realized by Cut-AQAM. Similar to (8), we parameterize $u_{jk}(\mathbf{v}, t)$ by a normalized linear combination of Legendre's polynomial.

Comparisons. The experiments are set up in a similar way as in Section 4.1, with details in Appendix D.1.2. Results are shown in Figure 2b. The circuit QAOA and SLSQP converges to 0.08 at 200 epoch, while our method converges to 2.6×10^{-6}. Finite difference method, SPSA, and CMAES do not converge to a value less than 1. The analysis is similar to Section 4.1. Since Cut-AQAM does not have a high frequency modulation, SLSQP also converges close to 0, but is slower than our approach. We conduct larger experiments for up to 11 qubits, which shows good scalability and better performance compared to circuit QAOA. For details, see Figure 7 in Appendix D.1.2.

5 Quantum Control

Quantum control problems fall into two categories: 1) *state preparation*: to steer a given initial state into a target final state; 2) *gate synthesis*: to effect a specific unitary transformation (quantum gate) in the system. In what follows, we discuss how to formulate and solve quantum control problems using our differentiable analog quantum computing framework. We demonstrate our methodology by numerical experiments on the IBM-AQAM.

5.1 State Preparation

To prepare the target state $|\psi_{tar}\rangle$ from certain fixed initial state, we desire a parameter vector $\mathbf{v}$ that minimizes the loss function defined in (4) with the observable $M = \mathbb{I} - |\psi_{tar}\rangle \langle \psi_{tar}|$. We consider two tasks: 1) to prepare the state $|+\rangle$ from $|0\rangle$; 2) to prepare the two-qubit maximally entangled state $|\Phi^+\rangle$ from $|00\rangle$.[3] In both tasks, the loss function is readily computed as the measurement merely involves local Pauli operators (see Appendix D.2.1), and can be carried out on the IBM-AQAM.

In the numerical experiments, the pulse duration is fixed as $T = 20\mathtt{dt}$ for the $|+\rangle$ state, and $T = 1200\mathtt{dt}$ for the $|\Phi^+\rangle$ state. We also compare our method with two gradient-free methods (SLSQP, CMAES) and the GRAPE algorithm. In both tasks, ours achieves faster convergence than all other three methods. In the $|+\rangle$ task, the final loss value from our method reads approximately 10^{-5}, which is 18 times better than the second best result (i.e., SLSQP), as in in Figure 3 (a). In the $|\Phi^+\rangle$ task, the final loss value from our method reads 0.034, which is 3 times better than GRAPE and 6 times better than SLSQP, as shown in Figure 3 (b).

---

[2]We note that the benefits of using analog controls in VQE for H_2 molecule are also discovered in a recent result [45], where the optimization is conducted based on GRAPE-like techniques.

[3]$|+\rangle = \frac{1}{\sqrt{2}}(|0\rangle + |1\rangle)$ and $|\Phi^+\rangle = \frac{1}{\sqrt{2}}(|00\rangle + |11\rangle)$.

5.2 Gate Synthesis

Gate synthesis is more challenging than state preparation because we hope to engineer a full unitary gate U_{tar} instead of just mapping a single state to a target state. To this end we first specify a set of pairs $\mathcal{S} = \{(|\mathbf{x}_j\rangle, |\mathbf{y}_j\rangle)\}_{j=1}^{k}$ that completely determines U_{tar} in the sense that no unitary map U other than U_{tar} satisfies $\left|\langle\mathbf{y}_j|\, U\, |\mathbf{x}_j\rangle\right| = 1$ for all $j = 1, 2, .., k$. Then, we consider the loss function $\mathcal{L} = \frac{1}{k}\sum_{j=1}^{k} \mathcal{L}_j$, where each $\mathcal{L}_j$ is defined as in (4) with quantum observable $M = \mathbb{I} - |\mathbf{y}_j\rangle\langle\mathbf{y}_j|$ and initial state $|\mathbf{x}_j\rangle$. When $\mathcal{L}(\mathbf{v})$ is close to 0, the time evolution controlled by the parameter $\mathbf{v}$ is approximately U_{tar}.

(a) Preparing $|+\rangle$ (b) Preparing $|\Phi^+\rangle$

(c) Synthesizing X gate   (d) Synthesizing CNOT

Figure 3: **Quantum Control.** We apply our methodology to state preparation and gate synthesis. Lower loss corresponds higher accuracy. In gate synthesis, the loss of the built-in gates from IBM Qiskit is shown in dashed lines. Our method outperforms the other algorithms in terms of convergence rate and accuracy by up to orders of magnitude.

The X gate and CNOT gate are widely used in digital quantum computing and supported by IBM Qiskit. We now exemplify our method by recovering these two gates on the IBM-AQAM. In both cases, the loss function can be readily computed on IBM machines. See Appendix D.2.2 for detail.

The pulse duration is chosen to be comparable to the built-in ones in IBM Qiskit: $T = 160\mathtt{dt}$ for X gate, and $T = 1200\mathtt{dt}$ for CNOT gate.[4] We apply four methods (SLSQP, CMAES, GRAPE, ours) to the gate synthesis tasks. The results are shown in Figure 3 (c), (d). In the synthesis of X gate, the final loss value from our method is 1.17×10^{-7}, which is over 10^4 times more accurate than the other three methods. In the more involved task of synthesizing CNOT gate, our method returns a pulse sequence with loss 0.0172, while the results from other methods are no less than 0.2. It is worth noting that our results also outperform the built-in gates in IBM Qiskit (0.019 for X gate and 0.043 for CNOT gate), if the accuracy is measured using the same loss function as in our formulation.

6 Conclusion and Future Work

We have introduced the first differentiable analog quantum computing framework with a quantum stochastic gradient descent algorithm that allows directly optimizing the analog pulse control signal on quantum computers. Since the computation history in a quantum system cannot be stored or reused for the purpose of computing gradient, we construct a novel formulation for derivatives on quantum computers based on a forward pass with Monte Carlo sampling. With the proposed algorithm, our method outperforms prior methods by orders of magnitude with better hardware efficiency on quantum optimization and control tasks.

Generalization. This work suggests a larger scope of differentiable physics that extends beyond classical cases to quantum scale, where insights and techniques from one scale could potentially be translated to the other. For instance, our quantum differentiable framework is largely inspired by the classical counterpart. We also believe some of our findings for quantum computing could also be generally applicable in the classical paradigm: e.g., our differentiation technique is likely extendable to *general linear dynamical systems* and our robustness analysis also holds in general when *only approximate machine descriptions are known*.

Limitations and Future Work. As a first step, we only describe our framework with a few important, but small, demonstrating examples running on simulators. The great promise of our framework lies in implementing large-scale VQA applications on real quantum machines and bringing useful quantum applications to practice. To that end, we plan to incorporate real-world quantum machines into our framework, and solve large-scale VQA tasks.

---

[4]In IBM Qiskit, the X gate is implemented by a pulse of duration $T = 160\mathtt{dt}$, and CNOT is by $T = 1056\mathtt{dt}$.

References

[1] Arute, F., Arya, K., Babbush, R., Bacon, D., Bardin, J. C., Barends, R., Biswas, R., Boixo, S., Brandao, F. G., Buell, D. A., et al. Quantum supremacy using a programmable superconducting processor. *Nature*, 574(7779):505–510, 2019.

[2] Arute, F., Arya, K., Babbush, R., Bacon, D., Bardin, J. C., Barends, R., Biswas, R., Boixo, S., Brandao, F. G. S. L., Buell, D. A., Burkett, B., Chen, Y., Chen, Z., Chiaro, B., Collins, R., Courtney, W., Dunsworth, A., Farhi, E., Foxen, B., Fowler, A., Gidney, C., Giustina, M., Graff, R., Guerin, K., Habegger, S., Harrigan, M. P., Hartmann, M. J., Ho, A., Hoffmann, M., Huang, T., Humble, T. S., Isakov, S. V., Jeffrey, E., Jiang, Z., Kafri, D., Kechedzhi, K., Kelly, J., Klimov, P. V., Knysh, S., Korotkov, A., Kostritsa, F., Landhuis, D., Lindmark, M., Lucero, E., Lyakh, D., Mandrà, S., McClean, J. R., McEwen, M., Megrant, A., Mi, X., Michielsen, K., Mohseni, M., Mutus, J., Naaman, O., Neeley, M., Neill, C., Niu, M. Y., Ostby, E., Petukhov, A., Platt, J. C., Quintana, C., Rieffel, E. G., Roushan, P., Rubin, N. C., Sank, D., Satzinger, K. J., Smelyanskiy, V., Sung, K. J., Trevithick, M. D., Vainsencher, A., Villalonga, B., White, T., Yao, Z. J., Yeh, P., Zalcman, A., Neven, H., and Martinis, J. M. Quantum supremacy using a programmable superconducting processor. *Nature*, 574(7779):505–510, 2019.

[3] Banchi, L. and Crooks, G. E. Measuring Analytic Gradients of General Quantum Evolution with the Stochastic Parameter Shift Rule. *Quantum*, 5:386, January 2021. ISSN 2521-327X. doi: 10.22331/q-2021-01-25-386. URL https://doi.org/10.22331/q-2021-01-25-386.

[4] Benedetti, M., Lloyd, E., Sack, S., and Fiorentini, M. Parameterized quantum circuits as machine learning models. *Quantum Science and Technology*, 4(4):043001, 2019.

[5] Biamonte, J., Wittek, P., Pancotti, N., Rebentrost, P., Wiebe, N., and Lloyd, S. Quantum machine learning. *Nature*, 549(7671):195–202, 2017.

[6] Brif, C., Chakrabarti, R., and Rabitz, H. Control of quantum phenomena: past, present and future. *New Journal of Physics*, 12(7):075008, 2010.

[7] Bruzewicz, C. D., Chiaverini, J., McConnell, R., and Sage, J. M. Trapped-ion quantum computing: Progress and challenges. *Applied Physics Reviews*, 6(2):021314, 2019.

[8] Caneva, T., Calarco, T., and Montangero, S. Chopped random-basis quantum optimization. *Physical Review A*, 84(2):022326, 2011.

[9] Castaldo, D., Rosa, M., and Corni, S. Quantum optimal control with quantum computers: A hybrid algorithm featuring machine learning optimization. *Physical Review A*, 103(2):022613, 2021.

[10] Chen, T. Q., Rubanova, Y., Bettencourt, J., and Duvenaud, D. Neural ordinary differential equations. In *NeurIPS*, pp. 6572–6583, 2018.

[11] Childs, A. M., Su, Y., Tran, M. C., Wiebe, N., and Zhu, S. A theory of trotter error. *Physical Review X*, 11(011020):26, 2021.

[12] d'Alessandro, D. *Introduction to quantum control and dynamics*. Chapman and Hall/CRC, 2007.

[13] Dalgaard, M., Motzoi, F., Sørensen, J. J., and Sherson, J. Global optimization of quantum dynamics with alphazero deep exploration. *npj Quantum Information*, 6(1):1–9, 2020.

[14] de Avila Belbute-Peres, F., Smith, K. A., Allen, K. R., Tenenbaum, J., and Kolter, J. Z. End-to-end differentiable physics for learning and control. In *Neural Information Processing Systems*, 2018.

[15] de Keijzer, R., Tse, O., and Kokkelmans, S. Pulse based variational quantum optimal control for hybrid quantum computing. *arXiv preprint arXiv:2202.08908*, 2022.

[16] Degrave, J., Hermans, M., Dambre, J., and wyffels, F. A differentiable physics engine for deep learning in robotics. *Frontiers in Neurorobotics*, 13, 2019.

[17] Dive, B., Pitchford, A., Mintert, F., and Burgarth, D. In situ upgrade of quantum simulators to universal computers. *Quantum*, 2:80, 2018.

[18] Dong, D. and Petersen, I. R. Quantum control theory and applications: a survey. *IET Control Theory & Applications*, 4(12):2651–2671, 2010.

[19] Du, T., Wu, K., Ma, P., Wah, S., Spielberg, A., Rus, D., and Matusik, W. Diffpd: Differentiable projective dynamics. *ACM Trans. Graph.*, 41(2), 2021.

[20] Farhi, E., Goldstone, J., and Gutmann, S. A quantum approximate optimization algorithm. *arXiv preprint arXiv:1411.4028*, 2014.

[21] Geilinger, M., Hahn, D., Zehnder, J., Bächer, M., Thomaszewski, B., and Coros, S. ADD: Analytically differentiable dynamics for multi-body systems with frictional contact. *ACM Transactions on Graphics (TOG)*, 39(6), 2020.

[22] Greydanus, S., Dzamba, M., and Yosinski, J. Hamiltonian neural networks. In *Advances in Neural Information Processing Systems*, volume 32, 2019.

[23] Ha, S., Coros, S., Alspach, A., Kim, J., and Yamane, K. Joint optimization of robot design and motion parameters using the implicit function theorem. In *Robotics: Science and Systems (RSS)*, 2017.

[24] Haber, E. and Ruthotto, L. Stable architectures for deep neural networks. *Inverse problems*, 34 (1):014004, 2017.

[25] Hansen, N. and Ostermeier, A. Adapting arbitrary normal mutation distributions in evolution strategies: The covariance matrix adaptation. In *Proceedings of IEEE international conference on evolutionary computation*, pp. 312–317. IEEE, 1996.

[26] Harrow, A. W. and Montanaro, A. Quantum computational supremacy. *Nature*, 549(7671): 203–209, 2017.

[27] He, K., Zhang, X., Ren, S., and Sun, J. Deep residual learning for image recognition. In *Proceedings of the IEEE conference on computer vision and pattern recognition*, pp. 770–778, 2016.

[28] Heiden, E., Macklin, M., Narang, Y. S., Fox, D., Garg, A., and Ramos, F. DiSECt: A Differentiable Simulation Engine for Autonomous Robotic Cutting. In *Proceedings of Robotics: Science and Systems*, 2021.

[29] Holl, P., Koltun, V., and Thuerey, N. Learning to control PDEs with differentiable physics. In *ICLR*, 2020.

[30] Horn, R. A. and Johnson, C. R. *Matrix Analysis*. Cambridge University Press, USA, 2nd edition, 2012. ISBN 0521548233.

[31] Hu, Y., Anderson, L., Li, T.-M., Sun, Q., Carr, N., Ragan-Kelley, J., and Durand, F. Difftaichi: Differentiable programming for physical simulation. *ICLR*, 2020.

[32] Huang, H.-L., Wu, D., Fan, D., and Zhu, X. Superconducting quantum computing: a review. *Science China Information Sciences*, 63(8):1–32, 2020.

[33] Kandala, A., Mezzacapo, A., Temme, K., Takita, M., Brink, M., Chow, J. M., and Gambetta, J. M. Hardware-efficient variational quantum eigensolver for small molecules and quantum magnets. *Nature*, 549(7671):242–246, 2017.

[34] Khaneja, N., Reiss, T., Kehlet, C., Schulte-Herbrüggen, T., and Glaser, S. J. Optimal control of coupled spin dynamics: design of nmr pulse sequences by gradient ascent algorithms. *Journal of magnetic resonance*, 172(2):296–305, 2005.

[35] Kingma, D. P. and Ba, J. Adam: A method for stochastic optimization. *arXiv preprint arXiv:1412.6980*, 2014.

[36] Kjaergaard, M., Schwartz, M. E., Braumüller, J., Krantz, P., Wang, J. I.-J., Gustavsson, S., and Oliver, W. D. Superconducting qubits: Current state of play. *Annual Review of Condensed Matter Physics*, 11(1):369–395, 2020. doi: 10.1146/annurev-conmatphys-031119-050605. URL https://doi.org/10.1146/annurev-conmatphys-031119-050605.

[37] Kraft, D. et al. A software package for sequential quadratic programming. 1988.

[38] Krishna Murthy, J., Macklin, M., Golemo, F., Voleti, V., Petrini, L., Weiss, M., Considine, B., Parent-Lévesque, J., Xie, K., Erleben, K., et al. gradSim: Differentiable simulation for system identification and visuomotor control. In *ICLR*, 2021.

[39] Liang, Z., Wang, H., Cheng, J., Ding, Y., Ren, H., Qian, X., Han, S., Jiang, W., and Shi, Y. Variational quantum pulse learning. *arXiv preprint arXiv:2203.17267*, 2022.

[40] Lu, Y., Zhong, A., Li, Q., and Dong, B. Beyond finite layer neural networks: Bridging deep architectures and numerical differential equations. In *International Conference on Machine Learning*, pp. 3276–3285. PMLR, 2018.

[41] Ma, P., Du, T., Zhang, J. Z., Wu, K., Spielberg, A., Katzschmann, R. K., and Matusik, W. Diffaqua: A differentiable computational design pipeline for soft underwater swimmers with shape interpolation. *ACM Transactions on Graphics (TOG)*, 40(4):132, 2021.

[42] Magann, A. B., Arenz, C., Grace, M. D., Ho, T.-S., Kosut, R. L., McClean, J. R., Rabitz, H. A., and Sarovar, M. From pulses to circuits and back again: A quantum optimal control perspective on variational quantum algorithms. *PRX Quantum*, 2:010101, Jan 2021. doi: 10.1103/PRXQuantum.2.010101. URL https://link.aps.org/doi/10.1103/PRXQuantum.2.010101.

[43] Magesan, E. and Gambetta, J. M. Effective hamiltonian models of the cross-resonance gate. *Physical Review A*, 101(5):052308, 2020.

[44] Massaroli, S., Poli, M., Park, J., Yamashita, A., and Asama, H. Dissecting neural odes. In *Advances in Neural Information Processing Systems*, volume 33, pp. 3952–3963, 2020.

[45] Meitei, O. R., Gard, B. T., Barron, G. S., Pappas, D. P., Economou, S. E., Barnes, E., and Mayhall, N. J. Gate-free state preparation for fast variational quantum eigensolver simulations. *npj Quantum Information*, 7(1):155, 2021.

[46] Mitarai, K., Negoro, M., Kitagawa, M., and Fujii, K. Quantum circuit learning. *Physical Review A*, 98(3):032309, 2018.

[47] Moll, N., Barkoutsos, P., Bishop, L. S., Chow, J. M., Cross, A., Egger, D. J., Filipp, S., Fuhrer, A., Gambetta, J. M., Ganzhorn, M., et al. Quantum optimization using variational algorithms on near-term quantum devices. *Quantum Science and Technology*, 3(3):030503, 2018.

[48] Palao, J. P. and Kosloff, R. Optimal control theory for unitary transformations. *Physical Review A*, 68(6):062308, 2003.

[49] Peruzzo, A., McClean, J., Shadbolt, P., Yung, M.-H., Zhou, X.-Q., Love, P. J., Aspuru-Guzik, A., and O'brien, J. L. A variational eigenvalue solver on a photonic quantum processor. *Nature communications*, 5(1):1–7, 2014.

[50] Preskill, J. Quantum computing in the nisq era and beyond. *Quantum*, 2:79, 2018.

[51] Press, W. H., Teukolsky, S. A., Vetterling, W. T., and Flannery, B. P. *Numerical Recipes 3rd Edition: The Art of Scientific Computing*. Cambridge University Press, USA, 3 edition, 2007. ISBN 0521880688.

[52] Qiao, Y.-L., Liang, J., Koltun, V., and Lin, M. C. Efficient differentiable simulation of articulated bodies. In *ICML*, 2021.

[53] Rabitz, H., de Vivie-Riedle, R., Motzkus, M., and Kompa, K. Whither the future of controlling quantum phenomena? *Science*, 288(5467):824–828, 2000.

[54] Rubanova, Y., Chen, R. T. Q., and Duvenaud, D. K. Latent ordinary differential equations for irregularly-sampled time series. In *Advances in Neural Information Processing Systems*, volume 32, 2019.

[55] Saffman, M. Quantum computing with atomic qubits and rydberg interactions: progress and challenges. *Journal of Physics B: Atomic, Molecular and Optical Physics*, 49(20):202001, 2016.

[56] Schuld, M., Bergholm, V., Gogolin, C., Izaac, J. A., and Killoran, N. Evaluating analytic gradients on quantum hardware. *Physical Review A*, 2019.

[57] Shi, Y., Gokhale, P., Murali, P., Baker, J. M., Duckering, C., Ding, Y., Brown, N. C., Chamberland, C., Javadi-Abhari, A., Cross, A. W., Schuster, D. I., Brown, K. R., Martonosi, M., and Chong, F. T. Resource-efficient quantum computing by breaking abstractions. *Proceedings of the IEEE*, 108(8):1353–1370, 2020. doi: 10.1109/JPROC.2020.2994765.

[58] Um, K., Brand, R., Fei, Y. R., Holl, P., and Thuerey, N. Solver-in-the-loop: Learning from differentiable physics to interact with iterative PDE-solvers. In *Neural Information Processing Systems*, 2020.

[59] Wandel, N., Weinmann, M., and Klein, R. Learning incompressible fluid dynamics from scratch – towards fast, differentiable fluid models that generalize. In *ICLR*, 2021.

[60] Werling, K., Omens, D., Lee, J., Exarchos, I., and Liu, C. K. Fast and feature-complete differentiable physics for articulated rigid bodies with contact. In *Robotics: Science and Systems (RSS)*, 2021.

[61] Wootters, W. K. and Zurek, W. H. A single quantum cannot be cloned. *Nature*, 299(5886): 802–803, 1982.

[62] Zhong, H.-S., Wang, H., Deng, Y.-H., Chen, M.-C., Peng, L.-C., Luo, Y.-H., Qin, J., Wu, D., Ding, X., Hu, Y., Hu, P., Yang, X.-Y., Zhang, W.-J., Li, H., Li, Y., Jiang, X., Gan, L., Yang, G., You, L., Wang, Z., Li, L., Liu, N.-L., Lu, C.-Y., and Pan, J.-W. Quantum computational advantage using photons. *Science*, 370(6523):1460–1463, 2020. ISSN 0036-8075. doi: 10. 1126/science.abe8770. URL https://science.sciencemag.org/content/370/6523/1460.

[63] Zhu, S., Hung, S.-H., Chakrabarti, S., and Wu, X. On the principles of differentiable quantum programming languages. In *Proceedings of the 41st ACM SIGPLAN Conference on Programming Language Design and Implementation*, PLDI 2020, pp. 272–285, New York, NY, USA, 2020. Association for Computing Machinery. ISBN 9781450376136. doi: 10.1145/3385412.3386011. URL https://doi.org/10.1145/3385412.3386011.

[64] Zhu, W. and Rabitz, H. Noniterative algorithms for finding quantum optimal controls. *The Journal of chemical physics*, 110(15):7142–7152, 1999.

[65] Zhu, W., Botina, J., and Rabitz, H. Rapidly convergent iteration methods for quantum optimal control of population. *The Journal of Chemical Physics*, 108(5):1953–1963, 1998.

[66] Zhuang, J., Dvornek, N. C., Tatikonda, S., and Duncan, J. S. Mali: A memory efficient and reverse accurate integrator for neural odes. *International Conference on Learning Representations*, 2021.

 # Appendix

 ## A Connection between Our Method and Deep Learning

 We show the similarities between our method, Neural ODE, and differentiable physics in Figure 4. All
 the three approaches have a differentiable system governed by some kinds of differential equations.
 Our method parametrizes the dynamics using continuous basis functions; Neural ODE uses neural
 networks; and Differentiable physics describes the dynamics system using physics equations like
Newton's Second Law, Navier–Stokes equations.

(a) Diff. Analog QC   (b) Neural ODE   (c) Diff. Physics

Figure 4: Connections between Diff. Analog computing and other deep learning models.

 ## B Theory

 ### B.1 Derivation of gradient

 Lemma B.1. *The derivative of the time evolution operator is*

$$\frac{\partial U_{\mathbf{v}}(t_2, t_1)}{\partial \mathbf{v}} = -i \int_{t_1}^{t_2} \mathrm{d}\tau \, U_{\mathbf{v}}(t_2, \tau) \frac{\partial H(\mathbf{v}, \tau)}{\partial \mathbf{v}} U_{\mathbf{v}}(\tau, t_1) \tag{9}$$

 Proof. Let $U_{\mathbf{v}}(t_2, t_1)$ be as defined in Theorem 3.2. We can re-write (1) in the form of time evolution
 operator,

$$i\frac{\partial U_{\mathbf{v}}(t, 0)}{\partial t} = H(\mathbf{v}, t)U(t, 0). \tag{10}$$

 It follows that

$$\begin{aligned} &i\left(U_{\mathbf{u}}(t, 0) - U_{\mathbf{v}}(t, 0)\right)' \\ =&H(\mathbf{u}, t)U_{\mathbf{u}}(t, 0) - H(\mathbf{v}, t)U_{\mathbf{v}}(t, 0) \\ =&[H(\mathbf{u}, t) - H(\mathbf{v}, t)]U_{\mathbf{u}}(t, 0) + H(\mathbf{v}, t)(U_{\mathbf{u}} - U_{\mathbf{v}})(t, 0). \end{aligned} \tag{11}$$

 By the variation-of-parameters formula [11], we have

$$U_{\mathbf{u}}(t, 0) - U_{\mathbf{v}}(t, 0) = -i \int_0^t \mathrm{d}\tau \, U_{\mathbf{v}}(t, \tau)[H(\mathbf{u}, \tau) - H(\mathbf{v}, \tau)]U_{\mathbf{u}}(\tau, 0). \tag{12}$$

 Now, if $\mathbf{u} = \mathbf{v} + h$, we have $H(\mathbf{u}, t) = H(\mathbf{v}, t) + h\frac{\partial H(\mathbf{v}, t)}{\partial \mathbf{v}} + O(h^2)$. Therefore, for each $t \geq 0$, we
 have

$$\frac{U_{\mathbf{u}}(t, 0) - U_{\mathbf{v}}(t, 0)}{h} = -i \int_0^t \mathrm{d}\tau \, U_{\mathbf{v}}(t, \tau) \frac{\partial H(\mathbf{v}, \tau)}{\partial \mathbf{v}} U_{\mathbf{u}}(\tau, 0) + O(h), \tag{13}$$

 which implies the desired result (9) by taking $h \to 0$. $\qquad\square$

 Proposition B.2. *Let $\mathcal{L}$ be defined as (4), and $H(\mathbf{v}, t) = \sum_j f_j(\mathbf{v}, t)H_j$.*

$$\frac{\partial \mathcal{L}}{\partial \mathbf{v}} = \left(-i \int_0^T \mathrm{d}s \sum_{j=1}^m \frac{\partial f_j(\mathbf{v}, s)}{\partial \mathbf{v}} \langle \psi(s)| M_s H_j |\psi(s)\rangle\right) + h.c., \tag{14}$$

 where $|\psi(s)\rangle = U(0, s) |\psi(0)\rangle$, $M_s = U^\dagger(1, s)MU(1, s)$.

Proof. The derivatives can be computed as,

$$\frac{\partial \mathcal{L}}{\partial \mathbf{v}} = \langle \psi(0)| U^\dagger(0,T) M \frac{\partial U(0,T)}{\partial \mathbf{v}} |\psi(0)\rangle + h.c.$$

$$= \left(-i \int_0^T \mathrm{d}s \sum_j \frac{\partial f_j(\mathbf{v},s)}{\partial \mathbf{v}} \langle \psi(0)| U^\dagger(0,s) U^\dagger(s,T) M U(s,T) H_j U(0,s) |\psi(0)\rangle \right) + h.c. \tag{15}$$

$\square$

To compute the derivative $\frac{\partial \mathcal{L}}{\partial \mathbf{v}}$ on a quantum machine, we invoke the parameter-shift formula.

Then we show the MCI generates an unbiased estimation of $\frac{\partial \mathcal{L}}{\partial \mathbf{v}}$ and converges of rate $O(b_{\mathrm{int}}^{-\frac{1}{2}})$. We require that the derivatives of $u(\mathbf{v},t)$ are bounded: $\forall t \in [0,T]$, $\left| \frac{\partial u_j(\mathbf{v},t)}{\partial \mathbf{v}} \right| \leq D$.

The integration mini-batch draws time samplings $\tau \sim \mathrm{Uniform}(0,T)$, and evaluates

$$f(\tau) = \sum_{j=1}^m \frac{\partial u_j}{\partial \mathbf{v}}(\mathbf{v},\tau) \left(p_j^-(\tau) - p_j^+(\tau) \right). \tag{16}$$

Then (6) turns to $\frac{\partial \mathcal{L}}{\partial \mathbf{v}} = \int_0^T f(\tau) \mathrm{d}\tau$. By MCI, the average value of $T \cdot f(\tau)$ in the integration mini-batch is an unbiased estimation of $\frac{\partial \mathcal{L}}{\partial \mathbf{v}}$. By applying the Popocivius's inequality and the Cauchy-Schwarz inequality, we obtain the following variance bound, which guarantees the low error of MCI.

Proposition B.3. *The variance of $f(\tau)$ is finite. Specifically,*

$$Var[f(\tau)] \leq 4m^2 \|M\|^2 D^2. \tag{17}$$

B.2 Proof of Lemma 3.3

Proof. We let $\widehat{\frac{\partial \mathcal{L}}{\partial \mathbf{v}}}$ denote the accurate gradient of the loss function of the quantum machine, and $\frac{\partial \mathcal{L}}{\partial \mathbf{v}}$ denote the estimated gradient via Algorithm 1. Their analytical expressions are

$$\frac{\partial \mathcal{L}}{\partial \mathbf{v}} = -i \int_0^T \mathrm{d}\tau \langle \psi_0| \widehat{U}_\mathbf{v}^\dagger(T,0) M \widehat{U}_\mathbf{v}(T,\tau) \frac{\partial H}{\partial \mathbf{v}} \widehat{U}(\tau,0) |\psi_0\rangle + h.c., \tag{18}$$

$$\widehat{\frac{\partial \mathcal{L}}{\partial \mathbf{v}}} = -i \int_0^T \mathrm{d}\tau \langle \psi_0| \widehat{U}_\mathbf{v}^\dagger(T,0) M \widehat{U}_\mathbf{v}(T,\tau) \frac{\partial \widehat{H}}{\partial \mathbf{v}} \widehat{U}(\tau,0) |\psi_0\rangle + h.c., \tag{19}$$

where $h.c.$ means the Hermitian conjugate of the first half of the expression (this is a common abbreviation among physics, resulting in a Hermitian matrix), and $\widehat{U}_\mathbf{v}(t_2,t_1)$ is the evolution operator under the actual Hamiltonian $\widehat{H}(\mathbf{v},t)$ of the realistic machine. Hence the difference between these two evaluations are

$$\left| \frac{\partial \mathcal{L}}{\partial \mathbf{v}} - \widehat{\frac{\partial \mathcal{L}}{\partial \mathbf{v}}} \right| = \left| -i \int_0^T \mathrm{d}\tau \langle \psi_0| \widehat{U}_\mathbf{v}^\dagger(T,0) M \widehat{U}_\mathbf{v}(T,\tau) \left(\frac{\partial H}{\partial \mathbf{v}} - \frac{\partial \widehat{H}}{\partial \mathbf{v}} \right) \widehat{U}(\tau,0) |\psi_0\rangle + h.c. \right| \tag{20}$$

$$\leq 2T\|M\| \max_{\tau \in [0,T]} \left\| \frac{\partial H}{\partial \mathbf{v}}(\mathbf{v},\tau) - \frac{\partial \widehat{H}}{\partial \mathbf{v}}(\mathbf{v},\tau) \right\|, \tag{21}$$

where $\|\cdot\|$ is the spectral norm [30]. $\square$

B.3 Simulating Approximated System

We show that there are cases that, when simulating the system based on imprecise approximation of the machine Hamiltonian, the gradient estimated is largely off to the actual gradient.

Consider a 1 qubit system $H(v, t) = \frac{\pi}{4} Y + vY$ evolve for time in $[0, 1]$ with initial state $|\psi_0\rangle = |0\rangle$, and measurement $M = |0\rangle \langle 0|$. Let the approximation be $\tilde{H}(v, t) = vY$, whose difference to $H(v, t)$ is constant. Then by Algorithm 1 where the system evolution is executed on quantum machine, the estimated gradient is exact since $\frac{\partial H}{\partial \mathbf{v}} = \frac{\partial \tilde{H}}{\partial \mathbf{v}} = Y$. When simulating the system with $\tilde{H}$ and estimating the gradient as $\widehat{\frac{\partial \mathcal{L}}{\partial \mathbf{v}}}$, however, consider when $v = 0$. Note

$$\widehat{\frac{\partial \mathcal{L}}{\partial \mathbf{v}}} = -i \langle \psi_0 | MY | \psi_0 \rangle + h.c. = 0, \tag{22}$$

$$\frac{\partial \mathcal{L}}{\partial \mathbf{v}} = -i \langle \psi_0 | e^{i \frac{\pi}{4} Y} M Y e^{-i \frac{\pi}{4} Y} | \psi_0 \rangle + h.c. = 1. \tag{23}$$

In a similar way, one can construct cases where the difference between estimated gradient based on the approximated system and actual gradient is as large as $\Theta(T \cdot \|M\| \cdot \|H(v, t) - \tilde{H}(v, t)\|)$.

C IBM Pulse-level control

We adopt the following effective Hamiltonian [43] to model the pulse-level qubit control on the n-qubit IBM machine:

$$H(t) = H_{sys} + H_{ctrl}(t). \tag{24}$$

The system (drift) Hamiltonian is independent of time,

$$H_{sys} = \sum_{j=1}^{n} \frac{\epsilon_j}{2} (I_j - Z_j) + \sum_{\substack{(j,k) \in E \\ j \neq k}} \frac{J_{jk}}{4} (X_j X_k + Y_j Y_k), \tag{25}$$

where E is a bidirectional connectivity graph with self loops, and $J_{jk} = J_{kj}$. The control Hamiltonian is

$$H_{ctrl}(t) = \sum_{j=1}^{n} \sum_{k \in E_j} \mathcal{M}_{jk}(u_{jk}, t) X_j., \tag{26}$$

where the function $\mathcal{M}_{jk}(u_{jk}, t)$ modulates pulse u_{jk} with a local oscillatory frequency ω_k of qubit k:

$$\mathcal{M}_{jk}(u_{jk}, t) = \Omega_j \mathbf{Re}\{e^{i\omega_k t} u_{jk}(t)\}, \tag{27}$$

where Ω_j is the maximal energy input on qubit j, $u_{jk}(t)$ is a complex-valued control pulses and $|u_{jk}(t)| \leq 1$.

On the real machine, $u_{jk}(t)$ should be a piece-wise constant complex-valued function, with each piece having length `dt` $= 0.222$ns. In our simulation we take $u_{jk}(t)$ as continuous function. Taking piece-wise constant approximation of our results will generate pulses that are available on the real machine.

In our 1-qubit experiments, the involved constants are: $n = 1$, $\epsilon_1 = 3.29 \times 10^{10}$, $\omega_1 = 2\pi \times 5.23 \times 10^9$, $\Omega_1 = 9.55 \times 10^8$ and $E_1 = \{1\}$.

In our 2-qubit experiments, the involved constants are: $n = 2$, $\epsilon_1 = 3.29 \times 10^{10}$, $\epsilon_2 = 3.15 \times 10^{10}$, $\omega_1 = 2\pi \times 5.23 \times 10^9$, $\omega_2 = 2\pi \times 5.01 \times 10^9$, $\Omega_1 = 9.55 \times 10^8$, $\Omega_2 = 9.87 \times 10^8$, $J_{12} = 1.23 \times 10^7$ and $E_1 = E_2 = \{1, 2\}$.

D Experiment Details

We present the detailed experiment setups here. Our code is written in Python and C++ and the experiments run on a Desktop with an Intel Xeon W-2123 CPU @ 3.6GHz. In the comparisons, we use existing packages for CMAES and SLSQP with default hyperparameters. More details can be found in our supplementary code.

D.1 Quantum Optimization

D.1.1 Experiment details in comparison to VQE

The workflow of analog-ansatz-based VQE is shown in Figure 5.

Figure 5: Schematic diagram of analog-ansatz-based VQE for the H_2 system.

The H_2 molecule Hamiltonian at bond distance has coefficients $\alpha_0 = -1.0524, \alpha_1 = -0.0113, \alpha_2 = 0.1809, \alpha_3 = -0.3979, \alpha_4 = 0.3979$.

The parameters of different methods are presented below. When updating, the measurements for all methods has sampling size (observation mini-batch size) $b_{\text{obs}} = 100$. When evaluating, matrix multiplication is utilized to have accurate loss function calculation.

Hyper-parameters in our approach. The integration mini-batch size $b_{\text{int}} = 6$; the maximal degree of Legendre polynomial is $d = 3$; the initialization uses Gaussian distribution centered at 0; the optimizer is Adam with learning rate $lr = 0.02$; time duration is $T = 720\mathtt{dt}$ and $T = 360\mathtt{dt}$ correspondingly.

Circuit ansatz VQE: We use a three layered circuit ansatz. Let $U_j(\theta_1, \theta_2, \theta_3) = e^{-i\frac{\theta_3}{2}Z_j}e^{-i\frac{\theta_2}{2}X_j}e^{-i\frac{\theta_1}{2}Z_j}$, and $V_j(\theta) = U_1(\theta_{j11}, \theta_{j21}, \theta_{j31})U_2(\theta_{j12}, \theta_{j22}, \theta_{j32})$. Then the circuit ansatz is $U(\theta) = V_2(\theta)e^{-i\frac{\pi}{2}Z_1X_2}V_1(\theta)$. We substitute a ZX rotation for the cross resonance gate in [33] since they generate the same entanglement.

Finite difference: We use the same ansatz as in our approach. The finite difference formula used is:

$$FD\left(\frac{\partial\mathcal{L}}{\partial\mathbf{v}_i}, h\right) = \frac{1}{2h}\left(\mathcal{L}(\mathbf{v} + h\mathbf{e}_i) - \mathcal{L}(\mathbf{v} - h\mathbf{e}_i)\right), \tag{28}$$

where $\mathbf{e}_i$ is the unit vector whose only non-zero entry is the i-th entry with value 1. We take a small pertubation $h = 10^{-4}$ and simulate the quantum system twice to evaluate corresponding influences.

D.1.2 Experiment details in comparison to QAOA

The workflow of analog-ansatz-based QAOA is shown in Figure 6. The settings of the measurements and the finite difference method are similar as Appendix D.1.1.

Figure 6: Schematic diagram of analog-ansatz-based QAOA for a MaxCut problem.

| (c) 6 qubits | (d) 9 qubits | (d) 11 qubits |

Figure 7: **Comparison with circuit QAOA in scaling up MaxCut problems.** As the size of graphs increases, the number of qubits increases and ours still converges better than VQAs.

Hyper-parameters in our approach: The integration mini-batch size $b_{\text{int}} = 1$; the maximal degree of Legendre polynomial is $d = 3$; the initialization uses Gaussian distribution centered at 0; the optimizer is Adam with learning rate $lr = 0.02$; time duration is $T = 4$.

We also conduct larger experiments on cycle graph involving $6, 9, 11$ vertices, as in Figure 7. Our method still outperforms circuit QAOA with better convergence rate and lower final loss.

D.2 Quantum Control

D.2.1 Experiment details in state preparation

We implement our method, together with three other methods (SLSQP, CAMES, GRAPE) to the two state preparation tasks: (a) to prepare $|+\rangle$ from $|0\rangle$; (b) to prepare $|\Phi^+\rangle$ from $|00\rangle$.

Quantum measurement. In both tasks, the quantum observable used in computing the loss function can be expressed as a sum local Pauli operators. This nice property makes the loss function easy to evaluate on the quantum computer. For the state $|+\rangle$, the observable is

$$M = \mathbb{I} - |+\rangle\langle+| = \frac{1}{2}(\mathbb{I} - X). \tag{29}$$

Similarly, we compute the observable used in preparing the $|\Phi^+\rangle$ state:

$$M = \mathbb{I} - |\Phi^+\rangle\langle\Phi^+| = \frac{1}{4}(X_1X_2 - Y_1Y_2 + Z_1Z_2 - 3\mathbb{I}). \tag{30}$$

Hyper-parameters in our approach. The integration mini-batch size is $b_{int} = 1$ in task (a), and $b_{int} = 400$ in task (b). The maximal degree of Legendre polynomial is $d = 4$ in both cases. The initialization uses Gaussian distribution centered at 0. The optimizer is Adam in both tasks, with learning rate $lr = 0.01$ in (a) and $lr = 0.05$ in (b).

D.2.2 Experiment details in gate synthesis

We implement our method, together with three other methods (SLSQP, CAMES, GRAPE) to the two gate synthesis tasks: (a) to synthesize X gate; (b) to synthesize CNOT gate. The matrix representation of the X gate can be found in (3). The CNOT gate is shown below:

$$\text{CNOT} = \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & 1 & 0 \end{bmatrix}. \tag{31}$$

Quantum measurement. We identify two sets $\mathcal{S}_{\text{X}}$ and $\mathcal{S}_{\text{CNOT}}$ that completely determine the X gate and CNOT gate correspondingly:

$$\mathcal{S}_{\text{X}} = \{(|0\rangle, |1\rangle), (|1\rangle, |0\rangle), (|+\rangle, |+\rangle)\}, \tag{32}$$
$$\mathcal{S}_{\text{CNOT}} = \{(|00\rangle, |00\rangle), (|01\rangle, |01\rangle), (|10\rangle, |11\rangle),$$
$$(|11\rangle, |10\rangle), (|++\rangle, |++\rangle)\}. \tag{33}$$

In $\mathcal{S}_{\text{X}}$ and $\mathcal{S}_{\text{CNOT}}$, one of the computational basis pair can be safely removed. But for the convenience of training we keep them in our experiments.

Hyper-parameters in our approach. The integration mini-batch size is $b_{int} = 1$ in task (a), and $b_{int} = 400$ in task (b). The maximal degree of Legendre polynomial is $d = 4$ in both cases. The initialization uses Gaussian distribution centered at 0. The optimizer is Adam in both tasks, with learning rate $lr = 0.005$ in (a) and $lr = 0.03$ in (b).