Tuning Frequency Bias in Neural Network Training with Nonuniform Data

Abstract

Small generalization errors of over-parameterized neural networks (NNs) can be partially explained by the frequency biasing phenomenon, where gradient-based algorithms minimize the low-frequency misfit before reducing the high-frequency residuals. Using the Neural Tangent Kernel (NTK), one can provide a theoretically rigorous analysis for training where data are drawn from constant or piecewise-constant probability densities. Since most training data sets are not drawn from such distributions, we use the NTK model and a data-dependent quadrature rule to theoretically quantify the frequency biasing of NN training given fully nonuniform data. By replacing the loss function with a carefully selected Sobolev norm, we can further amplify, dampen, counterbalance, or reverse the intrinsic frequency biasing in NN training.

1 Introduction

Neural networks (NNs) are often trained in supervised learning on a small data set. They are observed to provide accurate predictions for a large number of test examples that are not seen during training. A mystery is how training can achieve quite small generalization errors in an overparameterized NN and a so-called "double-descent" risk curve (Belkin et al., 2019). In recent years, a potential answer has emerged called "frequency biasing," which is the phenomenon that in the early epochs of training, an overparameterized NN finds a low-frequency fit of the training data while higher frequencies are learned in later epochs (Rahaman et al., 2019; Yang & Salman, 2019; Xu, 2020). Currently, frequency biasing is theoretically understood via the Neural Tangent Kernel (NTK) (Jacot et al., 2018) for uniform training data (Arora et al., 2019; Cao et al., 2019; Basri et al., 2019) and data distributed according to a piecewise constant probability measure (Basri et al., 2020). However, most training data sets in practice are highly clustered and not uniform. Yet, frequency biasing is still observed during NN training (Fridovich-Keil et al., 2021), even though the theory is absent. This paper proves that frequency biasing is present when there is nonuniform training data by using a new viewpoint based on a data-dependent quadrature rule. We use this theory to propose new loss functions for NN training that accelerate its convergence and improve stability with respect to noise.

A NN function is a map $\mathcal{N} : \mathbb{R}^d \to \mathbb{R}$ given by

$$\mathcal{N}(\mathbf{x}) = \mathbf{W}_{N_L}\sigma\left(\mathbf{W}_{N_L-1}\sigma\left(\cdots\left(\mathbf{W}_2\sigma\left(\mathbf{W}_1\mathbf{x}+\mathbf{b}_1\right)+\mathbf{b}_2\right)+\cdots\right)+\mathbf{b}_{N_L-1}\right)+\mathbf{b}_{N_L},$$

where $\mathbf{W}_i \in \mathbb{R}^{m_i \times m_{i-1}}$ are weights, $m_0 = d$, $\mathbf{b}_i \in \mathbb{R}^{m_i}$ are biases, and N_L is the number of layers. Here, σ is the activation function and applied entry-wise to a vector, i.e., $\sigma(\mathbf{a})_j = \sigma(\mathbf{a}_j)$. In supervised learning, the goal of NN training is to learn weights and bias terms in a NN function, which we denote by $\mathcal{N}(\mathbf{x})$, given training data $(\mathbf{x}_i, y_i)$ for $1 \leq i \leq n$, where $\mathbf{x}_i \in \mathbb{R}^d$ and $y \in \mathbb{R}$. To introduce a continuous perspective, we assume that there is an underlying function $g : \mathbb{R}^d \to \mathbb{R}$ such that $y_i = g(\mathbf{x}_i)$ for $1 \leq i \leq n$ and the $\mathbf{x}_i$'s are distributed according to a distribution $\mu(\mathbf{x})$. The training procedure is often a gradient-based optimization algorithm that minimizes the residual in the squared $L^2(d\mu)$ norm, i.e.,

$$\Phi(\mathbf{W}) = \frac{1}{2}\int_{\mathbb{R}^d} |g(\mathbf{x}) - \mathcal{N}(\mathbf{x}; \mathbf{W})|^2 d\mu(\mathbf{x}) \approx \frac{1}{2n}\sum_{i=1}^{n} |y_i - \mathcal{N}(\mathbf{x}_i; \mathbf{W})|^2, \tag{1}$$

where $\mathbf{W}$ represents the weights and bias terms. In this paper, we consider ReLU NNs, which are NNs for which the activation function is the ReLU function given by $\text{ReLU}(t) = \max(t, 0)$.

The ReLU activation function has a useful multiplicative property that $\mathrm{ReLU}(\alpha t) = \alpha \mathrm{ReLU}(t)$ for any $\alpha > 0$. Due to this property, we assume that the training samples are normalized so that $\mathbf{x}_1, \ldots, \mathbf{x}_n \in \mathbb{S}^{d-1}$. Similar to most theoretical studies investigating frequency biasing, we restrict ourselves to 2-layer NNs (Arora et al., 2019; Basri et al., 2019; Su & Yang, 2019; Cao et al., 2019).

To study NN training, it is common to consider the dynamics of $\Phi(\mathbf{W})$ as one optimizes the weights and biases in $\mathbf{W}$. For example, the gradient flow of the NN weights is given by $\frac{d\mathbf{W}}{dt} = -\frac{\partial \Phi}{\partial \mathbf{W}}$. Define the residual $z(\mathbf{x}; \mathbf{W}) = g(\mathbf{x}) - \mathcal{N}(\mathbf{x}; \mathbf{W})$. We have

$$\frac{dz(\mathbf{x}; \mathbf{W})}{dt} = -\int_{\mathbb{S}^{d-1}} K(\mathbf{x}, \mathbf{x}'; \mathbf{W}) z(\mathbf{x}'; \mathbf{W}) d\mu(\mathbf{x}'), \tag{2}$$

where $K(\mathbf{x}, \mathbf{x}'; \mathbf{W}) = \left\langle \frac{\partial \mathcal{N}(\mathbf{x}; \mathbf{W})}{\partial \mathbf{W}}, \frac{\partial \mathcal{N}(\mathbf{x}'; \mathbf{W})}{\partial \mathbf{W}} \right\rangle$. Under the assumptions that the weights do not change much during training, one can consider the NTK in the mean-field regime given the underlying time-independent distribution of $\mathbf{W}$, i.e., $K^{\infty}(\mathbf{x}, \mathbf{x}') = \mathbb{E}_{\mathbf{W}}[K(\mathbf{x}, \mathbf{x}'; \mathbf{W})]$ (Du et al., 2018). Based on eq. (2), one can understand the decay of the residual by studying the reproducing kernel Hilbert space (RKHS) through a spectral decomposition of the integral operator $\mathcal{L}$ defined by $(\mathcal{L}z)(\mathbf{x}) = \int K^{\infty}(\mathbf{x}, \mathbf{x}') z(\mathbf{x}') d\mu(\mathbf{x}')$. Most results in the literature require $\mu(\mathbf{x})$ to be the uniform distribution over the sphere so that the eigenfunctions of $\mathcal{L}$ are spherical harmonics and the eigenvalues have explicit forms (Cao et al., 2019; Basri et al., 2019; Scetbon & Harchaoui, 2021). These explicit formulas for the eigenvalues and eigenfunctions of $\mathcal{L}$ rely on the Funk–Hecke theorem, which provides a formula allowing one to express an integral over a hypersphere by an integral over an interval (Seeley, 1966). The frequency biasing of NN training can be explained by the fact that low-degree spherical harmonic polynomials are eigenfunctions of $\mathcal{L}$ associated with large eigenvalues (Basri et al., 2019). Thus, for uniform training data, the optimization of the weights and biases of an NN tends to fit the low-frequency components of the residual first.

When $\mu(\mathbf{x})$ is nonuniform, it is difficult to analyze the spectral properties of $\mathcal{L}$ and thus the frequency biasing properties of NN training. Since the Funk–Hecke formula no longer holds, there are only a few special cases where frequency biasing is understood (Williams & Rasmussen, 2006, Sec. 4.3). Although one may derive asymptotic bounds for the eigenvalues (Widom, 1963; 1964; Bach & Jordan, 2002), it is very hard to obtain formulas for the eigenfunctions, and one usually relies on numerical approximations (Baker, 1977). For the ReLU-based NTK, (Basri et al., 2020) provided explicit eigenfunctions assuming that the $\mu(\mathbf{x})$ is piecewise constant on $\mathbb{S}^1$, but this analysis does not generalize to higher dimension. To study the frequency biasing of NN training, one needs to understand both the eigenvalues and eigenfunctions of $\mathcal{L}$, and this remains a significant challenge for a general $\mu(\mathbf{x})$ due to the absence of the Funk–Hecke formula.

To overcome this challenge, we take a radically different point-of-view. While it is standard to discretize the integral in eq. (1) using a Monte Carlo-like average, we discretize it using a data-dependent quadrature rule where the nodes are at the training data. That is, we investigate frequency biasing of NN training when minimizing the residual in the standard squared L^2 norm:

$$\widetilde{\Phi}(\mathbf{W}) = \frac{1}{2} \int_{\mathbb{S}^{d-1}} |g(\mathbf{x}) - \mathcal{N}(\mathbf{x}; \mathbf{W})|^2 d\mathbf{x} \approx \frac{1}{2} \sum_{i=1}^{n} c_i |y_i - \mathcal{N}(\mathbf{x}_i; \mathbf{W})|^2, \tag{3}$$

where $c_1, \ldots, c_n$ are the quadrature weights associated with the (nonuniform) input data $\mathbf{x}_1, \ldots, \mathbf{x}_n$. If $\mathbf{x}_1, \ldots, \mathbf{x}_n$ are drawn from a uniform distribution over the hypersphere, then one can select $c_i = A_d/n$ for $1 \leq i \leq n$, where A_d is the Lebesgue measure of the hypersphere; otherwise, one can choose any quadrature weights so that the integration rule is accurate (see section 4.2). If $\mathbf{x}_1, \ldots, \mathbf{x}_n$ are drawn at random from $\mu(\mathbf{x})$, then it is often reasonable to select $c_i = 1/(np(\mathbf{x}_i))$, where $d\mu(\mathbf{x}) = p(\mathbf{x})d\mathbf{x}$. While $c_1, \ldots, c_n$ depend on $\mathbf{x}_1, \ldots, \mathbf{x}_n$, the continuous expression for $\widetilde{\Phi}(\mathbf{W})$ is always unaltered in eq. (3). Therefore, we can use the Funk–Hecke formula to analyze the eigenvalues and eigenfunctions of $\tilde{\mathcal{L}}$ defined by $(\tilde{\mathcal{L}}z)(\mathbf{x}) = \int_{\mathbb{S}^{d-1}} K^{\infty}(\mathbf{x}, \mathbf{x}') z(\mathbf{x}') d\mathbf{x}'$, allowing us to understand frequency biasing.

In this paper, we propose to minimize the residual in a squared Sobolev H^s norm for a carefully selected $s \in \mathbb{R}$. Unlike the L^2 norm (the case of $s = 0$), the H^s norm for $s \neq 0$ has its own frequency bias. For $s > 0$, H^s penalizes high frequencies more than low, while for $s < 0$, low frequencies are penalized the most. We implement the squared H^s norm using a quadrature rule, which induces a different integral operator $\mathcal{L}_s$. We analyze the eigenvalues and eigenfunctions of $\mathcal{L}_s$,

and consequently, the frequency biasing in the NN training using the Funk–Hecke formula. Given our new understanding of frequency biasing, we select s so that the H^s norm amplifies, dampens, counterbalances, or reverses the natural frequency biasing from an overparameterized NN training.

Contributions. We have three main contributions.

(1) From our quadrature point-of-view, we analyze the frequency biasing in training a 2-layer over-parameterized ReLU NN with nonuniform training data. In Theorem 2, we show that the theory of frequency biasing in (Basri et al., 2019) for uniform training data continues to hold in the nonuniform case up to quadrature errors. In Theorem 3, we provide control of the quadrature errors.

(2) We use our knowledge of frequency biasing to modify the usual squared L^2 loss function to a squared H^s norm. By carefully selecting s, we can amplify, dampen, counterbalance, or reverse the intrinsic frequency biasing in NN training and accelerate the observed convergence of gradient-based optimization procedures.

(3) A potential issue with the H^s norm is the difficulties of implementing with high-dimensional training data. Using an image dataset of dimension $28^2 = 784$, we show how to use an encoder-decoder architecture to implement a practical version of the squared H^s norm loss and adjust the frequency biasing in NN training to suppress noises of different frequencies. (see Figure 4).

2 PRELIMINARIES AND NOTATION

For $d > 1$, let $g : \mathbb{S}^{d-1} \to \mathbb{R}$ be a square-integrable function defined on $\mathbb{S}^{d-1}$. The function g can be expressed in a spherical harmonic expansion given by

$$g(\mathbf{x}) = \sum_{\ell=0}^{\infty} \sum_{p=1}^{N(d,\ell)} \hat{g}_{\ell,p} Y_{\ell,p}(\mathbf{x}), \qquad \hat{g}_{\ell,p} = \int_{\mathbb{S}^{d-1}} g(\mathbf{x}) Y_{\ell,p}(\mathbf{x}) d\mathbf{x}, \tag{4}$$

where $Y_{\ell,p}$ is the spherical harmonic function of degree ℓ and order p. Here, $N(d,\ell)$ is the number of spherical harmonic functions of degree ℓ so that $N(d,0) = 1$ and $N(d,\ell) = (2\ell + d - 2)\Gamma(\ell + d - 2)/(\Gamma(\ell + 1)\Gamma(d - 1))$ for $\ell \geq 1$. The set $\{Y_{\ell,p}\}_{\ell \geq 0, 1 \leq p \leq N(d,\ell)}$ is an orthonormal basis for $L^2(\mathbb{S}^{d-1})$. Let $\mathcal{H}_\ell^d$ be the span of $\{Y_{\ell,p}\}_{p=1}^{N(d,\ell)}$. Let $\Pi_\ell^d = \bigoplus_{j=0}^{\ell} \mathcal{H}_j^d$ be the space of spherical harmonics of degree $\leq \ell$.

Given distinct training data $\{\mathbf{x}_i\}_{i=1}^n$ from $\mathbb{S}^{d-1}$ and evaluations $y_i = g(\mathbf{x}_i)$ for $1 \leq i \leq n$, our goal is to understand the intrinsic frequency-biasing behavior of training a 2-layer ReLU NN given by

$$\mathcal{N}(\mathbf{x}) = \frac{1}{\sqrt{m}} \sum_{r=1}^{m} a_r \mathrm{ReLU}(\mathbf{w}_r^\top \mathbf{x} + b_r), \qquad \mathrm{ReLU}(t) = \max(t, 0), \tag{5}$$

where m is the number of neurons, $\mathbf{w}_1, \ldots, \mathbf{w}_m$ and $a_1, \ldots, a_m$ are weights, and $b_1, \ldots, b_m$ are the bias terms. We begin with the same setup as in Basri et al. (2020): assuming that (1) $\mathbf{w}_1, \ldots, \mathbf{w}_m$ are initialized independently and identically distributed (iid) from Gaussian random variables with covariance matrix $\kappa^2 \mathbf{I}$, where $\kappa > 0$, (2) the bias terms are initialized to zero, and (3) $a_1, \ldots, a_m$ are initialized iid as $+1$ with probability $1/2$ and -1 otherwise, and $\{a_r\}$ are not updated during the training process.

We use a gradient-based optimization scheme to train for the weights and biases and aim to minimize the residual defined by a symmetric positive definite matrix $\mathbf{P}$, which can be neatly written as

$$\Phi_\mathbf{P}(\mathbf{W}) = \frac{1}{2}(\mathbf{y} - \mathbf{u})^\top \mathbf{P}(\mathbf{y} - \mathbf{u}), \tag{6}$$

where $\mathbf{y} = (g(\mathbf{x}_1), \ldots, g(\mathbf{x}_n))^\top$ and $\mathbf{u} = (\mathcal{N}(\mathbf{x}_1), \ldots, \mathcal{N}(\mathbf{x}_n))^\top$. For example, we have $\mathbf{P} = n^{-1}\mathbf{I}$ in eq. (1) and $\mathbf{P} = \mathrm{diag}(c_1, \ldots, c_n)$ in eq. (3). Recall that $\mathbf{W}$ represents all the weights and biases of the NN. Given the loss function, we train the NN based on the gradient descent algorithm:

$$\mathbf{w}_r(k+1) - \mathbf{w}_r(k) = -\eta \frac{\partial \Phi_\mathbf{P}}{\partial \mathbf{w}_r}, \qquad b_r(k+1) - b_r(k) = -\eta \frac{\partial \Phi_\mathbf{P}}{\partial b_r}, \tag{7}$$

where k is the iteration number and $\eta > 0$ is the learning rate. The matrix $\mathbf{P}$ induces an inner product $\langle \boldsymbol{\xi}, \boldsymbol{\zeta} \rangle_\mathbf{P} = \boldsymbol{\xi}^\top \mathbf{P} \boldsymbol{\zeta}$, which leads to a finite-dimensional Hilbert space with the

norm $\|\boldsymbol{\xi}\|_{\mathbf{P}} = \sqrt{\langle \boldsymbol{\xi}, \boldsymbol{\xi} \rangle_{\mathbf{P}}}$. Given a matrix $\mathbf{A} \in \mathbb{R}^{n \times n}$, we define its operator norm $\|\mathbf{A}\|_{\mathbf{P}} = \sup_{\boldsymbol{\xi} \in \mathbb{R}^n, \|\boldsymbol{\xi}\|_{\mathbf{P}}=1} \|\mathbf{A}\boldsymbol{\xi}\|_{\mathbf{P}}$. We also define a finite positive number that depends on $\mathbf{P}$:

$$M_{\mathbf{P}} = \sup_{\boldsymbol{\xi} \in \mathbb{R}^n, \|\boldsymbol{\xi}\|_2 = 1} \|\boldsymbol{\xi}\|_{\mathbf{P}} = \sup_{\boldsymbol{\xi} \in \mathbb{R}^n \backslash \{\mathbf{0}\}} \sqrt{\frac{\boldsymbol{\xi}^\top \mathbf{P} \boldsymbol{\xi}}{\boldsymbol{\xi}^\top \boldsymbol{\xi}}} = \sup_{\boldsymbol{\zeta} \in \mathbb{R}^n \backslash \{\mathbf{0}\}} \sqrt{\frac{\boldsymbol{\zeta}^\top \mathbf{P}^{1/2} \mathbf{P} \mathbf{P}^{1/2} \boldsymbol{\zeta}}{\boldsymbol{\zeta}^\top \mathbf{P}^{1/2} \mathbf{P}^{1/2} \boldsymbol{\zeta}}} = \sup_{\boldsymbol{\zeta} \in \mathbb{R}^n, \|\boldsymbol{\zeta}\|_{\mathbf{P}}=1} \|\mathbf{P}\boldsymbol{\zeta}\|_2 . \quad (8)$$

Note that by the third expression in eq. (8), we also have $M_{\mathbf{P}} = \|\mathbf{P}^{1/2}\|_2 = \sqrt{\|\mathbf{P}\|_2}$. Furthermore, we define the matrix $\mathbf{H}^\infty \in \mathbb{R}^{n \times n}$ by

$$H_{ij}^\infty = \mathbb{E}_{\mathbf{w} \sim \mathcal{N}(\mathbf{0}, \kappa^2 \mathbf{I})} \left[\frac{\mathbf{x}_i^\top \mathbf{x}_j + 1}{2} \mathbb{I}_{\{\mathbf{w}^\top \mathbf{x}_i, \mathbf{w}^\top \mathbf{x}_j \geq 0\}} \right] = \frac{(\mathbf{x}_i^\top \mathbf{x}_j + 1)(\pi - \arccos(\mathbf{x}_i^\top \mathbf{x}_j))}{4\pi}. \quad (9)$$

Note that due to the introduction of the biases, $\mathbf{H}^\infty$ is slightly different than the one in (Du et al., 2018; Arora et al., 2019). In fact, in contrast with (Du et al., 2018), $\mathbf{H}^\infty$ defined in eq. (9) is positive definite regardless of the distribution of the training data, as shown in the supplementary material.

Proposition 1. If $\mathbf{x}_1, \ldots, \mathbf{x}_n$ are distinct, then $\mathbf{H}^\infty$ in eq. (9) is symmetric and positive definite.

As a consequence of Proposition 1, the matrix $\mathbf{H}^\infty \mathbf{P}$ has positive eigenvalues, which we denote by $\lambda_{n-1} \geq \cdots \geq \lambda_0 > 0$. One can view $\mathbf{H}^\infty$ as coming from sampling a continuous kernel $K^\infty : \mathbb{S}^{d-1} \times \mathbb{S}^{d-1} \to \mathbb{R}$ given by

$$K^\infty(\mathbf{x}, \mathbf{y}) = K^\infty(\langle \mathbf{x}, \mathbf{y} \rangle) = \frac{(\langle \mathbf{x}, \mathbf{y} \rangle + 1)(\pi - \arccos(\langle \mathbf{x}, \mathbf{y} \rangle))}{4\pi}, \quad (10)$$

where $\langle \cdot, \cdot \rangle$ is the ℓ^2 inner-product. It is convenient to view $\mathbf{H}^\infty$ as being a discretization of K^∞ as the eigenvalues and eigenfunctions of K^∞ are known explicitly via the Funk–Hecke formula (Basri et al., 2019). It follows that

$$\int_{\mathbb{S}^{d-1}} K^\infty(\mathbf{x}, \mathbf{y}) Y_{\ell,p}(\mathbf{y}') d\mathbf{y} = \mu_\ell Y_{\ell,p}(\mathbf{x}), \qquad \ell \geq 0. \quad (11)$$

The explicit formulas for μ_ℓ with $\ell \geq 0$ are given in the supplementary material. We find that $\mu_\ell > 0$ for all ℓ and μ_ℓ is asymptotically $\mathcal{O}(\ell^{-d})$ for large ℓ (Basri et al., 2019; Bietti & Mairal, 2019).

3 THE CONVERGENCE OF NEURAL NETWORK TRAINING WITH A GENERAL LOSS FUNCTION

Given the NN model in eq. (5) and a general loss function $\Phi_{\mathbf{P}}$ in eq. (6), we are interested in the convergence rate of NN training. We study this by analyzing the convergence rate for each harmonic component. We start by presenting a convergence result that holds for any SPD matrix $\mathbf{P}$. It says that up to an error ϵ, which can be made arbitrarily small by taking κ small enough and m large enough, the residual of the NN at the kth iteration is approximately $(\mathbf{I} - 2\eta \mathbf{H}^\infty \mathbf{P})^k \mathbf{y}$.

Theorem 1. In eq. (5), suppose that $\mathbf{w}_1, \ldots, \mathbf{w}_m$ are initialized iid from Gaussian random variables with covariance matrix $\kappa^2 \mathbf{I}$, $b_1, \ldots, b_m$ are initialized to zero, and $a_1, \ldots, a_m$ are initialized iid as $+1$ with probability $1/2$ and -1 otherwise. Suppose the NN is trained with training data $(\mathbf{x}_i, y_i)$ for $1 \leq i \leq n$, loss function $\Phi_{\mathbf{P}}$ in eq. (6) for a symmetric positive definite matrix $\mathbf{P}$, and the training procedure is the gradient descent update rule eq. (7) with step size η. Let $\mathcal{N}_k$ be the NN function after the kth iteration and $\mathbf{u}(k) = (\mathcal{N}_k(\mathbf{x}_1), \ldots, \mathcal{N}_k(\mathbf{x}_n))$, where $\mathcal{N}_0$ is the initial NN function. Let an accuracy goal $0 < \epsilon < 1$, a probability of failure $0 < \delta < 1$, and a time span $T > 0$ be given. Then, there exist constants $C_1, C_2 > 0$ that depend only on the dimension d such that if $0 \leq \eta \leq 1/(2M_{\mathbf{P}}^2 n)$ (see eq. (8)), $\kappa \leq C_1 \epsilon M_{\mathbf{P}}^{-1} \sqrt{\delta/n}$, and m satisfies

$$m \geq C_2 \left(\frac{M_{\mathbf{P}}^6 n^3}{\kappa^2 \epsilon^2} \left(\lambda_0^{-4} + \eta^4 T^4 \epsilon^4 \right) + \frac{M_{\mathbf{P}}^4 n^2 \log(n/\delta)}{\epsilon^2} \left(\lambda_0^{-2} + \eta^2 T^2 \epsilon^2 \right) \right), \quad (12)$$

then with probability $\geq 1 - \delta$, we have

$$\mathbf{y} - \mathbf{u}(k) = (\mathbf{I} - 2\eta \mathbf{H}^\infty \mathbf{P})^k \mathbf{y} + \boldsymbol{\epsilon}(k), \qquad \|\boldsymbol{\epsilon}(k)\|_{\mathbf{P}} \leq \epsilon, \qquad 0 \leq k \leq T. \quad (13)$$

Here, $\mathbf{H}^\infty$ is defined in eq. (9), $\mathbf{y} = (g(\mathbf{x}_1), \ldots, g(\mathbf{x}_n))^\top$, and λ_0 is the smallest eigenvalue of $\mathbf{H}^\infty \mathbf{P}$.

We defer the proof to the supplementary material, which uses techniques from (Su & Yang, 2019). The main idea behind the proof is that $\mathbf{I} - 2\eta\mathbf{H}^\infty\mathbf{P}$ is close to the transition matrix for the residual $\mathbf{y} - \mathbf{u}(k)$ when m is large. By taking κ small, we can control the size of $\mathbf{u}(0)$ and therefore obtain $\mathbf{y} - \mathbf{u}(k) \approx (\mathbf{I} - 2\eta\mathbf{H}^\infty\mathbf{P})^k(\mathbf{y} - \mathbf{u}(0)) \approx (\mathbf{I} - 2\eta\mathbf{H}^\infty\mathbf{P})^k\mathbf{y}$. Furthermore, $M_\mathbf{P}^2 n$ is an upper bound on λ_{n-1}, the maximum eigenvalue of $\mathbf{H}^\infty\mathbf{P}$. Therefore, our rate of convergence does not vanish as the number of training data points $n \to \infty$, provided that $M_\mathbf{P} = \mathcal{O}(n^{-1/2})$. This is the case when $\mathbf{P} = n^{-1}\mathbf{I}$, which corresponds to eq. (1). So, we overcome the vanishing convergence rate issue that appears in previous analyses of frequency biasing (Arora et al., 2019; Basri et al., 2019). As η decreases, the gradient descent algorithm gets closer to the gradient flow algorithm (Du et al., 2018), which allows us to more accurately quantify the frequency biasing (see section 4).

4 FREQUENCY BIASING WITH AN $\mathbf{L^2}$-BASED LOSS FUNCTION

The standard mean-squared loss function in eq. (1) corresponds to setting $c_i = 1/n$ for $1 \leq i \leq n$ in eq. (3). When μ is uniform, eq. (1) and eq. (3) are equivalent; when μ is nonuniform, we introduce a quadrature rule with nodes $\mathbf{x}_1, \ldots, \mathbf{x}_n$ and weights $c_1, \ldots, c_n$ to approximate the standard L^2 loss function eq. (3). The weights are selected so that for low-frequency functions $f : \mathbb{S}^{d-1} \to \mathbb{R}$, the quadrature error

$$E_c(f) = \int_{\mathbb{S}^{d-1}} f(\mathbf{x})d\mathbf{x} - \sum_{i=1}^{n} c_i f(\mathbf{x}_i) \tag{14}$$

is relatively small.[1] A reasonable quadrature rule has positive weights for numerical stability and satisfies $\sum_{i=1}^{n} c_i = A_d$ so that it exactly integrates constants. The continuous squared L^2 loss function based on the Lebesgue measure is then discretized to be the square of a weighted discrete ℓ^2 norm (see eq. (3)). Hence, we take $\mathbf{P} = \mathbf{D}_c = \mathrm{diag}(c_1, \ldots, c_n)$, which is positive definite as the c_i's are positive. For a vector $\mathbf{v} \in \mathbb{R}^n$, we write $\|\mathbf{v}\|_c^2 = \mathbf{v}^\top \mathbf{D}_c \mathbf{v}$ and set $c_{\max} = \max_{1 \leq i \leq n}\{c_i\}$.

We now apply Theorem 1 to study the frequency biasing of NN training with the squared L^2 loss function eq. (3). We state these results in terms of quadrature errors. Recall our continuous setup where we assume that the training data is taken from a function $g : \mathbb{S}^{d-1} \to \mathbb{R}$ so that $y_i = g(\mathbf{x}_i)$ for $1 \leq i \leq n$. We further assume that g is bandlimited with bandlimit L where $g = g_0 + \cdots + g_L$ and $g_\ell \in \mathcal{H}_\ell^d$ for $0 \leq \ell \leq L$. We define our quadrature errors as

$$e_{j,\ell,p}^a = E_c(g_j Y_{\ell,p}), \quad e_{i,\ell,p}^b = E_c(K^\infty(\mathbf{x}_i, \cdot)Y_{\ell,p}), \quad e_{j,\ell}^c = E_c(g_j g_\ell), \quad e_{i,\ell}^d = E_c(K^\infty(\mathbf{x}_i, \cdot)g_\ell), \tag{15}$$

where $1 \leq i \leq n$, $j, \ell \geq 0$, and $1 \leq p \leq N(d, \ell)$, and we interpret $g_\ell = 0$ when $\ell > L$.

4.1 A FREQUENCY-BASED FORMULA FOR THE TRAINING ERROR

We obtain a similar result to (Arora et al., 2019, Thm. 4.1) when using the standard squared L^2 loss function eq. (3), except our step size does not depend on λ_0. Instead of expressing the training error in terms of the eigenvalues and eigenvectors of $\mathbf{H}^\infty\mathbf{D}_c$, we directly relate the training error to the frequency component of the target function g and the eigenvalues of the continuous kernel K^∞.

Theorem 2. Under the same setup and assumptions of Theorem 1, let $\mathbf{P} = \mathbf{D}_c$ and $M_\mathbf{P} = \sqrt{c_{\max}}$. If $g : \mathbb{S}^{d-1} \to \mathbb{R}$ is a bandlimited function with bandlimit L and $1 - 2\eta\mu_\ell > 0$ for all $0 \leq \ell \leq L$ (see eq. (11)), then with probability $\geq 1 - \delta$ we have

$$\|\mathbf{y} - \mathbf{u}(k)\|_c = \sqrt{\sum_{\ell=0}^{L}(1 - 2\eta\mu_\ell)^{2k}\|g_\ell\|_{L^2}^2 + \varepsilon_1(k) + \varepsilon_2 + \varepsilon_3(k)}, \quad |\varepsilon_3(k)| \leq \epsilon, \quad 0 \leq k \leq T, \tag{16}$$

where $\varepsilon_1(k)$ and ε_2 satisfy

$$|\varepsilon_1(k)| \leq \left|\sum_{j=0}^{L}\sum_{\ell=0}^{L}(1 - 2\eta\mu_j)^k(1 - 2\eta\mu_\ell)^k e_{j,\ell}^c\right|, \qquad |\varepsilon_2| \leq \sum_{\ell=0}^{L}\frac{\sqrt{A_d}}{\mu_\ell}\max_{1 \leq i \leq n}\left|e_{i,\ell}^d\right|.$$

---

[1] In the case where we do not have a good quadrature rule associated with $\{\mathbf{x}_i\}_{i=1}^n$, we could only have very limited understanding of the spectral property of the target function given its values at $\{\mathbf{x}_i\}_{i=1}^n$, making frequency bias a void topic. Hence, we assume the existence of a good quadrature rule for theoretical purposes.

The proof of Theorem 2 is postponed to the supplementary material. The idea is that by Theorem 1, we know $\mathbf{y} - \mathbf{u}(k) = (\mathbf{I} - 2\eta\mathbf{H}^\infty\mathbf{D_c})^k\mathbf{y} + \boldsymbol{\varepsilon}_3(k)$. Using Funk–Hecke formula and quadrature, we have that $1 - 2\eta\mu_\ell$ are roughly the eigenvalues of $\mathbf{I} - 2\eta\mathbf{H}^\infty\mathbf{D_c}$ and $\mathbf{y}_\ell = (g_\ell(\mathbf{x}_1), \ldots, g_\ell(\mathbf{x}_n))^\top$ are associated eigenvectors. Hence, $\mathbf{y} - \mathbf{u}(k) \approx \sum_{\ell=0}^{L}(1 - 2\eta\mu_\ell)^k\mathbf{y}_\ell$. This can be made precise by introducing ε_2. Finally, up to some quadrature error ε_1, we have $\langle g_j, g_\ell \rangle_{L^2} \approx A_d n^{-1}\mathbf{y}_j^\top\mathbf{y}_\ell$, which gives us eq. (16). Since $\sum_{i=1}^{n}c_i = A_d$, For a fixed data distribution μ, we expect that $c_{\max} = \mathcal{O}(n^{-1})$ as $n \to \infty$ so that η does not decay as $n \to \infty$. Up to a quadrature error, $\|\mathbf{y} - \mathbf{u}(k)\|_{\mathbf{c}}$ is close to the L^2 norm of the residual function $g - \mathcal{N}_k$. Explicit formulas for the eigenvalues $\{\mu_\ell\}$ (see eq. (11)) are given in (Basri et al., 2019), and it was shown that $\mu_\ell = \mathcal{O}(\ell^{-d})$ (Bietti & Mairal, 2019). Theorem 2 demonstrates the frequency bias in NN training as the rate of convergence for frequency $0 \leq \ell \leq L$ is $1 - 2\eta\mu_\ell$, which is close to 1 when ℓ is large. As $\eta \to 0$, we have $(1 - 2\eta\mu_\ell)^{2t/\eta} \to e^{-4\mu_\ell t}$, which is the rate of convergence for frequency using gradient flow. Therefore, we expect that NN training approximates the low-frequency content of g faster than its high-frequency one, which is similar to the case of training with uniform data (Basri et al., 2019).

4.2 Estimating the quadrature errors

We now quantify the quadrature errors in Theorem 2. If we can design a quadrature rule at the training data $\mathbf{x}_1, \ldots, \mathbf{x}_n$ such that the quadrature error satisfies

$$|E_{\mathbf{c}}(h)| = \left| \int_{\mathbb{S}^{d-1}} h(\mathbf{x})d\mathbf{x} - \sum_{i=1}^{n} c_i h(\mathbf{x}_i) \right| \leq \gamma_{n,\ell}\|h\|_{L^\infty}, \qquad h \in \Pi_\ell^d, \quad \ell \geq 0, \qquad (17)$$

for some constant $\gamma_{n,\ell} \geq 0$, then we can bound the terms in eq. (15). We expect that for each fixed ℓ, $\gamma_{n,\ell} \to 0$ as $n \to \infty$ as this is saying that integrals can be calculated more accurately for a large number of quadrature nodes. Under the reasonable assumption that our quadrature rule satisfies eq. (17), we can bound the quadrature errors appearing in Theorem 2.

Theorem 3. Under the same assumptions of Theorem 2, and that the quadrature rule satisfies eq. (17), there exist constants $C_1, C_2 > 0$ only depending on the dimension d such that the terms $|\varepsilon_1(k)|$ and $|\varepsilon_2|$ in Theorem 2 satisfy

$$|\varepsilon_1(k)| \leq C_1\left(\frac{L^3}{\ell} + L^2\gamma_{n,\ell}\right)\max_{0 \leq j \leq L}\|g_j\|_{L^\infty}, \qquad |\varepsilon_2| \leq C_2\left(\frac{L^2}{\ell} + L\gamma_{n,\ell}\right)\max_{0 \leq j \leq L}\|g_j\|_{L^\infty}\sum_{j=0}^{L}\mu_j^{-1}$$

for all $k \geq 0$, $\ell \geq 1$, where $g = g_0 + \cdots + g_L$ with $g_j \in \mathcal{H}_j^d$.

The proof is in the supplementary material. Theorem 3 states that $\varepsilon_1(k)$ and ε_2 can be made arbitrarily small if the quadrature errors converges to 0 as the number of nodes $n \to \infty$. In particular, if there is a sequence $\{\ell_n\}$ that increases to ∞ such that the quadrature rule is exact for all functions $h \in \Pi_{\ell_n}^d$, i.e., $E_{\mathbf{c}}(h) = 0$, where $\ell_n \to \infty$ (see e.g. (Mhaskar et al., 2000)), the rates of convergence of $\varepsilon_1(k)$ and ε_2 are both $\mathcal{O}(1/\ell_n)$ for a fixed g. Without the quadrature being exact, we still have nice convergence provided the quadrature errors are small, as the following corollary shows.

Corollary 1. Suppose there exists a sequence $\ell_n \to \infty$ such that $\gamma_{n,\ell_n} \to 0$ as $n \to \infty$. Then, for a fixed $L \geq 0$, we have $\max_{k \geq 0, g \in \Pi_L^d}|\varepsilon_1(k)|/\|g\|_{L^2}^2$ and $\max_{g \in \Pi_L^d}|\varepsilon_2|/\|g\|_{L^2} \to 0$ as $n \to \infty$.

Corollary 1 shows that as n increases, the quadrature errors $\varepsilon_1(k)$ and ε_2 converge to zero. Moreover, this convergence is uniform in the sense that it does not depend on the specific choice of $g \in \Pi_L^d$. Here, we normalize $\varepsilon_1(k)$ and ε_2 by $\|g\|_{L^2}^2$ and $\|g\|_{L^2}$, respectively, to obtain the "relative" quadrature errors that do not scale when g is multiplied by a scalar (see (16)).

5 Frequency biasing with a Sobolev-norm loss function

The frequency biasing during the training of an overparameterized NN has several consequences. In some situations, worse convergence rates for high-frequency components of a function are beneficial since the NN training procedure is less sensitive to the oscillatory noise in the data, acting as a low-pass filter. This significantly improves the generalization error of overparameterized NNs.

However, in other situations, NN training struggles to accurately learn the high-frequency content of g, resulting in slow convergence. To precisely control the frequency biasing of NN training, we propose to train a NN with a loss function that has intrinsic spectral bias. One such example is the so-called Sobolev norm. Let $\mathcal{D}'(\mathbb{S}^{d-1})$ be the space of distributions on $\mathbb{S}^{d-1}$. Given $s \in \mathbb{R}$, consider $\mathcal{L}^s : \mathcal{D}'(\mathbb{S}^{d-1}) \mapsto \mathcal{D}'(\mathbb{S}^{d-1})$, where $\mathcal{L}^s = \left(I + (-\Delta)^{1/2}\right)^s$ and Δ is the Laplace–Beltrami operator on the sphere. We follow (Barceló et al., 2021) and define the spherical Sobolev space $H^s(\mathbb{S}^{d-1}) = \{f \in \mathcal{D}'(\mathbb{S}^{d-1}) : \mathcal{L}^s f \in L^2(\mathbb{S}^{d-1})\}$, equipped with a norm equivalent to eq. (1.24) in (Barceló et al., 2021),

$$\|f\|^2_{H^s(\mathbb{S}^{d-1})} = \sum_{\ell=0}^{\infty} \sum_{p=1}^{N(d,\ell)} (1+\ell)^{2s} \left|\hat{f}_{\ell,p}\right|^2,$$

where $\hat{f}_{\ell,p}$ are the spherical harmonic coefficients of f (see eq. (4)) and $N(d,\ell)$ is given in Section 2. We propose to set the loss function to be $\frac{1}{2}\|g - \mathcal{N}\|^2_{H^s}$ in replace of $\frac{1}{2}\|g - \mathcal{N}\|^2_{L^2}$ in eq. (3). When $s = 0$, the H^0 Sobolev norm reduces to the L^2 norm as all spherical harmonic coefficients have an equal weight of 1. If $s > 0$, then the high-frequency spherical harmonic coefficients are amplified by $(1+\ell)^{2s}$. The high-frequency components of the residual are then penalized more in the loss function. Hence, we expect the NN training to learn the high-frequency components faster with the squared H^s loss function than the case of eq. equation 3. Similarly, if $s < 0$, then the high-frequency spherical harmonic coefficients are dampened by $(1+\ell)^{2s}$. Consequently, one expects that the NN training process captures the high-frequency components of the residual more slowly with the squared H^s loss function. However, when $s < 0$, we expect that the training is more robust to high-frequency noise in the training data. By tuning the parameter s, we can control the frequency biasing in NN training (see Theorem 4). The choice of s for a particular application can be determined from theory or by cross-validation.

First, we justify that the residual function is indeed in H^s. Since we assume that g is bandlimited, $g \in H^s$ for all $s \in \mathbb{R}$. Proposition 2 shows that we could consider $s < 3/2$ for ReLU-based NN.

Proposition 2. Suppose $\mathcal{N} : \mathbb{S}^{d-1} \to \mathbb{R}$ is a 2-layer ReLU NN (see eq. (5)). Then, we have $\mathcal{N} \in H^s(\mathbb{S}^{d-1})$ for all $s < 3/2$. Moreover, if $s \geq 3/2$, $\mathcal{N} \in H^s(\mathbb{S}^{d-1})$ if and only if $\mathcal{N}$ is affine.

The proof is deferred to the supplementary material. When $s \geq 3/2$, the residual function $\mathcal{N} - g$ may not be in H^s. However, we can still use the truncated sum to a maximum frequency $\ell_{\max}$ to train the NN, although the sum can no longer be interpreted as an approximation of some Sobolev norm at the continuous level. We discretize the Sobolev-based loss function as

$$\Phi_s(\mathbf{W}) = \frac{1}{2} \sum_{\ell=0}^{\ell_{\max}} \sum_{p=1}^{N(d,\ell)} (1+\ell)^{2s} \left(\sum_{i=1}^{n} c_i Y_{\ell,p}(\mathbf{x}_i)(g-\mathcal{N})(\mathbf{x}_i)\right)^2 = \frac{1}{2}(\mathbf{y}-\mathbf{u})^\top \mathbf{P}_s(\mathbf{y}-\mathbf{u}), \quad (18)$$

where $\mathbf{u}$ and $\mathbf{y}$ follow eq. (6), and $\mathbf{P}_s = \sum_{\ell=0}^{\ell_{\max}} \sum_{p=1}^{N(d,\ell)} (1+\ell)^{2s} \mathbf{P}_{\ell,p}$, $\mathbf{P}_{\ell,p} = \mathbf{a}_{\ell,p} \mathbf{a}_{\ell,p}^\top$, and $(\mathbf{a}_{\ell,p})_i = c_i Y_{\ell,p}(\mathbf{x}_i)$. We assume that $\mathbf{P}_s$ is positive definite, which requires that $(\ell_{\max}+1)^2 \geq n$. Next, we present our convergence theorem for Sobolev training.

Theorem 4. Suppose $g \in \Pi_L^d$ and Φ_s is the loss function in eq. equation 18, where $\mathbf{P}_s$ is positive definite and $\ell_{\max} \geq L$. Under the assumptions of Theorem 1, if $1 - 2\eta\mu_\ell(1+\ell)^{2s} > 0$ for all $0 \leq \ell \leq L$, then with probability $\geq 1 - \delta$ over the random initialization, we have

$$\mathbf{y} - \mathbf{u}(k) = \sum_{\ell=0}^{L} \left(1 - 2\eta\mu_\ell(1+\ell)^{2s}\right)^k \mathbf{y}^\ell + \boldsymbol{\varepsilon}_1 + \boldsymbol{\varepsilon}_2(k), \qquad \|\boldsymbol{\varepsilon}_2(k)\|_{\mathbf{P}_s} \leq \epsilon, \qquad 0 \leq k \leq T,$$

where $\mathbf{y}^\ell = (g_\ell(\mathbf{x}_1), \ldots, g_\ell(\mathbf{x}_n))^\top$ and $\boldsymbol{\varepsilon}_1$ satisfies

$$\|\boldsymbol{\varepsilon}_1\|_{\mathbf{P}_s} \leq \sum_{\ell=0}^{L} \mu_\ell^{-1} \|\boldsymbol{\varepsilon}_1^\ell\|_{\mathbf{P}_s}, \quad (\varepsilon_1^\ell)_i = e_{i,\ell}^d + \sum_{j=0}^{\ell_{\max}} \frac{(1+j)^{2s}}{(1+\ell)^{2s}} \sum_{p=1}^{N(d,j)} e_{\ell,j,p}^a \left(\mu_j Y_{j,p}(\mathbf{x}_i) + e_{i,j,p}^b\right).$$

Compared to Theorem 2, Theorem 4 says that up to the level of quadrature errors, the convergence rate of the degree-ℓ component is $1 - 2\eta\mu_\ell(1+\ell)^{2s}$. In particular, since $\mu_\ell = \mathcal{O}(\ell^{-d})$, there is an $s^* > 0$, which depends on d, such that $(1+\ell)^{2s^*}\mu_\ell$ can be bounded from above and below by positive constant that are independent of ℓ for all $\ell \geq 0$. This means for any $s > s^*$, we expect to reverse the frequency biasing behavior of NN training. Figure 2 shows the reversal of frequency biasing as s increases from -1 to 4 (see section 6.1).

Figure 1: Left: the nonuniform data $\mathbf{x} = (\cos\theta, \sin\theta)$ on the unit circle ($\mathbb{S}^1$). Middle: the change of frequency loss for $\ell = 1$ (blue), 5 (red) and 9 (yellow) against the number of iterations for loss function Φ (solid lines) and $\widetilde{\Phi}$ (dash lines). Right: the number of iterations for the NN training to achieve a fixed loss threshold in learning $g_\ell(\mathbf{x}) = \sin(\ell\theta)$ for $3 \leq \ell \leq 10$ given the loss function $\widetilde{\Phi}$ while the black line represents the $\mathcal{O}(\ell^2)$ rate based on the analysis in (Basri et al., 2019).

Figure 2: Frequency-biasing during NN training with a squared H^s loss function. The blue-to-red rainbow corresponds to low-to-high frequency losses $|\widehat{\mathcal{N}}(\ell) - \hat{g}(\ell)|$ for the frequency index ℓ ranging from 1 (blue) to 9 (red) with nonuniform training data, respectively. Here, an overparameterized 2-layer ReLU NN $\mathcal{N}(\mathbf{x})$ is trained for 5000 epochs to learn function $g(\mathbf{x}) = \tilde{g}(\theta) = \sum_{\ell=1}^{9} \sin(\ell\theta)$ on $\mathbb{S}^1$ given the H^s loss with $-1 \leq s \leq 4$. The inversion of the rainbow as s increases demonstrates the reversal of the frequency biasing phenomenon with the squared Sobolev H^s loss.

6 EXPERIMENTS AND DISCUSSION

This section presents three experiments with synthetic and real-world datasets to investigate the frequency biasing of NN training using squared L^2 loss and squared H^s loss. The first two experiments learn functions on $\mathbb{S}^1$ and $\mathbb{S}^2$, respectively. In the third test, we train an autoencoder on the MNIST dataset for a denoising task. One can find more details in the supplementary material.

6.1 LEARNING TRIGONOMETRIC POLYNOMIALS ON THE UNIT CIRCLE

First, we consider learning a function on $\mathbb{S}^1$. We create a set of $n = 1140$ nonuniform data $\{\mathbf{x}_i\}_{i=1}^{n}$, as seen in Figure 1, and compute the quadrature weights $\{c_i\}_{i=1}^{n}$ for the loss function $\widetilde{\Phi}$ in eq. (3). We train a 2-layer ReLU NN to learn $g(\mathbf{x}) = \tilde{g}(\theta) = \sum_{\ell=1}^{9} \sin(\ell\theta)$, where $\mathbf{x} = (\cos\theta, \sin\theta)$. We define the frequency loss $|\widehat{\mathcal{N}}(\ell) - \hat{g}(\ell)|$ where $\widehat{\mathcal{N}}$ and $\hat{g}$ are the Fourier coefficients of $\mathcal{N}$ and g, respectively. In Figure 1, we plot the frequency loss for $\ell = 1, 5, 9$ in different colors to illustrate how well the NN fits each frequency component. The solid and dash lines correspond to the loss function Φ in eq. (1) and $\widetilde{\Phi}$ in eq. (3), respectively. The comparisons show that the frequency biasing is more evident given the loss function $\widetilde{\Phi}$. This observation collaborates the theoretical statements in Theorem 2. There is no guarantee that frequency biasing always exists when using Φ as the loss function for nonuniform data training, which is also observed here. Moreover, Figure 1 also shows that it takes asymptotically $\mathcal{O}(\ell^2)$ iterations to learn the ℓth frequency $\sin(\ell\theta)$ given the loss function $\widetilde{\Phi}$. A similar plot appears in Basri et al. (2019) for uniform data training.

We also use the squared H^s norm as the loss function to learn g. After 5000 epochs, we plot the ℓth frequency loss with ℓ ranging from 1 (blue) to 9 (red) in Figure 2, given different s values. As s

Figure 3: Frequency losses for $\ell = 4$ (blue), 10 (red), and 20 (yellow), when learning a function on $\mathbb{S}^2$ using different squared H^s loss function. Compared to low-frequency biasing in the cases of $s = -1$ (left) and $s = 0$ (middle), we observe a high-frequency biasing when $s = 2.5$ (right).

| (a) blurred image | (b) $s = -1.0$ | (c) $s = 0.0$ | (d) $s = 1.0$ |
| (e) blurred image | (f) $s = -1.0$ | (g) $s = 0.0$ | (h) $s = 1.0$ |

Figure 4: The output of a squared H^s loss-trained autoencoder on a typical test image when the input images are contaminated by low-frequency noise (top row) and high-frequency noise (bottom row).

increases, the higher-frequency components are learned faster. When $s > 2$, the frequency biasing is entirely reversed in the sense that higher-frequency parts are learned faster than the lower-frequency ones rather than a low-frequency biasing under the squared L^2 loss (see Theorem 2). The gradually changing "rainbow" in Figure 2 demonstrates that the smoothing property of an overparameterized NN can be compensated by the intrinsic high-frequency biasing of the H^s loss function for a large enough s, corroborating Theorem 4.

6.2 LEARNING SPHERICAL HARMONICS ON THE UNIT SPHERE

Similar to the previous example in $\mathbb{S}^1$, we design an experiment on $\mathbb{S}^2$. We utilize a data set $\{\mathbf{x}_i\}_{i=1}^n$ in (Wright & Michaels, 2015) where $n = 2500$, which comes with carefully designed positive quadrature weights $\{c_i\}_{i=1}^n$. We test the squared H^s norm as the loss function in NN training with training data coming from a function $g(\mathbf{x}) = \sum_{\ell=0, \ell \text{ even}}^{30} Y_{\ell,0}$ defined on $\mathbb{S}^2$ that involves more high-frequency components than the $\mathbb{S}^1$ example. The training results are shown in Figure 3 with different s values. The natural low-frequency biasing of NN in the case of L^2-based training (the case of $s = 0$) is enhanced when $s = -1$, and is totally reversed when $s = 2.5$.

6.3 AUTOENCODER ON THE MNIST DATASET

The idea of Sobolev training is also useful for high-dimensional training data. Here, we present the results of the autoencoder for image denoising using the MNIST dataset LeCun et al. (2010). In Figure 4, the outputs of the autoencoder are presented when trained with the squared H^s norm as the loss function. We contaminate the dataset with random low-frequency noise (top row) and high-frequency noise (bottom row). When high-frequency noise is present, the H^s loss function generally performs better with $s < 0$, while the case of $s > 0$ helps image deblurring when the input image suffers from low-frequency noise. This corroborates our discussion in Section 5.

REFERENCES

S. Arora, S. S. Du, W. Hu, Z. Li, and R. Wang. Fine-grained analysis of optimization and generalization for overparameterized two-layer neural networks. In *Inter. Conf. Mach. Learn.*, pp. 322–332. PMLR, 2019.

A.P. Austin and L.N. Trefethen. Trigonometric interpolation and quadrature in perturbed points. *SIAM Journal on Numerical Analysis*, 55(5):2113–2122, 2017. doi: 10.1137/16M1107760.

F. R. Bach and M. I. Jordan. Kernel independent component analysis. *J. Mach. Learn. Res.*, 3(Jul): 1–48, 2002.

C. T. H. Baker. *The numerical treatment of integral equations*. Oxford University Press, 1977.

J. A. Barceló, T. Luque, and S. Pérez-Esteva. Characterization of Sobolev spaces on the sphere. *J. Math. Anal. Appl.*, 491(1):124240, 2020.

JA Barceló, M Folch-Gabayet, T Luque, S Pérez-Esteva, and MC Vilela. The Fourier extension operator of distributions in Sobolev spaces of the sphere and the Helmholtz equation. *Proceedings of the Royal Society of Edinburgh Section A: Mathematics*, 151(6):1768–1789, 2021.

R. Basri, D. Jacobs, Y. Kasten, and S. Kritchman. The convergence rate of neural networks for learned functions of different frequencies. *Adv. Neur. Info. Proc. Syst.*, 32, 2019.

R. Basri, M. Galun, A. Geifman, D. Jacobs, Y. Kasten, and S. Kritchman. Frequency bias in neural networks for input of non-uniform density. In *Inter. Conf. Mach. Learn.*, pp. 685–694. PMLR, 2020.

M. Belkin, D. Hsu, S. Ma, and S. Mandal. Reconciling modern machine-learning practice and the classical bias–variance trade-off. *Proc. Nat. Acad. Sci.*, 116(32):15849–15854, 2019.

A. Bietti and J. Mairal. On the inductive bias of neural tangent kernels. *Adv. Neur. Info. Proc. Syst.*, 32, 2019.

Y. Cao, Z. Fang, Y. Wu, D.-X. Zhou, and Q. Gu. Towards understanding the spectral bias of deep learning. *arXiv preprint arXiv:1912.01198*, 2019.

F Chollet. Building autoencoders in keras. `https://blog.keras.io/building-autoencoders-in-keras.html`, 2016.

F. Dai and Y. Xu. *Approximation theory and harmonic analysis on spheres and balls*, volume 23. Springer, 2013.

DLMF. *NIST Digital Library of Mathematical Functions*. http://dlmf.nist.gov/, Release 1.1.6 of 2022-06-30. URL `http://dlmf.nist.gov/`. F. W. J. Olver, A. B. Olde Daalhuis, D. W. Lozier, B. I. Schneider, R. F. Boisvert, C. W. Clark, B. R. Miller, B. V. Saunders, H. S. Cohl, and M. A. McClain, eds.

S. S. Du, X. Zhai, B. Poczos, and A. Singh. Gradient descent provably optimizes over-parameterized neural networks. *Inter. Confer. Learn. Rep.*, 2018.

B. Engquist, K. Ren, and Y. Yang. The quadratic Wasserstein metric for inverse data matching. *Inverse Problems*, 36(5):055001, 2020.

S. Fridovich-Keil, R. Gontijo-Lopes, and R. Roelofs. Spectral bias in practice: The role of function frequency in generalization. *arXiv preprint arXiv:2110.02424*, 2021.

W. Hoeffding. Probability inequalities for sums of bounded random variables. *J. Amer. Stat. Assoc.*, 58:13–30, 1963.

A. Jacot, F. Gabriel, and C. Hongler. Neural tangent kernel: Convergence and generalization in neural networks. *Adv. Neur. Info. Proc. Syst.*, 31, 2018.

]kurbiel T. Kurbiel. Derivative of the softmax function and the categorical cross-entropy loss. Towards Data Science, 2021 [Online]. URL `https://towardsdatascience.com/derivative-of-the-softmax-function-and-the-categorical-cross-entropy-loss-ffceefc081d1`.

Y. LeCun, C. Cortes, and C. J. Burges. MNIST handwritten digit database. *ATT Labs [Online]. Available: http://yann.lecun.com/exdb/mnist*, 2, 2010.

S. Li. Concise formulas for the area and volume of a hyperspherical cap. *Asian J. Math. Stat.*, 4: 66–70, 2011.

H. N. Mhaskar, F. J. Narcowich, and J. D. Ward. Spherical Marcinkiewicz–Zygmund inequalities and positive quadrature. *Math. Comp.*, 70(235):1113–1130, 2000.

E. Parzen. On Estimation of a Probability Density Function and Mode. *The Annals of Mathematical Statistics*, 33(3):1065 – 1076, 1962. doi: 10.1214/aoms/1177704472. URL `https://doi.org/10.1214/aoms/1177704472`.

N. Rahaman, A. Baratin, D. Arpit, F. Draxler, M. Lin, F. Hamprecht, Y. Bengio, and A. Courville. On the spectral bias of neural networks. In *Inter. Conf. Mach. Learn.*, pp. 5301–5310. PMLR, 2019.

M. Rosenblatt. Remarks on Some Nonparametric Estimates of a Density Function. *The Annals of Mathematical Statistics*, 27(3):832 – 837, 1956. doi: 10.1214/aoms/1177728190. URL `https://doi.org/10.1214/aoms/1177728190`.

M. Scetbon and Z. Harchaoui. A spectral analysis of dot-product kernels. In *Inter. Conf. Art. Intell. and Stat.*, pp. 3394–3402. PMLR, 2021.

R. T. Seeley. Spherical harmonics. *Amer. Math. Mon.*, 73(4P2):115–121, 1966.

L. Su and P. Yang. On learning over-parameterized neural networks: A functional approximation perspective. In H. Wallach, H. Larochelle, A. Beygelzimer, F. d'Alché-Buc, E. Fox, and R. Garnett (eds.), *Adv. Neur. Info. Proc. Syst.*, volume 32. Curran Associates, Inc., 2019.

H. Widom. Asymptotic behavior of the eigenvalues of certain integral equations. *Trans. Amer. Math. Soc.*, 109(2):278–295, 1963.

H. Widom. Asymptotic behavior of the eigenvalues of certain integral equations. II. *Arch. Rat. Mech. Anal.*, 17(3):215–229, 1964.

C. K. Williams and C. E. Rasmussen. *Gaussian processes for machine learning*. MIT press Cambridge, MA, 2006.

G. Wright and T. Michaels. Spherepts. `https://github.com/gradywright/spherepts`, 2015.

Z.-Q. J. Xu. Frequency principle: Fourier analysis sheds light on deep neural networks. *Commun. Comput. Phys.*, 28(5):1746–1767, 2020.

G. Yang and H. Salman. A fine-grained spectral perspective on neural networks. *arXiv preprint arXiv:1907.10599*, 2019.

Annan Yu and Alex Townsend. On the stability of unevenly spaced samples for interpolation and quadrature. *arXiv preprint arXiv:2202.04722*, 2022.

B. Zhu, J. Hu, Y. Lou, and Y. Yang. Implicit regularization effects of the Sobolev norms in image processing. *arXiv preprint arXiv:2109.06255*, 2021.

SUPPLEMENTARY MATERIAL

This is the supplementary material for the paper titled "Tuning Frequency Bias in Neural Network Training with Nonuniform Data."

The supplementary material is organized as follows. In Appendix A, we recall the notations used in the paper and introduce additional concepts for our analysis. In Appendix B, we prove that $\mathbf{H}^\infty$ is a symmetric and positive definite matrix. In Appendix C, we prove Theorem 1 of the paper, while the proofs of results in Section 4 and Section 5 are given in Appendix D and Appendix E, respectively. In Appendix F, we provide the further details of our three experiments. In Appendix G, we briefly discuss the computation of positive quadrature weights.

A PRELIMINARIES AND NOTATION

For $d > 1$, let $g : \mathbb{S}^{d-1} \to \mathbb{R}$ be a square-integrable function defined on $\mathbb{S}^{d-1}$. The function g has a spherical harmonic expansion given in Section 2. We denote the space of harmonic functions of degree ℓ as $\mathcal{H}_\ell^d$, which is the span of $\{Y_{\ell,p}\}_{p=1}^{N(d,\ell)}$. We further denote the space of spherical harmonics of degree $\leq \ell$ as $\Pi_\ell^d = \bigoplus_{j=0}^\ell \mathcal{H}_j^d$.

Given distinct training data $\{\mathbf{x}_i\}_{i=1}^n$ from $\mathbb{S}^{d-1}$ and evaluations $y_i = g(\mathbf{x}_i)$ for $1 \leq i \leq n$, our goal is to understand the intrinsic frequency-biasing behavior of training a 2-layer ReLU NN given in eq. (5). It is important for the theory that we initialize the weights as independently and identically distributed (iid) Gaussian random variables with a covariance matrix $\kappa^2 \mathbf{I}$, the bias terms are initialized to zero, and the coefficients, i.e., $a_1, \ldots, a_m$, are initialized iid as $+1$ with probability $1/2$ and -1 otherwise. During the training process, the values of $\{a_r\}$ are not updated.

We train with the loss function given in eq. (6) so that the gradient descent algorithm for NN training is given by eq. (7). An important object in understanding the frequency biasing of NN training is the symmetric and positive definite matrix $\mathbf{H}^\infty \in \mathbb{R}^{n \times n}$ in eq. (9). Since $\mathbf{H}^\infty$ are symmetric positive definite matrices (see Proposition 1), $\mathbf{H}^\infty \mathbf{P}$ has positive real eigenvalues. To see this, note that $\mathbf{H}^\infty \mathbf{P} = \mathbf{H}^\infty \mathbf{P}^{1/2} \mathbf{P}^{1/2} = \mathbf{P}^{-1/2} (\mathbf{P}^{1/2} \mathbf{H}^\infty \mathbf{P}^{1/2}) \mathbf{P}^{1/2}$. This means that $\mathbf{H}^\infty \mathbf{P}$ and $\mathbf{P}^{1/2} \mathbf{H}^\infty \mathbf{P}^{1/2}$ are similar. Since the matrix $\mathbf{P}^{1/2} \mathbf{H}^\infty \mathbf{P}^{1/2}$ is symmetric positive definite, $\mathbf{H}^\infty \mathbf{P}$ has positive eigenvalues. We denote the eigenvalues of $\mathbf{H}^\infty \mathbf{P}$ by $\lambda_{n-1} \geq \cdots \geq \lambda_0 > 0$, which partially govern the frequency biasing phenomena.

It is convenient to analyze the eigenvalues and eigenvectors of $\mathbf{H}^\infty \mathbf{P}$ via the zonal kernel $K^\infty : \mathbb{S}^{d-1} \times \mathbb{S}^{d-1} \to \mathbb{R}$ given in eq. (10). The key is the Funk–Hecke formula (Seeley, 1966).

Theorem 5 (Funk–Hecke). Suppose $K : [-1, 1] \to \mathbb{R}$ is measurable and $K(t)(1 - t^2)^{(d-3)/2}$ is integrable on $[-1, 1]$. Then, for any $h \in \mathcal{H}_\ell^d$, we have

$$\int_{\mathbb{S}^{d-1}} K(\langle \boldsymbol{\xi}, \boldsymbol{\zeta} \rangle) h(\boldsymbol{\xi}) d\boldsymbol{\xi} = \left(A_d \int_{-1}^1 K(t) P_{\ell,d}(t)(1 - t^2)^{(d-3)/2} dt \right) h(\boldsymbol{\zeta}), \qquad \boldsymbol{\zeta} \in \mathbb{S}^{d-1}, \quad (19)$$

where $P_{\ell,d}$ is the ultraspherical polynomial given by

$$P_{\ell,d}(t) = \frac{(-1)^\ell \Gamma((d-1)/2)}{2^\ell \Gamma(\ell + (d-1)/2)(1 - t^2)^{(d-3)/2}} \frac{d^\ell}{dt^\ell} (1 - t^2)^{\ell + (d-3)/2}. \qquad (20)$$

Applying Theorem 5, we have that

$$\int_{\mathbb{S}^{d-1}} K^\infty(\mathbf{x}, \mathbf{y}) h(\mathbf{y}) d\sigma(\mathbf{y}) = \mu_\ell h(\mathbf{x}), \qquad h \in \mathcal{H}_\ell^d,$$

where $\mu_\ell > 0$, $\forall \ell$, given by (Basri et al., 2019)

$$\mu_\ell = \begin{cases} \frac{1}{2} C_1^d(0) \left(\frac{1}{(d-1)2^d} \binom{d-1}{\frac{d-1}{2}} + \frac{2^{d-2}}{(d-1)\binom{d-2}{\frac{d-1}{2}}} - \frac{1}{2} \sum_{p=0}^{\frac{d-3}{2}} (-1)^p \binom{\frac{d-3}{2}}{p} \frac{1}{2p+1} \right), & \ell = 0, \\[2mm] \frac{1}{2} C_1^d(1) \sum_{p=\lceil \frac{\ell}{2} \rceil}^{\ell + \frac{d-3}{2}} C_2^d(p,1) \left(\frac{1}{2(2p+1)} + \frac{1}{4p} \left(1 - \frac{1}{2^{2p}} \binom{2p}{p} \right) \right), & \ell = 1, \\[2mm] \frac{1}{2} C_1^d(\ell) \sum_{p=\lceil \frac{\ell}{2} \rceil}^{\ell + \frac{d-3}{2}} C_2^d(p,\ell) \left(\frac{-1}{2(2p-\ell+1)} + \frac{1}{2(2p-\ell+2)} \left(1 - \frac{1}{2^{2p-\ell+2}} \binom{2p-\ell+2}{\frac{2p-\ell+2}{2}} \right) \right), & \ell \geq 2 \text{ even}, \\[2mm] \frac{1}{2} C_1^d(\ell) \sum_{p=\lceil \frac{\ell}{2} \rceil}^{\ell + \frac{d-3}{2}} C_2^d(p,\ell) \left(\frac{1}{2(2p-\ell+1)} \left(1 - \frac{1}{2^{2p-\ell+1}} \binom{2p-\ell+1}{\frac{2p-\ell+1}{2}} \right) \right), & \ell \geq 2 \text{ odd} \end{cases}$$

for $d \geq 3$, d odd, where

$$C_1^d(\ell) = \frac{(-1)^\ell 2\pi^{(d-1)/2}}{(d-1)2^\ell \Gamma(\ell + (d-1)/2)}, \qquad C_2^d(p, \ell) = (-1)^p \binom{\ell + \frac{d-3}{2}}{p} \frac{(2p)!}{(2p - \ell)!}.$$

Here, the exclamation mark means a factorial and $\binom{\cdot}{\cdot}$ denotes the binomial coefficient.

Given $\mathbf{x}$, $\mathbf{w}_r$, and b_r in eq. (5), we write $\tilde{\mathbf{x}} = \frac{1}{\sqrt{2}}(\mathbf{x}, 1) \in \mathbb{S}^d$ and $\tilde{\mathbf{w}}_r = (\mathbf{w}_r, b_r) \in \mathbb{R}^{d+1}$. Therefore, we have $\mathrm{ReLU}(\mathbf{w}_r^\top \mathbf{x} + b_r) = \sqrt{2}\mathrm{ReLU}(\tilde{\mathbf{w}}_r^\top \tilde{\mathbf{x}})$ and the NN function can be rewritten as

$$\mathcal{N}(\mathbf{x}) = \frac{\sqrt{2}}{\sqrt{m}} \sum_{r=1}^m a_r \mathrm{ReLU}(\tilde{\mathbf{w}}_r^\top \tilde{\mathbf{x}}).$$

By replacing the expectation over random initialization of $\tilde{\mathbf{w}}$ by $\tilde{\mathbf{w}}(t)$, we define the instantiations of $\mathbf{H}^\infty$ at the kth iteration by $\mathbf{H}(k)$, where

$$H_{ij}(k) = \frac{1}{m} \tilde{\mathbf{x}}_i^\top \tilde{\mathbf{x}}_j \sum_{r=1}^m \mathbb{1}_{\{\tilde{\mathbf{x}}_i^\top \tilde{\mathbf{w}}_r(k) \geq 0, \tilde{\mathbf{x}}_j^\top \tilde{\mathbf{w}}_r(k) \geq 0\}}, \tag{21}$$

where $\mathbb{1}$ is an indicator function.

B THE MATRIX $\mathbf{H}^\infty$ IS SYMMETRIC AND POSITIVE DEFINITE

Proposition 1 states that the matrix $\mathbf{H}^\infty$ defined by eq. (9) is symmetric and positive definite. While the symmetry of $\mathbf{H}^\infty$ is immediate from its closed-form expression, the fact that it is positive definite requires a more detailed analysis. The proof idea is similar to that of Theorem 3.1 of (Du et al., 2018), in which the matrix $\mathbf{H}^\infty$ is associated with a 2-layer ReLU NN without biases. However, our $\mathbf{H}^\infty$ is associated with a 2-layer ReLU NN with biases. While (Du et al., 2018) requires no two training data points are parallel, we allow the existence of $\mathbf{x}_{i_1} = -\mathbf{x}_{i_2}$ for some i_1 and i_2. Hence, our proof employs on a pair of nodes denoted by $\mathbf{x}_{i_1}, \mathbf{x}_{i_2}$.

Proof of Proposition 1. For a measurable function $f : \mathbb{R}^d \to \mathbb{R}^{d+1}$, we define a norm of f as

$$\|f\|_{\mathcal{H}}^2 = \mathbb{E}_{\mathbf{w} \sim \mathcal{N}(\mathbf{0}, \kappa^2 \mathbf{I})} \|f(\mathbf{w})\|_2^2,$$

and let $\mathcal{H}$ be the space of measurable functions such that $\|f\|_{\mathcal{H}} < \infty$. It can be shown that $\mathcal{H}$ is a Hilbert space with respect to the inner product $\langle f, g \rangle_{\mathcal{H}} = \mathbb{E}_{\mathbf{w} \sim \mathcal{N}(\mathbf{0}, \kappa^2 \mathbf{I})} [f(\mathbf{w})^\top g(\mathbf{w})]$. For each $\mathbf{x}_i$, $1 \leq i \leq n$, we define the function ϕ_i by

$$\phi_i(\mathbf{w}) = \tilde{\mathbf{x}}_i \mathbb{1}_{\{\mathbf{w}^\top \mathbf{x}_i \geq 0\}}, \qquad \mathbf{w} \in \mathbb{R}^d.$$

Then, $\phi_i \in \mathcal{H}$ for all i, and $H_{ij}^\infty = \langle \phi_i, \phi_j \rangle_{\mathcal{H}}$. We prove that $\mathbf{H}^\infty$ is positive definite by showing that $\{\phi_i\}_{i=1}^n$ is a linearly independent set in $\mathcal{H}$.

To show $\{\phi_i\}_{i=1}^n$ is a linearly independent set, we show that

$$\alpha_1 \phi_1(\mathbf{w}) + \cdots + \alpha_n \phi_n(\mathbf{w}) = \mathbf{0} \qquad \text{for almost every } \mathbf{w} \in \mathbb{R}^d \tag{22}$$

implies that $\alpha_i = 0$ for $1 \leq i \leq n$. We fix some $1 \leq i_1 \leq n$ and, without loss of generality, assume that $\mathbf{x}_{i_2} = -\mathbf{x}_{i_1}$.[2] Define the set $D_j = \{\mathbf{w} \in \mathbb{R}^d \mid \mathbf{w}^\top \mathbf{x}_j = 0\}$ for $1 \leq j \leq n$. As a result, $D_{i_1} = D_{i_2}$. Since each D_j is a hyperplane passing through the origin and $D_{i_1} \neq D_j$ for any $j \neq i_1, i_2$, $\exists \mathbf{z} \in D_{i_1}$ such that $\mathbf{z} \notin D_j$ for any $j \neq i_1, i_2$. For a positive radius $R > 0$, let $B_R = B(\mathbf{z}, R)$ be the ball centered at $\mathbf{z}$ of radius R. Define a partition of B_R into two sets denoted by B_R^+ and B_R^- (possibly missing a subset of B_R that has zero Lebesgue measure), where

$$B_R^+ = \{\mathbf{w} \in B_R \mid \mathbf{w}^\top \mathbf{x}_{i_1} > 0\} = \{\mathbf{w} \in B_R \mid \mathbf{w}^\top \mathbf{x}_{i_2} < 0\},$$
$$B_R^- = \{\mathbf{w} \in B_R \mid \mathbf{w}^\top \mathbf{x}_{i_1} < 0\} = \{\mathbf{w} \in B_R \mid \mathbf{w}^\top \mathbf{x}_{i_2} > 0\}.$$

---

[2]Otherwise, if such i_2 does not exist, we can add an element ϕ_{n+1} associated with $-\mathbf{x}_{i_1}$ to $\{\phi_i\}_{i=1}^n$. If we can show $\{\phi_i\}_{i=1}^{n+1}$ is linearly independent, then so is $\{\phi_i\}_{i=1}^n$.

Since D_j is closed for each $1 \le j \le n$, B_R is eventually disjoint from D_j as $R \to 0$. Hence, we have

$$\lim_{R \to 0} \sup_{\mathbf{w} \in B_R} |\phi_j(\mathbf{z}) - \phi_j(\mathbf{w})| = 0, \qquad j \ne i_1, i_2,$$

where $|\cdot|$ denotes the Euclidean distance. Then, for any $j \ne i_1, i_2$, we have

$$\lim_{R \to 0} \frac{1}{|B_R^+|} \int_{B_R^+} \phi_j(\mathbf{w}) d\mathbf{w} = \phi_j(\mathbf{z}), \quad \lim_{R \to 0} \frac{1}{|B_R^-|} \int_{B_R^-} \phi_j(\mathbf{w}) d\mathbf{w} = \phi_j(\mathbf{z}).$$

Consequently, we find that

$$\lim_{R \to 0} \left(\frac{1}{|B_R^+|} \int_{B_R^+} \phi_j(\mathbf{w}) d\mathbf{w} - \frac{1}{|B_R^-|} \int_{B_R^-} \phi_j(\mathbf{w}) d\mathbf{w} \right) = \mathbf{0}, \qquad j \ne i_1, i_2.$$

Now, consider the integral of ϕ_{i_1} and ϕ_{i_2}. We have

$$\lim_{R \to 0} \left(\frac{1}{|B_R^+|} \int_{B_R^+} \phi_{i_1}(\mathbf{w}) d\mathbf{w} - \frac{1}{|B_R^-|} \int_{B_R^-} \phi_{i_1}(\mathbf{w}) d\mathbf{w} \right) = \lim_{R \to 0} \left(\frac{1}{|B_R^+|} \int_{B_R^+} \tilde{\mathbf{x}}_{i_1} d\mathbf{w} - \frac{1}{|B_R^-|} \int_{B_R^-} \mathbf{0} d\mathbf{w} \right) = \tilde{\mathbf{x}}_{i_1},$$

$$\lim_{R \to 0} \left(\frac{1}{|B_R^+|} \int_{B_R^+} \phi_{i_2}(\mathbf{w}) d\mathbf{w} - \frac{1}{|B_R^-|} \int_{B_R^-} \phi_{i_2}(\mathbf{w}) d\mathbf{w} \right) = \lim_{R \to 0} \left(\frac{1}{|B_R^+|} \int_{B_R^+} \mathbf{0} d\mathbf{w} - \frac{1}{|B_R^-|} \int_{B_R^-} \tilde{\mathbf{x}}_{i_2} d\mathbf{w} \right) = -\tilde{\mathbf{x}}_{i_2}.$$

By applying these limiting expressions to $\sum_{j=1}^{n} \alpha_j \phi_j(\mathbf{w}) = \mathbf{0}$, we find that $\alpha_{i_1} \tilde{\mathbf{x}}_{i_1} - \alpha_{i_2} \tilde{\mathbf{x}}_{i_2} = \mathbf{0}$. Since the last entries of both $\tilde{\mathbf{x}}_{i_1}$ and $\tilde{\mathbf{x}}_{i_2}$ are $1/\sqrt{2}$, we have $\alpha_{i_1} = \alpha_{i_2}$. Thus, we have $\alpha_{i_1} = 0$ because $\mathbf{x}_{i_1} \ne \mathbf{0}$. Since i_1 is arbitrary, the statement of the proposition follows. $\quad\square$

It is clear that the proof of Proposition 1 is also true if we assume that each entry of $\mathbf{w}_r$ is initialized from an iid sub-Gaussian distribution with zero mean and whose support is the entire $\mathbb{R}$, and we update the definition of $\mathbf{H}^\infty$ according to eq. (9).

C THE CONVERGENCE OF NEURAL NETWORK TRAINING

In this section, we develop the theory for learning a NN with a general loss function $\Phi_{\mathbf{P}}$ defined by a positive definite matrix $\mathbf{P}$ in eq. (6). In particular, we prove Theorem 1, which states that provided the learning rate is sufficiently small, the weights are initialized without too much variance, and the NN is sufficiently wide, then the residual in the first few epochs can be described with the matrix $\mathbf{H}^\infty \mathbf{P}$.

While our proof is similar to that of (Su & Yang, 2019), the argument is distinct in three essential ways: (1) Our proof applies to any loss function defined by a positive definite matrix $\mathbf{P}$, which requires us to use a different Hilbert space $(\mathbb{R}^n, \langle \cdot, \cdot \rangle_{\mathbf{P}})$. (2) While the result in (Su & Yang, 2019) bounds the residual using the minimum eigenvalue of $\mathbf{H}^\infty$, we estimate the residual as a matrix-vector product of $(\mathbf{I} - 2\eta \mathbf{H}^\infty \mathbf{P})^k \mathbf{y}$, which allows us to analyze the training error using all eigenvalues of $\mathbf{H}^\infty \mathbf{P}$. (3) We use a different NN function that incorporates the bias terms and we do not assume that we initialize the weights in a way that makes $\mathcal{N}_0 = 0$.

Before we prove the theorem, we define some useful quantities. Let $\mathcal{A}$ be the set of indices such that the coefficients a_r are initialized to 1 and let $\mathcal{B}$ be the set initialized to -1. We then decompose $\mathbf{H}(k)$ into two parts, where $\mathbf{H}(k)$ is defined in eq. (21), so that $\mathbf{H}(k) = \mathbf{H}^+(k) + \mathbf{H}^-(k)$ with

$$H_{ij}^+(k) = \frac{1}{m} \tilde{\mathbf{x}}_i^\top \tilde{\mathbf{x}}_j \sum_{r \in \mathcal{A}} \mathbb{1}_{\left\{ \substack{\tilde{\mathbf{w}}_r(k)^\top \tilde{\mathbf{x}}_i \ge 0 \\ \tilde{\mathbf{w}}_r(k)^\top \tilde{\mathbf{x}}_j \ge 0} \right\}}, \qquad H_{ij}^-(k) = \frac{1}{m} \tilde{\mathbf{x}}_i^\top \tilde{\mathbf{x}}_j \sum_{r \in \mathcal{B}} \mathbb{1}_{\left\{ \substack{\tilde{\mathbf{w}}_r(k)^\top \tilde{\mathbf{x}}_i \ge 0 \\ \tilde{\mathbf{w}}_r(k)^\top \tilde{\mathbf{x}}_j \ge 0} \right\}}.$$

Similarly, we define two other matrices $\tilde{\mathbf{H}}^+(k)$ and $\tilde{\mathbf{H}}^-(k)$ as

$$\tilde{H}_{ij}^+(k) = \frac{1}{m} \tilde{\mathbf{x}}_i^\top \tilde{\mathbf{x}}_j \sum_{r \in \mathcal{A}} \mathbb{1}_{\left\{ \substack{\tilde{\mathbf{w}}_r(k+1)^\top \tilde{\mathbf{x}}_i \ge 0 \\ \tilde{\mathbf{w}}_r(k)^\top \tilde{\mathbf{x}}_j \ge 0} \right\}}, \quad \tilde{H}_{ij}^-(k) = \frac{1}{m} \tilde{\mathbf{x}}_i^\top \tilde{\mathbf{x}}_j \sum_{r \in \mathcal{B}} \mathbb{1}_{\left\{ \substack{\tilde{\mathbf{w}}_r(k+1)^\top \tilde{\mathbf{x}}_i \ge 0 \\ \tilde{\mathbf{w}}_r(k)^\top \tilde{\mathbf{x}}_j \ge 0} \right\}}.$$

Unfortunately, $\tilde{\mathbf{H}}^+(k)$ and $\tilde{\mathbf{H}}^-(k)$ are not necessarily symmetric and they differ from $\mathbf{H}^+(k)$ and $\mathbf{H}^-(k)$ up to sign flips. To simplify the notation later, we also define two auxiliary matrices $\mathbf{L}(k)$ and $\mathbf{M}(k)$ as

$$\mathbf{L}(k) = \tilde{\mathbf{H}}^+(k) - \mathbf{H}^+(k), \qquad \mathbf{M}(k) = \tilde{\mathbf{H}}^-(k) - \mathbf{H}^-(k).$$

We now prove that $\mathbf{I} - 2\eta\mathbf{H}(k)\mathbf{P}$ is close to the transition matrix for the residual, up to sign flips, i.e., $\mathbf{y} - \mathbf{u}(k+1) \approx (\mathbf{I} - 2\eta\mathbf{H}(k)\mathbf{P})(\mathbf{y} - \mathbf{u}(k))$.

Lemma 1. Let $\mathbf{z}(k) = \mathbf{y} - \mathbf{u}(k)$ be the residual after the kth iteration. For any $k \geq 0$ and $\eta > 0$, we have

$$\left(\mathbf{I} - 2\eta\left(\tilde{\mathbf{H}}^+(k) + \mathbf{H}^-(k)\right)\mathbf{P}\right)\mathbf{z}(k) \leq \mathbf{z}(k+1) \leq \left(\mathbf{I} - 2\eta\left(\mathbf{H}^+(k) + \tilde{\mathbf{H}}^-(k)\right)\mathbf{P}\right)\mathbf{z}(k),$$

where the inequalities are entry-wise.

Proof. First, by the gradient descent update rule, we have

$$\tilde{\mathbf{w}}_r(k+1) - \tilde{\mathbf{w}}_r(k) = -\eta\frac{\partial\Phi_\mathbf{P}(\tilde{\mathbf{w}}_1(k),\ldots,\tilde{\mathbf{w}}_m(k))}{\partial\tilde{\mathbf{w}}_r} = -\eta\frac{\partial\mathbf{u}(k)}{\partial\tilde{\mathbf{w}}_r}\frac{\partial\Phi_\mathbf{P}(\mathbf{u})}{\partial\mathbf{u}},$$

where the $(d+1) \times n$ Jacobian matrix is given by

$$\frac{\partial\mathbf{u}(k)}{\partial\tilde{\mathbf{w}}_r} = \frac{\sqrt{2}a_r}{\sqrt{m}}\left[\tilde{\mathbf{x}}_1\mathbb{1}_{\{\tilde{\mathbf{x}}_1^\top\tilde{\mathbf{w}}_r(k)\geq0\}} \quad \cdots \quad \tilde{\mathbf{x}}_n\mathbb{1}_{\{\tilde{\mathbf{x}}_n^\top\tilde{\mathbf{w}}_r(k)\geq0\}},\right] \tag{23}$$

and the gradient of the loss function $\Phi_\mathbf{P}$ defined in eq. (6) with respect to $\mathbf{u}$ is given by

$$\frac{\partial\Phi_\mathbf{P}(\mathbf{u})}{\partial\mathbf{u}} = -\mathbf{P}(\mathbf{y} - \mathbf{u}(k)) = -\mathbf{P}\mathbf{z}(k), \tag{24}$$

which is a vector of length n. Hence, it follows that

$$\tilde{\mathbf{w}}_r(k+1)^\top\tilde{\mathbf{x}}_i - \tilde{\mathbf{w}}_r(k)^\top\tilde{\mathbf{x}}_i = \frac{\sqrt{2}\eta a_r}{\sqrt{m}}\sum_{p=1}^n(\mathbf{P}\mathbf{z}(k))_p\,\tilde{\mathbf{x}}_i^\top\tilde{\mathbf{x}}_p\mathbb{1}_{\{\tilde{\mathbf{x}}_p^\top\tilde{\mathbf{w}}_r(k)\geq0\}},$$

where $(\mathbf{P}\mathbf{z}(k))_p$ denotes the pth element of $\mathbf{P}\mathbf{z}(k)$. Using the property of ReLU that

$$(b-a)\mathbb{1}_{\{a>0\}} \leq \mathrm{ReLU}(b) - \mathrm{ReLU}(a) \leq (b-a)\mathbb{1}_{\{b>0\}}, \qquad a,b \in \mathbb{R},$$

we have

$$\mathrm{ReLU}\left(\tilde{\mathbf{w}}_r(k+1)^\top\tilde{\mathbf{x}}_i\right) - \mathrm{ReLU}\left(\tilde{\mathbf{w}}_r(k)^\top\tilde{\mathbf{x}}_i\right)$$
$$\leq \frac{\sqrt{2}\eta a_r}{\sqrt{m}}\sum_{p=1}^n(\mathbf{P}\mathbf{z}(k))_p\,\tilde{\mathbf{x}}_i^\top\tilde{\mathbf{x}}_p\mathbb{1}_{\{\tilde{\mathbf{x}}_p^\top\tilde{\mathbf{w}}_r(k)\geq0\}}\mathbb{1}_{\{\tilde{\mathbf{x}}_i^\top\tilde{\mathbf{w}}_r(k+1)\geq0\}},$$

and

$$\mathrm{ReLU}\left(\tilde{\mathbf{w}}_r(k+1)^\top\tilde{\mathbf{x}}_i\right) - \mathrm{ReLU}\left(\tilde{\mathbf{w}}_r(k)^\top\tilde{\mathbf{x}}_i\right)$$
$$\geq \frac{\sqrt{2}\eta a_r}{\sqrt{m}}\sum_{p=1}^n(\mathbf{P}\mathbf{z}(k))_p\,\tilde{\mathbf{x}}_i^\top\tilde{\mathbf{x}}_p\mathbb{1}_{\{\tilde{\mathbf{x}}_p^\top\tilde{\mathbf{w}}_r(k)\geq0\}}\mathbb{1}_{\{\tilde{\mathbf{x}}_i^\top\tilde{\mathbf{w}}_r(k)\geq0\}}.$$

Hence, we have

$$(\mathbf{u}(k+1))_i - (\mathbf{u}(k))_i = \frac{\sqrt{2}}{\sqrt{m}}\sum_{r\in\mathcal{A}}\left(\mathrm{ReLU}(\tilde{\mathbf{w}}_r(k+1)^\top\tilde{\mathbf{x}}_i) - \mathrm{ReLU}(\tilde{\mathbf{w}}_r(k)^\top\tilde{\mathbf{x}}_i)\right)$$

$$- \frac{\sqrt{2}}{\sqrt{m}}\sum_{r\in\mathcal{B}}\left(\mathrm{ReLU}(\tilde{\mathbf{w}}_r(k+1)^\top\tilde{\mathbf{x}}_i) - \mathrm{ReLU}(\tilde{\mathbf{w}}_r(k)^\top\tilde{\mathbf{x}}_i)\right)$$

$$\leq \frac{2\eta}{m}\sum_{r\in\mathcal{A}}\sum_{p=1}^n(\mathbf{P}\mathbf{z}(k))_p\,\tilde{\mathbf{x}}_i^\top\tilde{\mathbf{x}}_p\mathbb{1}_{\{\tilde{\mathbf{x}}_p^\top\tilde{\mathbf{w}}_r(k)\geq0\}}\mathbb{1}_{\{\tilde{\mathbf{x}}_i^\top\tilde{\mathbf{w}}_r(k+1)\geq0\}}$$

$$+ \frac{2\eta}{m}\sum_{r\in\mathcal{B}}\sum_{p=1}^n(\mathbf{P}\mathbf{z}(k))_p\,\tilde{\mathbf{x}}_i^\top\tilde{\mathbf{x}}_p\mathbb{1}_{\{\tilde{\mathbf{x}}_p^\top\tilde{\mathbf{w}}_r(k)\geq0\}}\mathbb{1}_{\{\tilde{\mathbf{x}}_i^\top\tilde{\mathbf{w}}_r(k)\geq0\}}$$

$$= 2\eta\sum_{p=1}^n\left(\tilde{H}_{ip}^+(k) + H_{ip}^-(k)\right)(\mathbf{P}\mathbf{z}(k))_p.$$

This proves the first inequality. The second inequality can be shown with a similar argument. $\qquad\square$

In particular, if there is no sign flip of the weights, then $\tilde{\mathbf{H}}(k) = \tilde{\mathbf{H}}^+(k) + \tilde{\mathbf{H}}^-(k) = \mathbf{H}(k)$ and the inequalities in Lemma 1 are equalities. Next, using Lemma 1, we can derive an expression for $\mathbf{y} - \mathbf{u}(k)$ using $\mathbf{H}^\infty$, up to an error term.

Lemma 2. For any $0 < \eta < 1/(2M_\mathbf{P}^2 n)$ and any $k \geq 0$, we have that

$$\mathbf{y} - \mathbf{u}(k) = (\mathbf{I} - 2\eta\mathbf{H}^\infty\mathbf{P})^k (\mathbf{y} - \mathbf{u}(0)) + \boldsymbol{\epsilon}(k), \tag{25}$$

where

$$
\begin{aligned}
\|\boldsymbol{\epsilon}(k)\|_\mathbf{P} &\leq 2\eta \sum_{t=0}^{k-1} \|(\mathbf{H}^\infty - \mathbf{H}(t))\mathbf{P}\|_\mathbf{P} \left\| (\mathbf{I} - 2\eta\mathbf{H}^\infty\mathbf{P})^t (\mathbf{y} - \mathbf{u}(0)) \right\|_\mathbf{P} \\
&\quad + 2\eta \sum_{t=0}^{k-1} (\|\mathbf{M}(t)\mathbf{P}\|_\mathbf{P} + \|\mathbf{L}(t)\mathbf{P}\|_\mathbf{P}) \|\mathbf{y} - \mathbf{u}(t)\|_\mathbf{P}.
\end{aligned}
\tag{26}
$$

Proof. For $k \geq 1$, we define $\mathbf{r}(k)$ by

$$\mathbf{r}(k) = \mathbf{y} - \mathbf{u}(k) - (\mathbf{I} - 2\eta\mathbf{H}(k-1)\mathbf{P}) (\mathbf{y} - \mathbf{u}(k-1)). \tag{27}$$

Then, by Lemma 1 we have

$$\|\mathbf{r}(k)\|_\mathbf{P} \leq 2\eta (\|\mathbf{M}(k-1)\mathbf{P}\|_\mathbf{P} + \|\mathbf{L}(k-1)\mathbf{P}\|_\mathbf{P}) \|\mathbf{y} - \mathbf{u}(k-1)\|_\mathbf{P}. \tag{28}$$

Note that eq. (27) is a first-order non-homogeneous recurrence relation for $\mathbf{y} - \mathbf{u}(k)$, which has an analytic solution. Thus, we can expand $\mathbf{y} - \mathbf{u}(k)$ for $k \geq 1$ as

$$
\begin{aligned}
\mathbf{y} - \mathbf{u}(k) &= ((\mathbf{I} - 2\eta\mathbf{H}(k-1)\mathbf{P}) \cdots (\mathbf{I} - 2\eta\mathbf{H}(0)\mathbf{P})) (\mathbf{y} - \mathbf{u}(0)) \\
&\quad + \mathbf{r}(k) + \sum_{t=1}^{k-1} ((\mathbf{I} - 2\eta\mathbf{H}(k-1)\mathbf{P}) \cdots (\mathbf{I} - 2\eta\mathbf{H}(t)\mathbf{P})) \mathbf{r}(t).
\end{aligned}
\tag{29}
$$

Moreover, we can write the product of of the matrices as (Su & Yang, 2019)

$$
\begin{aligned}
&(\mathbf{I} - 2\eta\mathbf{H}(k-1)\mathbf{P}) \cdots (\mathbf{I} - 2\eta\mathbf{H}(0)\mathbf{P}) \\
=&(\mathbf{I} - 2\eta\mathbf{H}^\infty\mathbf{P})^k + 2\eta(\mathbf{H}^\infty\mathbf{P} - \mathbf{H}(k-1)\mathbf{P})(\mathbf{I} - 2\eta\mathbf{H}^\infty\mathbf{P})^{k-1} \\
&+ 2\eta \sum_{t=1}^{k-1} ((\mathbf{I} - 2\eta\mathbf{H}(k-1)\mathbf{P}) \cdots (\mathbf{I} - 2\eta\mathbf{H}(t)\mathbf{P})) (\mathbf{H}^\infty\mathbf{P} - \mathbf{H}(t-1)\mathbf{P})(\mathbf{I} - 2\eta\mathbf{H}^\infty\mathbf{P})^{t-1}.
\end{aligned}
\tag{30}
$$

Combining eq. (29) and eq. (30), we obtain eq. (25) where

$$
\begin{aligned}
\boldsymbol{\epsilon}(k) &= 2\eta(\mathbf{H}^\infty\mathbf{P} - \mathbf{H}(k-1)\mathbf{P})(\mathbf{I} - 2\eta\mathbf{H}^\infty\mathbf{P})^{k-1}(\mathbf{y} - \mathbf{u}(0)) \\
&\quad + 2\eta \sum_{t=1}^{k-1} (\mathbf{I} - 2\eta\mathbf{H}(k-1)\mathbf{P}) \cdots (\mathbf{I} - 2\eta\mathbf{H}(t)\mathbf{P})(\mathbf{H}^\infty - \mathbf{H}(t-1))\mathbf{P}(\mathbf{I} - 2\eta\mathbf{H}^\infty\mathbf{P})^{t-1}(\mathbf{y} - \mathbf{u}(0)) \\
&\quad + \mathbf{r}(k) + \sum_{t=1}^{k-1} (\mathbf{I} - 2\eta\mathbf{H}(k-1)\mathbf{P}) \cdots (\mathbf{I} - 2\eta\mathbf{H}(t)\mathbf{P})\mathbf{r}(t).
\end{aligned}
$$

Finally, we note that

$$
\begin{aligned}
\lambda_{\max}(\mathbf{H}(t)\mathbf{P}) = \lambda_{\max}(\mathbf{P}^{1/2}\mathbf{H}(t)\mathbf{P}^{1/2}) &= \left\| \mathbf{P}^{1/2}\mathbf{H}(t)\mathbf{P}^{1/2} \right\|_2 = \sup_{\boldsymbol{\xi} \in \mathbb{R}^n \setminus \{\mathbf{0}\}} \frac{\left\| \mathbf{P}^{1/2}\mathbf{H}(t)\mathbf{P}^{1/2}\boldsymbol{\xi} \right\|_2}{\|\boldsymbol{\xi}\|_2} \\
&= \sup_{\boldsymbol{\zeta} \in \mathbb{R}^n \setminus \{\mathbf{0}\}} \frac{\left\| \mathbf{P}^{1/2}\mathbf{H}(t)\mathbf{P}\boldsymbol{\zeta} \right\|_2}{\left\| \mathbf{P}^{1/2}\boldsymbol{\zeta} \right\|_2} = \sup_{\boldsymbol{\zeta} \in \mathbb{R}^n \setminus \{\mathbf{0}\}} \frac{\|\mathbf{H}(t)\mathbf{P}\boldsymbol{\zeta}\|_\mathbf{P}}{\|\boldsymbol{\zeta}\|_\mathbf{P}} = \|\mathbf{H}(t)\mathbf{P}\|_\mathbf{P},
\end{aligned}
\tag{31}
$$

and that

$$\|\mathbf{H}(t)\mathbf{P}\|_\mathbf{P} = \sup_{\boldsymbol{\xi} \in \mathbb{R}^n \setminus \{\mathbf{0}\}} \frac{\|\mathbf{H}(t)\mathbf{P}\boldsymbol{\xi}\|_\mathbf{P}}{\|\boldsymbol{\xi}\|_\mathbf{P}} = \sup_{\boldsymbol{\xi} \in \mathbb{R}^n \setminus \{\mathbf{0}\}} \frac{\|\mathbf{H}(t)\mathbf{P}\boldsymbol{\xi}\|_\mathbf{P}}{\|\mathbf{H}(t)\mathbf{P}\boldsymbol{\xi}\|_2} \frac{\|\mathbf{H}(t)\mathbf{P}\boldsymbol{\xi}\|_2}{\|\mathbf{P}\boldsymbol{\xi}\|_2} \frac{\|\mathbf{P}\boldsymbol{\xi}\|_2}{\|\boldsymbol{\xi}\|_\mathbf{P}}. \tag{32}$$

We can then bound $\|\mathbf{H}(t)\mathbf{P}\|_{\mathbf{P}}$ using $M_{\mathbf{P}}$ defined in eq. (8) and $\|\mathbf{H}(t)\|_2$ as

$$\|\mathbf{H}(t)\mathbf{P}\|_{\mathbf{P}} \le M_{\mathbf{P}} \|\mathbf{H}(t)\|_2 M_{\mathbf{P}} \le M_{\mathbf{P}}^2 \sqrt{\|\mathbf{H}(t)\|_1 \|\mathbf{H}(t)\|_\infty} \le M_{\mathbf{P}}^2 n.$$

By requiring that $\eta < 1/(2M_{\mathbf{P}}^2 n)$, we have $\lambda_{\min}(\mathbf{I} - 2\eta\mathbf{H}(t)\mathbf{P}) > 0$ for all t. Hence, $\mathbf{I} - 2\eta\mathbf{H}(t)\mathbf{P}$ is positive definite in $(\mathbb{R}^n, \langle \cdot, \cdot \rangle_{\mathbf{P}})$, and according to eq. (31), we have $\|\mathbf{I} - 2\eta\mathbf{H}(t)\mathbf{P}\|_{\mathbf{P}} = \lambda_{\max}(\mathbf{I} - 2\eta\mathbf{H}(t)\mathbf{P}) < 1$. The upper bound in eq. (26) follows from the triangle inequality and our estimate on $\mathbf{r}_k$ in eq. (28). $\qquad\square$

The residual terms in Lemma 2 can be made small by controlling $\|\mathbf{M}(t)\mathbf{P}\|_{\mathbf{P}} + \|\mathbf{L}(t)\mathbf{P}\|_{\mathbf{P}}$ and $\|(\mathbf{H}(0) - \mathbf{H}(t))\mathbf{P}\|_{\mathbf{P}}$. Their upper bounds are given in Lemma 3. First, we define

$$S_i(t) = \left\{ 1 \le r \le m \mid \mathbb{1}_{\{\tilde{\mathbf{w}}_r(t')^\top \tilde{\mathbf{x}}_i \ge 0\}} \ne \mathbb{1}_{\{\tilde{\mathbf{w}}_r(0)^\top \tilde{\mathbf{x}}_i \ge 0\}} \text{ for some } 0 \le t' \le t \right\}$$

to be the set of indices of the weights that have changed sign at least once by the kth iteration.

Lemma 3. For all $t \ge 0$, we have

$$\max\left(\|\mathbf{M}(t)\mathbf{P}\|_{\mathbf{P}} + \|\mathbf{L}(t)\mathbf{P}\|_{\mathbf{P}}, \|(\mathbf{H}(0) - \mathbf{H}(t))\mathbf{P}\|_{\mathbf{P}} \right) \le \sqrt{\frac{4M_{\mathbf{P}}^4 n}{m^2} \sum_{i=1}^n |S_i(t)|^2},$$

where we Moreover, for any $0 < \delta < 1$, with probability at least $1 - \delta$, we have

$$\|(\mathbf{H}^\infty - \mathbf{H}(0))\mathbf{P}\|_{\mathbf{P}} \le 2M_{\mathbf{P}}^2 n \sqrt{\frac{\log(2n/\delta)}{m}}.$$

Proof. First, we have

$$\|\mathbf{M}(t)\mathbf{P}\|_{\mathbf{P}}^2 \le M_{\mathbf{P}}^4 \|\mathbf{M}(t)\|_2^2 \le M_{\mathbf{P}}^4 \|\mathbf{M}(t)\|_F^2$$

$$\le \frac{M_{\mathbf{P}}^4}{m^2} \sum_{i=1}^n \sum_{p=1}^n \left(\sum_{r \in \mathcal{A}} \left| \mathbb{1}_{\{\tilde{\mathbf{w}}_r(t)^\top \tilde{\mathbf{x}}_i \ge 0, \tilde{\mathbf{w}}_r(t)^\top \tilde{\mathbf{x}}_p \ge 0\}} - \mathbb{1}_{\{\tilde{\mathbf{w}}_r(t+1)^\top \tilde{\mathbf{x}}_i \ge 0, \tilde{\mathbf{w}}_r(t)^\top \tilde{\mathbf{x}}_p \ge 0\}} \right| \right)^2$$

$$\le \frac{M_{\mathbf{P}}^4 n}{m^2} \sum_{i=1}^n |S_i(t)|^2.$$

The estimate for $\|\mathbf{L}(t)\mathbf{P}\|_{\mathbf{P}}^2$ is exactly the same and obtained by replacing $\mathcal{A}$ with $\mathcal{B}$. We also have

$$\|(\mathbf{H}(0) - \mathbf{H}(t))\mathbf{P}\|_{\mathbf{P}}^2 \le M_{\mathbf{P}}^4 \|\mathbf{H}(0) - \mathbf{H}(t)\|_2^2 \le M_{\mathbf{P}}^4 \|\mathbf{H}(0) - \mathbf{H}(t)\|_F^2$$

$$\le \frac{M_{\mathbf{P}}^4}{m^2} \sum_{i=1}^n \sum_{p=1}^n \left(\sum_{r=1}^m \left| \mathbb{1}_{\{\tilde{\mathbf{w}}_r(0)^\top \tilde{\mathbf{x}}_i \ge 0, \tilde{\mathbf{w}}_r(0)^\top \tilde{\mathbf{x}}_p \ge 0\}} - \mathbb{1}_{\{\tilde{\mathbf{w}}_r(t)^\top \tilde{\mathbf{x}}_i \ge 0, \tilde{\mathbf{w}}_r(t)^\top \tilde{\mathbf{x}}_p \ge 0\}} \right| \right)^2$$

$$\le \frac{M_{\mathbf{P}}^4}{m^2} \sum_{i=1}^n \sum_{p=1}^n (|S_i(t)| + |S_p(t)|)^2 \le \frac{M_{\mathbf{P}}^4}{m^2} \sum_{i=1}^n \sum_{p=1}^n \left(2|S_i(t)|^2 + 2|S_p(t)|^2 \right)$$

$$= \frac{4M_{\mathbf{P}}^4 n}{m^2} \sum_{i=1}^n |S_i(t)|^2.$$

This proves the first inequality. Since $H_{ij}(0)$ is the average of m iid random variables bounded in $[0, 1]$, by Hoeffding's inequality (Hoeffding, 1963), for any $t > 0$ and any $1 \le i, j \le n$, we have

$$\mathbb{P}\left(m \left| H_{ij}(0) - H_{ij}^\infty \right| \ge t \right) \le 2\exp\left(-\frac{2t^2}{m} \right) \le 2\exp\left(-\frac{t^2}{m} \right). \tag{33}$$

Set $t = \sqrt{m \log(2n^2/\delta)}$. With probability at least $1 - \delta/n^2$, we have

$$\left| H_{ij}(0) - H_{ij}^\infty \right| \le \sqrt{\frac{\log(2n^2/\delta)}{m}} \le 2\sqrt{\frac{\log(2n/\delta)}{m}}. \tag{34}$$

Hence, by a union bound, we know that with probability at least $1 - \delta$, we have

$$\|\mathbf{H}^\infty - \mathbf{H}(0)\|_2 \le \|\mathbf{H}^\infty - \mathbf{H}(0)\|_F \le 2n\sqrt{\frac{\log(2n/\delta)}{m}}.$$

The last estimate follows from the definitions of $M_{\mathbf{P}}$ (see eq. (8) and eq. (32)). $\qquad\square$

Now, we state and prove our initial control of the decay of the residual.

Lemma 4. Let $\epsilon > 0, \kappa > 0, 0 < \delta < 1$ and $T > 0$ be given. There exist constants $C_m, C_m' > 0$ such that if $0 \leq \eta \leq 1/(2M_{\mathbf{P}}^2 n)$ and m satisfies

$$m \geq C_m \frac{M_{\mathbf{P}}^6 n^3}{\kappa^2 \epsilon^2} \left(\lambda_0^{-4} \left(1 + \frac{\kappa^2 M_{\mathbf{P}}^2 n}{\delta} \right)^2 + \eta^4 T^4 \epsilon^4 \right)$$

and

$$m \geq C_m' \frac{M_{\mathbf{P}}^4 n^2 \log(n/\delta)}{\epsilon^2} \left(\lambda_0^{-2} \left(1 + \frac{\kappa^2 M_{\mathbf{P}}^2 n}{\delta} \right) + \eta^2 T^2 \epsilon^2 \right),$$

then with probability at least $1 - \delta$, we have the following for all $0 \leq k \leq T$:

$$\mathbf{y} - \mathbf{u}(k) = (\mathbf{I} - 2\eta \mathbf{H}^\infty \mathbf{P})^k (\mathbf{y} - \mathbf{u}(0)) + \boldsymbol{\epsilon}(k), \qquad \|\boldsymbol{\epsilon}(k)\|_{\mathbf{P}} \leq \epsilon. \tag{35}$$

Proof. Set $\delta' = \delta/3$. For any $R > 0$ and $r = 1, \ldots, m$, since $\mathbf{w}_r(0)^\top \mathbf{x}_i \sim \mathcal{N}(0, \kappa^2)$, we have

$$\mathbb{P}\left(\left| \tilde{\mathbf{w}}_r(0)^\top \tilde{\mathbf{x}}_i \right| \leq R \right) = \mathbb{E}\left[\mathbb{1}_{\{|\tilde{\mathbf{w}}_r(0)^\top \tilde{\mathbf{x}}_i| \leq R\}} \right] < \frac{2R}{\sqrt{\pi}\kappa}.$$

By Hoeffding's inequality (Hoeffding, 1963), for any $t > 0$ we have

$$\mathbb{P}\left(\sum_{r=1}^m \mathbb{1}_{\{|\tilde{\mathbf{w}}_r(0)^\top \tilde{\mathbf{x}}_i| \leq R\}} \geq \frac{2mR}{\sqrt{\pi}\kappa} + t \right) \leq \exp\left(-\frac{2t^2}{m} \right) \leq \exp\left(-\frac{t^2}{m} \right), \qquad 1 \leq i \leq n. \tag{36}$$

Thus, if we set $t = \sqrt{m \log(n/\delta')}$ then we find that with probability at least $1 - \delta'/n$ we have

$$\sum_{r=1}^m \mathbb{1}_{\{|\tilde{\mathbf{w}}_r(0)^\top \tilde{\mathbf{x}}_i| \leq R\}} \leq \frac{2mR}{\sqrt{\pi}\kappa} + \sqrt{m \log(n/\delta')} \leq 2m \left(\frac{R}{\sqrt{\pi}\kappa} + \sqrt{\frac{\log(n/\delta')}{m}} \right).$$

By a union bound, we have with probability at least $1 - \delta'$,

$$\sum_{i=1}^n \left(\sum_{r=1}^m \mathbb{1}_{\{|\tilde{\mathbf{w}}_r(0)^\top \tilde{\mathbf{x}}_i| \leq R\}} \right)^2 \leq 4m^2 n \left(\frac{R}{\sqrt{\pi}\kappa} + \sqrt{\frac{\log(n/\delta')}{m}} \right)^2.$$

By combining this with Lemma 3, we have that with probability at least $1 - 2\delta'$,

$$\sqrt{\frac{4M_{\mathbf{P}}^4 n}{m^2} \sum_{i=1}^n \left(\sum_{r=1}^m \mathbb{1}_{\{|\tilde{\mathbf{w}}_r(0)^\top \tilde{\mathbf{x}}_i| \leq R\}} \right)^2} \leq 4M_{\mathbf{P}}^2 n \left(\frac{R}{\sqrt{\pi}\kappa} + \sqrt{\frac{\log(n/\delta')}{m}} \right), \tag{37}$$

and

$$\|(\mathbf{H}^\infty - \mathbf{H}(0))\mathbf{P}\|_{\mathbf{P}} \leq 2M_{\mathbf{P}}^2 n \sqrt{\frac{\log(2n/\delta')}{m}}. \tag{38}$$

Since the ith entry of $\mathbf{u}(0)$ has mean 0 and variance $\leq \kappa^2$, we have $\mathbb{E}[(\mathbf{u}(0))_i^2] \leq \kappa^2$, where $(\mathbf{u}(0))_i$ is the ith entry. Hence, we have $\mathbb{E}\left[\|\mathbf{u}(0)\|_{\mathbf{P}}^2 \right] \leq M_{\mathbf{P}}^2 n \kappa^2$. By Markov's inequality, with probability at least $1 - \delta'$, we have

$$\|\mathbf{u}(0)\|_{\mathbf{P}} \leq \kappa M_{\mathbf{P}} \sqrt{n/\delta'}, \qquad \|\mathbf{y} - \mathbf{u}(0)\|_{\mathbf{P}} \leq \|\mathbf{y}\|_{\mathbf{P}} + \kappa M_{\mathbf{P}} \sqrt{n/\delta'}. \tag{39}$$

By a union bound, we know that eqs. (37) to (39) hold with probability of at least $1 - 3\delta'$. The theorem now follows using induction, where the base case when $k = 0$ is obvious. Assume eq. (35) holds for $t = 0, \ldots, k-1$, where $1 \leq k \leq T$. Then, we have

$$2\eta \sum_{t=0}^{k-1} \|\mathbf{y} - \mathbf{u}(t)\|_{\mathbf{P}} \leq 2\eta \sum_{t=0}^{k-1} \left[(1 - 2\eta\lambda_0)^t \|\mathbf{y} - \mathbf{u}(0)\|_{\mathbf{P}} + \epsilon \right] \leq \lambda_0^{-1} \|\mathbf{y} - \mathbf{u}(0)\|_{\mathbf{P}} + 2\eta T\epsilon, \tag{40}$$

where the first inequality follows from the fact that $\mathbf{I} - 2\eta \mathbf{H}^\infty \mathbf{P}$ is positive semidefinite in $(\mathbb{R}^n, \langle \cdot, \cdot \rangle_{\mathbf{P}})$ with the maximum eigenvalue being $1 - 2\eta\lambda_0$, and the second inequality follows by bounding the power series. By the definition of λ_0, we have

$$2\eta \sum_{t=0}^{k-1} \left\| (\mathbf{I} - 2\eta \mathbf{H}^\infty \mathbf{P})^t (\mathbf{y} - \mathbf{u}(0)) \right\|_{\mathbf{P}} \leq 2\eta \sum_{t=0}^{k-1} (1 - 2\eta\lambda_0)^t \|\mathbf{y} - \mathbf{u}(0)\|_{\mathbf{P}} \leq \lambda_0^{-1} \|\mathbf{y} - \mathbf{u}(0)\|_{\mathbf{P}}.$$

$$\tag{41}$$

By Lemma 2 and 3, we have

$$\mathbf{y} - \mathbf{u}(k) = \left(\mathbf{I} - 2\eta\mathbf{H}^\infty\mathbf{P}\right)^k \left(\mathbf{y} - \mathbf{u}(0)\right) + \boldsymbol{\epsilon}(k)$$

with

$$\|\boldsymbol{\epsilon}(k)\|_\mathbf{P} \le \lambda_0^{-1} \|(\mathbf{H}(0) - \mathbf{H}^\infty)\mathbf{P}\|_\mathbf{P} \|\mathbf{y} - \mathbf{u}(0)\|_\mathbf{P}$$
$$+ 2\sqrt{\frac{4M_\mathbf{P}^4 n}{m^2} \sum_{i=1}^n |S_i(k)|^2} \left(\lambda_0^{-1} \|\mathbf{y} - \mathbf{u}(0)\|_\mathbf{P} + \eta T\epsilon\right), \tag{42}$$

where we used the fact that $|S_i(t)|$ is a nondecreasing function of t and the triangle inequality $\|(\mathbf{H}^\infty - \mathbf{H}(t))\mathbf{P}\|_\mathbf{P} \le \|(\mathbf{H}(0) - \mathbf{H}^\infty)\mathbf{P}\|_\mathbf{P} + \|(\mathbf{H}(t) - \mathbf{H}(0))\mathbf{P}\|_\mathbf{P}$. Here, we also combined $\lambda_0^{-1} \|(\mathbf{H}(t) - \mathbf{H}(0))\mathbf{P}\|_\mathbf{P} \|\mathbf{y} - \mathbf{u}(0)\|_\mathbf{P}$ with the last term on the right-hand side of eq. (26) and applied Lemma 3, eq. (40), and eq. (41) to obtain the last term on the right-hand side of eq. (42). To control $|S_i(k)|$, we first bound the change of the weights. For any $0 \le t \le k-1$ and $1 \le r \le m$, the change of weights in one iteration can be bounded by

$$\|\tilde{\mathbf{w}}_r(t+1) - \tilde{\mathbf{w}}_r(t)\|_2 = \eta \left\| \frac{\partial \mathbf{u}(t)}{\partial \tilde{\mathbf{w}}_r} \frac{\partial \Phi_\mathbf{P}(\mathbf{u})}{\partial \mathbf{u}} \right\|_2$$
$$\le \eta \left\| \frac{\partial \mathbf{u}(t)}{\partial \tilde{\mathbf{w}}_r} \right\|_F \|\mathbf{P}(\mathbf{y} - \mathbf{u}(t))\|_2 \le \eta \sqrt{\frac{2n}{m}} M_\mathbf{P} \|\mathbf{y} - \mathbf{u}(t)\|_\mathbf{P},$$

where the inequalities follow from eq. (23) and eq. (24). Hence, the total change of the weights can be bounded by

$$\|\tilde{\mathbf{w}}_r(t) - \tilde{\mathbf{w}}_r(0)\|_2 \le \eta M_\mathbf{P} \sqrt{\frac{2n}{m}} \sum_{t'=0}^{t-1} \|\mathbf{y} - \mathbf{u}(t')\|_\mathbf{P} \le R_T, \tag{43}$$

where $R_T = M_\mathbf{P}\sqrt{\frac{n}{2m}}\left(\lambda_0^{-1} \|\mathbf{y} - \mathbf{u}(0)\|_\mathbf{P} + 2\eta T\epsilon\right)$. Recall that $S_i(k)$ is the set of indices of weights that have gone through at least one sign flip by iteration k. Thus, if $r \in S_i(k)$, we have $\|\tilde{\mathbf{w}}_r(t) - \tilde{\mathbf{w}}_r(0)\|_2 \ge \left|\tilde{\mathbf{w}}_r(0)^\top \tilde{\mathbf{x}}_i\right|$ for some $0 \le t \le k$ as the sign flip leads to $\left|\tilde{\mathbf{w}}_r(0)^\top \tilde{\mathbf{x}}_i\right| \le \left|\tilde{\mathbf{w}}_r(0)^\top \tilde{\mathbf{x}}_i - \tilde{\mathbf{w}}_r(t)^\top \tilde{\mathbf{x}}_i\right|$. This gives us

$$|S_i(k)| \le \left|\left\{r \in [m] : \left|\tilde{\mathbf{w}}_r(0)^\top \tilde{\mathbf{x}}_i\right| \le \|\tilde{\mathbf{w}}_r(t) - \tilde{\mathbf{w}}_r(0)\|_2 \text{ for some } 0 \le t \le k\right\}\right|$$
$$\le \left|\left\{r \in [m] : \left|\tilde{\mathbf{w}}_r(0)^\top \tilde{\mathbf{x}}_i\right| \le R_T\right\}\right|, \tag{44}$$

where $[m] = \{1, \ldots, m\}$. Hence, there exists a constant $C > 0$ such that

$$\|\boldsymbol{\epsilon}(k)\|_\mathbf{P} \le 2M_\mathbf{P}^2 n \sqrt{\frac{\log(2n/\delta')}{m}} \lambda_0^{-1} \|\mathbf{y} - \mathbf{u}(0)\|_\mathbf{P}$$
$$+ 8M_\mathbf{P}^2 n \left(\frac{R_T}{\sqrt{\pi}\kappa} + \sqrt{\frac{\log(n/\delta')}{m}}\right) \left(\lambda_0^{-1} \|\mathbf{y} - \mathbf{u}(0)\|_\mathbf{P} + \eta T\epsilon\right)$$
$$\le 2M_\mathbf{P}^2 n \underbrace{\sqrt{\frac{\log(6n/\delta)}{m}} \lambda_0^{-1} C \left(1 + \kappa M_\mathbf{P}\sqrt{\frac{3n}{\delta}}\right)}_{A_1}$$
$$+ 8M_\mathbf{P}^2 n \left(\underbrace{\frac{1}{\sqrt{\pi}\kappa} M_\mathbf{P}\sqrt{\frac{n}{2m}}\left(\lambda_0^{-1} C\left(1 + \kappa M_\mathbf{P}\sqrt{\frac{3n}{\delta}}\right) + 2\eta T\epsilon\right)}_{A_2} + \underbrace{\sqrt{\frac{\log(3n/\delta)}{m}}}_{A_3}\right)$$
$$\times \underbrace{\left(\lambda_0^{-1} C\left(1 + \kappa M_\mathbf{P}\sqrt{\frac{3n}{\delta}}\right) + \eta T\epsilon\right)}_{A_4},$$

where the first inequality follows from eq. (37), eq. (42), and eq. (44), and the second inequality follows from eq. (39) and eq. (43). Finally, eq. (35) follows from the way we define m. By taking C_m large enough, we guarantee that $2M_\mathbf{P}^2 n A_1, 8M_\mathbf{P}^2 n A_2 A_4 < \epsilon/3$. By taking C_m' large enough, we guarantee that $8M_\mathbf{P}^2 n A_3 A_4 < \epsilon/3$. Hence, eq. (35) follows. □

Lemma 4 gives us an estimate of the residual $\mathbf{y} - \mathbf{u}(k)$ in terms of the initial residual $\mathbf{y} - \mathbf{u}(0)$. However, in analyzing the frequency bias, we hope to express the residual in terms of $\mathbf{y}$ only. This can be done by controlling the size of $\mathbf{u}(0)$. First, we note that the proof of eq. (39) does not rely on the assumptions on m in Lemma 4. Hence, it holds for any $n, m \geq 1, \kappa > 0, 0 < \delta < 1$, and positive definite matrix $\mathbf{P}$. Now we are ready to prove our first main result Theorem 1.

Proof of Theorem 1. By eq. (39), with probability at least $1 - \delta/2$, we have
$$\left\| (\mathbf{I} - \eta \mathbf{H}^\infty \mathbf{P})^k \mathbf{u}(0) \right\|_{\mathbf{P}} \leq \|\mathbf{u}(0)\|_{\mathbf{P}} \leq \kappa M_{\mathbf{P}} \sqrt{2n/\delta}.$$
By taking $\kappa \leq \epsilon \sqrt{\delta/2n}/(2M_{\mathbf{P}})$, we guarantee that
$$\left\| (\mathbf{I} - \eta \mathbf{H}^\infty \mathbf{P})^k \mathbf{u}(0) \right\|_{\mathbf{P}} \leq \epsilon/2.$$
By the way we pick κ and m, for some constant $C' > 0$ that only depends on d, we have
$$1 + \frac{\kappa^2 M_{\mathbf{P}}^2 n}{\delta} \leq C'.$$
Hence, by taking C_2 in eq. (12) large enough, we guarantee that m satisfies the assumptions in Lemma 4 with ϵ, κ, T, and δ to be $\epsilon/2, \kappa, T$, and $\delta/2$, respectively. Then, we have eq. (35) is true with probability of at least $1 - \delta/2$, for which $\|\boldsymbol{\epsilon}(k)\|_{\mathbf{P}} \leq \epsilon/2$. The result follows from the triangle inequality and union bound. $\square$

Notably, there are other initialization schemes that allow us to avoid using κ. One of the examples is to initialize the weights at odd indices $\mathbf{w}_{2p+1}$ and a_{2p+1} randomly and set $\mathbf{w}_{2p+2} = \mathbf{w}_{2p+1}$, $a_{2p+2} = -a_{2r+1}$, assuming m is even (Su & Yang, 2019). This initialization scheme guarantees that $\mathbf{u}(0) = \mathbf{0}$ and hence we do not need to introduce κ to control the initialization size $\|\mathbf{u}(0)\|_{\mathbf{P}}$. In addition, if we assume that each entry of $\mathbf{w}_r$ is initialized from an iid sub-Gaussian distribution with zero mean and whose support is the entire $\mathbb{R}$, then since $\mathbf{H}^\infty$ is still SPD (see the remark at the end of Appendix B) and the Hoeffding's inequality holds, the proof does not break down and a result similar to Theorem 1 can be shown.

Following the same steps of proof, we can study the case when the gradient descent steps are slightly perturbed. That is, Suppose we perturb the output of the NN by $\delta \mathbf{u}_j$ at the jth iteration. Then, we expect that the residual of the NN at the kth iteration is approximately
$$\mathbf{y} - \mathbf{u}(k) \approx (\mathbf{I} - 2\eta \mathbf{H}^\infty \mathbf{P}) \cdots ((\mathbf{I} - 2\eta \mathbf{H}^\infty \mathbf{P})((\mathbf{I} - 2\eta \mathbf{H}^\infty \mathbf{P})\mathbf{y} + \delta \mathbf{u}_1) + \delta \mathbf{u}_2) + \cdots + \delta \mathbf{u}_k$$
$$= (\mathbf{I} - 2\eta \mathbf{H}^\infty \mathbf{P})^k \mathbf{y} + \sum_{j=1}^{k} (\mathbf{I} - 2\eta \mathbf{H}^\infty \mathbf{P})^{k-j} \delta \mathbf{u}_j.$$
Since the maximum eigenvalue of $\mathbf{I} - 2\eta \mathbf{H}^\infty \mathbf{P}$ is less than one, we can then control the errors in this approximation using arguments similar to previous lemmas.

While this paper is primarily concerned with learning a continuous function using loss functions that are adapted from MSE, we briefly discuss the changes that are needed to study classifiers trained by cross-entropy. If the classification task has p classes, then our NN has p outputs, each of which is then passed through a softmax layer and represents an estimate of the likelihood that the input belongs to the corresponding class. More information on the NN architecture and the cross-entropy loss function can be found in (**?**). Let $\mathcal{N}_j(\mathbf{x}; \mathbf{W})$ be the jth entry of the outputs of the NN and let $u_j(\mathbf{x}; \mathbf{W}) = \text{softmax}(\mathcal{N}_j(\mathbf{x}; \mathbf{W})), 1 \leq j \leq p$. Let $g_j(\mathbf{x})$ be the ground-truth of the jth entry of the outputs and let $z_j(\mathbf{x}; \mathbf{W}) = g_j(\mathbf{x}) - u_j(\mathbf{x}; \mathbf{W})$ be the residual. Assume we use the gradient flow and have access to data on the entire domain. Then, to derive a formula analogous to eq. (2), for each fixed $\mathbf{x}$, we have
$$\frac{dz_j(\mathbf{x}; \mathbf{W})}{dt} = -\frac{du_j(\mathbf{x}; \mathbf{W})}{dt} = -\sum_{i=1}^{p} \frac{du_j(\mathbf{x}; \mathbf{W})}{d\mathcal{N}_i} \frac{d\mathcal{N}_i(\mathbf{x}; \mathbf{W})}{dt}$$
$$= -\sum_{i=1}^{p} \frac{du_j(\mathbf{x}; \mathbf{W})}{d\mathcal{N}_i} \frac{\partial \mathcal{N}_i(\mathbf{x}; \mathbf{W})}{\partial \mathbf{W}} \frac{d\mathbf{W}}{dt} = \sum_{i=1}^{p} \frac{du_j(\mathbf{x}; \mathbf{W})}{d\mathcal{N}_i} \frac{\partial \mathcal{N}_i(\mathbf{x}; \mathbf{W})}{\partial \mathbf{W}} \left(\frac{\partial \mathcal{L}(\mathbf{W})}{\partial \mathbf{W}} \right)^\top$$
$$= \sum_{i=1}^{p} \left(\frac{du_j(\mathbf{x}; \mathbf{W})}{d\mathcal{N}_i} \frac{\partial \mathcal{N}_i(\mathbf{x}; \mathbf{W})}{\partial \mathbf{W}} \sum_{i'=1}^{p} \int_{\mathbb{S}^{d-1}} \left(-z_{i'}(\mathbf{x}'; \mathbf{W}) \frac{\partial \mathcal{N}_{i'}(\mathbf{x}'; \mathbf{W})}{\partial \mathbf{W}} \right)^\top d\mu(\mathbf{x}') \right),$$

where $\mathcal{L}$ is the cross-entropy loss function computed as an integral over $\mathbb{S}^{d-1}$ and in the last step we used the fact that $(d/d\mathcal{N}_{i'})\mathcal{L}(\mathbf{x}';\mathbf{W}) = u_{i'}(\mathbf{x}';\mathbf{W}) - g_{i'}(\mathbf{x}') = -z_{i'}(\mathbf{x}';\mathbf{W})$ **?**. Hence, eq. (2) now becomes

$$\frac{dz_j(\mathbf{x};\mathbf{W})}{dt} = -\sum_{i=1}^{p}\left(\frac{du_j(\mathbf{x};\mathbf{W})}{d\mathcal{N}_i}\sum_{i'=1}^{p}\underbrace{\int_{\mathbb{S}^{d-1}}\left\langle\frac{\partial\mathcal{N}_i}{\partial\mathbf{W}}(\mathbf{x};\mathbf{W}),\frac{\partial\mathcal{N}_{i'}}{\partial\mathbf{W}}(\mathbf{x}';\mathbf{W})\right\rangle z_{i'}(\mathbf{x}';\mathbf{W})d\mu(\mathbf{x}')}_{=K_{i,i'}(\mathbf{x},\mathbf{x}';\mathbf{W})}\right),$$

where we also know that $(d/d\mathcal{N}_i)u_j(\mathbf{x};\mathbf{W}) = u_i(\mathbf{x};\mathbf{W})(\mathbb{I}_{\{i=j\}} - u_j(\mathbf{x};\mathbf{W}))$. Again, we define $\mathbf{H}_{i,i'}^{\infty}$ as the discretization of $K_{i,i'}$ in expectation over random initialization of $\mathbf{W}$. Note that $\mathbf{H}_{i,i}^{\infty}$ coincides with $\mathbf{H}^{\infty}$ that we used extensively in this paper. However, the entries of $\mathbf{H}_{i,i'}^{\infty}$ might differ with $\mathbf{H}^{\infty}$ in signs. This potentially causes difficulties in analyzing the spectrum of $\mathbf{H}_{i,i'}^{\infty}$. Now, by the formula above, we expect that the residual can approximately be written as

$$\mathbf{z}_j(k+1) - \mathbf{z}_j(k) = [g_j(\mathbf{x}) - \mathbf{u}_j(k+1)] - [g_j(\mathbf{x}) - \mathbf{u}_j(k)]$$

$$\approx -\eta\sum_{i=1}^{p}\left(\mathbf{u}_i(k)\circ(\mathbb{I}_{\{i=j\}} - \mathbf{u}_j(k))\circ\sum_{i'=1}^{p}\left(\mathbf{H}_{i,i'}^{\infty}\mathbf{P}\mathbf{z}_{i'}(k)\right)\right), \tag{45}$$

where $\mathbf{u}_j(k) = u_j(\mathbf{x};\mathbf{W}(k))$ and '$\circ$' is the Hadamard product. Suppose we define the vectorized residual $\mathbf{z} = \left[\mathbf{z}_1^{\top},\ldots,\mathbf{z}_p^{\top}\right]^{\top}$ and define the $np \times np$ block matrix $\mathbf{J}(k)$ by $\mathbf{J}(k)_{(in+1):(i+1)n,(jn+1):(j+1)n} = \mathrm{diag}\left(\mathbf{u}_i(k)\circ(\mathbb{I}_{\{i=j\}} - \mathbf{u}_j(k))\right)$ for $i,j = 0,\ldots,p-1$. Let $\boldsymbol{\mathcal{H}}^{\infty}$ be the $np \times np$ block matrix such that $\boldsymbol{\mathcal{H}}_{(in+1):(i+1)n,(i'n+1):(i'+1)n}^{\infty} = \mathbf{H}_{i,i'}^{\infty}$ for $i,i' = 0,\ldots,p-1$. Then, eq. (45) can be written compactly as

$$\mathbf{z}(k+1) - \mathbf{z}(k) \approx -\eta\mathbf{J}(k)\boldsymbol{\mathcal{H}}^{\infty}(\mathbf{I}_p\otimes\mathbf{P})\mathbf{z}(k), \tag{46}$$

where '$\otimes$' is the Kronecker product. Frequency biasing can be analyzed by studying the dynamics of $\mathbf{z}(k)$ based on eq. (46). However, the fact that $\mathbf{J}$ depends on k is expected to add complication to the analysis.

D   THE THEORY OF FREQUENCY BIASING WITH AN $\mathbf{L}^2$-BASED LOSS FUNCTION

In this section, we prove the results stated in Section 4, where we are concerned with the frequency biasing behavior of NN training when using the squared L^2 norm as the loss function. We theoretically show the frequency biasing phenomena in this setting, up to a quadrature error.

D.1   A CONSEQUENCE OF THEOREM 1

Given a bandlimited function $g : \mathbb{S}^{d-1} \to \mathbb{R}$ with bandlimit L, we can uniquely decompose g into a spherical harmonic expansion as $g(\mathbf{x}) = \sum_{\ell=0}^{L} g_\ell(\mathbf{x})$, where $g_\ell(\mathbf{x}) \in \mathcal{H}_\ell^d$. Here, $\mathcal{H}_\ell^d$ is the space of the restriction of (real) homogeneous harmonic polynomials of degree ℓ on $\mathbb{S}^{d-1}$. That is,

$$g_\ell(\mathbf{x}) = \sum_{p=1}^{N(d,\ell)}\hat{g}_{\ell,p}Y_{\ell,p}, \qquad \hat{g}_{\ell,p} = \int_{\mathbb{S}^{d-1}}g(\mathbf{x})Y_{\ell,p}(\mathbf{x})d\mathbf{x}.$$

where $N(d,\ell)$ is given in section 2 and $Y_{\ell,p}$ are the spherical harmonic function of degree ℓ and order p. As a consequence of Theorem 1, we can consider the NN training error with the squared L^2-based loss function.

Proof of Theorem 2. By Theorem 1, for every $k = 0,\ldots,T$, we can write

$$\|\mathbf{u}(k) - \mathbf{y}\|_{\mathbf{c}} = \left\|(\mathbf{I}-2\eta\mathbf{H}^{\infty}\mathbf{D}_{\mathbf{c}})^k\mathbf{y}\right\|_{\mathbf{c}} + \varepsilon_3(k), \qquad |\varepsilon_3(k)| \le \|\boldsymbol{\epsilon}(k)\|_{\mathbf{c}} \le \epsilon. \tag{47}$$

To estimate the first term, we first note that the matrix $\mathbf{I} - 2\eta\mathbf{H}^{\infty}\mathbf{D}_{\mathbf{c}}$ is positive semidefinite in $(\mathbb{R}^n,\langle\cdot,\cdot\rangle_{\mathbf{c}})$ and $\|\mathbf{I} - 2\eta\mathbf{H}^{\infty}\mathbf{D}_{\mathbf{c}}\|_{\mathbf{c}} \le 1 - 2\eta\lambda_0$ (see Theorem 1). Since $g(\mathbf{x}) = \sum_{\ell=0}^{L}g_\ell(\mathbf{x})$, we have

$$(\mathbf{I} - 2\eta\mathbf{H}^{\infty}\mathbf{D}_{\mathbf{c}})^k\mathbf{y} = \sum_{\ell=0}^{L}(\mathbf{I} - 2\eta\mathbf{H}^{\infty}\mathbf{D}_{\mathbf{c}})^k\mathbf{y}^\ell, \qquad \mathbf{y} = \sum_{\ell=0}^{L}\mathbf{y}^\ell,$$

where $\mathbf{y}^\ell = [g_\ell(\mathbf{x}_1), \ldots, g_\ell(\mathbf{x}_n)]^\top \in \mathbb{R}^n$. By the Funk–Hecke formula and the quadrature rule, we have

$$\left(\mathbf{H}^\infty \mathbf{D_c} \mathbf{y}^\ell\right)_p = \sum_{i=1}^n c_i K^\infty(\mathbf{x}_p, \mathbf{x}_i) g_\ell(\mathbf{x}_i) = \int_{\mathbb{S}^{d-1}} K^\infty(\mathbf{x}_p, \boldsymbol{\xi}) g_\ell(\boldsymbol{\xi}) d\boldsymbol{\xi} + e_{p,\ell}^d = \mu_\ell g_\ell(\mathbf{x}_p) + e_{p,\ell}^d,$$

where $e_{p,\ell}^d$ is a quadrature error (see eq. (15)). Therefore, in vectorized form, we have $\mathbf{H}^\infty \mathbf{D_c} \mathbf{y}^\ell = \mu_\ell \mathbf{y}^\ell + \mathbf{e}_\ell^d$ or, equivalently, $(\mathbf{I} - 2\eta \mathbf{H}^\infty \mathbf{D_c}) \mathbf{y}^\ell = (1 - 2\eta\mu_\ell) \mathbf{y}^\ell - 2\eta \mathbf{e}_\ell^d$, where $\mathbf{e}_\ell^d = (e_{1,\ell}^d, \ldots, e_{n,\ell}^d)^\top$. By applying $\mathbf{I} - 2\eta \mathbf{H}^\infty \mathbf{D_c}$ to $\mathbf{y}^\ell$ for k times, we find that

$$(\mathbf{I} - 2\eta\mathbf{H}^\infty\mathbf{D_c})^k \mathbf{y}^\ell = (1 - 2\eta\mu_\ell)^k \mathbf{y}^\ell \underbrace{- 2\eta \sum_{t=0}^{k-1} (1 - 2\eta\mu_\ell)^t (\mathbf{I} - 2\eta\mathbf{H}^\infty\mathbf{D_c})^{k-t-1} \mathbf{e}_\ell^d}_{\boldsymbol{\varepsilon}_2^\ell}.$$

The second term, $\boldsymbol{\varepsilon}_2^\ell$, can be easily bounded from above to obtain

$$\left\|\boldsymbol{\varepsilon}_2^\ell\right\|_{\mathbf{c}} \le 2\eta \left\|\mathbf{e}_\ell^d\right\|_{\mathbf{c}} \sum_{t=0}^\infty (1 - 2\eta\mu_\ell)^t = \frac{1}{\mu_\ell} \left\|\mathbf{e}_\ell^d\right\|_{\mathbf{c}}.$$

The inequality above shows that $(\mathbf{I} - 2\eta\mathbf{H}^\infty\mathbf{D_c})^k \mathbf{y}^\ell$ is close to $(1 - 2\eta\mu_\ell)^k \mathbf{y}^\ell$. We define

$$\varepsilon_2 = \left\|\sum_{\ell=0}^L (\mathbf{I} - 2\eta\mathbf{H}^\infty\mathbf{D_c})^k \mathbf{y}^\ell\right\|_{\mathbf{c}} - \left\|\sum_{\ell=0}^L (1 - 2\eta\mu_\ell)^k \mathbf{y}^\ell\right\|_{\mathbf{c}}$$

to be the quantity in the statement of Theorem 2, which measures the accuracy of approximating the eigenvalues and eigenvectors of $\mathbf{H}^\infty \mathbf{D_c}$ using the eigenvalues and eigenfunctions of the continuous kernel K^∞. Hence, we have

$$\left\|(\mathbf{I} - 2\eta\mathbf{H}^\infty\mathbf{D_c})^k \mathbf{y}\right\|_{\mathbf{c}} = \left\|\sum_{\ell=0}^L (1 - 2\eta\mu_\ell)^k \mathbf{y}^\ell\right\|_{\mathbf{c}} + \varepsilon_2. \tag{48}$$

Using the triangle inequality, we have

$$|\varepsilon_2| \le \sum_{\ell=0}^L \left\|\boldsymbol{\varepsilon}_2^\ell\right\|_{\mathbf{c}} \le \sum_{\ell=0}^L \frac{1}{\mu_\ell} \left\|\mathbf{e}_\ell^d\right\|_{\mathbf{c}} = \sum_{\ell=0}^L \frac{1}{\mu_\ell} \sqrt{\sum_{i=1}^n c_i (e_{i,\ell}^d)^2} \le \sum_{\ell=0}^L \frac{\sqrt{A_d}}{\mu_\ell} \max_{1 \le i \le n} \left| e_{i,\ell}^d \right|.$$

Recall that $\sum_{i=1}^n c_i = A_d$, the surface area of $\mathbb{S}^{d-1}$. Next, we can write

$$\left\|\sum_{\ell=0}^L (1 - 2\eta\mu_\ell)^k \mathbf{y}^\ell\right\|_{\mathbf{c}}^2 = \left(\sum_{\ell=0}^L (1 - 2\eta\mu_\ell)^k \mathbf{y}^\ell\right)^\top \mathbf{D_c} \left(\sum_{\ell=0}^L (1 - 2\eta\mu_\ell)^k \mathbf{y}^\ell\right)$$

$$= \sum_{j=0}^L \sum_{\ell=0}^L (1 - 2\eta\mu_j)^k (1 - 2\eta\mu_\ell)^k {\mathbf{y}^j}^\top \mathbf{D_c} \mathbf{y}^\ell$$

$$= \sum_{j=0}^L \sum_{\ell=0}^L (1 - 2\eta\mu_j)^k (1 - 2\eta\mu_\ell)^k \left(\int_{\mathbb{S}^{d-1}} g_j(\boldsymbol{\xi}) g_\ell(\boldsymbol{\xi}) d\boldsymbol{\xi} + e_{j,\ell}^c\right)$$

$$= \sum_{\ell=0}^L (1 - 2\eta\mu_\ell)^{2k} \|g_\ell\|_{L^2}^2 + \underbrace{\sum_{j=0}^L \sum_{\ell=0}^L (1 - 2\eta\mu_j)^k (1 - 2\eta\mu_\ell)^k e_{j,\ell}^c}_{\varepsilon_1(k)}, \tag{49}$$

where we used the fact that g_j and g_ℓ are orthogonal in $L^2(\mathbb{S}^{d-1})$ for $j \ne \ell$. Combining eq. (48) and eq. (49), we can write

$$\left\|(\mathbf{I} - 2\eta\mathbf{H}^\infty\mathbf{D_c})^k \mathbf{y}\right\|_{\mathbf{c}} = \sqrt{\sum_{j=0}^L (1 - 2\eta\mu_j)^{2k} \|g_j\|_{L^2}^2 + \varepsilon_1(k) + \varepsilon_2}, \tag{50}$$

where

$$|\varepsilon_1(k)| \leq \left| \sum_{j=0}^{L} \sum_{\ell=0}^{L} (1-2\eta\mu_j)^k (1-2\eta\mu_\ell)^k e_{j,\ell}^c \right|.$$

The result follows from eq. (47) and eq. (50). □

D.2 FREQUENCY BIASING UP TO AN APPROXIMATION ERROR

Theorem 2 shows that we theoretically have frequency biasing up to the level of quadrature errors $\varepsilon_1(k)$ and ε_2. If the quadrature errors are large, then we may not observe frequency biasing in practice. Here, we show that the quadrature errors can be made arbitrarily small by taking enough samples in the training data. Recall that our quadrature rule satisfies eq. (17).

Next, we pass the quadrature error to the approximation error, which may not necessarily be tight. However, this allows us to use the existing theory of spherical harmonics approximation to show the decay of quadrature errors.

Lemma 5. Let $f : \mathbb{S}^{d-1} \to \mathbb{R}$ be a function and $\mathrm{dist}(f, \Pi_\ell^d) = \min_{h \in \Pi_\ell^d} \|f - h\|_{L^\infty}$. We have

$$\left| \int_{\mathbb{S}^{d-1}} f(\boldsymbol{\xi}) d\boldsymbol{\xi} - \sum_{i=1}^{n} c_i f(\mathbf{x}_i) \right| \leq 2\gamma_{n,\ell} \|f\|_{L^\infty} + 2A_d \mathrm{dist}(f, \Pi_\ell^d) \tag{51}$$

for any integer $\ell \geq 0$.

Proof. Let $h_\ell = \underset{h \in \Pi_\ell^d}{\arg\min} \|f - h\|_{L^\infty}$. By the triangle inequality, we have

$$\left| \int_{\mathbb{S}^{d-1}} f(\boldsymbol{\xi}) d\boldsymbol{\xi} - \sum_{i=1}^{n} c_i f(\mathbf{x}_i) \right|$$

$$\leq \left| \int_{\mathbb{S}^{d-1}} f(\boldsymbol{\xi}) d\boldsymbol{\xi} - \int_{\mathbb{S}^{d-1}} h_\ell(\boldsymbol{\xi}) d\boldsymbol{\xi} \right| + \left| \int_{\mathbb{S}^{d-1}} h_\ell(\boldsymbol{\xi}) d\boldsymbol{\xi} - \sum_{i=1}^{n} c_i h_\ell(\mathbf{x}_i) \right| + \left| \sum_{i=1}^{n} c_i (h_\ell(\mathbf{x}_i) - f(\mathbf{x}_i)) \right|$$

$$\leq A_d \mathrm{dist}(f, \Pi_\ell^d) + \gamma_{n,\ell} \|h_\ell\|_{L^\infty} + A_d \mathrm{dist}(f, \Pi_\ell^d) \leq 2\gamma_{n,\ell} \|f\|_{L^\infty} + 2A_d \mathrm{dist}(f, \Pi_\ell^d),$$

where we used the fact that $c_i > 0$ for $i = 1, \dots, n$ and the fact that $\|h_\ell\|_{L^\infty} \leq 2\|f\|_{L^\infty}$. □

Next, we focus on controlling the minimum approximation error $\mathrm{dist}(f, \Pi_\ell^d)$ on the right-hand side of eq. (51). To do so, we prove the following lemma.

Lemma 6. Let $f_{ij}(\boldsymbol{\xi}) = K^\infty(\mathbf{x}_i, \boldsymbol{\xi}) g_j(\boldsymbol{\xi})$ and $g_{jp}(\boldsymbol{\xi}) = g_j(\boldsymbol{\xi}) g_p(\boldsymbol{\xi})$. Then, for a constant $C > 0$ that only depends on d, we have

$$\mathrm{dist}(f_{ij}, \Pi_\ell^d) \leq C \frac{j+1}{\ell} \|g_j\|_{L^\infty}, \qquad 1 \leq i \leq n, 0 \leq j \leq L,$$

$$\mathrm{dist}(g_{jp}, \Pi_\ell^d) \leq C \frac{j+p}{\ell} \|g_j\|_{L^\infty} \|g_p\|_{L^\infty}, \quad 0 \leq j, p \leq L,$$

for all $\ell \geq 1$.

Proof. For $1 \leq a < b \leq d$ where $a, b \in \mathbb{N}$, and $t \in [-\pi, \pi)$, let $Q_{a,b,t}$ denote the action on $\mathbb{S}^{d-1}$ of rotation by the angle t in the (x_a, x_b)-plane. For an integer $\alpha \geq 1$, we define the operator on functions on $\mathbb{S}^{d-1}$ by

$$\Delta_{a,b,t}^\alpha = (I - T(Q_{a,b,t}))^\alpha,$$

where $T(Q)f(\mathbf{x}) = f(Q^{-1}\mathbf{x})$. If $f \in C(\mathbb{S}^{d-1})$, then we define for $t > 0$ that

$$\omega_\alpha(f; t) = \max_{1 \leq a < b \leq d} \sup_{|\theta| \leq t} \left\| \Delta_{a,b,\theta}^\alpha f \right\|_{L^\infty}.$$

By (Dai & Xu, 2013, Thm. 4.4.2), we have

$$\mathrm{dist}(f, \Pi_\ell^d) \leq c_1 \omega_\alpha(f; \ell^{-1}), \qquad \ell \geq 1, \alpha \geq 1,$$

where $c_1 > 0$ is some constant that only depends on α. Then it is sufficient to bound $\omega_\alpha(f_{ij}; \ell^{-1})$ and $\omega_\alpha(g_{jp}; \ell^{-1})$ to finish the proof.

First, we aim to bound the term $\text{dist}(f_{ij}, \Pi_\ell^d)$ where $f_{ij}(\boldsymbol{\xi}) = K^\infty(\mathbf{x}_i, \boldsymbol{\xi})g_j(\boldsymbol{\xi})$. We fix $1 \leq i \leq n$, $1 \leq a < b \leq d$ where $i, a, b \in \mathbb{N}$, and choose θ such that $|\theta| \leq \ell^{-1}$. We have

$$\left\|\Delta_{a,b,\theta}^1 f_{ij}\right\|_{L^\infty} = \left\|f_{ij}(\boldsymbol{\xi}) - f_{ij}(Q_{a,b,\theta}^{-1}\boldsymbol{\xi})\right\|_{L^\infty}.$$

We then define

$$\delta K_i^\infty(\boldsymbol{\xi}) := K^\infty(\mathbf{x}_i, Q_{a,b,\theta}^{-1}\boldsymbol{\xi}) - K^\infty(\mathbf{x}_i, \boldsymbol{\xi}), \qquad \delta g_j(\boldsymbol{\xi}) := g_j(Q_{a,b,\theta}^{-1}\boldsymbol{\xi}) - g_j(\boldsymbol{\xi}).$$

We then have

$$
\begin{aligned}
\left\|f_{ij}(\boldsymbol{\xi}) - f_{ij}(Q_{a,b,\theta}^{-1}\boldsymbol{\xi})\right\|_{L^\infty} &= \|K^\infty(\mathbf{x}_i, \boldsymbol{\xi})g_j(\boldsymbol{\xi}) - (K^\infty(\mathbf{x}_i, \boldsymbol{\xi}) + \delta K_i^\infty(\boldsymbol{\xi}))(g_j(\boldsymbol{\xi}) + \delta g_j(\boldsymbol{\xi}))\|_{L^\infty} \\
&\leq \|\delta K_i^\infty(\boldsymbol{\xi})(g_j(\boldsymbol{\xi}) + \delta g_j(\boldsymbol{\xi}))\|_{L^\infty} + \|K^\infty(\mathbf{x}_i, \boldsymbol{\xi})\delta g_j(\boldsymbol{\xi})\|_{L^\infty}.
\end{aligned}
\tag{52}
$$

We control the two terms separately. First, to control the second term, we write

$$\|K^\infty(\mathbf{x}_i, \boldsymbol{\xi})\delta g_j(\boldsymbol{\xi})\|_{L^\infty} \leq \|K^\infty(\mathbf{x}_i, \boldsymbol{\xi})\|_{L^\infty} \|\delta g_j(\boldsymbol{\xi})\|_{L^\infty} \leq \frac{1}{2}\|\delta g_j(\boldsymbol{\xi})\|_{L^\infty}, \tag{53}$$

based on the definition of K^∞ in eq. (10). For some constant $c_2 > 0$ that depends only on d, we have

$$\|\delta g_j(\boldsymbol{\xi})\|_{L^\infty} = \left\|\Delta_{a,b,\theta}^1 g_j(\boldsymbol{\xi})\right\|_{L^\infty} \leq c_2 \ell^{-1} \|D_{a,b} g_j(\boldsymbol{\xi})\|_{L^\infty} \leq c_2 \frac{j}{\ell}\|g_j\|_{L^\infty}, \tag{54}$$

where $D_{a,b} := x_a\partial_b - x_b\partial_a$ and the two inequalities follow from (Dai & Xu, 2013, Lem. 4.2.2 (iii)) and (Dai & Xu, 2013, Lem. 4.2.4), respectively. Next, we control the first term of eq. (52) by writing

$$\|\delta K_i^\infty(\boldsymbol{\xi})(g_j(\boldsymbol{\xi}) + \delta g_j(\boldsymbol{\xi}))\|_{L^\infty} \leq \|\delta K_i^\infty(\boldsymbol{\xi})\|_{L^\infty} \left\|g_j(Q_{a,b,\theta}^{-1}\boldsymbol{\xi})\right\|_{L^\infty} = \|\delta K_i^\infty(\boldsymbol{\xi})\|_{L^\infty} \|g_j\|_{L^\infty}. \tag{55}$$

We fix $\boldsymbol{\xi}$ and define $\boldsymbol{\xi}' = Q_{a,b,\theta}^{-1}\boldsymbol{\xi}$. It follows that

$$
\begin{aligned}
\delta K_i^\infty(\boldsymbol{\xi}) &= K^\infty(\mathbf{x}_i, \boldsymbol{\xi}') - K^\infty(\mathbf{x}_i, \boldsymbol{\xi}) \\
&= \frac{1}{4\pi}\left[(\mathbf{x}_i^\top\boldsymbol{\xi}' + 1)\left(\pi - \arccos(\mathbf{x}_i^\top\boldsymbol{\xi}')\right) - (\mathbf{x}_i^\top\boldsymbol{\xi} + 1)\left(\pi - \arccos(\mathbf{x}_i^\top\boldsymbol{\xi})\right)\right] \\
&= \frac{1}{4\pi}\left[\mathbf{x}_i^\top(\boldsymbol{\xi}' - \boldsymbol{\xi})\left(\pi - \arccos(\mathbf{x}_i^\top\boldsymbol{\xi})\right) - (\mathbf{x}_i^\top\boldsymbol{\xi}' + 1)\left(\arccos(\mathbf{x}_i^\top\boldsymbol{\xi}) - \arccos(\mathbf{x}_i^\top\boldsymbol{\xi}')\right)\right]
\end{aligned}
$$

Next, by the triangle inequality for angles, we have

$$\left|\arccos(\mathbf{x}_i^\top\boldsymbol{\xi}) - \arccos(\mathbf{x}_i^\top\boldsymbol{\xi}')\right| \leq |\theta| \leq \ell^{-1}.$$

Since $\arccos$ is monotone and $|(d/dt)\arccos(t)| > 1$ for all t, by the fundamental theorem of calculus, we must have

$$\left|\mathbf{x}_i^\top\boldsymbol{\xi}' - \mathbf{x}_i^\top\boldsymbol{\xi}\right| \leq \left|\arccos(\mathbf{x}_i^\top\boldsymbol{\xi}) - \arccos(\mathbf{x}_i^\top\boldsymbol{\xi}')\right| \leq \ell^{-1}.$$

As a result, we have

$$|\delta K_i^\infty(\boldsymbol{\xi})| \leq \frac{1}{4\pi}\left[\ell^{-1}\pi + 2\ell^{-1}\right] = \frac{\pi + 2}{4\pi}\ell^{-1}. \tag{56}$$

By eq. (55) and eq. (56), we find that

$$\|\delta K_i^\infty(\boldsymbol{\xi})(g_j(\boldsymbol{\xi}) + \delta g_j(\boldsymbol{\xi}))\|_{L^\infty} \leq \frac{\pi + 2}{4\pi}\ell^{-1}\|g_j\|_{L^\infty}. \tag{57}$$

Putting eqs. (52) to (54) and (57) together, we obtain

$$\left\|\Delta_{a,b,\theta}^1 f_{ij}\right\|_{L^\infty} = \left\|f_{ij}(\boldsymbol{\xi}) - f_{ij}(Q_{a,b,\theta}^{-1}\boldsymbol{\xi})\right\|_{L^\infty} \leq \left(c_2 j + \frac{\pi + 2}{4\pi}\right)\ell^{-1}\|g_j\|_{L^\infty}.$$

Since a, b, and θ are chosen arbitrarily, this bound also holds for $\omega_1(f_{ij}; \ell^{-1})$.

Second, we aim to bound the term $\text{dist}(g_{jp}, \Pi_\ell^d)$ where $g_{jp}(\boldsymbol{\xi}) = g_j(\boldsymbol{\xi})g_p(\boldsymbol{\xi})$. As before, we fix the indices $a, b \in \mathbb{N}$ where $1 \le a < b \le d$ and θ such that $|\theta| \le \ell^{-1}$. Similarly, we define

$$\delta g_j(\boldsymbol{\xi}) = g_j(Q_{a,b,\theta}^{-1}\boldsymbol{\xi}) - g_j(\boldsymbol{\xi}), \quad \delta g_p(\boldsymbol{\xi}) = g_p(Q_{a,b,\theta}^{-1}\boldsymbol{\xi}) - g_p(\boldsymbol{\xi}).$$

By eq. (54), we have

$$
\begin{aligned}
\left\| g_j g_p(\boldsymbol{\xi}) - g_j g_p(Q_{a,b,\theta}^{-1}\boldsymbol{\xi}) \right\|_{L^\infty} &= \| g_j(\boldsymbol{\xi})g_p(\boldsymbol{\xi}) - (g_j(\boldsymbol{\xi}) + \delta g_j(\boldsymbol{\xi}))(g_p(\boldsymbol{\xi}) + \delta g_p(\boldsymbol{\xi})) \|_{L^\infty} \\
&\le \| \delta g_j(\boldsymbol{\xi})(g_p(\boldsymbol{\xi}) + \delta g_p(\boldsymbol{\xi})) \|_{L^\infty} + \| g_j(\boldsymbol{\xi})\delta g_p(\boldsymbol{\xi}) \|_{L^\infty} \quad (58) \\
&\le c_2 \frac{j+p}{\ell} \| g_j \|_{L^\infty} \| g_p \|_{L^\infty}.
\end{aligned}
$$

Since a, b, and θ are arbitrary numbers, this bound also holds for $\omega_1(g_{jp}; \ell^{-1})$. $\qquad\square$

Using these lemmas, we can prove that Theorem 3 asymptotically controls the quadrature errors.

Proof of Theorem 3. First, we control $\varepsilon_1(k)$ as

$$
\begin{aligned}
|\varepsilon_1(k)| &\le \left| \sum_{j=0}^{L} \sum_{p=0}^{L} (1-2\eta\mu_j)^k (1-2\eta\mu_p)^k e_{jp}^c \right| \le \left| \sum_{j=0}^{L} \sum_{p=0}^{L} e_{jp}^c \right| \\
&\le \sum_{j=0}^{L} \sum_{p=0}^{L} \left| 2\gamma_{n,\ell} \| g_{jp} \|_{L^\infty} + 2A_d \text{dist}(g_{jp}, \Pi_\ell^d) \right| \\
&\le \sum_{j=0}^{L} \sum_{p=0}^{L} \left(2\gamma_{n,\ell} \| g_j \|_{L^\infty} \| g_p \|_{L^\infty} + 2A_d C \frac{j+p}{\ell} \| g_j \|_{L^\infty} \| g_p \|_{L^\infty} \right),
\end{aligned}
$$

where the third and the forth inequalities follow from Lemma 5 and Lemma 6, respectively. The final upper bound for $|\varepsilon_1(k)|$ holds since $\sum_{j=0}^{L} \sum_{p=0}^{L} (j+p) = \mathcal{O}(L^3)$. Next, there exists $C_2 > 0$ such that we can control ε_2 by writing

$$
\begin{aligned}
|\varepsilon_2| &\le \sum_{j=0}^{L} \frac{\sqrt{A_d}}{\mu_j} \max_{1 \le i \le n} |e_{ij}^b| \le \sum_{j=0}^{L} \frac{\sqrt{A_d}}{\mu_j} \left(2\gamma_{n,\ell} \| g_j \|_{L^\infty} + 2A_d C \frac{j+1}{\ell} \| g_j \|_{L^\infty} \right) \\
&\le C_2 \left(\sum_{j=0}^{L} \mu_j^{-1} \right) \left(\frac{L^2}{\ell} + L\gamma_{n,\ell} \right) \max_j \| g_j \|_{L^\infty},
\end{aligned}
$$

where the second and the third inequalities follow from Lemma 5 and Lemma 6, respectively. The proof is complete. $\qquad\square$

Proof of Corollary 1. By Theorem 3, it suffices to show that $\max_{0 \le j \le L} \| g_j \|_{L^\infty} \le C \| g \|_{L^2}$ for some constant $C > 0$ that does not depend on g. Since $\mathcal{H}_i^d \perp \mathcal{H}_j^d$ in L^2 for $i \ne j$, we have $\| g_j \|_{L^2} \le \| g \|_{L^2}$ for $0 \le j \le L$. The claim follows from the fact that $\| \cdot \|_{L^2}$ and $\| \cdot \|_{L^\infty}$ are equivalent in Π_L^d. $\qquad\square$

E THE THEORY OF FREQUENCY BIASING WITH A $\mathbf{H^s}$-BASED LOSS FUNCTION

This section presents detailed proofs for Proposition 2 and Theorem 4 in Section 5, which concerns the frequency biasing behavior of NN training using the H^s loss function.

E.1 A 2-LAYER RELU NEURAL NETWORK IS IN $\mathbf{H^s}(\mathbb{S}^{\mathbf{d-1}})$ FOR $\mathbf{s < 3/2}$

We prove that a 2-layer ReLU NN map is contained in $H^s(\mathbb{S}^{d-1})$ for any $s < 3/2$ (see Proposition 2).

Proof of Proposition 2. Since $\mathcal{N}$ can be written as

$$\mathcal{N}(\mathbf{x}) = \sum_{r=1}^{m} a_r \mathrm{ReLU}(\mathbf{w}_r^\top \mathbf{x} + b_r),$$

it suffices to prove that $f(\mathbf{x}) = \mathrm{ReLU}(\mathbf{w}^\top \mathbf{x} + b)$ is in H^s for all $\mathbf{w} \in \mathbb{R}^d, b \in \mathbb{R}$. Since $\mathrm{ReLU}(a\mathbf{x}) = a\mathrm{ReLU}(\mathbf{x})$ for any $a > 0$, we can assume that $\|\mathbf{w}\|_2 = 1$. Moreover, since the Sobolev spaces are rotationally invariant, we can assume that $\mathbf{w} = (1, 0, \dots, 0)^\top$. Then, f can be written as

$$f(\mathbf{x}) = \mathrm{ReLU}(x_1 + b).$$

If $b \le -1$ or $b \ge 1$, then $f(\mathbf{x})$ is a constant, and thus $f \in H^s(\mathbb{S}^{d-1})$ for all $s \in \mathbb{R}$. We assume $-1 < b < 1$. Then, we have

$$f(\mathbf{x}) = \begin{cases} x_1 + b, & x_1 > -b, \\ 0, & x_1 \le -b. \end{cases}$$

We define the function

$$\mathcal{S}_s(f)(\mathbf{x}) = \int_0^\pi \frac{|\mathcal{I}_t f(\mathbf{x}) - f(\mathbf{x})|^2}{t^{2s+1}} dt,$$

where

$$\mathcal{I}_t f(\mathbf{x}) = \fint_{C(\mathbf{x},t)} f(\boldsymbol{\xi}) d\boldsymbol{\xi}, \qquad C(\mathbf{x}, t) = \{\boldsymbol{\xi} \in \mathbb{S}^{d-1} \mid \arccos(\boldsymbol{\xi} \cdot \mathbf{x}) \le t\}.$$

Here, $\fint_{C(\mathbf{x},t)} f(\boldsymbol{\xi}) d\boldsymbol{\xi} = |C(\mathbf{x},t)|^{-1} \int_{C(\mathbf{x},t)} f(\boldsymbol{\xi}) d\boldsymbol{\xi}$ is the averaged integral, where $|C(\mathbf{x},t)|$ is the Lebesgue measure of $C(\mathbf{x}, t)$. Then, by (Barceló et al., 2020, Thm. 1.1), we have $f \in H^s(\mathbb{S}^{d-1})$ if and only if $\mathcal{S}_s(f)$ is integrable. We now show that $\mathcal{S}_s(f)$ is integrable on both $E_1 = \{\mathbf{x} \in \mathbb{S}^{d-1} \mid x_1 > -b\}$ and $E_2 = \{\mathbf{x} \in \mathbb{S}^{d-1} \mid x_1 < -b\}$ if $s < 3/2$.

First, we define the function

$$h(\mathbf{x}) = x_1 + b.$$

Then, $h \in H^s(\mathbb{S}^{d-1})$. If we can show that

$$\mathcal{S}_s(h - f)(\mathbf{x}) = \int_0^\pi \frac{|\mathcal{I}_t(h - f)(\mathbf{x}) - (h - f)(\mathbf{x})|^2}{t^{2s+1}} dt$$

is integrable on E_1, then we have

$$\int_{E_1} \mathcal{S}_s(f)(\mathbf{x}) d\mathbf{x} = \int_{E_1} \int_0^\pi \frac{|\mathcal{I}_t f(\mathbf{x}) - f(\mathbf{x})|^2}{t^{2s+1}} dt d\mathbf{x}$$

$$\le 2 \int_{E_1} \int_0^\pi \frac{|\mathcal{I}_t h(\mathbf{x}) - h(\mathbf{x})|^2 + |\mathcal{I}_t(h-f)(\mathbf{x}) - (h-f)(\mathbf{x})|^2}{t^{2s+1}} dt d\mathbf{x} \quad (59)$$

$$= 2 \int_{E_1} \mathcal{S}_s(h)(\mathbf{x}) d\mathbf{x} + 2 \int_{E_1} \mathcal{S}_s(h - f)(\mathbf{x}) d\mathbf{x} < \infty.$$

Assume $\mathbf{x} \in E_1$, and let ρ be the minimum angular distance between $\mathbf{x}$ and any point in the set $S = \{\boldsymbol{\xi} \in \mathbb{S}^{d-1} \mid \xi_1 = -b\}$, i.e., $\rho = \min_{\boldsymbol{\xi} \in S} \arccos(\boldsymbol{\xi} \cdot \mathbf{x})$. Then, for $0 < t \le \rho$, we clearly have $\mathcal{I}_t(h - f)(\mathbf{x}) = 0 = (h - f)(\mathbf{x})$. Assume $\rho < t < \pi$. We divide $C(\mathbf{x}, t)$ into two parts C_1 and C_2 up to a Lebesgue null set, where $C_i = C(\mathbf{x}, t) \cap E_i$. Then, $h - f = 0$ on C_1. Next, by Li (2011), we know that the measure of C_2 satisfies[3]

$$\frac{|C_2|}{|C(\mathbf{x}, t)|} = \Theta\left(I\left(\frac{t^2 - \rho^2}{t^2}; \frac{d}{2}, \frac{1}{2}\right)\right) = \Theta\left(B\left(\frac{t^2 - \rho^2}{t^2}; \frac{d}{2}, \frac{1}{2}\right)\right), \qquad t \to \rho^+,$$

where I is the regularized incomplete beta function and B is the incomplete beta function. Here and throughout the proof, the constants in the big-Θ notations are independent of ρ or t, but possibly depend on b and d, which are fixed in the proof. Moreover, we have the formula

$$B\left(\frac{t^2 - \rho^2}{t^2}; \frac{d}{2}, \frac{1}{2}\right) = \frac{[(t^2 - \rho^2)/t^2]^{d/2}}{d/2} F\left(\frac{d}{2}, \frac{1}{2}, \frac{d+2}{2}; \frac{t^2 - \rho^2}{t^2}\right),$$

---

[3]For two functions $\alpha(t)$ and $\beta(t)$, we say $\alpha(t) = \Theta(\beta(t))$ as $t \to \rho^+$ if there exist positive constants C_l, C_r and radius $r > 0$ such that $C_l \beta(t) \le \alpha(t) \le C_r \beta(t)$ for all $0 < t - \rho < r$.

where F is the hypergeometric function that converges to 1 as $t \to \rho^+$ (DLMF, sect. 8.17, sect. 15.2). Hence, we have

$$\frac{|C_2|}{|C(\mathbf{x},t)|} = \Theta\left(\frac{(t-\rho)^{d/2}}{t^{d/2}}\right), \qquad t \to \rho^+. \tag{60}$$

Now, by the way we defined $h - f$, there exist constants $R_1, R_2 > 0$ such that

$$|h-f|(\boldsymbol{\xi}) \le R_1(t-\rho), \qquad \boldsymbol{\xi} \in C_2,$$

$$|h-f|(\boldsymbol{\xi}) \ge R_2(t-\rho), \qquad \boldsymbol{\xi} \in \left\{ \boldsymbol{\zeta} \in C_2 \Big| \min_{\boldsymbol{\theta} \in S} \arccos(\boldsymbol{\zeta} \cdot \boldsymbol{\theta}) \ge \frac{t-\rho}{2} \right\}.$$

This gives us

$$\left| \fint_{C(\mathbf{x},t)} (h-f)(\boldsymbol{\xi})d\boldsymbol{\xi} \right| = \Theta\left(\frac{(t-\rho)^{(d+2)/2}}{t^{d/2}}\right), \qquad t \to \rho^+. \tag{61}$$

Now, we have

$$\mathcal{S}_s(h-f)(\mathbf{x}) = \int_\rho^\pi t^{-2s-1} \mathcal{I}_t(h-f)(\mathbf{x})^2 dt = \int_\rho^\pi t^{-2s-1} \left(\fint_{C(\mathbf{x},t)} (h-f)(\boldsymbol{\xi})d\sigma(\boldsymbol{\xi}) \right)^2 dt$$

$$= \Theta\left(\int_\rho^\pi t^{-2s-1-d}(t-\rho)^{d+2} dt \right) = \Theta(\rho^{2-2s}+1).$$

To integrate $\mathcal{S}_s(h-f)$ over E_1, we first change the coordinates and integrate over $\mathbb{S}^{d-2}$ by fixing a ρ. The resulting integral is still in $\Theta(\rho^{2-2s}+1)$. We then integrate over ρ and the result follows from the fact that a function in $\Theta(\rho^{2-2s}+1)$ is integrable near $\rho = 0$ if and only if $s < 3/2$. This proves $\mathcal{S}_s(h-f)$ is integrable on E_1 if and only if $s < 3/2$. Note that if $\mathcal{S}_s(h-f)$ is not integrable on E_1, then $\mathcal{S}_s(f)$ is neither integrable. This proves the proposition when $s \ge 3/2$.

To see $\mathcal{S}_s(f)$ is integrable over E_2 when $s < 3/2$, we note that f can be rewritten as $\tilde{f} - \tilde{h}$, where $\tilde{f}(\mathbf{x}) = \mathrm{ReLU}(-x_1 - b)$ and $\tilde{h}(\mathbf{x}) = -x_1 - b$. By the same argument, we have that $\mathcal{S}_s(f) = \mathcal{S}_s(\tilde{f} - \tilde{h})$ is integrable on E_2, which completes the proof. $\qquad\square$

E.2 Frequency biasing with a squared Sobolev norm as the loss function

In this section, we prove Theorem 4 on Sobolev training. Recall that we compute the H^s-based loss based on eq. (18).

Proof of Theorem 4. Fix some $0 \le \ell \le L$. We can write

$$\mathbf{H}^\infty \mathbf{P}_s \mathbf{y}^\ell = \sum_{j=0}^{\ell_{\max}} \sum_{p=1}^{N(d,j)} \mathbf{H}^\infty \omega_j \mathbf{a}_{j,p} \mathbf{a}_{j,p}^\top \mathbf{y}^\ell = \sum_{p=1}^{N(d,\ell)} \mathbf{H}^\infty \omega_\ell \mathbf{a}_{\ell,p} \hat{g}_{\ell,p} + \sum_{j=0}^{\ell_{\max}} \sum_{p=1}^{N(d,j)} \mathbf{H}^\infty \omega_j \mathbf{a}_{j,p} e^a_{\ell,j,p}, \tag{62}$$

where $\omega_\ell = (1+\ell)^{2s}$ and we used the fact that

$$\mathbf{a}_{j,p}^\top \mathbf{y}^\ell = \int_{\mathbb{S}^{d-1}} Y_{j,p}(\boldsymbol{\xi}) g_\ell(\boldsymbol{\xi})d\boldsymbol{\xi} + e^a_{\ell,j,p} = \begin{cases} \hat{g}_{\ell,p} + e^a_{\ell,j,p}, & \text{if } \ell = j, \\ e^a_{\ell,j,p}, & \text{otherwise.} \end{cases}$$

Next, we have

$$(\mathbf{H}^\infty \mathbf{a}_{j,p})_i = \int_{\mathbb{S}^{d-1}} K^\infty(\mathbf{x}_i, \boldsymbol{\xi}) Y_{j,p}(\boldsymbol{\xi})d\boldsymbol{\xi} + e^b_{i,j,p} = \mu_j Y_{j,p}(\mathbf{x}_i) + e^b_{i,j,p},$$

where the last equality follows from the Funk–Hecke formula. Hence, the first term in eq. (62) can be written as

$$\left(\sum_{p=1}^{N(d,\ell)} \mathbf{H}^\infty \omega_\ell \mathbf{a}_{\ell,p} \hat{g}_{\ell,p} \right)_i = \sum_{p=1}^{N(d,\ell)} (\mu_j Y_{\ell,p}(\mathbf{x}_i) + e^b_{i,\ell,p}) \omega_\ell \hat{g}_{\ell,p} = \mu_j \omega_\ell g_j(\mathbf{x}_i) + \sum_{p=1}^{N(d,\ell)} e^b_{i,\ell,p} \omega_\ell \hat{g}_{\ell,p}.$$

Moreover, the second term in eq. (62) can be written as

$$\left(\sum_{j=0}^{\ell_{\max}} \sum_{p=1}^{N(d,j)} \mathbf{H}^{\infty} \omega_j \mathbf{a}_{j,p} e_{\ell,j,p}^a \right)_i = \sum_{j=0}^{\ell_{\max}} \sum_{p=1}^{N(d,j)} \omega_j e_{\ell,j,p}^a \left(\mu_j Y_{j,p}(\mathbf{x}_i) + e_{i,j,p}^b \right).$$

Therefore, we have

$$\mathbf{H}^{\infty} \mathbf{P}_s \mathbf{y}^{\ell} = \mu_{\ell} \omega_{\ell} \mathbf{y}^{\ell} + \omega_{\ell} \boldsymbol{\varepsilon}_1^{\ell}, \tag{63}$$

where

$$(\boldsymbol{\varepsilon}_1^{\ell})_i = \sum_{p=1}^{N(d,\ell)} e_{i,\ell,p}^b \hat{g}_{\ell,p} + \sum_{j=0}^{\ell_{\max}} \sum_{p=1}^{N(d,j)} \frac{\omega_j}{\omega_{\ell}} e_{\ell,j,p}^a \left(\mu_j Y_{j,p}(\mathbf{x}_i) + e_{i,j,p}^b \right). \tag{64}$$

Applying eq. (63) recursively, we have

$$(\mathbf{I} - 2\eta \mathbf{H}^{\infty} \mathbf{P}_s)^k \mathbf{y} = \sum_{\ell=0}^{L} (1 - 2\eta \mu_{\ell} \omega_{\ell})^k \mathbf{y}^{\ell} \underbrace{-2\eta \sum_{\ell=0}^{L} \sum_{t=0}^{k-1} (1 - 2\eta \mu_{\ell} \omega_{\ell})^t (\mathbf{I} - 2\eta \mathbf{H}^{\infty} \mathbf{P}_s)^{k-t-1} \omega_{\ell} \boldsymbol{\varepsilon}_1^{\ell}}_{\boldsymbol{\varepsilon}_1}.$$

Now, since $\mathbf{H}^{\infty} \mathbf{P}_s$ is self-adjoint and positive definite in $(\mathbb{R}^n, \langle \cdot, \cdot \rangle_{\mathbf{P}_s})$, by the way we pick η, we guarantee that $\mathbf{I} - 2\eta \mathbf{H}^{\infty} \mathbf{P}_s$ is positive definite in $(\mathbb{R}^n, \langle \cdot, \cdot \rangle_{\mathbf{P}_s})$ and hence

$$\|\mathbf{I} - 2\eta \mathbf{H}^{\infty} \mathbf{P}_s\|_{\mathbf{P}_s} \leq 1 - 2\eta \lambda_0.$$

This gives us $\|\boldsymbol{\varepsilon}_1\|_{\mathbf{P}_s} \leq \sum_{\ell=0}^{L} \mu_{\ell}^{-1} \|\boldsymbol{\varepsilon}_1^{\ell}\|_{\mathbf{P}_s}$, and the result follows from Theorem 1. □

While Theorem 4 captures the frequency biasing in squared H^s loss training up to quadrature errors, analyzing the quadrature errors can be task-specific. Therefore, studying the quadrature rules could be a direction of future research.

F EXPERIMENTAL DETAILS

We now present the details of the three experiments in Section 6.

F.1 LEARNING TRIGONOMETRIC POLYNOMIALS ON THE UNIT CIRCLE

In section 6.1, we train a NN with data derived from sampling a trigonometric polynomial at nonuniform points on the unit circle. The $n = 1140$ nonuniform data points $\{\mathbf{x}_i\}$ for this test are generated by taking the union of three sets of equally spaced points, as shown in Figure 1. The data set $\{(\cos(\theta_i), \sin(\theta_i))\}$ contains 100 equally spaced nodes sampled from $\theta \in (0, 2\pi]$, superimposed with 40 equally spaced nodes sampled from $\theta \in [0, 0.3\pi]$ and 1000 equally spaced nodes sampled from $\theta \in [1.4\pi, 1.8\pi]$ (see Figure 1, left). We construct the quadrature weights c_j by minimizing $\sum_{j=1}^{n} c_j^2$, under the constraints that the c_i's are positive and the quadrature rule is exact on Π_{55}^2. Here, 55 is selected as it is close to the maximum degree such that we can efficiently solve the optimization problem for the quadrature weights.

The experiment consists of two parts. First, we compare the effects of training with the loss function Φ based on eq. (1) against the squared L^2 loss function $\widetilde{\Phi}$ in eq. (3), where

$$\Phi(\mathbf{W}) = \frac{1}{2n} \sum_{i=1}^{n} |\mathcal{N}(\mathbf{x}_i) - g(\mathbf{x}_i)|^2, \qquad \widetilde{\Phi}(\mathbf{W}) = \frac{1}{2} \sum_{i=1}^{n} c_i |\mathcal{N}(\mathbf{x}_i) - g(\mathbf{x}_i)|^2.$$

We define the target function to be

$$g(\mathbf{x}) = \tilde{g}(\theta) = \sum_{\ell=1}^{9} \sin(\ell\theta), \qquad \mathbf{x} = \mathbf{x}(\theta) = (\cos\theta, \sin\theta) \in \mathbb{S}^1,$$

where $\tilde{g}(\theta) = g(\mathbf{x}(\theta))$. We set up two 2-layer ReLU-activated NNs with 5×10^4 hidden neurons in each layer and train them using the same training data and gradient descent procedure, except with different loss functions Φ and $\widetilde{\Phi}$.

Figure 5: Frequency loss for $\ell = 3$ (blue), $\ell = 5$ (red), and $\ell = 9$ (yellow) based on the squared H^s norm as the loss function. Left: $s = -1$; Middle: $s = 0$; Right: $s = 1$. The error bars are generated using the results obtained by executions with thirty different random seeds. In the left figure, the result of one of the thirty executions is omitted because the NN is trapped by a local minimizer that is not a global one, making the NN not converge to the target function.

To evaluate the frequency loss, we collect 100 uniform samples from $\mathcal{N}(\mathbf{x})$ and $g(\mathbf{x})$ and compute the Fourier coefficients $\widehat{\mathcal{N}}(\ell)$ and $\hat{g}(\ell)$ such that functions

$$\mathcal{N}(\mathbf{x}) = \widetilde{\mathcal{N}}(\theta) \approx \sum_{\ell=0}^{30} \widehat{\mathcal{N}}(\ell)e^{i\ell\theta}, \qquad g(\mathbf{x}) = \tilde{g}(\theta) \approx \sum_{\ell=0}^{30} \hat{g}(\ell)e^{i\ell\theta},$$

where $\widetilde{\mathcal{N}}(\theta) = \mathcal{N}(\mathbf{x}(\theta))$. The frequency loss $|\widehat{\mathcal{N}}(\ell) - \hat{g}(\ell)|$ estimates how $g(\mathbf{x})$ is approximated by $\mathcal{N}(\mathbf{x})$ at the frequency ℓ when training with the different loss functions (see Figure 1, middle). In addition, we also train the NN to learn each individual frequency with the training data coming from $g_\ell = \sin(\ell\theta)$ and count the number of iterations it takes to obtain $\widetilde{\Phi}(\mathbf{W}) < 1.0 \times 10^{-3}$ (see Figure 1, right).

The second part of the experiment focuses on NN training with a discretized squared Sobolev norm as the loss function. More precisely, we fix some $s \in \mathbb{R}$ and consider the Sobolev loss function eq. (18). For $\mathbb{S}^1$, we have $N(d, \ell) = 2$ if $\ell > 0$. We take $Y_{\ell,1}(\mathbf{x}) = \sin(\ell\theta)/\sqrt{2\pi}$ and $Y_{\ell,2}(\mathbf{x}) = \cos(\ell\theta)/\sqrt{2\pi}$, where the $\sqrt{2\pi}$ factor is a normalization factor.

We set $\ell_{\max} = 30$ in eq. (18) and learn g with different s values ranging from -1 to 4. For each s, we compute the frequency loss $|\widehat{\mathcal{N}}(\ell) - \hat{g}(\ell)|$ after different numbers of epochs. As s increases, the frequency loss for higher frequencies decays faster (see Figure 5). In particular, we see in Figure 2, the "rainbow" plot, that when $s = -1$, the lower-frequency losses are much smaller than the higher ones after 5000 iterations, while when $s = 3$ the higher frequencies are learned faster than the lower ones.

F.2 LEARNING SPHERICAL HARMONICS ON THE UNIT SPHERE

In section 6.2, we train a NN with data derived from sampling function defined on $\mathbb{S}^2$ at nonuniform points. The training data is a maximum determinant set of 2500 points that comes from the so-called "spherepts" dataset (Wright & Michaels, 2015). In this experiment, the target function is

$$g(\mathbf{x}) = \sum_{\ell=1}^{15} Y_{2\ell,0}(\mathbf{x}),$$

where $Y_{2\ell,0}$ is the normalized zonal spherical harmonic function of degree 2ℓ. Therefore, the spherical harmonic coefficients of g defined in eq. (4) satisfy $\hat{g}_{\ell,p} = 1$ if $p = 0$ and $\ell = 2, 4, \ldots, 30$, and $\hat{g}_{\ell,p} = 0$ otherwise. We then train an NN with the squared H^s norm as the loss function (see eq. (18)) for $s = -1, 0, 2.5$. By Theorem 4, we need $\ell_{\max} \geq L = 30$. We set $\ell_{\max} = 40$ in eq. (18), assuming that the bandwidth L is not known a priori. We observe frequency biasing in this experiment by considering $|\widehat{\mathcal{N}}_{\ell,p} - \hat{g}_{\ell,p}|$ after each epoch for $\ell = 4, 10, 20$. We confirm that low frequencies of g are captured earlier in training than high frequencies when $s = -1$ and $s = 0$ (see Figure 3, left and middle), and that this frequency biasing phenomena can be counterbalanced by taking $s = 2.5$ (see Figure 3, right).

F.3 TEST ON AUTOENCODER

Autoencoders can be used as a generative model to randomly generate new data that is similar to the training data. In this experiment, we use Sobolev-based norms to improve NN training for producing new images of digits that match the MNIST dataset. In our final experiment, we use the same autoencoder architecture as in (Chollet, 2016), except we train the autoencoder with a different loss function (see section 6.3).

Here, for training images $\{\mathbf{x}_i\}$, a standard loss function can be

$$\Phi(\mathbf{W}) = \frac{1}{2} \int \text{dist}(\mathcal{N}(\mathbf{x}), \mathbf{x}) d\mu(\mathbf{x}) \approx \frac{1}{2n} \sum_{i=1}^{n} \text{dist}(\mathcal{N}(\mathbf{x}_i), \mathbf{x}_i),$$

where μ is the distribution of the training images and $\text{dist}(\mathcal{N}(\mathbf{x}_i), \mathbf{x}_i)$ is a distance between the output of the NN given by $\mathcal{N}(\mathbf{x})$ and the image $\mathbf{x}$. We select the distance metric to measure the difference between $\mathcal{N}(\mathbf{x})$ and $\mathbf{x}$ as

$$\Phi(\mathbf{W}) = \frac{1}{2n} \sum_{i=1}^{n} \|\mathcal{N}(\mathbf{x}_i) - \mathbf{x}_i\|_F^2, \tag{65}$$

where $\|\cdot\|_F$ denotes the matrix Frobenius norm. The distance metric in eq. (65) can be viewed as a discretization of the continuous L^2 norm. That is, if one imagines generating a continuous function $x : [0,1]^2 \to [0,\infty)$ that interpolates an image as well as a function that interpolates the NN, then

$$\frac{1}{N_{\text{pixel}}} \|\mathcal{N}(\mathbf{x}) - \mathbf{x}\|_F^2 \approx \iint |\mathcal{N}(x)(y_1, y_2) - x(y_1, y_2)|^2 dy_1 dy_2 = \|\mathcal{N}(x) - x\|_{L^2}^2,$$

where N_{pixel} is the total number of pixels of the image $\mathbf{x}$. In this continuous viewpoint, the H^s norm is given by (assuming that the continuous interpolating functions x and $\mathcal{N}(x)$ are constructed with periodic boundary conditions)

$$\|\mathcal{N}(x) - x\|_{H^s}^2 = \int (1 + |\xi|^2)^s |\widehat{\mathcal{N}(x)}(\xi) - \widehat{x}(\xi)|^2 d\xi \approx \|\mathbf{S}_s \circ \left(\mathbf{F}_l \left(\mathcal{N}(\mathbf{x}) - \mathbf{x}\right) \mathbf{F}_r^\top\right)\|_F^2, \quad (66)$$

where $\mathbf{F}_l, \mathbf{F}_r$ are the left and right 2D-DFT matrices, respectively, $(S_s)_{j\ell} = (1 + j^2 + \ell^2)^{s/2}$, and '$\circ$' is the Hadamard product. Hence, if we define $\text{vec}(\mathbf{A})$ to be the vector obtained by reshaping a matrix $\mathbf{A}$ using the column major order, then we have

$$\|\mathbf{S}_s \circ \left(\mathbf{F}_l \left(\mathcal{N}(\mathbf{x}) - \mathbf{x}\right) \mathbf{F}_r^\top\right)\|_F^2 = \|\text{diag}(\text{vec}(\mathbf{S}_s))(\mathbf{F}_r \otimes \mathbf{F}_l)\text{vec}(\mathcal{N}(\mathbf{x}) - \mathbf{x})\|_2^2,$$

where $\otimes$ is the Kronecker product of two matrices. Setting $\mathbf{J}_s = \text{diag}(\text{vec}(\mathbf{S}_s))(\mathbf{F}_r \otimes \mathbf{F}_l)$, the loss function in our NN training can be written as

$$\Phi_s(\mathbf{W}) = \frac{1}{2n} \sum_{i=1}^{n} \|\mathbf{J}_s \text{vec}\left(\mathcal{N}(\mathbf{x}_i) - \mathbf{x}_i\right)\|_2^2 = \frac{1}{2n}(\mathbf{u} - \mathbf{y})^\top (\mathbf{I} \otimes \mathbf{J}_s^\top \mathbf{J}_s)(\mathbf{u} - \mathbf{y}), \tag{67}$$

where $\mathbf{I}$ is the n-by-n identity matrix and $\mathbf{u}, \mathbf{y}$ are the vectors of length $n \times N_{\text{pixel}}$ given by $\mathbf{u} = \left(\text{vec}(\mathcal{N}(\mathbf{x}_1))^\top, \ldots, \text{vec}(\mathcal{N}(\mathbf{x}_n))^\top\right)^\top$ and $\mathbf{y} = \left(\text{vec}(\mathbf{x}_1)^\top, \ldots, \text{vec}(\mathbf{x}_n)^\top\right)^\top$. Hence, the discrete NTK matrix is given by $n^{-1}\mathbf{H}^\infty(\mathbf{I} \otimes \mathbf{J}_s^\top \mathbf{J}_s)$, where the (i,j)th sub-block is $\mathbf{H}_{ij}^\infty = \left\langle \frac{\partial \text{vec}(\mathcal{N}(\mathbf{x}_i; \mathbf{W}))}{\partial \mathbf{W}}, \frac{\partial \text{vec}(\mathcal{N}(\mathbf{x}_j; \mathbf{W}))}{\partial \mathbf{W}} \right\rangle$ for $i, j = 1, \ldots, n$. Here, $\left\langle \frac{\partial \text{vec}(\mathcal{N}(\mathbf{x}_i; \mathbf{W}))}{\partial \mathbf{W}}, \frac{\partial \text{vec}(\mathcal{N}(\mathbf{x}_j; \mathbf{W}))}{\partial \mathbf{W}} \right\rangle$ is interpreted as the N_{pixel}-by-N_{pixel} matrix whose (i',j')th entry is $\left\langle \frac{\partial [\text{vec}(\mathcal{N}(\mathbf{x}_i; \mathbf{W}))]_{i'}}{\partial \mathbf{W}}, \frac{\partial [\text{vec}(\mathcal{N}(\mathbf{x}_j; \mathbf{W}))]_{j'}}{\partial \mathbf{W}} \right\rangle$. This means that the frequency biasing behavior during NN training is directly affected by the choice of s. We remark that while eq. (67) is a mathematically equivalent expression for the loss function that allows us to easily express the NTK, in practice, we implement the loss function based on eq. (66) using a 2D FFT protocol.

We use the same autoencoder architecture as in (Chollet, 2016), except with the loss function in eq. (67) for $s = -1, 0, 1$. We train the autoencoder using mini-batch gradient descent with batch size equal to 256. We first pollute the training images with low-frequency noise and train the NN, hoping that the trained NN will act as filter for the noise. We see that training the NN with eq. (67) for $s = 1$ gives us the best results due to the high-frequency biasing induced by the

choice of the loss function. Although $\mathbf{H}^\infty$ is low frequency biasing, the high-frequency biasing of $\mathbf{J}_s^\top \mathbf{J}_s$ dominates for sufficiently large s. In that case, the low-frequency noise barely changes the training in the earlier epochs as the low-frequency components of the residual correspond to small eigenvalues of $\mathbf{H}^\infty(\mathbf{I} \otimes \mathbf{J}_s^\top \mathbf{J}_s)$. Similar results are discussed in (Engquist et al., 2020) and (Zhu et al., 2021) in the inverse problem and image processing contexts, respectively.

The opposite phenomenon occurs when we add high-frequency noise (see Figure 4, bottom row). Since $\mathbf{H}^\infty$ by itself makes the NN training procedure bias towards low-frequencies, the output for $s = 0$ does already filter high-frequency noise. Since $\mathbf{J}_s^\top \mathbf{J}_s$ for $s < 0$ further biases towards low-frequencies, one can obtain better high-frequency filters. We observe that the best denoising results for the autoencoder comes from selecting $s = -1$ (see Figure 4, bottom row).

G COMPUTATION OF QUADRATURE WEIGHTS

In practice, the training dataset usually does not come with a carefully designed quadrature rule. Hence, we inevitably need to compute a set of quadrature weights before training the NN. In this section, we briefly discuss methods for computing positive quadrature weights.

Given a set of points $\{\mathbf{x}_i\}_{i=1}^n$ on $\mathbb{S}^{d-1}$, we wish to construct a quadrature rule so that

$$I_n(f) := \sum_{i=1}^n c_i f(\mathbf{x}_i) \approx \int_{\mathbb{S}^{d-1}} f(\mathbf{x})d\mathbf{x}$$

for sufficiently smooth f, where $c_i > 0$ are positive quadrature weights. One approach that could give us a very accurate quadrature rule is to guarantee that

$$I_n(f) = \int_{\mathbb{S}^{d-1}} f(\mathbf{x})d\mathbf{x}, \qquad f \in \Pi_\ell^d, \tag{68}$$

where $\dim(\Pi_\ell^d) \le n$. The one-dimensional case of such quadrature rules was studied in (Austin & Trefethen, 2017; Yu & Townsend, 2022) and the general higher-dimensional case was analyzed in (Mhaskar et al., 2000; Dai & Xu, 2013). Given any dataset $\{\mathbf{x}_i\}_{i=1}^n$ and ℓ so that $\dim(\Pi_\ell^d) \le n$, one cannot guarantee the existence of a positive quadrature rule satisfying eq. (68) (Mhaskar et al., 2000; Dai & Xu, 2013), even when the distribution of $\{\mathbf{x}_i\}_{i=1}^n$ is very regular (Yu & Townsend, 2022). On the other hand, by choosing ℓ to be small, we can eventually find an ℓ for which eq. (68) holds. When such a positive quadrature rule exists, Mhaskar et al. (2000) proposed to solve the following feasible constrained quadratic program

$$
\begin{aligned}
\min_{c_i} \quad & \sum_{i=1}^n c_i^2 \\
\text{s.t.} \quad & c_i > 0 \quad \forall 1 \le i \le n, \\
& \sum_{i=1}^n c_i Y_{j,p}(\mathbf{x}_i) = \int_{\mathbb{S}^{d-1}} Y_{j,p}(\mathbf{x})d\mathbf{x} \quad \forall 0 \le j \le \ell, 1 \le p \le N(d,j).
\end{aligned}
$$

While eq. (68) gives us guarantee on the accuracy of the quadrature rule (provided ℓ is not too small), it is not always practical to compute the quadrature weights in this way. Indeed, if d is large, then we need tremendous amount of points to guarantee that $\dim(\Pi_\ell^d) \le n$ even for a small ℓ. Also, if we have too many data points, then the quadratic program can get infeasible to solve. Hence, we need some other methods for computing quadrature weights that, albeit less accurate, can be applied more cheaply to general datasets. One of the many possible approaches is to do kernel density estimation (Rosenblatt, 1956; Parzen, 1962). To do so, we fix a positive kernel $\mathcal{K}(\mathbf{x}, \mathbf{y}) = \mathcal{K}(\arccos(\mathbf{x}^\top \mathbf{y}))$ defined on $\mathbb{S}^{d-1} \times \mathbb{S}^{d-1}$. A common choice of $\mathcal{K}$ can be the Gaussian density function of standard deviation 1 centered at 0. For each $h > 0$, we then define a function p_h on $\mathbb{S}^{d-1}$ by

$$p_h(\mathbf{x}) = \sum_{i=1}^n \mathcal{K}\left(\frac{\arccos(\mathbf{x}^\top \mathbf{x}_i)}{h}\right).$$

The bandwidth h is a hyperparameter, and with an appropriate h, the function p_h is an (unnormalized) estimate of the density function of the distribution of nodes. Hence, by setting

$$c_i = A_d \frac{p_h^{-1}(\mathbf{x}_i)}{\sum_{j=1}^n p_h^{-1}(\mathbf{x}_j)}, \tag{69}$$

we obtain a positive quadrature rule that approximates the integral of smooth functions on $\mathbb{S}^{d-1}$.