Enhanced Adaptive Optics Control with Image to Image Translation

Abstract

We aim to significantly enhance the science return of astronomical observatories, and in particular giant terrestrial optical telescopes. Observatories employ Adaptive Optics (AO) systems in order to acquire high sensitivity diffraction limited images of the sky. The incumbent "workhorse" for control of AO systems employs a linear real-time controller in a closed loop, with sensing of state performed via a (*Shack-Hartmann*) wavefront sensor (WFS). The actuators of a *deformable mirror* (DM) are driven, with the action performed in each iteration having a continuous representation as an array of DC voltages. The typical control regime is practical and scalable, nonetheless, there remains a residual uncompensated turbulence that leads to optical aberrations limiting the class of scientific assets that can be acquired. We have developed and trained a translational GAN model that accurately estimates residual perturbations from WFS images. Model inference occurs in 0.34 milliseconds using off-the-shelf GPU hardware, and is applicable for use in AO control where the control loop might be running at 500Hz. We develop an AO control regime with a second controller stage actuating a second DM controlled in an open loop according to the estimated residual turbulence. Using the open-source *COMPASS* tool for simulation, we are able to significantly improve the performance using our new regime.

1 INTRODUCTION

Adaptive Optics (AO) systems are an important component of astronomical imaging for large ground based telescopes, enabling the capture of high contrast images of faint objects in space. Aberrations due to Earth's atmospheric turbulence are a significant impediment to deep-space imaging, so the ability to estimate and compensate is critical. The scale of data requirements for this estimation problem increases quadratically with the telescope diameter, an ongoing problem as astronomers build larger telescopes to capture light from ever fainter objects, such as exoplanets and distant galaxies.

An AO system contains three main components: *(i)* a Deformable Mirror (DM) with a reflective surface that can be adjusted with an array of actuators to counteract some of the wavefront phase aberrations, *(ii)* a Wave Front Sensor (WFS) that collects information about the wavefront phase, and *(iii)* a controller that interprets the wavefront sensor observations and computes a control action to drive actuators to update the DM state. Wavefront phase estimation is required because atmospheric turbulence is a stochastic process typically evolving over a few milliseconds time frame. The real-time control of an instrument's mirror incorporates estimation at high-frequency – e.g. 500Hz. The WFS is used to capture the instantaneous state of the phase into intensity variations in an image. In the case of the Shack-Hartmann concept, the telescope aperture is split into sub-regions, called sub-apertures, and an image of the reference guide source is created for each of these sub-apertures and captured by a camera. A centroider algorithm is then used to estimate the spot displacements, in each of these sub-apertures, with respect to a reference position. These displacements are directly related to the local slopes of the wavefront [Roddier, 1999].

Existing real-time closed-loop mirror control uses displacement information. A key drawback is that all such control regimes neglect non-linear, high-order wavefront information captured on the WFS. This is an important limitation of existing instruments. It is highly desirable that non-linear information is available in real-time. This enables the conception of novel control regimes, to increase performance of the AO system and thereby the image quality at the focus of the telescope.

Submitted to the 38th Conference on Uncertainty in Artificial Intelligence (UAI 2022). **To be used for reviewing only**.

1.1 CONTRIBUTIONS

Building on a translational GAN network architecture motivated in a range of computer vision applications, we have developed and evaluated: *(i)* A new method for real-time phase estimation from wavefront sensing data in AO, and *(ii)* a new robust control regime that is able to significantly enhance instrument performance by leveraging our innovative approach to phase estimation. Compared to the model-based state-of-the art, our network-based approach to phase estimation is: *(i)* fast enough for use in real-time control, *(ii)* avoids strong (unrealistic) assumptions about the nature of the stochastic process driving atmospheric turbulence and system geometry, and *(iii)* conceptually simple and based on established machine learning technology. Specifically, we use a translational CNN to infer the phase directly from the Shack-Hartman WFS image. Our method takes advantage of high frequency information available in the Shack-Hartman WFS that is not accessible with existing estimation methods. On the control side, we develop a *GAN Assisted Open Loop* (GAOL) AO design. To our knowledge this is the first AO concept to apply accurate wavefront estimates in a way that is amenable to real-time control of AO systems with real-world operating parameters. We expose higher-order information in the control loop via our phase estimates, enabling control of DMs with relatively high actuator counts, and thereby enable AO systems that effectively compensate for high-frequency turbulence. Our simulation experiments demonstrate that our approach robustly leads to substantially improved performance—specifically a 10% improvement in *Strehl ratio*, which translates to an improvement which materially adds to the range of science tasks that an instrument can perform—in a range of atmospheric conditions when compared to incumbent AO methods.

The paper is structured as follows. First, we discuss the AO setting and current methods. Secondly, we describe COMPASS – a state-of-the-art GPU accelerated AO simulation package. Thirdly, we describe our approach to using image-to-image CNNs for phase recovery in our setting. Fourthly, we describe current methods in wavefront phase estimation and control methods for AO systems. Finally we present a detailed analysis of experimental results comparing our approach to a classical AO systems control approach.

2 ADAPTIVE OPTICS BACKGROUND

The goal of AO is to obtain a sharp image of an observed target. Any perturbation of the incoming wavefront creates aberrations in the image, which reduces the contrast of the observation – this translates as blur. A perfectly unaberrated image of a point source obtained through a circular aperture telescope will produce a *point spread function* (PSF) that is an *Airy disk* – i.e., image quality and resolution are only limited by the diffraction of the telescope aperture. Aberrations

(e.g., from turbulence) perturb the wavefront by introducing optical path differences between the different points of the telescope aperture, affecting the PSF, and therefore image quality.

The PSF is related to the wavefront phase as the absolute square of the Fourier transform of the complex electromagnetic field. This is an important relationship and is not directly invertible from PSF to phase, shown in Equation 1.

$$\text{PSF} = |\mathcal{F}(\text{amplitude} \cdot \text{e}^{\text{i} \cdot \text{phase}})|^2 \qquad (1)$$

In an AO system a DM is controlled in real-time to compensate for aberrations. The compensation made using incumbent control regimes is imperfect, leading to residual error. The residual error (AO loop error) is made up of several contributing sources and is dealt with in detail through an error budget estimation. The error budget describes the total AO loop error in terms of components for Bandwidth error, Anisoplanatism, Aliasing, Noise, Wavefront measurement error, mode filtering and fitting error. All of these error sources contribute to a decrease in image quality at the output of the telescope, and are described and incorporated into the state-of-the-art residual wavefront error estimation by Ferreira et al. [2018a].

The Shack-Hartman WFS used in AO systems is designed to take the wavefront phase information and encode it as an intensity image distributed over small sub-regions of the aperture. It does this with an array of small lenslets that focus the aperture sub-region onto a sensor, creating a spot that is tilted off axis by the average slope of the incoming wavefront sub-region in two dimensions. Figure 1 shows the one dimensional case and how the aberrated wavefront of a sub-region moves the focal point on the sensor off center. This displacement gives an indication of the average slope of the area of the wavefront covered by the sub-aperture. From the sensor image for all sub-apertures, centroider algorithms are used to find the centre of the spots and so a granular map of slopes is created and passed to the DM control system.

Figure 1: Shack-Hartmann WFS lenslet diagram showing displacement of spots due to wave from purturbations

Slope measurements made from centroider data are inherently lossy due to limits on sub-aperture size. Non-linear information is lost when the algorithm picks the centroid of

Figure 2: Shack-Hartmann WFS lenslet spots

the spot for each sub-aperture, reducing the image to points on an x, y plane. Figure 1 shows the off axis measurements (Δx) that are used to measure the wavefront sub-aperture slopes, where the higher order wavefront information is lost. The size of the lenslets limits the spatial frequency that can be measured, behaving like a low pass filter.

The sensor image captured at each subaperture corresponds to a low fidelity PSF, where the captured irregular patterns of light intensity correspond to a representation of higher-order information about the wavefront profile. A depiction of such patterns is given in Figure 2, which shows a portion of a simulated Shack-Hartman WFS image. For the intuition about what is being lost using centroider algorithms, Figure 1 gives a simplified 1D schematic of the wavefront, lenslet array and sensor image. The dashed lines drawn in the turbulent wavefront above lenslets represent the gradient measured by a centroider, here clearly missing out important details about high frequency turbulence. It remains an open question in astronomy, to quantify exactly how much information is being lost in this setting depending on the actual instrument design (e.g. number of sub-apertures, number of pixels per sub-apertures, measurement wavelength, etc.) Model-based approaches to phase retrieval rely on detailed physical models to recover phase information from centroider slopes only – i.e. the irregular patterns from the WFS are not used. Our approach is model free, using precisely that information to recover phase.

AI for Adaptive Optics: AO systems have been used to compensate for atmospheric turbulence since the late 1980s, when the available computer technology was first able to match the requirements for controlling the available DM technology. Since then, efforts to improve wavefront estimates have been ongoing both in model-based statistical estimation and other techniques using advances in Artificial Intelligence.

Some AI based techniques for improving AO systems have been investigated with many studies using slope estimates from centroider data [Swanson et al., 2021] and typically made wavefront estimates by predicting the weights of a small number of low order, linearly independent Zernike modes [Guo et al., 2006; Weddell and Webb, 2007] that can be added to create the wavefront phase. Using the slope

estimates from centroider algorithms limits WFS data to low order information, as these wavefront slope estimates filter out higher order information captured on the Shack-Hartman WFS. Sensor-less methods with Convolutional Neural Networks (CNNs) [Guo et al., 2019] make estimates directly from the PSF in the AO loop, rather than from a WFS, can avoid the loss of some higher order information but are best suited to low turbulence conditions and small telescope settings.

COMPASS Simulation Software: The COMPASS AO simulation software [Ferreira et al., 2018b] simulates atmospheric conditions, telescope and AO system to create accurate simulated residual wavefront and WFS images used to train our CNNs. COMPASS is a GPU accelerated AO loop simulator with a comprehensive API that allows simple integration with Python code. Highly detailed parameter information can be input to generate specific atmospheric conditions and other AO loop characteristics such as sensor noise and control loop delay. This is perfect for generating training data for CNNs and also for testing ranges of conditions for inference performance with trained models. [1]

3   AO CONTROL

Typical AO systems consist of three main components, i.e. the DM, WFS and controller. Such systems have many possible configurations that are designed for purpose. The incumbent design that we are using for a benchmark is a Single Conjugate Adaptive Optics (SCAO) system with a Shack-Hartman WFS [2]. The command signal, u_k, applied to the DM at time $t = kT$ (where T is the AO control period) is derived from the WFS slope vector s_k, and the previous DM commands $u_{k-1}, u_{k-2}, \cdots, u_{k-d}$, where d is the AO control loop latency in frames. For the remainder of this paper, we assume a 2-frame delay (without loss of generality). This delay is the source of *bandwidth error* in an AO system, and is the combination of several effects: integration time on the WFS camera, frame transfer and read-out on the detector, pixel data transfer to the Real-Time Control (RTC), RTC pure delay, DM rise time and DM zero-order hold.

For its convenient stability properties and robust performance, we employ a *Pseudo-Open-Loop Control* (POLC) scheme [Ellerbroek and Vogel, 2003; Piatrou and Gilles, 2005], which has a recursive control law in the form:

$$u_0 = \mathbf{0},$$
$$u_k = (1 - g)u_{k-1} + gRDu_{k-2} + gRs_k, \qquad (2)$$

where $1 - g$ and g are the input and output coefficients (respectively) of a first-order IIR filter, and can be tuned to obtain a desired temporal cut-off frequency [Cranney

---

[1]See Appendix for sample of the simulated data.

[2]See Appendix for AO loop diagram

et al., 2020]. The matrix D is the interaction matrix between the WFS slopes and the DM commands. The matrix R is the linear reconstructor matrix, which takes WFS slopes, and computes the (filtered) commands that would optimally regulate those measurements.

Our GAOL Control Regime: In the following section, we develop a nonlinear network-based method to extract high resolution wavefront estimates from closed-loop WFS pixel data (beyond slope-only estimation). This is the basis of our GAOL control regime, in which such wavefront estimates are projected onto a DM in order to provide an improved wavefront correction at a higher order than possible using a linear slope-based controller.The most direct method to evaluate the performance of such a scheme in AO is to add a second DM (with a high actuator density) before the science camera, but after the first DM and WFS, and to control this second DM in open-loop using the output of the nonlinear estimator. The use of an open-loop DM has several advantages and disadvantages that will not all be discussed in detail here. The most notable are that the second DM has guaranteed *bounded-input bounded-output* stability, assuming that actuator creep is negligible, coming at the financial cost and opto-mechanical burden of having multiple DMs.

In principle the control of all DMs could be done on an orthogonalised set of modes, with the modes able to be linearly controlled put on the first DM, and the remainder allocated to the second DM (i.e., a *Woofer / Tweeter* pair), [Gavel and Norton, 2014]. For our GAOL approach, we instead match the first DM to the WFS geometry, and increase the resolution of the second DM beyond this limit. In future work we will investigate alternative mode-optimised control schemes.

The closed-loop linear control law in this regime remains identical to Eq. (2), and the open-loop nonlinear control law operates in parallel with the following structure:

$$u_0^{\mathrm{nl}} = \mathbf{0},$$
$$u_k^{\mathrm{nl}} = (1 - g^{\mathrm{nl}})u_{k-1}^{\mathrm{nl}} + g^{\mathrm{nl}}R^{\mathrm{nl}}\hat{y}_k, \tag{3}$$

where u_k^{nl} is the nonlinear command signal to be applied to the second DM, $\hat{y}_k$ is the high resolution network-derived estimate of the residual phase error after the first mirror has acted, R^{nl} is the high resolution reconstructor which takes the estimated phase and projects to the DM space, and $1 - g^{\mathrm{nl}}$ and g^{nl} are the input and output coefficients (respectively) of a first-order IIR filter (*cf.* Eqn. (2)).

4 GAN FOR PHASE ESTIMATION

We estimate the residual phase by adapting an artificial neural network for Image to Image translation [Isola et al., 2017], where Figure 3 gives a visual breakdown of the network. This design is a conditional Generative Adversarial Network (cGAN), with the translational encoding performed by a UNet and the adversarial training performed using a Markov discriminator. The network learns to take an input of a Shack-Hartman WFS image and output the inferred wavefront phase.

To motivate the UNet generator component of the network, it can be compared to the similar and widely used auto-encoder – a CNN – that is used for image transformation. An auto-encoder encodes an image to some latent variable through successive convolutional layers, and then through deconvolutional steps generates a new image from the latent variable. An auto-encoder learns to transform images minimising a reconstruction loss and can be used for several applications, however for our purposes it is not ideal as it is deterministic by design and we want to preserve some structure from the original image for our application, such as spatial relationships for translation. The UNet design adds skip connections, where information from layers of the encoder is transported to corresponding decoder layers via concatenation, allowing for some structure from the input image to be preserved. Since we aim to translate WFS images from sensor data with incomplete information we cannot map from image to image in a deterministic manner as there will be many possible wavefront phase images that could be represented by each input image. To avoid the deterministic nature of the auto-encoder (and UNet) structure, some stochastic process needs to be added to allow for variability in the output. This is accomplished by introducing noise to the network via network dropout (z), where Gaussian noise is ineffective because this approach learns to filter it.

Considering the Variational Auto-Encoder (VAE) as an alternative - it also has the ability to create varied translations from an input image and does not have deterministic outcomes due to encoding and sampling from distributions. The output images from a VAE tend to be blurry and faint, which is not ideal for our application, as we find this occurs in important regions of the wavefront phase. The loss function for a VAE must be carefully designed, which additionally very difficult to do in practice. By contrast, a GAN [Goodfellow et al., 2014] has the benefit of learning a loss function, and so simplifies the loss design problem associated with VAEs, as well as tending toward sharper output images, while adding complexity to the network with the addition of a CNN classifier forming the discriminator network that is trained simultaneously with the generator.

A *conditional* GAN improves the performance of the GAN by including a 'semantic-image' in the discriminator as a paired image with either the "real" or "fake" image, which acts as a label for the distribution generated, adding supervision which further improves the sharpness and accuracy of the translated image. The discriminator in Figure 3 is a PatchGAN discriminator, also known as a Markov discrimi-

nator [Li and Wand, 2016]. This discriminator architecture operates by classifying local image regions, and is broadly motivated in computer vision applications due to the speed of inference (i.e. local inference is relatively fast), and the quality of PatchGAN architectures in preserving complex image detail, such as texture. The discriminator component is a convolutional classifier, trained simultaneously with the generator, with the objective to maximise the value of Eq. 4.

The overall objective function (Eq. 5) combines the cGAN loss (Eq. 4), with the $L1$ reconstruction loss terms (e.g., of the form in Eq. 6) that provide strong guidance to learning of low frequency structure. Note that a second reconstruction loss term is added in Eq. 5 to reinforce the reconstruction loss where the network underestimates the upper and lower extreme phase values G_M (or G 'masked'). These regions of the wavefront with the largest perturbations substantially impact the important metrics in our setting, and our ablation testing of this parameter shows this term is required.

The approach is to simultaneously train: *(i)* a generator, $G(x, z)$, that models the distribution of wavefront phases consistent with the input WFS image x – i.e. z is a noise term, specifically dropout noise, and *(ii)* a discriminator, $D(x, y)$, that estimates the probability that a pair (x, y), comprising a wavefront phase image y and a corresponding WFS image x, are "real".

$$\mathcal{L}_{cGAN}(G, D) = E_{x,y}[logD(x,y)]$$
$$+ E_{z,x}[log(1 - D(x, G(x,z)))] \quad (4)$$

$$G^* = \arg\min_G \max_D \mathcal{L}_{cGAN}(G, D)$$
$$+ \lambda\mathcal{L}_{L1}(G) + \lambda_M\mathcal{L}_{L1}(G_M) \quad (5)$$

$$\mathcal{L}_{L1}(G) = E_{x,y,z}[|||y - G(x,z)||_1] \quad (6)$$

Figure 3: cGAN architecture – UNet / PatchGAN

Data Transformations: The raw data from astronomical instruments and simulators requires some transformation to be amenable to the translational architecture we have just discussed. First, the piston mode—i.e., a constant phase shift across the full aperture—is removed from the residual phase data, since it is not measured by the WFS. This is done by subtracting the average value of the wavefront phase that is inside the pupil from the phase array. Second, the residual phase data is normalised to sit in the range $[0, 1]$ by dividing through by a constant value so that the

amplitude can be restored by multiplying any inferred image from the network by the same constant. The normalisation factor is a tuning parameter, with high values scaling small wavefront errors too much, leading to mode collapse. When normalise perfectly, so the largest value in the training data is exactly 1, we find the trained network does not perform well in generalisation evaluations – For example, where we infer a residual phase in turbulence unseen during training. In our work we have set this factor to 10, leaving some headroom over the minimum required value, apprx. 7. The WFS image is also normalised, again dividing by a constant value which is slightly above the maximum. The WFS scale is preserved because the WFS amplitude information, along with the shape of the WFS spots, is the additional nonlinear information captured using our estimation method. In all cases our networks use a constant scaling factor of 1.2 million for WFS images. This value is chosen according to the magnitude of the guide star, with our simulations using a fixed guide of magnitude 10.

5 EXPERIMENTAL RESULTS

COMPASS Parameters: Parameters for simulation were selected to demonstrate performance for realistic large telescope AO loop scenarios. The degree of turbulence is defined by the so-called Fried parameter, r_0, which is a measure of the coherence scale of the turbulence [Roddier, 1999] and depends on the wavelengths we are observing. Typically the real-world operating conditions for r_0 are in the range of $0.16m$ at visible light wavelengths for the lower range of atmospheric turbulence to $0.05m$ for extreme conditions. For the purposes of this study we have selected a typical r_0 value of $0.10m$ for GAOL design analysis and a range from 0.06 to 0.16 for robustness testing to atmospheric turbulence.

AO loop data has been simulated for a typical wind speed of 10 ms^{-1}, and 50000 sample image pairs each from data generated with r_0 values in the range $[0.093, 0.15, 0.20, 0.25, 0.30, 0.35, 0.40]$ to provide the network with a range of turbulence scenarios to learn from to aid robustness for estimation in variable atmospheric turbulence that would be expected for on-sky operating conditions. The upper limit of 0.093 was selected as it corresponded with a pupil size of 512 pixels. The training and evaluation atmospheres are different, so when interrogating network model performance, in a control setting below and otherwise, we use simulations that are seeded differently, and therefore are of atmospheres not seen during training.

GAN Network Parameters: We adapted the network architecture and code from Isola et al. [2017] to use our revised loss regime. Both Generator and Discriminator networks used 64 filters. The Generator performs better with 64 filters over trials run with 32 or 16, however this comes with a computational cost as the number of parameters is sig-

nificantly increased which in turn increases training time and hardware memory requirements. Our training dataset is generated using COMPASS, and consists of $350,000$ image pairs. In training these are selected at random and we use a batch size of 1.

Loss parameters were manually optimised for our setting, and indeed we require a second loss term. The loss regimes from the literature lead to models that underestimate extreme maximum and minimum phase, and this has substantial repercussions in our application. Our method has a second L1 loss term, which increases the weight of L1 loss for regions of phase screens with boundary values. This extends Equation 5 with the additional masked L1 loss term where G_M defines the region of extremes masked in the generated image G, and λ_M is the weighting coefficient for the added masked loss term. All experimental results in this paper use a single trained network with hyper-parameters $\lambda = 150$ and $\lambda_M = 30$.

5.1 AO LOOP SIMULATIONS

One of the benefits of the GAOL design we propose is the simplicity in extending a typical SCAO linear closed controller by adding a second DM before the science camera. This mirror is controlled by the estimates from the GAN and operates in open loop, i.e, the effect of the second DM is not fed back to the closed loop. For ease of reference we will refer to the first DM as the 'Woofer' DM, in reference to the low order information it corrects for, and the 'Tweeter' DM that is driven by the GAN estimates that allow for high order corrections [Gavel and Norton, 2014].

Figure 4: GAOL AO Loop diagram

Referring to Figure 4, the simulated GAOL AO system consists of a linear controller in closed loop operation, to which we add a second DM 'Tweeter' and controller before the science camera (highlighted). Our translation network makes estimates that include high order wavefront information that is able to drive the Tweeter DM with a higher number of actuators but still from the same WFS image that is used by

the closed loop linear control section of the system.

For our experiments we contrast the performance of the GAOL design against the Linear controller, with the Tweeter DM removed, by varying the number of actuators to take advantage of the higher order information captured. As AO loops take time to stabilize, we run each experiment for 2000 iterations (4 seconds) before recording the *long exposure* (LE) SR from COMPASS. The average RMS wavefront error can be estimated from the LE SR, given simulation parameters shown in Table 3.

5.2 EVALUATION METRICS

For the purposes of evaluating the performance of GAOL control we choose a benchmark of the incumbent SCAO control regime that is easily simulated with COMPASS. Contrasting the performance of our novel control variants in terms of Strehl Ratio (SR) and RMS wavefront error (RMS WFE) will demonstrate relative performance in industry specific metrics. The realisation of turbulence for each simulation is identical, so performance can be compared directly.

The SR measures the light intensity at the core of the PSF relative to a diffraction limited PSF, so a SR of 100% implies an aberration-free image. The RMS WFE is independent of imaging wavelength, and determines the quantity of residual wavefront phase of a given wavefront. A RMS WFE of 0 nanometres (nm) implies an aberration-free wavefront, which produces an aberration-free image. Comparisons of RMS WFE (and relative boost) are calculated as discussed in Ross [2009].

5.3 RESULTS AND ANALYSIS

The GAOL method is a two step process, leveraging the incumbent closed loop linear controller that relies on slope measurements through centroider techniques on the Shack-Hartmann WFS image. The phase estimate from the slope measurements is then used to find a control solution to drive the closed loop Woofer DM state. The GAOL method extends this AO system taking the closed loop WFS image using the GAN to infer the residual phase and from the inferred wavefront command a second (Tweeter) DM state to further reduce the WFE. In this way, we can keep a closed loop residual phase that is unaffected by the GAOL open loop control for future iterations of the AO loop.

To demonstrate the accuracy of the two phase estimates, Figure 5 shows for some AO loop iteration the true residual phase (top-left) seen by the WFS, after interacting with the Woofer DM. The two estimates are made from the WFS observation (top-right) – one from the centroider slopes (mid-right) and the other inferred using the GAN to generate a phase estimate (mid-left). Each of these phase images is shown with the phase error by subtracting the true phase and

	GAN Control		Oracle Control	
Method	LE Strehl @ 1650 nm	RMS WFE Boost (nm)	LE Strehl @ 1650 nm	RMS WFE Boost (nm)
Linear closed-loop	62.08%	0	73.49%	0
GAOL +0 (17x17)	67.11%	73.31	73.49%	0
GAOL +1 (18x18)	69.63%	88.97	75.47%	42.85
GAOL +3 (20x20)	70.47%	93.49	78.84%	69.61
GAOL +7 (24x24)	72.22%	102.15	83.61%	94.33
GAOL +15 (32x32)	73.10%	106.15	88.75%	114.07
GAOL +31 (48x48)	71.98%	101.01	92.82%	126.91

Table 1: GAN Assisted Open Loop performance by configuration and actuator count, fixed r_0 of 0.10m (RMS-WFE Boost for GAOL measured from first row, Oracle Control RMS-WFE Boost relative to first row (17x17 actuator Oracle Control)

	Linear closed-loop	GAOL +7 actu (24x24)	
Fried parameter r_0 (m)	LE Strehl @ 1650 nm	LE Strehl @ 1650 nm	RMS WFE Boost (nm)
0.06	39.01%	43.89%	90.17
0.08	52.96%	61.85%	103.45
0.10	62.08%	72.22%	102.15
0.12	68.29%	79.04%	100.41
0.14	72.68%	83.54%	97.99
0.16	75.89%	86.72%	95.91

Table 2: Robustness of optimal setting compared to baseline.

shown below. As the slope measurements are being used to control the Woofer DM in closed loop, the WFE seen by the centroiders is significantly reduced. The residual phase estimate inferred by the GAN however is clearly picking up higher order wavefront information from the WFS, and is a very close fit to the true residual. Comparing the two residual phase errors on the bottom row of Figure 5 it is clear that the centroider method misses the high order information modelled by the GAN, and that the GAN estimate can be used to greatly reduce the residual phase error of the closed loop linear controller if it can be effectively applied to a secondary DM in open loop.

The results for GAOL AO experiments relative to closed loop linear control are shown in Table 1 under 'GAN Control'. The first two records are a comparison of the two control methods where the Tweeter DM actuator count is the same as the closed loop Woofer DM. The remaining records detail performance benefit of increased actuator count in the Tweeter DM. Measurements are all fixed for a Fried parameter $r_0 = 0.10$m, wind speed of $10ms^{-1}$ and a telescope diameter of 8m [3].

The 'Oracle Control' columns in Table 1 shows a second benchmark for our results, where we have used the true phase, rather than an estimate, to control a DM, with the various actuator count. In this way we eliminate the estimation error from the experiment and can see the fitting error - i.e., the error due to the number of actuators limiting the DM from matching the actual wavefront. In this case we have a

delay of two frames added as a like for like measure with the GAOL experiments. We can use this benchmark as the upper limit of what would be theoretically possible to do with each of the DM actuator configurations and compare with our results.

Looking to the GAOL method with no extra actuators, we see the performance increase over 5% SR over the closed loop linear control case, and a boost for the RMS WFE of 73nm. This is a strong result and it demonstrates that the GAOL system preserves the linear control residual data, allowing accurate inference of the residual wavefront and can effectively control the Tweeter DM in open loop for considerable performance gain. Adding actuators to the Tweeter DM shows additional improvement to the SR and RMS WFE with some configurations well exceeding 10% SR and over 100nm RMS WFE boost. The benefit of additional actuators falls off eventually, however there are large performance gains with just seven additional actuators in the Tweeter DM. Comparing the simulations with the corresponding fitting limits from Table 1 Oracle values, we can see that there is still a lot of wavefront information we are not capturing as the SR eventually falls away while the fitting limit continues to increase with the actuator count. Even with the enormous increase in performance we have discovered, there remains potential opportunities for improvement, though it is likely that much of the gap between GAOL and the DM fitting limit is due to the Shack-Hartmann WFS image not containing enough information to recover the entire true residual phase image.

From Table 2 it is clear that the GAOL control loop consis-

---
[3]See Appendix for simulation parameters

True R-Phase : 184.1 nm RMS

WFS Image

GAN R-Phase Estimate : 184.3 nm RMS

Slope R-Phase Estimate: 37.1 nm RMS

GAN Estimation Error : 162.1 nm RMS

Slope Estimation Error : 185.2 nm RMS

Figure 5: Phase images from GAOL AO design (Linear and GAN Residual Phase Estimate steps) compared with the simulated true residual phase image in the AO Loop, all images after 2000 iterations.

tently delivers large performance gains over the standalone closed loop linear control method for all r_0 values, where the performance improves slightly as the turbulence increases. This demonstrates the robustness to changes in the degree of atmospheric turbulence, where a single pre-trained GAN can infer for a wide range of conditions, removing the need to match networks to conditions.

6   DISCUSSION & FUTURE WORK

We have shown that with CNN Image to Image Translation we can utilise high order information from the Shack-Hartman WFS in an AO loop that is inaccessible with centroider algorithms applied by current practical wavefront estimation strategies. With this high order data, our translational network can accurately estimate the wavefront from just the WFS image. By adding a second, open loop DM that is controlled by our estimates of the closed loop residual

phase error, we can further correct the non-linear wavefront error not captured by existing methods and increase performance of the AO system by at least 10% SR where performance is robust over a range of real world turbulent conditions.

With access to higher order Shack-Hartman WFS data, we can control more DM actuators with less Shack-Hartman WFS sub-apertures. This translates to a substantial impact on how future AO systems will be designed – either as a cost saving (using cheaper components), or a science enabler (increasing sky coverage, and building a more potent systems providing extreme AO correction—high actuators count—with same sky coverage as current instruments).

We are the first to design a highly accurate method of residual wavefront estimation and apply it to real-time control. Specifically, the time-to-solution is in the right regime, with an average inference time of 0.34ms on a desktop GPU. With optimization and dedicated hardware [Perret et al., 2016; Gratadour et al., 2020], and the COSMIC framework platform [Ferreira et al., 2020], there is potential for hard real-time AO control using wavefronts inferred from pre-trained networks. Future lab experiments will allow for verification of loop control with real sensor equipment.

While these experimental results are just the beginning for this project, they are a proof of concept that image to image translation with CNNs can efficiently and accurately estimate the residual wavefront in AO systems and be easily applied in simulation with few additional components. The speed and simplicity, combined with demonstrated performance benefit of our method is of great practical interest to the AO community and shows a lot of promise for the implementation requirements of the in-construction ELT, applying eXtreme Adaptive Optics (XAO) to search for exoplanets[Kasper et al., 2021]. Additionally, our method opens the door to upgrading existing AO systems to provide better turbulence compensation while preserving sky coverage, since the number of sub-apertures can remain unchanged. In particular, currently contemplated upgrade projects like SPHERE+ as discussed by Beuzit et al. [2018] would clearly benefit from this approach by providing a cost effective way to increase the AO performance and enhance the science return of this existing instrument.

References

Jean-Luc Beuzit, David Mouillet, Thierry Fusco, Jean-François Sauvage, Kjetil Dohlen, Julien Milli, Laurent M. Mugnier, Arthur Vigan, Carlos M. Correia, Anthony Boccaletti, Gérard Rousset, Pierre Baudoz, Alexis Carlotti, Mamadou N'Diaye, Frantz Martinache, and Markus Kasper. A possible VLT-SPHERE XAO upgrade: going faster, going fainter, going deeper (Conference Presentation). 2018.

Jesse Cranney, Hao Zhang, Nicolas Doucet, François Rigaut, Damien Gratadour, Visa A. Korkiakoski, Jose De Dona, Yuxi Hong, Hatem Ltaief, and David E. Keyes. Predictive learn and apply: MAVIS application - apply. 2020.

Brent L. Ellerbroek and Curtis R. Vogel. Simulations of closed-loop wavefront reconstruction for multiconjugate adaptive optics on giant telescopes. In *Astronomical Adaptive Optics Systems and Applications*, volume 5169, 2003.

F Ferreira, E Gendron, G Rousset, and D Gratadour. Numerical estimation of wavefront error breakdown in adaptive optics. *Astronomy and astrophysics (Berlin)*, 616:A102, 2018a. ISSN 1432-0746;0004-6361;.

F Ferreira, A Sevin, J Bernard, O Guyon, A Bertrou-Cantou, J Raffard, F Vidal, E Gendron, and D Gratadour. Hard real-time core software of the AO RTC COSMIC platform: architecture and performance. In *Proc.SPIE*, volume 11448, 12 2020.

Florian Ferreira, Damien Gratadour, Arnaud Sevin, and Nicolas Doucet. COMPASS: An efficient GPU-based simulation software for adaptive optics systems. In *Proceedings - 2018 International Conference on High Performance Computing and Simulation, HPCS 2018*, 2018b.

Donald Gavel and Andrew Norton. Woofer-tweeter deformable mirror control for closed-loop adaptive optics: theory and practice. In *Adaptive Optics Systems IV*, volume 9148, 2014.

Ian Goodfellow, Jean Pouget-Abadie, Mehdi Mirza, Bing Xu, David Warde-Farley, Sherjil Ozair, Aaron Courville, and Yoshua Bengio. Generative Adversarial Nets. In Z Ghahramani, M Welling, C Cortes, N Lawrence, and K Q Weinberger, editors, *Advances in Neural Information Processing Systems*, volume 27. Curran Associates, Inc., 2014.

Damien Gratadour, Julien Bernard, Nicolas Doucet, Florian Ferreira, Arnaud Sevin, Roberto Biasi, and François Rigaut. MAVIS real-time control system: a high-end implementation of the COSMIC platform. 2020.

Hong Guo, Nina Korablinova, Qiushi Ren, and Josef Bille. Wavefront reconstruction with artificial neural networks. *Optics Express*, 14(14):6456–6462, 2006.

Hongyang Guo, Yangjie Xu, Qing Li, Shengping Du, Dong He, Qiang Wang, and Yongmei Huang. Improved Machine Learning Approach for Wavefront Sensing. *Sensors (Basel, Switzerland)*, 19(16):3533, 2019. ISSN 1424-8220.

Phillip Isola, Jun Yan Zhu, Tinghui Zhou, and Alexei A. Efros. Image-to-image translation with conditional adversarial networks. In *Proceedings - 30th IEEE Conference on Computer Vision and Pattern Recognition, CVPR 2017*, volume 2017-January, 2017.

Markus Kasper, Nelly Cerpa Urra, Prashant Pathak, Markus Bonse, Jalo Nousiainen, Byron Engler, Cédric Taïssir Heritier, Jens Kammerer, Serban Leveratto, Chang Rajani, Paul Bristow, Miska Le Louarn, Pierre-Yves Madec, Stefan Ströbele, Christophe Verinaud, Adrian Glauser, Sascha P. Quanz, Tapio Helin, Christoph Keller, Frans Snik, Anthony Boccaletti, Gaël Chauvin, David Mouillet, Caroline Kulcsár, and Henri-François Raynaud. PCS – A Roadmap for Exoearth Imaging with the ELT. 2021.

Chuan Li and Michael Wand. Precomputed real-time texture synthesis with markovian generative adversarial networks. In *Lecture Notes in Computer Science (including subseries Lecture Notes in Artificial Intelligence and Lecture Notes in Bioinformatics)*, volume 9907 LNCS, 2016.

Denis Perret, Maxime Lainé, Julien Bernard, Damien Gratadour, and Arnaud Sevin. Bridging FPGA and GPU technologies for AO real-time control. In *Proc.SPIE*, volume 9909, 7 2016.

Piotr Piatrou and Luc Gilles. Robustness study of the pseudo open-loop controller for multiconjugate adaptive optics. *Applied Optics*, 44(6), 2005. ISSN 15394522.

François Roddier, editor. *Adaptive Optics in Astronomy*. Cambridge University Press, 6 1999. ISBN 9780521553759.

T. Sean Ross. Limitations and applicability of the Maréchal approximation. *Applied Optics*, 48(10), 2009. ISSN 15394522.

Robin Swanson, Masen Lamb, Carlos M Correia, Suresh Sivanandam, and Kiriakos Kutulakos. Closed loop predictive control of adaptive optics systems with convolutional neural networks. *Monthly Notices of the Royal Astronomical Society*, 503(2), 2021. ISSN 0035-8711.

S. J. Weddell and R. Y. Webb. A Neural Network Architecture for the Reconstruction of Turbulence Degraded Point Spread Functions. *Proc. Image and Vision Computing New Zealand*, (December), 2007.

7 APPENDIX

7.1 SIMULATION PARAMETERS

Telescope Parameters	
Diameter	$8\ m$
Simulated Atmospheric Parameters	
Number of Layers	1
r_0	$0.10\ m$
Wind Velocity	$10\ ms^{-1}$
Target Parameters	
Wavelength λ_t	$1.65\ \mu m$
WFS Parameters	
Number of sub-apertures	16 x 16 x 8pix
Wavelength λ_{wfs}	$0.5\ \mu m$
AO Parameters	
Loop frequency	$500\ Hz$
Delay	2 frames
Integrator Gain	0.4
# Frames per experiment	2000
DM Parameters	
Number of DM actuators (Woofer)	17 x 17
1 tip-tilt mirror	

Table 3: Simulation parameters

7.2 SIMULATION IMAGE COMPONENTS

The top left image shows the simulated atmosphere, top-middle and top-right shows the deformable and tip tilt mirrors respectively. The bottom left image is the residual wavefront phase and the bottom middle is the Shack-Hartman WFS image – these are the two images we will use for training data. The bottom-right image is the short exposure PSF image in log scale.

Figure 6: COMPASS Artifacts - typical data available through simulator

7.3 NETWORK ARCHITECTURE

We adapted our network architecture and code from Isola et al. [2017], where much of the architecture details remains the same and we will follow the same labeling conventions. Ck denotes a Convolution-Batchnorm-ReLU layer with k filters and CDk denotes a Convolution-BatchNorm-Dropout-ReLU layer. Dropout rates, stride, downsample scaling, and upsample scaling, are all determined as per the literature mentioned above. Refer to the literature for any other parameters.

7.3.1 Generator architecture

Our network uses a UNet generator, consisting of an encoder, a decoder and skip connections between some layers as shown in the following layer structures:

UNet encoder:

$C64$-$C128$-$C256$-$C512$-$C512$-$C512$-$C512$-$C512$

UNet decoder:

$CD1024$-$CD1024$-$CD1024$-$C1024$-$C1024$-$C512$-$C256$-$C128$

7.3.2 Discriminator architecture

The Markovian Discriminator architecture by layer:

$C64$-$C128$-$C256$-$C256$