WiNeRT: Towards Neural Ray Tracing for Wireless Channel Modelling and Differentiable Simulations

Abstract

In this paper, we work towards a neural surrogate to model wireless electromagnetic propagation effects in indoor environments. Such neural surrogates provide a fast, differentiable, and continuous representation of the environment and enables end-to-end optimization for downstream tasks (e.g., network planning). Specifically, the goal of the paper is to render the wireless signal (e.g., time-of-flights, power of each path) in an environment as a function of the sensor's spatial configuration (e.g., placement of transmit and receive antennas). NeRF-based approaches have shown promising results in the visual setting (RGB image signal, with a camera sensor), where the key idea is to algorithmically evaluate the 'global' signal (e.g., using volumetric rendering) by breaking it down in a sequence of 'local' evaluations (e.g., using co-ordinate neural networks). In a similar spirit, we model the time-angle channel impulse response (the global wireless signal) as a superposition of multiple paths. The wireless characteristics (e.g., power) of each path is a result of multiple evaluations of a neural network that learns implicit ray-surface interaction properties. We evaluate our approach in multiple indoor scenarios and demonstrate that our model achieves strong performance (e.g., <0.33ns error in time-of-flight predictions). Furthermore, we demonstrate that our neural surrogate whitens the 'black-box' wireless simulators, and thus enables inverse rendering applications (e.g., user localization).

1 Introduction

Realistic simulations of physical processes are vital to many scientific and engineering disciplines. In this paper, we focus on simulation of *wireless* electromagnetic (EM) signals within a propagation environment. The physics of such EM wave propagation between a transmit and receive point are analytically given by Maxwell equations: the transmitted wave undergoes different interactions with the environment (e.g., reflection), and the receiver gets the wave through multiple *paths* with different time-of-flights and powers, and from different directions. However, solving the Maxwell equations with boundary conditions requires in-depth knowledge of the propagation environment, hence classically modelling EM propagation is intractable for most engineering applications.

Existing techniques make such simulations tractable by trading-off accuracy for speed. At one end of the spectrum, such simulations are represented in a statistical sense where a probabilistic model roughly captures the marginalized distribution over time-of-flights, gains and direction of transmit-receive paths. However, this level of accuracy is insufficient for designing systems that efficiently operate in high frequency bands. This motivates solutions at the other end of the spectrum: wireless ray tracing simulators. Given a detailed CAD representation of the environment along with the material properties, and numerous wireless configuration parameters (e.g., placement of a base station), the simulators generate resulting propagation characteristics.

Although wireless ray tracing simulators are appealing, there are a few drawbacks. First, they are generally slow, which poses a bottleneck for closed-loop design pipelines, as wireless configurations cannot be quickly mapped to propagation characteristics. Second, because they are non-differentiable, they are not amenable with inverse physical design formulations, for example optimizing base station placement with the simulator in the optimization loop. Third, they usually

require additional fine-tuning with real data as they are not data-driven. Calibrating them with real-world measurements is non-trivial and tedious. Fourth, they cannot generally inter-operate with probabilistic frameworks which have the advantage of better dealing with epistemic uncertainties. We believe *neural* surrogates provide a natural solution to circumvent many of these drawbacks of classical ray tracing simulators.

In this work, we propose a neural wireless simulator ('WiNeRT') by building on recent advances in scenes representation as continuous-function neural networks (Sitzmann et al., 2019; Tancik et al., 2020; Mildenhall et al., 2020). In particular, central to our approach is learning a network to model ray-surface interactions, i.e., the network transforms an incident wireless ray to an attenuated out-going ray. By shooting out a number of rays and evaluating the network at relevant spatial regions in the environment, we estimate the wireless characteristics as a set of transmit-receive paths, each path encodes attributes such as time-of-flight and gain. Our approach also addresses some unique technical challenges posed by the non-visual wireless modality, such as dealing with sparse high-dimensional time-angle measurement signals.

We demonstrate that our neural wireless simulator reasonably renders the wireless propagation aspects by evaluating on two datasets which captures 50-100 m^2 indoor propagation scenes. Interestingly, we find that the 3D-structure-aware implicit formulation is a strong inductive bias and helps generalization to significant inference-time distributions shifts. Finally, we demonstrate the potential of our differentiable forward model in solving inverse problem by tackling the user localization problem after posing it as an inverse rendering problem. Our results indicate that neural wireless simulators are promising first step towards closed-loop design pipelines of wireless communication systems.

2 RELATED WORK

Physics-based Neural Simulations. There exists a wide body of literature to model physical processes using advances in neural networks (Djeumou et al., 2022; Karniadakis et al., 2021; Raissi et al., 2017). As simulating physical processes can be expensive and can also present non-differentiable 'black-box' in design pipelines, recent literature addresses how to work towards neural surrogates, such as for particle simulation (Sanchez-Gonzalez et al., 2020), mesh simulations (Pfaff et al., 2020), design of particle accelerators (Shirobokov et al., 2020), and inverse kinematics (Sun et al., 2021). In this paper, we are particularly interested in a specific physical process – wireless EM-wave propagation. Although this has received limited recent attention (Xia et al., 2020) in a 3D-oblivious setting, it is unclear whether these extend to complex configurations. Consequently, in this work, we work towards the first 3d-structure-aware surrogates for wireless ray tracing simulation.

Neural Channel Modelling. Although propagation channel modeling has been a central topic in wireless communication (Jakes & Cox, 1994; Lee, 1982; Rappaport et al., 2022), there has been a recent trend for fully data-driven models. The main paradigm of these activities is to use machine learning to learn complex distributions, model non-linearities and have differentiable simulators. These works can be categorized as statistical channel models where the channel input-output relation is modelled as a conditional probability distribution. Many works leverage recent advances in generative modelling and use models like generative adversarial networks (GANs) (Goodfellow et al., 2014) or variational autoencoders (VAEs) (Kingma & Welling, 2013) to learn the channel model (O'Shea et al., 2019; Ye et al., 2018; Yang et al., 2019; O'Shea et al., 2019; Orekondy et al., 2022; Ye et al., 2020; Dörner et al., 2020). In contrast to these works, our approach inscribes within ray tracing channel modeling paradigm, where wireless propagation is precisely modelled by tracing wireless rays, however, unlike classical ray tracers, our model is able to blend in the elements of statistical modeling and is trainable directly on field data. To the best of our knowledge, this work is the first differentiable neural ray tracer for wireless channel modelling.

Neural Scene Representations. Representing scenes (or more generally signals) has been widely studied in literature, such as encoding the signal in the latent space of a generative model (Kingma & Welling, 2013; Goodfellow et al., 2014). A more recent link of work encodes the signal in the parameters of a co-ordinate MLP (Park et al., 2019; Sitzmann et al., 2020; Tancik et al., 2020; Fathony et al., 2020), thereby mapping co-ordinates (e.g., spatial, temporal) to the signal intensity values (e.g., pixel intensity, amplitude). In a specific case where the signal is a 2D RGB image, recent

Figure 1: Approach Overview. We learn a forward simulator $\texttt{render}_\theta(\cdot)$ that maps an environment configuration to a wireless channel $\boldsymbol{h}_i$. Here, $\boldsymbol{h}_i$ is a set of wireless propagation paths between $\boldsymbol{x}_{\text{tx}}$-$\boldsymbol{x}_{\text{rx}}$ (green rays in right image), each path encoding certain channel attributes e.g., path gain.

works (Schwarz et al., 2020; Niemeyer & Geiger, 2021; Mildenhall et al., 2020) show promising results by additionally employing image-based differentiable rendering paradigms (Drebin et al., 1988; Liu et al., 2019) to recover 3D properties of the scene. Inspired by this idea, our work neurally represents a *non-visual scene* (wireless in our case) by tackling a set of orthogonal challenges, such as dealing with sparse high-dimensional signals and particularly modelling reflection and transmission effects. Consequently, we work towards the first 3D-aware neural 'wireless' scene representation model in this paper.

3 APPROACH

In this section, we begin with some preliminaries to the subsequent formulation of the neural wireless ray tracing problem. We then provide an initial overview of our approach in Sec. 3.1 and then dive deeper into specific technical aspects of wireless ray marching in Sec. 3.2.

Preliminaries: Wireless Channels Scattering, reflection and diffraction are among the main effects in electromagnetic propagation. A general mathematical description of a wireless channel, seen as linear time varying system, is given by its impulse response Tse & Viswanath (2005); Rappaport (1996). A general model can be written as (Samimi & Rappaport, 2016):

$$h(t, \boldsymbol{\Theta}, \boldsymbol{\Phi}) = \sum_k a_k(t)\delta(t - \tau_k(t))\delta(\boldsymbol{\Theta} - \boldsymbol{\Theta}_k(t))\delta(\boldsymbol{\Phi} - \boldsymbol{\Phi}_k(t)) \tag{1}$$

where $a_k(t)$ is the complex gain, $\tau_k(t)$ is the delay (time-of-flight) of path k, $\boldsymbol{\Theta}_k(t)$ is azimuth and elevation angle of departure (AoD), and $\boldsymbol{\Phi}_k(t)$ is azimuth and elevation angle of arrival (AoA). Going forward, we use $\boldsymbol{\phi}_k = (\boldsymbol{\Theta}_k, \boldsymbol{\Phi}_k)$ as a shorthand to collectively represent all angles. Intuitively equation 1, represents each path as a dirac function in time-angle space. The task of channel modeling can, therefore, be reduced to predicting channel attributes $(a_k(t), \tau_k(t), \boldsymbol{\phi_k}(t))$ for a given environment map, and a transmit and receive location. See A.1 for a discussion on how these attributes are generally derived.

Forward Model: `render`$_\theta$. The general goal of our forward model is to run a wireless ray simulation given a certain configuration of the propagation environment. More specifically, as shown in Figure 1, the model takes three configuration parameters as input: a 3D representation of the environment $\boldsymbol{F}$ and the spatial co-ordinates of the transmitter $\boldsymbol{x}_{\text{tx}}$ and receiver $\boldsymbol{x}_{\text{rx}}$ devices. The model predicts the wireless scene as:

$$\hat{\boldsymbol{h}} = \{\boldsymbol{u}\}_{k=1}^K = \{(a_k, \tau_k, \boldsymbol{\phi}_k)\}_{k=1}^K = \texttt{render}_\theta(\boldsymbol{x}_{\text{tx}}, \boldsymbol{x}_{\text{rx}}, \boldsymbol{F}) \tag{2}$$

where the output is a variably-sized set of K paths. Each path $\boldsymbol{u}_k$ encodes three channel attributes: gain a_k, time-of-flight τ_k and angles $\boldsymbol{\phi}_k$. With these predicted channel attributes, we can obtain a time-angle impulse response (the 'channel') to characterize the wireless propagation effects.

Key Idea: Implicit Representation Network $\boldsymbol{f_\theta}$. Our approach recursively constructs the channel by using a learnt function $f_\theta : \boldsymbol{F} \times \boldsymbol{u}_k^{(r)} \mapsto \boldsymbol{u}_k^{(r+1)}$ As shown in Figure 1, given an initial ray $\boldsymbol{u}_k^{(r=0)}$, we model the final state as an evaluation of interactions that the ray undergoes with the environment $\boldsymbol{F}$. Intuitively, f_θ models the *local* interaction of any given ray k either in free-space, or in particular when it is incident on an interacting surface. In the latter case of ray-surface interaction, we leverage a co-ordinate MLP to predict the transformation (e.g., attenuation, rotation) to the incident ray.

Representing Environment $\boldsymbol{F}$. We primarily focus on indoor propagation environments in this paper, where the environment is a 3D geometric representation. Specifically, we consider the environment represented as a 3D mesh composed of F faces and V vertices, where each face corresponds

Figure 2: Renderer: Ray Marching Steps. At each step r of the simulation, we learn the transformation introduced on a ray $\boldsymbol{u}_k^{(r)}$ e.g., reflection off a particular surface.

to some surface on a wall. We consider a mesh structure with two subtleties: (a) we represent walls as a flattened polygon and thereby do not explicitly consider its thickness; and (b) we do not encode materials of the corresponding wall faces, but rather learn the properties implicitly from data.

3.1 OVERVIEW: NEURAL RENDERING

In this section, we present an overview of the three steps in our approach (as shown in Fig. 1).

Ray Launching. We begin by shooting out a fixed set of K rays from the transmitter location $\boldsymbol{x}_k^{(r=0)} := \boldsymbol{x}_{\text{tx}}(\forall k)$. We launch the rays omni-directionally from the transmitter co-ordinate, agnostic to the environment and location of the receiver location. Direction $\boldsymbol{d}_k^{(r=0)}$ of each ray is oriented in the direction of a unique vertex of a ico-sphere centered at $\boldsymbol{x}_{\text{tx}}$. We use the number of sub-divisions of the ico-sphere to trade-off between computational complexity and accuracy.

Ray Marching. The crux of our approach involves 'marching' the ray and accounting for interactions (e.g., transmission) with various surfaces of the environment. A key aspect here is using a neural network to make *local* evaluations: mapping an incident ray with some direction and power to an updated outgoing attenuated ray. The neural network is hence tasked to learn a complex non-linear characterization of the surface materials at a spatial co-ordinate. We further elaborate on the ray marching procedure in the next section.

Ray Aggregation and Reception. Of the K rays launched from the ray launching step, we are now interested in the subset of the rays that impinges on the receiver. We model the reception sphere with a specific radius, where radius can be tuned to achieve a desired level of precision. To mitigate double-counting of received rays, we filter rays based by associating them with a unique interaction path.

3.2 RAY MARCHING

We now dive deeper into the ray marching step, which tracks the evaluation of each ray as it propagates in the environment and hits various surfaces. We walk through the steps as shown sequentially in Fig. 2. We begin with a set of geometric rays $\boldsymbol{u}_k^{(r=0)}$, originating at the transmitter co-ordinate $\boldsymbol{x}_{\text{tx}}$. In addition to the channel attributes of each ray (see Eq. 2), we also consider in this section an additional set of meta-attributes (e.g., origin $\boldsymbol{x}_k$, direction $\boldsymbol{d}_k$) that helps us with the ray marching steps (elaborated in Sec. A.2).

Ray-Environment Intersections. For each ray, we evaluate its first interaction with the environment (e.g., first wall it hits). Representing the ray geometry as $\boldsymbol{p}(t) = \boldsymbol{x}_k^{(r)} + t\boldsymbol{d}_k^{(r)}$, we are primarily interested in a solution $t > 0$ for which the ray is incident on some surface. This location helps us determine the relay (i.e., new origin) $\boldsymbol{x}_k^{(r+1)}$ for the subsequent step.

Ray-Surface Interaction. While the previous step solves for *where* the ray is incident in the environment, a crucial step is determining attributes of the outgoing ray as a result of this interaction. We specifically focus on determining two attributes in this step: the new direction $\boldsymbol{d}_k^{(r+1)}$ and gain

$a_k^{(r+1)}$. This is a complex problem and typically requires in-depth knowledge of the surface (e.g., material type) as well as it's specific EM properties (e.g., frequency-dependent effects). Our solution is to instead predict the attributes using learnt network as a function of the incident location $\boldsymbol{x}_k^{(r+1)}$ and direction $\boldsymbol{d}_k^{(r)}$ (see f_θ^1 in Fig. 2). The ray-surface interaction network f_θ^1 used in our experiments is a ReLU MLP with 3 layers (with 64-hidden units). Similar to NeRF (Mildenhall et al., 2020), we split the network into learning incident direction-independent and dependent features by concatenating direction $\boldsymbol{d}_k^{(r)}$ with bottlenecked outputs of the penultimate layer in the network. We present more detailed discussions on the architecture in Sec. A.3) Furthermore, instead of directly predicting the new direction and gain, the network predicts transformations that we manually combine with the gains. Specifically, the network predicts an attenuation factor s (s.t $a_k^{(r+1)} = s a_k^{(r)}$) and rotation matrix $\boldsymbol{A}$ (s.t $\boldsymbol{d}_k^{(r+1)} = \boldsymbol{A} \boldsymbol{d}_k^{(r)}$). We predict the rotation matrix as a 4-dim Euler-Rodrigues parameter vector.

Reception/Termination check. For some special cases, we halt ray marching for a subset of rays. Namely, when ray k impinges on a reception sphere of a pre-specified radius (30cm in our experiments). This prevents a future version of the already received ray being potentially incorrectly received at a future iteration. In addition, for computation reasons, we also terminate ray marching if the ray exits the region of interest (e.g., ray exiting the environment).

Free-space interaction. While the previous steps modeled the interaction of *material* properties of the environment on wireless propagation, we now switch focus to free-space. In this case, we model propagation of a ray using the empirically-adjusted Friis' Equation: $P_r(d) = P_t G \left(\frac{d_0}{d}\right)^\lambda \ (d \geq d_0)$ which represents the power at the received at the receive antenna P_r as a function of the power fed into transmitting antenna P_t, and the distance travelled by the ray d. We learn the remaining scalar parameters G (antenna gain constant), λ (attenuation factor), and d_0 (reference distance).

3.3 TRAINING

Over the previous sections, we walked through our approach on predicting a channel $\hat{\boldsymbol{h}} = \texttt{render}_\theta(\boldsymbol{x}_\text{tx}, \boldsymbol{x}_\text{rx}, \boldsymbol{F})$. We train the model in a supervised setting, with ground-truth time-angle impulse response measurements. Importantly, we rely only on final measurements (i.e., at $r = R$) for training and do not use any intermediate information (e.g., interaction data through a ray tracer).

Set-based Channel Loss. Comparing the predicted channel $\hat{\boldsymbol{h}} = \{\hat{\boldsymbol{u}}_k\}_{k=1}^K$ with ground-truth measurement $\boldsymbol{h} = \{\boldsymbol{u}_l\}_{l=1}^L$ to evaluate the loss raises a complication as we compare two sets of paths, each path representing heterogeneous properties (e.g., angles, times). To this end, we propose a set-based channel loss to evaluate the consistency of the prediction with ground-truth channel measurements:

$$\mathcal{L}_\text{chan}(\boldsymbol{h}, \hat{\boldsymbol{h}}) = \sum_l d(\boldsymbol{u}_l, \hat{\boldsymbol{u}}_{\Pi(l)}) \tag{3}$$

$$\text{where} \qquad d(\hat{\boldsymbol{u}}_k, \boldsymbol{v}_l) = ||a_k - a_l|| + ||\tau_k - \tau_l|| + \langle \boldsymbol{\phi}_k, \boldsymbol{\phi}_l \rangle \tag{4}$$

Here, Equation 3 calculates the distance between two paths given some correspondence Π. We use direction-of-departure based correspondence, and hence associate two paths launched in approximately the same direction. To compare two paths as in Equation 4, we use mean square error for scalar-values (e.g., time-of-flights) and cosine distances between angles represented as unit vectors in cartesian coordinates.

Training and Implementation Details. We train our approach for 100 epochs using Adam optimizer with a learning rate of 10^{-3}. We found it crucial to not aggregate rays (Sec. 3.1) in the training steps, as it led to vanishing gradients due to negligible number of rays that contributed towards gradient updates. We model the reception sphere as a fixed-sized sphere of radius 30cm.

4 EXPERIMENTAL RESULTS

In this section, we discuss experimental analysis of our neural simulator approach. We begin by discussing the preliminaries: the choice of datasets and the evaluation metrics to compare simulations.

The section concludes by discussing overall performances and highlights certain benefits of neural simulations, such as running controllable simulations outside of training conditions.

4.1 DATASETS

We train and evaluate our algorithm using ground-truth data from wireless ray tracing packages. We collect two datasets, where each dataset contains channel measurements (i.e., gains, time-of-flights, angles) for different distributions of environments (e.g., floor layout). We keep the wireless configuration fixed to using omni-directional antennas at both the transmitter and receiver operating at a 3.5GHz carrier frequency. Now we further elaborate on the datasets used in our experiments.

Dataset 1: WI3ROOMS. We create a synthetic dataset which gives us greater control over many aspects over the generation process. Using a 10m×5m×3m hull, we randomly synthesize interior brick walls such that the eventual configuration consists of three rooms inter-connected with 1m doorways. We import the environment into an open-source wireless propagation toolbox (Amiot et al., 2013) and collect 41.6K channel measurements, of which roughly 37% of measurements are used for training.

Dataset 2: WIRPLAN. We use the indoor floorplans from the RPLAN dataset (Wu et al., 2019), which is popularly used to model indoor scenes (Nauata et al., 2020; 2021; Para et al., 2021). These layouts represent real-world single floor houses, with 4-8 rooms and 65-120m^2 areas. Each floorplan is further accompanied with room semantics such as whether a certain area is a living room, bed room, bathroom, etc. We use these semantics to selectively sample transmit/receiver locations (e.g., locations are not outside the boundary) and to determine wall materials (e.g., external facing walls are bricks, where as internal facing walls are dry plaster walls). We use a commercial ray tracer 'Wireless Insite' (Remcom, 2022) to collect measurements in the RPLAN environment. Similar to the earlier dataset, we collect 42.5K measurements, of which 36% are used for training the model.

Train and Test Regimes. For the training dataset set, per environment, we sample approximately 10 transmitter co-ordinates on an XY plane at an elevation of 2.8m. Similarly, we sample receiver co-ordinates on a 60×30 grid at a lower elevation of 2.0m. Keeping this training dataset fixed, we create three challenging test sets (see Figure A2 in appendix for an illustration) that evaluates generalization performances of novel spatial co-ordinates within the scene: (a) Checkerboard : where train and test Rx locations form a checkerboard pattern on the same XY plane at 2m elevation; (b) Generalization-z: where we move the test Rx locations in (a) to a novel elevation (z=1.0m for ThreeRooms and z=2.5m for RPLAN); and (c) Generalization-diag: where we sample test Rx locations on a diagonal XYZ plane. Such regimes let us validate the generalization performance under reasonable distribution shifts.

4.2 EVALUATION METRICS AND BASELINES

Evaluation Metrics. We consider three evaluation metrics to evaluate our approach: **(i) Overall prediction error ('Overall')**: We follow a similar formulation as our loss Equation 3 with one key difference – we find correspondences Π by solving a linear-sum assignment problem. The eventual error aggregates all attributes relevant for the path (e.g., gain, angles). Intuitively, this measures the distance between two sets (sets of multi-dim paths in our case), using a similar metric common in set prediction tasks (Fan et al., 2017; Zhang et al., 2019). **(ii) Geometry prediction error ('Geometry')**: We follow a formulation similar to (i), but now focus on two specific features that captures the geometrical accuracy of the path – time-of-flight and angles at departure and arrival. Intuitively, this metric measures whether the predicted rays take the same GT route between the transmit and receive co-ordinates. **(iii) Average Delay Time - MAE ('AvgDelay')**: We average the time-of-flights τ_k per path of the channel, weighted by its linear power $p(a_k)$. We report the mean absolute error of average delays between the predicted and ground-truth channel attributes.

Baselines. We propose two reference baselines **(i)** k**-NN** (with k=1): which predicts the channel, given the closest match to the input spatial co-ordinates in terms of Euclidean distance **(ii) MLP**: A geometry-oblivious MLP regressor with 3-hidden layers, each with 128 units. We train the MLP using the same loss as WiNeRT (Equation 3).

		WI3ROOMS			WIRPLAN		
		Overall	Geometry	AvgDelay	Overall	Geometry	AvgDelay
checkerboard	kNN	0.232	0.212	2.238	0.412	0.396	2.484
	MLP	0.287	0.330	2.051	0.373	0.399	1.745
	WiNeRT	**0.202**	**0.087**	**2.029**	**0.237**	**0.207**	**1.546**
gen-z	kNN	0.253	0.226	2.033	0.424	0.428	2.487
	MLP	0.297	0.350	1.797	0.388	0.421	1.969
	WiNeRT	**0.217**	**0.084**	**1.522**	**0.285**	**0.250**	**1.839**
gen-diag	kNN	0.252	0.213	2.118	0.380	0.251	1.377
	MLP	0.312	0.322	1.889	0.390	0.315	1.513
	WiNeRT	**0.229**	**0.085**	**1.792**	**0.369**	**0.170**	**0.828**

Table 1: Quantitative Results. Comparing errors of our approach (WiNeRT) with baselines, over two datasets (column groups) and three test regimes (row groups). In all cases, lower values are better and the lowest errors are marked in **bold**.

Figure 3: Receive Powers. By fixing the transmit location (x_{tx}, red cross), we measure the receive power (color at each point; in dB) predicted at each location in WI3ROOMS dataset. kNN and MLP suffer from memorization and falsely predicted highest receive powers around phantom transmit locations (purple star).

4.3 OVERALL RESULTS

In this section, we present the overall results of our approach, by discussing its performances on three test regimes (checkerboard, gen-z, gen-diag) for each of the datasets (WI3ROOMS and WIRPLAN). We additionally compare our approach with the two baselines k-NN and MLP. We complement the overall performances presented in this section with additional analysis in the next section.

Quantitative Results. We report the quantitative results for the two datasets (column groups) and three test sets (row groups) in Table 1. We observe from the table: (a) by focusing on the overall errors, we find WiNeRT generally outperforms all baselines, with a significant average decrease of -0.071 points compared to kNN and -0.085 with MLP; (b) WiNeRT is especially strong in capturing the geometry (e.g., 59-63% drop in errors w.r.t second best on WI3ROOMS) of the environment, which can be likely attributed to a strong inductive bias enforced by decoupling global rendering from local evaluations; (c) Although WiNeRT has reasonable performance in capturing the average delays, the performance gap here (e.g., 1-15% reduction in errors on WI3ROOMS) is not especially large compared to other metrics. We attribute this to contributions from 'false positive' rays with non-negligible power arising from our dense ray-launching technique. (d) The contributions of false positives can be mitigated by using a more sophisticated ray launching technique. For instance, by piggybacking on ray launch directions from GT channels, we can significantly improve performances across all metrics e.g., from 1-15% error reduction to 15-20% reduction in average delays on WI3ROOMS. (e) Overall, we attribute the underperformance of the baselines to poor generalization performance. For instance, in Figure 3, we illustrate the receive powers (in dB) predicted by all approaches in WI3ROOMS, for some placement of the transmitter (red cross in top-right room). We observe in this particular case that the high-power areas in the kNN and MLP baselines are predicted for a false phantom location (purple star), which roughly corresponds to a transmitter location in training set. This contrasts predictions by WiNeRT where the high-power areas are correctly concentrated around the transmitter location. As a result, we find that simple baselines find it challenging to generalize to new unseen spatial co-ordinates at inference time.

Qualitative Results. We complement the previous quanitative discussions with observations drawn from qualitative analysis. WiNeRT particularly helps for this analysis, as we can recovert intermediate ray-environment interaction information. From qualitative examples shown in Figure 4(a, b), we

(a) WI3ROOMS   **(b)** WIRPLAN   **(c)** WI3ROOMS (novel $\boldsymbol{F}$)

Figure 4: Qualitative results. (a, b) Evaluation on WiNeRT on the environment seen during training. (c) We use the previously trained model and re-render on a re-configured floormap $\boldsymbol{F}$.

(a) Ray-surface interactions   (b) Attenuation: Reflection   (b) Attenuation: Transmission

Figure 5: Evaluating Ray-surface interaction MLP. We display a cut-out of the 3ROOMS represented as a wireframe, with a specific focus on a particular wall. (a) We find a train-test distribution shift of ray-surface incidence points (b, c) Evaluation of the MLP at various incidence points.

draw some observations: (a) WiNeRT surprisingly learns ray-surface interactions implicitly, without any direct supervision. For instance, we observe multiple reflected paths between Tx and Rx; (b) we also find that our predictions (red rays) are generally consistent with the underlying simulation process (green rays) e.g., reflections from adjacent walls, floor and ceiling; and (c) we notice WiN-eRT sometimes predicts false positives (e.g., above $\boldsymbol{x}_{\text{tx}}$ in Figure 4b), which we attribute to dense omni-directional ray launching.

4.4 ANALYSIS

In the previous section, we evaluated the overall performance of the channels predicted by WiNeRT and found promising results. Now, we take a closer look at our approach and investigate additional generalization benefits.

What does the ray-surface interaction learn? We begin by investigating the ray-surface network (f_θ^1 in Figure 2) in isolation. The network is tasked to map an incident ray (gain a_{in}, direction $\boldsymbol{d}_{\text{in}}$) to an outgoing ray ($a_{\text{out}}, \boldsymbol{d}_{\text{out}}$). To accurately make this prediction, the network needs to learn direction- and material-dependent properties at the incident location $\boldsymbol{x}_{\text{inc}}$. This poses two complications. First, the network does not have explicit supervision to learn these properties. Rather, the network needs to *implicitly* learn these properties by optimizing over a number of channel measurements. This is reminiscent of NeRF-based approaches (Mildenhall et al., 2020) that learn certain direction-dependent visual properties (e.g., volume density) by solely observing image measurements (i.e., RGB pixels). Second, specific to our case, the measurements collected involve sparse ray-surface interactions i.e., in practise we cannot expect for paths in the training measurements to interact densely with all possible surfaces. For instance, consider Figure 5a, which show the incident points $\boldsymbol{x}_{\text{inc}}$ for a particular wall (black edges) that we recover from the underlying ray tracing tool. Here, we observe that the implicit training set interactions (red markers; never used during our training) are localized to a $\sim$50cm band (15% area of the wall). However, at test-time, the network is tasked to generalize to interactions for a different distribution of incidence points (purple markers).

In spite of the challenges – i.e., lack of direction supervision and sparsely-available interactions – we find that the ray-surface network is able to associate meaningful information to surface co-ordinates. For instance, we show the attenuation factor predicted for the reflected (Fig. 5b) and transmitted co-ordinates (Fig. 5c) for rays arriving from a fixed $\boldsymbol{x}_{\text{tx}}$ co-ordinate (placed at x=8m). We find that the network learns a smooth material- and direction-dependent function over the surface. In the next set

of experiments, we exploit these locally learnt properties and evaluate the effectiveness of WiNeRT to controllably render in novel scenarios.

Controllable synthesis: Predicting in Novel Environment Configurations. The previous experiments focused on evaluating approaches for novel locations of transmit and receive co-ordinates at simulation time. Now, we consider novel test-time environments by simulating approaches on *reconfigured layouts* F' of the train-time environment F, such as by randomly editing placement of interior walls. Overall, we find that WiNeRT remarkably extrapolates to the reconfigured environment, with the overall error unchanged with WiNeRT (0.202 on F vs. 0.203 on F'; more results in Figure A3). Furthermore, by observing the results qualitatively in Figure A4, we find the predicted interactions remain consistent with the ground-truth simulated rays in novel environment configurations. This is particularly appealing as for simulation use-cases which require modelling dynamic objects (e.g., moving vehicle), as WiNeRT enables customizing environment configurations without retraining.

Controllable synthesis: Simulating Higher-order Interactions. We investigate another inference-time controllable knob where we expect WiNeRT's learnt local properties to hold: simulating either lower- or higher-order interactions not captured in training measurements. We evaluate all approaches (trained only with first-order interaction measurements) without any additional retraining. With WiNeRT, we have the ability to control the number of interactions at test-time (i.e., by unrolling f_θ for fewer or more steps). We briefly summarize our observations here (see Table A2 for more details). WiNeRT exhibits promising results: while the baselines struggle with a simpler task of lower-order interactions (e.g., 0.22-0.58 overall errors at $r=0$), WiNeRT's performance improves (from 0.20 to 0.12). A better performance is natural in this particular setting, since the model is required to perform an *easier* task than original (predicting only line-of-sight component). For higher-order interactions, we observe performances of all approaches degrades, but WiNeRT outperforms the baselines. In particular, even at $r = 3$, we find the geometric-errors of WiNeRT (0.27) comparable to baselines in their originally trained setting ($r=1$, 0.21-0.33 errors).

Application: User Localization via inverse (differentiable) rendering. We now move focus to a specific application of differentiable rendering of wireless channels: user localization i.e., can we predict the user location x_{rx} given an observed channel h_{obs}? We solve for x_{rx}, by performing gradient on spatial coordinate $x_{\text{rx}}^{\text{ukn}}$ that minimizes the channel loss $\texttt{render}_\theta(x_{\text{tx}}, x_{\text{rx}}^{\text{ukn}}, F_i)$. This is specifically possible with WiNeRT, since we can backpropagate through the neural simulation of the channel. We optimize for x_{rx} using SGD with momentum (lr=0.01, momentum=0.9, 2000 iterations) with two additional considerations: (a) we constrain x_{rx} to lie in valid ranges (positive, upper-bounded by x_{max}) by clamping the values at each iteration; and (b) to prevent solutions in local minimas, we take the result which yields the minimum loss over five

Figure 6: User Localization.

random initializations of x_{rx}. We present the results over 100 test examples in Figure 6, as a CDF over localization errors. We find promising results for the localization problem, with a median error of 0.58m in WI3ROOMS (a 150m^3 volume) and 1.21m in WIRPLAN (a 300m^3 volume).

5 CONCLUSION

In this paper, we proposed the first *neural* forward model for wireless ray tracing-based simulations. Such models are particularly appealing as they help alleviate some drawbacks of classical non-neural simulators (e.g., better handling model-measurement mismatches, non-differentiability). Towards this goal, we proposed WiNeRT which tasks an MLP to learn how surfaces in a 3D environment influence propagation of wireless rays, such as by predicting attenuation factor of a reflective component. By shooting and bouncing rays, and with multiple evaluations of the MLP, we are able to neurally synthesize the wireless paths and generate corresponding channel attributes (e.g., path gains) for point-to-point communication. Overall, we find promising results, where we find neural simulators closely capture propagation effects (especially geometric effects). As neural simulators are additionally differentiable, we further show that they can be used to optimize inverse problems such as user localization.

REPRODUCIBILITY STATEMENT

To ensure reproducibility, we take a number of steps. On the dataset side, we use either publicly available indoor layouts (e.g., RPLAN) or synthetically generate layouts with known random seeds (0 and 10 in our case). We further elaborate on the simulation settings to recreate our dataset in 4.1 and B. We additionally plan to release the simulated data measurements. On the implementation side, we provide specific training details in Section 3.3 and further elaborate on the detailed architecture in A.3.

ETHICS STATEMENT

The data used in our paper corresponds to simulated data of physical processes (EM wave propagation). Since this does not involve any human subjects or personally identifiable information, we believe there is no conflict in this regard.

REFERENCES

Nicolas Amiot, Mohamed Laaraiedh, and Bernard Uguen. Pylayers: An open source dynamic simulator for indoor propagation and localization. In *ICC*, 2013.

Franck Djeumou, Cyrus Neary, Eric Goubault, Sylvie Putot, and Ufuk Topcu. Neural networks with physics-informed architectures and constraints for dynamical systems modeling. In *Learning for Dynamics and Control Conference*. PMLR, 2022.

Sebastian Dörner, Marcus Henninger, Sebastian Cammerer, and Stephan ten Brink. Wgan-based autoencoder training over-the-air. In *IEEE International Workshop on Signal Processing Advances in Wireless Communications*, 2020.

Robert A Drebin, Loren Carpenter, and Pat Hanrahan. Volume rendering. *SIGGRAPH*, 1988.

Haoqiang Fan, Hao Su, and Leonidas J Guibas. A point set generation network for 3d object reconstruction from a single image. In *CVPR*, 2017.

Rizal Fathony, Anit Kumar Sahu, Devin Willmott, and J Zico Kolter. Multiplicative filter networks. In *ICLR*, 2020.

Andrew S. Glassner. *An introduction to ray tracing*. Morgan Kaufmann, 1989.

Ian Goodfellow, Jean Pouget-Abadie, Mehdi Mirza, Bing Xu, David Warde-Farley, Sherjil Ozair, Aaron Courville, and Yoshua Bengio. Generative adversarial nets. In *NeurIPS*, 2014.

Fumio Ikegami, Tsutomu Takeuchi, and Susumu Yoshida. Theoretical prediction of mean field strength for urban mobile radio. *IEEE Transactions on Antennas and Propagation*, 39(3):299–302, 1991.

William C. Jakes and Donald C. Cox. *Microwave mobile communications*. Wiley-IEEE press, 1994.

George Em Karniadakis, Ioannis G. Kevrekidis, Lu Lu, Paris Perdikaris, Sifan Wang, and Liu Yang. Physics-informed machine learning. *Nature Reviews Physics*, 3(6):422–440, June 2021.

Diederik P Kingma and Max Welling. Auto-encoding variational bayes. *arXiv preprint arXiv:1312.6114*, 2013.

William C. Y. Lee. *Mobile communications engineering*. McGraw-Hill, 1982. ISBN 978-0-07-037039-5.

Shichen Liu, Tianye Li, Weikai Chen, and Hao Li. Soft rasterizer: A differentiable renderer for image-based 3d reasoning. In *ICCV*, 2019.

J.W. McKown and R.L. Hamilton. Ray tracing as a design tool for radio networks. *IEEE Network*, 5(6):27–30, November 1991.

Ben Mildenhall, Pratul P. Srinivasan, Matthew Tancik, Jonathan T. Barron, Ravi Ramamoorthi, and Ren Ng. Nerf: Representing scenes as neural radiance fields for view synthesis. In *ECCV*, 2020.

Nelson Nauata, Kai-Hung Chang, Chin-Yi Cheng, Greg Mori, and Yasutaka Furukawa. House-gan: Relational generative adversarial networks for graph-constrained house layout generation. In *ECCV*, 2020.

Nelson Nauata, Sepidehsadat Hosseini, Kai-Hung Chang, Hang Chu, Chin-Yi Cheng, and Yasutaka Furukawa. House-gan++: Generative adversarial layout refinement network towards intelligent computational agent for professional architects. In *CVPR*, 2021.

Michael Niemeyer and Andreas Geiger. Giraffe: Representing scenes as compositional generative neural feature fields. In *CVPR*, 2021.

Tribhuvanesh Orekondy, Arash Behboodi, and Joseph B Soriaga. Mimo-gan: Generative mimo channel modeling. In *IEEE ICC*, 2022.

Timothy J O'Shea, Tamoghna Roy, and Nathan West. Approximating the void: Learning stochastic channel models from observation with variational generative adversarial networks. In *ICNC*, 2019.

Wamiq Para, Paul Guerrero, Tom Kelly, Leonidas J Guibas, and Peter Wonka. Generative layout modeling using constraint graphs. In *CVPR*, 2021.

Jeong Joon Park, Peter Florence, Julian Straub, Richard Newcombe, and Steven Lovegrove. Deepsdf: Learning continuous signed distance functions for shape representation. In *CVPR*, 2019.

Tobias Pfaff, Meire Fortunato, Alvaro Sanchez-Gonzalez, and Peter W Battaglia. Learning mesh-based simulation with graph networks. *arXiv preprint arXiv:2010.03409*, 2020.

Maziar Raissi, Paris Perdikaris, and George Em Karniadakis. Physics informed deep learning (part i): Data-driven solutions of nonlinear partial differential equations. *arXiv preprint arXiv:1711.10561*, 2017.

Theodore S. Rappaport. *Wireless communications: principles and practice*, volume 2. prentice hall PTR New Jersey, 1996.

Theodore S Rappaport, Kate A Remley, Camillo Gentile, Andreas F Molisch, and Alenka Zajić. *Radio Propagation Measurements and Channel Modeling*. Cambridge University Press, 2022.

Remcom. Wireless insite, 2022. URL https://www.remcom.com/wireless-insite-em-propagation-software.

Mathew K. Samimi and Theodore S. Rappaport. 3-D millimeter-wave statistical channel model for 5G wireless system design. *IEEE Transactions on Microwave Theory and Techniques*, 64(7): 2207–2225, 2016.

Alvaro Sanchez-Gonzalez, Jonathan Godwin, Tobias Pfaff, Rex Ying, Jure Leskovec, and Peter Battaglia. Learning to simulate complex physics with graph networks. In *ICML*, 2020.

Katja Schwarz, Yiyi Liao, Michael Niemeyer, and Andreas Geiger. Graf: Generative radiance fields for 3d-aware image synthesis. *NeurIPS*, 2020.

Sergey Shirobokov, Vladislav Belavin, Michael Kagan, Andrei Ustyuzhanin, and Atilim Gunes Baydin. Black-box optimization with local generative surrogates. In *NeurIPS*, 2020.

Vincent Sitzmann, Michael Zollhöfer, and Gordon Wetzstein. Scene representation networks: Continuous 3d-structure-aware neural scene representations. *NeurIPS*, 2019.

Vincent Sitzmann, Julien Martel, Alexander Bergman, David Lindell, and Gordon Wetzstein. Implicit neural representations with periodic activation functions. *NeurIPS*, 2020.

Xingyuan Sun, Tianju Xue, Szymon Rusinkiewicz, and Ryan P Adams. Amortized synthesis of constrained configurations using a differentiable surrogate. *NeurIPS*, 2021.

Matthew Tancik, Pratul Srinivasan, Ben Mildenhall, Sara Fridovich-Keil, Nithin Raghavan, Utkarsh Singhal, Ravi Ramamoorthi, Jonathan Barron, and Ren Ng. Fourier features let networks learn high frequency functions in low dimensional domains. *NeurIPS*, 2020.

David Tse and Pramod Viswanath. *Fundamentals of wireless communication*. Cambridge university press, 2005.

Joram Walfisch and Henry L. Bertoni. A theoretical model of UHF propagation in urban environments. *IEEE Transactions on antennas and propagation*, 36(12):1788–1796, 1988.

Wenming Wu, Xiao-Ming Fu, Rui Tang, Yuhan Wang, Yu-Hao Qi, and Ligang Liu. Data-driven interior plan generation for residential buildings. *ACM Transactions on Graphics (TOG)*, 38(6): 1–12, 2019.

William Xia, Sundeep Rangan, Marco Mezzavilla, Angel Lozano, Giovanni Geraci, Vasilii Semkin, and Giuseppe Loianno. Millimeter wave channel modeling via generative neural networks. In *2020 IEEE Globecom Workshops*, 2020.

Yang Yang, Yang Li, Wuxiong Zhang, Fei Qin, Pengcheng Zhu, and Cheng-Xiang Wang. Generative-adversarial-network-based wireless channel modeling: Challenges and opportunities. *IEEE Communications Magazine*, 2019.

Hao Ye, Geoffrey Ye Li, Biing-Hwang Fred Juang, and Kathiravetpillai Sivanesan. Channel agnostic end-to-end learning based communication systems with conditional gan. In *IEEE Globecom Workshops*, 2018.

Hao Ye, Le Liang, Geoffrey Ye Li, and Biing-Hwang Juang. Deep learning-based end-to-end wireless communication systems with conditional gans as unknown channels. *IEEE Transactions on Wireless Communications*, 2020.

Yan Zhang, Jonathon Hare, and Adam Prugel-Bennett. Deep set prediction networks. *NeurIPS*, 2019.

Appendix

A APPROACH

A.1 BUILDING CHANNEL MODELS

This section accompanies the text in section 3.

Channel models are defined either in a statistical way by defining a distribution over channel attributes or in deterministic way using ray tracing. Statistical channel models are inadequate for applications involving positioning, sensing and challenges of communication at higher frequencies (e.g., mmWave at 30-300 GHz (Rappaport et al., 2022)). Inspired by similar techniques in computer graphics (Glassner, 1989), traditional ray tracing approaches (see for example (McKown & Hamilton, 1991; Ikegami et al., 1991; Walfisch & Bertoni, 1988)) approximate propagation of electromagnetic waves by modeling interactions of each *ray* with objects in its paths. These interactions include for example reflection, diffraction and penetration. Although this is more efficient than solving Maxwell equations, ray tracing methods need a detailed knowledge of the environment and are generally slow for prototyping. They generally utilize hard coded and mathematically tractable models for example knife-edge model for diffraction (Lee, 1982; Rappaport, 1996). These abstractions suffer from mismatches and require occasional tedious fine-tuning and calibration with real data. Improving these models while remaining tractable for rapid simulation rounds is not straightforward. Finally, they are non-differentiable and cannot be integrated into a closed loop design pipeline. We plan to tackle these issues by building a neural surrogate of a physics-based wireless ray tracer in this paper.

A.2 REPRESENTING RAY ATTRIBUTES

We represent the k-th ray (among K rays) at the r-th iteration of rendering as $\boldsymbol{u}_k^{(r)}$. For notation convenience, we drop the sub- and super-script for the rest of the section. We characterize the wireless ray analogous to the concept of an optical ray (such as with geometric direction, intensity). In additional to the wireless attributes (see Equation 2), we further include meta-level attributes that helps us propagate and render the eventual ray received at the receiver co-ordinate $\boldsymbol{x}_{\mathrm{rx}}$. We briefly describe these attributes here and elaborate on how they are obtained or updated over the next sections. The ray contains the attributes:

$$\boldsymbol{u} = \underbrace{(\ a \quad \tau \quad \phi}_{\text{(a) Channel Attributes}} \quad \underbrace{\boldsymbol{x} \quad \boldsymbol{d} \quad t_s \quad t_{rx} \quad \rho_{\mathrm{rx}}}_{\text{(b) Ray Geometry}} \quad \underbrace{\sigma_{\mathrm{upd}} \quad \sigma_{\mathrm{rx}}\ )}_{\text{(c) State}}$$

which as shown can be grouped into three categories: **(a) Wireless Channel Attributes.** Exactly as discussed earlier in the section (see Equation 2), it contains the attributes to construct the wireless channel time-angle impulse response (Equation 1) **(b) Ray Geometry.** We additionally include geometrical representation of the ray, which helps us determine how to propagate the ray through the environment. Specifically, we represent the geometry of the ray using the line equation: $\boldsymbol{p}(t) = \boldsymbol{x} + t\boldsymbol{d}$, where $\boldsymbol{x}$ is the origin and $\boldsymbol{d}$ is a unit-vector encoding the ray direction. We are interested in two particular solutions of t in this equation: t_s for which the ray intersects with a surface (mesh face in our case) and t_{rx} for which the ray is tangential to a sphere around some receiver of radius ρ_{rx}. **(c) Ray state.** To help with subsequent updates to the ray at future iterations, we track two binary variables. σ_{upd} denotes whether the ray has to be updated in the next iteration. σ_{rx} denotes whether the ray has impinged on a reception sphere of a predefined radius.

A.3 RAY MARCHING: DETAILS

Ray-Environment Intersections. For each ray, we are interested in their first interaction with the environment (e.g., first wall it hits, impinging on the receiver). For this, we are interested in the solutions to the line equation representing the geometry of the ray: $\boldsymbol{p}(t) = \boldsymbol{x}_k^{(r)} + t\boldsymbol{d}_k^{(r)}$. In particular, we are interested in two solutions of t: **(a) Ray-Face intersection.** The smallest value of $t > 0$ for which $\boldsymbol{p}(t)$ lies on a surface (a triangular mesh face in our case). For this, we perform ray-triangle intersections with each face in the environment and find the corresponding solution $t = t_s$.

$$\mathbf{f}_i = \text{face}\left(\mathbf{x}_k^{(r+1)}\right)$$

Surface normal $\mathbf{n}_i$

$$\mathbf{b}_i = \text{sdf}(\mathbf{x}_k^{(r+1)}, \mathbf{x}_{rx})$$

Spatial MLP $\quad \mathbf{v}_i$

Dirc. MLP

$\mathbf{d}_k^{(r)}$

$\mathbf{s}_i$

$\boldsymbol{\rho}_i \rightarrow \mathbf{A} = \Gamma(\boldsymbol{\rho}_i) \rightarrow$

$\in SO(3)$

New complex gain

$a_k^{(r+1)} = \mathbf{s}_i a_k^{(r)}$

$\mathbf{d}_k^{(r+1)} = \mathbf{A}\mathbf{d}_k^{(r)}$

New direction

Figure A1: Ray-surface interaction network f_θ^1

This helps us estimate the new relay location: $\boldsymbol{x}_k^{(r+1)} = \boldsymbol{x}_k^{(r)} + t_s \boldsymbol{d}_k^{(r)}$ **(a) Ray-Rx intersection.** In parallel, we are also interested in positive solutions of t for which the ray hits the receiver if it were modeled as a sphere of radius ρ_{rx}. In this case, we obtain the value of t as the projection of $\boldsymbol{x}_{rx}$ on $\boldsymbol{p}(t)$:

$$t_{rx} = \max(0, \ (\boldsymbol{x}_{rx} - \boldsymbol{x}_k^{(r)}) \cdot \boldsymbol{d}_k^{(r)}) \tag{5}$$

$$\rho_{rx} = ||(\boldsymbol{x}_{rx} - \boldsymbol{x}_k^{(r)}) - t_{rx}\boldsymbol{d}_k^{(r)}|| \tag{6}$$

Consequently, at the end of ray-environment, we analytically estimate the first intersections of the ray with both the environment and (potentially) the receiver.

Ray-Surface Interaction. If the ray $\boldsymbol{u}_k^{(r)}$ (originating at $\boldsymbol{x}_k^{(r)}$ and travelling in direction $\boldsymbol{d}_k^{(r)}$) hits a wall at $\boldsymbol{x}_k^{(r+1)}$ (as estimated in the previous step), we are now interested in characterizing the outgoing ray with origin at $\boldsymbol{x}_k^{(r+1)}$. Specifically, we are interested in estimating the new direction $\boldsymbol{d}_k^{(r+1)}$ (does the ray penetrate the wall? or reflect?) and the corresponding change in gain that arises (i.e., loss of power, change of phase). This is a complex problem and typically requires in-depth knowledge of the surface (e.g., which material) as well as it's specific EM properties (e.g., frequency-dependent effects). Our solution is to instead learn these properties by associating spatial regions in the environment with EM-specific properties. Towards this, we delegate the association to a neural network show in Figure A1. The key idea is to associate spatial co-ordinates (or sets of co-ordinates, given by face on which they lie) with EM properties. We achieve this by mapping spatial properties (e.g., face corresponding to $\boldsymbol{x}_k^{(r+1)}$) to EM properties (e.g., gain factor).

Specifically, our neural network is:

$$\boldsymbol{v}_i = \texttt{spatial\_net}(\boldsymbol{f}_i, \boldsymbol{n}_i, \boldsymbol{b}_i) \tag{7}$$

$$\boldsymbol{s}_i, \boldsymbol{\varphi}_i = \texttt{directional\_net}(\boldsymbol{v}_i, \boldsymbol{d}_i) \tag{8}$$

which consists of a `spatial_net` to encode EM properties specific to a spatial region, but *independent* of the incidence direction. This network takes as inputs the one-hot encoding of the face $\boldsymbol{f}_i$ on which the relay point $\boldsymbol{x}_k^{(r+1)}$ lies and the surface normal vector at that point $\boldsymbol{n}_i$. In addition, we also provide the network a 3-dim conditioning vector of signed distances

$$\boldsymbol{b}_i = (\text{sdf}(\boldsymbol{x}_{tx}, \boldsymbol{f}_i), \quad \text{sdf}(\boldsymbol{x}_{rx}, \boldsymbol{f}_i), \quad \text{sdf}(\boldsymbol{x}_k^{(r+1)}, \boldsymbol{f}_i)) \tag{9}$$

where $\text{sdf}(\boldsymbol{x}, \boldsymbol{f})$ is the signed distance function between co-ordinate $\boldsymbol{x}$ and face $\boldsymbol{f}$. We find it crucial to condition the network on these values to help predict EM-properties for relevant outgoing components (e.g., reflective, transmission).

The output of the network is a gain factor $\boldsymbol{s}_i$, such that the new complex gain of the ray $\boldsymbol{u}_k^{(r+1)}$ is $a_k^{(r+1)} = s_i a_k^{(r)}$. In parallel, the network also predicts the rotation a ray incident with direction $\boldsymbol{d}_k^{(r)}$ on $\boldsymbol{f}_i$ undergoes. We characterize rotations using a 4-dim rotation $\boldsymbol{\varphi}_i$ using Euler-Rodrigues parameterization. This parameterization encodes the axis of rotation and about which $\boldsymbol{d}_k^{(r)}$ rotates by angle ϑ. We represent the rotation by a 3×3 $SO(3)$ matrix $\boldsymbol{A}$ and the new outgoing direction of ray k is given by $\boldsymbol{d}_k^{(r+1)} = \boldsymbol{A}\boldsymbol{d}_k^{(r)}$.

Reception/Termination check. For some special cases, we halt ray marching for a subset of rays. Namely, when ray k impinges on a reception sphere of radius under ϱ meters. This prevents a future version of the ray being potentially being incorrectly received once again. In addition, for

(a) Testset 1: "Checkerboard" (b) Testset 2: "Generalization-z" (c) Testset 3: "Generalization-diag"

Figure A2: Train and test regimes: We consider disjoint subsets of train (blue markers; identical in all figures) and test (orange markers) co-ordinates of transmit and receive locations.

computation reasons, we also terminate ray marching if the ray exits the region of interest (e.g., ray exiting the environment).

Free-space interaction. While the previous steps modeled the interaction of *material* properties of the environment on wireless propagation, we now switch focus to free-space. In this case, we model propagation of a ray using the empirically-adjusted Friis' Equation:

$$P_r(d) = P_t K \left(\frac{d_0}{d} \right)^\lambda, \qquad d \geq d_0 \tag{10}$$

which represents the power at the received at the receive antenna P_r as a function of the power fed into transmitting antenna P_t and the distance travelled by the ray d. We learn the remaining scalar parameters K (constant representing of antenna gains), λ (wavelength of signal), and d_0 (reference distance).

B DATASET: ADDITIONAL DETAILS

B.1 TRAIN AND TEST REGIMES

Figure A2 accompanies the text in subsection 4.1.

B.2 SIMULATION FOR WIRPLAN DATASET: DETAILS

We created 3 different floor-plans in Wireless Insite where 2D floor-plans layout and semantic labels of each room are picked from House GAN++ dataset and mapped into a 3D layout where the scale and dimensions are determined based on practical floor-plan scenarios. All layouts are scaled to 10m×10m with ceiling height at 3m. All the inner walls and floor materials are layered dielectrics with specific permittivity, conductivity & roughness. These have finite reflection and transmission coefficients. The reflection coefficient is corrected if the surface is not smooth while the transmission coefficients are unaffected by surface roughness.

Materials. Propagation characteristics are naturally affected by the medium and we create a dataset with fairly diverse set of materials. Layered dielectric with two layers separated by free-space of 89cm is chosen for all inner walls and the outer-walls were made of thicker materials of concrete. Doors were created using free space except the balcony door which was created using glass with a small thickness. The balcony walls were laid out using brick walls. The propagation factor and index of reflection are functions of the permittivity(ϵ) and conductivity(σ) of medium. In Table Table A1, we present the relative permittivity and conductivity.

Antenna and Transceiver configuration. Omnidirectional beam patterned antenna with polarization perpendicular to the z axis is setup for all receive and transmit antennas. Location, Orientation of the antenna are set relative to global reference such that they are rotated about the z axis by 90deg and placed at a height of 2.8m. All antennas employ the same configuration with no transmission loss.

	thickness(cm)	permittivity ϵ	conductivity σ (S/m)
Layered drywall(1,3)	1.3	2.8	0.013
Brick	12.5	4.44	0.0001
Concrete	30	5.31	0.015
Glass	3	2.4	0

Table A1: Material properties

	Overall	Geometry	Avg. Delay
kNN	0.264	0.288	1.479
MLP	0.280	0.378	**1.191**
WiNeRT	**0.203**	**0.114**	1.297

Figure A3: Quantitative results. For a trained approach evaluated on a reconfigured floormap $\boldsymbol{F}'$

Figure A4: Qualitative results

Simulation. We currently run the simulation using the shoot and bounce model where a geometric path is drawn from every point on the transmitter field pattern to the receive point. This also includes transmission through surfaces allowing it to model transmittance and reflection. Rays are first traced from the source points with the rays reflecting specularly from the building walls. The rays that hit building walls are reflected specularly and continue to be traced up to the maximum number of reflections and transmissions.

The spatial separation of rays is set to $0.75°$. The geometric path traced by the ray undergoes upto 6 specular reflection and 3 transmittance with path loss threshold set to -70dBm.

Total received power of all paths is determined as the sum of time averaged power of group of correlated paths. A set of ray paths that interact with similar set of faces and follow nearly same path are defined as group.

C EVALUATION: ADDITIONAL DETAILS

C.1 CONTROLLABLE SYNTHESIS: GENERALIZATION TO RECONFIGURED FLOORMAPS

Figure A3 accompanies the discussions in subsection 4.4, where we evaluate a WiNeRT model trained in one environment $\boldsymbol{F}$ and evaluated in a reconfigured environment $\boldsymbol{F}'$.

C.2 CONTROLLABLE SYNTHESIS: LOWER- AND HIGHER-ORDER INTERACTIONS

See Table A2, which accompanies the discussions in 4.4.

	Overall (DoD)				Geometry				Avg. Delay			
#interactions r	0	1*	2	3	0	1*	2	3	0	1*	2	3
kNN	0.22	0.33	0.50	0.55	0.31	0.21	0.29	0.33	1.30	2.24	2.96	3.40
MLP	0.58	0.46	0.61	0.67	0.34	0.33	0.37	0.41	0.98	2.05	2.93	3.48
WiNeRT	**0.12**	**0.25**	**0.44**	**0.51**	**0.00**	**0.09**	**0.21**	**0.27**	**0.03**	**2.03**	**2.43**	**2.8**

Table A2