Learning Stable Deep Dynamics Models for Partially Observed or Delayed Dynamical Systems

Abstract

Learning how complex dynamical systems evolve over time is a key challenge in system identification. For safety critical systems it is often crucial that the learned model is guaranteed to converge to some equilibrium point. To this end neural ODEs regularized with neural Lyapunov functions are a promising approach when states are fully observed. For practical applications however, *partial observations* are the norm. As we will demonstrate, initialization of unobserved augmented states can become a key problem for neural ODEs. To alleviate this issue, we propose to augment the system's state with its history. Inspired by state augmentation in discrete-time systems, we thus obtain *neural delay differential equations*. Based on classical time delay stability analysis, we then show how to ensure stability of the learned models, and theoretically analyze our approach. Our experiments demonstrate its applicability to stable system identification of partially observed systems and learning a stabilizing feedback policy in delayed feedback control.

1 Introduction

In this paper, we address the task of learning stable, partially observed, continuous-time dynamical systems from data. More specifically, given access to a data set $\{(t_0, y_0^l), \ldots, (t_N^l, y_N^l)\}_{l=1}^{L}$ of noisy, partial observations collected along L trajectories of a stable, autonomous dynamical system,

$$
\begin{cases}
\dot{z}(t) & = g\left(z(t)\right) & , z(t) \in \mathbb{R}^m \\
x(t) & = h(z(t)) & , x(t) \in \mathbb{R}^n, m \geq n, \\
y_i^l & = x(t_i^l) + \epsilon_i^l & , \epsilon_i^l \overset{\text{i.i.d.}}{\sim} \mathcal{N}(0, \sigma^2),
\end{cases}
\tag{1}
$$

we would like to learn a model for the evolution of the continuous time series $\{x(t)\}_{t \geq t_0}$. Moreover, it should be ensured that the model remains stable (we will be concerned with exponential convergence to 0) on unseen trajectories.

Learning such systems in a data-driven way is a key challenge in many disciplines, including robotics [Wensing et al., 2017], continuous-time optimal control [Esposito, 2009] or system biology [Brunton et al., 2016]. One powerful continuous-time approach to non-linear system identification are deep Neural ODEs (NODE), as presented by Chen et al. [2018a]. Since neural networks are very expressive, they can be deployed in a variety of applications [Rackauckas et al., 2020]. However, because of that expressiveness, little is known about their system theoretical properties after training. Thus, there has been growing interest in regularizing such dynamics models to ensure favorable properties. In the context of ensuring stability of the learned dynamics, Manek and Kolter [2020] propose to jointly learn a dynamics model and a neural network Lyapunov function, that guarantees global stability via a projection method. Neural network Lyapunov functions have previously been employed by Richards et al. [2018] to estimate the safe region of a fixed feedback policy and by Chang et al. [2019]

32 to learn a stabilizing feedback policy for given dynamics. Moreover, Boffi et al. [2020] proof that
33 neural Lyapunov functions can also be learned efficiently from data collected along trajectories.

34 Thus far, all of these approaches are working directly with a standard ODE dynamics model. If the
35 system's states are fully observed and the system is Markovian, this can be a valid choice. However,
36 in many practical settings, partial observations and non-Markovian effects like hysteresis or delays are
37 the norm. To address the limited expressivity of neural ODEs in the classification setting, Dupont et al.
38 [2019] introduce Augmented Neural ODEs (ANODE). Here, a standard neural ODE is augmented
39 with unobserved states, to extend the family of functions the model is able to capture. While Dupont
40 et al. [2019] demonstrate that initializing the unobserved states at 0 is sufficient for the classification
41 case, this is certainly not true when deploying ANODE as a dynamical system. In fact, our experiments
42 in Section 4 demonstrate that learning this initial condition is a key problem in practice.

43 Inspired by state-augmentation methods in the time-discrete case, we thus propose to capture partial
44 observability and non-Markovian effects via Neural Delay Differential Equations (NDDE). NDDEs
45 were very recently proposed in the context of classification by Zhu et al. [2021] and in the context of
46 closure models for partial differential equations by Gupta and Lermusiaux [2020]. While NDDEs
47 offer an elegant solution to avoid the Markovianity of neural ODEs, again little can be said about
48 stability outside of the training set. In fact, our experiments in Section 4 show that in a sparse
49 observation and high noise setting, a NDDE model that is stable on training trajectories may become
50 unstable along new unseen trajectories. We therefore extend the ideas of neural network Lyapunov
51 functions to time-delay systems and introduce a Lyapunov-like regularization term to stabilize the
52 NDDE. The applicability of the proposed network is showcased for the stabilization of the NDDE
53 model and for the task of learning a stabilizing feedback policy in delayed feedback control of known
54 open loop dynamics.

55 In summary, we demonstrate the applicability of NDDEs to the case of modeling a partially observed
56 dynamical system. We then leverage classical approaches for stability analysis in the context
57 of delayed systems to develop a novel, Lyapunov-like regularization term to stabilize NDDEs.
58 Furthermore, we provide theoretical guarantees and code for our implementation.[1]

2 Model and background

60 The main model of this paper, NDDEs, is mathematically belonging to the class of time-delay systems
61 that come with some additional difficulties compared to ODEs both on the theoretical as well as the
62 numerical side. Thus, we first recall some preliminaries and notation on time-delay systems. Then
63 we continue with the model architecture and stability of time-delay systems.

2.1 Time-delay systems

65 Suppose $r > 0$ and consider the infinite-dimensional state space $\mathcal{C}_r := \mathcal{C}([-r, 0], \mathbb{R}^n)$ of continuous
66 mappings from the interval $[-r, 0]$ to $\mathbb{R}^n$. Throughout this paper we endow $\mathbb{R}^n$ with the Euclidean
67 norm $\|\cdot\|_2$ and $\mathcal{C}_r$ with the supremum norm $\|\phi\|_r = \sup_{s \in [-r, 0]} \|\phi(s)\|_2$ for $\phi \in \mathcal{C}_r$. Further on,
68 along a trajectory $x \in \mathcal{C}([-r, t_f], \mathbb{R}^n)$ we make use of the notation $x_t(\cdot) := x(t + \cdot) \in \mathcal{C}_r$ to denote
69 the infinite-dimensional state at time $t \in [0, t_f]$. For a locally Lipschitz function $f : \mathcal{C}_r \to \mathbb{R}^n$ an
70 autonomous time-delay system is defined by the family of initial value problems:

$$\begin{cases} \dot{x}(t) & = f(x_t) \\ x(s) & = \psi(s), \ s \in [-r, 0], \ \psi \in \mathcal{C}_r. \end{cases} \tag{2}$$

71 In contrast to ODEs the dynamics are given by a Functional Differential Equation (FDE) and the
72 initial condition by a function $\psi \in \mathcal{C}_r$. As we are interested in autonomous dynamics we will always
73 set the initial time to zero. Furthermore, we denote by $x(\psi)(t) \in \mathbb{R}^n$ the solution and by $x_t(\psi) \in \mathcal{C}_r$
74 the history state at time t, starting from the initial history ψ. In the course of this paper, we will mainly
75 focus on the important special case of retarded delay differential equations with commensurate delays
76

$$\dot{x}(t) = f(x(t), x(t - \tau), ..., x(t - K\tau)) = f(\mathbf{x}^\tau_{-K}(t)). \tag{3}$$

77 Here, it holds $r = K\tau$, and for convenience we introduced the short-hand notation $\mathbf{x}^\tau_{-K}(t) :=$
78 $(x(t), x(t - \tau), \ldots, x(t - K\tau))$. Note, that while the instantaneous change (i.e., the vector field)

---

[1]Github link to code follows

in (3) is depending only on a discrete set of observations $\mathbf{x}^\tau_{-K}(t)$, the initial history $\psi \in \mathcal{C}_r$ has to be given on the entire interval $[-r, 0]$ in order to have well-defined dynamics for $t \geq \tau$. As a consequence, in practice we need an interpolation of the initial history, and for numerical integration a specific DDE solver based on the method of steps [Alfredo Bellen, 2013] is required. Apart from this, existence and uniqueness of solutions to (2) and (3) follow in a similar fashion as for ODEs [Hale and Lunel, 1993, Diekmann, 1995].

2.2 Neural Delay Differential Equations

Model architecture   The motivation of the model architecture is the following: We look for a general method to learn continuous non-Markovian time series which occur, for example, in partially observed dynamical systems. As already mentioned before, the temporal evolution of an ODE is uniquely determined by its current state, which makes NODEs inherently Markovian. Instead of augmenting NODEs with additional states, our approach is inspired by neural network based system identification of discrete-time dynamical systems: the latter copes with non-Markovian effects by augmenting the state space with past observations (i.e., literally memory states) in order to lift the problem back into a Markovian setting (see e.g. [Chen et al., 1990]). A continuous-time analog leads us to a FDE $\dot{x}(t) = f(x_t)$ where the current change is depending on the history $x_t(s) := x(t + s)$, $s \in [-r, 0]$ up to some maximal delay $r > 0$. Since a neural network cannot represent a general non-linear functional f, we discretize the infinite-dimensional memory state x_t as in Equation (3). This leads us, as illustrated in Figure 1, to the NDDE model

Figure 1: Graphical illustration of the NDDE model.

$$\dot{x}(t) = f^{NN}_\theta \left(x(t), x(t-\tau), \ldots, x(t-K\tau) \right) = f^{NN}_\theta \left(\mathbf{x}^\tau_{-K}(t) \right). \tag{4}$$

Here, f^{NN}_θ is a feedforward neural network and K the number of delays.

Predictions   Given an initial history $\psi \in \mathcal{C}_r$ we integrate equation (4) to get the prediction at time t

$$\hat{x}(t) = \text{DDESolve}(\psi, f^{NN}_\theta, t_0, t). \tag{5}$$

However, in practice observations are subject to noise and cannot be sampled at an infinite rate. Hence, we need to approximate ψ by a smoothed interpolation. For this purpose we employ Gaussian Process (GP) regression. Given a set $\{(t_0, y_0), \ldots, (t_{N_{\text{hist}}}, y_{N_{\text{hist}}}\}$ of N_{hist} observations along the initial history, we fit for each scalar initial history component a zero-mean GP with Radial Basis Function (RBF) kernel

$$k_{\gamma, \sigma_k}(t, t') = \sigma^2_k \exp \left(-\frac{|t - t'|}{2l^2} \right) \tag{6}$$

of length-scale l and kernel variance σ^2_k. For the smoothed interpolation of the initial history we are then using the posterior mean function,

$$\psi(t)_i = \bar{m}(t) = k_{tT} \left(K_{TT} + \sigma^2 I \right)^{-1} Y_i, \quad 1 \leq i \leq n, \tag{7}$$

where $Y_i = ((y_0)_i, \ldots, (y_{N_{\text{hist}}})_i)$, $T = (t_0, \ldots, t_{N_{\text{hist}}})$, $k_{tT} = (k(t, t_0), \ldots, k(t, t_{N_{\text{hist}}}))$, and $K_{TT} = (k(t_j, t_k))^{N_{\text{hist}}}_{j,k=1}$. The kernel hyperparameters l, σ^2_k as well as the observation noise variance σ^2 are estimated from data by marginal likelihood maximization.

Training   For training we proceed similar to NODEs and minimize the least squared loss

$$J = \sum_{i=0}^{N} \|y_i - \hat{x}(t_i)\|^2_2 \tag{8}$$

along trajectories. While it is possible to make use of an interpolated continuous adjoint sensitivity method for calculation of the loss gradients, differentiation through DDE solvers turned out to be significantly more efficient in our experiments. As discussed by Calver and Enright [2016] one

reason is that jump discontinuities need to be accounted for that are later propagated in higher order derivatives along the solution of the adjoint state, and the DDE solver needs to be restarted accordingly. We therefore refrain from going into further details about adjoint methods and simply make use of the differentiable DDE solvers provided by Rackauckas and Nie [2017].

Approximation capabilities As opposed to neural ODEs, we are no longer learning an ordinary differential equation, but a retarded-type delay differential equation with constant delays. An interesting question is under which conditions a NDDE can model the time series corresponding to the partial observations $h(z(t))$ of the ODE system (1). A sufficient condition for this is that the delay coordinate map,

$$E : \mathbb{R}^m \to \mathbb{R}^{(K+1)n},$$
$$z(t) \mapsto \mathbf{x}^\tau_{-K}(t) = \left(h(z(t)), h(z(t - \tau)), \dots, h(z(t - K\tau)) \right), \tag{9}$$

is one-to-one. For dynamical systems confined on periodic or chaotic attractors so-called delay embedding theorems indeed show that this holds true for large enough K (for more details see Appendix B and the references therein). Although system (1) is not confined to such an attractor, our experimental results in Section 4 demonstrate approximation power and generalization capabilities of NDDEs when applied to dissipative systems.

2.3 Stability of time-delay systems

We discuss stability analysis for the general class of time delay-systems (2). We assume that the origin is an equilibrium, $f(0) = 0$, and slightly adjust the definition of exponential stability with respect to this equilibrium point as provided in [Fridman, 2014] to our needs:

Definition 1 *For a fixed set of initial histories $\mathcal{S} \subseteq \mathcal{C}_r$ and constants $\gamma, M > 0$, system* (2) *is said to be (γ, M)-exponentially decaying on $\mathcal{S}$ over the time horizon $[0, t_f)$ if*

$$\|x(t)\|_2 \le M e^{-\gamma t} \|\psi\|_r \quad \text{for } 0 \le t < t_f, \ \forall \psi \in \mathcal{S}. \tag{10}$$

For some invariant set $B \subseteq \mathcal{C}_r$ with $0 \in B$ the time delay system (2) *is referred to be (γ, M)-exponentially stable on B if it is (γ, M)-exponentially decaying on B over the time horizon $[0, \infty)$. Furthermore, it is referred to be globally (γ, M)-exponentially stable if it is exponentially stable on the entire state space $\mathcal{C}_r$.*

Here, γ measures the rate of decay and M is an upper bound on the transient overshoot. In cases where we do not care about the specific values of γ, M we simply denote the system (2) to be exponentially decaying or stable, respectively. If system (2) is (γ, M)-exponentially decaying on a set of initial histories $\mathcal{S}$ over $[0, \infty)$, then it is also (γ, M)-exponentially decaying over $[0, \infty)$ for all initial histories in its positive orbit $\gamma^+(\mathcal{S}) := \{x_t(\psi) \in \mathcal{C}_r : \psi \in \mathcal{S}, t \ge 0\}$. Since $\gamma^+(\mathcal{S})$ is by definition invariant, it is therefore (γ, M)-exponentially stable on $\gamma^+(\mathcal{S})$ in this case.

Razumikhin's method A key method to prove exponential stability of non-linear ODEs are Lyapunov functions [Lyapunov, 1992]. However, directly applying ODE Lyapunov functions to time delay systems leads to very restrictive results (e.g. a 1-dimensional system would not be allowed to oscillate [Fridman, 2014]). Nevertheless, along the same lines two approaches geared towards stability analysis of non-linear time delay systems exist. Whereas the method of Lyapunov-Krasovskii functionals [Krasovskii, 1963] is a natural extension of Lyapunov's direct method to an infinite-dimensional state space, the idea of Razumikhin-type theorems [Razumikhin, 1956] is to make use of positive-definite Lyapunov functions $V : \mathbb{R}^n \to \mathbb{R}_+$ with finite domains familiar from the ODE case and to relax the decay condition. Namely, a negative derivative of $V(x(t))$ at time t is required only when we are about to leave the sublevel set $V^{\le \eta} = \{x \in \mathbb{R}^n : V(x) \le \eta\}$ of $\eta := \sup_{s \in [-r,0]} V(x(t+s))$. The following theorem establishes sufficient conditions for exponential stability.

Theorem 1 ([Efimov and Aleksandrov, 2020]) *Assume there exists a differentiable function $V : \mathbb{R}^n \to \mathbb{R}_+$, positive reals c_1, c_2, α, and a constant $q > 1$ such that along all trajectories starting in $\psi \in \mathcal{S} \subseteq \mathcal{C}_r$ the following conditions hold for all $t \in [0, t_f]$:*

(i) $c_1 \|x(t)\|_2^2 \le V(x(t)) \le c_2 \|x(t)\|_2^2$

(ii) $\dot{V}(x(t)) \leq -\alpha V(x(t))$ *whenever* $V(x(t+s)) \leq qV(x(t)) \quad \forall s \in [-r, 0]$.

Then system (2) *is* (γ, M)*-exponentially decaying on* $\mathcal{S}$ *over* $[0, T)$ *with decay rate* $\gamma = \min(\alpha, \frac{\log q}{r})/2$ *and* $M = c_2/c_1$. *If for an invariant set* $B \subseteq \mathcal{C}_r$ *with* $0 \in B$ *conditions* $(i), (ii)$ *hold for all* $x_t \in B$ *then the time delay system* (2) *is exponentially stable on* B.

A function satisfying conditions $(i), (ii)$ in Theorem 1 on the entire state space is referred to as a Lyapunov-Razumikhin Function (LRF). The invariant set B may be the entire state space $\mathcal{C}_r$ or, for a fixed set of initial conditions $S \subseteq \mathcal{C}_r$, the positive orbit $\gamma^+(S)$. Moreover, for some LRF sublevel set $V^{\leq c} \subset \mathbb{R}^n$ the corresponding function space $\mathcal{C}\left([-r, 0], V^{\leq c}\right)$ is invariant [Gu, 2003].

Note that the above Theorem 1 establishes sufficient, but not necessary conditions for exponential stability. The problem is that often it is not strong enough to check the Razumikhin condition

$$qV(x(t)) - V(x(t+s)) \geq 0 \tag{11}$$

only on the interval $s \in [-r, 0]$, but we should take into account more of the past observations of $V(x(t))$. It can therefore be helpful to reinterpret problem (2) as one in the state space $\mathcal{C}_{r_V}$ with some $r_V > r$ and to apply Theorem 1 to that problem. However, in this new larger state space only initial histories of the form

$$\tilde{\psi}(s) = \begin{cases} \psi(s) & , s \in [-r_V, -r_V + r] \\ x(\psi)(s - r_V + r) & , s \in [-r_V + r, 0] \end{cases} \tag{12}$$

need to be considered for stability in $\mathcal{C}_r$ [Hale and Lunel, 1993]. Furthermore, Proposition 1, which we prove in Appendix A, shows that also exponential stability follows, albeit for the price of a larger bound on the transient overshoot.

Proposition 1 *If* f *is* L_f*-Lipschitz,* $f(0) = 0$, *and* $\psi, \tilde{\psi}$ *defined as in* (12), *then*

$$\left\|\tilde{\psi}\right\|_{r_V} \leq \|\psi\|_r \, e^{L_f(r_V - r)}. \tag{13}$$

Centred around this idea necessary and sufficient Razumikhin-type conditions for discrete-time delay systems are stated in [Gielen et al., 2013]. In the following we will treat r_V therefore as a hyperparameter that has to be chosen for the respective problem at hand.

3 Learning stable dynamics

In this section we propose an approach, based on neural LRFs, to enforce stability of a parametric DDE. The key idea is to jointly learn a neural network Lyapunov-Razumikhin function and the dynamics model. Similarly to [Richards et al., 2018, Chang et al., 2019] we propose to enforce stability via the loss function. This is in contrast to [Manek and Kolter, 2020] that use a projection-based approach to ensure stability in the forward pass. The main reason for this design choice is that a projective approach based on LRFs leads to discontinuities in the forward pass, which are problematic for DDE solvers [Alfredo Bellen, 2013]. Moreover, incorporating the Lyapunov neural network into the forward pass renders the model slow during inference time and a loss function based approach offers the opportunity to actively stabilize an initially unstable system, as we demonstrate in Section 4.

Lyapunov neural network construction Except for the decay condition along solutions (condition (ii) in Theorem 1), an LRF has the same form as an ODE Lyapunov function. We are thus employing the same Lyapunov neural network as proposed by Manek and Kolter [2020]. The construction is based on an Input-Convex Neural Network (ICNN) [Amos et al., 2016]. The ICNN $x \mapsto g_\phi^{NN}(x)$ is convex by construction and any convex function can be approximated by such neural networks [Chen et al., 2018b]. In our setting, the activation functions σ of g_ϕ^{NN} are required to additionallly have slope no greater than one in order to satisfy the upper bound in condition (i) of Theorem 1. To ensure strict convexity, and to make sure that the global minimum lies at $x = 0$, we choose as a final layer

$$V_\phi^{NN}(x) = \sigma(g_\phi^{NN}(x) - g_\phi^{NN}(0)) + c \|x\|_2^2. \tag{14}$$

Here, $c > 0$ is a small constant. As for the activation function σ, having a global minimum at $x = 0$ requires $\sigma(0) = 0$. Furthermore, since we want to ensure Lipschitz continuity of the loss derivatives, we use a twice continuously differentiable smoothed ReLU version

$$\sigma(x) = \begin{cases} 0 & , x \leq 0 \\ \dfrac{x^3}{d^2} - \dfrac{x^4}{(2d)^3} & , 0 \leq x \leq d \\ x - \dfrac{d}{2} & , x > d. \end{cases} \tag{15}$$

This slightly differs from the original σ proposed by Manek and Kolter [2020], since they only needed a once continuously differentiable one. This construction ensures that $V_\phi^{NN}(x) = \mathcal{O}(\|x\|_2^2)$ as $x \to 0$ and also $V_\phi^{NN}(x) = \mathcal{O}(\|x\|_2^2)$ as $\|x\|_2 \to \infty$. We can therefore always find constants c_1, c_2 such that the conditions (i) in Theorem 1 are satisfied. In the next step, we explain how to employ this neural network architecture to learn neural LRFs and at the same time stabilize a parametric delay differential equation of the form (3).

Lyapunov-Razumikhin loss   As stated before, V_ϕ^{NN} satisfies condition (i) in Theorem 1 by construction. The relaxed decay condition (ii) however, has to be enforced during training. Since it is practically infeasible to check the Razumikhin condition (11) on the continuous interval $[-r_V, 0]$, we propose the following loss with discretized Razumikhin condition:

$$\ell_{\text{LRF}}\left(\phi, \theta, \mathbf{x}_{-K_V}^{\tau_V}(t)\right) =$$
$$\text{ReLU}\left(\dot{V}_{\phi,\theta}^{NN}\left(\mathbf{x}_{-K_V}^{\tau_V}(t)\right) + \alpha V_\phi^{NN}(x(t))\right) \Theta\left(q V_\phi^{NN}(x(t)) - \max_{1 \leq j \leq K_V} V_\phi^{NN}\left(x(t - j\tau_V)\right)\right) \tag{16}$$

Here, $\Theta(\cdot)$ denotes the unit step function. Furthermore, for notational simplicity we choose $\tau_V \leq \tau$ and such that $\tau = l \cdot \tau_V$ for some integer $l \in \mathbb{N}$. According to Theorem 1, a zero loss $\ell_{\text{LRF}}(\phi, \theta, \mathbf{x}_\tau(t))$ along a trajectory of length $[0, t_f]$ implies exponential decay along this trajectory. Moreover, if for a fixed set of initial histories $\mathcal{S} \subseteq \mathcal{C}_r$ the loss (16) is zero along all trajectories starting in $\mathcal{S}$ and over a time horizon $[0, \infty)$, then the delay differential equation is stable on $\gamma^+(\mathcal{S})$. However, since we cannot check this for $t_f = \infty$ we choose t_f large enough that convergence to a sufficiently small region around the origin is ensured. While for a zero loss exponential decay is guaranteed, it is possible that we miss a $s \in [-r, 0]$ where (11) holds and therefore enforce the decay condition too often. However, Proposition 2 tells us that if the discretized Razumikhin condition holds, τ_V is small enough, and the current state is outside of an ε-ball from the origin, then the continuous condition holds for some $\tilde{q} > q$. Furthermore, $\tilde{q}$ converges quadratically to q as $\tau_V \to 0$. Remembering that the decay rate in Theorem 1 is $\gamma = \min(\alpha, \frac{\log q}{r})/2$, it becomes apparent that by discretization we are requiring a slightly larger rate of decay, which can however be controlled by the choice of τ_V.

Proposition 2 *Let K_V and τ_V be such that $r_V := K_V \tau_V \geq r$ and let $x(\cdot)$ be a solution of $\dot{x}(t) = f(x_t)$ passing through $x_{t_0} \in \mathcal{C}_r$. Assume $\|x_{t_0}\|_{r_V + 2r} < \infty$ and $\|x_{t_0}\|_{r_V} > \varepsilon$. Furthermore, let f be L_f-Lipschitz and differentiable. Then, if the discretized Razumikhin condition,*

$$V_\phi^{NN}(x(t_0 - k\tau_V)) \leq q V_\phi^{NN}(x(t_0)) \quad , \forall k \in \{0, 1, ..., K_V\}, \tag{17}$$

is satisfied and τ_V is small enough, then the continuous Razumikhin condition,

$$V_\phi^{NN}(x(t_0 + s)) \leq \tilde{q}(\tau_V) V_\phi^{NN}(x(t_0)), \tag{18}$$

holds for any $s \in [-r_V, 0]$ and some $\tilde{q}(\tau_V)$ with $\tilde{q}(\tau_V) = q + \mathcal{O}(\tau_V^2)$ as $\tau_V \to 0$.

The condition that the current state lies outside some ε-ball of the origin can be replaced by an assumption on the solutions decay in $\|\cdot\|_{r_V}$. However, in practice we are usually satisfied with convergence to some small neighborhood of the origin, since as already noted we cannot choose an infinite time horizon and also because for very small resolution modeling errors become too large anyways. A more elaborate discussion on this and a full proof of Proposition 2 is provided in Appendix A.

Stabilizing NDDEs In order to stabilize an NDDE on a fixed set of initial conditions $\mathcal{S} \subseteq \mathcal{C}_r$ we minimize the stabilizing loss (16) on a set of data points $\{\mathbf{x}^{(1)}, \ldots, \mathbf{x}^{(N_{\text{LRF}})}\}$ with $\mathbf{x}^{(i)} \in \mathbb{R}^{n(K_V+1)}$ collected along trajectories starting in $\mathcal{S}$. The resulting gradients are added up with those from the NDDE loss (8). While this enables us to stabilize the NDDE on unseen trajectories, we still need an efficient method to generate realistic initial histories. Especially in the setting of partially observed systems we do not know much more about initial histories but that they are contained within a bounded, Lipschitz subset of $\mathcal{C}_r$. However, since for our NDDE model the initial history is given by a GP-mean function, we know that $\mathcal{S}$ is contained within the finite subset

$$\{\psi \in \mathcal{H}_k | \psi(t) = \sum_{i=1}^{N_{\text{hist}}} c_i k_{l,\sigma_k}(t, t_i)\} \tag{19}$$

of the reproducing kernel Hilbert space $\mathcal{H}_k$ corresponding to $k_{l,\sigma_k}(t, t')$. Boundedness of ψ translates into a bound on the norm of the expansion coefficients $\|(c_1, ..., c_{N_{\text{hist}}})\|_2 \leq A$ and Lipschitz continuity can be accounted for by upper bounding the inverse length-scale $1/l \leq B$ and the kernel variance $\sigma_k^2 \leq C$ [C. E. Rasmussen, 2005]. To satisfy this constraints, we uniformly sample values $(c_1, ..., c_{N_{\text{hist}}})$ in an L2-ball, and $1/l, \sigma_k$ on bounded intervals $[0, B], [0, C]$, respectively.

Note, that while another possibility would be to integrate the loss (16) as a continuous regularization term into the NDDE loss, the discontinuities in (16) turn out to be problematic for DDE solvers.

Delayed feedback control The stabilizing loss (16) is essentially applicable to any parametric DDE of the form (3). Equations of this form also occur in delayed feedback control. Assume we want to learn a stabilizing state feedback $u(t) = \pi_\phi(x(t))$ for a known open loop control system $\dot{x}(t) = f(x(t), u(t - \tau))$ with input delay. In practice, such delays in the feedback loop are often introduced as a consequence of communication latencies and typically cause instability [Krstic, 2009]. The resulting closed loop system is a parametric DDE $\dot{x}(t) = f(x(t), \pi_\phi(x(t - \tau)))$, which can for small enough delays be stabilized in a data-driven way with our LRF loss (16). If the input delay exceeds some critical value, the system can no longer be stabilized by DDE methods and infinite-dimensional feedback taking into account the inputs history would be required [Krstic, 2009]. Experimental results for delayed feedback stabilization are provided in Section 4.

(a) Ground truth   (b) ANODE true IC   (c) ANODE learned IC   (d) train loss

Figure 2: Comparison of ANODEs and Vanilla NDDEs. In (a)-(c) the phase portrait for ground truth and ANODE models are provided. Note, that since we are only interested in the first state the direction of rotation is irrelevant for the ANODE models. As it is impossible to draw a phase portrait of the NDDE model, the train losses for all three models are compared in Figure (d).

4 Experiments

Learning partially observed dynamics We first compare the applicability of Vanilla NDDEs and ANODEs for the task of learning a partially observed harmonical oscillator,

$$\dot{z}(t) = \frac{d}{dt}\begin{pmatrix} z_1(t) \\ z_2(t) \end{pmatrix} = \begin{pmatrix} 0 & 1 \\ -1 & 0 \end{pmatrix} z(t), \quad h(z(t)) = (1 \quad 0) z(t). \tag{20}$$

We train the models over two training trajectories starting from $z_{0,1} = (1, 0)$ and $z_{0,1} = (0, 2)$ and with zero observation noise. For ANODEs we compare a model trained with given true augmented initial conditions against another model where we initialize the augmented states with 0 and learn

them via the adjoint method. The resulting vector field plots illustrated in Figures 2a-2c demonstrate that whereas for true initial conditions the dynamics match the ground truth well, learning the augmented initial conditions turns out to be a key problem. In contrast for our NDDE model the initialization is conveniently provided by the GP interpolation. This is also reflected in the learning curves illustrated in Figure 2d, where we see that the training of NDDEs yields a significantly lower train loss for fewer iterations compared to both the ANODE models. For more information about the setup and additional experiments we refer to Appendix C.

Learning stable NDDEs   Manek and Kolter [2020] show that in the ODE case a neural network dynamics model trained on stable data may become unstable for long-term prediction. For NDDEs we observed this to be a problem in the setting of sparse observations, a high noise level, and generalization over initial histories. To investigate this we consider a partially observed damped double compound pendulum where only the angles of deflection θ_1 and θ_2, but not the angular velocities are observed. This is a complex non-linear dynamical system which is for low friction exhibiting chaotic behavior [Shinbrot et al., 1992]. The governing equations are derived in Appendix C.

For observation noise of variance $\sigma = 0.05$ and training and test data along 4 training trajectories, we compare the generalization performance of a Vanilla NDDE and a NDDE stabilized with LRF regularization. We repeat the training for 20 independent weight initializations and noise realizations. The resulting predictions illustrated in Figures 3a-3b demonstrate that while the median prediction is stable the upper 0.95 quantile is exploding for the Vanilla NDDE. In contrast, the stabilized NDDE remains stable on all the test trajectories. Moreover, we see that whereas the test loss in Figure 3d is exploding for the unstable NDDE, the train losses in Figures 3c are approximately staying the same. This suggests the conclusion that multiple, equally valued optima exist and that the LRF regularization is guiding us to a stable one.

Figure 3: In (a)-(b) the test predictions are shown for one of the test trajectories and in (c)-(d) train and test loss for all trajectories are illustrated. The lines indicate the median and the shaded area the 0.05 and 0.95 quantiles.

Stabilization with delayed feedback control As an application for learning a stabilizing feedback policy of a known open loop system, we consider a friction-less inverted pendulum with input delay, whose open loop dynamics are given by

$$\begin{pmatrix} \dot{x}_1(t) \\ \dot{x}_2(t) \end{pmatrix} = \begin{pmatrix} x_2(t) \\ \dfrac{g}{l}\sin(x_1(t)) + \dfrac{1}{ml^2}u(t-\tau) \end{pmatrix}. \tag{21}$$

Here, the states are $(x_1, x_2) = (\varphi, \dot{\varphi})$ where $\varphi(t)$ is the angle of deflection with respect to the fully upright position, g indicates the acceleration of gravity, and l and m the length and mass of the pendulum. Furthermore, $u(t)$ is the torque which is applied at the pivot point. The goal is to learn a stabilizing feedback policy

$$u(t) = \pi(x(t)) = k_1 x_1(t) + k_2 x_2(t). \tag{22}$$

Similar to [Chang et al., 2019] we initialize the parameters k_1, k_2 with the values from the Linear Quadratic Regulator (LQR) feedback policy calculated for the linearization of (22). For the training new initial histories are continuously generated as follows: We sample ODE initial conditions on a circle of radius $\pi/2$ and the control is assumed to be zero for $t < 0$. Thus the dynamics are described by an autonomous ODE along initial histories. As depicted in Figure 4a the initially unstable state feedback can be stabilized by means of our Razumikhin loss. Furthermore, the speed of decay can be controlled by the choice of the hyperparameters α and q. Moreover, ℓ_{LRF} is zero along new test trajectories indicating that we indeed learned a valid LRF candidate for this set of initial histories.

(a) Delayed state-feedback (b) Learned (left) and randomly initialized (right) V_ϕ^{NN}

Figure 4: In Figure (a) the learned delayed state feedback policy is compared to the LQR control. The left plot in Figure (b) shows the learned LRF candidate V_ϕ^{NN} and the right figure a random initialization.

5 Conclusion

In the course of this paper, we demonstrate that NDDEs are powerful tool to learn the non-Markovian dynamics of a partially observed dynamical system. By state augmentation with the past history we avoid the estimation of unobserved augmented states, which we show to be a major problem of ANODEs when applied to partially observed systems. Based on classical time-delay stability theory we then propose a regularization term based on a neural network Lyapunov-Razumikhin function to stabilize NDDEs. Further on, we discuss how this approach can also be employed to learn a stabilizing feedback policy for control systems with input delays. Besides experiments showcasing the applicability of our approach, we also provide code and a theoretical analysis.

References

M. Z. Alfredo Bellen. *Numerical Methods for Delay Differential Equations*. OXFORD UNIV PR, Apr. 2013. ISBN 0199671370. URL `https://www.ebook.de/de/product/19829143/alfredo_bellen_marino_zennaro_numerical_methods_for_delay_differential_equations.html`.

B. Amos, L. Xu, and J. Z. Kolter. Input convex neural networks. *CoRR*, abs/1609.07152, 2016. URL `http://arxiv.org/abs/1609.07152`.

N. M. Boffi, S. Tu, N. Matni, J.-J. E. Slotine, and V. Sindhwani. Learning stability certificates from data, 2020.

S. L. Brunton, J. L. Proctor, and J. N. Kutz. Discovering governing equations from data by sparse identification of nonlinear dynamical systems. *Proceedings of the national academy of sciences*, 113(15):3932–3937, 2016.

C. K. I. U. o. E. W. C. E. Rasmussen. *Gaussian Processes for Machine Learning*. MIT Press Ltd, Nov. 2005. ISBN 026218253X. URL `https://www.ebook.de/de/product/5192092/carl_edward_university_of_cambridge_rasmussen_christopher_k_i_university_of_edinburgh_williams_gaussian_processes_for_machine_learning.html`.

J. Calver and W. Enright. Numerical methods for computing sensitivities for ODEs and DDEs. *Numerical Algorithms*, 74(4):1101–1117, sep 2016. doi: 10.1007/s11075-016-0188-6.

Y.-C. Chang, N. Roohi, and S. Gao. Neural lyapunov control. In H. Wallach, H. Larochelle, A. Beygelzimer, F. d'Alché-Buc, E. Fox, and R. Garnett, editors, *Advances in Neural Information Processing Systems*, volume 32, pages 3245–3254. Curran Associates, Inc., 2019. URL `https://proceedings.neurips.cc/paper/2019/file/2647c1dba23bc0e0f9cdf75339e120d2-Paper.pdf`.

R. T. Q. Chen, Y. Rubanova, J. Bettencourt, and D. Duvenaud. Neural ordinary differential equations. June 2018a.

S. Chen, S. A. Billings, and P. M. Grant. Non-linear system identification using neural networks. *International Journal of Control*, 51(6):1191–1214, 1990. doi: 10.1080/00207179008934126. URL `https://doi.org/10.1080/00207179008934126`.

Y. Chen, Y. Shi, and B. Zhang. Optimal control via neural networks: A convex approach. May 2018b.

O. Diekmann. *Delay Equations : Functional-, Complex-, and Nonlinear Analysis*. Springer New York, New York, NY, 1995. ISBN 9781461242062.

E. Dupont, A. Doucet, and Y. W. Teh. Augmented neural odes. Apr. 2019.

D. Efimov and A. Aleksandrov. On estimation of rates of convergence in lyapunov–razumikhin approach. *Automatica*, 116:108928, jun 2020. doi: 10.1016/j.automatica.2020.108928.

W. R. Esposito. *Dynamic programming: continuous-time optimal controlDynamic Programming: Continuous-time Optimal Control*, pages 844–846. Springer US, Boston, MA, 2009. ISBN 978-0-387-74759-0. doi: 10.1007/978-0-387-74759-0_146. URL `https://doi.org/10.1007/978-0-387-74759-0_146`.

E. Fridman. *Introduction to time-delay systems : analysis and control*. Birkhäuser, Cham, 2014. ISBN 9783319093925.

R. H. Gielen, M. Lazar, and S. V. Rakovic. Necessary and sufficient razumikhin-type conditions for stability of delay difference equations. *IEEE Transactions on Automatic Control*, 58(10): 2637–2642, oct 2013. doi: 10.1109/tac.2013.2255951.

K. V. L. C. J. Gu, Keqin. *Stability of Time-Delay Systems*. Birkhäuser Boston Imprint Birkhäuser, Boston, MA, 2003. ISBN 9781461200390.

A. Gupta and P. F. J. Lermusiaux. Neural closure models for dynamical systems, 2020.

J. K. Hale and S. M. V. Lunel. *Introduction to Functional Differential Equations*. Springer New York, 1993. doi: 10.1007/978-1-4612-4342-7.

N. N. Krasovskii. Stability of motion (translated from the (1959) russian ed. by j. l. brenner). *Stanford University Press*, 1963. doi: 10.1017/s0008439500026886.

M. Krstic. *Delay Compensation for Nonlinear, Adaptive, and PDE Systems*. Birkhäuser Boston, 2009. doi: 10.1007/978-0-8176-4877-0.

A. M. Lyapunov. The general problem of the stability of motion. *International Journal of Control*, 55(3):531–534, mar 1992. doi: 10.1080/00207179208934253.

G. Manek and J. Z. Kolter. Learning stable deep dynamics models. Jan. 2020.

G. M. Phillips. *Interpolation and Approximation by Polynomials*. Springer New York, 2003. doi: 10.1007/b97417.

C. Rackauckas and Q. Nie. Differentialequations.jl–a performant and feature-rich ecosystem for solving differential equations in julia. *Journal of Open Research Software*, 5(1), 2017.

C. Rackauckas, Y. Ma, J. Martensen, C. Warner, K. Zubov, R. Supekar, D. Skinner, A. Ramadhan, and A. Edelman. Universal differential equations for scientific machine learning. *arXiv preprint arXiv:2001.04385*, 2020.

B. Razumikhin. On the stability of systems with a delay (russian). *Prikladnaya Matematika i Mekhanika, vol. 20, pp. 500-512*, 1956.

S. M. Richards, F. Berkenkamp, and A. Krause. The lyapunov neural network: Adaptive stability certification for safe learning of dynamical systems. Aug. 2018.

J. C. Robinson. A topological delay embedding theorem for infinite-dimensional dynamical systems. *Nonlinearity*, 18(5):2135–2143, jul 2005. doi: 10.1088/0951-7715/18/5/013. URL https://doi.org/10.1088/0951-7715/18/5/013.

T. Sauer, J. A. Yorke, and M. Casdagli. Embedology. *Journal of Statistical Physics*, 65(3-4):579–616, nov 1991. doi: 10.1007/bf01053745.

T. Shinbrot, C. Grebogi, J. Wisdom, and J. A. Yorke. Chaos in a double pendulum. *American Journal of Physics*, 60(6):491–499, jun 1992. doi: 10.1119/1.16860.

F. Takens. Detecting strange attractors in turbulence. In D. Rand and L.-S. Young, editors, *Dynamical Systems and Turbulence, Warwick 1980*, pages 366–381, Berlin, Heidelberg, 1981. Springer Berlin Heidelberg. ISBN 978-3-540-38945-3.

P. M. Wensing, S. Kim, and J.-J. E. Slotine. Linear matrix inequalities for physically consistent inertial parameter identification: A statistical perspective on the mass distribution. *IEEE Robotics and Automation Letters*, 3(1):60–67, 2017.

Q. Zhu, Y. Guo, and W. Lin. Neural delay differential equations, 2021.