PRACTICAL ADVERSARIAL ATTACKS ON BRAIN–COMPUTER INTERFACES

ABSTRACT

Deep learning has been widely employed in brain–computer interfaces (BCIs) to decode a subject's intentions based on recorded brain activities enabling direct interaction with computers and machines. BCI systems play a crucial role in motor rehabilitation and have recently experienced a significant market boost as consumer-grade products. Recent studies have shown that deep learning-based BCIs are vulnerable to adversarial attacks. Failures in such systems might cause medical misdiagnoses, physical harm, and financial damages, hence it is of utmost importance to analyze and understand in-depth, potential malicious attacks to develop countermeasures. In this work, we present the first study that analyzes and models adversarial attacks based on physical domain constraints in EEG-based BCIs. Specifically, we assess the robustness of EEGNet which is the current state-of-the-art network for embedded BCIs. We propose new methods to induce denial-of-service attacks and incorporate domain-specific insights and constraints to accomplish two key goals: (i) create smooth adversarial attacks that are physiologically plausible; (ii) consider the realistic case where the attack happens at the origin of the signal acquisition and it propagates on the human head. Our results show that EEGNet is significantly vulnerable to adversarial attacks with an attack success rate of more than 50%. With our work, we want to raise awareness and incentivize future developments of proper countermeasures.

1 INTRODUCTION

Recent work has shown that adversarial perturbations can cause state-of-the-art (SoA) deep learning models to misbehave in various domains including vision (Szegedy et al., 2014; Goodfellow et al., 2015), NLP (Li et al., 2019a; Zhang et al., 2020), speech (Qin et al., 2019; Li et al., 2019b), and biomedicine (Finlayson et al., 2019; Han et al., 2020). Neural networks have been applied in brain–computer interfaces (BCIs) achieving impressive results (Lawhern et al., 2018; Dose et al., 2018). A BCI enables direct interactions with external devices based on brain activities, typically recorded using electroencephalographic (EEG) systems. It can provide a communication pathway for severely paralyzed patients or assist in rehabilitation (Chaudhary et al., 2016). Besides medical applications, recent developments in wearable devices have pushed BCIs towards consumer-grade products to improve life quality (Aricò et al., 2020), e.g., the Interaxon Muse headband for stress relief (Arsalan et al., 2019) or the Emotiv headset for controlling drones (Marin et al., 2020) and ground vehicles (Zhuang et al., 2021). Safety in BCI systems is paramount (Dutta, 2020; Bernal et al., 2021), because a failure would cause misdiagnoses, user frustration, or even danger while driving a wheelchair or controlling a drone, causing physical and financial damages.

Recent studies have shown that EEG-based BCIs are vulnerable to adversarial attacks (Zhang & Wu, 2019; Liu et al., 2021). They assume that the signals are transmitted with a wired or wireless setup to a remote processing unit, e.g., a computer. This gives the opportunity to an attacker to tamper the data during transmission. With the advent of TinyML (Foundation, 2021) and low-power smart edge computing for wearable BCIs (Akmandor & Jha, 2018; Beach et al., 2021), this attack scenario becomes inapplicable. Novel BCI solutions (Kartsch et al., 2019; Wang et al., 2020) embed the signal processing and classification directly at the sensor edge without requiring remote transmission. This reduces latency, preserves user privacy, and improves system security (Akmandor & Jha, 2018; Beach et al., 2021). Li et al. (2019b) have shown an attack scenario in the audio domain by considering the on-board edge processing of a wake-word detection system, where an adversarial audio trace is

delivered to the environment causing denial-of-service (DoS). No similar studies can be currently found in the BCI domain.

Challenges: Creating natural attacks and modeling its propagation. Previous works on applying traditional attack methods on EEG-based BCIs (Jiang et al., 2019; Zhang & Wu, 2019) and other biosignals such as electrocardiograms (ECGs) (Han et al., 2020) introduce square-wave artefacts that are not realistically and physiologically plausible. For the attacks to be imperceptible to the human eye, the perturbation has to be smooth (Han et al., 2020), and has to resemble natural noise. All previous works on attacking BCI ignore this and mostly focus on achieving the imperceptibility by limiting the amplitude of the perturbation yielding lower attack success rate (ASR) (Jiang et al., 2019; Zhang & Wu, 2019; Liu et al., 2021).

Further, unlike in audio applications where the signal can simply propagate over-the-air and is sensed by a microphone, extra modeling is required to evaluate the signal propagation in BCIs based on the physical properties of the biological tissues. In this work, rather than injecting a "jamming" module between the preprocessing and the classification steps, we consider a more realistic and practically applicable attack scenario where the adversarial perturbations are introduced at the *source* of the data acquisition, as showcased in Figure 1. This can be achieved via electromagnetic waves delivered to the environment (Dutta, 2020) or via transcranial current stimulation with electrical current delivered directly to the scalp (Bodranghien et al., 2017; Yang et al., 2021), by exploiting wearable devices, such as smart glasses, in-ear or over-ear headsets (Flowneuroscience, 2021; Marin et al., 2020). The adversarial perturbations translate into electrical signals propagating over the scalp and are sensed by the electrodes in addition to the EEG signals.

This work: Practical attacks on BCI models. To address the above technical challenges, and for analyzing the vulnerability of embedded BCI models in practical scenarios, we design a new attack algorithm that generates smooth adversarial examples based on the signals' first derivative and enables the creation of practically effective perturbations, that can be delivered by an external device to attack EEG-based BCIs at the source of signal acquisition. We attack the SoA embedded convolutional neural network (CNN) called EEGNet (Lawhern et al., 2018), which has been embedded on energy-efficient microcontrollers for smart wearable BCIs (Wang et al., 2020; Schneider et al., 2020). We further model the propagation of the perturbation based on a realistic head model that depends on the attack source and the electrical and physical properties of the conducting tissues.

We evaluate our methods and show experimental results on BCIs based on the motor imagery (MI) paradigm, which is of special interest among others because it can be asynchronously self-paced without external stimuli (Freer & Yang, 2020). By imagining the movement of different body parts, the decoded intention is translated into control signals. It is widely applied in several BCI applications (Padfield et al., 2019), such as controlling wheelchairs, prosthetic arms, and ground vehicles (Yu et al., 2018; Elstob & Secco, 2016; Zhuang et al., 2021) and in communication (Brumberg et al., 2016). It has been proven to be the most difficult task to be attacked among the most common BCI paradigms (Zhang & Wu, 2019; Meng et al., 2021). We evaluate for the first time the DoS attack in BCIs, where the attacker "fools" the victim model to always predict rest EEG signals, i.e., no subject's intention detected which yields no control action. While for healthy subjects it might solely cause user frustration and financial losses, for severely paralyzed patients it can lead to medical misdiagnoses. We believe that our methodology can also be adapted to other BCI systems (Lawhern et al., 2018; Zhang & Wu, 2019).

Main contributions Our main contributions are:

- We design a new method to generate smooth adversarial perturbations that are physiologically plausible and imperceptible to the human eye.

- We consider a practical scenario where the perturbation is added at the signal acquisition source and model its propagation constrained by the physical properties of the human scalp.

- The first study of adversarial perturbations in BCI to consider the practical scenario of smart edge computing and physical signal propagation. We create both local and global perturbations and show that our attacks consistently achieve a success rate of $> 50\%$ in different settings pointing to the significant vulnerability of the state-of-the-art EEGNet.

We hope that our work raises awareness for potential risks and motivates the future development of appropriate countermeasures.

Figure 1: Practical adversarial attack scenario in BCIs: a smart device close to the ear emits a perturbation signal which propagates over the head surface to the EEG electrodes.

2 RELATED WORKS

Zhang & Wu (2019) have demonstrated for the first time that EEG-based BCIs are vulnerable to adversarial attacks by proposing an unsupervised fast gradient sign method (FGSM) (Goodfellow et al., 2015). Perturbations are computed specifically for each EEG channel, i.e., channel-specific, every time an input trial is attacked, considering black-, gray-, and white-box scenarios. More recent work has proposed a more practical attack where a universal adversarial perturbation (UAP) is computed once and can be applied to all EEG trials without learning it for every new input (Liu et al., 2021). The authors have evaluated the UAP with within-subject experiments and cross-subject experiments to account for inter-subject variability. Both works assume that the acquired signals are sent to a remote compute engine, e.g., a computer or a cloud, and the attacker can alter the signals before or during the transmission by attaching a jamming module between the signal preprocessing step and the classifier. Recent developments in smart edge computing (Beach et al., 2021) eliminate the need for data transmission, making this attack scenario inapplicable. A more practical adversarial example has been identified by Meng et al. (2021). It consists of a square-shaped signal that can be added to EEG trials before the preprocessing step. However, the attack is proposed as a backdoor key, which means that the attacker has direct access to the training dataset and pollutes it with adversarial examples, which is improbable if the attacker is not directly involved in the data acquisition or in the training of the classifier. Moreover, as pointed out by Han et al. (2020), square waves are physiologically implausible for biosignals. In fact, to guarantee the imperceptibility of the attacks, previous works in BCIs create perturbations that are small in amplitude limiting the ASR (Zhang & Wu, 2019; Jiang et al., 2019; Liu et al., 2021).

In this work, we create smooth adversarial perturbations and consider the practical attack scenario where the adversarial perturbations are delivered at the *source* of the signal acquisition, e.g., via environmental electromagnetic waves (Dutta, 2020; Sazgar & Young, 2019) or via direct current stimulation (Bodranghien et al., 2017; Flowneuroscience, 2021). We train a single perturbation and analyze its adversarial effects by modeling the signal propagation on the scalp based on physical properties of the underlying conducting tissues. We explicitly evaluate the DoS attack (Li et al., 2019b) in BCIs by targeting the EEG trials to the "rest" class, since resting-state EEG is considered to be no subject's intention or response, i.e., no actions need to be taken, in all the BCI paradigms.

3 BACKGROUND

3.1 CLASSIFICATION IN BCIS

We first describe the commonly used approach in BCIs for classification, consisting of a preprocessing step and a classifier. The brain activity is recorded with an EEG device which samples N_{ch} channels at rate F_s. We define one trial j as $(\mathbf{X}^{(j)}, y^{(j)})$, where $y^{(j)} \in \{0, 1, ..., N_{cl} - 1\}$ is the true label of N_{cl} MI tasks, and $\mathbf{X}^{(j)} \in \mathbb{R}^{N_s \times N_{ch}}$ the multi-channel recording defined as

$$\mathbf{X}^{(j)} := \left(\mathbf{x}_0^{(j)}, \mathbf{x}_1^{(j)}, ..., \mathbf{x}_{N_{ch}-1}^{(j)}\right), \tag{1}$$

with $\mathbf{x}_i^{(j)} \in \mathbb{R}^{N_s}$ corresponding to the recording of the j-th trial and the i-th channel containing N_s temporal samples. For simplicity, we denote $\mathbf{X} := \mathbf{X}^{(j)}$ and $y := y^{(j)}$.

The EEG recordings are often preprocessed with a band-pass filter, e.g., using a Fast Fourier Transform (FFT) filter $h_{bp}(\cdot)$, before being fed to a classifier, yielding

$$\mathbf{X}_{bp} = H_{bp}(\mathbf{X}) = (h_{bp}(\mathbf{x}_0), h_{bp}(\mathbf{x}_1), ..., h_{bp}(\mathbf{x}_{N_{ch}-1})). \tag{2}$$

Finally, the preprocessed signal $\mathbf{X}_{bp}$ is classified with a trainable model f and is mapped to $\mathbf{p} := f(\mathbf{X}_{bp})$, where $\mathbf{p} \in \mathbb{R}^{N_{cl}}$ contains the output probabilities, e.g., originating from a softmax activation as final operation in f. The model's final prediction $\hat{y}$ is the index with the maximum score in $\mathbf{p}$:

$$\hat{y} = \hat{f}(\mathbf{X}_{bp}) = \underset{y \in \{0, ..., N_{cl}-1\}}{\text{argmax}} f(\mathbf{X}_{bp})[y]. \tag{3}$$

3.2 Instance-based attacks

Instance-based attacks try to fool an EEG classifier f to misclassify an EEG signal $\mathbf{X}$ to a targeted class y_t. In this section, we describe the attack directly on the classifier f without considering the preprocessing H_{bp}; the inclusion of the preprocessing will be described in Section 4.3. We define an adversarial example as any $\mathbf{X}^* = \mathbf{X} + \mathbf{V} \in \mathbb{R}^{N_s \times N_{ch}}$ such that

$$\hat{f}(\mathbf{X}) \neq \hat{f}(\mathbf{X}^*) = y_t. \tag{4}$$

FGSM. The FGSM (Goodfellow et al., 2015) generates an adversarial perturbation $\mathbf{V} \in \mathbb{R}^{N_s \times N_{ch}}$ of magnitude ϵ which points in the negative direction of a loss function's gradient:

$$\mathbf{V} = -\epsilon \cdot \text{sign}(\nabla_{\mathbf{X}} \cdot l(\mathbf{X}, y_t)), \tag{5}$$

where the loss function contains the negative log likelihood

$$l(\mathbf{X}, y_t) = -\log(\mathbf{p}[y_t]) = -\log(f(\mathbf{X})[y_t]). \tag{6}$$

As $\mathbf{p}$ is the output of the softmax activation function, equation 6 becomes a cross-entropy loss which maximizes the output $\mathbf{p}[y_t]$ while minimizing the remaining outputs.

PGD. The projected gradient descent (PGD) (Madry et al., 2018) is a variant of the basic iterative method (Kurakin et al., 2016), generally considered to be more effective than FGSM. PGD aims to find a perturbation by iteratively taking small steps of size α in the gradient's direction and projecting the resulting perturbation back to the sample's neighborhood after each iteration. We randomly initialize the attack inside the L_∞ ball of radius ϵ and update the attack $\mathbf{V}_{t+1}$ for any iteration t with

$$\mathbf{V}_{t+1} = \text{clip}_\epsilon(\mathbf{V}_t - \alpha \cdot \text{sign}(\nabla_{\mathbf{V}} l(\mathbf{X} + \mathbf{V}_t, y_t))), \tag{7}$$

where α is a step size smaller than ϵ which decays linearly with each iteration and the function $\text{clip}_\epsilon(\cdot)$ clips the signal at the maximum desired amplitude ϵ.

3.3 Universal attacks

UAPs have been introduced by Moosavi-Dezfooli et al. (2017) in the context of natural images, seeking to find an image-agnostic perturbation that fools the classifier on any input image. In the BCI domain (Liu et al., 2021), we seek to find a perturbation $\mathbf{V} \in \mathbb{R}^{N_s \times N_{ch}}$ such that

$$\hat{f}(\mathbf{X} + \mathbf{V}) \neq \hat{f}(\mathbf{X}) \text{ for "most" } \mathbf{X} \sim D, \tag{8}$$

where D is the distribution of the EEG data. The UAP can be determined by optimizing the log-loss with respect to $\mathbf{V}$ using batch gradient descent on the trials in the training set.

4 Modeling practical attacks in BCI

This section is the main contribution of the paper: we present a design of practical DoS attacks on MI-BCIs that operates at the source of the signal acquisition, shown in Figure 1. We propose a new method to eliminate the square wave artifacts to generate adversarial examples that are natural and physiologically plausible. The perturbation is emitted by a smart, adversarial device placed close to the ear, e.g., a smart glass or in-ear headphones, and is propagated to the individual EEG electrodes

Figure 2: Magnitude of the spatial propagation for different λ_m. The perturbation is emitted from the left side of the head and propagates over the head surface. The leftmost electrode senses the highest magnitude (red), which linearly decreases towards zero (white) with growing propagation distance and λ_m. Electrodes with magnitude >0 are marked either with a label and dot for T9, C3, C4, and T10, or only with a dot.

over the scalp's skin. As can be experimentally observed on measured EEG traces (Merlet et al., 2013; Sazgar & Young, 2019), the same electrical source, e.g., electrocardiographic activities, is sensed by each EEG electrode with different degrees of attenuation and delay. We present a practical propagation model that determines the magnitude and delay for every individual electrode based on the distance along the scalp to the adversarial device. The perturbation is trained end-to-end to fool the classifier to always output "rest," hence DoS, while respecting the spatial model and the amplitude constraints to remain imperceptible.

4.1 DESIGN AND ASSESSMENT OF PHYSIOLOGICALLY PLAUSIBLE ATTACKS

PGD-designed attacks on EEG tend to form perturbation signals which resemble a square-wave artifact (see Figure 4), an effect that has been observed on ECG data, too (Han et al., 2020). However, EEG signals are of random nature and can be modeled as frequency dependent stationary or non-stationary random processes (Karlekar & Gupta, 2014). To this end, we introduce a new loss term in the PGD optimization such that the perturbation resembles the random nature of EEG signals, which we achieve by promoting signal changes represented in the first order derivative. We estimate the per-channel derivative $\mathbf{V}' = (\mathbf{v}'_0, \mathbf{v}'_1, ..., \mathbf{v}'_{N_{ch}-1}) \in \mathbb{R}^{N_s-1 \times N_{ch}}$ using the sample-wise difference:

$$\mathbf{v}'_c[t] := \mathbf{v}_c[t] - \mathbf{v}_c[t-1] \quad t \in \{1, 2, ..., N_s - 1\}, c \in \{0, 1, ..., N_{ch} - 1\} \quad (9)$$

The new loss term is the negative ℓ_1-norm of the derivative of all channels which is weighted with a scalar $\beta \geq 0$ and the inverse of maximum perturbation amplitude ϵ.

Measuring the Plausibility of Attacks None of the previous works have given quantitative measures to assess the physiological plausibility of an EEG adversarial attack. In this work, we propose data-driven measures for quantifying the naturalism of an attack. We compute either the cross correlation, the Euclidian distance, or the cosine similarity between the attacked signal and the original EEG, and average the values over the N_{ch} channels and over the samples in the dataset.

4.2 SPATIAL PROPAGATION MODEL

So far, a perturbation signal was designed for every individual channel. It is unrealistic for an attacker to perturb the signal for all individual channels simultaneously; hence, we consider a more practical use case where the perturbation signal $\mathbf{v} \in \mathbb{R}^{N_s}$ is emitted from one location, e.g., from an adversarial device placed on the left side of the subject or close to the left ear. More specifically, in this study, we assume that the EEG electrode at the position T9 according to the international 10-10 system (Schalk et al., 2004), which is the closest to the left ear, senses the largest perturbation. The signal subsequently propagates over the skin to each electrode, which results in an individual magnitude and delay depending on the distance between the adversarial device and the electrode. More formally, we model the sensed perturbation at channel i and time instant t as

$$h_i(\mathbf{v}, \lambda_m, \lambda_d)(t) := m(l_i, \lambda_m) \cdot \mathbf{v}\left(t - d(l_i, \lambda_d)\right), \quad (10)$$

where $m(l_i, \lambda_m)$ and $d(l_i, \lambda_d)$ are the magnitude and the delay respectively, both of which depend on the distance l_i and on characteristic parameters λ_m and λ_d. We define the resulting multi-channel perturbation $\mathbf{V} \in \mathbb{R}^{N_S \times N_{ch}}$, which is added to the multi-channel EEG signal, as

$$\mathbf{V}(\lambda_m, \lambda_d) = H(\mathbf{v}, \lambda_m, \lambda_d) := (h_0(\mathbf{v}, \lambda_m, \lambda_d), h_1(\mathbf{v}, \lambda_m, \lambda_d), ..., h_{C-1}(\mathbf{v}, \lambda_m, \lambda_d)). \quad (11)$$

We estimate the distance l_i between the electrode at position T9 and the remaining, attacked positions using the 10-10 system and a head model with a diameter of 8.7 cm (Algazi et al., 2001). We decouple the distance-dependent modeling of the magnitude and delay, explained in the following paragraphs.

Magnitude. For modeling the magnitude, we assume that the adversarial device injects or induces a current I, yielding a potential V measured near T9. The current propagates over the head surface through the skin to each of the remaining attacked electrodes, which can be modeled as a cylindrical resistor with resistance

$$R_i = \frac{l_i}{\sigma A}, \tag{12}$$

where σ is the conductivity of the skin which can be in the range of [0.28, 0.87] Siemens/m (Vorwerk et al., 2019), and A is the area of the skin conductor. The potential at electrode i is $V_i = V - I \cdot R_i$, and hence the magnitude can be described as

$$m(l_i, \lambda_m) = 1 - \frac{V - V_i}{V} = 1 - \frac{I}{V \sigma A} l_i = 1 - \lambda_m l_i, \tag{13}$$

where we further constrain $0 \leq m(l_i, \lambda_m) \leq 1$. The characteristic magnitude parameter λ_m represents the complex interplay between input current, voltage, conductivity, and area, covering various attack scenarios. A large λ_m represents cases with large attenuation and limited propagation, e.g., in case of an earworn device or a wireless attack over the air. Conversely, a small λ_m covers cases with lower attenuation where the perturbation can propagate farther, e.g., a smart glass that has input and ground signal close to T9 and T10, respectively. Hence, we consider different characteristic magnitude parameters $\lambda_m \in [1, 15]$ that represent various attack scenarios as illustrated in Figure 2.

Delay. The propagation of a signal on the head surface yields a position-dependent phase angle or delay, as shown by experimental measurements of related studies (Plutchik & Hirsch, 1963; Qiao et al., 1994). The delay stems from a combination of resistive and capacitive components that are encountered during the propagation of the signal, which can be modeled as an RC-circuit with resistance R, capacity C, and time constant $\tau = R \cdot C$ that relates to the group delay. Specifically, the contacts between the electrodes and the skin are predominantly capacitive whereas the skin itself is both resistive and capacitive (Kim et al., 2010). As explained in the previous part, an increasing distance between the attacker and the target electrode yields a larger resistance R. As a result, the time constant τ and the delay increase too.

Here, we model a linear distance-delay relation. We rely on a study by Plutchik & Hirsch (1963), which conducted human skin impedance and phase angle measurements by placing electrodes at an approximate distance of 10 cm and applying voltages with frequencies in the range 2–1000 Hz. When assuming a linear frequency-phase relation in low-frequency region (Qiao et al., 1994), one can derive the group delay to be 2.8 ms when considering a measured angle of $10°$ at 10 Hz. As those measurements were conducted for only one distance, we extrapolate the delay for the remaining distances using a rectified linear model:

$$\lambda_d \cdot (l_i - l_0) > 0 \;?\; d(l_i, \lambda_d) = \lambda_d \cdot (l_i - l_0) + d_0 : d(l_i, \lambda_d) = 0, \tag{14}$$

where $d_0 = 2.8$ ms is the delay at distance $l_0 = 10$ cm. The delay depends not only on the distance, but also on other parameters such as the electrode-to-skin contact, the humidity of the skin, etc. To this end, we evaluate the propagation of the attack with different characteristic delay parameters $\lambda_d \in [0.1, 0.563]$ s/m. The largest considered $\lambda_d = 0.563$ s/m yields a maximum delay of 0.1 s at the farthest electrode T10, which is in alignment with the observed EEG measurements (Merlet et al., 2013; Sazgar & Young, 2019).

4.3 ATTACK DESIGN

We present practical DoS attacks in BCIs that respect domain constraints such as maximum amplitude, spectral distribution, physiological plausibility, and the spatial propagation of the perturbation. To this end, we formulate a general objective function that contains the spatial propagation, the preprocessing step, and the first order derivative loss term:

$$\mathcal{L}_{tot}(\mathbf{X}, \mathbf{v}, \lambda_m, \lambda_d) = l\left(H_{bp}\left(\mathbf{X} + H(\mathbf{v}, \lambda_m, \lambda_d)\right), y_{rest}\right) - \frac{\beta}{\epsilon}||\mathbf{v}'||_1, \tag{15}$$

where $l(\cdot, \cdot)$ is the log-loss defined in equation 6 and β=1e-6 is a scalar that weights the contribution of the derivative loss term. In the following, we compare different attack scenarios:

	$\eta\ [10^{-3}\mathrm{V}^2]$		ℓ_2-norm [mV]		$\gamma\ [\%]$	
ε	w/o	w/	w/o	w/	w/o	w
1	3.31	1.98	20.83	15.16	99.89	99.93
5	16.6	7.76	99.05	61.15	97.99	99.22
10	32.5	12.6	191.63	112.48	93.82	97.47
25	74.9	27.3	460.63	263.01	79.61	90.05
50	125	39.0	822.93	461.73	64.17	79.70

Table 1: Plausibility metrics for PGD attack with and without the derivative loss term. The smaller the cross correlation η and the Euclidian distance ℓ_2-norm, and the higher the cosine similarity γ, the more natural the generated attack.

Figure 3: Performance of FGSM, PGD, and UAP with and without derivative loss term. X-axis is in log scale.

Figure 4: A successful attack with (b) and without (a) derivative (PGD, ϵ=10mV). The background traces show the original signal before the preprocessing filter.

Instance-based attacks. A perturbation is computed using either FGSM or PGD based on the knowledge of the currently attacked EEG signal $\mathbf{X}$. FGSM computes the perturbation as stated in equation 5, where the ϵ defines the perturbation amplitude which is varied between 1–50 mV. Alternatively, we compute the perturbation using PGD with 10 iterations, where each iteration consists of a gradient-based update of the perturbation and a projection to the L_∞ ball with radius ϵ (see equation 7). The update rate α is initialized with $\epsilon/2$ and linearly decreased with each iteration, reaching a final value of 0.1 mV at iteration 10. The PGD computation is restarted 5 times with different initial perturbations, which are drawn from a uniform distribution within the range $[-\epsilon, +\epsilon]$.

Universal attacks. A universal perturbation is computed for all the samples in the training data. We optimize the UAP objective function

$$\min_{\mathbf{v}} E_{\mathbf{X}\sim D}\mathcal{L}_{tot}\left(\mathbf{X}, \mathbf{v}, \lambda_m, \lambda_d\right) \quad \mathrm{s.t.} ||\mathbf{v}||_\infty \leq \epsilon \tag{16}$$

using batched PGD. We pass a batch of 16 samples together with the current perturbation through the preprocessing and classifier, compute the loss function, and update the perturbation based on the negative gradient with consecutive projection to the L_∞ ball with radius ϵ. This step is repeated 10 times before processing the next batch. Overall, the UAP is learned for 10 epochs.

Propagation model. We distinguish between three use cases of spatial propagation model, where in all cases either a instance-specific attack or a universal attack can be computed: Case 1) Ignore the propagation model: a multi-channel perturbation $\mathbf{V}$ is computed, which attacks each channel individually, replacing the terms $H(\mathbf{v}, \lambda_m, \lambda_d)$ by $\mathbf{V}$ and $\mathbf{v}'$ by $\mathbf{V}'$ in equation 15. Case 2) Consider the propagation model: a single-channel perturbation $\mathbf{v}$ is computed and tested with a specific propagation configuration λ_m and λ_d. Case 3) Consider a use-case where the attacker does not know the spatial propagation model and computes the same perturbation $\mathbf{v}$ for all channels. The actual propagation model is applied during testing to model the real-world signal propagation.

The hyperparameters α, β, the number of PGD iterations and the restarts, the batch size and the number of epochs in UAP are determined based on a cross-validated grid search on the training set.

Figure 5: A successful attack with derivative loss term and spatial constraints $\lambda_m = 1$ and $\lambda_d = 0.563$ (PGD, ϵ=50mV). The background traces show the original signal before the preprocessing filter.

Figure 6: ASR of PGD and UAP in Case 2), i.e., computed with head model (w/HM); and in Case 3), i.e., computed without head model (w/oHM).

Figure 7: ASR with the PGD attack propagating from different EEG channels with fixed λ_d=0.3 and variable λ_m.

5 EXPERIMENTS AND RESULTS

Dataset. We use the Physionet EEG Motor Movement/Imagery Dataset (Goldberger et al., 2000; Schalk et al., 2004) containing valid EEG recordings of 105 subjects (Dose et al., 2018), publicly available under Open Data Commons Attribution License v1.0. We use the MI recordings that contain tasks of the imagination of left against right fist for 3 s. The EEG trials were recorded with N_{ch}=64 channels sampled at F_s=160 Hz, yielding N_s=3·160=480 samples per trial. Additional baseline runs provide resting-state data, where the subjects did not perform any tasks while having eyes open. Overall, we get a total of 6615 trials with N_{cl}=3 balanced classes "left", "right", and "rest."

Training and validation. We train and validate both the classification models and the generated adversarial examples with a 5-fold cross-validation, splitting the dataset into 84 subjects used for training and 21 subjects used for validation to effectively test the model on inter-subject variability. Similar to Wang et al. (2020), which achieved SoA performance on this dataset, the baseline model is trained for 100 epochs using Adam with β_1=0.9, β_1=0.999, and batch size of 16. The learning rate is 0.01 and decreased by a factor of 10 at epochs 20 and 50, achieving an average accuracy of 74.78%.

An FFT band-pass filter h_{bp} with a customary passband of 0.1–40 Hz (Lawhern et al., 2018) is used as preprocessing step in both baseline and attack experiments.To determine the ASR, we compute the ratio between the successfully fooled trials, i.e., trials now classified as "rest", and the total number of attacked trials, where we only consider the ones initially correctly classified as "left"/"right".

Physiologically plausible attacks We first analyze the instance-based attacks without considering the propagation model (Case 1), depicted in Figure 3. For both FGSM and PGD, the ASR increases together with the maximum amplitude ϵ of the perturbation, with PGD performing slightly better than FGSM. They reach the maximum ASR of 99.97% with 10mV. Figure 4a shows the signals of a successful attack using PGD. The adversarial perturbation has a square-wave form which negatively affects the natural shape of the EEG signal. By adding the proposed derivative term, the square-wave artifacts are significantly reduced (4b), making the perturbation more physiologically plausible. Moreover, the introduction of the derivative term does not degrade the ASR (see Figure 3). The quantitative measures between the original and the adversarial samples are reported in Table 1, demonstrating that our proposed method with derivative term generates adversarial samples that are more similar to the original EEG.

We extend the application of the derivative term to the UAP attack, while still not considering the propagation model (Case 1). Figure 3 shows a comparison in performance for different values of ϵ. The saturation in ASR is reached with higher ϵ, i.e., 99.94% with 50mV. This is expected since the UAP is a more difficult attack where a single set of perturbations per EEG channel is generated for all the test samples. Likewise in PGD, the ASR does not drop with the addition of the derivative term.

Spatial Propagation Finally, we introduce the spatial constraints in the signal propagation over the scalp (Case 2). We consider 9 different scenarios by combining 3 realistic attenuation configurations $\lambda_m \in \{1, 5, 15\}$ with 3 delay configurations $\lambda_d \in \{0.1, 0.3, 0.563\}$, which capture the range described in Section 4.2. For evaluating the highest achievable attack efficiency, we test a scenario where the attacker is assumed to know the propagation model: the adversarial perturbation is generated and evaluated on fixed spatial parameters λ_m and λ_d, shown in Figure 6, where the ASR reaches up to 69.2% with PGD and 45.6% with UAP at 50mV. Figure 5 depicts an example of a successful attack with the highest perturbation amplitude. The introduction of the spatial constraints makes the attack problem harder yielding seldom square distortions. However, the resulting EEG signals still resemble physiological random processes typical of EEGs.

Next, we ablate the spatial constraints during generation and test the resulting perturbations on the 9 above-mentioned scenarios (Case 3). The ASR drops significantly, especially for λ_m=5 and λ_m=15 where the attenuation of the perturbation over the scalp is greater (see Figure 2), and with the global UAP attack, where the attacker does not have access to the attacked EEG signals.

Our spatial propagation models allows us to identify the vulnerability of the individual EEG channels. Figure 7 shows the ASR when initiating an attack from a specific channel (T9, T10, etc.) and propagating it to the rest of the head. In the case with the greatest attenuation (λ_m=15) we find the maximum ASR at the electrode Cz between the regions of the electrodes C3 and C4, which are the most relevant ones for MI of the left and right hand tasks (Pfurtscheller & Lopes da Silva, 1999).

Overall, our methods successfully generates perturbations resembling natural noise in EEGs, that can be added at the source of the signal acquisition and are propagated over the scalp, creating attacked signals that are physiologically plausible.

6 CONCLUSION

With the incentive of improving security in BCIs, in this work, we demonstrated that DoS attacks are feasible and effective despite physical domain constraints. Experimental results reveal potential risks of realistic attacks on smart wearable BCIs and incentivize the need for future development of defense mechanisms while designing deep learning models to be embedded in smart wearable BCIs. Our detailed analysis on each EEG channel shows that special attention has to be paid, combined with the findings in neuroscience, to the brain regions that are found responsible for a specific task. In future work, the proposed attacks can cover uncertainty in the propagation model and the timing of the MI activity. Moreover, hardware implementations of such attacks can be created to evaluate the proposed methods in real-world, with the ultimate goal of developing effective countermeasures.

ETHICS STATEMENT

The sore goal of this work is to raise awareness of potential adversarial attacks in BCIs and incentivize the development of coutermeasures, especially in the current moment when the BCIs are facing an increasing growth in applications of everyday life. The active development of smart wearable BCIs is introducing a paradigm shift where the processing algorithms are embedded near the data acquisition. While this improves the system security to a certain extend, with this work we have shown that it is not the only and ultimate way to a safe and reliable BCI, since we have shown that BCI systems are vulnerable also to attacks at the signals' source. We hope that our work sheds light on the fact that practical BCI systems are vulnerable, despite the physical constraints, and motivates the design and development of more reliable and robust BCI systems.

REPRODUCIBLITY

A link to a anonymous downloadable source code of this work is submitted as supplementary materials.

REFERENCES

Ayten Ozge Akmandor and Niraj K. Jha. Smart health care: An edge-side computing perspective. *IEEE Consumer Electronics Magazine*, 7(1):29–37, 2018.

Ralph Algazi, Carlos Avendano, and Richard O Duda. Estimation of a spherical-head model from anthropometry. *J. Aud. Eng. Soc.*, 49, 2001.

Pietro Aricò, Nicolina Sciaraffa, and Fabio Babiloni. Brain–computer interfaces: Toward a daily life employment. *Brain Sciences*, 10(3), 2020.

Aamir Arsalan, Muhammad Majid, Amna Rauf Butt, and Syed Muhammad Anwar. Classification of perceived mental stress using a commercially available eeg headband. *IEEE Journal of Biomedical and Health Informatics*, 23(6):2257–2264, 2019.

Christopher Beach, Ertan Balaban, and Alexander J. Casson. Chapter 14 - edge algorithms for wearables: an overview of a truly multi-disciplinary problem. In Edward Sazonov (ed.), *Wearable Sensors (Second Edition)*, pp. 379–414. Academic Press, Oxford, second edition edition, 2021.

Sergio López Bernal, Alberto Huertas Celdrán, Gregorio Martínez Pérez, Michael Taynnan Barros, and Sasitharan Balasubramaniam. Security in brain-computer interfaces: State-of-the-art, opportunities, and future challenges. *ACM Comput. Surv.*, 54(1), January 2021.

Florian C. A. A. Bodranghien, Margot Langlois Mahe, Serge Clément, and Mario U. Manto. A pilot study on the effects of transcranial direct current stimulation on brain rhythms and entropy during self-paced finger movement using the epoc helmet. *Frontiers in Human Neuroscience*, 11:201, 2017.

Jonathan S. Brumberg, Jeremy D. Burnison, and Kevin M. Pitt. Using motor imagery to control brain-computer interfaces for communication. In Dylan D. Schmorrow and Cali M. Fidopiastis (eds.), *Foundations of Augmented Cognition: Neuroergonomics and Operational Neuroscience*, pp. 14–25, Cham, 2016. Springer International Publishing.

Ujwal Chaudhary, Niels Birbaumer, and Ander Ramos-Murguialday. Brain–computer interfaces for communication and rehabilitation. *Nature Reviews Neurology*, 12, 08 2016.

Hauke Dose, Jakob S. Moller, Sadasivan Puthusserypady, and Helle K. Iversen. A Deep Learning MI - EEG Classification Model for BCIs. In *2018 26th European Signal Processing Conference (EUSIPCO)*, pp. 1676–1679. IEEE, 2018.

Anirban Dutta. Brain–computer interface spellers for communication: Why we need to address their security and authenticity. *Brain Sciences*, 10:139, 03 2020.

Daniel Elstob and Emanuele Secco. A low cost eeg based bci prosthetic using motor imagery. *International Journal of Information Technology Convergence and Services*, 6:23–36, 02 2016.

Samuel G. Finlayson, John D. Bowers, Joichi Ito, Jonathan L. Zittrain, Andrew L. Beam, and Isaac S. Kohane. Adversarial attacks on medical machine learning. *Science*, 363(6433):1287–1289, 2019.

Flowneuroscience. Flow tdcs device. `https://flowneuroscience.com/`, 2021. Accessed: 2021-05-27.

TinyML Foundation. tinyml®. `https://www.tinyml.org/`, 2021. Accessed: 2021-05-27.

Daniel Freer and Guang-Zhong Yang. Data augmentation for self-paced motor imagery classification with c-lstm. *Journal of Neural Engineering*, 17, 01 2020.

Ary L Goldberger, Luis A N Amaral, Leon Glass, Jeffrey M Hausdorff, Plamen Ch Ivanov, Roger G Mark, Joseph E Mietus, George B Moody, Chung-Kang Peng, and H Eugene Stanley. PhysioBank, PhysioToolkit, and PhysioNet: components of a new research resource for complex physiologic signals. *circulation*, 101(23):e215–e220, 2000.

Ian J. Goodfellow, Jonathon Shlens, and Christian Szegedy. Explaining and harnessing adversarial examples. In Yoshua Bengio and Yann LeCun (eds.), *Proc. International Conference on Learning Representations, ICLR*, 2015.

Xintian Han, Yuxuan Hu, Luca Foschini, Larry Chinitz, Lior Jankelson, and Rajesh Ranganath. Deep learning models for electrocardiograms are susceptible to adversarial attack. *Nature medicine*, 26 (3):360–363, 2020.

Xue Jiang, Xiao Zhang, and Dongrui Wu. Active learning for black-box adversarial attacks in eeg-based brain-computer interfaces. In *2019 IEEE Symposium Series on Computational Intelligence (SSCI)*, pp. 361–368, 2019.

Mandar Karlekar and Anubha Gupta. Stochastic modeling of eeg rhythms with fractional gaussian noise. In *2014 22nd European Signal Processing Conference (EUSIPCO)*, pp. 2520–2524, 2014.

Victor Kartsch, Giuseppe Tagliavini, Marco Guermandi, Simone Benatti, Davide Rossi, and Luca Benini. Biowolf: A sub-10-mw 8-channel advanced brain–computer interface platform with a nine-core processor and ble connectivity. *IEEE Transactions on Biomedical Circuits and Systems*, 13(5):893–906, 2019.

Min Kim, Youngchang Cho, Suk-Tae Seo, Chang-Sik Son, Hee-Joon Park, and Yoon-Nyun Kim. A new method for non-invasive measurement of skin in the low frequency range. *Healthcare informatics research*, 16:143–8, 09 2010.

Alexey Kurakin, Ian J. Goodfellow, and Samy Bengio. Adversarial examples in the physical world. *CoRR*, abs/1607.02533, 2016.

Vernon J Lawhern, Amelia J Solon, Nicholas R Waytowich, Stephen M Gordon, Chou P Hung, and Brent J Lance. EEGNet: a compact convolutional neural network for EEG-based brain–computer interfaces. *Journal of Neural Engineering*, 15(5):056013, 7 2018.

Jinfeng Li, Shouling Ji, Tianyu Du, Bo Li, and Ting Wang. Textbugger: Generating adversarial text against real-world applications. In *Proc. Network and Distributed System Security Symposium, NDSS*. The Internet Society, 2019a.

Juncheng Li, Shuhui Qu, Xinjian Li, Joseph Szurley, J. Zico Kolter, and Florian Metze. Adversarial music: Real world audio adversary against wake-word detection system. In *Proc. Neural Information Processing Systems (NeurIPS)*, pp. 11908–11918, 2019b.

Zihan Liu, Lubin Meng, Xiao Zhang, Weili Fang, and Dongrui Wu. Universal adversarial perturbations for cnn classifiers in eeg-based bcis, 2021.

Aleksander Madry, Aleksandar Makelov, Ludwig Schmidt, Dimitris Tsipras, and Adrian Vladu. Towards deep learning models resistant to adversarial attacks. In *Proc. International Conference on Learning Representations (ICLR)*, 2018.

Iuliana Marin, Myssar Jabbar Hammood Al-Battbootti, and Nicolae Goga. Drone control based on mental commands and facial expressions. In *2020 12th International Conference on Electronics, Computers and Artificial Intelligence (ECAI)*, pp. 1–4, 2020.

Lubin Meng, Jian Huang, Zhigang Zeng, Xue Jiang, Shan Yu, Tzyy-Ping Jung, Chin-Teng Lin, Ricardo Chavarriaga, and Dongrui Wu. Eeg-based brain-computer interfaces are vulnerable to backdoor attacks, 2021.

Isabelle Merlet, Gwénaël Birot, Ricardo Salvador, Behnam Molaee-Ardekani, Abeye Mekonnen, Aureli Soria-Frish, Giulio Ruffini, Pedro C. Miranda, and Fabrice Wendling. From oscillatory transcranial current stimulation to scalp eeg changes: A biophysical and physiological modeling study. *PLOS ONE*, 8:1–12, 02 2013.

Seyed-Mohsen Moosavi-Dezfooli, Alhussein Fawzi, Omar Fawzi, and Pascal Frossard. Universal adversarial perturbations. In *Proceedings of the IEEE Conference on Computer Vision and Pattern Recognition (CVPR)*, July 2017.

Natasha Padfield, Jaime Zabalza, Huimin Zhao, Valentin Masero, and Jinchang Ren. Eeg-based brain-computer interfaces using motor-imagery: Techniques and challenges. *Sensors*, 19(6), 2019.

G. Pfurtscheller and F.H. Lopes da Silva. Event-related EEG/MEG synchronization and desynchronization: basic principles. *Clinical Neurophysiology*, 110(11):1842–1857, 11 1999. ISSN 1388-2457.

Robert Plutchik and Henry R Hirsch. Skin impedance and phase angle as a function of frequency and current. *Science*, 141(3584):927–928, 1963.

ZG Qiao, L Mørkrid, and NK Vøllestad. Characteristics of phase angle, extrapolated conductance and ion relaxation time in the low-frequency admittance locus plot of human palmar skin. *Medical and Biological Engineering and Computing*, 32(2):161–167, 1994.

Yao Qin, Nicholas Carlini, Ian J. Goodfellow, Garrison W. Cottrell, and Colin Raffel. Imperceptible, robust, and targeted adversarial examples for automatic speech recognition. *CoRR*, abs/1903.10346, 2019.

Mona Sazgar and Michael G. Young. *EEG Artifacts*, pp. 149–162. Springer International Publishing, Cham, 2019.

G. Schalk, D.J. McFarland, T. Hinterberger, N. Birbaumer, and J.R. Wolpaw. BCI2000: A General-Purpose Brain-Computer Interface (BCI) System. *IEEE Transactions on Biomedical Engineering*, 51(6):1034–1043, 6 2004. ISSN 0018-9294.

Tibor Schneider, Xiaying Wang, Michael Hersche, Lukas Cavigelli, and Luca Benini. Q-eegnet: an energy-efficient 8-bit quantized parallel eegnet implementation for edge motor-imagery brain-machine interfaces. In *2020 IEEE International Conference on Smart Computing (SMARTCOMP)*, pp. 284–289, 2020.

Christian Szegedy, Wojciech Zaremba, Ilya Sutskever, Joan Bruna, Dumitru Erhan, Ian J. Goodfellow, and Rob Fergus. Intriguing properties of neural networks. In *Proc. International Conference on Learning Representations, ICLR*, 2014.

Johannes Vorwerk, Ümit Aydin, Carsten H Wolters, and Christopher R Butson. Influence of head tissue conductivity uncertainties on eeg dipole reconstruction. *Frontiers in neuroscience*, 13:531, 2019.

Xiaying Wang, Michael Hersche, Batuhan Tömekce, Burak Kaya, Michele Magno, and Luca Benini. An accurate eegnet-based motor-imagery brain–computer interface for low-power edge computing. In *2020 IEEE International Symposium on Medical Measurements and Applications (MeMeA)*, pp. 1–6, 2020.

Dalin Yang, Yong-Il Shin, and Keum-Shik Hong. Systemic review on transcranial electrical stimulation parameters and eeg/fnirs features for brain diseases. *Frontiers in Neuroscience*, 15:274, 2021.

Yang Yu, Yadong Liu, Jun Jiang, Erwei Yin, Zongtan Zhou, and Dewen Hu. An asynchronous control paradigm on sequential motor imagery and its application in wheelchair navigation. *IEEE Transactions on Neural Systems and Rehabilitation Engineering*, 26(12):2367–2375, 2018.

Wei Emma Zhang, Quan Z. Sheng, Ahoud Abdulrahmn F. Alhazmi, and Chenliang Li. Adversarial attacks on deep-learning models in natural language processing: A survey. *ACM Trans. Intell. Syst. Technol.*, 11(3):24:1–24:41, 2020.

Xiao Zhang and Dongrui Wu. On the vulnerability of cnn classifiers in eeg-based bcis. *IEEE Transactions on Neural Systems and Rehabilitation Engineering*, 27(5):814–825, 2019.

Jiayu Zhuang, Keke Geng, and Guodong Yin. Ensemble learning based brain–computer interface system for ground vehicle control. *IEEE Transactions on Systems, Man, and Cybernetics: Systems*, 51(9):5392–5404, 2021.