ENCODING RECURRENCE INTO TRANSFORMERS

ABSTRACT

This paper novelly breaks down with ignorable loss an RNN layer into a sequence of simple RNNs, each of which can be further rewritten into a lightweight positional encoding matrix of a self-attention, named the Recurrence Encoding Matrix (REM). Thus, recurrent dynamics introduced by the RNN layer can be encapsulated into the positional encodings of a multihead self-attention, and this makes it possible to seamlessly incorporate these recurrent dynamics into a Transformer, leading to a new module, Self-Attention with Recurrence (RSA). The proposed module can leverage the recurrent inductive bias of REMs to achieve a better sample efficiency than its corresponding baseline Transformer, while the self-attention is used to model the remaining non-recurrent signals. The relative proportions of these two components are controlled by a data-driven gated mechanism, and the effectiveness of RSA modules are demonstrated by four sequential learning tasks.

1 INTRODUCTION

Sequential data modeling is an important topic in machine learning, and the recurrent networks such as LSTM (Hochreiter and Schmidhuber, 1997) and GRU (Chung et al., 2014) have served as the benchmarks in this area over a long period of time. The success mainly contributes to the variety of recurrent dynamics introduced by these models, referred to as the recurrent inductive bias. More specifically, the dependence between any two inputs can be described by a parametric form, which heavily depends on their relative temporal locations. However, the recurrent models are well known to suffer from two drawbacks. The first one is the gradient vanishing problem (Hochreiter et al., 2001), i.e. the recurrent models have difficulty in depicting the possibly high correlation between distant inputs. This problem cannot be solved fundamentally by the recurrent models themselves, although it can be alleviated to some extent, say by introducing long memory patterns (Zhao et al., 2020). Secondly, the sequential nature renders these models difficult to be trained in parallel (Vaswani et al., 2017). In practice, many techniques were proposed to improve the computational efficiency of recurrent models, while they all come with compromises (Luo et al., 2020; Lei et al., 2017).

In recent years, Transformer models (Vaswani et al., 2017) have been revolutionizing the field of natural language processing by achieving the state-of-the-art performance on a wide range of tasks, such as language modeling (Kenton and Toutanova, 2019), machine translation (Dai et al., 2019) and text summarization (Liu and Lapata, 2019), etc. They have also demonstrated a great potential in other types of sequence learning problems, for instance, time series forecasting (Zhou et al., 2021; Li et al., 2019). The success of Transformers is due to the fact that the similarity (or dependence) between any two tokens (or inputs) is well taken into account (Vaswani et al., 2017), and hence they can model long range dependence effortlessly. Moreover, contrary to the recurrent models, the self-attention mechanism in Transformers is feed-forward in nature, and this enables them to be computed in parallel on the GPU infrastructure (Vaswani et al., 2017). However, the flexibility also leads to sample inefficiency in training a Transformer, i.e. much more samples will be needed to guarantee a good generalization ability (d'Ascoli et al., 2021). Moreover, the chronological orders are usually ignored by Transformers since they are time-invariant, and some additional efforts, in the form of positional encoding, will be required to further aggregate the temporal information (Shaw et al., 2018; Vaswani et al., 2017; Dai et al., 2019).

In short, both recurrent and Transformer models have the pros and cons in modeling sequential data. On one hand, due to inductive bias, the recurrent models excel at capturing the recurrent patterns even with relatively small sample sizes; see Figure 1(a). Meanwhile, sample size is the bottleneck for Transformers and, when there are sufficient samples, Transformers are supposed to be able to depict any recurrent or non-recurrent patterns in the data; see Figure 1(b). On the other hand, sequential

Figure 1: (a) – (c) plot the two data features, namely the sample signal and the sample size as the x and y axis, respectively. The model performance in each data region for the RNN, Transformer and RSA are given, where deeper color implies a better performance. (d) Under a fixed moderate sample size, the gate value $\sigma(\mu)$ in RSA defined in (4) increases as the recurrent signal becomes stronger.

data have recurrent patterns more or less, and Transformers may have an improved performance if the recurrent model can be involved to handle these recurrent patterns, especially when the sample size is relatively small. Specifically, if the recurrent and non-recurrent components are separable, one then can apply a parsimonious recurrent model on the recurrent component and a Transformer on the non-recurrent one, and the sample efficiency can be improved comparing to the Transformer-only baseline; see illustration in Figure 1(c).

There have been various attempts in the literature to combine the two models. Merity (2019) used the self-attention mechanism of a Transformer to process the memory from an LSTM network. Chen et al. (2018) mixed and matched a Transformer's encoder with an recurrent-based decoder. Hao et al. (2019) introduced an additional recurrent encoder to a Transformer, while Wang et al. (2019) stacked a recurrent layer prior to the multihead self-attention. However, the above approaches combine both types of models in a straightforward manner, and hence they inherit both the aforementioned shortcomings of Transformer and recurrent models. In particular, the computationally expensive sequential operation in the recurrent models limits the attractiveness of these proposals.

In an attempt to simplify the numerical calculation of RNNs, we found surprisingly that an RNN layer with linear activation can be broken down into a series of simple RNNs with scalar hidden coefficients. Each simple RNN induces a distinct recurrent pattern, and their combination forms the recurrent dynamics of the RNN layer. Hence the calculation time can be greatly reduced by training these simple RNNs in parallel. On top of that, it can be equivalently rewritten into the positional encodings of a multihead self-attention (MHSA). This spontaneously inspires a solution, the multihead Self-Attention with Recurrence (RSA), to combine a Transformer with an RNN while maintaining parallel computation. This solution enables our design to preserve the merits from both Transformer and recurrent models, while their respective shortcomings are avoided. Our paper makes three main contributions below.

1. With ignorable approximation loss, we demonstrate that an RNN layer with linear activation is equivalent to a multihead self-attention (MHSA); see Figure 2. Specifically, each attention head can be used to recover a type of the recurrent dependence structure, and multiple heads working in sync replicate the complex temporal dynamics of the RNN layer.

2. In the above MHSA, recurrent dynamics of the RNN layer are encapsulated entirely into the positional encodings, which we name the Recurrence Encoding Matrices (REMs). This makes it possible to add the REMs to any existing Transformer architecture that has the self-attention mechanism, leading to the Self-Attention with Recurrence (RSA) module. A gated mechanism is used to control the proportion of REMs, and the gate value may also be interpreted as the proportion of the recurrent signals in the data.

3. Our experiments on four sequential tasks demonstrate that the proposed RSA module can effectively enhance the baseline Transformers' forecasting power. Moreover, from the fitted gate values, we have an interesting finding that time series data have stronger recurrent signals than those of the regular languages, while the code or natural languages have much weaker recurrent signals.

1.1 RELATED WORKS

Adding recurrence to Transformers Feedback Transformer (Fan et al., 2021) introduces the memory vectors to aggregate information across layers, and uses them to update the next token in a recursive

manner. Other papers provide alternative ways to think of recurrence for Transformer models. One example is the Universal Transformer (Dehghani et al., 2018), which considers recurrence along depth. Specifically, it shares the parameters between consecutive layers in the encoder or decoder block. Another example is the Transformer-XL (Dai et al., 2019), which creates a memory between sequentially ordered samples across batches. Since these works and ours explore recurrence from different perspectives, our proposed RSA may potentially bring further benefit to their architectures. As an illustration, we use Transformer-XL to be one of our baseline models for the time series forecasting and the natural language modeling tasks, and the RSA-XL model is shown to achieve better performance; see details in Section 4.1 & 4.3.

Relative positional encoding The proposed REMs can provide complementary positional encoding in the RSA module. Essentially, its recurrent pattern can convey relative location information. This property is inherited from the distance-awareness of the RNN. Compared to the relative positional encoding (RPE) in the existing literature, it is more parsimonious and interpretable. The fully learnable RPE proposed by Shaw et al. (2018) requires $O(T^2 d)$ parameters, where T is the number of tokens and d is the token dimension. Later, different variants are introduced by Huang et al. (2019) and Dai et al. (2019), which reduce the number of parameters to $O(Td)$ and $O(d)$, respectively. In contrast, our REMs have parametric forms of merely one or two parameters.

Time series forecasting Recent literature sees a surge in deep learning models designed specially for time series forecasting tasks, which are not Transformer-based. For instance, DLinear (Zeng et al., 2022) and Autoformer (Wu et al., 2021) decompose the series into trend and non-trend components. Autoformer and SCINet (Liu et al., 2021) further exploit the temporal dependence structure of the time series via the autocorrelation function and multi-level convolution operations, respectively. FiLM (Zhou et al., 2022a) and FEDformer (Zhou et al., 2022b) transform the series to the frequency domain in order to capture meaningful signals while removing noises. This paper, however, differs from the above literature in both target and methodology. We aim to develop a simple method to introduce the recurrent inductive bias to general-purpose Transformers. To this end, we approximate the recurrent dynamics of a linear RNN by the REMs and plug them into different Transformers that has the self-attention mechanism. As a tradeoff for our board range of applicability, the performance of an RSA model may rely heavily on the baseline Transformer that it modifies.

2 RELATIONSHIP BETWEEN RNN AND MULTIHEAD SELF-ATTENTION

This section demonstrates that, without loss of much generality, an RNN layer can be approximated by a series of simple RNNs with scalar (hidden) coefficients, which can be further represented in the form of a multihead self-attention.

2.1 BREAKING DOWN AN RNN LAYER

Consider an RNN layer with the input variables $\{\boldsymbol{x}_t \in \mathbb{R}^{d_{\text{in}}}, 1 \le t \le T\}$, and it has the form of $\boldsymbol{h}_t = g(\boldsymbol{W}_h \boldsymbol{h}_{t-1} + \boldsymbol{W}_x \boldsymbol{x}_t + \boldsymbol{b})$, where $g(\cdot)$ is the activation function, $\boldsymbol{h}_t \in \mathbb{R}^d$ is the output or hidden variable with $\boldsymbol{h}_0 = 0$, $\boldsymbol{b} \in \mathbb{R}^{d_{\text{in}}}$ is the bias term, $\boldsymbol{W}_h \in \mathbb{R}^{d \times d}$ and $\boldsymbol{W}_x \in \mathbb{R}^{d \times d_{\text{in}}}$ are weights.

Figure 2: Illustration on how an RNN layer can be equivalently represented by a set of simple RNNs and further by a multihead self-attention.

When the activation function is linear, i.e. $g(x) = x$, the RNN becomes

$$\boldsymbol{h}_t = \boldsymbol{W}_h \boldsymbol{h}_{t-1} + \boldsymbol{W}_x \boldsymbol{x}_t, \text{ or equivalently } \boldsymbol{h}_t = \sum_{j=0}^{t-1} \boldsymbol{W}_h^j \boldsymbol{W}_x \boldsymbol{x}_{t-j}, \tag{1}$$

where the bias term $\boldsymbol{b}$ is suppressed for simplicity. Although it has a feedforward form, the RNN cannot be trained in parallel, and this is mainly caused by the recurrent weights $\boldsymbol{W}_h$. This section makes an effort to block diagonalize $\boldsymbol{W}_h$ such that the RNN at (1) can be broken down into a sequence of simple RNNs with scalar (hidden) coefficients.

Lemma 1 (Theorem 1 in Hartfiel (1995)). *Real matrices with R distinct nonzero eigenvalues are dense in the set of all $d \times d$ real matrices with rank at most R, where $0 < R \leq d$.*

Suppose that the weight matrix $\boldsymbol{W}_h$ has rank $R \leq d$. By Lemma 1, without loss of much generality, we can assume that the nonzero eigenvalues of $\boldsymbol{W}_h$ are all distinct. Specifically, $\boldsymbol{W}_h$ has r real nonzero eigenvalues $\lambda_1, \ldots, \lambda_r$, and s pairs of complex nonzero eigenvalues $\lambda_{r+1}, \ldots, \lambda_{r+2s}$, where $(\lambda_{r+2k-1}, \lambda_{r+2k}) = (\gamma_k e^{i\theta_k}, \gamma_k e^{-i\theta_k})$ for $1 \leq k \leq s$, i represents the imaginary unit, and $R = r + 2s$. As a result, from Horn and Johnson (2012), we have the Jordan decomposition in real form, $\boldsymbol{W}_h = \boldsymbol{B}\boldsymbol{J}\boldsymbol{B}^{-1}$, where $\boldsymbol{B} \in \mathbb{R}^{d \times d}$ is invertible and $\boldsymbol{J} \in \mathbb{R}^{d \times d}$ is a block diagonal matrix. It holds that $\boldsymbol{W}_h^j = \boldsymbol{B}\boldsymbol{J}^j\boldsymbol{B}^{-1}$ for all $j \geq 1$, and we can then break down the recurrence induced by $\boldsymbol{W}_h$ into that of the $p \times p$ block matrices in $\boldsymbol{J}$ with $p = 1$ or 2.

Similar to (1), we define three types of RNNs with linear activation below,

$$\boldsymbol{h}_t^{\mathrm{R}}(\lambda) = \sum_{j=1}^{t-1} \lambda^j \boldsymbol{W}_x^{\mathrm{R}} \boldsymbol{x}_{t-j}, \quad \boldsymbol{h}_t^{\mathrm{C1}}(\gamma, \theta) = \sum_{j=1}^{t-1} \gamma^j \cos(j\theta) \boldsymbol{W}_x^{\mathrm{C1}} \boldsymbol{x}_{t-j}, \tag{2}$$

and $\boldsymbol{h}_t^{\mathrm{C2}}(\gamma, \theta) = \sum_{j=1}^{t-1} \gamma^j \sin(j\theta) \boldsymbol{W}_x^{\mathrm{C2}} \boldsymbol{x}_{t-j}$, where the first one corresponds to the real eigenvalues, i.e. the 1×1 block matrices in $\boldsymbol{J}$, while the last two correspond to the complex eigenvalues, i.e. the 2×2 block matrices in $\boldsymbol{J}$. Note that each of the three RNNs has the recurrent weights of λ or (γ, θ), and its form with a nonlinear activation function is given in the Appendix.

Proposition 1. *Suppose that $\boldsymbol{W}_h$ has rank $R = r + 2s \leq d$, and its eigenvalues are defined above. Let $\boldsymbol{h}_{0,t} = \boldsymbol{W}_x \boldsymbol{x}_t$, and then the RNN with linear activation at (1) can be equivalently rewritten into*

$$\boldsymbol{h}_t = \sum_{k=1}^{r} \boldsymbol{h}_t^{\mathrm{R}}(\lambda_k) + \sum_{k=1}^{s} \boldsymbol{h}_t^{\mathrm{C1}}(\gamma_k, \theta_k) + \sum_{k=1}^{s} \boldsymbol{h}_t^{\mathrm{C2}}(\gamma_k, \theta_k) + \boldsymbol{h}_{0,t}.$$

2.2 AN EQUIVALENT MHSA REPRESENTATION

Consider the RNN of $\{\boldsymbol{h}_t^{\mathrm{R}}\}$, and let $\boldsymbol{X} = (\boldsymbol{x}_1, \ldots, \boldsymbol{x}_T)' \in \mathbb{R}^{T \times d_{\mathrm{in}}}$ be an input matrix consisting of T tokens with dimension d_{in}, where the transpose of a matrix $\boldsymbol{A}$ is denoted by $\boldsymbol{A}'$ throughout this paper. We first give the value matrix $\boldsymbol{V}$ by projecting $\boldsymbol{X}$ with a linear transformation, i.e. $\boldsymbol{V} = \boldsymbol{X}\boldsymbol{W}_V$ with $\boldsymbol{W}_V = \boldsymbol{W}_x^{\mathrm{R}\prime} \in \mathbb{R}^{d_{\mathrm{in}} \times d}$, and the relative positional encoding matrix is set to

$$\boldsymbol{P}_{\mathrm{mask}}^{\mathrm{R}}(\lambda) = \begin{pmatrix} 0 & 0 & 0 & \cdots & 0 \\ f_1(\lambda) & 0 & 0 & \cdots & 0 \\ f_2(\lambda) & f_1(\lambda) & 0 & \cdots & 0 \\ \vdots & \vdots & \vdots & \ddots & \vdots \\ f_{T-1}(\lambda) & f_{T-2}(\lambda) & f_{T-3}(\lambda) & \cdots & 0 \end{pmatrix}, \tag{3}$$

where $f_t(\lambda) = \lambda^t$ for $1 \leq t \leq T - 1$. As a result, the first RNN at (2) can be represented into a self-attention (SA) form,

$$(\boldsymbol{h}_1^{\mathrm{R}}, \ldots, \boldsymbol{h}_T^{\mathrm{R}})' = \mathrm{SA}^{\mathrm{R}}(\boldsymbol{X}) = [\mathrm{softmax}(\boldsymbol{Q}\boldsymbol{K}') + \boldsymbol{P}_{\mathrm{mask}}^{\mathrm{R}}(\lambda)]\boldsymbol{V},$$

where $\boldsymbol{Q}$ and $\boldsymbol{K}$ are zero query and key matrices, respectively. We call $\boldsymbol{P}_{\mathrm{mask}}^{\mathrm{R}}(\lambda)$ the recurrence encoding matrix (REM) since it summarizes all the recurrence in $\{\boldsymbol{h}_t^{\mathrm{R}}\}$.

For the RNN of $\{\boldsymbol{h}_t^{\mathrm{C1}}\}$, the REM is denoted by $\boldsymbol{P}_{\mathrm{mask}}^{\mathrm{C1}}(\gamma, \theta)$, which has the form of (3) with $f_t(\lambda)$ being replaced by $f_t(\gamma, \theta) = \gamma^t \cos(t\theta)$ for $1 \leq t \leq T - 1$, and the value matrix has the form of $\boldsymbol{V} = \boldsymbol{X}\boldsymbol{W}_V$ with $\boldsymbol{W}_V = \boldsymbol{W}_x^{\mathrm{C1}\prime} \in \mathbb{R}^{d_{\mathrm{in}} \times d}$. Similarly, for the RNN of $\{\boldsymbol{h}_t^{\mathrm{C2}}\}$, the REM, $\boldsymbol{P}_{\mathrm{mask}}^{\mathrm{C2}}(\gamma, \theta)$,

has the form of (3) with $f_t(\lambda)$ being replaced by $f_t(\gamma, \theta) = \gamma^t \sin(t\theta)$ for $1 \leq t \leq T - 1$, and the value matrix is defined as $\boldsymbol{V} = \boldsymbol{X}\boldsymbol{W}_V$ with $\boldsymbol{W}_V = \boldsymbol{W}_x^{C2\prime} \in \mathbb{R}^{d_{\text{in}} \times d}$. Thus, these two RNNs at (2) can also be represented into SA forms,

$$(\boldsymbol{h}_1^{\text{Ci}}, \ldots, \boldsymbol{h}_T^{\text{Ci}})' = \text{SA}^{\text{Ci}}(\boldsymbol{X}) = [\text{softmax}(\boldsymbol{Q}\boldsymbol{K}') + \boldsymbol{P}_{\text{mask}}^{\text{Ci}}(\gamma, \theta)]\boldsymbol{V} \quad \text{with} \quad i = 1 \text{ or } 2,$$

where query and key matrices $\boldsymbol{Q}$ and $\boldsymbol{K}$ are both zero.

Finally, for the remaining term in Proposition 1, $\boldsymbol{h}_{0,t}$ depends on $\boldsymbol{x}_t$ only, and there is no interdependence involved. Mathematically, we can represent it into a SA with the identity relative positional encoding matrix and zero query and key matrices.

Proposition 2. *If the conditions of Proposition 1 hold, then the RNN with linear activation at (1) can be represented into a multihead self-attention (MHSA) with $r + 2s + 1$ heads, where the query and key matrices are zero, and relative positional encoding matrices are $\{\boldsymbol{P}_{mask}^{R}(\lambda_k), 1 \leq k \leq r\}$, $\{\boldsymbol{P}_{mask}^{C1}(\gamma_k, \theta_k), \boldsymbol{P}_{mask}^{C2}(\gamma_k, \theta_k), 1 \leq k \leq s\}$ and an identity matrix, respectively.*

The three simple RNNs at (2) provide different temporal decay patterns: $\boldsymbol{h}_t^{\text{R}}$ provides the regular exponential decay induced by the real eigenvalues λ_k's, and $\{\boldsymbol{h}_t^{\text{C1}}, \boldsymbol{h}_t^{\text{C2}}\}$ provide the cyclical damped cosine or sine decay induced by the pair of complex eigenvalues $(\gamma_k e^{i\theta_k}, \gamma_k e^{-i\theta_k})$'s. These temporal decay patterns are further summarized into the regular REM, $\boldsymbol{P}_{\text{mask}}^{\text{R}}(\lambda)$, and cyclical REMs, $\boldsymbol{P}_{\text{mask}}^{\text{C1}}(\gamma, \theta)$ and $\boldsymbol{P}_{\text{mask}}^{\text{C2}}(\gamma, \theta)$, respectively; see Figure 2 for the illustration. From Proposition 2, the combination of these three types of temporal decay patterns forms the recurrent dynamics of the RNN layer at (1).

For each head, the REM has one or two parameters, and $\boldsymbol{W}_V$ can be regarded as one $d \times d$ learnable matrix. This leads to a parameter complexity of $O(Rd^2)$, and it is slightly larger than that of the RNN at (1) since R is usually much smaller than d (Prabhavalkar et al., 2016). Moreover, the MHSA representation in Proposition 2 gives us a chance to make use of parallel matrix calculation on the GPU hardware; see the Appendix B.3 for an illustration of the computational efficiency of the REMs.

3 ENCODING RECURRENCE INTO SELF-ATTENTION

Note that the REMs in Section 2 are all lower triangular matrices, which corresponds to a unidirectional RNN, and we may also consider a bidirectional design. Specifically, we define the unmasked versions of REMs, i.e. the regular REM is $\boldsymbol{P}^{\text{R}}(\lambda) = \boldsymbol{P}_{\text{mask}}^{\text{R}}(\lambda) + [\boldsymbol{P}_{\text{mask}}^{\text{R}}(\lambda)]'$, and the cyclical REMs are $\boldsymbol{P}^{\text{Ci}}(\gamma, \theta) = \boldsymbol{P}_{\text{mask}}^{\text{Ci}}(\gamma, \theta) + [\boldsymbol{P}_{\text{mask}}^{\text{Ci}}(\gamma, \theta)]'$ with $i = 1$ or 2. Moreover these REMs will be explosive when $|\lambda| > 1$ or $|\gamma| > 1$. To avoid this problem, we further bound these two parameters by transformations in this paper, i.e. $\lambda = \tanh(\eta)$ and $\gamma = \text{sigmoid}(\nu)$, and these notations then become $\boldsymbol{P}^{\text{R}}(\eta)$, $\boldsymbol{P}^{\text{C1}}(\nu, \theta)$ and $\boldsymbol{P}^{\text{C2}}(\nu, \theta)$ accordingly.

While the query and key matrices are set to zero in the MHSA representation at Proposition 2, they play a central role in a standard Transformer. This motivates us to propose the Self-Attention with Recurrence (RSA) module to seamlessly combine the strengths of RNNs and Transformers:

$$\text{RSA}(\boldsymbol{X}) = [(1 - \sigma(\mu))\text{softmax}(\boldsymbol{Q}\boldsymbol{K}') + \sigma(\mu)\boldsymbol{P}]\boldsymbol{V}, \tag{4}$$

where $\boldsymbol{P}$ is a regular or cyclical REM, and $\sigma(\mu) \in [0, 1]$ is a gate with σ being the sigmoid function and μ being the learnable gate-control parameter. The multihead RSA can be defined accordingly.

Sequential data more or less have recurrent patterns, i.e. $p_{\text{total}} = p_{\text{re}} + p_{\text{nr}}$, where p_{total} represents the total temporal patterns in the data. Specifically, p_{re} contains the recurrent patterns, which can be captured by REMs, while the remaining non-recurrent patterns p_{nr} can be modeled by the baseline Transformer via softmax$(\boldsymbol{Q}\boldsymbol{K}')$. The learnable gate $\sigma(\mu)$ is used to measure the proportion of p_{re}; see Figure 1(d) for an illustration. When the sample size is relatively small, it is also possible to use REMs to approximate a part of non-recurrent patterns to obtain a better bias-variance trade-off, leading to a higher value of $\sigma(\mu)$. On one hand, comparing with the baseline Transformer, the inclusion of REMs will lead to a significant improvement in modeling the recurrent patterns p_{re}, and hence a higher accuracy in prediction can be expected for the proposed RSA. Or in other words, the proposed RSA will achieve a higher sample efficiency. On the other hand, comparing with the recurrent models, the non-recurrent patterns in p_{nr} are taken care of by the flexible Transformers, and hence the representation power of the RSA module is as good as that of the baseline Transformer.

In addition, the REM can act as a complementary positional encoding scheme to further provide relative location information. For a multihead RSA module, the gate-control parameter μ is shared

Figure 3: The boxplot for gate values at different attention layers of RSA models. The layer number for outliers are presented in the third boxplot.

among the heads in the same layer, and varies across layers, while the parameters controlling the matrix $\boldsymbol{P}$ vary across all heads and layers.

Initialization Two types of parameters are introduced in (4). The gate-control parameter μ is initialized in the interval $[-3, 3]$ for all the layers. The second type of parameters are $(\lambda, \gamma, \theta)$, which determine the recurrent patterns. To encourage REMs to be non-zero and well-diversified, we initialize λ's at different heads to spread out between $[-2, -1] \cup [1, 2]$ and ν's to spread out between $[1, 2]$, and θ is initialized at $\pi/4$.

Dilated REM variants The dilated REMs can be further obtained by considering the block matrix formed by the first T columns and first T rows of $\boldsymbol{P} \otimes \boldsymbol{I}_d$, where d is the dilating factor. In fact, the dilated REMs can encapsulate the recurrence patterns of the dilated RNNs (Chang et al., 2017); see Proposition 3 in the Appendix. They describe potentially periodic recurrence over a long-term timespan, and can significantly enrich the temporal dynamics of our RSA.

Hyperparameters k_i and d. In each multihead RSA layer with H heads, the number of the six types of REMs, namely one regular, two cyclical, one dilated regular and two dilated cyclical REMs, are denoted by $k_1 - k_6$, respectively. Since it holds that $\sum_{i=1}^{6} k_i = H$, we can apply constrained hyperparameter search to optimize over the choices of k_i's. For simplicity, we can set $k_2 = k_3$ and $k_5 = k_6$, which indicates that the cyclical REMs come in pairs. The search for d, on the other hand, can be guided by various data analytic tools. For instance, d can be observed from the autocorrelation plots as the seasonal period length for time series data (Cryer, 1986); while for the language-related data, d can be heuristically deduced from the recurrence plots (Webber et al., 2016).

4 EXPERIMENTS

This section contains four sequential modeling tasks and, for each task, we modify some popular Transformer baselines by adding the REMs to their attention weights via a gated mechanism as in (4). The modified models are named with the prefix "RSA-". The trained gate $\sigma(\mu)$ controls the percentage of weights allocated to the REMs, and it hence provides a possible measure for recurrent signals in the data. From Figure 3, we may argue that time series data have the strongest recurrent signals, followed by the regular language (Yu, 1997), and finally the code or natural languages. The gate values also vary across different layers of the Transformer model, indicating the changes in recurrent signals as the data propagate through each layer. Nevertheless, the data-driven gated mechanism can help maintain the optimal allocation between REM and the self-attention to achieve better sample efficiency, and improved performance can be overall observed. All experiments are conducted on Nvidia V100 32GB GPUs.

4.1 TIME SERIES FORECASTING

Time series have many unique attributes that can be leveraged to boost forecasting accuracy, one of which is the strong recurrent signals. Section 1.1 provides a brief review of a few state-of-the-art (SOTA) models. Although the Transformer-based models are not the current SOTA models, it is still of interest to explore how their performance can be further improved by the proposed RSA module.

Our experiments are performed on two public benchmark datasets: the ETT[1] dataset is comprised of seven features related to the electric power long-term deployment, where {ETTh$_1$, ETTh$_2$} are

---

[1]It is publicly accessible at https://github.com/zhouhaoyi/ETDataset.

Table 1: Multivariate long sequence time-series forecasting results. The results are reported on different prediction window sizes. We compare the MSE and MAE of RSA models with their baselines under all settings (a total of 32 comparisons), and report the number of times each model surpasses its comparing model in the last row. Note that XL requires a sequential ordering for training, and we hence adopt the same scheme for Informer and LogSparse to make the results comparable across all models.

Methods		Informer		RSA-Informer		LogSparse		RSA-LogSparse		XL		RSA-XL	
Metric		MSE	MAE	MSE	MAE	MSE	MAE	MSE	MAE	MSE	MAE	MSE	MAE
ETTh1	24	0.762	0.632	**0.414**	**0.450**	1.124	0.826	**0.858**	**0.668**	0.514	0.518	**0.466**	**0.493**
	48	1.006	0.763	**0.467**	**0.493**	1.161	0.841	**0.818**	**0.659**	0.571	0.556	**0.528**	**0.535**
	168	1.141	0.823	**0.753**	**0.659**	1.104	0.818	**1.042**	**0.781**	0.898	0.734	**0.813**	**0.694**
	336	1.416	0.987	**0.895**	**0.755**	1.178	0.851	**0.972**	**0.774**	0.963	0.758	**0.942**	**0.756**
ETTh2	24	2.558	1.253	**1.264**	**0.879**	2.894	1.375	**1.076**	**0.844**	0.763	0.699	**0.705**	**0.660**
	48	2.487	1.268	**1.878**	**1.067**	3.009	1.363	**1.362**	**0.975**	1.293	0.917	**1.171**	**0.877**
	168	2.869	1.324	**2.830**	**1.301**	2.876	1.307	**2.165**	**1.235**	2.780	1.288	**2.671**	1.290
	336	**2.055**	**1.113**	2.113	1.124	3.005	**1.350**	**2.909**	1.365	**2.447**	**1.231**	2.461	1.238
ETTm1	24	0.536	0.511	**0.534**	**0.507**	1.105	0.837	**0.619**	**0.553**	**0.561**	**0.537**	0.591	0.549
	48	0.781	0.633	**0.644**	**0.612**	1.150	0.852	**0.541**	**0.519**	0.562	0.543	**0.556**	**0.536**
	96	0.823	0.697	**0.732**	**0.665**	1.227	0.897	**0.526**	**0.520**	0.714	**0.640**	**0.707**	0.645
	288	1.371	0.945	**0.835**	**0.710**	1.167	0.862	**0.955**	**0.766**	0.969	0.795	**0.967**	**0.795**
Weather	24	**0.316**	**0.371**	0.328	0.380	0.560	0.553	**0.394**	**0.441**	**0.364**	**0.411**	0.367	0.414
	48	0.606	0.566	**0.432**	**0.464**	0.582	0.567	**0.432**	**0.466**	0.473	0.490	**0.466**	**0.484**
	168	1.009	0.771	**0.862**	**0.702**	0.929	0.754	**0.602**	**0.580**	0.684	0.616	**0.592**	**0.572**
	336	1.096	0.801	**0.846**	**0.697**	0.874	0.734	**0.638**	**0.602**	0.895	0.713	**0.816**	**0.679**
count		4		28		1		31		8		24	

recorded by the hour and ETTm$_1$ is recorded by 15-minute intervals; and the Weather[2] dataset contains twelve climate indicators collected every 1 hour over a 4-year period. For the baseline models, we adopt Informer (Zhou et al., 2021), LogSparse Transformer (Li et al., 2019) and Transformer-XL (Dai et al., 2019). In particular, to accommodate the cases where the attention map is non-square, we extend the recurrent patterns and adjust the shape of our REMs; see details in Appendix B.2. For this task, we let the REMs substitute the original positional encoding scheme in the RSA models. Moreover, since the distilling operation in the original Informer design is likely to distort the relative positions, we exclude it from both our Informer baseline and the RSA-Informer. The hyperparameters in RSA are fine tuned via grid search. Meanwhile, the hyperparameters in baseline models, namely the number of self-attention heads and layers, are set to the optimal setting in Zhou et al. (2021), and we also follow their train/val/test division and training schemes to conduct our experiments.

Table 1 summarizes the mean squared error (MSE) and mean absolute error (MAE) for the three baselines against their RSA counterparts, averaged across 5 repetitions. Overall, the revised models show significant improvement in performance over their baselines. Moreover, it is interesting to see that the REMs can act as effective substitutions for positional encoding. For Transformer-XL in particular, although we remove their learnable relative positional encoding, superior performance is attained by RSA-XL while the total number of parameters is reduced. We further provide a boxplot for the fitted gate values at different attention layers of RSA-Informer on the four datasets in Figure 3. Since more than 70% of weights are allocated to the REMs, it numerically verifies that the recurrent signals dominate the non-recurrent ones for time series data.

4.2 REGULAR LANGUAGE LEARNING

Regular languages are a subset of formal languages that are intimately related to the linear recurrence sequences, such as the Fibonacci numbers (Kotek and Makowsky, 2010; Chomsky and Schützenberger, 1959). It is reported in some recent works that Transformers have difficulty in generalizing the rules of regular languages (Bhattamishra et al., 2020; Tran et al., 2018; Hahn, 2020). Experiments are conducted to show that the proposed RSA module can leverage the recurrent inductive bias of the REMs to improve Transformer's sample efficiency, and subsequently its generalization ability.

For the experiments, we deliberately choose six types of regular languages on which the Transformer model has been shown to perform poorly, namely Parity, Tomita 3, 5 & 6 (Tomita, 1982), D_2 and D_4 (Bhattamishra et al., 2020). Given that the first four belong to the subclass of non-star-free languages, recognizing them requires the ability to capture periodicity and to perform modular

---
[2]Weather dataset can be acquired at https://www.ncei.noaa.gov/data/local-climatological-data/.

Table 2: Prediction accuracy of the vanilla Transformer, the Transformer with learnable relative positional encoding ("Transformer⋆") on the six languages, together with the RSA-Transformer under different hyperparameter settings. All Transformers are 5-headed, and the hyperparameter settings for RSA-Transformer, Cases I-IV, are denoted by the tuple $(k_1, k_2, k_3, k_4, k_5, k_6)$.

| Methods | Transformer | | Transformer⋆ | | RSA-Transformer | | | | | | | |
| | | | | | I: (5,0,0,0,0,0) | | II: (3,0,0,2,0,0) | | III: (3,1,1,0,0,0) | | IV: (3,0,0,0,1,1) | |
	Bin 0	Bin 1	Bin 0	Bin 1	Bin 0	Bin 1	Bin 0	Bin 1	Bin 0	Bin 1	Bin 0	Bin 1
D_2	0.2	0.2	0.87	0.94	**1**	**1**	**1**	**1**	**1**	**1**	**1**	**1**
D_4	1	0.08	0.99	0.9	**1**	**1**	**1**	**1**	**1**	**1**	**1**	**1**
Parity	0.29	0	0.13	0	**0.99**	**0.67**	0.97	0.53	0.91	0.62	0.9	0.52
Tomita 3	0.89	0.11	0.98	0.48	1	0.97	1	0.97	**1**	**0.98**	**1**	**0.98**
Tomita 5	0.07	0	0.01	0	0.63	0.16	**0.82**	0.17	0.49	0	0.72	**0.35**
Tomita 6	0	0	0	0	0.78	0.35	0.89	0.38	**0.95**	**0.46**	0.64	0.39

counting. Although the D_n languages belong to the simpler star-free subclass, they have nested structures with n measuring the depth. This type of language acquires more sophisticated hierarchical structure as n increases, and hence becomes harder to learn.

We use the decoder-only vanilla Transformer model as the baseline, and modify its self-attention layers into our RSA form under four hyperparameter settings (detailed in Table 2). For comparison, another benchmark model (denoted by Transformer⋆) is obtained by replacing the absolute sinusoidal positional encoding with the learnable relative positional encoding (Dai et al., 2019). We adopt a simple setting with 3 layers and 5 heads. The embedding size is set to 20. During training, the Adam optimizer is intialized at 0.005 with a 0.5× decay every 5 epochs. And all models are run for 25 epochs without early stopping. To evaluate their generalization ability, the test set is further separated into bin 0 and bin 1. Both the training set and bin 0 contain samples with length in the range of $[2, 50]$ for Parity and Tomita, and $[2, 100]$ for D_n, while bin 1 contains longer test samples with length in the range of $[51, 100]$ for Parity and Tomita, and $[101, 200]$ for D_n. The models are trained on 10K samples and tested on 2K samples per bin for Parity and Tomita, and trained on 5K samples with 1K test samples per bin for D_n. Following Bhattamishra et al. (2020), we train the models as below: starting from the first position of an input sequence, the model outputs a string of possible characters for the next position, and this continues until the sequence is exhausted. The prediction task is recast into a classfication task, where the prediction is deemed a success if and only if the output values at each position are correct, and a failure otherwise.

From Table 2, it can be seen that the vanilla Transformer model fails to grasp the recurring rules of these languages. With the assistance of the learned relative positional encoding, they can learn better on D_2, D_4 and Tomita 3, but not the others. However, the RSA-Transformer not only achieves near 100% accuracy on D_2, D_4 and Tomita 3, but also gains a significant boost in performance on the other three languages. In particular, Figure 3 shows that approximately 60% of weights are allocated to the REMs, implying strong recurrent signals in the datasets. The Transformer-only models may require much more training samples to learn these patterns. Moreover, when the training samples are shorter than the test samples, they will have difficulty in extending the learned patterns to longer sequences, even with absolute or learned relative positional encoding. Meanwhile, REMs can easily extend its learned patterns to any sequence length, which may account for the better generalization ability of RSA-Transformer. We further provide some visualization of the REMs under Cases I – IV and their interpretaions in Appendix C.2.

4.3 CODE AND NATURAL LANGUAGE MODELING

Different from the regular languages, the recurrence relationship in programming or natural languages is weaker and harder to interpret. Nevertheless, they have a wide range of applications on which the Transformers are serving as the baseline models. Our experiments show that the baseline models can improve in performance with the inclusion of a small percentage of REMs.

We first conduct a defect detection task based on the C language dataset provided by Zhou et al. (2019), which is a binary classification task to evaluate whether a code is vulnerable to external attacks. The pretrained CodeT5 (Wang et al., 2021)[3] is adapted to this downstream task. Specifically, we use CodeT5-small as our baseline model with 12 layers and 8 heads, and directly add the REMs on

---

[3]Pretrained weights available from https://github.com/salesforce/CodeT5.

Table 3: (a) The defect accuracy is reported for the CodeT5-small baseline and the RSA-CodeT5-small. In addition, we report the percentage of the parameters added by the RSA model against its baseline. (b) The number of Bit-per-character (BPC) is reported for Enwik8 and Text8 (lower is better), and the perplexity (PPL) is reported for WikiText-103 (lower is better).

Models	Defect Accuracy (%)
CodeT5-small	64.60
RSA-CodeT5-small	**65.96**
# Params Added (%)	5×10^{-4}

(a) Code defect detection

	Enwik8	Text8	WikiText-103
XL	1.074	1.328	23.83
RSA-XL	**1.068**	**1.164**	**23.73**
# Params Added (%)	1.5×10^{-4}	1.5×10^{-4}	7.3×10^{-5}

(b) Natural language modeling

top of the self-attention with fully learnable RPE via a gated mechanism. The gate-control parameter μ is initialized at -3 and we fine-tune both the baseline and our RSA models for 20 epochs with early stopping. It can be observed from the boxplot in Figure 3 that the gate values at different layers remain close to the initialization, with only 5% of weights allocated to the REMs. Although the recurrent signals in the code language is apparently much weaker than those in the time series or regular language, our RSA-CodeT5-small is still able to achieve a significant improvement in performance against the CodeT5-small baseline as shown in Table 3(a). The RSA-CodeT5-small model has only about 320 additional parameters over the baseline with 66 million parameters, which is equal to $5 \times 10^{-4}\%$. More surprisingly, it surpasses the current SOTA result which is 65.78%, given by the CodeT5-base model with a total number of 220 million parameters (Wang et al., 2021). Due to limited resources, we have not yet fine-tuned RSA-CodeT5-base model.

The natural language modeling task is conducted on three standard NLP datasets, namely the word-level WikiText-103 (Merity et al., 2017), Enwik8 (LLC., 2009) and Text8 (LLC., 2009). WikiText-103 consists of extracted text from Wikipedia, containing 103M training tokens from 28K articles. Enwik8 is a character-level dataset which contains unprocessed Wikipedia text, while Text8 is its cleaned version with non-alphabetical characters removed and all uppercases changed into lowercases. We use a 16-layer Transformer-XL with 12 heads as the baseline for WikiText-103, and directly add the REMs on top of some of its self-attention heads with learnable RPE via a gated mechanism. In the meantime, a 14-layer Transformer-XL with 8 heads is adopted as the baseline model for both Enwik8 and Text8. We also follow the training schemes of the original Transformer-XL paper, and the results are reported in Table 3(b). Overall, it can be seen that RSA-XL models can achieve better performance than their respective baselines. From Figure 3, we can see that the REMs at the first three self-attention layers contribute more substantially for Text8 comparing to the other two datasets, which may provide an explanation for RSA-XL achieving a more significant improvement on this particular dataset.

5 CONCLUSION AND DISCUSSION

By formulating RNN into an MHSA form, we novelly propose an RSA module to incorporate the recurrent dynamics of an RNN into a Transformer. Specifically, the lightweight REMs are combined with the self-attention weights via a gated mechanism, maintaining a parallel and efficient computation on the GPU infrastructure. Experiments on four sequential learning tasks show that the proposed RSA module can boost the sample efficiency of the baseline Transformer, supported by significantly improved performance. In addition, with the fitted gate values to measure the recurrent signal strength in the data, it can be observed that the code or natural languages have much smaller proportion of recurrent patterns, which further explain the superiority of Transformer models in these two data domains, while the inclusion of REMs still can boost the baseline performance.

This paper can be extended along three directions below. Firstly, while six typical examples of REMs are introduced, we may also consider other types of REM designs, such as the non-distinct eigenvalues of the RNN weight matrix W_h, and long-memory filters operated on top of the RNNs (Zhao et al., 2020). Secondly, the proposed RSA module can be further applied to other types of sequential learning tasks such as video learning (Bulat et al., 2021) and skeleton-based human motion detection (Shu et al., 2021). Finally, it is of interest to incorporate the REMs into models other than Transformers, or even to apply it directly as a standalone recurrent unit.

6 REPRODUCIBILITY STATEMENT

To ensure the reproducibility and completeness of this paper, we include the Appendix with three main sections. Appendix A contains the complete proofs for all propositions presented in this paper. An efficient method to compute the REMs is detailed in Appendix B, together with an extension to non-square REMs and an empirical study on the time efficiency of the proposed method. The experiments in the paper are reproducible with additional implementation details provided in Appendix C. We also include the hyperparameter settings for all results contained in Tables 1 and 3. We will make the codes available to the public.

REFERENCES

Bhattamishra, S., Ahuja, K., and Goyal, N. (2020). On the ability and limitations of transformers to recognize formal languages. In *EMNLP*, pages 7096–7116.

Bulat, A., Perez Rua, J. M., Sudhakaran, S., Martinez, B., and Tzimiropoulos, G. (2021). Space-time mixing attention for video transformer. *Advances in Neural Information Processing Systems*, 34:19594–19607.

Chang, S., Zhang, Y., Han, W., Yu, M., Guo, X., Tan, W., Cui, X., Witbrock, M., Hasegawa-Johnson, M., and Huang, T. S. (2017). Dilated recurrent neural networks. In *Proceedings of the 31st International Conference on Neural Information Processing Systems*, pages 76–86.

Chen, M. X., Firat, O., Bapna, A., Johnson, M., Macherey, W., Foster, G., Jones, L., Schuster, M., Shazeer, N., Parmar, N., Vaswani, A., Uszkoreit, J., Kaiser, L., Chen, Z., Wu, Y., and Hughes, M. (2018). The best of both worlds: Combining recent advances in neural machine translation. In *Proceedings of the 56th Annual Meeting of the Association for Computational Linguistics (Volume 1: Long Papers)*, pages 76–86, Melbourne, Australia. Association for Computational Linguistics.

Chomsky, N. and Schützenberger, M. P. (1959). The algebraic theory of context-free languages. In *Studies in Logic and the Foundations of Mathematics*, volume 26, pages 118–161. Elsevier.

Chung, J., Gulcehre, C., Cho, K., and Bengio, Y. (2014). Empirical evaluation of gated recurrent neural networks on sequence modeling. In *NIPS 2014 Workshop on Deep Learning, December 2014*.

Cryer, J. D. (1986). *Time series analysis*, volume 286. Springer.

Dai, Z., Yang, Z., Yang, Y., Carbonell, J. G., Le, Q., and Salakhutdinov, R. (2019). Transformer-xl: Attentive language models beyond a fixed-length context. In *Proceedings of the 57th Annual Meeting of the Association for Computational Linguistics*, pages 2978–2988.

Dehghani, M., Gouws, S., Vinyals, O., Uszkoreit, J., and Kaiser, L. (2018). Universal transformers. In *International Conference on Learning Representations*.

d'Ascoli, S., Touvron, H., Leavitt, M. L., Morcos, A. S., Biroli, G., and Sagun, L. (2021). Convit: Improving vision transformers with soft convolutional inductive biases. In *International Conference on Machine Learning*, pages 2286–2296. PMLR.

Fan, A., Lavril, T., Grave, E., Joulin, A., and Sukhbaatar, S. (2021). Addressing some limitations of transformers with feedback memory. *arXiv preprint arXiv:2002.09402*.

Hahn, M. (2020). Theoretical limitations of self-attention in neural sequence models. *Transactions of the Association for Computational Linguistics*, 8:156–171.

Hao, J., Wang, X., Yang, B., Wang, L., Zhang, J., and Tu, Z. (2019). Modeling recurrence for transformer. In *Proceedings of the 2019 Conference of the North American Chapter of the Association for Computational Linguistics: Human Language Technologies, Volume 1 (Long and Short Papers)*, pages 1198–1207, Minneapolis, Minnesota. Association for Computational Linguistics.

Hartfiel, D. J. (1995). Dense sets of diagonalizable matrices. *Proceedings of the American Mathematical Society*, 123:1669–1672.

Hochreiter, S., Bengio, Y., Frasconi, P., Schmidhuber, J., and Elvezia, C. (2001). Gradient flow in recurrent nets: the difficulty of learning long-term dependencies. *A Field Guide to Dynamical Recurrent Networks*, pages 237–243.

Hochreiter, S. and Schmidhuber, J. (1997). Long short-term memory. *Neural computation*, 9(8):1735–1780.

Horn, R. A. and Johnson, C. R. (2012). *Matrix Analysis*. Cambridge University Press, New York, 2nd edition.

Huang, C.-Z. A., Vaswani, A., Uszkoreit, J., Simon, I., Hawthorne, C., Shazeer, N., Dai, A. M., Hoffman, M. D., Dinculescu, M., and Eck, D. (2019). Music transformer. In *International Conference on Learning Representations*.

Kenton, J. D. M.-W. C. and Toutanova, L. K. (2019). Bert: Pre-training of deep bidirectional transformers for language understanding. In *Proceedings of NAACL-HLT*, pages 4171–4186.

Kotek, T. and Makowsky, J. A. (2010). Definability of combinatorial functions and their linear recurrence relations. In *Fields of Logic and Computation*, pages 444–462. Springer.

Lei, T., Zhang, Y., Wang, S. I., Dai, H., and Artzi, Y. (2017). Simple recurrent units for highly parallelizable recurrence. *arXiv preprint arXiv:1709.02755*.

Li, S., Jin, X., Xuan, Y., Zhou, X., Chen, W., Wang, Y.-X., and Yan, X. (2019). Enhancing the locality and breaking the memory bottleneck of transformer on time series forecasting. *Advances in Neural Information Processing Systems*, 32.

Liu, M., Zeng, A., Xu, Z., Lai, Q., and Xu, Q. (2021). Time series is a special sequence: Forecasting with sample convolution and interaction. *arXiv preprint arXiv:2106.09305*.

Liu, Y. and Lapata, M. (2019). Hierarchical transformers for multi-document summarization. In *Proceedings of the 57th Annual Meeting of the Association for Computational Linguistics*, pages 5070–5081, Florence, Italy. Association for Computational Linguistics.

LLC., M. (2009). Large text compression benchmark.

Luo, Y., Chen, Z., and Yoshioka, T. (2020). Dual-path RNN: efficient long sequence modeling for time-domain single-channel speech separation. In *ICASSP 2020-2020 IEEE International Conference on Acoustics, Speech and Signal Processing (ICASSP)*, pages 46–50. IEEE.

Merity, S. (2019). Single headed attention RNN: Stop thinking with your head. *arXiv preprint arXiv:1911.11423*.

Merity, S., Xiong, C., Bradbury, J., and Socher, R. (2017). Pointer sentinel mixture models. In *International Conference on Learning Representations*.

Prabhavalkar, R., Alsharif, O., Bruguier, A., and McGraw, L. (2016). On the compression of recurrent neural networks with an application to lvcsr acoustic modeling for embedded speech recognition. In *2016 IEEE International Conference on Acoustics, Speech and Signal Processing (ICASSP)*, pages 5970–5974.

Salinas, D., Flunkert, V., Gasthaus, J., and Januschowski, T. (2020). Deepar: Probabilistic forecasting with autoregressive recurrent networks. *International Journal of Forecasting*, 36(3):1181–1191.

Shaw, P., Uszkoreit, J., and Vaswani, A. (2018). Self-attention with relative position representations. In *Proceedings of the 2018 Conference of the North American Chapter of the Association for Computational Linguistics: Human Language Technologies, Volume 2 (Short Papers)*, pages 464–468. Association for Computational Linguistics.

Shu, X., Zhang, L., Qi, G.-J., Liu, W., and Tang, J. (2021). Spatiotemporal co-attention recurrent neural networks for human-skeleton motion prediction. *IEEE Transactions on Pattern Analysis and Machine Intelligence*, 44(6):3300–3315.

Tomita, M. (1982). Dynamic construction of finite automata from examples using hill-climbing. In *Proceedings of the Fourth Annual Conference of the Cognitive Science Society*, pages 105–108, Ann Arbor, Michigan.

Tran, K., Bisazza, A., and Monz, C. (2018). The importance of being recurrent for modeling hierarchical structure. In *Proceedings of the 2018 Conference on Empirical Methods in Natural Language Processing*, pages 4731–4736, Brussels, Belgium. Association for Computational Linguistics.

Vaswani, A., Shazeer, N., Parmar, N., Uszkoreit, J., Jones, L., Gomez, A. N., Kaiser, L. u., and Polosukhin, I. (2017). Attention is all you need. In *Advances in Neural Information Processing Systems*, volume 30. Curran Associates, Inc.

Wang, Y., Wang, W., Joty, S., and Hoi, S. C. (2021). Codet5: Identifier-aware unified pre-trained encoder-decoder models for code understanding and generation. In *Proceedings of the 2021 Conference on Empirical Methods in Natural Language Processing, EMNLP 2021*.

Wang, Z., Ma, Y., Liu, Z., and Tang, J. (2019). R-transformer: Recurrent neural network enhanced transformer. *arXiv preprint arXiv:1907.05572*.

Webber, C. L., Ioana, C., and Marwan, N. (2016). Recurrence plots and their quantifications: expanding horizons. *Springer Proceedings in Physics. doi: https://doi. org/10.1007/978-3-319-29922-8*.

Wu, H., Xu, J., Wang, J., and Long, M. (2021). Autoformer: Decomposition transformers with auto-correlation for long-term series forecasting. *Advances in Neural Information Processing Systems*, 34:22419–22430.

Yu, S. (1997). Regular languages. In *Handbook of formal languages*, pages 41–110. Springer.

Zeng, A., Chen, M., Zhang, L., and Xu, Q. (2022). Are transformers effective for time series forecasting? *arXiv preprint arXiv:2205.13504*.

Zhao, J., Huang, F., Lv, J., Duan, Y., Qin, Z., Li, G., and Tian, G. (2020). Do RNN and LSTM have long memory? In *Proceedings of the 37th International Conference on Machine Learning*, volume 119 of *Proceedings of Machine Learning Research*, pages 11365–11375. PMLR.

Zhou, H., Zhang, S., Peng, J., Zhang, S., Li, J., Xiong, H., and Zhang, W. (2021). Informer: Beyond efficient transformer for long sequence time-series forecasting. In *Proceedings of AAAI*.

Zhou, T., Ma, Z., Wen, Q., Sun, L., Yao, T., Jin, R., et al. (2022a). Film: Frequency improved legendre memory model for long-term time series forecasting. *arXiv preprint arXiv:2205.08897*.

Zhou, T., Ma, Z., Wen, Q., Wang, X., Sun, L., and Jin, R. (2022b). FEDformer: Frequency enhanced decomposed transformer for long-term series forecasting. In *Proc. 39th International Conference on Machine Learning (ICML 2022)*.

Zhou, Y., Liu, S., Siow, J., Du, X., and Liu, Y. (2019). Devign: Effective vulnerability identification by learning comprehensive program semantics via graph neural networks. *Advances in neural information processing systems*, 32.

APPENDIX

This Appendix contains three sections. The first section presents Proposition 3, and then gives the proofs for Propositions 1 – 3. An efficient method to compute the REMs is detailed in Section 2, and we further extend it to non-square REMs and conduct an empirical study on the training time per batch for the RSA models against their baselines. Section 3 provides additional implementation details for the experiments, additional ablation studies and visualization of the learned patterns.

A PROPOSITION 3 AND PROOFS FOR ALL PROPOSITIONS

A.1 PROPOSITION 3 FOR DILATED RNNS

For some positive integer d, let $\bar{\boldsymbol{P}}^{\mathrm{R}}_{\mathrm{mask}}$ be the block matrix formed by the first T columns and the first T rows of $\boldsymbol{P}^{\mathrm{R}}_{\mathrm{mask}} \otimes \boldsymbol{I}_d$. And $\bar{\boldsymbol{P}}^{\mathrm{C}_i}_{\mathrm{mask}}$ can be defined similarly for $i = 1$ or 2. Consider a dilated RNN (Chang et al., 2017) with the dilating factor d. It has the form $\boldsymbol{h}_t = g(\boldsymbol{W}_h \boldsymbol{h}_{t-d} + \boldsymbol{W}_x \boldsymbol{x}_t + \boldsymbol{b})$ where $g(\cdot)$ is the activation function, $\boldsymbol{h}_t \in \mathbb{R}^d$ is the output or hidden variable with $\boldsymbol{h}_0 = 0$, $\boldsymbol{b} \in \mathbb{R}^{d_{\mathrm{in}}}$ is the bias term, $\boldsymbol{W}_h \in \mathbb{R}^{d \times d}$ and $\boldsymbol{W}_x \in \mathbb{R}^{d \times d_{\mathrm{in}}}$ are weights. When the activation function is linear, i.e. $g(x) = x$, the RNN becomes

$$\boldsymbol{h}_t = \boldsymbol{W}_h \boldsymbol{h}_{t-d} + \boldsymbol{W}_x \boldsymbol{x}_t, \quad \text{or} \quad \boldsymbol{h}_t = \sum_{j=0}^{t-1} \boldsymbol{W}_h^j \boldsymbol{W}_x \boldsymbol{x}_{t-j \cdot d}, \tag{5}$$

where the bias term $\boldsymbol{b}$ is suppressed for simplicity. We have the following proposition.

Proposition 3. *If the conditions of Proposition 1 hold for $\boldsymbol{W}_h$ in (5), then the RNN with linear activation at (5) can be represented into a multihead self-attention (MHSA) with $r + 2s + 1$ heads, where the query and key matrices are zero, and relative positional encoding matrices are $\{\bar{\boldsymbol{P}}^{\mathrm{R}}_{mask}(\lambda_k), 1 \le k \le r\}$, $\{\bar{\boldsymbol{P}}^{\mathrm{C1}}_{mask}(\gamma_k, \theta_k), \bar{\boldsymbol{P}}^{\mathrm{C2}}_{mask}(\gamma_k, \theta_k), 1 \le k \le s\}$ and an identity matrix, respectively.*

Proof. The proof follows directly from Proposition 1 and 2. $\square$

A.2 PROOF FOR PROPOSITION 1

Let $\boldsymbol{W}_h$ be a $d \times d$ real matrix with distinct eigenvalues, and from Chapter 3 of Horn and Johnson (2012), we have the Jordan decomposition, $\boldsymbol{W}_h = \boldsymbol{B}\boldsymbol{J}\boldsymbol{B}^{-1}$, where $\boldsymbol{B} \in \mathbb{R}^{d \times d}$ is invertible, and $\boldsymbol{J} \in \mathbb{R}^{d \times d}$ has a real Jordan form, $\boldsymbol{J} = \mathrm{diag}\{\lambda_1, \ldots, \lambda_r, \boldsymbol{C}_1, \ldots, \boldsymbol{C}_s, \boldsymbol{0}\}$ with

$$\boldsymbol{C}_k = \gamma_k \cdot \begin{pmatrix} \cos(\theta_k) & \sin(\theta_k) \\ -\sin(\theta_k) & \cos(\theta_k) \end{pmatrix} \in \mathbb{R}^{2 \times 2}, \quad 1 \le k \le s.$$

Then,

$$\boldsymbol{W}_h^j = \boldsymbol{B}\boldsymbol{J}^j\boldsymbol{B}^{-1} = \sum_{k=1}^{r} \lambda_k^j \boldsymbol{G}_k^{\mathrm{R}} + \sum_{k=1}^{s} \gamma_k^j \left\{ \cos(j\theta_k)\boldsymbol{G}_k^{\mathrm{C1}} + \sin(j\theta_k)\boldsymbol{G}_k^{\mathrm{C2}} \right\} \quad \text{for all } j \ge 1,$$

where $\boldsymbol{G}_k^{\mathrm{R}}$'s, $\boldsymbol{G}_k^{\mathrm{C1}}$'s and $\boldsymbol{G}_k^{\mathrm{C2}}$'s are $d \times d$ real matrices determined jointly by $\boldsymbol{B}$ and $\boldsymbol{B}^{-1}$. Let $\boldsymbol{h}_{0,t} = \boldsymbol{W}_x \boldsymbol{x}_t$ and then,

$$\boldsymbol{h}_t = \sum_{j=0}^{t-1} \boldsymbol{W}_h^j \boldsymbol{W}_x \boldsymbol{x}_{t-j}$$

$$= \sum_{j=1}^{t-1} \sum_{k=1}^{r} \lambda_k^j \boldsymbol{G}_k^{\mathrm{R}} \boldsymbol{W}_x \boldsymbol{x}_{t-j} + \sum_{j=1}^{t-1} \sum_{k=1}^{s} \gamma_k^j \left\{ \cos(j\theta_k)\boldsymbol{G}_k^{\mathrm{C1}} + \sin(j\theta_k)\boldsymbol{G}_k^{\mathrm{C2}} \right\} \boldsymbol{W}_x \boldsymbol{x}_{t-j} + \boldsymbol{W}_x \boldsymbol{x}_t$$

$$= \sum_{k=1}^{r} \boldsymbol{h}_t^{\mathrm{R}}(\lambda_k) + \sum_{k=1}^{s} \boldsymbol{h}_t^{\mathrm{C1}}(\gamma_k, \theta_k) + \sum_{k=1}^{s} \boldsymbol{h}_t^{\mathrm{C2}}(\gamma_k, \theta_k) + \boldsymbol{h}_{0,t},$$

where

$$\boldsymbol{h}_t^{\mathrm{R}} = \sum_{j=1}^{t-1} \lambda^j \boldsymbol{G}^{\mathrm{R}} \boldsymbol{W}_x \boldsymbol{x}_{t-j} \quad \text{or equivalently,} \quad \boldsymbol{h}_t^{\mathrm{R}} = g(\lambda \boldsymbol{h}_{t-1}^{\mathrm{R}} + \boldsymbol{G}^{\mathrm{R}} \boldsymbol{W}_x \boldsymbol{x}_{t-1}), \tag{6}$$

$g(\cdot)$ being the identity function and $\boldsymbol{h}_t^{C_1} = \sum_{j=1}^{t-1} \gamma^j \cos(j\theta) \boldsymbol{G}^{C1} \boldsymbol{W}_x \boldsymbol{x}_{t-j}$, $\boldsymbol{h}_t^{C2} = \sum_{j=1}^{t-1} \gamma^j \sin(j\theta) \boldsymbol{G}^{C2} \boldsymbol{W}_x \boldsymbol{x}_{t-j}$ which can be obtained via the recursive relationships,

$$\begin{cases} \boldsymbol{h}_t^{C1} = g(\gamma \cos\theta \boldsymbol{h}_{t-1}^{C1} + (\gamma \cos\theta \boldsymbol{G}\boldsymbol{W}_x \boldsymbol{x}_{t-1} - \gamma \sin\theta \boldsymbol{h}_{t-1}^{C2})), \\ \boldsymbol{h}_t^{C2} = g(\gamma \cos\theta \boldsymbol{h}_{t-1}^{C2} + \gamma \sin\theta (\boldsymbol{h}_{t-1}^{C1} + \boldsymbol{G}\boldsymbol{W}_x \boldsymbol{x}_{t-1})), \end{cases} \tag{7}$$

with $\boldsymbol{G}$ being $\boldsymbol{G}^{C1}$ or $\boldsymbol{G}^{C2}$, respectively. For a more general form, we can further assume that the activation function $g(\cdot)$ is nonlinear for the simple RNNs at (6) and (7).

A.3 Proof for Proposition 2

Using the SA form, we can represent the three types of the RNNs by

$$(\boldsymbol{h}_1^R(\lambda_k), \cdots, \boldsymbol{h}_1^R(\lambda_k)) = \mathrm{SA}_k^R(\boldsymbol{X}) \text{ and}$$

$$(\boldsymbol{h}_1^{Ci}(\gamma_k, \theta_k), \cdots, \boldsymbol{h}_1^{Ci}(\gamma_k, \theta_k)) = \mathrm{SA}_k^{Ci}(\boldsymbol{X}) \text{ for } i = 1 \text{ or } 2.$$

Therefore, the first term in Proposition 1 can be represented as

$$\mathrm{MHSA}(\boldsymbol{X}) = \mathrm{concat}[\mathrm{SA}_1^R(\boldsymbol{X}), \ldots, \mathrm{SA}_r^R(\boldsymbol{X})]\boldsymbol{W}_o = \left(\sum_{k=1}^r \boldsymbol{h}_1^R(\lambda_k), \ldots, \sum_{k=1}^r \boldsymbol{h}_T^R(\lambda_k) \right)', \tag{8}$$

where $\boldsymbol{W}_o = (\boldsymbol{I}_d, \ldots, \boldsymbol{I}_d)' \in \mathbb{R}^{rd \times d}$ with $\boldsymbol{I}_d$ being d-dimensional identity matrix. Similarly the MHSA for second and third term in Proposition 1 is given by

$$\mathrm{MHSA}(\boldsymbol{X}) = \mathrm{concat}[\mathrm{SA}_1^{Ci}(\boldsymbol{X}), \ldots, \mathrm{SA}_s^{Ci}(\boldsymbol{X})]\boldsymbol{W}_o = \left(\sum_{k=1}^s \boldsymbol{h}_1^{Ci}(\gamma_k, \theta_k), \ldots, \sum_{k=1}^s \boldsymbol{h}_T^{Ci}(\gamma_k, \theta_k) \right)' \tag{9}$$

where $\boldsymbol{W}_o = (\boldsymbol{I}_d, \ldots, \boldsymbol{I}_d)' \in \mathbb{R}^{sd \times d}$.

And we define the additional head as $\mathrm{SA}_0(\boldsymbol{X}) = (\boldsymbol{h}_{0,1}, \ldots, \boldsymbol{h}_{0,T})' = [\mathrm{softmax}(\boldsymbol{Q}\boldsymbol{K}') + \boldsymbol{I}]\boldsymbol{V}$ with $\boldsymbol{W}_Q = \boldsymbol{W}_K = 0$ and $\boldsymbol{W}_V = \boldsymbol{W}_x'$. Combine with (8) and (9), we have

$$\mathrm{MHSA}(\boldsymbol{X}) = \mathrm{concat}[\{\mathrm{SA}_k^R(\boldsymbol{X})\}_{1 \le k \le r}, \{\mathrm{SA}_k^{C1}(\boldsymbol{X}), \mathrm{SA}_k^{C2}(\boldsymbol{X})\}_{1 \le k \le s}, \mathrm{SA}_0(\boldsymbol{X})]\boldsymbol{W}_o \tag{10}$$

where $\boldsymbol{W}_o = (\boldsymbol{I}_d, \ldots, \boldsymbol{I}_d)' \in \mathbb{R}^{(r+2s+1)d \times d}$.

B Computation of the REMs

B.1 Efficient computation of the REMs

For any matrix $\boldsymbol{A}$, let $\cos(\boldsymbol{A})$ and $\sin(\boldsymbol{A})$ refer to applying the cosine and sine functions to each element of $\boldsymbol{A}$. To compute the REMs, we first construct the exponent matrix $\boldsymbol{L}$ that has a Toeplitz form:

$$\boldsymbol{L} = \begin{pmatrix} 0 & 1 & 2 & \cdots & T-1 \\ 1 & 0 & 1 & \cdots & T-2 \\ 2 & 1 & 0 & \cdots & T-3 \\ \vdots & \vdots & \vdots & \ddots & \vdots \\ T-1 & T-2 & T-3 & \cdots & 0 \end{pmatrix}$$

Denote the square matrix whose elements are all equal to λ as $\boldsymbol{\lambda}$. Similarly, we define $\boldsymbol{\gamma}$ and $\boldsymbol{\theta}$ for γ and θ, respectively. Extending the conventional power notation, we let $\boldsymbol{\lambda}^{\boldsymbol{L}} = \mathrm{pow}(\boldsymbol{\lambda}, \boldsymbol{L})$ and $\boldsymbol{\gamma}^{\boldsymbol{L}} = \mathrm{pow}(\boldsymbol{\gamma}, \boldsymbol{L})$, i.e., $(\boldsymbol{\lambda}^{\boldsymbol{L}})_{i,j} = \boldsymbol{\lambda}_{i,j}^{\boldsymbol{L}_{i,j}}$ and $(\boldsymbol{\gamma}^{\boldsymbol{L}})_{i,j} = \boldsymbol{\gamma}_{i,j}^{\boldsymbol{L}_{i,j}}$. Then we can calculate the REMs by

$$\boldsymbol{P} = \begin{cases} \boldsymbol{D}^R - \boldsymbol{I}_T & \text{for regular REM}, \\ \boldsymbol{D}^{Ci} - \boldsymbol{I}_T & \text{for cyclical REMs with } 1 \le i \le 2, \end{cases}$$

where $\boldsymbol{D}^R = \boldsymbol{\lambda}^{\boldsymbol{L}}$, $\boldsymbol{D}^{C1} = \boldsymbol{\gamma}^{\boldsymbol{L}} \odot \cos(\boldsymbol{\theta} \odot \boldsymbol{L})$, $\boldsymbol{D}^{C2} = \boldsymbol{\gamma}^{\boldsymbol{L}} \odot \sin(\boldsymbol{\theta} \odot \boldsymbol{L})$ and $\odot$ is the Hadamard product. Such design allows us to circumvent redundant computations and achieve parallelization as much as possible. To avoid extremely large or small values, we mask the entries that have power larger than a preset number K. In practice, we set $K = 200$.

Moreover, we can easily extend the above calculation to dilated REMs by substituting $\boldsymbol{L}$ with $\boldsymbol{L}_d$, where $(\boldsymbol{L}_d)_{i,j} = \mathbb{I}_{\{\boldsymbol{L}_{i,j} \bmod d = 0\}} \boldsymbol{L}_{i,j}/d$ and d is the dilating factor. The remaining operations are unchanged.

B.2 FLEXIBLE ADAPTATION TO DIFFERENT ATTENTION SHAPES

In some cases, the query and key have different time spans with an overlapping period; examples including the cross-attention and all attention in the Transformer-XL. We show in this section that our REMs can be adapted for such cases. Typically, the historical information will be mostly stored in the query matrix, and the new information will be included in the key and the value matrices. Assume that the query matrix contains the tokens from time 1 to time T, and the key matrix contains that from time $T - K$ to time $T + L$, where $K > 0$ is the overlapping period length and $L > 0$ is the length of new information. Then the REM is of size $(L + K + 1) \times T$ and takes the form of

$$
\begin{array}{c}
 \\
T-K \\
T-K+1 \\
\vdots \\
T-1 \\
T \\
T+1 \\
\vdots \\
T+L
\end{array}
\begin{pmatrix}
\overset{1}{f_{T-K-1}(\beta)} & \overset{2}{f_{T-K-2}(\beta)} & \overset{\cdots}{\cdots} & \overset{T-K-1}{f_1(\beta)} & \overset{T-K}{0} & \overset{\cdots}{\cdots} & \overset{T-1}{f_{K-1}(\beta)} & \overset{T}{f_K(\beta)} \\
f_{T-K-2}(\beta) & f_{T-K-3}(\beta) & \cdots & f_2(\beta) & f_1(\beta) & \cdots & f_{K-2}(\beta) & f_{K-1}(\beta) \\
\vdots & \vdots & \ddots & \vdots & \vdots & \ddots & \vdots & \vdots \\
f_{T-2}(\beta) & f_{T-3}(\beta) & \cdots & f_K(\beta) & f_{K-1}(\beta) & \cdots & 0 & f_1(\beta) \\
f_{T-1}(\beta) & f_{T-2}(\beta) & \cdots & f_{K+1}(\beta) & f_K(\beta) & \cdots & f_1(\beta) & 0 \\
f_T(\beta) & f_{T-1}(\beta) & \cdots & f_{K+2}(\beta) & f_{K+1}(\beta) & \cdots & f_2(\beta) & f_1(\beta) \\
\vdots & \vdots & \ddots & \vdots & \vdots & \ddots & \vdots & \vdots \\
f_{T+L-1}(\beta) & f_{T+L-2}(\beta) & \cdots & f_{K+L+1}(\beta) & f_{K+L}(\beta) & \cdots & f_{L+1}(\beta) & f_L(\beta)
\end{pmatrix},
$$

which maintains the recurrent patterns while considering the shift in the relative time locations, where $\beta = \lambda$ for regular REM or (γ, θ) for cyclical REMs. And we can extend to the dilated REMs similarly.

B.3 THE COMPUTATIONAL EFFICIENCY OF THE REMS FOR VARIOUS TRANSFORMER BASELINES

Figure 4: The training time ber batch for each RSA model, which can be decomposed into the additional computation time due to the REMs (green bar) and the others (blue bar).

Figure 5: Comparison of the training time of ber batch between RSA-Informer and Informer (left panel), RSA-Logsparse Transformer and Logsparse Transformer (middle panel), RSA-Transformer-XL and Transformer-XL (right panel). The experiment is performed on Weather dataset.

We first conduct an empirical study on the Weather dataset to evaluate the computational time of the REMs for RSA-Informer, RSA-LogSparse and RSA-XL. Specifically, we record the training time per batch for the RSA models, while simultaneously we exclude the REMs from the models and record the training time again. The difference between the two gives the additional computation time due to the REMs, as shown by the green bar in Figure 4. It can be seen that the calculations involving the REMs account for less than 20% of the total training time in general.

In the next experiment, we further compare the computational time between the RSA models and their respective baseline models. Note that the original Informer and LogSparse Transformer use absolute positional encoding (APE), while Transformer-XL adopts a learned relative positional encoding (RPE). These positional encoding schemes are excluded from the RSA models. The training time per batch for all the models are reported in Figure 5. We can observe a small increase in computational time for RSA-Informer and RSA-LogSparse against their baselines, while that for RSA-XL remains nearly unchanged. This implies that the REMs requires a bit more computation effort than the APEs, and the same computation effort as the RPE introduced by Transformer-XL.

C ADDITIONAL EXPERIMENTS AND RESULTS

Table 4: Multivariate long sequence time-series forecasting results on ETT and Weather datasets. The standard deviation of the 5 repetitions is included in brackets below the mean value. The results are reported on different prediction window sizes. We compare the MSE and MAE of RSA models with their baselines under all settings (a total of 32 comparisons), and report the number of times each model surpasses its comparing model in the last row.

Methods		Informer		RPSA-Informer		LogSparse		RPSA-LogSparse		XL		RPSA-XL	
Metric		MSE	MAE	MSE	MAE	MSE	MAE	MSE	MAE	MSE	MAE	MSE	MAE
ETTh1	24	0.762	0.632	**0.414**	**0.450**	1.124	0.826	**0.858**	**0.668**	0.514	0.518	**0.466**	**0.493**
		(0.144)	(0.076)	(0.014)	(0.012)	(0.052)	(0.034)	(0.052)	(0.034)	(0.031)	(0.018)	(0.003)	(0.002)
	48	1.006	0.763	**0.467**	**0.493**	1.161	0.841	**0.818**	**0.659**	0.571	0.556	**0.528**	**0.535**
		(0.024)	(0.020)	(0.018)	(0.017)	(0.094)	(0.059)	(0.021)	(0.010)	(0.010)	(0.009)	(0.009)	(0.008)
	168	1.141	0.823	**0.753**	**0.659**	1.104	0.818	**1.042**	**0.781**	0.898	0.734	**0.813**	**0.694**
		(0.022)	(0.023)	(0.036)	(0.018)	(0.010)	(0.016)	(0.021)	(0.007)	(0.010)	(0.006)	(0.011)	(0.008)
	336	1.416	0.987	**0.895**	**0.755**	1.178	0.851	**0.972**	**0.774**	0.963	0.758	**0.942**	**0.756**
		(0.071)	(0.034)	(0.040)	(0.016)	(0.055)	(0.036)	(0.013)	(0.008)	(0.033)	(0.012)	(0.012)	(0.008)
ETTh2	24	2.558	1.253	**1.264**	**0.879**	2.894	1.375	**1.076**	**0.844**	0.763	0.699	**0.705**	**0.660**
		(1.177)	(0.275)	(0.479)	(0.135)	(0.131)	(0.029)	(0.034)	(0.017)	(0.042)	(0.021)	(0.050)	(0.018)
	48	2.487	1.268	**1.878**	**1.067**	3.009	1.363	**1.362**	**0.975**	1.293	0.917	**1.171**	**0.877**
		(0.088)	(0.018)	(0.455)	(0.128)	(0.074)	(0.012)	(0.089)	(0.043)	(0.061)	(0.031)	(0.082)	(0.030)
	168	2.869	1.324	**2.830**	**1.301**	2.876	1.307	**2.165**	**1.235**	2.780	**1.288**	**2.671**	1.290
		(0.124)	(0.019)	(0.188)	(0.039)	(0.068)	(0.012)	(0.131)	(0.030)	(0.157)	(0.045)	(0.133)	(0.026)
	336	**2.055**	**1.113**	2.113	1.124	3.005	**1.350**	2.909	1.365	**2.447**	**1.231**	2.461	1.238
		(0.058)	(0.017)	(0.120)	(0.039)	(0.073)	(0.045)	(0.094)	(0.047)	(0.080)	(0.020)	(0.083)	(0.028)
ETTm1	24	0.536	0.511	**0.534**	**0.507**	1.105	0.837	**0.619**	**0.553**	**0.561**	**0.537**	0.591	0.549
		(0.023)	(0.014)	(0.023)	(0.011)	(0.053)	(0.034)	(0.063)	(0.031)	(0.021)	(0.011)	(0.012)	(0.011)
	48	0.781	0.633	**0.644**	**0.612**	1.150	0.852	**0.541**	**0.519**	0.562	0.543	**0.556**	**0.536**
		(0.265)	(0.135)	(0.079)	(0.049)	(0.015)	(0.016)	(0.010)	(0.005)	(0.009)	(0.005)	(0.020)	(0.012)
	96	0.823	0.697	**0.732**	**0.665**	1.227	0.897	**0.526**	**0.520**	0.714	**0.640**	**0.707**	0.645
		(0.095)	(0.052)	(0.079)	(0.051)	(0.057)	(0.035)	(0.090)	(0.057)	(0.075)	(0.049)	(0.045)	(0.029)
	288	1.371	0.945	**0.835**	**0.710**	1.167	0.862	**0.955**	**0.766**	0.969	0.795	**0.967**	**0.795**
		(0.246)	(0.059)	(0.058)	(0.036)	(0.026)	(0.019)	(0.149)	(0.072)	(0.093)	(0.051)	(0.007)	(0.003)
Weather	24	**0.316**	**0.371**	0.328	0.380	0.560	0.553	**0.394**	**0.441**	**0.364**	**0.411**	0.367	0.414
		(0.003)	(0.002)	(0.001)	(0.001)	(0.069)	(0.046)	(0.015)	(0.012)	(0.001)	(0.001)	(0.000)	(0.000)
	48	0.606	0.566	**0.432**	**0.464**	0.582	0.567	**0.432**	**0.466**	0.473	0.490	**0.466**	**0.484**
		(0.194)	(0.100)	(0.004)	(0.002)	(0.029)	(0.021)	(0.012)	(0.009)	(0.002)	(0.002)	(0.001)	(0.001)
	168	1.009	0.771	**0.862**	**0.702**	0.929	0.754	**0.602**	**0.580**	0.684	0.616	**0.592**	**0.572**
		(0.006)	(0.003)	(0.189)	(0.088)	(0.200)	(0.101)	(0.027)	(0.017)	(0.176)	(0.085)	(0.017)	(0.012)
	336	1.096	0.801	**0.846**	**0.697**	0.874	0.734	**0.638**	**0.602**	0.895	0.713	**0.816**	**0.679**
		(0.236)	(0.069)	(0.187)	(0.084)	(0.132)	(0.071)	(0.025)	(0.014)	(0.155)	(0.071)	(0.167)	(0.079)
count		4		28		1		31		8		24	

C.1 TIME SERIES FORECASTING

We apply the same time series datasets as in the Informer paper (Zhou et al., 2021), and the details are given below for completeness. The first dataset is the Electricity Transformer Temperature (ETT). It contains the records for seven electric power indicators over a two-year period from two separated counties in China. Zhou et al. (2021) created three separate datasets $ETTh_1$ and $ETTh_2$ for hourly level, and $ETTm_1$ for the fifteen-minute level. The train/val/test is 12/4/4 months. The second dataset consists of climatological data over a four-year period from 2010 to 2013 for various locations in US. The train/val/test is 28/10/10 months. To ensure the quality of our baselines models, we make reference to the following two github repositories, namely *Informer2020*[4] and *transformer-xl*[5]. Since

---

[4]The link to the repository is https://github.com/zhouhaoyi/Informer2020 under Apache-2.0 license.

[5]The link to the repository is https://github.com/kimiyoung/transformer-xl under Apache-2.0 license.

Table 5: The fine-tuned hyperparameter settings used for the RSA models in Table 1. The tuple $(k_1, k_2, k_3, k_4, k_5, k_6)$ refer to the number of the six types of REMs. The values of different dilating factors are listed, where those for regular heads are followed by those for the cyclical heads. $d = $ " $-$ " means no dilated REMs are considered.

Methods		RSA-Informer		RSA-LogSparse		RSA-XL	
Setting		$(k_1, k_2, k_3, k_4, k_5, k_6)$	d	$(k_1, k_2, k_3, k_4, k_5, k_6)$	d	$(k_1, k_2, k_3, k_4, k_5, k_6)$	d
ETTh1	24	(0,2,2,0,2,2)	[24,24,24,24]	(4,0,0,4,0,0)	[24,24,24,24]	(4,0,0,4,0,0)	[24,24,24,24]
	48	(0,2,2,2,1,1)	[24,24,24,24]	(4,0,0,4,0,0)	[24,24,24,24]	(4,0,0,4,0,0)	[24,24,24,24]
	168	(0,2,2,2,1,1)	[24,24,24,24]	(4,0,0,4,0,0)	[24,24,24,24]	(0,2,2,0,2,2)	[48,24,48,24]
	336	(4,0,0,4,0,0)	[24,24,24,24]	(0,2,2,0,2,2)	[48,24,48,24]	(1,2,2,1,1,1)	[48,24,24]
ETTh2	24	(4,2,2,0,0,0)	-	(4,0,0,4,0,0)	[24,24,24,24]	(4,0,0,4,0,0)	[24,24,24,24]
	48	(0,2,2,0,2,2)	[24,24,24,24]	(8,0,0,0,0,0)	-	(0,2,2,0,2,2)	[48,24,48,24]
	168	(4,2,2,0,0,0)	-	(4,0,0,4,0,0)	[24,24,24,24]	(4,0,0,4,0,0)	[24,24,24,24]
	336	(0,2,2,0,2,2)	[24,24,24,24]	(4,0,0,4,0,0)	[24,24,24,24]	(4,0,0,4,0,0)	[24,24,24,24]
ETTm1	24	(0,0,0,0,4,4)	[2,3,6,24,2,3,6,24]	(4,0,0,4,0,0)	[96,96,96,96]	(0,1,1,0,3,3)	[48,24,24,48,24,24]
	48	(0,2,2,0,2,2)	[96,96,96,96]	(4,0,0,4,0,0)	[96,96,96,96]	(0,1,1,2,2,2)	[48,24,48,96,48,96]
	96	(0,2,2,0,2,2)	[96,96,96,96]	(4,0,0,4,0,0)	[96,96,96,96]	(0,1,1,2,2,2)	[48,24,48,96,48,96]
	288	(0,2,2,0,2,2)	[96,96,96,96]	(4,0,0,4,0,0)	[96,96,96,96]	(0,1,1,2,2,2)	[48,24,48,96,48,96]
Weather	24	(0,0,0,0,4,4)	[3,5,7,24,3,5,7,24]	(4,0,0,4,0,0)	[24,24,24,24]	(0,2,2,0,2,2)	[24,24,24,24]
	48	(0,2,2,0,2,2)	[24,24,24,24]	(4,0,0,4,0,0)	[24,24,24,24]	(0,2,2,0,2,2)	[48,24,48,24]
	168	(0,2,2,0,2,2)	[24,24,24,24]	(4,0,0,4,0,0)	[24,24,24,24]	(1,2,2,1,1,1)	[48,24,24]
	336	(0,2,2,0,2,2)	[24,24,24,24]	(8,0,0,0,0,0)	-	(0,2,2,0,2,2)	[48,24,48,24]

Table 6: Ablation study on the hyperparameters for the 8-headed RSA-Informer on ETTh$_1$ dataset. $\bar{s}$ and s correspond to the number of dilated and non-dilated cyclical REMs. And $\bar{s} = $"-" refers to the case where no dilated REMs are considered. Otherwise, 4 out of 8 dilated REMs are considered. The MSEs are averaged over 5 repetitions.

$\bar{s}$	s	0	1	2
	-	0.997	0.962	0.878
	0	0.455	0.472	0.430
	1	0.475	0.505	**0.414**
	2	0.521	0.511	0.422

$\bar{s}$	s	0	1	2
	-	1.071	1.072	1.066
	0	0.586	0.561	0.572
	1	0.558	0.548	0.584
	2	0.473	**0.467**	0.469

$\bar{s}$	s	0	1	2
	-	1.254	1.183	1.089
	0	0.800	0.795	0.994
	1	0.772	0.806	1.005
	2	0.777	**0.753**	0.879

$\bar{s}$	s	0	1	2
	-	1.507	1.382	1.239
	0	**0.895**	1.048	0.946
	1	1.076	1.150	**0.895**
	2	1.192	1.198	1.060

 pred window = 24   pred window = 48   pred window = 168   pred window = 336

Transformer-XL requires a sequential order for training, testing and validation sets, we generate the training samples by sliding window starting from different points of the original time series following the practice in Salinas et al. (2020).

Table 5 reports the fine-tuned hyperparameter settings considered in Table 1 of the main paper. To provide additional information about the standard deviation, we provide a more detailed version of Table 1 of the main paper, given in Table 4.

Ablation on the hyperparameters   To shed light on the importance of different recurrent dynamics, we provide an ablation study with RSA-Informer on ETTh$_1$. The model has a total of 8 heads, and we set $k_2 = k_3$ to some positive integer s and $k_5 = k_6$ to some positive integer $\bar{s}$. In particular, when $\bar{s} = 0$, we also take $k_4 = 0$ and hence there are not any dilated REMs, leading to $k_1 = 8 - 2s$. Otherwise, we take $k_4 = 4 - 2\bar{s}$ and $k_1 = 4 - 2s$. It can be observed from Table 6 that the inclusion of dilation and the cyclical patterns can significantly improve the forecasting performance. The concurrence of dilated and non-dilated RSA heads allows the model to capture both the short- and long-term recurrent dynamics.

Gate-control parameter learning   To study how much proportion of the RSA output is accounted for by the REMs, Figure 6 plots the change in its relative importance i.e. $\sigma(\mu)$ during training for all the attention layers, starting from different initializations. As the learning rate drops rapidly, all curves are flattened towards the end. The relative positional attention is the most effective for the cross-attention layer, and the least effective for the self-attention layer in the decoder, whose recurrent patterns may be disrupted by zero paddings. We observe a decrease in MSE as the initialization increases from -1 to 1, which provides an empirical support for initializing at $\mu = 1$.

Figure 6: (a) – (c) report the change in $\sigma(\mu)$ at each attention layer during training, where μ is initialized at $-1, 0$, and 1, respectively. An 8-headed RSA-Informer is applied to the ETTh$_1$ dataset with settings reported in Table 5. The prediction window size equals to 24.

C.2 REGULAR LANGUAGE LEARNING

The six types of regular language datasets are obtained from the github repository *Transformer-Formal-Language*.[6] We briefly describe the rules of these languages:

- The Parity language contains the numbers $\{0, 1\}$ with an even number of 1's. For example, the string 0110 belongs to the language but 0111 does not.
- The D_n language is defined on the alphabets $\{a,b\}$. The D_1 language can be written using the regular expression $(ab)^\star$, where "$\star$" represents the Kleene star operation. Then for $n \geq 1$, D_n can be expressed by the recursive relationship $D_n = (aD_{n-1}b)^\star$. We choose D_2 and D_4, where $D_2 = (a(ab)^\star b)$ and $D_4 = (a(a(a(ab)^\star b)^\star b)^\star b)^\star$.
- The Tomita languages also use the numbers $\{0, 1\}$ and include seven different grammars. In our experiment, we choose Tomita 3, 5 and 6. In Tomita 3, consecutive 1's must be of an odd number and consecutive 0's must be of an even number. In Tomita 5, the total numbers of 1's and 0's must both be even. Finally, Tomita 6 requires the difference between the total number of 1's and 0's to be a multiple of 3.

Figure 7: We visualize four recurrent patterns provided by the RSA heads on different languages (top), and their corresponding output, averaged over embedding dimension (bottom). The corresponding input sequence is given on x-axis.

To help interpret the results in Table 2, we provide some visualizations of the learned recurrent patterns on different languages in Figure 7. Learning Parity requires the model to count the number of 1's, and then decide whether it is an even number. Its recurrent pattern at (a) mainly consists of alternating $\{-1, 1\}$ that leads to regular oscillations when encountering an even or odd number of 1's. Tomita 5 has an additional requirement that the number of 0 is also even, and hence its learning can be assisted by dilated patterns; see (b) for illustration. Although Tomita 6 is more complicated, the regular cyclical patterns at (c) seems sufficient for it to learn well. This gives us a glimpse of how the RSA-Transformer manages to learn the regular languages.

C.3 CODE AND NATURAL LANGUAGE MODELING

For RSA-CodeT5-small, our code is based on the original CodeT5, which can be referred to in the repository `https://github.com/salesforce/CodeT5`.

---

[6]The link to the repository is https://github.com/satwik77/Transformer-Formal-Languages under MIT license.

For the RSA-XL models adopted for the natural language modeling, only some of the heads are replaced with the RSA heads, while the remaining ones are still the original XL heads. In Table 7, we report the detailed hyperparameters settings for the RSA and their baseline models used in Table 3, where "n_RSA_heads" refers to the number of heads that are changed to the RSA heads.

Table 7: The hyperparameter settings for the RSA and their baseline models used in Table 3.

Dataset	Model	n_layer	n_heads	n_RSA_heads	$(k_1, k_2, k_3, k_4, k_5, k_6)$	d	μ_init	#Params
Devign	CodeT5-small	12	8	-	-	-	-	60492288
	RSA-CodeT5-small	12	8	8	(0,0,0,8,0,0)	64	-3	60492396
Text8	XL	14	8	-	-	-	-	47789595
	RSA-XL	14	8	4	(0,0,0,0,2,2)	6,6,12,12	1	47789665
Enwik8	XL	14	8	-	-	-	-	47880396
	RSA-XL	14	8	4	(0,0,0,0,2,2)	3,6,9,12	1	47880466
WikiText-103	XL	16	12	-	-	-	-	153797302
	RSA-XL	16	12	6	(0,0,0,2,2,2)	12,24,12,24,12,24	-1	153797414