AR-ELBO: PREVENTING POSTERIOR COLLAPSE INDUCED BY OVERSMOOTHING IN GAUSSIAN VAE

ABSTRACT

Variational autoencoders (VAEs) often suffer from posterior collapse, which is a phenomenon that the learned latent space becomes uninformative. This is related to local optima introduced by a fixed hyperparameter resembling the data variance in the objective function. We suggest that this variance parameter regularizes the VAE and affects its smoothness, which is the magnitude of its gradient. An inappropriate choice of this parameter causes oversmoothness and leads to posterior collapse. This is shown theoretically by analysis on the linear approximated objective function and empirically in general cases. We propose AR-ELBO, which stands for adaptively regularized ELBO (Evidence Lower BOund). It controls the strength of regularization by adapting the variance parameter, and thus avoids oversmoothing the model. Generation models trained by proposed objectives show improved Fréchet inception distance (FID) of images generated from the MNIST and CelebA datasets.

1 INTRODUCTION

The variational autoencoder (VAE) framework (Kingma & Welling, 2014; Higgins et al., 2017; Zhao et al., 2019) is a popular approach to achieve generative modeling in the field of machine learning. In this framework, a model that approximates the true posterior of observation data, is learned by a joint training of encoder and decoder, which creates a stochastic mapping between the observation data and the learned deep latent space. The latent space is assumed to follow a prior distribution. The generation of a new data sample can be done by sampling the latent space and passing the sample through the decoder. It is common to assume that both the prior on the latent space and the posterior of the observation data follow a Gaussian distribution. This setup is also known as the *Gaussian VAE*. In this case, the variance of the decoder output is usually modeled as an isotropic matrix $\sigma_x^2 \mathbf{I}$ with a scalar parameter $\sigma_x^2 \geq 0$. Furthermore, in order to deal with the intractable log-likelihood of the true posterior, the evidence lower bound (ELBO) (Jordan et al., 1999) is adopted as the objective function instead.

While VAE-based generative models are usually considered to be more stable and easier to train than generative adversarial networks (Goodfellow et al., 2014), they often suffer from the problem of *posterior collapse* (Bowman et al., 2015; Sønderby et al., 2016; Alemi et al., 2017; Xu & Durrett, 2018; He et al., 2019; Razavi et al., 2019a; Ma et al., 2019), in which the latent space has little information of the input data. The phenomenon is generally mentioned as "the posterior collapses to the prior in the latent space" (Razavi et al., 2019a). Recently, several works have suggested that the variance parameter σ_x^2 in the ELBO is strongly related to posterior collapse. For example, Lucas et al. (2019) analyzed posterior collapse through the analysis on a linear VAE. It revealed that an inappropriate choice of σ_x^2 will introduce sub-optimal local optima and cause posterior collapse. Contrary to popular belief, these local optima are not introduced by replacing the log-likelihood with the ELBO, but by an excessively large σ_x^2. On the other hand, it can be shown that fixing σ_x^2 to an excessively small value leads to under-regularization of the decoder, which can cause overfitting. However, in most implementations of a Gaussian VAE, the variance parameter σ_x^2 is fixed to a constant of 1.0. In another work, Dai & Wipf (2019) proposed a two-stage VAE and treated σ_x^2 as a training parameter.

In this work, we suggest that σ_x^2 affects the strength of regulation over the gradient magnitude of the decoder. We call the expected gradient magnitude the *smoothness* throughout this paper. The

smaller the gradient magnitude, the smoother the model. In particular, we would like to focus on the *local smoothness* of the model, which is the smoothness evaluated within the neighborhood of the encoded latent variable of the observation data. Thus, we begin with the following hypothesis:

Main Hypothesis. *The value of σ_x^2 controls the regularization strength of the smoothness of the decoder. Therefore, an excessively large σ_x^2 causes oversmoothness, which results in posterior collapse.*

Following the hypothesis, we suggest that the estimation of σ_x^2 should be related to properties of the approximated posterior of the latent space, such as its local smoothness. We will start with analyzing how σ_x^2 regularizes the local smoothness of the stochastic decoder and then propose new objective functions that inherently determine σ_x^2 via maximum likelihood estimation (MLE). This proposed objective function is named AR-ELBO (Adaptively Regularized ELBO), which controls the regularization strength via σ_x^2. Furthermore, several variations are derived for different parameterizations of variance parameters.

Our main contributions are listed as follows:

1. We show that our main hypothesis holds for linear approximated ELBO and empirically holds in the general case in Section 3.
2. We propose the AR-ELBO, an ELBO-based objective function that adaptively regularizes the smoothness of the decoder by MLE of the variance parameter σ_x^2 in Section 4. Variations of AR-ELBO for several variance parameterizations of posterior distributions are also derived. AR-ELBO prevents the model from the posterior collapse induced by oversmoothing and improves the quality of generation, which is shown in Section 5.

The organization of this paper is as follows. In Section 2, we propose a mathematical definition of **posterior collapse** in the form of mutual information. This also includes the conventional definition: "the posterior collapses to the prior in the latent space". In Section 3, the theoretical analysis and empirical support of the main hypothesis are given. We perform an analysis showing that σ_x^2 affects the smoothness of the decoder via variance parameters of the latent space learned by the encoder. In Section 4, we propose new AR-ELBO objective functions for various variance parameterizations of posterior distributions, which can relieve the decoder from being oversmoothed in the training and prevent posterior collapse. These objective functions no longer include any hyperparameters and can adaptively estimate the variance parameter σ_x^2 from the observation data. It should be noted that if we adaptively determine σ_x^2 with the proposed AR-ELBO, the strength of regularization of the decoder smoothness will gradually decrease as training progresses. In Section 5, we conduct an experiment on the MNIST and CelebA datasets, which shows that utilizing the proposed AR-ELBO with the standard Gaussian VAE can be competitive with many other variations of VAE models in most situations.

Throughout this paper, we use a, $\mathbf{a}$ and $\mathbf{A}$ for a scalar, a column vector and a matrix, and $\ln$ and $\log$ denote the natural logarithm and common logarithm, respectively. Our code is available from the following URL[1].

2   POSTERIOR COLLAPSE IN GAUSSIAN VAE

We begin with the standard formulation of the Gaussian VAE, which is the foundation of our research. A definition of posterior collapse is proposed by using mutual information (MI).

2.1   GAUSSIAN VAE

Consider a data space $\mathcal{X} \subset \mathbb{R}^{d_x}$ and a sample set $\{\mathbf{x}_i\}_{i=1}^N \subset \mathcal{X}$, where $\mathbf{x}_i \sim p_{\text{data}}(\mathbf{x})$. The empirical distribution $\tilde{p}_{\text{data}}(\mathbf{x})$ on $\mathcal{X}$ can be evaluated by $\tilde{p}_{\text{data}}(\mathbf{x}) = \frac{1}{N} \sum_{n=1}^N \delta(\mathbf{x} - \mathbf{x}_n)$, where $\delta(\cdot)$ denotes the Dirac delta function. In the standard VAE framework, a latent space $\mathcal{Z} \subset \mathbb{R}^{d_z}$ is learned and the sampled latent variables $\mathbf{z} \in \mathcal{Z}$ are used to generate data samples $\mathbf{x}' \in \mathcal{X}$. Let $q_\phi(\mathbf{z}|\mathbf{x})$ and $p_\theta(\mathbf{x}|\mathbf{z})$ denote the stochastic encoder and decoder, respectively. Trainable parameters of the two neural networks are denoted as ϕ and θ. The decoder generates data samples by $p_\theta(\mathbf{x}) := \mathbb{E}_{p(\mathbf{z})}[p_\theta(\mathbf{x}|\mathbf{z})]$,

---

[1]URL hidden due to blind review.

where $p(\mathbf{z})$ is the prior distribution on $\mathcal{Z}$. The encoder and decoder are jointly trained by minimizing the following objective function:

$$\mathcal{L} = -\mathbb{E}_{p_{\text{data}}(\mathbf{x})}\left[\ln p_\theta(x)\right] + \mathbb{E}_{p_{\text{data}}(\mathbf{x})} D_{\text{KL}}\left(q_\phi(\mathbf{z}|\mathbf{x}) \parallel p_\theta(\mathbf{z}|\mathbf{x})\right) + \mathbb{E}_{p_{\text{data}}(\mathbf{x})}\left[\ln p_{\text{data}}(\mathbf{x})\right]$$
$$= D_{\text{KL}}\left(p_{\text{data}}(\mathbf{x}) \parallel p_\theta(\mathbf{x})\right) + \mathbb{E}_{p_{\text{data}}(\mathbf{x})} D_{\text{KL}}\left(q_\phi(\mathbf{z}|\mathbf{x}) \parallel p_\theta(\mathbf{z}|\mathbf{x})\right). \tag{1}$$

This objective function was derived in Zhao et al. (2019), which represents everything in the form of Kullback–Leibler divergence, and is equivalent to ELBO maximization up to an additive constant.

In the context of the Gaussian VAE, the encoder and decoder are assumed to satisfy

$$q_\phi(\mathbf{z}|\mathbf{x}) = \mathcal{N}(\mathbf{z}|\boldsymbol{\mu}_\phi(\mathbf{x}), \text{diag}(\boldsymbol{\sigma}_\phi^2(\mathbf{x}))) \qquad \text{and} \qquad p_\theta(\mathbf{x}|\mathbf{z}) = \mathcal{N}(\mathbf{x}|\boldsymbol{\mu}_\theta(\mathbf{z}), \sigma_x^2\mathbf{I}). \tag{2}$$

The prior $p(\mathbf{z})$ is also assumed to be the Gaussian distribution as $p(\mathbf{z}) = \mathcal{N}(\mathbf{z}|\mathbf{0}, \mathbf{I})$. Substituting (2) into (1) while omitting terms independent of θ and ϕ leads to the following objective:

$$\tilde{\mathcal{J}}_{\sigma_x^2}(\theta, \phi) = \mathbb{E}_{\tilde{p}_{\text{data}}(\mathbf{x})}\left[\frac{1}{2\sigma_x^2}\mathbb{E}_{q_\phi(\mathbf{z}|\mathbf{x})}[\|\mathbf{x} - \boldsymbol{\mu}_\theta(\mathbf{z})\|_2^2] + D_{\text{KL}}(q_\phi(\mathbf{z}|\mathbf{x}) \parallel p(\mathbf{z}))\right], \tag{3}$$

which can be interpreted as the sum of the expected values of the reconstruction loss and the regularization term. In the case of a Gaussian prior and posterior, the regularization term is equal to $\frac{1}{2}\sum_{i=1}^{d_z}(\sigma_{\phi,i}^2(\mathbf{x}) + \mu_{\phi,i}(\mathbf{x})^2 - \log\sigma_{\phi,i}^2(\mathbf{x}) - 1)$.

2.2 POSTERIOR COLLAPSE

Posterior collapse is a major problem, where the encoder learns to map inputs to the latent space while ignoring the data distribution. In this phenomenon, the MI between input data and reconstructed data through the encoder-decoder path is reduced because the latent space has less information about the data distribution. Here, we suggest the following definition of **posterior collapse**.

Definition 1. *Posterior collapse is defined as the MI $\mathcal{I}(\mathbf{x}; \mathbf{x}')$ becoming nearly zero, where $\mathbf{x}' := \boldsymbol{\mu}_\theta(\mathbf{z})$ with $\mathbf{z} \sim q_\phi(\mathbf{z}|\mathbf{x})$.*

In many works (Bowman et al., 2015; Sønderby et al., 2016; Alemi et al., 2017; He et al., 2019; Razavi et al., 2019a), the phenomenon denoted as *posterior collapse* has been mathematically represented as $\mathbb{E}_{p_{\text{data}}(\mathbf{x})} D_{\text{KL}}(q_\phi(\mathbf{z}|\mathbf{x}) \parallel p(\mathbf{z})) \to 0$, which we hereafter refer to as *KL collapse* (Xu & Durrett, 2018). However, posterior collapse is not always caused by the diminished KL divergence, i.e., posterior collapse with $\mathbb{E}_{p_{\text{data}}(\mathbf{x})} D_{\text{KL}}(q_\phi(\mathbf{z}|\mathbf{x}) \parallel p(\mathbf{z})) \neq 0$ can occur. The proposed definition of posterior collapse includes *KL collapse* from the following theorem, which is proven in Appendix A.

Theorem 2. *$\mathcal{I}(\mathbf{x}; \mathbf{x}') \to 0$ as $\mathbb{E}_{p_{\text{data}}(\mathbf{x})} D_{\text{KL}}(q_\phi(\mathbf{z}|\mathbf{x}) \parallel p(\mathbf{z})) \to 0$ holds for any $p_\theta(\mathbf{x}|\mathbf{z})$.*

In Appendix E, it is demonstrated that posterior collapse can happen even if the KL divergence is nonzero when the posterior variance is fixed in $\mathcal{Z}$.

3 VARIANCE PARAMETER σ_x^2 AND THE LOCAL SMOOTHNESS

In this section, we provide mathematical and empirical support of the main hypothesis. Throughout this section, we adopt the following parameterization for the encoder for simplicity: $q_{\phi,\sigma_z^2}(\mathbf{z}|\mathbf{x}) = \mathcal{N}(\mathbf{z}|\boldsymbol{\mu}_\phi(\mathbf{x}), \sigma_z^2\mathbf{I})$, where the variance is parameterized as an isotropic matrix unlike the conventional VAE. A similar analysis on the conventional VAE can be found in Appendix B. It begins with showing that the choice of σ_x^2 affects the convergence point of σ_z^2, which is the variance parameter of the latent space. Then, we show that σ_z^2 acts as the weight of the gradient penalty, which is implicitly included in (3). This supports the main hypothesis that the over-regulation imposed by a large σ_x^2 via σ_z^2 causes the oversmoothness of the decoder and leads to **posterior collapse**. It is also empirically supported by observing the tendencies of the convergence point of σ_z^2, the smoothness and the MI $\mathcal{I}(\mathbf{x}, \mathbf{x}')$. Ultimately, these items of evidence motivated us to develop a method that adapts σ_x^2 to prevent oversmoothing of the decoder.

3.1 REGULARIZATION EFFECT OF σ_x^2 IN LINEAR APPROXIMATED ELBO

The effect of σ_x^2 on the convergence point of the variance parameter σ_z^2 can be observed from two extreme cases, $\sigma_x^2 \to 0+$ and $\sigma_x^2 \to \infty$. In the first case, $\tilde{\mathcal{J}}_{\sigma_x^2}$ reduces to

$\mathbb{E}_{\tilde{p}_{\text{data}}(\mathbf{x})}\mathbb{E}_{q_{\phi,\sigma_z^2}(\mathbf{z}|\mathbf{x})}[\|\mathbf{x} - \boldsymbol{\mu}_\theta(\mathbf{z})\|_2^2]$, and it becomes zero only if $\sigma_z^2 = 0$. In the second case, $\tilde{\mathcal{J}}_{\sigma_x^2}$ reduces to $\mathbb{E}_{\tilde{p}_{\text{data}}(\mathbf{x})}D_{\text{KL}}(q_{\phi,\sigma_z^2}(\mathbf{z}|\mathbf{x}) \parallel p(\mathbf{z}))$, and σ_z^2 becomes 1 at the minimum point, from $D_{\text{KL}}(q_{\phi,\sigma_z^2}(\mathbf{z}|\mathbf{x}) \parallel p(\mathbf{z})) = \frac{d_z}{2}(\sigma_z^2 - \log \sigma_z^2 - 1) + \|\boldsymbol{\mu}_\phi(\mathbf{x})\|_2^2$. This shows that a small σ_x^2 makes σ_z^2 converge to a value around 0, while a large σ_x^2 makes σ_z^2 converge to a value around 1.

If σ_z^2 is sufficiently small, as the training progresses to a certain extent, the perturbed decoding process $\boldsymbol{\mu}_\theta(\mathbf{z} + \boldsymbol{\epsilon}_z)$ around $\mathbf{z} = \boldsymbol{\mu}_\phi(\mathbf{x})$ with $\boldsymbol{\epsilon}_z \sim \mathcal{N}(\boldsymbol{\epsilon}_z|\mathbf{0}, \sigma_z^2\mathbf{I})$ can be approximated as a linear function. The ELBO can be approximated as follows by using the linear approximation of $\boldsymbol{\mu}_\theta(\cdot)$ and omitting terms independent of θ and ϕ:

$$\tilde{\mathcal{J}}_{\sigma_x^2}(\theta, \phi, \sigma_z^2) \approx \frac{1}{2\sigma_x^2}\mathbb{E}_{\tilde{p}_{\text{data}}(\mathbf{x})}\Big[\|\mathbf{x} - \boldsymbol{\mu}_\theta(\boldsymbol{\mu}_\phi(\mathbf{x}))\|_2^2 + \sigma_z^2\|\nabla\boldsymbol{\mu}_\theta(\boldsymbol{\mu}_\phi(\mathbf{x}))\|_F^2 + 2\sigma_x^2\|\boldsymbol{\mu}_\phi(\mathbf{x})\|_2^2\Big]. \quad (4)$$

In the approximation above, $\|\cdot\|_F$ is the Frobenius norm and σ_z^2 is treated as a function parameter. The derivation of the above approximation can be found in Appendix B. Equation (4) decomposes the objective function into three terms: a reconstruction error term, gradient penalty term and L_2 regularization term. As one can see from (4), σ_z^2 regularizes the smoothness of the decoder by penalizing its gradient norm in training. Although the linear approximation above is derived for the simplified VAE parameterization, we also provide the linear approximation of the ELBO for the standard VAE parameterization (2) in Appendix B, where the second term in (4) becomes a weighted gradient penalty.

Summarizing the above observations shows that σ_x^2 affects the smoothness via σ_z^2, while σ_z^2 directly regularizes the smoothness. This means that if σ_x^2 is excessively large, it will cause over-regularization of the decoder and suppress $\mathcal{I}(\mathbf{z}, \mathbf{x}')(\geq \mathcal{I}(\mathbf{x}, \mathbf{x}'))$, which finally leads to posterior collapse. To avoid such over-regularization, σ_x^2 and σ_z^2 should be determined appropriately. In addition, an experiment shows that posterior collapse can be triggered by directly manipulating σ_z^2, as discussed in Appendix E.

3.2 EMPIRICAL STUDY ON SMOOTHNESS OF DECODER IN THE GENERAL CASE

Section 3.1 shows the impact of σ_x^2 on the regularization of the decoder smoothness through the linear approximated objective function. To support the main hypothesis in the general case, an experiment on the MNIST dataset (LeCun et al., 1998) is conducted. Several criteria are accessed to provide evidence for the regularization effect of σ_x^2 on the decoder smoothness and its consequential effect on MI $\mathcal{I}(\mathbf{x}, \mathbf{x}')$. To confirm that σ_x^2 affects the smoothness via σ_z^2, we conduct the experiment for two cases: **stochastic encoding** and **deterministic encoding**. While the stochastic encoder $q_{\phi,\sigma_z^2}(\mathbf{z}|\mathbf{x})$ is used in the former case, a VAE equipped with a deterministic encoder, i.e., σ_z^2 is fixed to zero during the training, is investigated in the latter case. Observing the difference between the two cases provides empirical support for Section 3.1. To investigate the relation between σ_x^2 and the smoothness of the decoder clearly, common generalization techniques such as batch normalization (Ioffe & Szegedy, 2015; Santurkar et al., 2018) and weight decay are not used.

Criteria We used several criteria to observe the impact of σ_x^2 in the experiment, such as the reconstruction error (MSE), KL divergence value $\mathbb{E}_{\tilde{p}_{\text{data}}(\mathbf{x})}D_{\text{KL}}(q_\phi(\mathbf{z}|\mathbf{x}) \parallel p(\mathbf{z}))$ and the final converged value of σ_z^2. In addition, we also estimate the local smoothness of the decoder and the MI between $\mathbf{x}$ and $\mathbf{x}'$, denoted as $\mathcal{I}(\mathbf{x}, \mathbf{x}')$. To access the local smoothness, the **expected local smoothness** (ELS) is introduced, which is the lower bound of the Lipschitz constant of the decoder. Consider a sample that is decoded with perturbation $\boldsymbol{\mu}_\theta(\boldsymbol{\mu}_\phi(\mathbf{x}) + \boldsymbol{\epsilon}_z)$, where the perturbation follows a zero-mean Guassian distribution with variance s_z^2, $\boldsymbol{\epsilon}_z \sim \mathcal{N}(\boldsymbol{\epsilon}_z|\mathbf{0}, s_z^2\mathbf{I})$. Let $\boldsymbol{\epsilon}_z$ and $\boldsymbol{\epsilon}_z'$ be i.i.d. random variables. We define the **expected gap** $\Delta^2(s_z^2)$ as

$$\Delta^2(s_z^2) := \mathbb{E}_{p_{\text{data}}(\mathbf{x})}\mathbb{E}_{\mathcal{N}(\boldsymbol{\epsilon}_z|\mathbf{0}, s_z^2\mathbf{I})\mathcal{N}(\boldsymbol{\epsilon}_z'|\mathbf{0}, s_z^2\mathbf{I})}[\Delta^2(\mathbf{x}, \boldsymbol{\epsilon}_z, \boldsymbol{\epsilon}_z')] \quad (5)$$

with $\Delta^2(\mathbf{x}, \boldsymbol{\epsilon}_z, \boldsymbol{\epsilon}_z') := \|\boldsymbol{\mu}_\theta(\boldsymbol{\mu}_\phi(\mathbf{x}) + \boldsymbol{\epsilon}_z) - \boldsymbol{\mu}_\theta(\boldsymbol{\mu}_\phi(\mathbf{x}) + \boldsymbol{\epsilon}_z')\|_2^2.$

As s_z^2 decereases, the ratio $\Delta^2(s_z^2)/(2s_z^2)$ converges and becomes an indicator of $\mathbb{E}_{\tilde{p}_{\text{data}}(\mathbf{x})}[\|\nabla\boldsymbol{\mu}_\theta(\boldsymbol{\mu}_\phi(\mathbf{x}))\|_F^2]$, which is regularized by σ_z^2 in (4). Therefore, we can now define the ELS as

$$\mathbb{E}_{\tilde{p}_{\text{data}}(\mathbf{x})}[\|\nabla\boldsymbol{\mu}_\theta(\boldsymbol{\mu}_\phi(\mathbf{x}))\|_F^2]. \quad (6)$$

Table 1: Evaluation of various criteria for different σ_x^2: the expected value of $\|\mathbf{x}' - \mathbf{x}\|_2^2$ (MSE), KL divergence, the converged value of σ_z^2, the upper bound of the MI $\mathcal{I}(\mathbf{x}'; \mathbf{z})$, the expected gap (perturbation variance s_z^2 are set to 10^{-2} and 10^{-3}) and expected local smoothness (ELS).

| $\log \sigma_x^2$ | Stochastic encoding | | | | | | | Deterministic encoding | | | | |
| | MSE | KL | σ_z^2 | MI | Expected gap | | ELS | MSE | MI | Expected gap | | ELS |
					10^{-2}	10^{-3}				10^{-2}	10^{-3}	
0.0	**52.74**	**0.00**	**1.00**	**0.03**	6.31e-5	6.35e-6	**3.97e-4**	5.95	12.5	74.6	25.3	7.43e+2
−0.1	18.03	9.39	9.56e-2	9.7	1.05	0.108	6.76	5.69	14.7	69.1	22.5	6.82e+2
−0.2	15.15	10.93	6.48e-2	12.5	1.30	0.135	8.34	5.38	17.9	63.4	20.7	6.37e+2
−0.3	13.08	12.54	4.36e-2	16.0	1.51	0.157	9.72	5.37	21.4	58.1	17.9	5.78e+2
−0.4	11.38	14.13	3.01e-2	20.6	1.77	0.184	1.14e+1	5.31	25.8	58.2	15.5	5.40e+2
−0.5	10.18	15.30	2.14e-2	26.3	1.99	0.208	1.28e+1	5.26	30.6	53.1	12.9	4.74e+2
−0.6	9.16	16.72	1.55e-2	33.2	2.16	0.227	1.40e+1	5.14	38.9	48.9	11.8	4.42e+2
−0.7	8.25	18.05	1.11e-2	42.3	2.31	0.244	1.50e+1	5.17	46.1	45.5	10.1	3.98e+2
−0.8	7.72	19.27	8.21e-3	52.9	2.40	0.254	1.56e+1	5.06	58.0	43.2	9.15	3.71e+2
−0.9	7.13	20.55	5.97e-3	64.9	2.43	0.257	1.58e+1	4.98	71.9	39.2	7.83	3.29e+2
−1.0	6.70	21.75	4.45e-3	82.3	2.57	0.272	1.67e+1	5.01	89.1	35.3	6.61	2.89e+2

Further details of the ELS are described in Appendix C. As a reference, we estimate the upper bound of $\mathcal{I}(\mathbf{x}, \mathbf{x}')$, which is $\mathcal{I}(\mathbf{x}'; \mathbf{z})$, by Monte Carlo estimation.

Results Table 1 summarizes the results for different σ_x^2. In the *stochastic encoding* case, a larger σ_x^2 consistently leads to a larger σ_z^2. This results in a smaller expected gap, a smaller ELS and a lower upper bound of MI. This supports the main hypothesis that a larger σ_x^2 makes the decoder smoother. In the case of $\sigma_x^2 = 1.0$, all the criteria except MSE become nearly zero, where KL collapse and posterior collapse both occur due to the over-regularization of the smoothness of the latent space. On the other hand, in the *deterministic encoding* case, the ELS increases with σ_x^2. This is because σ_x^2 does not directly regularize the decoder via the gradient penalty as in (4). As a result, the MI upper bound does not shrink to zero even if $\sigma_x^2 = 1.0$, where posterior collapse occurs in the case of stochastic encoding. The difference in the results between the two cases clearly suggests that a large σ_x^2 triggers the oversmoothness via σ_z^2, which is consistent with the discussion in Section 3.1. These results provide empirical support of the main hypothesis as well as the discussion in Section 3.1. Further details and examples of images are shown in Appendix D.

3.3 DIFFICULTY OF CHOOSING AN APPROPRIATE σ_x^2

According to previous sections, a large σ_x^2 will cause oversmoothness. Therefore, we consider the case of fixing σ_x^2 to a sufficiently small value to avoid the problem. We arrive at the following theorem, whose proof can be found in Appendix F:

Theorem 3. *Consider the global optimum of $\mathcal{J}_{\sigma_x^2}(\theta, \phi, \sigma_z^2)$ w.r.t. a given σ_x^2. If $\sigma_x^2 \to 0$, then $\sigma_z^2 \to 0$.*

In Theorem 3, $\mathcal{J}_{\sigma_x^2}(\theta, \phi, \sigma_z^2)$ is optimized on the basis of the true data distribution instead of the empirical data distribution. According to the theorem, σ_z^2 converges to zero as σ_x^2 approaches zero, which leads to zero gradient penalty for the decoder as the VAE training progresses. In practice, we have no access to $p_{\text{data}}(\mathbf{x})$, but we have access to the empirical distribution $\tilde{p}_{\text{data}}(\mathbf{x})$. Theorem 3 is satisfied even when $p_{\text{data}}(\mathbf{x})$ is replaced with $\tilde{p}_{\text{data}}(\mathbf{x})$. In this case, where σ_x^2 is chosen to be small, the optimization process of $\tilde{\mathcal{J}}_{\sigma_x^2}$ will fit $p_{\theta,\sigma_x^2}(\mathbf{x})$ to the empirical distribution $\tilde{p}_{\text{data}}(\mathbf{x})$, which usually results in overfitting.

As shown above, choosing an appropriate σ_x^2 that avoids both oversmoothness and overfitting is nontrivial. Moreover, it is likely that σ_x^2 should be adapted depending on the status of training. Therefore, it is intuitive to adapt σ_x^2 instead of fixing it, which will be described in the next section.

4 ADAPTIVELY REGULARIZED ELBO

A modified ELBO-based objective function is proposed, which can be interpreted as an implicit update scheme that simultaneously updates σ_x^2 and the rest of the parameters. We also derive corresponding objective functions for models with different variance parameterizations.

4.1 ELBO WITH ADAPTIVE σ_x^2

In this subsection, we newly optimize the VAE objective function (1) w.r.t. all the parameters including σ_x^2, which is usually fixed in existing implementations. Following the process of establishing (3) but keeping the terms related to σ_x^2, we arrive at:

$$\tilde{\mathcal{J}}(\theta, \phi, \sigma_x^2) = \mathbb{E}_{\tilde{p}_{\text{data}}(\mathbf{x})}\left[\frac{1}{2\sigma_x^2}\mathbb{E}_{q_\phi(\mathbf{z}|\mathbf{x})}\left[\|\mathbf{x} - \boldsymbol{\mu}_\theta(\mathbf{z})\|_2^2\right] + D_{\text{KL}}\left(q_\phi(\mathbf{z}|\mathbf{x}) \parallel p(\mathbf{z})\right)\right] + \frac{d_x}{2}\ln\sigma_x^2. \quad (7)$$

From the partial derivative of $\tilde{\mathcal{J}}$ w.r.t. σ_x^2, the MLE of σ_x^2, denoted as $\hat{\sigma}_x^2$, can be evaluated with the other parameters fixed. Then, the ordinary network parameters θ and ϕ can be updated by optimizing (7) with the variance σ_x^2 fixed. This combination of MLE and the alternative update between (θ, ϕ) and σ_x^2 guarantees that (i) if θ and ϕ are fixed, then there exists $\hat{\sigma}_x^2$ such that $\tilde{\mathcal{J}}(\theta, \phi, \hat{\sigma}_x^2) \leq \tilde{\mathcal{J}}(\theta, \phi, \sigma_x^2)$ and (ii) for the $\hat{\sigma}_x^2$ obtained in the previous step, there exist $\hat{\theta}$ and $\hat{\phi}$, such that $\tilde{\mathcal{J}}(\hat{\theta}, \hat{\phi}, \hat{\sigma}_x^2) \leq \tilde{\mathcal{J}}(\theta, \phi, \hat{\sigma}_x^2)$. In this respect, the convergence of the optimization is assured and the parameter σ_x^2 is kept as the MLE during the whole training stage. This inspired us to develop a weight scheduling scheme for $\hat{\sigma}_x^2$, leading to a modified ELBO-based objective function. Consider the trainable network parameters (θ, ϕ) and the variance parameter σ_x^2. The update of the objective $\tilde{\mathcal{J}}(\theta, \phi, \sigma_x^2)$ is divided as

$$\sigma_x^{2(t+1)} = \frac{1}{d_x}\mathbb{E}_{\tilde{p}_{\text{data}}(\mathbf{x})}\mathbb{E}_{q_{\phi^{(t)}}(\mathbf{z}|\mathbf{x})}\left[\|\mathbf{x} - \boldsymbol{\mu}_{\theta^{(t)}}(\mathbf{z})\|_2^2\right] \quad (8a)$$

$$\theta^{(t+1)}, \phi^{(t+1)} = \arg\min_{\theta, \phi} \tilde{\mathcal{J}}_{\sigma_x^{2(t+1)}}(\theta, \phi), \quad (8b)$$

where t is the iteration index. The step updating (θ, ϕ) is the same as that in the standard VAE; the step updating σ_x^2 in (8a) can be interpreted as determining an appropriate balance between the reconstruction error and the KL term in $\tilde{\mathcal{J}}_{\sigma_x^2}(\theta, \phi)$. As the learning progresses, the parameter σ_x^2 will decrease along with the MSE $\mathbb{E}_{\tilde{p}_{\text{data}}(\mathbf{x})}\mathbb{E}_{q_\phi(\mathbf{z}|\mathbf{x})}[\|\mathbf{x} - \boldsymbol{\mu}_\theta(\mathbf{z})\|_2^2]$, which is consistent with the discussion in Dai & Wipf (2019).

Proposed objective function (AR-ELBO) The update scheme above can be further simplified by substituting (8a) into (7), which converts $\tilde{\mathcal{J}}(\theta, \phi, \hat{\sigma}_x^2)$ into

$$\tilde{\mathcal{J}}_{\text{AR}}(\theta, \phi) = \frac{d_x}{2}\ln\mathbb{E}_{\tilde{p}_{\text{data}}(\mathbf{x})}\mathbb{E}_{q_\phi(\mathbf{z}|\mathbf{x})}\left[\|\mathbf{x} - \boldsymbol{\mu}_\theta(\mathbf{z})\|_2^2\right] + \mathbb{E}_{\tilde{p}_{\text{data}}(\mathbf{x})}D_{\text{KL}}\left(q_\phi(\mathbf{z}|\mathbf{x}) \parallel p(\mathbf{z})\right), \quad (9)$$

where all constant terms w.r.t. the parameters are omitted. Optimizing (9) also makes σ_x^2 remain as the MLE during the VAE training. Moreover, (9) is equivalent to the standard Gaussian VAE plus weight balancing with (8b). This relieves the VAE from the problem of imbalance between the KL divergence term and the reconstruction loss. Also, as stated by Theorem 3, decreasing σ_x^2 also decreases σ_z^2. This gradually relieves the regularization of the ELS (6), which can be observed from (4). However, this eventually diminishes the gradient penalty; therefore, we suggest using early-stopping and learning rate scheduling to deal with this situation, which can give the decoder both appropriate smoothness and generalization capability.

4.2 OBJECTIVES FOR VARIOUS PARAMETERIZATIONS

In the standard VAE given by (2), the variance of the decoded distribution on $\mathcal{X}$, denoted as $\boldsymbol{\Sigma}_x$, is modeled as an identity matrix, i.e., $\boldsymbol{\Sigma}_x = \sigma_x^2\mathbf{I}$. In this case, σ_x^2 is simply a scalar value and the reconstruction objective is the same as conventional MSE and is minimized as in (9). However, out of curiosity, we would like to explore three other variance parameterizations in addition to (2) and derive corresponding reconstruction objectives for these cases, in which the reconstruction objectives are no longer equal to MSE.

In fact, the variance $\boldsymbol{\Sigma}_x$ can not only be parameterized by an **isotropic/diagonal** matrix but also be chosen to be **independent** or **dependent** on z. We denote these in Table 2 as **Iso-I** (Isotropic-Independent), **Iso-D** (Isotropic-Dependent), **Diag-I** (Diagonal-Independent) and **Diag-D** (Diagonal-Dependent). The first case, Iso-I, corresponds to the standard variance model $\boldsymbol{\Sigma}_x = \sigma_x^2\mathbf{I}$. For these

Table 2: Parameterizations of posterior variance in $\mathcal{X}$ and corresponding reconstruction objectives.

	Variance model ($\boldsymbol{\Sigma}_x$)	Reconstruction objective ($\tilde{\mathcal{J}}_{\text{rec}}(\theta, \phi, \hat{\boldsymbol{\Sigma}}_x)$)
(Iso-I)	$\sigma_x^2 \mathbf{I}$	$\frac{d_x}{2} \ln \mathbb{E}_{\tilde{p}_{\text{data}}(\mathbf{x})} \mathbb{E}_{q_\phi(\mathbf{z}|\mathbf{x})}[\|\mathbf{x} - \boldsymbol{\mu}_\theta(\mathbf{z})\|_2^2]$
(Iso-D)	$\sigma_x^2(\mathbf{z})\mathbf{I}$	$\frac{d_x}{2} \mathbb{E}_{\tilde{p}_{\text{data}}(\mathbf{x})} \mathbb{E}_{q_\phi(\mathbf{z}|\mathbf{x})}[\ln \|\mathbf{x} - \boldsymbol{\mu}_\theta(\mathbf{z})\|_2^2]$
(Diag-I)	$\text{diag}(\boldsymbol{\sigma}_x^2)$	$\frac{1}{2} \sum_{i=1}^{d_x} \ln \mathbb{E}_{\tilde{p}_{\text{data}}(\mathbf{x})} \mathbb{E}_{q_\phi(\mathbf{z}|\mathbf{x})}[(x_i - \mu_{\theta,i}(\mathbf{z}))^2]$
(Diag-D)	$\text{diag}(\boldsymbol{\sigma}_x^2(\mathbf{z}))$	$\frac{1}{2} \sum_{i=1}^{d_x} \mathbb{E}_{\tilde{p}_{\text{data}}(\mathbf{x})} \mathbb{E}_{q_\phi(\mathbf{z}|\mathbf{x})}[\ln(x_i - \mu_{\theta,i}(\mathbf{z}))^2]$

parameterizations, the corresponding objectives may be summarized as

$$\tilde{\mathcal{J}}_{\text{AR}}(\theta, \phi, \hat{\boldsymbol{\Sigma}}_x) = \tilde{\mathcal{J}}_{\text{rec}}(\theta, \phi, \hat{\boldsymbol{\Sigma}}_x) + \mathbb{E}_{\tilde{p}_{\text{data}}(\mathbf{x})} D_{\text{KL}}(q(\mathbf{z}|\mathbf{x}) \| p(\mathbf{z})) \tag{10a}$$

$$\tilde{\mathcal{J}}_{\text{rec}}(\theta, \phi, \boldsymbol{\Sigma}_x) = \frac{1}{2} \mathbb{E}_{\tilde{p}_{\text{data}}(\mathbf{x})} \mathbb{E}_{q(\mathbf{z}|\mathbf{x})} \left[\text{trace} \left(\boldsymbol{\Sigma}_x^{-1} (\mathbf{x} - \boldsymbol{\mu}_\theta(\mathbf{z}))(\mathbf{x} - \boldsymbol{\mu}_\theta(\mathbf{z}))^\top \right) + \ln |\boldsymbol{\Sigma}_x| \right]. \tag{10b}$$

By evaluating the partial derivative of $\tilde{\mathcal{J}}_{\text{rec}}$ w.r.t. $\boldsymbol{\Sigma}_x$, i.e., using its MLE, the reconstruction loss $\tilde{\mathcal{J}}_{\text{rec}}$ corresponding to each case can be derived. All the derivations can be found in Appendix G. The final reconstruction objectives with different parameterizations of $\boldsymbol{\Sigma}_x$ are listed in Table 2. It is interesting to note that the reconstruction error for each dimension in the data space has to be calculated separately for Diag-D; meanwhile, only MSE for the whole minibatch is needed in Iso-I. Considering the optimization stability in practical situations, we suggest adding a small constant, e.g., 10^{-6}, before taking the logarithm except for in the case of Iso-I.

Although the proposed objective functions are capable of determining $\boldsymbol{\Sigma}_x$ appropriately, it should be noted that a gap still exists between the prior $p(\mathbf{z})$ and the aggregated posterior $q_\phi(\mathbf{z})$ obtained by the proposed methods. The cause can be observed from the reformulated (1) (see Appendix H):

$$\mathcal{L} = D_{\text{KL}}(p_{\text{data}}(\mathbf{x}) \| p_\theta(\mathbf{x})) + D_{\text{KL}}(p_{\text{data}}(\mathbf{x})q_\phi(\mathbf{z}|\mathbf{x}) \| q_\phi(\mathbf{z})p_\theta(\mathbf{x}|\mathbf{z})) + D_{\text{KL}}(q_\phi(\mathbf{z}) \| p(\mathbf{z})). \tag{11}$$

The first two terms in (11) can eventually become dominant in the VAE training. As a consequence, generation through sampling latent variables from the prior can cause off-distribution samples to be generated. To overcome this prior–posterior mismatch, at least two approaches can be adopted: (i) conduct another posterior estimation after the ordinary VAE training (van den Oord et al., 2017; Razavi et al., 2019b; Dai & Wipf, 2019; Ghosh et al., 2020; Morrow & Chiu, 2020) or (ii) add another regularizing term to the objective function (Makhzani et al., 2015; Tolstikhin et al., 2018; Zhao et al., 2019). The former approach is adopted in our work since it is effective (Ghosh et al., 2020) and is applicable to any VAE variation.

To summarize, the proposed AR-ELBO regularizes the Gaussian VAE with appropriate weighting for the gradient penalty without the need for an extra hyperparameter. Moreover, the remaining mismatch between the prior and posterior is mitigated by an extra pass of posterior estimation. A detailed discussion comparing the proposed objective function with previous works can be found in Appendix I.

5 EXPERIMENTS

We compare the proposed methods with the following models: VAE, RAE (Ghosh et al., 2020), WAE-MMD (Tolstikhin et al., 2018) and plain autoencoder (AE). The quality of generated images is evaluated using Fréchet Inception Distance (FID) (Heusel et al., 2017) on the MNIST and CelebA (Liu et al., 2015) datasets with the default train/test split. Regarding the prior–posterior mismatch, three approaches are tested on all the models. The first approach is the conventional case, which samples the latent variables from the prior. The other two approaches are applied after the ordinary training. The second approach forms an aggregated posterior $q_\phi(\mathbf{z})$ by a second-stage VAE (Dai & Wipf, 2019). The third approach uses a Gaussian mixture model (GMM) with 10 to 100 components (Ghosh et al., 2020) to fit the posterior. The baseline is the standard VAE, and two methods of choosing σ_x^2 are tested: (i) σ_x^2 fixed to 1.0 as in general implementations; and (ii) σ_x^2 learned with (7) by an optimizer as an usual trainable parameter (Dai & Wipf, 2019). In RAE, its

Table 3: Numerical evaluation on MNIST and CelebA. The MSE of sample reconstruction is evaluated on the test set. The quality of generated samples is measured by FID for three cases: sampling the latent variables from the prior and from the estimated posterior by 2^{nd} VAE and GMM.

	MNIST				CelebA				
	MSE	FID			MSE	FID			
		Prior	2^{nd}VAE	GMM-10		Prior	2^{nd}VAE	GMM-10	GMM-100
VAE ($\sigma_x^2 = 1.0$)	20.25	55.85	182.64	58.96	121.91	55.46	139.32	54.66	53.94
VAE (σ_x^2: optimizer)[†]	4.28	20.93	14.83[‡]	13.39	61.42	63.21	63.12[†]	51.40	49.61
WAE-MMD	4.34	22.76	15.00	13.70	62.66	**52.89**	51.32	43.57	41.88
AE	4.31	–	20.66	13.20	61.44	–	62.34	46.47	43.41
RAE	**4.28**	–	18.54	13.68	61.49	–	57.26	46.50	43.89
RAE-GP	4.30	–	18.89	13.71	61.48	–	54.54	43.63	41.10
Ours (Iso-I)	4.40	22.78	15.77	12.21	62.02	82.20	52.48	**42.82**	41.03
Ours (Diag-I)	5.35	24.15	17.18	13.38	63.51	87.44	53.60	45.85	42.83
Ours (Iso-D)	4.31	22.94	17.57	12.89	**61.38**	78.24	**49.97**	43.27	**40.39**
Ours (Diag-D)	6.80	**16.64**	**10.49**	**10.05**	70.75	64.40	55.30	46.63	45.27

[†] σ_x is learned as a trainable parameter similarly to in Dai & Wipf (2019).

[‡] 2^{nd}VAE is the second-stage VAE proposed in Dai & Wipf (2019) after the main VAE.

objective function is the sum of the reconstruction error, the regularization of the decoder and the L_2 regularization of the latent space. In RAE-GP, gradient penalty is used as the regularization of the decoder. The objective function of RAE-GP is equivalent to (4) except for that the weighting parameters are determined manually. For WAE-MMD, inverse multi-quadratic kernels with seven scales are used as proposed by Tolstikhin et al. (2018). Note that both WAE and RAE have hyperparameters in their objective functions. In contrast, the other methods, as well as the proposed objective functions, include no hyperparameters. However, regarding the major factor that affects the smoothness of the decoder, the proposed methods and VAE control smoothness by regularizing terms in their objective functions, while WAE and AE rely only on the network architecture and generalization techniques.

The latent space dimensions for MNIST and CelebA were set to $d_z = 16$ and 64, respectively, consistent with Ghosh et al. (2020). A common network architecture, which is adopted from Chen et al. (2016) and described in Appendix J, is used for all models. In Table 3, we report the evaluation result of each method as: (i) the MSE of the reconstructed test data and (ii) the FID of generated images. The proposed methods (Diag-I, Iso-D and Diag-D) except for Iso-I do not necessarily achieve the best MSE, since the MSE is no longer the reconstruction loss for them. In the case of sampling $z \in \mathcal{Z}$ from the prior, a low FID is achieved by WAE due to the relatively strong regularization of the aggregated posterior with MMD. The images generated by the proposed method achiev the best FID score on MNIST, and is competitive on CelebA. It should be noted that the learned σ_x^2 values on MNIST and CelebA from Iso-I are 0.0056 and 0.0050, respectively, which are much smaller than 1.0. Examples of reconstructed and generated images are shown in Appendix K.

6 CONCLUSION

We analyzed the posterior collapse phenomenon on the Gaussian VAE and investigated how strongly the variance parameter impacts the local smoothness of the decoder. The relation between the variance parameter and the local smoothness is examined both theoretically and empirically. We proposed optimization schemes to regulate the local smoothness appropriately, which leads to the prevention of posterior collapse due to oversmoothness. The proposed AR-ELBO implicitly optimizes the variance parameter to avoid over-regularizing of the smoothness. In addition, variations of AR-ELBO for different parameterizations of posterior variances were also derived. Our experiments show that the Gaussian VAE equipped with the proposed objective functions is competitive with other state-of-the-art models. In this work, the prior–posterior mismatch was covered by extra posterior estimation methods; however, we would like to seek a thorough solution for this in the future.

REFERENCES

Alexander A Alemi, Ben Poole, Ian Fischer, Joshua V Dillon, Rif A Saurous, and Kevin Murphy. Fixing a broken ELBO. *arXiv preprint arXiv:1711.00464*, 2017.

Samuel R Bowman, Luke Vilnis, Oriol Vinyals, Andrew M Dai, Rafal Jozefowicz, and Samy Bengio. Generating sentences from a continuous space. *arXiv preprint arXiv:1511.06349*, 2015.

Xi Chen, Yan Duan, Rein Houthooft, John Schulman, Ilya Sutskever, and Pieter Abbeel. InfoGAN: Interpretable representation learning by information maximizing generative adversarial nets. In *Proc. Advances in Neural Information Processing Systems (NeurIPS)*, pp. 2172–2180, 2016.

Bin Dai and David Wipf. Diagnosing and enhancing VAE models. In *Proc. International Conference on Learning Representation (ICLR)*, 2019.

Bin Dai, Ziyu Wang, and David Wipf. The usual suspects? Reassessing blame for VAE posterior collapse. In *Proc. International Conference on Machine Learning (ICML)*, 2020.

Hao Fu, Chunyuan Li, Xiaodong Liu, Jianfeng Gao, Asli Celikyilmaz, and Lawrence Carin. Cyclical annealing schedule: A simple approach to mitigating KL vanishing. *arXiv preprint arXiv:1903.10145*, 2019.

Partha Ghosh, Mehdi SM Sajjadi, Antonio Vergari, Michael Black, and Bernhard Schölkopf. From variational to deterministic autoencoders. In *Proc. International Conference on Learning Representation (ICLR)*, 2020.

Ian Goodfellow, Jean Pouget-Abadie, Mehdi Mirza, Bing Xu, David Warde-Farley, Sherjil Ozair, Aaron Courville, and Yoshua Bengio. Generative adversarial nets. In *Proc. Advances in Neural Information Processing Systems (NeurIPS)*, pp. 2672–2680, 2014.

Ishaan Gulrajani, Faruk Ahmed, Martin Arjovsky, Vincent Dumoulin, and Aaron C Courville. Improved training of Wasserstein GANs. In *Proc. Advances in Neural Information Processing Systems (NeurIPS)*, pp. 5767–5777, 2017.

Junxian He, Daniel Spokoyny, Graham Neubig, and Taylor Berg-Kirkpatrick. Lagging inference networks and posterior collapse in variational autoencoders. In *Proc. International Conference on Learning Representation (ICLR)*, 2019.

Martin Heusel, Hubert Ramsauer, Thomas Unterthiner, Bernhard Nessler, and Sepp Hochreiter. GANs trained by a two time-scale update rule converge to a local Nash equilibrium. In *Proc. Advances in Neural Information Processing Systems (NeurIPS)*, pp. 6626–6637, 2017.

Irina Higgins, Loic Matthey, Arka Pal, Christopher Burgess, Xavier Glorot, Matthew Botvinick, Shakir Mohamed, and Alexander Lerchner. beta-VAE: Learning basic visual concepts with a constrained variational framework. In *Proc. International Conference on Learning Representation (ICLR)*, 2017.

Sergey Ioffe and Christian Szegedy. Batch normalization: Accelerating deep network training by reducing internal covariate shift. In *Proc. International Conference on Machine Learning (ICML)*, 2015.

Michael I Jordan, Zoubin Ghahramani, Tommi S Jaakkola, and Lawrence K Saul. An introduction to variational methods for graphical models. *Machine Learning*, 37(2):183–233, 1999.

Diederik P Kingma and Jimmy Ba. Adam: A method for stochastic optimization. In *Proc. International Conference on Learning Representation (ICLR)*, 2015.

Diederik P Kingma and Max Welling. Auto-encoding variational Bayes. In *Proc. International Conference on Learning Representation (ICLR)*, 2014.

Yann LeCun, Léon Bottou, Yoshua Bengio, and Patrick Haffner. Gradient-based learning applied to document recognition. *Proc. IEEE*, 86(11):2278–2324, 1998.

Ziwei Liu, Ping Luo, Xiaogang Wang, and Xiaoou Tang. Deep learning face attributes in the wild. In *Proc. IEEE Conference on Computer Vision and Pattern Recognition (CVPR)*, pp. 3730–3738, 2015.

James Lucas, George Tucker, Roger B Grosse, and Mohammad Norouzi. Don't blame the ELBO! A linear VAE perspective on posterior collapse. In *Proc. Advances in Neural Information Processing Systems (NeurIPS)*, pp. 9403–9413, 2019.

Xuezhe Ma, Chunting Zhou, and Eduard Hovy. MAE: Mutual posterior-divergence regularization for variational autoencoders. In *Proc. International Conference on Learning Representation (ICLR)*, 2019.

Laurens van der Maaten and Geoffrey Hinton. Visualizing data using t-SNE. *Journal of Machine Learning Research*, 9:2579–2605, 2008.

Alireza Makhzani, Jonathon Shlens, Navdeep Jaitly, Ian Goodfellow, and Brendan Frey. Adversarial autoencoders. In *Proc. International Conference on Learning Representation (ICLR) Workshop*, 2015.

Takeru Miyato, Toshiki Kataoka, Masanori Koyama, and Yuichi Yoshida. Spectral normalization for generative adversarial networks. In *Proc. International Conference on Learning Representation (ICLR)*, 2018.

Rogan Morrow and Wei-Chen Chiu. Variational autoencoders with normalizing flow decoders. *arXiv preprint arXiv:2004.05617*, 2020.

Ali Razavi, Aäron van den Oord, Ben Poole, and Oriol Vinyals. Preventing posterior collapse with delta-VAEs. In *Proc. International Conference on Learning Representation (ICLR)*, 2019a.

Ali Razavi, Aaron van den Oord, and Oriol Vinyals. Generating diverse high-fidelity images with VQ-VAE-2. In *Proc. Advances in Neural Information Processing Systems (NeurIPS)*, pp. 14866–14876, 2019b.

Shibani Santurkar, Dimitris Tsipras, Andrew Ilyas, and Aleksander Madry. How does batch normalization help optimization? In *Proc. Advances in Neural Information Processing Systems (NeurIPS)*, pp. 2483–2493, 2018.

Huajie Shao, Shuochao Yao, Dachun Sun, Aston Zhang, Shengzhong Liu, Dongxin Liu, Jun Wang, and Tarek Abdelzaher. Controllable variational autoencoder. In *Proc. International Conference on Machine Learning (ICML)*, 2020.

Casper Kaae Sønderby, Tapani Raiko, Lars Maaløe, Søren Kaae Sønderby, and Ole Winther. Ladder variational autoencoders. In *Proc. Advances in Neural Information Processing Systems (NeurIPS)*, pp. 3738–3746, 2016.

Ilya Tolstikhin, Olivier Bousquet, Sylvain Gelly, and Bernhard Schoelkopf. Wasserstein autoencoders. In *Proc. International Conference on Learning Representation (ICLR)*, pp. 5885–5892, 2018.

Aäron van den Oord, Oriol Vinyals, and Koray Kavukcuoglu. Neural discrete representation learning. In *Proc. Advances in Neural Information Processing Systems (NeurIPS)*, pp. 6306–6315, 2017.

Jiacheng Xu and Greg Durrett. Spherical latent spaces for stable variational autoencoders. 2018.

Shengjia Zhao, Jiaming Song, and Stefano Ermon. InfoVAE: Balancing learning and inference in variational autoencoders. In *Proc. AAAI Conference on Artificial Intelligence (AAAI)*, pp. 5885–5892, 2019.

A   PROOF OF THEOREM 2

Let $\mathbf{x}$ be the input sample. We denote its corresponding latent space vector as $\mathbf{z}$ and the reconstructed sample as $\mathbf{x}'$. We have the following relation:

$$\mathcal{I}(\mathbf{x}; \mathbf{z}) \geq \mathcal{I}(\mathbf{x}; \mathbf{x}'), \tag{12}$$

which can be proved similarly to the proof of Lemma 5 in Appendix F. On the other hand, $\mathcal{I}(\mathbf{x}; \mathbf{z})$ can be evaluated by using the definition of the MI as

$$\begin{aligned}
\mathcal{I}(\mathbf{x}; \mathbf{z}) &= D_{\mathrm{KL}}(\tilde{p}_{\mathrm{data}}(x) q_\phi(\mathbf{z}|\mathbf{x}) \parallel \tilde{p}_{\mathrm{data}}(x) q_\phi(\mathbf{z})) \\
&= \mathbb{E}_{\tilde{p}_{\mathrm{data}}(x)} \mathbb{E}_{q_\phi(\mathbf{z}|\mathbf{x})} [\ln q_\phi(\mathbf{z}|\mathbf{x}) - \ln q_\phi(\mathbf{z})] \\
&= \mathbb{E}_{\tilde{p}_{\mathrm{data}}(x)} D_{\mathrm{KL}}(q_\phi(\mathbf{z}|\mathbf{x}) \parallel p(\mathbf{z})) - D_{\mathrm{KL}}(q_\phi(\mathbf{z}) \parallel p(\mathbf{z})) \\
&\leq \mathbb{E}_{\tilde{p}_{\mathrm{data}}(x)} D_{\mathrm{KL}}(q_\phi(\mathbf{z}|\mathbf{x}) \parallel p(\mathbf{z})),
\end{aligned} \tag{13}$$
$$\tag{14}$$

where $\mathcal{I}(\mathbf{x}; \mathbf{z})$, $D_{\mathrm{KL}}(q_\phi(\mathbf{z}|\mathbf{x}) \parallel p(\mathbf{z}))$ and $D_{\mathrm{KL}}(q_\phi(\mathbf{z}) \parallel p(\mathbf{z}))$ are all non-negative. Inequalities (12) and (14) lead to the proof.

B   LINEAR APPROXIMATION OF THE ELBO-BASED OBJECTIVE $\mathcal{J}_{\sigma_x^2}$

We start with parameterizing the encoder while following the assumption in (2). Given a sufficiently small perturbation with $p(\boldsymbol{\epsilon}_z) = \mathcal{N}(\mathbf{z}|\mathbf{0}, \mathrm{diag}(\boldsymbol{\sigma}_\phi^2(\mathbf{x})))$, the linear approximation of $\boldsymbol{\mu}_\theta(\cdot)$ at $\boldsymbol{\mu}_\phi(\mathbf{x})$ can be represented as

$$\boldsymbol{\mu}_\theta(\boldsymbol{\mu}_\phi(\mathbf{x}) + \boldsymbol{\epsilon}_z) = \boldsymbol{\mu}_\theta(\boldsymbol{\mu}_\phi(\mathbf{x})) + J_{\boldsymbol{\mu}_\theta}(\boldsymbol{\mu}_\phi(\mathbf{x}))\boldsymbol{\epsilon}_z, \tag{15}$$

where $J_{\boldsymbol{\mu}_\theta}(\boldsymbol{\mu}_\phi(\mathbf{x}))$ represents the Jacobian matrix of $\boldsymbol{\mu}_\theta(\mathbf{z})$ at $\mathbf{z} = \boldsymbol{\mu}_\phi(\mathbf{x})$. Substituting (15) into (3) leads to

$$\begin{aligned}
&\mathbb{E}_{q_\phi(\mathbf{z}|\mathbf{x})} [\|\mathbf{x} - \boldsymbol{\mu}_\theta(\mathbf{z})\|_2^2] \\
&= \mathbb{E}_{\mathcal{N}(\mathbf{z}|\mathbf{0}, \mathrm{diag}(\boldsymbol{\sigma}_\phi^2(\mathbf{x})))} \left[\|\mathbf{x} - (\boldsymbol{\mu}_\theta(\boldsymbol{\mu}_\phi(\mathbf{x})) + J_{\boldsymbol{\mu}_\theta}(\boldsymbol{\mu}_\phi(\mathbf{x}))\boldsymbol{\epsilon}_z)\|_2^2 \right] \\
&= \|\mathbf{x} - \boldsymbol{\mu}_\theta(\boldsymbol{\mu}_\phi(\mathbf{x}))\|_2^2 + \mathbb{E}_{\mathcal{N}(\mathbf{z}|\mathbf{0}, \mathrm{diag}(\boldsymbol{\sigma}_\phi^2(\mathbf{x})))} \left[\boldsymbol{\epsilon}_z^\top J_{\boldsymbol{\mu}_\theta}(\boldsymbol{\mu}_\phi(\mathbf{x}))^\top J_{\boldsymbol{\mu}_\theta}(\boldsymbol{\mu}_\phi(\mathbf{x}))\boldsymbol{\epsilon}_z \right] \\
&\quad + \underbrace{\mathbb{E}_{\mathcal{N}(\mathbf{z}|\mathbf{0}, \mathrm{diag}(\boldsymbol{\sigma}_\phi^2(\mathbf{x})))} \left[(\mathbf{x} - \boldsymbol{\mu}_\theta(\boldsymbol{\mu}_\phi(\mathbf{x})))^\top J_{\boldsymbol{\mu}_\theta}(\boldsymbol{\mu}_\phi(\mathbf{x}))\boldsymbol{\epsilon}_z \right]}_{=0},
\end{aligned} \tag{16}$$

where the last term is zero under the assumption that the perturbation is sufficiently small. The expectation in the second right-hand-side term can be evaluated as

$$\begin{aligned}
&\mathbb{E}_{\mathcal{N}(\mathbf{z}|\mathbf{0}, \mathrm{diag}(\boldsymbol{\sigma}_\phi^2(\mathbf{x})))} \left[\boldsymbol{\epsilon}_z^\top J_{\boldsymbol{\mu}_\theta}(\boldsymbol{\mu}_\phi(\mathbf{x}))^\top J_{\boldsymbol{\mu}_\theta}(\boldsymbol{\mu}_\phi(\mathbf{x}))\boldsymbol{\epsilon}_z \right] \\
&= \mathrm{trace} \left(\mathbb{E}_{\mathcal{N}(\mathbf{z}|\mathbf{0}, \mathrm{diag}(\boldsymbol{\sigma}_\phi^2(\mathbf{x})))} \left[\boldsymbol{\epsilon}_z \boldsymbol{\epsilon}_z^\top \right] J_{\boldsymbol{\mu}_\theta}(\boldsymbol{\mu}_\phi(\mathbf{x}))^\top J_{\boldsymbol{\mu}_\theta}(\boldsymbol{\mu}_\phi(\mathbf{x})) \right) \\
&= \mathrm{trace} \left(\mathrm{diag}(\boldsymbol{\sigma}_\phi^2(\mathbf{x})) J_{\boldsymbol{\mu}_\theta}(\boldsymbol{\mu}_\phi(\mathbf{x}))^\top J_{\boldsymbol{\mu}_\theta}(\boldsymbol{\mu}_\phi(\mathbf{x})) \right) \\
&= \sum_{i=1}^{d_x} \sum_{j=1}^{d_z} \sigma_{\phi,j}^2(\mathbf{x}) \left(\left. \frac{\partial \mu_{\theta,i}(\mathbf{z})}{\partial z_j} \right|_{z=\boldsymbol{\mu}_\phi(\mathbf{z})} \right)^2,
\end{aligned} \tag{17}$$

which can be interpreted as the gradient penalty for the decoder weighted by $\boldsymbol{\sigma}_\phi^2(\mathbf{x})$. By substituting the above result into (3), its linear approximation can be obtained as

$$\begin{aligned}
\tilde{\mathcal{J}}_{\sigma_x^2}(\theta, \phi) \approx \frac{1}{2\sigma_x^2} \mathbb{E}_{\tilde{p}_{\mathrm{data}}(\mathbf{x})} \Bigg[&\|\mathbf{x} - \boldsymbol{\mu}_\theta(\boldsymbol{\mu}_\phi(\mathbf{x}))\|_2^2 \\
&+ \sum_{i=1}^{d_x} \sum_{j=1}^{d_z} \sigma_{\phi,j}^2(\mathbf{x}) \left(\left. \frac{\partial \mu_{\theta,i}(\mathbf{z})}{\partial z_j} \right|_{\mathbf{z}=\boldsymbol{\mu}_\phi(\mathbf{x})} \right)^2 + 2\sigma_x^2 \|\boldsymbol{\mu}_\phi(\mathbf{x})\|_2^2 \Bigg].
\end{aligned} \tag{18}$$

In the case of the simplified parameterization described in Section 3, the second right-hand-side term in (18) can be further reduced to $\sigma_z^2 \|\nabla \boldsymbol{\mu}_\theta(\boldsymbol{\mu}_\phi(\mathbf{x}))\|_F^2$. In the simplified case, the perturbation

follows a multivariate i.i.d. Gaussian distribution, $\epsilon_z \sim \mathcal{N}(\mathbf{z}|\mathbf{0}, \sigma_z^2\mathbf{I})$. Under this assumption, we have

$$
\begin{aligned}
\mathbb{E}_{p(\epsilon_z)}\left[\epsilon_z^\top J_{\boldsymbol{\mu}_\theta}(\boldsymbol{\mu}_\phi(\mathbf{x}))^\top J_{\boldsymbol{\mu}_\theta}(\boldsymbol{\mu}_\phi(\mathbf{x}))\epsilon_z\right] &= \mathbb{E}_{p(\epsilon_z)}\left[\epsilon_z^\top \left(\sum_{i=1}^{d_z}\lambda_i\mathbf{u}_i(\mathbf{x})\mathbf{u}_i(\mathbf{x})^\top\right)\epsilon_z\right] \\
&= \sum_{i=1}^{d_z}\lambda_i\mathbf{u}_i(\mathbf{x})^\top\mathbb{E}_{p(\epsilon_z)}[\epsilon_z\epsilon_z^\top]\mathbf{u}_i(\mathbf{x}) \\
&= 2\sigma_z^2\sum_{i=1}^{d_z}\lambda_i,
\end{aligned} \tag{19}
$$

where λ_i is the ith eigenvalue of $J_{\boldsymbol{\mu}_\theta}(\boldsymbol{\mu}_\phi(\mathbf{x}))J_{\boldsymbol{\mu}_\theta}(\boldsymbol{\mu}_\phi(\mathbf{x}))^\top$, which is a symmetrical positive definite matrix, and the corresponding eigenvectors are $(\mathbf{u}_i(\mathbf{x}))_{i=1}^{d_z}$. Following the simplified assumption, the second right-hand-side term in (16) now becomes $\mathbb{E}_{\mathcal{N}(\mathbf{z}|\mathbf{0},\sigma_z^2\mathbf{I})}\left[\epsilon_z^\top J_{\boldsymbol{\mu}_\theta}(\boldsymbol{\mu}_\phi(\mathbf{x}))^\top J_{\boldsymbol{\mu}_\theta}(\boldsymbol{\mu}_\phi(\mathbf{x}))\epsilon_z\right]$. Combining (19) and the fact that $\sum_{i=1}^{d_z}\lambda_i = \text{trace}(J_{\boldsymbol{\mu}_\theta}(\boldsymbol{\mu}_\phi(\mathbf{x}))J_{\boldsymbol{\mu}_\theta}(\boldsymbol{\mu}_\phi(\mathbf{x}))^\top) = \|\nabla\boldsymbol{\mu}_\theta(\boldsymbol{\mu}_\phi(\mathbf{x}))\|_2^2$, we can finally obtain the following linear approximation for the simplified parameterization:

$$
\begin{aligned}
\mathbb{E}_{\mathcal{N}(\mathbf{z}|\mathbf{0},\sigma_z^2\mathbf{I})} &\left[\epsilon_z^\top J_{\boldsymbol{\mu}_\theta}(\boldsymbol{\mu}_\phi(\mathbf{x}))^\top J_{\boldsymbol{\mu}_\theta}(\boldsymbol{\mu}_\phi(\mathbf{x}))\epsilon_z\right] \\
&= \mathbb{E}_{\mathcal{N}(\mathbf{z}|\mathbf{0},\sigma_z^2\mathbf{I})}\left[\text{trace}\left(J_{\boldsymbol{\mu}_\theta}(\boldsymbol{\mu}_\phi(\mathbf{x}))^\top J_{\boldsymbol{\mu}_\theta}(\boldsymbol{\mu}_\phi(\mathbf{x}))\right)\right] \\
&= \sigma_z^2\sum_{i=1}^{d_x}\sum_{j=1}^{d_z}\left(\frac{\partial\mu_{\theta,i}(\mathbf{z})}{\partial z_j}\Bigg|_{\mathbf{z}=\boldsymbol{\mu}_\phi(\mathbf{z})}\right)^2 \\
&= \sigma_z^2\|\nabla\boldsymbol{\mu}_\theta(\boldsymbol{\mu}_\phi(\mathbf{x}))\|_F^2.
\end{aligned} \tag{20}
$$

C EXPECTED LOCAL SMOOTHNESS OF DECODER

Here, we describe the relation between the expected local smoothness $\mathbb{E}_{\tilde{p}_{\text{data}}(\mathbf{x})}[\|\nabla\boldsymbol{\mu}_\theta(\boldsymbol{\mu}_\phi(\mathbf{x}))\|_F^2]$ and the expected gap $\Delta^2(s_z^2)$. First, consider the relation

$$
\Delta^2(\mathbf{x}, \epsilon_z, \epsilon_z') := \|\boldsymbol{\mu}_\theta(\boldsymbol{\mu}_\phi(\mathbf{x}) + \epsilon_z) - \boldsymbol{\mu}_\theta(\boldsymbol{\mu}_\phi(\mathbf{x}) + \epsilon_z')\|_2^2 = K_\theta(\boldsymbol{\mu}_\phi(\mathbf{x}), \epsilon_z, \epsilon_z')^2\|\epsilon_z - \epsilon_z'\|_2^2, \tag{21}
$$

with the perturbation ϵ_z following the Gaussian distribution $\mathcal{N}(\epsilon_z|\mathbf{0}, s_z^2\mathbf{I})$. Applying the expectation operator to (21) leads to

$$
\begin{aligned}
\Delta^2(\mathbf{x}, \epsilon_z, \epsilon_z') &= \mathbb{E}_{p(\epsilon_z,\epsilon_z')}\left[K_\theta(\boldsymbol{\mu}_\phi(\mathbf{x}), \epsilon_z, \epsilon_z')^2\|\epsilon_z - \epsilon_z'\|_2^2\right] \tag{22}\\
&\leq \mathbb{E}_{p(\epsilon_z,\epsilon_z')}\left[K_\theta(\boldsymbol{\mu}_\phi(\mathbf{x}), \epsilon_z, \epsilon_z')^2\right]\mathbb{E}_{p(\epsilon_z,\epsilon_z')}\left[\|\epsilon_z - \epsilon_z'\|_2^2\right] \tag{23}\\
&=: 2K_\theta^2(\boldsymbol{\mu}_\phi(\mathbf{x}), s_z^2)d_z s_z^2, \tag{24}
\end{aligned}
$$

where $p(\epsilon_z, \epsilon_z') := \mathcal{N}(\epsilon_z|\mathbf{0}, s_z^2\mathbf{I})\mathcal{N}(\epsilon_z'|\mathbf{0}, s_z^2\mathbf{I})$, $\epsilon_z - \epsilon_z' \sim \mathcal{N}(\epsilon_z - \epsilon_z'|\mathbf{0}, 2s_z^2\mathbf{I})$ and $K_\theta^2(\boldsymbol{\mu}_\phi(\mathbf{x})) := \mathbb{E}_{p(\epsilon_z,\epsilon_z')}\left[K_\theta(\boldsymbol{\mu}_\phi(\mathbf{x}), \epsilon_z, \epsilon_z')^2\right]$. Note that in (23), we assume that $K_\theta^2(\boldsymbol{\mu}_\phi(\mathbf{x}))$ is independent of ϵ_z and ϵ_z'. Consider the case that the variance s_z^2 is sufficiently small to approximate $\boldsymbol{\mu}_\theta(\mathbf{z})$ linearly around $z = \boldsymbol{\mu}_\phi(\mathbf{x})$, which is perturbed with variance s_z^2. In such a case, $K_\theta(\boldsymbol{\mu}_\phi(\mathbf{x}), \epsilon_z, \epsilon_z')$ is independent of ϵ_z and ϵ_z', which fits the assumption in (23). Under this local linearity assumption, $K_\theta^2(\boldsymbol{\mu}_\phi(\mathbf{x}))$ is bounded as

$$
K_\theta^2(\boldsymbol{\mu}_\phi(\mathbf{x}), s_z^2) \leq K_\theta^2, \tag{25}
$$

where K_θ denotes the Lipschitz constant of the decoder.

Following the assumption, $K_\theta^2(\boldsymbol{\mu}_\phi(\mathbf{x}), s_z^2)$ can be formulated by invoking (15) as

$$
\begin{aligned}
K_\theta^2(\boldsymbol{\mu}_\phi(\mathbf{x}), s_z^2) &= \frac{\mathbb{E}_{p(\boldsymbol{\epsilon}_z, \boldsymbol{\epsilon}_z')}[\|\boldsymbol{\mu}_\theta(\boldsymbol{\mu}_\phi(\mathbf{x}) + \boldsymbol{\epsilon}_z) - \boldsymbol{\mu}_\theta(\boldsymbol{\mu}_\phi(\mathbf{x}) + \boldsymbol{\epsilon}_z')\|_2^2]}{\mathbb{E}_{p(\boldsymbol{\epsilon}_z, \boldsymbol{\epsilon}_z')}[\|\boldsymbol{\epsilon}_z - \boldsymbol{\epsilon}_z'\|_2^2]} \\
&= \frac{\mathbb{E}_{p(\boldsymbol{\epsilon}_z, \boldsymbol{\epsilon}_z')}[(\boldsymbol{\epsilon}_z - \boldsymbol{\epsilon}_z')^\top J_{\boldsymbol{\mu}_\theta}(\boldsymbol{\mu}_\phi(\mathbf{x}))^\top J_{\boldsymbol{\mu}_\theta}(\boldsymbol{\mu}_\phi(\mathbf{x}))(\boldsymbol{\epsilon}_z - \boldsymbol{\epsilon}_z')]}{2 d_z s_z^2} \\
&= \frac{\text{trace}\left(\mathbb{E}_{p(\boldsymbol{\epsilon}_z, \boldsymbol{\epsilon}_z')}[(\boldsymbol{\epsilon}_z - \boldsymbol{\epsilon}_z')(\boldsymbol{\epsilon}_z - \boldsymbol{\epsilon}_z')^\top] J_{\boldsymbol{\mu}_\theta}(\boldsymbol{\mu}_\phi(\mathbf{x}))^\top J_{\boldsymbol{\mu}_\theta}(\boldsymbol{\mu}_\phi(\mathbf{x}))\right)}{2 d_z s_z^2} \\
&= \frac{\text{trace}\left(J_{\boldsymbol{\mu}_\theta}(\boldsymbol{\mu}_\phi(\mathbf{x}))^\top J_{\boldsymbol{\mu}_\theta}(\boldsymbol{\mu}_\phi(\mathbf{x}))\right)}{d_z}.
\end{aligned}
\tag{26}
$$

Applying the expectation operator to (26) leads to

$$
\begin{aligned}
K_\theta^2(s_z^2) &:= \mathbb{E}_{\tilde{p}_{\text{data}}}\left[K_\theta^2(\boldsymbol{\mu}_\phi(\mathbf{x}), s_z^2)\right] \\
&= \frac{\mathbb{E}_{\tilde{p}_{\text{data}}(\mathbf{x})}\left[\text{trace}\left(J_{\boldsymbol{\mu}_\theta}(\boldsymbol{\mu}_\phi(\mathbf{x}))^\top J_{\boldsymbol{\mu}_\theta}(\boldsymbol{\mu}_\phi(\mathbf{x}))\right)\right]}{d_z} \\
&= \frac{\mathbb{E}_{\tilde{p}_{\text{data}}}\left[\|\nabla \boldsymbol{\mu}_\theta(\boldsymbol{\mu}_\phi(\mathbf{x}))\|_F^2\right]}{d_z}.
\end{aligned}
\tag{27}
$$

Finally, combining (24) and (27) yields the following connection between the expected gap and the expected local smoothness:

$$
\Delta^2(s_z^2) = 2 \mathbb{E}_{\tilde{p}_{\text{data}}}\left[\|\nabla \boldsymbol{\mu}_\theta(\boldsymbol{\mu}_\phi(\mathbf{x}))\|_F^2\right] s_z^2.
\tag{28}
$$

D EXPERIMENTAL DETAILS FOR SECTION 3.2

D.1 EXPERIMENTAL SETUP

In the experiment, the model is trained with the Adam optimizer with a learning rate of 10^{-3}. The dimension of the latent space is set to 8. We run 200 epochs with a minibatch size of 64 for all σ_x^2. We use the following DNN architectures for the encoder and decoder, respectively:

$$
\begin{aligned}
x \in \mathbb{R}^{28 \times 28} &\to \text{Conv}_{64} \to \text{ReLU} && \text{size of } (64, 14, 14) \\
&\to \text{Conv}_{128} \to \text{ReLU} \to \text{Reshape}(128, 7, 7) && \text{size of } (128, 7, 7) \\
&\to \text{Flatten} \to \text{FC}_{1024} \to \text{ReLU} \\
&\to \text{FC}_{16}, \\
z \in \mathbb{R}^{16} &\to \text{FC}_{1024} \to \text{ReLU} \\
&\to \text{FC}_{128 \times 7 \times 7} \to \text{ReLU} && \text{size of } (128, 7, 7) \\
&\to \text{ConvT}_{64} \to \text{ReLU} && \text{size of } (64, 14, 14) \\
&\to \text{ConvT}_1 \to \text{Sigmoid} && \text{size of } (1, 28, 28).
\end{aligned}
$$

Here, FC_k, Conv_k, ConvT_k and ReLU denote the fully connected layer mapping to $\mathbb{R}^k$, the convolutional layer mapping to k channels, the transpose convolutional layer mapping to k channels and the rectified linear units (ReLU), respectively. The 3-tuple $(\text{channels}, \text{height}, \text{width})$ in the right column represents the output shape of each layer. In all the Conv_k and ConvT_k layers, 4×4 convolutional filters are used with a common stride of $(2, 2)$.

Regarding the evaluation of criteria, MSE and KL are evaluated on the training set because the aim of the experiment is to validate the relation between σ_z^2 and the smoothness of the decoder. The upper bound of the MI is obtained by calculating

$$
-\mathbb{E}_{\tilde{p}_{\text{data}}(\mathbf{x})} \mathbb{E}_{q_{\phi, \sigma_z^2}(\mathbf{z}|\mathbf{x})}\left[\ln \mathbb{E}_{\tilde{p}_{\text{data}}(\mathbf{x}')} \exp\left(-\frac{1}{2\sigma_z^2}\|\mathbf{z} - \boldsymbol{\mu}_\phi(\mathbf{x}')\|_2^2\right)\right] - \frac{d_x}{2}
\tag{29}
$$

for each minibatch and then taking their mean, where the batch size is $10,000$ for all the evaluations.

Table 4: Evaluation of various criteria for different σ_z^2. These criteria are the expected value of $\|\mathbf{x}' - \mathbf{x}\|_2^2$ (MSE), KL divergence, the upper bound of MI $\mathcal{I}(\mathbf{x}', \mathbf{z})$, the expected gap (the perturbation variance s_z^2 is set to 10^{-2} and 10^{-3}) and expected local smoothness (ELS).

$\log \sigma_z^2$	MSE	KL	MI	Expected gap 10^{-2}	10^{-3}	ELS
1.0	**52.74**	**26.79**	**8.0e-3**	6.20e-6	6.15e-7	**3.81e-5**
0.9	**52.74**	**19.48**	**6.8e-3**	7.19e-6	7.11e-7	**4.42e-5**
0.8	22.96	134.83	8.5e+1	2.03e-2	2.03e-3	1.27e-1
0.7	20.50	139.09	1.0e+2	2.37e-2	2.37e-3	1.48e-1
0.6	19.30	132.61	1.2e+2	2.87e-2	2.87e-3	1.80e-1
0.5	17.38	132.05	1.7e+2	3.44e-2	3.44e-3	2.16e-1
0.4	15.91	128.96	1.9e+2	3.94e-2	3.94e-3	2.47e-1
0.3	14.63	125.97	2.3e+2	4.50e-2	4.50e-3	2.82e-1
0.2	13.50	122.07	2.8e+2	5.16e-2	5.16e-3	3.23e-1
0.1	12.40	118.89	3.1e+2	5.83e-2	5.81e-3	3.67e-1
0.0	11.71	112.50	3.6e+2	6.79e-2	6.80e-3	4.26e-1
−0.1	10.97	107.32	4.0e+2	7.53e-2	7.55e-3	4.74e-1
−0.2	10.23	103.87	4.2e+2	8.69e-2	8.70e-3	5.46e-1
−0.3	9.63	98.48	4.6e+2	9.84e-2	9.88e-3	6.18e-1
−0.4	9.12	93.86	5.2e+2	1.12e-1	1.12e-2	7.05e-1
−0.5	8.71	88.35	5.2e+2	1.25e-1	1.26e-2	7.88e-1
−0.6	8.26	83.68	5.9e+2	1.42e-1	1.43e-2	8.94e-1
−0.7	7.82	79.70	6.6e+2	1.62e-1	1.62e-2	1.02
−0.8	7.55	74.75	7.1e+2	1.80e-1	1.80e-2	1.13
−0.9	7.26	70.63	7.3e+2	2.04e-1	2.05e-2	1.29
−1.0	7.05	66.14	7.6e+2	2.28e-1	2.30e-2	1.45

D.2 SAMPLES OF GENERATED IMAGES AND T-SNE VISUALIZATION OF LATENT SPACES

Figure 1 shows several images decoded from $\boldsymbol{\mu}_\phi(\mathbf{x}) + \boldsymbol{\epsilon}_z$ with $\boldsymbol{\epsilon}_z \sim \mathcal{N}(\boldsymbol{\epsilon}_z|\mathbf{0}, s_z^2\mathbf{I})$ for the cases with $\sigma_x^2 = 1.0$ and 0.1. Posterior collapse can be observed from these blurry images decoded from the *stochastic encoding* case with $\sigma_x^2 = 1.0$. This is due to the removal of batch normalization, which makes $\sigma_x^2 = 1.0$ become an inappropriate choice. However, if σ_x^2 is determined or adapted appropriately such as by using the proposed method, posterior collapse will not happen. In the other settings, the tendency of how the image changes with the perturbation is similar, as shown in Table 1.

	Stochastic encoding		Deterministic encoding	
	$s_z^2 = 10^{-2}$	$s_z^2 = 10^{-3}$	$s_z^2 = 10^{-2}$	$s_z^2 = 10^{-3}$
$\sigma_x^2 = 1.0$				
$\sigma_x^2 = 0.1$				

Figure 1: Images in red boxes are the original images sampled from the MNIST dataset. The images in blue boxes are reconstructed by $\boldsymbol{\mu}_\theta(\boldsymbol{\mu}_\phi(\mathbf{x}))$. The other images are decoded from neighbor points of $\boldsymbol{\mu}_\phi(\mathbf{x})$, which are perturbed by $\boldsymbol{\epsilon}_z \sim \mathcal{N}(\boldsymbol{\epsilon}_z|\mathbf{0}, s_z^2\mathbf{I})$.

The latent spaces are also visualized via t-SNE (Maaten & Hinton, 2008) in Figure 2. The dots with different colors represent the latent vectors encoded from images of different labels (numbers), and the pink dots are the sampling points generated from the prior $p(\mathbf{z})$. As mentioned earlier, to observe the effect of σ_x^2 clearly, we remove batch normalization, which usually helps prevent posterior collapse to a certain extent. As a result, the latent space with $\sigma_x^2 = 1.0$ completely collapses and $q_\phi(z)$ approaches $p(z)$ as shown in Figures 1 and 2(a). In this case, both KL collapse and posterior collapse occur.

E FIXING THE POSTERIOR VARIANCE OF LATENT SPACE

From the previous sections, we know that σ_z^2 affects the smoothness via σ_x^2. However, it would be interesting to see what will happen if σ_z^2 is fixed while σ_x^2 is optimized. In this experiment, the variance parameter σ_z^2 is fixed while σ_x^2 is optimized with the AR-ELBO (9) under the parameterization in Section 3. The other settings remain the same as those in Section 3.2. We evaluate the numerical results for different σ_z^2 with the criteria listed in Section 3.2. According to Table 4, the tendencies of the expected gap and ELS show that a large σ_z^2 makes the decoder smoother, which is consistent with the discussion in Section 3.1. However, the tendency of the KL divergence is different from

Figure 2: Visualization of latent space via t-SNE. Pink dots are sampling points generated from the prior $p(\mathbf{z})$.

Figure 3: Visualization of latent space via t-SNE. Pink dots are sampling points generated from the prior $p(\mathbf{z})$.

that in Section 3.2. Although a larger σ_z^2 consistently leads to a smaller MI, and eventually the MI collapses to zero; the KL divergence still remains far from zero, which means that posterior collapse can happen without KL collapse. This phenomenon can be visually confirmed by observing the t-SNE plot in Figure 3. The cause of this phenomenon can be roughly reasoned from the linear approximated ELBO (4), in which σ_z^2 directly affects the gradient penalty and causes oversmoothness. It should be pointed out that the strength of L_2 regularization in (4) is gradually decreased with decreasing σ_x^2; therefore, it does not dominate the whole objective function. As a result, the mean of

the approximated posterior $q_\phi(z)$ is far from the mean of the prior $p(z)$ (which is $\mathbf{0}$), and therefore $D_{\mathrm{KL}}(q_\phi(z) \parallel p(z))$ in (13) does not diminish to zero.

F   PROOF OF THEOREM 3

According to Theorem 4 in Dai & Wipf (2019), we know that

$$\lim_{\sigma_x^2 \to 0} \mathbb{E}_{p_{\mathrm{data}}(\mathbf{x})} \mathbb{E}_{q_{\phi,\sigma_z^2}(\mathbf{z}|\mathbf{x})} \left[\|\mathbf{x} - \boldsymbol{\mu}_\theta(\mathbf{z})\|_2^2 \right] = 0, \tag{30}$$

which also leads to $\hat{\sigma}_x^2 \to 0$ ($\sigma_x^2 \to 0$). Here, $\hat{\sigma}_x^2$ is estimated through MLE and is given by

$$\hat{\sigma}_x^2 = \frac{1}{d_x} \mathbb{E}_{\tilde{p}_{\mathrm{data}}(\mathbf{x})} \mathbb{E}_{q_{\phi,\sigma_z^2}(\mathbf{z}|\mathbf{x})} \left[\|\mathbf{x} - \boldsymbol{\mu}_\theta(\mathbf{z})\|_2^2 \right]. \tag{31}$$

To prove Theorem 3, we need the following auxiliary theorem:

Theorem 4. *In the training stage of VAE, we have $\sigma_z^2 \to 0$ ($\hat{\sigma}_x^2 \to 0$).*

First, we state the two lemmas with proofs.

Lemma 5. *In a VAE, $\mathcal{I}(\mathbf{x}, \mathbf{x}') \leq \mathcal{I}(\mathbf{z}, \mathbf{z}_e)$ always holds, where $\mathbf{z}_e$ is the encoded latent variable $\mathbf{z}_e = \boldsymbol{\mu}_\phi(\mathbf{x})$ with $x \sim p_{data}(\mathbf{x})$.*

Proof. The data processing flow of the VAE is $\mathbf{x} \to \mathbf{z}_e \to \mathbf{z} \to \mathbf{x}'$; $\mathbf{z}_e = \boldsymbol{\mu}_\phi(\mathbf{x})$, $\mathbf{z} = \mathbf{z}_e + \boldsymbol{\epsilon}_z$, and $\mathbf{x}' = \boldsymbol{\mu}_\theta(\mathbf{z})$, where $\boldsymbol{\epsilon}_z \sim \mathcal{N}(\boldsymbol{\epsilon}_z|\mathbf{0}, \sigma_z^2\mathbf{I})$. The MI $\mathcal{I}(\mathbf{x}; \mathbf{z}, \mathbf{x}')$ can be represented as

$$\mathcal{I}(\mathbf{x}; \mathbf{z}, \mathbf{x}') = \mathcal{I}(\mathbf{x}; \mathbf{x}') + \mathcal{I}(\mathbf{x}; \mathbf{z}|\mathbf{x}') \tag{32}$$

$$= \mathcal{I}(\mathbf{x}; \mathbf{z}) + \mathcal{I}(\mathbf{x}; \mathbf{x}'|\mathbf{z}). \tag{33}$$

Since $\mathbf{x}$ and $\mathbf{x}'$ are conditionally independent on the given z, it follows that $\mathcal{I}(\mathbf{x}; \mathbf{x}'|\mathbf{z}) = 0$. From the non-negativity of MI, we have $\mathcal{I}(\mathbf{x}; \mathbf{z}) \geq \mathcal{I}(\mathbf{x}; \mathbf{x}')$. Repeating the same procedure for $\mathcal{I}(\mathbf{x}; \mathbf{z}_e, \mathbf{z})$ leads to the proof. □

Lemma 6. *The MI between $\mathbf{x}$ and $\mathbf{x}'$ diverges to positive infinity as $\sigma_x^2 \to 0$, where $\mathbf{x}'$ is obtained from $\mathbf{x} \sim p_{data}(\mathbf{x})$ as $\mathbf{x}' = \boldsymbol{\mu}_\theta(\boldsymbol{\mu}_\phi(\mathbf{x}) + \boldsymbol{\epsilon}_z)$.*

Proof. A lower bound of $\mathcal{I}(\mathbf{x}; \mathbf{x}')$ is

$$\mathcal{I}(\mathbf{x}; \mathbf{x}') = D_{\mathrm{KL}}\left(p_{\mathrm{data}}(\mathbf{x})p_{\theta,\phi}(\mathbf{x}'|\mathbf{x}) \parallel p_{\mathrm{data}}(\mathbf{x})p_{\theta,\phi}(\mathbf{x}')\right)$$

$$= \mathbb{E}_{p_{\mathrm{data}}(\mathbf{x})} \mathbb{E}_{p_{\theta,\phi}(\mathbf{x}'|\mathbf{x})} \left[\ln p_{\theta,\phi}(\mathbf{x}'|\mathbf{x}) - \ln p_{\theta,\phi}(\mathbf{x}')\right]$$

$$= \mathcal{H}\left[p_{\theta,\phi}(\mathbf{x}')\right] - \mathbb{E}_{p_{\mathrm{data}}(\mathbf{x})} \mathcal{H}\left[p_{\theta,\phi}(\mathbf{x}'|\mathbf{x})\right]$$

$$\geq \mathcal{H}\left[p_{\theta,\phi}(\mathbf{x}')\right] - \mathbb{E}_{p_{\mathrm{data}}(\mathbf{x})} H(\hat{\sigma}_x^2\mathbf{I}), \tag{34}$$

where $p_{\theta,\phi}(\mathbf{x}'|\mathbf{x}) := \mathbb{E}_{q_\phi(\mathbf{z}|\mathbf{x})}[p_\theta(\mathbf{x}'|\mathbf{z})]$ and $p_{\theta,\phi}(\mathbf{x}') := \mathbb{E}_{p_{\mathrm{data}}(\mathbf{x})} \mathbb{E}_{q_\phi(\mathbf{z}|\mathbf{x})}[p_\theta(\mathbf{x}'|\mathbf{z})]$. Here, we denote the differential entropy of the Gaussian with variance $\hat{\sigma}_x^2\mathbf{I}$ as

$$H(\hat{\sigma}_x^2\mathbf{I}) := \frac{1}{2}\ln(2\pi e \hat{\sigma}_x^{2d_x}). \tag{35}$$

Since $\hat{\sigma}_x^2 \to 0$ as $\sigma_x^2 \to 0$, $\mathcal{H}[p_{\theta,\phi}(\mathbf{x}')] \to \mathcal{H}[p_{\mathrm{data}}(\mathbf{x})]$ and $H(\hat{\sigma}_x^2) \to -\infty$ in the inequality of (34). Therefore, $\mathcal{I}(\mathbf{x}; \mathbf{x}') \to \infty$ as $\sigma_x^2 \to 0$. □

Now we prove Theorem 3. The MI $\mathcal{I}(\mathbf{z}; \mathbf{z}_e)$ satisfies

$$\mathcal{I}(\mathbf{z}; \mathbf{z}_e) = D_{\mathrm{KL}}\left(q_\phi(\mathbf{z}_e)q_{\sigma_z^2}(\mathbf{z}|\mathbf{z}_e) \parallel q_\phi(\mathbf{z}_e)q_{\phi,\sigma_z^2}(\mathbf{z})\right)$$

$$= \mathbb{E}_{q_\phi(\mathbf{z}_e)} \mathbb{E}_{q_{\sigma_z^2}(\mathbf{z}|\mathbf{z}_e)} \left[\ln q_{\sigma_z^2}(\mathbf{z}|\mathbf{z}_e) - \ln q_{\phi,\sigma_z^2}(\mathbf{z})\right]$$

$$= \mathcal{H}\left[q_{\phi,\sigma_z^2}(\mathbf{z})\right] - \mathbb{E}_{q_\phi(\mathbf{z}_e)} \mathcal{H}\left[q_{\sigma_z^2}(\mathbf{z}|\mathbf{z}_e)\right]$$

$$\leq H(\boldsymbol{\Sigma}_{\phi,\sigma_z^2}) - H(\sigma_z^2\mathbf{I})$$

$$= \frac{d_z}{2}\ln\left(\frac{\det(\boldsymbol{\Sigma}_{\phi,\sigma_z^2})}{\sigma_z^2}\right), \tag{36}$$

where $\boldsymbol{\Sigma}_{\phi,\sigma_z^2}$ denotes the variance of $q_{\phi,\sigma_z^2}(\mathbf{z})$. Invoking Lemma 5 and (36) leads to

$$\mathcal{I}(\mathbf{x};\mathbf{x}') \leq \frac{d_z}{2} \ln\left(\frac{\det(\boldsymbol{\Sigma}_{\phi,\sigma_z^2})}{\sigma_z^2}\right). \tag{37}$$

Now, consider $\sigma_z^2 \nrightarrow 0$ as $\mathcal{L} \to 0$. According to Lemma 6, it follows that $\det(\boldsymbol{\Sigma}_{\phi,\sigma_z^2}) \to +\infty$, which contradicts the fact that $q_{\phi,\sigma_z^2}(\mathbf{z}) \to p(\mathbf{z})$. Thus, we must have $\sigma_z^2 \to 0$ as σ_x^2 converges to zero.

G   DERIVATION OF PROPOSED OBJECTIVES

Here, we derive the objectives listed in Table 2. Consider an arbitrary $\boldsymbol{\Sigma}_x$ without any condition. The MLE of $\boldsymbol{\Sigma}_x$, $\hat{\boldsymbol{\Sigma}}_x$, can be obtained by

$$\hat{\boldsymbol{\Sigma}}_x = \mathbb{E}_{\tilde{p}_{\text{data}}(\mathbf{x})}\mathbb{E}_{q_\phi(\mathbf{z}|\mathbf{x})}\left[(\mathbf{x}-\boldsymbol{\mu}_\theta(\mathbf{z}))(\mathbf{x}-\boldsymbol{\mu}_\theta(\mathbf{z}))^\top\right]. \tag{38}$$

From the partial derivative of $\tilde{\mathcal{J}}_{\text{rec}}(\theta,\phi,\boldsymbol{\Sigma}_x)$ w.r.t. $\boldsymbol{\Sigma}_x$, we have

$$\frac{\partial \tilde{\mathcal{J}}_{\text{rec}}(\theta,\phi,\boldsymbol{\Sigma}_x)}{\partial \boldsymbol{\Sigma}_x} = \frac{1}{2}\left(\mathbb{E}_{\tilde{p}_{\text{data}}}\mathbb{E}_{q_\phi(\mathbf{z}|\mathbf{x})}\left[(\mathbf{x}-\boldsymbol{\mu}_\theta(\mathbf{z}))(\mathbf{x}-\boldsymbol{\mu}_\theta(\mathbf{z}))^\top\right] + \boldsymbol{\Sigma}_x^{-1}\right). \tag{39}$$

The MLE of $\hat{\boldsymbol{\Sigma}}_x$ and the objectives for the different parameterizations are described in the following.

G.1   ISO-I

For Iso-I, the MLE of σ_x^2 can be given as

$$\hat{\sigma}_x^2 = \frac{1}{d_x}\mathbb{E}_{\tilde{p}_{\text{data}}(\mathbf{x})}\mathbb{E}_{q_\phi(\mathbf{z}|\mathbf{x})}\left[\|\mathbf{x}-\boldsymbol{\mu}_\theta(\mathbf{z})\|_2^2\right]. \tag{40}$$

Substituting (40) into (7) leads to

$$\begin{aligned}
\tilde{\mathcal{J}}_{\text{AR}}(\theta,\phi,\hat{\sigma}_x^2) &= \mathbb{E}_{\tilde{p}_{\text{data}}(\mathbf{x})}\left[\frac{1}{2\hat{\sigma}_x^2}\mathbb{E}_{q_\phi(\mathbf{z}|\mathbf{x})}[\|\mathbf{x}-\boldsymbol{\mu}_\theta(\mathbf{z})\|_2^2] + D_{\text{KL}}(q_\phi(\mathbf{z}|\mathbf{x}) \parallel p(\mathbf{z}))\right] + \frac{d_x}{2}\ln\hat{\sigma}_x^2 \\
&= \frac{d_x}{2} + \mathbb{E}_{\tilde{p}_{\text{data}}(\mathbf{x})}D_{\text{KL}}\left(q_\phi(\mathbf{z}|\mathbf{x}) \parallel p(\mathbf{z})\right) \\
&\quad + \frac{d_x}{2}\ln\mathbb{E}_{\tilde{p}_{\text{data}}(\mathbf{x})}\mathbb{E}_{q_\phi(\mathbf{z}|\mathbf{x})}\left[\|\mathbf{x}-\boldsymbol{\mu}_\theta(\mathbf{z})\|_2^2\right] - \frac{d_x}{2}\ln d_x,
\end{aligned} \tag{41}$$

where the first and fourth terms are constants and thus omitted in (9).

G.2   ISO-D

First, substitute $\boldsymbol{\Sigma}_x = \sigma_x^2(\mathbf{z})\mathbf{I}$ into (10b):

$$\tilde{\mathcal{J}}_{\text{rec}}(\theta,\phi,\boldsymbol{\Sigma}_x) = \mathbb{E}_{\tilde{p}_{\text{data}}(\mathbf{x})}\mathbb{E}_{q_\phi(\mathbf{z}|\mathbf{x})}\left[\frac{1}{2\sigma_x^2(\mathbf{z})}\|\mathbf{x}-\boldsymbol{\mu}_\theta(\mathbf{z})\|_2^2 + \frac{d_x}{2}\ln\sigma_x^2(\mathbf{z})\right]. \tag{42}$$

Also, we know that the MLE of $\sigma_x^2(\mathbf{z})$ is

$$\hat{\sigma}_x^2(\mathbf{z}) = \frac{1}{d_x}\|\mathbf{x}-\boldsymbol{\mu}_\theta(\mathbf{z})\|_2^2. \tag{43}$$

Substituting (43) into (42) leads to the reconstruction objective of Iso-D:

$$\begin{aligned}
\tilde{\mathcal{J}}_{\text{rec}}(\theta,\phi,\hat{\boldsymbol{\Sigma}}_x) &= \mathbb{E}_{\tilde{p}_{\text{data}}(\mathbf{x})}\mathbb{E}_{q_\phi(\mathbf{z}|\mathbf{x})}\left[\frac{1}{2\hat{\sigma}_x^2(\mathbf{z})}\|\mathbf{x}-\boldsymbol{\mu}_\theta(\mathbf{z})\|_2^2 + \frac{d_x}{2}\ln\hat{\sigma}_x^2(\mathbf{z})\right] \tag{44} \\
&= \frac{d_x}{2} + \frac{d_x}{2}\mathbb{E}_{\tilde{p}_{\text{data}}(\mathbf{x})}\mathbb{E}_{q_\phi(\mathbf{z}|\mathbf{x})}\left[\ln\|\mathbf{x}-\boldsymbol{\mu}_\theta(\mathbf{z})\|_2^2\right] - \frac{d_x}{2}\ln d_x. \tag{45}
\end{aligned}$$

G.3 DIAG-I

First, substitute $\mathbf{\Sigma}_x = \mathrm{diag}(\boldsymbol{\sigma}_x^2)$ into (10b):

$$\tilde{\mathcal{J}}_{\mathrm{rec}}(\theta, \phi, \mathbf{\Sigma}_x) = \mathbb{E}_{\tilde{p}_{\mathrm{data}}(\mathbf{x})} \left[\sum_{i=1}^{d_x} \frac{1}{2\sigma_{x,i}^2} \mathbb{E}_{q_\phi(\mathbf{z}|\mathbf{x})} \left[(x_i - \mu_{\theta,i}(\mathbf{z}))^2 \right] \right] + \sum_{i=1}^{d_x} \frac{1}{2} \ln \sigma_{x,i}^2. \tag{46}$$

Also, we know that the MLE of $\sigma_{x,i}^2$ is

$$\hat{\sigma}_{x,i}^2 = \mathbb{E}_{\tilde{p}_{\mathrm{data}}(\mathbf{x})} \mathbb{E}_{q_\phi(\mathbf{z}|\mathbf{x})} \left[(x_i - \mu_{\theta,i}(\mathbf{z}))^2 \right]. \tag{47}$$

Substituting (47) into (46) leads to the reconstruction objective for Diag-I:

$$\tilde{\mathcal{J}}_{\mathrm{rec}}(\theta, \phi, \hat{\mathbf{\Sigma}}_x) = \mathbb{E}_{\tilde{p}_{\mathrm{data}}(\mathbf{x})} \left[\sum_{i=1}^{d_x} \frac{1}{2\hat{\sigma}_{x,i}^2} \mathbb{E}_{q_\phi(\mathbf{z}|\mathbf{x})} \left[(x_i - \mu_{\theta,i}(\mathbf{z}))^2 \right] \right] + \sum_{i=1}^{d_x} \frac{1}{2} \ln \hat{\sigma}_{x,i}^2 \tag{48}$$

$$= \frac{d_x}{2} + \frac{1}{2} \sum_{i=1}^{d_x} \ln \mathbb{E}_{\tilde{p}_{\mathrm{data}}(\mathbf{x})} \mathbb{E}_{q_\phi(\mathbf{z}|\mathbf{x})} \left[(x_i - \mu_{\theta,i}(\mathbf{z}))^2 \right]. \tag{49}$$

G.4 DIAG-D

First, substitute $\mathbf{\Sigma}_x = \mathrm{diag}(\boldsymbol{\sigma}_x^2(\mathbf{z}))$ into (10b):

$$\tilde{\mathcal{J}}_{\mathrm{rec}}(\theta, \phi, \mathbf{\Sigma}_x) = \mathbb{E}_{\tilde{p}_{\mathrm{data}}(\mathbf{x})} \mathbb{E}_{q_\phi(\mathbf{z}|\mathbf{x})} \left[\sum_{i=1}^{d_x} \left(\frac{1}{2\sigma_{x,i}^2(\mathbf{z})} (x_i - \mu_{\theta,i}(\mathbf{z}))^2 + \frac{1}{2} \ln \sigma_{x,i}^2(\mathbf{z}) \right) \right]. \tag{50}$$

Also, we know that the MLE of $\sigma_{x,i}^2(\mathbf{z})$ is

$$\hat{\sigma}_{x,i}^2(\mathbf{z}) = (x_i - \mu_{\theta,i}(\mathbf{z}))^2. \tag{51}$$

Substituting (51) into (50) leads to the reconstruction objective for Diag-D:

$$\tilde{\mathcal{J}}_{\mathrm{rec}}(\theta, \phi, \hat{\mathbf{\Sigma}}_x) = \mathbb{E}_{\tilde{p}_{\mathrm{data}}(\mathbf{x})} \mathbb{E}_{q_\phi(\mathbf{z}|\mathbf{x})} \left[\sum_{i=1}^{d_x} \left(\frac{1}{2\hat{\sigma}_{x,i}^2(\mathbf{z})} (x_i - \mu_{\theta,i}(\mathbf{z}))^2 + \frac{1}{2} \ln \hat{\sigma}_{x,i}^2(\mathbf{z}) \right) \right] \tag{52}$$

$$= \frac{d_x}{2} + \frac{1}{2} \sum_{i=1}^{d_x} \mathbb{E}_{\tilde{p}_{\mathrm{data}}(\mathbf{x})} \mathbb{E}_{q_\phi(\mathbf{z}|\mathbf{x})} \left[\ln (x_i - \mu_{\theta,i}(\mathbf{z}))^2 \right]. \tag{53}$$

H DERIVATION OF (11)

The KL divergence terms of (1) can be represented as

$$\mathbb{E}_{p_{\mathrm{data}}(\mathbf{x})} D_{\mathrm{KL}}(q_\phi(\mathbf{z}|\mathbf{x}) \parallel p_\theta(\mathbf{z}|\mathbf{x})) = \mathbb{E}_{p_{\mathrm{data}}(\mathbf{x})q_\phi(\mathbf{z}|\mathbf{x})} [\ln q_\phi(\mathbf{z}|\mathbf{x}) - \ln p_\theta(\mathbf{z}|\mathbf{x})] \tag{54}$$

$$= \mathbb{E}_{p_{\mathrm{data}}(\mathbf{x})q_\phi(\mathbf{z}|\mathbf{x})} \left[\ln \frac{p_{\mathrm{data}}(\mathbf{x})q_\phi(\mathbf{z}|\mathbf{x})}{p(\mathbf{z})p_\theta(\mathbf{x}|\mathbf{z})} \right]$$

and

$$\mathbb{E}_{p_{\mathrm{data}}(\mathbf{x})q_\phi(\mathbf{z}|\mathbf{x})} [\ln q_\phi(\mathbf{z}) - \ln p(\mathbf{z})] = D_{\mathrm{KL}}(q_\phi(\mathbf{z}) \parallel p(\mathbf{z})). \tag{55}$$

Substituting the two equations above into (1), then $\mathcal{L}$ can be reformulated into (11).

I RELATED WORKS

To the best of our knowledge, Lucas et al. (2019) were among the first to suggest that posterior collapse may be caused by a sub-optimal σ_x^2. In the past, one of the common approaches for dealing with posterior collapse was to anneal the weight of the KL term in the ELBO. The first such attempt

was KL annealing (Bowman et al., 2015). Bowman et al. (2015) introduced a weighting coefficient on the KL term in the cost function during training. The weighting scheduling is determined in advance, e.g., the weight increases monotonically (Bowman et al., 2015; Sønderby et al., 2016) or changes cyclically (Fu et al., 2019) as the training progresses. Shao et al. (2020) proposed ControlVAE, which combined control theory with the VAE, and applied PI/PID control to determine the weight on the KL term. Although applying control theory to the weighting of the KL term makes it possible to reflect the status of the optimization, ControlVAE needs extra hyperparameters to be tuned in advance. On the other hand, our method prevents oversmoothness of the decoder, which can be interpreted as automatic KL annealing that estimates σ_x^2 through MLE without the need of tuning an extra hyperparameter.

Ghosh et al. (2020) interpreted the stochastic autoencoder with the reparameterization trick as noise injection process and proposed replacing such a mechanism with an explicit regularized autoencoder (RAE). RAE regularizes its decoder in several ways: L_2 regularization, a gradient penalty (Gulrajani et al., 2017) and spectral normalization (Miyato et al., 2018). As discussed in Section 3.1, if σ_z^2 is sufficiently small, the ELBO can also be approximately represented as a sum of three losses (4), which correspond to the terms included in the basic RAE objective function. The approximated objective function (4) can be obtained when RAE with a gradient penalty (RAE-GP) is used and tuned appropriately.

Dai & Wipf (2019) optimized σ_x^2 using an optimizer, which is the most similar approach to our Iso-I model in that (7) is used as an objective function. Our proposed method provides simplified objective functions that enable the variance parameter to be optimized automatically and guarantee that σ_x^2 decreases as the reconstruction loss decreases, enabling the gradient penalty to be gradually weakened. In a follow-up work, Dai et al. (2020) found that, in addition to the ELBO, small nonlinear perturbation introduced in the network architecture can result in extra sub-optimal local minima.

Comparing our work with these works showed that the proposed AR-ELBO and its variations are also capable of regularizing the Gaussian VAE via weighting of the gradient penalty. In the standard parameterization such as (2), the second term in (4) is a weighted gradient penalty, which makes it possible to regularize each dimension of the latent space differently according to the property of the input data. In addition, the combination of the proposed objective functions together with standard Gaussian VAE allows implicit gradient regularization on the decoder with lower computational cost than that of explicitly adding the gradient penalty to the objective function, such as in RAE.

J   DETAILS OF EXPERIMENTAL SETUP IN SECTION 5

In this experiment, the Adam optimizer (Kingma & Ba, 2015) is used and the maximum number of epochs is set to 100 for MNIST and 70 for CelebA. The learning rates are 0.001 for MNIST and 0.0002 for CelebA. A minibatch size of 64 is used. All the FID[2] values are evaluated with 10, 000 generated samples.

For the posterior estimation by the second-stage VAE, we adopt the same networks for the encoder and decoder as those in Dai & Wipf (2019). For GMM fitting, we use the same settings as those in Ghosh et al. (2020). Experimental details including the network architectures for each dataset are described in the following.

---

[2]We used the PyTorch version of the FID implementation from https://github.com/mseitzer/pytorch-fid for all the models. However, the result may slightly differ from that obtained with the TensorFlow implementation https://github.com/bioinf-jku/TTUR.

J.1 MNIST

We construct the encoder and decoder for the MNIST dataset using the architecture in Chen et al. (2016). The encoder is constructed as

$$
\begin{aligned}
x \in \mathbb{R}^{28 \times 28} &\to \text{Conv}_{64} \to \text{ReLU} &&\text{size of } (64, 14, 14) \\
&\to \text{Conv}_{128} \to \text{ReLU} \to \text{Reshape}(128, 7, 7) &&\text{size of } (128, 7, 7) \\
&\to \text{Flatten} \to \text{FC}_{1024} \to \text{BatchNorm} \to \text{ReLU} \\
&\to \text{FC}_{16 \times 2}.
\end{aligned}
$$

The decoder is constructed as

$$
\begin{aligned}
z \in \mathbb{R}^{16} &\to \text{FC}_{1024} \to \text{BatchNorm} \to \text{ReLU} \\
&\to \text{FC}_{128 \times 7 \times 7} \to \text{BatchNorm} \to \text{ReLU} &&\text{size of } (128, 7, 7) \\
&\to \text{ConvT}_{64} \to \text{BatchNorm} \to \text{ReLU} &&\text{size of } (64, 14, 14) \\
&\to \text{ConvT}_{1} \to \text{Sigmoid} &&\text{size of } (1, 28, 28).
\end{aligned}
$$

In all the Conv_k layers and all the ConvT_k layers except for the last, 5×5 convolutional filters with stride $(2, 2)$ are used. The difference between this architecture and those used in Appendix D.1 is whether batch normalization is applied or not. Although in the original work of Chen et al. (2016), the discriminator used leaky ReLU (lReLU), we adopt ReLU for the encoder part, which improves the performance for all the models evenly.

J.2 CELEBA

The CelebA images are preprocessed with center cropping of 140×140, then resized to 64×64 as described in Tolstikhin et al. (2018) and Ghosh et al. (2020). It should be noted that the size of cropping differs among the previous works, and it markedly affects the FID score. We choose the above cropping size as is the largest among the related works and seems to be the most difficult case for image generation. Moreover, Tolstikhin et al. (2018) and Ghosh et al. (2020) also used this cropping size. Similarly to in the previous section, the encoder and decoder are constructed on the basis of the discriminator and generator for CelebA used in Chen et al. (2016). The encoder is constructed as

$$
\begin{aligned}
x \in \mathbb{R}^{64 \times 64} &\to \text{Conv}_{128} \to \text{ReLU} &&\text{size of } (128, 32, 32) \\
&\to \text{Conv}_{256} \to \text{BatchNorm} \to \text{ReLU} &&\text{size of } (256, 16, 16) \\
&\to \text{Conv}_{512} \to \text{BatchNorm} \to \text{ReLU} &&\text{size of } (512, 8, 8) \\
&\to \text{Conv}_{1024} \to \text{BatchNorm} \to \text{ReLU} &&\text{size of } (1024, 4, 4) \\
&\to \text{Flatten} \to \text{FC}_{64 \times 2}.
\end{aligned}
$$

The decoder is constructed as

$$
\begin{aligned}
z \in \mathbb{R}^{64} &\to \text{FC}_{8 \times 8 \times 1024} \\
&\to \text{ConvT}_{512} \to \text{ReLU} &&\text{size of } (512, 16, 16) \\
&\to \text{ConvT}_{256} \to \text{BatchNorm} \to \text{ReLU} &&\text{size of } (256, 32, 32) \\
&\to \text{ConvT}_{128} \to \text{BatchNorm} \to \text{ReLU} &&\text{size of } (128, 64, 64) \\
&\to \text{ConvT}_{3} &&\text{size of } (3, 64, 64).
\end{aligned}
$$

In all the Conv_k layers and all the ConvT_k layers except for the last, 5×5 convolutional filters with stride $(2, 2)$ are used. We use ReLU instead of leaky ReLU due to the performance consideration described in the previous subsection. To fit the size of the input images in our experiment, one extra convolutional layer is added for the encoder and the channel size is twice as large as that in Chen et al. (2016),

K EXAMPLES OF RECONSTRUCTED AND GENERATED IMAGES IN SECTION 5

We show examples of reconstructed images and images generated by sampling the learned approximated posterior from the proposed method and other works in Figures 4 and 5.

Figure 4: Reconstructed images and examples of images generated from the prior and the estimated posterior on MNIST. "GT" stands for ground truth.

Figure 5: Reconstructed images and examples of images generated from the prior and the estimated posterior on CelebA.