Safe Nonlinear Control Using Robust Neural Lyapunov-Barrier Functions

Keywords: Certified control, learning for control

Abstract: Safety and stability are common requirements for robotic control systems; however, designing safe, stable controllers remains difficult for nonlinear and uncertain models. We develop a model-based learning approach to synthesize robust feedback controllers with safety and stability guarantees. We take inspiration from robust convex optimization and Lyapunov theory to define robust control Lyapunov barrier functions that generalize despite model uncertainty. We demonstrate our approach in simulation on problems including car trajectory tracking, nonlinear control with obstacle avoidance, satellite rendezvous with safety constraints, and flight control with a learned ground effect model. Simulation results show that our approach yields controllers that match or exceed the capabilities of robust MPC while reducing computational costs by an order of magnitude.

1 Introduction

Robot control systems are challenging to design, not least because of the problems of *task complexity* and *model uncertainty*. Robotics control problems like those in Fig. 1 often involve both safety and stability requirements, where the controller must drive the system towards a goal state while avoiding unsafe regions. Complicating matters, the model used to design the controller is seldom a perfect representation of the physical plant, and so controllers must account for uncertainty in any parameters (e.g. mass, friction, or unmodeled effects) that vary between the engineering model and true plant. Automatically synthesizing safe, stable, and robust controllers for nonlinear reach-avoid tasks is a long-standing open problem in controls. In this paper, we address this problem with a novel

Figure 1: Safe control problems considered in Section 6.

approach to robust model-based learning. Our work presents a unified framework for handling both model uncertainty and complex safety and stability specifications.

Over the years, several approaches have been proposed to solve this problem. In one view, reach-avoid can be treated as an optimal control problem and solved using model predictive control (MPC) schemes and their robust variants. Robust MPC promises a method for general-purpose controller synthesis, finding an optimal control signal given only a model of the system and a specification of the task. However, there are a number of recognized disadvantages of robust MPC. First, there are currently no techniques for guaranteeing the safety, stability, or recursive feasibility of robust MPC beyond the linear case [1]. Second, many sources of model uncertainty (e.g. mass or friction) are multiplicative in the dynamics, but robust MPC algorithms are typically limited to additive uncertainty [1, 2]. Finally, MPC is computationally expensive, making it difficult to achieve high control frequencies in practice [3].

An alternative method for synthesizing safe, stable controllers comes from Lyapunov theory, through the use of control Lyapunov and control barrier functions (resp., CLFs and CBFs, [4]) — certificates that prove the stability and safety of a control system, respectively. CLFs and CBFs are similar to

standard Lyapunov and barrier functions, but they can be used to synthesize a controller rather than just verifying the performance of a closed-loop system. Unfortunately, CLF and CBF certificates are very difficult construct in general, particularly for systems with nonlinear dynamics [5].

The most recent set of methods promising general-purpose controller synthesis come from the field of learning for control; for instance, using reinforcement learning [6, 7] or supervised learning [8, 9, 10, 11]. However, the introduction of learning-enabled components into safety-critical control tasks raises questions about soundness, robustness, and generalization. Some learning-based control techniques incorporate certificates such as Lyapunov functions [8], barrier functions [12, 10, 13], and contraction metrics [9, 11] to prove the soundness of learned controllers. Unfortunately, these certificates' guarantees are sensitive to uncertainties in the underlying model. In particular, if the model used during training differs from that encountered during deployment, then guarantees on safety and stability may no longer hold.

1.1 Contributions

Our main contribution is a learning-based framework for synthesizing robust nonlinear feedback controllers from safety and stability specifications. This contribution has two parts. First, we provide a novel extension of control Lyapunov barrier functions to robust control, defining a robust control Lyapunov barrier function (robust CLBF). Second, we develop a model-based approach to learning robust CLBFs, which we use to derive a safe controller using techniques from robust convex optimization. Other methods for learning Lyapunov and barrier certificates exist, but a key advantage of our approach is that we learn certificates with explicit robustness guarantees, enabling generalization beyond the system parameters seen during training.

We demonstrate our approach on a range of challenging control problems, including trajectory tracking, nonlinear control with obstacle avoidance, flight control with a learned model of ground effect, and a satellite rendezvous problem with non-convex safety constraints, comparing our approach with robust MPC. In all of these experiments, we find that our method either matches or exceeds the performance of robust MPC while reducing computational cost at runtime by at least a factor of 10.

2 Related Work

This work builds on a rich history of certificate-based control theory, including classical Lyapunov functions as well as more recent approaches such as control Lyapunov functions (CLFs [14, 15]) and control barrier functions (CBFs [16]). The majority of classical certificate-based controllers rely on hand-designed certificates [17, 18], but these can be difficult to obtain for nonlinear or high-dimensional systems. Some automated techniques exist for synthesizing CLFs and CBFs; however, many of these techniques (such as finding a Lyapunov function as the solution of a partial differential equation) are computationally intractable for many practical applications [5]. Other automated synthesis techniques are based on convex optimization, particularly sum-of-squares programming (SOS, [19]), but are limited to systems with polynomial dynamics and do not scale favorably with the dimension of the system.

A promising line of work in this area is to use neural networks to learn certificate functions. These techniques range in complexity from verifying the stability of a given control system [20, 21] to simultaneously learning a control policy and certificate [9, 8, 10]. Most of these works do not explicitly consider robustness to model uncertainty, although contraction metrics may be used to certify robustness to bounded additive disturbance [9].

Most approaches to handling model uncertainty in the context of certificate-guided learning for control involve online adaptation. For example, [17, 22] assume that a CLF or CBF are given and learn the unmodeled residuals in the CLF and CBF derivatives. When combined with a QP-based CLF/CBF controller, this technique enables adaptation to model uncertainty but relies on a potentially unsafe exploration phase. Although safe adaptation strategies exist, the main drawback with these techniques is their reliance on a hand-designed CLF and CBF, which are non-trivial to synthesize for nonlinear systems.

Online optimization-based control techniques such as model-predictive control (MPC) are also relevant as a general-purpose control synthesis strategy. However, the computational complexity of MPC, and particularly robust MPC, is a widely-recognized issue, particularly when considering de-

ployment to resource-constrained robotic systems such as UAVs [1, 3]. We revisit the computational cost of robust MPC, particularly as compared with the cost of our proposed method, in Section 6. Some approaches apply learning to characterize uncertainty in system dynamics and augment a robust MPC scheme [23], but these methods do not fundamentally change the computational burden of MPC. Other methods rely on imitation learning to recreate an MPC-based policy online [24], but these methods can encounter difficulties in generalizing beyond the training dataset.

A number of techniques from classical nonlinear control also deserve mention, such as sliding mode and adaptive controllers. These methods do not directly support state constraints and so must be paired with a separate trajectory planning layer [25]. Another drawback is that these techniques require significant effort to manually derive appropriate feedback control laws, and we are primarily interested in automated techniques for controller synthesis.

3 Preliminaries and Background

We consider continuous-time, control-affine dynamical systems of the form $\dot{x} = f_\theta(x) + g_\theta(x)u$, where $x \in \mathcal{X} \subseteq \mathbb{R}^n$, $u \in \mathbb{R}^\ell$, and $f_\theta : \mathbb{R}^n \to \mathbb{R}^n$ and $g_\theta : \mathbb{R}^n \to \mathbb{R}^{n \times \ell}$ are smooth functions modeling control-affine nonlinear dynamics. We assume that f_θ and g_θ depend on model parameters $\theta \in \Theta \subseteq \mathbb{R}^r$ and are affine in those parameters for any fixed x. This assumption on the dynamics is not restrictive; it covers many physical systems with uncertainty in inertia, damping, or friction, and it includes bounded additive and multiplicative disturbance as a special case. We also assume that f_θ and g_θ are Lipschitz but make no further assumptions, allowing us to consider cases when components of f_θ and g_θ are learned from experimental data. For concision, we will use f and g (without subscript) to refer to the dynamics evaluated with nominal parameters $\theta_0 \in \Theta$. In this paper, we consider the following control synthesis problem:

Definition 1 (Robust Safe Control Problem). *Given a control-affine system with uncertain parameters $\theta \in \Theta$, a goal configuration x_{goal}, a set of unsafe states $\mathcal{X}_{\text{unsafe}} \subseteq \mathcal{X}$, and a set of safe states $\mathcal{X}_{\text{safe}} \subseteq \mathcal{X}$ (such that $\mathcal{X}_{\text{safe}} \cap \mathcal{X}_{\text{unsafe}} = \emptyset$ and $x_{\text{goal}} \in \mathcal{X}_{\text{safe}}$), find a control policy $u = \pi(x)$ such that all trajectories $x(t)$ satisfying $\dot{x} = f_\theta(x) + g_\theta(x)\pi(x)$ and $x(0) \in \mathcal{X}_{\text{safe}}$ have the following properties for any parameters θ:*

    1. Reachability of x_{goal} with tolerance δ: $\lim_{t \to \infty} \|x(t) - x_{\text{goal}}\| \leq \delta$

    2. Safety: $x(t_1) \in \mathcal{X}_{\text{safe}} \implies x(t_2) \notin \mathcal{X}_{\text{unsafe}} \ \forall \ t_2 \geq t_1$

Simply put, we wish to *reach* the goal x_{goal} while *avoiding* the unsafe states $\mathcal{X}_{\text{unsafe}}$. We use the notion of reachability instead of asymptotic stability to permit (small) steady-state error; in the following we will use "stable" as shorthand for reachability. Note that we do not require $\mathcal{X}_{\text{safe}} \cup \mathcal{X}_{\text{unsafe}} = \mathcal{X}$, as it will be made clear in the following discussion that we need a non-empty boundary layer $\mathcal{X} \setminus (\mathcal{X}_{\text{safe}} \cup \mathcal{X}_{\text{unsafe}})$ to allow for flexibility in finding a safety certificate.

Lyapunov theory provides tools that are naturally suited to reach-avoid problems: control Lyapunov functions (for stability) and control barrier functions (for safety [4]). To avoid issues arising from learning two separate certificates, we rely on a single, unifying certificate known as a control Lyapunov barrier function (CLBF). Our definition of CLBFs is related to those in [26] and [27] (differing from the formulation in [26] by a constant offset c, and differing from [27] where safety and reachability are proven using two separate CLBFs). We begin by providing a standard definition of a CLBF in the non-robust case, but in the next section we provide a novel, robust extension of CLBF theory. In the following, we denote $L_f V$ as the Lie derivative of V along f.

Definition 2 (CLBF). *A function $V : \mathcal{X} \to \mathbb{R}$ is a CLBF if, for some $c, \lambda > 0$,*

$$V(x_{\text{goal}}) = 0 \tag{1a}$$
$$V(x) > 0 \ \forall \ x \in \mathcal{X} \setminus x_{\text{goal}} \tag{1b}$$
$$V(x) \leq c \ \forall \ x \in \mathcal{X}_{\text{safe}} \tag{1c}$$
$$V(x) > c \ \forall \ x \in \mathcal{X}_{\text{unsafe}} \tag{1d}$$

$$\inf_u L_f V + L_g V u + \lambda V(x) \leq 0 \ \forall \ x \in \mathcal{X} \setminus x_{\text{goal}} \tag{1e}$$

Intuitively, we can think of a CLBF as a special case of a control Lyapunov function where the safe and unsafe regions are contained in sub- and super-level sets, respectively. If we define a set of

admissible controls $K(x) = \{u \mid L_f V + L_g V u + \lambda V \leq 0\}$, then we arrive at a theorem proving the stability and safety of any controller that outputs elements of this set (the proof is included in the supplementary material).

Theorem 1. *If $V(x)$ is a CLBF then any control policy $\pi(x) \in K(x) \; \forall \; x \in \mathcal{X}$ will be both safe and stable, in the sense of Definition 1.*

Based on these results, we can define a CLBF-based controller, analogous to the CLF/CBF-based controller in [17] but without the risk of conflicts between the CLF and CBF conditions, relying on the CLBF V and some nominal controller π_{nominal} (e.g. the LQR policy):

$$\pi_{\text{CLBF}}(x) = \arg\min_u \quad \frac{1}{2} \|u - \pi_{\text{nominal}}(x)\|^2 \qquad \text{(CLBF-QP)}$$

$$\text{s.t.} \quad L_f V + L_g V u + \lambda V \leq 0 \qquad (2)$$

It should be clear that $\pi_{CLBF}(x) \in K(x) \; \forall \; x \in \mathcal{X} \setminus x_{\text{goal}}$, so this controller will result in a system that is certifiably safe and stable (with the CLBF V acting as the certificate). The nominal control signal π_{nominal} is included to encourage smoothness in the solution $\pi_{\text{CLBF}}(x)$, particularly near the desired fixed point at x_{goal} where $\dot{V}$ becomes small.

CLBFs provide a single, unified certificate of safety and stability; however, some significant issues remain. In particular, how do we guarantee that a CLBF will generalize beyond the nominal parameters?

4 Robust CLBF Certificates for Safe Control

In this section, we extend the definition of CLBFs to provide explicit robustness guarantees, and we present a key theorem proving the soundness of robust CLBF-based control.

Definition 3 (Robust CLBF, rCLBF). *A function $V : \mathcal{X} \to \mathbb{R}$ is a robust CLBF for bounded parametric uncertainty $\theta \in \Theta$, where Θ is the convex hull of scenarios $\theta_1, \theta_2, \ldots, \theta_{n_s}$ if the standard CLBF conditions* (1a)–(1d) *hold, and $\forall \; x \in \mathcal{X} \setminus x_{\text{goal}}$ there exist $c, \lambda > 0$ such that*

$$\inf_u L_{f_{\theta_i}} V + L_{g_{\theta_i}} V u + \lambda V(x) \leq 0 \qquad \forall i = 1, \ldots, n_s \qquad (3a)$$

As in the non-robust case, we define the set of admissible controls for a robust CLBF, $K_r(x) = \left\{ u \mid L_{f_{\theta_i}} V + L_{g_{\theta_i}} V u + \lambda V \leq 0 \; \forall \; i = 0, \ldots, n_s \right\}$, and the corresponding QP-based controller, the soundness of which is given by Theorem 2:

$$\pi_{\text{rCLBF}} = \arg\min_u \|u - \pi_{\text{nominal}}\|^2 \qquad \text{(rCLBF-QP)}$$

$$\text{s.t.} \; L_{f_{\theta_i}} V + L_{g_{\theta_i}} V u + \lambda V \leq 0; \; i = 0, \ldots, n_s \qquad (4)$$

Theorem 2. *If $V(x)$ is a robust CLBF, then any control policy $\pi(x) \in K_r(x) \; \forall \; x \in \mathcal{X}$ will be both safe and stable, in the sense of Definition 1, when executed on a system f_θ, g_θ with uncertain parameters $\theta \in \Theta$ (where Θ is the convex hull of scenarios $\theta_0, \ldots, \theta_{n_s}$).*

Proof. See the supplementary materials. $\qquad \square$

This result demonstrates the soundness and robustness of an rCLBF-based controller, but does not provide a means to construct a valid rCLBF. In the next section, we will present an automated model-based learning approach to rCLBF synthesis, yielding a general framework for solving robust safe control problems even for systems with complex, nonlinear, or partially-learned dynamics.

5 Learning Robust CLBFs

A persistent challenge in using of certificate-based controllers is the difficulty of finding valid certificates, especially for systems with nonlinear dynamics and complex specifications of $\mathcal{X}_{\text{safe}}$ and $\mathcal{X}_{\text{unsafe}}$ (e.g. obstacle avoidance). Taking inspiration from recent advances in certificate-guided learning for control [8, 10], we employ a model-based supervised learning framework to synthesize

an rCLBF-based controller. The architecture of this controller is shown in Fig. 2 and is comprised of three main parts: the rCLBF V, a proof controller π_{NN}, and the QP-based controller (rCLBF-QP). We parameterize $V : \mathcal{X} \to \mathbb{R}$ and $\pi_{\mathrm{NN}} : \mathcal{X} \to \mathbb{R}^{\ell}$ as neural networks. These networks are trained offline, where π_{NN} is used to prove that the feasible set of (rCLBF-QP) is non-empty, then V is evaluated online to provide the parameters of (rCLBF-QP), which is solved to find the control input.

In the offline training stage, our primary goal is finding an rCLBF $V(x)$ such that the conditions of Definition 3 are satisfied. To ensure (1b), we define $V(x) = w^T(x)w(x) \geq 0$, where w is the activation vector of the last hidden layer of the V neural network. To train V such that conditions (1a), (1c), (1d), and (3a) are satisfied over the domain of interest, we sample N_{train} points uniformly at random from $\mathcal{X}$ to yield a population of training points x, then define the empirical loss:

Figure 2: An illustration of the learned rCLBF-QP control architecture.

$$\mathcal{L}_{\mathrm{rCLBF}} = V(x_{\mathrm{goal}})^2 + a_1 \frac{1}{N_{\mathrm{safe}}} \sum_{x \in \mathcal{X}_{\mathrm{safe}}} [\epsilon + V(x) - c]_+ + a_2 \frac{1}{N_{\mathrm{unsafe}}} \sum_{x \in \mathcal{X}_{\mathrm{unsafe}}} [\epsilon + c - V(x)]_+ \tag{5a}$$

$$+ \frac{a_3}{n_s N_{\mathrm{train}}} \sum_{i=0}^{n_s} \sum_{x} [\epsilon + L_{f_{\theta_i}} V(x) + L_{g_{\theta_i}} V(x) \pi_{\mathrm{NN}}(x) + \lambda V(x)]_+ \tag{5b}$$

where a_1–a_3 are positive tuning parameters, $\epsilon > 0$ is a small parameter (typically 0.01) that allows us to encourage strict inequality satisfaction and enables generalization claims, N_{safe} and N_{unsafe} are the number of points in the training sample in $\mathcal{X}_{\mathrm{safe}}$ and $\mathcal{X}_{\mathrm{unsafe}}$, respectively, and $[\circ]_+ = \max(\circ, 0)$ is the ReLU function. The terms in this empirical loss are directly linked to conditions (1a), (1c), (1d), and (3a) such that each term is zero if the corresponding condition is satisfied at all N_{train} training points. For example, the final term in this loss (5b) is designed to encourage satisfaction of the robust CLBF decrease condition (3a).

Once defined, this loss is optimized using stochastic gradient descent, alternating epochs between training the V and u_{NN} networks. During training, we rely on π_{NN} to compute the time derivative of $V(x)$ in (5b). To provide a training signal for π_{NN}, we define an additional loss $\mathcal{L}_{\pi} = \|\pi_{\mathrm{NN}} - \pi_{\mathrm{nominal}}\|^2$, where π_{nominal} is a nominal controller (e.g. a policy derived from an LQR approximation). The parameters of V and π_{NN} are optimized using the combined loss $\mathcal{L} = \mathcal{L}_{\mathrm{rCLBF}} + (10^{-5})\mathcal{L}_{\pi}$. The small weight applied to $\mathcal{L}_{\pi}$ ensures that the training process prioritizes satisfying the CLBF conditions.

An important detail of our control architecture is that the learned control policy π_{NN} is used primarily to demonstrate that the feasible set of (rCLBF-QP) is non-empty. We are not required to use π_{NN} at execution time; we can choose any control policy from the admissible set $K_r(x)$. In the online stage, we rely on an optimization-based controller (rCLBF-QP), which solves a small quadratic program with n_s constraints and ℓ variables (one for each element of u). To ensure that this QP is always feasible at execution, we permit a relaxation of the CLBF constraints (4) and penalize relaxation with a large coefficient in the objective.

Once trained, V can be verified using neural-network verification tools [28], sampling [29], or a generalization error bound [10]. More details on potential verification strategies are provided in the supplementary materials, along with a comprehensive discussion of training strategies and implementation.

6 Experiments

To evaluate the performance of our learned rCLBF-QP controller, we compare against min-max robust model predictive control (as described in [2, 30]) on a series of simulated benchmark problems representing safe control problems with steadily increasing complexity. The first two concern trajectory tracking, where we wish to limit the tracking error despite uncertainty in the reference trajectory. The next two benchmarks are UAV stabiliziation problems that add additional safety

constraints and increasingly nonlinear dynamics. The last three benchmarks involve highly non-convex safety constraints. The first four benchmarks provide a solid basis for comparison between our proposed method and robust MPC, while the last three demonstrate the power of our approach to generalize to maintain safety even in complex environments.

In each experiment, we vary model parameters randomly in Θ, simulate the performance of the controller, and compute the rate of safety constraints violations and average error relative to the goal $\|x - x_{\text{goal}}\|$ across simulations. These data are reported along with average evaluation time for each controller in Table 1. To examine the effect of control frequency on MPC performance, we include results for two different control periods dt for all robust MPC experiments (we also report the horizon length N). In some cases we observed that the evaluation time for MPC exceeds the control period; in practice this would lead to the controller failing, but in our experiments we simply ran the simulation slower than real-time. Our robust MPC comparison supports only linear models with bounded additive disturbance; we linearize the systems about the goal point and select an additive disturbance to approximate the disturbance from uncertain model parameters. The following sections will present results from each benchmark separately, and more details are provided in the supplementary materials, including the dynamics and constraints used for each benchmark.

Table 1: Comparison of controller performance under parameter variation

Task	Algorithm	Safety rate	$\|x - x_{\text{goal}}\|$	Evaluation time (ms)
Car trajectory tracking[1]	rCLBF-QP	**0.7523**		**10.4**
Kinematic model	Robust MPC ($dt = 0.1\,\text{s}$, $N = 6$)	1.5148		194.6
($n = 5, \ell = 2, n_s = 2$)	Robust MPC ($dt = 0.25\,\text{s}$, $N = 6$)	12.4438		172.8
Car trajectory tracking[1]	rCLBF-QP	1.0340		**9.6**
Sideslip model	Robust MPC ($dt = 0.1\,\text{s}$, $N = 5$)	**0.1560**		336.5
($n = 7, \ell = 2, n_s = 2$)	Robust MPC ($dt = 0.25\,\text{s}$, $N = 5$)	18.1939		316.9
3D Quadrotor	rCLBF-QP	100%	0.4647	**9.7**
($n = 9, \ell = 4, n_s = 2$)	Robust MPC ($dt = 0.10\,\text{s}$, $N = 5$)	100%	**0.0980**	316.2
	Robust MPC ($dt = 0.25\,\text{s}$, $N = 5$)	100%	63.6303	291.0
Neural Lander	rCLBF-QP	100%	**0.1332**	**13.1**
($n = 6, \ell = 3, n_s = 1$)	Robust MPC ($dt = 0.10\,\text{s}$, $N = 5$)	100%	0.2086	247.2
	Robust MPC ($dt = 0.25\,\text{s}$, $N = 5$)	100%	0.3267	253.2
Segway	rCLBF-QP	**100%**	**0.0447**	**4.4**
($n = 4, \ell = 1, n_s = 4$)	Robust MPC ($dt = 0.10\,\text{s}$, $N = 5$)	21%	1.3977	214.8
	Robust MPC ($dt = 0.25\,\text{s}$, $N = 5$)	11%	1.9725	239.1
2D Quadrotor[2]	rCLBF-QP	**83%**		**18.6**
($n = 6, \ell = 2, n_s = 4$)	Robust MPC ($dt = 0.10\,\text{s}$, $N = 5$)	53%		276.9
	Robust MPC ($dt = 0.25\,\text{s}$, $N = 5$)	0%		265.2
Satellite Rendezvous	rCLBF-QP	**100%**	**0.1369**	**8.2**
($n = 4, \ell = 2$)	Robust MPC ($dt = 0.10\,\text{s}$, $N = 5$)	39%	6.3751	187.3
	Robust MPC ($dt = 0.25\,\text{s}$, $N = 5$)	15%	9.0592	197.4

[1] For car trajectory tracking, we compute maximum tracking error over the trajectory.

[2] For 2D quadrotor, we compute % of trials reaching the goal with tolerance $\delta = 0.3$ without collision.

Note: We also implemented SOS optimization to search for a CLBF and controller, but bilinear optimization (as in [31]) did not converge with maximum polynomial degree 10 and a Taylor expansion of the nonlinear dynamics.

6.1 Car trajectory tracking

First, we consider the problem of tracking an *a priori* unknown trajectory using two different car models. In the first model (the kinematic model), the vehicle state is $[x_e, y_e, \delta, v_e, \psi_e]$, representing error relative to the reference trajectory (δ is the steering angle). The second model (the sideslip model) has state $[x_e, y_e, \delta, v_e, \psi_e, \dot{\psi}_e, \beta]$, where β is the sideslip angle [32]. Both models have control inputs for the rate of change of δ and v_e. We assume that the reference trajectory is parameterized by an uncertain curvature: at any point the angular velocity of the reference point can vary on $[-1.5, 1.5]$. The goal point is zero error relative to the reference, and the safety constraint requires maintaining bounded tracking error.

The performance of our controller is shown in Fig. 3. We see that for both models, both our controller and robust MPC are able to track the reference trajectory. However, robust MPC was only successful when run at slower than real-time speeds (with a control period $dt = 0.1\,\text{s}$ roughly twice as fast as the average evaluation time). MPC became unstable when run at a slower control frequency $dt = 0.25\,\text{s}$. In contrast, our rCLBF-QP controller runs in real-time with a control period of $\approx 10\,\text{ms}$ on a laptop computer. This significant improvement in speed is due primarily to the reduction in the size of

256 (rCLBF-QP) relative to that of the QPs used by robust MPC. For example, for the sideslip model, our
257 controller solves a QP with 2 variables and 2 constraints, whereas the robust MPC controller solves
258 a QP with 35 variables and 23 constraints (after pre-compiling using YALMIP [30]). Because the
259 learned rCLBF encodes long-term safety and stability constraints into local constraints on the rCLBF
260 derivative, the rCLBF controller requires only a single-step horizon (as opposed to the receding
261 horizon used by MPC).

262 By comparing performance between these two models, we can discern an important feature of our
263 approach. Increasing the state dimension when moving between models does not substantially in-
264 crease the evaluation time for our controller (as it does for robust MPC), but it does degrade the
265 tracking performance, suggesting that the number of samples required to train the CLBF to any
266 given level of performance increases with the size of the state space.

Figure 3: Trajectory tracking on kinematic (left) and sideslip (right) vehicle models, with contour
plots of V. Blue shows the c-level set.

6.2 UAV stabilization

268 The next two examples involve stabilizing a quadrotor near the ground while maintaining a minimum
269 altitude. Relative to the previous examples, these benchmarks increase the complexity of the state
270 constraints, and we consider two models with increasingly challenging dynamics. The first model
271 (referred to as the "3D quadrotor") has 9 state dimensions for position, velocity, and orientation, with
272 control inputs for the net thrust and angular velocities [9]. The second model (the "neural lander")
273 has lower state dimension, including only translation and velocity, with linear acceleration as an
274 input, but its dynamics include a neural network trained to approximate the aerodynamic ground
275 effect, which is particularly relevant to this safe hovering task [33]. The mass of both models is
276 uncertain, but assumed to lie on $[1.0, 1.5]$ for the 3D quadrotor and $[1.47, 2.0]$ for the neural lander.

277 Fig. 4 shows simulation results on these two models. The trend from the previous benchmarks
278 continues: our controller maintains safety while reducing evaluation time by a factor of 10 relative
279 to MPC. Moreover, while the robust MPC method can achieve low error relative to the goal for the
280 the 3D quadrotor model, the nonlinear ground effect term prevents MPC from driving the neural
281 lander to the goal. In contrast, the rCLBF-QP method can consider the full nonlinear dynamics of
282 the system, including the learned ground effect, and achieves a much lower error relative to the goal.

Figure 4: Controller performance for the 3D quadrotor (left) and neural lander (right), with contour
plots of V. Blue shows the c-level set, white shows regions where condition (3a) is violated.

6.3 Navigation with non-convex safety constraints

284 The preceding benchmarks all include convex safety constraints that can be easily encoded in a
285 linear robust MPC scheme. Our next set of examples demonstrate the ability of our approach to

generalize to complex environments. These problems are commonly solved by combining planning and robust tracking control, so in our comparisons we use robust MPC to track a safe reference path through each environment. In contrast, our rCLBF-QP controller is not provided with a reference path and instead synthesizes a safe controller using only the model dynamics and (non-convex) safety constraints, which is a more challenging problem than the tracking problem as in Section 6.1. The three navigation problems we consider are: (a) controlling a Segway to duck under an obstacle to reach a goal [34], (b) navigating a 2D quadrotor model around obstacles [9], and (c) completing a satellite rendezvous that requires approaching the target satellite from a specific direction [35]. Simulated trajectories using both rCLBF-QP and robust MPC tracking are shown in Fig. 5. Note that in the segway and satellite examples, robust MPC fails to track the reference path, while the rCLBF controller successfully navigates the environment.

Figure 5: Navigation problems solved using our rCLBF-QP controller, compared with robust MPC. Clockwise from right: satellite rendezvous, planar quadrotor, and Segway.

7   Discussion

These results demonstrate two clear trends. First, the performance of our controller (in terms of both safety rate and error relative to the goal) is comparable to that of MPC when the MPC controller is stable. In some cases, our method achieves lower steady-state error due to its ability to consider highly nonlinear dynamics, as in the neural lander example. In other cases, the dynamics are well-approximated by the linearization and robust MPC achieves better steady-state error, but our approach still achieves a comparable safety rate. Second, we observe that the performance of the robust MPC algorithm is highly sensitive to the control frequency, and these controllers are only stable at control frequencies that cannot run in real-time on a laptop computer. This highlights one benefit of our method over traditional MPC, which trades increased offline computation for an order of magnitude reduction in evaluation time. In all cases, we find that our proposed algorithm finds a controller that satisfies the safety constraints despite variation in model parameters, validating our claim of presenting a framework for robust safe controller synthesis.

8   Conclusion

In this paper, we present a novel, learning-based approach to synthesizing robust nonlinear feedback controllers. Our approach is guided by a robust extension to the theory of control Lyapunov barrier functions that explicitly accounts for uncertainty in model parameters. Through experiments in simulation, we successfully demonstrate the performance of our approach on a range of challenging safe control problems. A number of interesting open questions remain, including scalable verification strategies for V, the sample complexity of this learning method, and the relative convergence rates of V, π_{NN}, and the QP controller derived from V, which we hope to revisit in future work. We also plan on exploring application to hardware systems, including considerations of delay and state estimation uncertainty.

References

[1] A. Bemporad and M. Morari. Robust model predictive control: A survey. In A. Garulli and A. Tesi, editors, *Robustness in identification and control*, pages 207–226, London, 1999. Springer London. ISBN 978-1-84628-538-7.

[2] J. Löfberg. Approximations of closed-loop mpc. In *Proceedings of the 42nd IEEE Conference on Decision and Control*, pages 1438–1442, Maui, Hawaii, 2003.

[3] W. S. Levine and S. V. Rakovic. *Handbook of Model Predictive Control*. Birkhäuser, Cham, 2019. ISBN 978-3-319-77488-6. doi:10.1007/978-3-319-77489-3. URL http://link.springer.com/10.1007/978-3-319-77489-3.

[4] A. D. Ames, X. Xu, J. W. Grizzle, and P. Tabuada. Control Barrier Function Based Quadratic Programs for Safety Critical Systems. *IEEE Transactions on Automatic Control*, 62(8):3861–3876, Aug 2017. ISSN 00189286. doi:10.1109/TAC.2016.2638961.

[5] P. Giesl and S. Hafstein. Review on computational methods for Lyapunov functions. *Discrete and Continuous Dynamical Systems - Series B*, 20(8):2291–2331, Oct 2015. ISSN 15313492. doi:10.3934/dcdsb.2015.20.2291. URL https://www.aimsciences.org/article/doi/10.3934/dcdsb.2015.20.2291.

[6] R. Cheng, G. Orosz, R. M. Murray, and J. W. Burdick. End-to-end safe reinforcement learning through barrier functions for safety-critical continuous control tasks. In *33rd AAAI Conference on Artificial Intelligence, AAAI 2019*, volume 33, pages 3387–3395. AAAI Press, Jul 2019. ISBN 9781577358091. doi:10.1609/aaai.v33i01.33013387. URL www.aaai.org.

[7] M. Han, L. Zhang, J. Wang, and W. Pan. Actor-Critic Reinforcement Learning for Control with Stability Guarantee. *IEEE Robotics and Automation Letters*, 5(4):6217–6224, Apr 2020. URL http://arxiv.org/abs/2004.14288.

[8] Y.-C. Chang, N. Roohi, and S. Gao. Neural Lyapunov Control. In *Advances in Neural Information Processing Systems*, volume 32, pages 3245–3254, 2019.

[9] D. Sun, S. Jha, and C. Fan. Learning Certified Control using Contraction Metric. In *Conference on Robot Learning*. Conference on Robot Learning, Nov 2020. URL http://arxiv.org/abs/2011.12569.

[10] Z. Qin, K. Zhang, Y. Chen, J. Chen, and C. Fan. Learning Safe Multi-Agent Control with Decentralized Neural Barrier Certificates. In *Conference on Learning Representations*. Conference on Learning Representations, Jan 2021. URL http://arxiv.org/abs/2101.05436.

[11] H. Tsukamoto and S.-J. Chung. Neural Contraction Metrics for Robust Estimation and Control: A Convex Optimization Approach. *IEEE Control Systems Letters*, 5(1):211–216, Jun 2020. doi:10.1109/LCSYS.2020.3001646. URL http://arxiv.org/abs/2006.04361http://dx.doi.org/10.1109/LCSYS.2020.3001646.

[12] S. Dean, A. J. Taylor, R. K. Cosner, B. Recht, and A. D. Ames. Guaranteeing Safety of Learned Perception Modules via Measurement-Robust Control Barrier Functions. In *Conference on Robot Learning*. Conference on Robot Learning, Oct 2020. URL http://arxiv.org/abs/2010.16001.

[13] A. Peruffo, D. Ahmed, and A. Abate. Automated and Formal Synthesis of Neural Barrier Certificates for Dynamical Models. *arXiv*, Jul 2020. URL http://arxiv.org/abs/2007.03251.

[14] Z. Artstein. Stabilization with relaxed controls. *Nonlinear Analysis*, 7(11):1163–1173, Jan 1983. ISSN 0362546X. doi:10.1016/0362-546X(83)90049-4.

[15] A. D. Ames, K. Galloway, K. Sreenath, and J. W. Grizzle. Rapidly exponentially stabilizing control lyapunov functions and hybrid zero dynamics. *IEEE Transactions on Automatic Control*, 59(4):876–891, 2014. ISSN 00189286. doi:10.1109/TAC.2014.2299335.

[16] A. D. Ames, S. Coogan, M. Egerstedt, G. Notomista, K. Sreenath, and P. Tabuada. Control barrier functions: Theory and applications. In *2019 18th European Control Conference, ECC 2019*, pages 3420–3431. Institute of Electrical and Electronics Engineers Inc., Jun 2019. ISBN 9783907144008. doi:10.23919/ECC.2019.8796030.

[17] J. Choi, F. Castañeda, C. J. Tomlin, and K. Sreenath. Reinforcement Learning for Safety-Critical Control under Model Uncertainty, using Control Lyapunov Functions and Control Barrier Functions. In *Robotics: Science and Systems*. Robotics: Science and Systems, Apr 2020. URL http://arxiv.org/abs/2004.07584.

[18] F. Castañeda, J. J. Choi, B. Zhang, C. J. Tomlin, and K. Sreenath. Gaussian Process-based Min-norm Stabilizing Controller for Control-Affine Systems with Uncertain Input Effects. *arXiv*, Nov 2020. URL http://arxiv.org/abs/2011.07183.

[19] A. A. Ahmadi and A. Majumdar. Some applications of polynomial optimization in operations research and real-time decision making. *Optimization Letters*, 10(4):709–729, Apr 2016. ISSN 18624480. doi:10.1007/s11590-015-0894-3. URL https://doi.org/10.1007/s11590-015-0894-3.

[20] A. Abate, D. Ahmed, M. Giacobbe, and A. Peruffo. Formal Synthesis of Lyapunov Neural Networks. *IEEE Control Systems Letters*, 5(3):773–778, Mar 2020. URL http://arxiv.org/abs/2003.08910.

[21] S. M. Richards, F. Berkenkamp, and A. Krause. The lyapunov neural network: Adaptive stability certification for safe learning of dynamical systems. In *Conference on Robot Learning*. arXiv, Aug 2018. URL http://arxiv.org/abs/1808.00924.

[22] A. J. Taylor, V. D. Dorobantu, H. M. Le, Y. Yue, and A. D. Ames. Episodic Learning with Control Lyapunov Functions for Uncertain Robotic Systems. In *IEEE International Conference on Intelligent Robots and Systems*, pages 6878–6884. Institute of Electrical and Electronics Engineers Inc., Mar 2019. doi:10.1109/IROS40897.2019.8967820. URL http://arxiv.org/abs/1903.01577http://dx.doi.org/10.1109/IROS40897.2019.8967820.

[23] D. Fan, A. Agha, and T. Evangelos. Deep Learning Tubes for Tube MPC. In *Robotics: Science and Systems*, 2020. URL https://roboticsconference.org/2020/program/papers/87.html.

[24] G. Kahn, T. Zhang, S. Levine, and P. Abbeel. PLATO: Policy Learning using Adaptive Trajectory Optimization. *Proceedings - IEEE International Conference on Robotics and Automation*, pages 3342–3349, mar 2016. URL http://arxiv.org/abs/1603.00622.

[25] J.-J. E. Slotine and W. Li. *Applied nonlinear control: an introduction*. Prentice-Hall, 1991.

[26] M. Z. Romdlony and B. Jayawardhana. Stabilization with guaranteed safety using Control Lyapunov-Barrier Function. In *Automatica*, volume 66, pages 39–47. Elsevier Ltd, Apr 2016. doi:10.1016/j.automatica.2015.12.011.

[27] W. Xiao, C. A. Belta, and C. G. Cassandras. High Order Control Lyapunov-Barrier Functions for Temporal Logic Specifications. In *2019 American Controls Conference, ACC 2019*, Feb 2021. URL https://arxiv.org/abs/2102.06787v1.

[28] C. Liu, T. Arnon, C. Lazarus, C. Strong, C. Barrett, and M. J. Kochenderfer. Algorithms for verifying deep neural networks. *Foundations and Trends in Optimization*, 4(3–4):244–404, 2021. doi:10.1561/2400000035. URL https://arxiv.org/abs/1903.06758.

[29] R. Bobiti and M. Lazar. Automated-Sampling-Based Stability Verification and DOA Estimation for Nonlinear Systems. *IEEE Transactions on Automatic Control*, 63(11):3659–3674, Nov 2018. ISSN 15582523. doi:10.1109/TAC.2018.2797196.

[30] J. Löfberg. Automatic robust convex programming. *Optimization methods and software*, 27(1):115–129, 2012.

[31] A. Majumdar, A. A. Ahmadi, and R. Tedrake. Control design along trajectories with sums of squares programming. In *Proceedings - IEEE International Conference on Robotics and Automation*, pages 4054–4061, 2013. ISBN 9781467356411. doi:10.1109/ICRA.2013.6631149.

[32] M. Althoff, M. Koschi, and S. Manzinger. Commonroad: Composable benchmarks for motion planning on roads. In *Proc. of the IEEE Intelligent Vehicles Symposium*, 2017. ISBN 9781509048045. doi:10.1109/ivs.2017.7995802.

[33] A. Liu, G. Shi, S.-J. Chung, A. Anandkumar, and Y. Yue. Robust regression for safe exploration in control, 2020.

[34] K. J. Åström and R. M. Murray. *Feedback systems: an introduction for scientists and engineers*. Princeton university press, 2021.

[35] C. Jewison and R. S. Erwin. A spacecraft benchmark problem for hybrid control and estimation. In *2016 IEEE 55th Conference on Decision and Control (CDC)*, pages 3300–3305. IEEE, 2016.

[36] A. Paszke, S. Gross, F. Massa, A. Lerer, J. Bradbury, G. Chanan, T. Killeen, Z. Lin, N. Gimelshein, L. Antiga, A. Desmaison, A. Kopf, E. Yang, Z. DeVito, M. Raison, A. Tejani, S. Chilamkurthy, B. Steiner, L. Fang, J. Bai, and S. Chintala. Pytorch: An imperative style, high-performance deep learning library. In H. Wallach, H. Larochelle, A. Beygelzimer, F. d'Alché-Buc, E. Fox, and R. Garnett, editors, *Advances in Neural Information Processing Systems 32*, pages 8024–8035. Curran Associates, Inc., 2019. URL http://papers.neurips.cc/paper/9015-pytorch-an-imperative-style-high-performance-deep-learning-library.pdf.

[37] e. a. Falcon, WA. Pytorch lightning. *GitHub. Note: https://github.com/PyTorchLightning/pytorch-lightning*, 3, 2019.

[38] T. Miyato, T. Kataoka, M. Koyama, and Y. Yoshida. Spectral normalization for generative adversarial networks. In *International Conference on Learning Representations*, 2018. URL https://openreview.net/forum?id=B1QRgziT-.

[39] S. Liu, D. Liberzon, and V. Zharnitsky. Almost lyapunov functions for nonlinear systems. *Automatica*, 113:108758, 2020.

[40] N. M. Boffi, S. Tu, N. Matni, J. J. E. Slotine, and V. Sindhwani. Learning stability certificates from data. In *Conference on Robot Learning*. arXiv, Aug 2020. URL http://arxiv.org/abs/2008.05952.

[41] L. Gurobi Optimization. Gurobi optimizer reference manual, 2021. URL http://www.gurobi.com.

[42] W. Clohessy and R. Wiltshire. Terminal guidance system for satellite rendezvous. *Journal of the Aerospace Sciences*, 27(9):653–658, 1960.