Theoretically Better and Numerically Faster Distributed Optimization with Smoothness-Aware Quantization Techniques

Abstract

To address the high communication costs of distributed machine learning, a large body of work has been devoted in recent years to designing various compression strategies, such as sparsification and quantization, and optimization algorithms capable of using them. Recently, Safaryan et al. [2021] pioneered a dramatically different compression design approach: they first use the local training data to form local *smoothness matrices* and then propose to design a compressor capable of exploiting the smoothness information contained therein. While this novel approach leads to substantial savings in communication, it is limited to sparsification as it crucially depends on the linearity of the compression operator. In this work, we generalize their smoothness-aware compression strategy to *arbitrary unbiased compression* operators, which also includes sparsification. Specializing our results to stochastic quantization, we guarantee significant savings in communication complexity compared to standard quantization. In particular, we prove that block quantization with n blocks theoretically outperforms single block quantization, leading to a reduction in communication complexity by an $\mathcal{O}(n)$ factor, where n is the number of nodes in the distributed system. Finally, we provide extensive numerical evidence with convex optimization problems that our smoothness-aware quantization strategies outperform existing quantization schemes as well as the aforementioned smoothness-aware sparsification strategies with respect to all relevant success measures: the number of iterations, the total amount of bits communicated, and wall-clock time.

1 Introduction

Training modern machine learning models is typically cast in terms of (regularized) empirical risk minimization problem and requires increasingly more training data to make empirical risk closer to the true risk [Schmidhuber, 2015, Vaswani et al., 2019]. This natural requirement makes it harder (and in some scenarios impossible) to collect all data in one place and carry out the training using a single data source. As a result, we reconciled with a flock of datasets disseminated across various compute nodes holding the actual training data [Bekkerman et al., 2011, Vogels et al., 2019]. However, such divide-and-conquer approach of handling vast amount of data means that local updates need to be communicated among the nodes (or through some central server orchestrating the process), which often forms the main bottleneck in modern distributed systems [Zhang et al., 2017, Lin et al., 2018]. This issue is further exacerbated by the fact that modern highly performing models are typically overparameterized [Brown et al., 2020, Narayanan et al., 2021].

Submitted to 36th Conference on Neural Information Processing Systems (NeurIPS 2022). Do not distribute.

1.1. Distributed training. In this paper, we consider distributed training formalized as the following optimization problem

$$\min_{x \in \mathbb{R}^d} f(x) + R(x), \quad \text{where} \quad f(x) \stackrel{\text{def}}{=} \frac{1}{n} \sum_{i=1}^{n} f_i(x), \tag{1}$$

and where d is the number of parameters of model $x \in \mathbb{R}^d$ to be trained, n is the number of machines/nodes participating in the training, $f_i(x)$ is the loss/risk associated with the data stored on machine $i \in [n] \stackrel{\text{def}}{=} \{1, 2, \ldots, n\}$, $f(x)$ is the empirical loss/risk, and $R(x)$ is a regularizer.

Because of the communication constraints, large body of work has been devoted in recent years to the design of various compression strategies, such as sparsification [Konečný and Richtárik, 2018, Wangni et al., 2018, Alistarh et al., 2018], quantization [Goodall, 1951, Roberts, 1962, Alistarh et al., 2017], low-rank approximation [Vogels et al., 2019], three point compressor [Richtárik et al., 2022], and optimization algorithms capable of using them, such as Distributed Compressed Gradient Descent (DCGD) [Khirirat et al., 2018], QSGD [Alistarh et al., 2017, Faghri et al., 2020], NUQSGD [Ramezani-Kebrya et al., 2021], DIANA [Mishchenko et al., 2019, Horváth et al., 2019], PowerSGD [Vogels et al., 2019], signSGD [Bernstein et al., 2018, Safaryan and Richtárik, 2021], intSGD [Mishchenko et al., 2021], ADIANA [Li et al., 2020], MARINA [Gorbunov et al., 2021].

1.2. From scalar smoothness to matrix smoothness. Typically, distributed optimization algorithms in the literature that employ compressed communication, including all methods from the aforementioned works, use only shallow smoothness information of the loss function such as scalar L-smoothness [Nesterov, 2004].

Definition 1 (Scalar Smoothness)**.** Differentiable function $\phi : \mathbb{R}^d \to \mathbb{R}$ is called L-smooth if there exists a non-negative scalar value $L \geq 0$ such that

$$\phi(x) \leq \phi(y) + \langle \nabla \phi(y), x - y \rangle + \frac{L}{2} \|x - y\|^2, \quad \forall x, y \in \mathbb{R}^d. \tag{2}$$

As pointed out by Safaryan et al. [2021], smoothness constant L reflects small part of the rich smoothness information often easily available through the training data. In their recent work, Safaryan et al. [2021] pioneered a dramatically different compression design approach. First, they propose to use the local training data to form local *smoothness matrices*, which they claim contain much more useful information than standard smoothness constants.

Definition 2 (Matrix Smoothness)**.** Differentiable function $\phi : \mathbb{R}^d \to \mathbb{R}$ is called $\mathbf{L}$-smooth if there exists a symmetric positive semidefinite matrix $\mathbf{L} \succeq \mathbf{0}$ such that

$$\phi(x) \leq \phi(y) + \langle \nabla \phi(y), x - y \rangle + \frac{1}{2} \|x - y\|_{\mathbf{L}}^2, \quad \forall x, y \in \mathbb{R}^d. \tag{3}$$

Using smoothness matrices $\mathbf{L}_i$ of all local loss functions $f_i(x)$, $i \in [n]$, Safaryan et al. [2021] design a compressor capable of exploiting the smoothness information contained within the smoothness matrices. In particular, under certain heterogeneity conditions on the smoothness matrices $\mathbf{L}_i$, their new compressor reduces total communication cost by a factor of $\mathcal{O}(\min(n, d))$.

While this novel approach leads to substantial savings in communication, it is limited to random sparsification as it crucially depends on the linearity of the compression operator. It is not clear whether this approach can be useful in the design of other smoothness-aware compression techniques.

2 Summary of Contributions

Motivated by the above mentioned development, in this work, we made the following contributions.

2.1. Extending matrix-smoothness-aware sparsification to general compression schemes. First, we generalize the smoothness-aware sparsification strategy [Safaryan et al., 2021] to arbitrary unbiased compressors. Instead of sparsification operator, we consider the generic class $\mathbb{B}(\omega)$ of (possibly randomized) unbiased compression operators $\mathcal{C} : \mathbb{R}^d \to \mathbb{R}^d$ with bounded variance $\omega \geq 0$, i.e.,

$$\mathbb{E}[\mathcal{C}(x)] = x, \quad \mathbb{E}\left[\|\mathcal{C}(x) - x\|^2\right] \leq \omega \|x\|^2, \quad \forall x, y \in \mathbb{R}^d.$$

This class is quite broad including random sparsification and various quantization schemes. To benefit from the matrix smoothness information with general compressor $\mathcal{C}$, we propose the following

Table 1: Summary of main theoretical results of this work. Below constants and $\log \frac{1}{\varepsilon}$ factors are hidden, n is the number of nodes, d is the model size, $L_{\max} = \max_i L_i$, $L_i = \lambda_{\max}(\mathbf{L}_i)$, the expected smoothness constant $\mathcal{L}_{\max}$ is defined in (4), the variance of generic compression operator is denoted by ω, parameters ν and ν_1 are defined in (8). Refer the notation table in the Appendix.

Regime	$\nabla f_i(x^*) \equiv 0$	arbitrary $\nabla f_i(x^*)$
Original Methods	**DCGD [Khirirat et al., 2018]**	**DIANA [Mishchenko et al., 2019]**
Iteration Complexity	$\frac{L}{\mu} + \frac{\omega L_{\max}}{n\mu}$	$\omega + \frac{L_{\max}}{\mu} + \frac{\omega L_{\max}}{n\mu}$
Communication Complexity Standard Quantization ($\omega = \mathcal{O}(n)$)	$d\frac{L_{\max}}{\mu}$	$nd + d\frac{L_{\max}}{\mu}$
Redesigned Methods	**DCGD+ (Algorithm 1) with general compression**	**DIANA+ (Algorithm 2) with general compression**
Iteration Complexity	$\frac{L}{\mu} + \frac{\mathcal{L}_{\max}}{n\mu}$	$\omega_{\max} + \frac{L}{\mu} + \frac{\mathcal{L}_{\max}}{n\mu}$
Communication Complexity Block Quantization ($n = \mathcal{O}(\sqrt{d})$)	$\frac{d}{n}\frac{L_{\max}}{\mu}$
(if $\nu,\ \nu_1$ are $\mathcal{O}(1)$)	$nd + \frac{d}{\sqrt{nd}}\frac{L_{\max}}{\mu}$
(if $\nu,\ \nu_1$ are $\mathcal{O}(1)$)
Communication Complexity Quantization with varying steps	$\frac{d}{n}\frac{L_{\max}}{\mu} + \frac{d}{d}\frac{L_{\max}}{\mu}$
(if $\nu,\ \nu_1$ are $\mathcal{O}(1)$)	$nd + \frac{d}{n}\frac{L_{\max}}{\mu} + \frac{d}{d}\frac{L_{\max}}{\mu}$
(if $\nu,\ \nu_1$ are $\mathcal{O}(1)$)
Theorems	1, 3, 5	2, 4, 6
Speedup factor (up to)	$\min(n, d)$	$\min(n, d)$

modification in the communication protocol. If $x \in \mathbb{R}^d$ is the vector to be communicated, instead of applying compressor $\mathcal{C}$ directly to x and sending $\mathcal{C}(x)$, we compress it by $\mathcal{C}(\mathbf{L}^{\dagger 1/2}x)$ and decompress it by multiplying $\mathbf{L}^{1/2}$. Overall, the receiver estimates the original x by $\mathbf{L}^{1/2}\mathcal{C}(\mathbf{L}^{\dagger 1/2}x)$.

2.2. Distributed compressed methods with improved communication complexity. To highlight the appropriateness of our generalization, we redesign two distributed compressed methods—DCGD [Khirirat et al., 2018] and DIANA [Mishchenko et al., 2019]—to effectively utilize both matrix smoothness information and general compression operators leading to new methods, which we call DCGD+ (Algorithm 1) and DIANA+ (Algorithm 2). The key notion we introduce that enables the technical analysis is the following quantity describing interaction between compression operator $\mathcal{C} \in \mathbb{B}^d(\omega)$ and smoothness matrix $\mathbf{L} \succeq \mathbf{0}$:

$$\mathcal{L}(\mathcal{C}, \mathbf{L}) \stackrel{\text{def}}{=} \inf \left\{ \mathcal{L} \geq 0 \colon \mathbb{E}\|\mathcal{C}(x) - x\|_{\mathbf{L}}^2 \leq \mathcal{L}\|x\|^2 \right\} \leq \omega \lambda_{\max}(\mathbf{L}).$$

This quantity generalizes the one defined in Safaryan et al. [2021] for sparsification, and provides means for tighter theoretical guarantees (Theorems 1 and 2) and better compression design.

2.3. Block quantization. As we are no longer constrained to sparsification to exploit matrix smoothness, we consider more aggressive quantization schemes to further reduce the communication cost. Our first extension of standard quantization [Alistarh et al., 2017] is *block quantization*, where each block is allowed to have a separate quantization parameter. Notably, we show theoretically that our block quantization with n blocks outperforms single block quantization and saves in communication by a factor of $\mathcal{O}(n)$ for both DCGD+ (Theorem 3) and DIANA+ (Theorem 4) when $n = \mathcal{O}(\sqrt{d})$.

2.3. Quantization with varying steps. In our second extension of standard quantization, we go even further and allow all coordinates to have their own quantization steps. This extension turns out to be more efficient in practice than block quantization and provides savings in communication cost by a factor of $\mathcal{O}(\min(n, d))$ for both DCGD+ (Theorem 5) and DIANA+ (Theorem 6).

2.4. Experiments. Finally, we perform extensive numerical experiments using LibSVM data [Chang and Lin, 2011] and provide clear numerical evidence that the proposed smoothness-aware quantization strategies outperform existing quantization schemes as well the aforementioned smoothness-aware sparsification strategies with respect to all relevant success measures: the number of iterations, the total amount of bits communicated, and wall-clock time (see Section 6 and the Appendix).

3   Smoothness-Aware Distributed Methods with General Compressors

In this section we extend methods DCGD+ and DIANA+ of Safaryan et al. [2021] to handle arbitrary unbiased compression operators. We consider the problem (1) with matrix smoothness assumption for all local losses $f_i(x)$ and with strong convexity of loss function $f(x)$.

107 **Assumption 1** (Matrix smoothness). The functions $f_i \colon \mathbb{R}^d \to \mathbb{R}$ are differentiable, convex, lower
108 bounded and $\mathbf{L}_i$-smooth. Besides, f is $\mathbf{L}$-smooth with the scalar smoothness constant $L \overset{\text{def}}{=} \lambda_{\max}(\mathbf{L})$.

109 Note that lower boundedness of $f_i(x)$ is not needed once $\mathbf{L}_i \succ 0$ is invertible. This part of the
110 assumption is not a restriction in applications as all loss function are lower bounded.

Assumption 2 (μ-convexity). The function $f \colon \mathbb{R}^d \to \mathbb{R}$ is μ-convex for some $\mu > 0$, i.e.,

$$f(x) \geq f(y) + \langle \nabla f(y), x - y \rangle + \tfrac{\mu}{2} \|x - y\|^2, \quad \forall x, y \in \mathbb{R}^d.$$

111 **3.1. DCGD+ with arbitrary unbiased compression.** In our version of DCGD+, each node $i \in [n]$
112 is allowed to control its own compression operator $\mathcal{C}_i \in \mathbb{B}(\omega)$ independent of other nodes. Denote

$$\mathcal{L}_{\max} \overset{\text{def}}{=} \max_{1 \leq i \leq n} \mathcal{L}_i, \quad \text{where} \quad \mathcal{L}_i \overset{\text{def}}{=} \mathcal{L}(\mathcal{C}_i, \mathbf{L}_i). \tag{4}$$

113 Furthermore, as the compressor $\mathcal{C}_i$ can be random, denote by $\mathcal{C}_i^k$ a copy of $\mathcal{C}_i$ generated at iteration k.

Algorithm 1 DCGD+ WITH ARBITRARY UNBIASED COMPRESSION

1: **Input:** Initial point $x^0 \in \mathbb{R}^d$, step size $\gamma > 0$, compression operators $\{\mathcal{C}_1^k, \dots, \mathcal{C}_n^k\}$
2: **on** server
3:      send x^k to all nodes
4:      get compressed updates $\mathcal{C}_i^k(\mathbf{L}_i^{\dagger 1/2} \nabla f_i(x^k))$ from all nodes $i \in [n]$
5:      update the model to $x^{k+1} = \text{prox}_{\gamma R}(x^k - \gamma g^k)$, where $g^k = \frac{1}{n} \sum_{i=1}^n \mathbf{L}_i^{1/2} \mathcal{C}_i^k(\mathbf{L}_i^{\dagger 1/2} \nabla f_i(x^k))$

---

114 Similar to the standard DCGD method, convergence of DCGD+ is linear up to some oscillation
115 neighborhood. However, for overparametrized models this neighborhood vanishes and the method
116 converges linearly to the exact solution.

117 **Theorem 1.** *Let Assumptions 1 and 2 hold and assume that each node $i \in [n]$ generates its own*
118 *copy of compression operator $\mathcal{C}_i^k \in \mathbb{B}^d(\omega_i)$ independently from others. Then, for the step-size*
119 $0 < \gamma \leq \frac{1}{L + \frac{2}{n}\mathcal{L}_{\max}}$, *the iterates $\{x^k\}$ of DCGD+ (Algorithm 1) satisfy*

$$\mathbb{E}\left[\|x^k - x^*\|^2\right] \leq (1 - \gamma\mu)^k \|x^0 - x^*\|^2 + \frac{2\gamma\sigma_+^*}{\mu n}, \tag{5}$$

120 *where $\sigma_+^* \overset{\text{def}}{=} \frac{1}{n} \sum_{i=1}^n \mathcal{L}_i \|\nabla f_i(x^*)\|_{\mathbf{L}_i^\dagger}^2$. In particular, if the model is overparameterized (i.e.,*
121 $\nabla f_i(x^*) = 0$ *for all $i \in [n]$), then DCGD+ converges linearly with iteration complexity*

$$\mathcal{O}\left(\left(\frac{L}{\mu} + \frac{\mathcal{L}_{\max}}{n\mu}\right) \log \frac{1}{\varepsilon}\right). \tag{6}$$

Algorithm 2 DIANA+ WITH ARBITRARY UNBIASED COMPRESSION

1: **Input:** Initial point $x^0 \in \mathbb{R}^d$, initial shifts $u_i^0 \in \text{range}(\mathbf{L}_i)$ and $u^0 \overset{\text{def}}{=} \frac{1}{n}\sum_{i=1}^n u_i^0$, step size
     parameters $\gamma > 0$ and $\alpha > 0$, compression operators $\{\mathcal{C}_1^k, \dots, \mathcal{C}_n^k\}$
2: **for** each node $i = 1, \dots, n$ in parallel **do**
3:      get x^k from the server and compute local gradient $\nabla f_i(x^k)$
4:      send compressed update $\Delta_i^k = \mathcal{C}_i^k(\mathbf{L}_i^{\dagger 1/2}(\nabla f_i(x^k) - u_i^k))$ to the server
5:      update local gradient and shift $\overline{\Delta}_i^k = \mathbf{L}_i^{1/2}\Delta_i^k$, $g_i^k = u_i^k + \overline{\Delta}_i^k$, $u_i^{k+1} = u_i^k + \alpha\overline{\Delta}_i^k$
6: **end for**
7: **on** server
8:      get all sparse updates Δ_i^k, $i \in [n]$ and $\overline{\Delta}^k = \frac{1}{n}\sum_{i=1}^n \overline{\Delta}_i^k = \frac{1}{n}\sum_{i=1}^n \mathbf{L}_i^{1/2}\Delta_i^k$, $g^k = \overline{\Delta}^k + u^k$
9:      update the global model to $x^{k+1} = \text{prox}_{\gamma R}(x^k - \gamma g^k)$ and global shift to $u^{k+1} = u^k + \alpha\overline{\Delta}^k$

---

122 We show later that the linear rate (6) of DCGD+ can be much better than one of DCGD. However,
123 the size of the neighborhood of DCGD+ might be bigger than of DCGD. In case of standard (scalar)
124 smoothness (i.e. $\mathbf{L}_i = L_i\mathbf{I}$) the size of the neighborhood would be $\sigma^* \overset{\text{def}}{=} \frac{1}{n}\sum_{i=1}^n \omega_i \|\nabla f_i(x^*)\|^2$,
125 which might be smaller than σ_+^*. Even though we have $\mathcal{L}_i \leq \omega_i\lambda_{\max}(\mathbf{L}_i)$ from the definition of $\mathcal{L}_i$,
126 it does not imply $\mathcal{L}_i\mathbf{L}_i^\dagger \preceq \omega_i\mathbf{I}$. Thus, with matrix-smoothness-aware compression we ensure faster
127 linear convergence at the cost of a possibly larger oscillation radius. This is not an issue for modern

128 overparameterized models, which can interpolate the whole training data with zero loss. Moreover,
129 next we present an algorithmic solution to remove the neighborhood using the DIANA method.

130 **3.2. DIANA+ with arbitrary unbiased compression.** The mechanism allowing to remove the
131 neighborhood in DIANA+ is based on the DIANA method, which was initially introduced for ternary
132 quantization by Mishchenko et al. [2019], and then extended to arbitrary unbiased compression
133 operators by Horváth et al. [2019]. The high level idea is to learn the local optimal gradients $\nabla f_i(x^*)$
134 by estimates u_i^k for all nodes $i \in [n]$ in a communication efficient manner. Nodes use these estimates
135 u_i^k to progressively construct better local gradient estimates g_i^k reducing the variance induced from
136 the compression.

137 We prove in the Appendix that both iterates x^k and all local gradient estimates u_i^k converge linearly
138 to the exact solution x^* and $\nabla f_i(x^*)$ respectively.

139 **Theorem 2.** *Let Assumptions 1 and 2 hold and assume that each node $i \in [n]$ generates its own copy*
140 *of compression operator $\mathcal{C}_i^k \in \mathbb{B}^d(\omega_i)$ independently from others. Then, if $\omega_{\max} = \max_{1 \leq i \leq n} \omega_i$*
141 *and the step-size $\gamma = \frac{1}{L + \frac{6}{n}\mathcal{L}_{\max}}$, DIANA+ (Algorithm 2) converges linearly with iteration complexity*
142

$$\mathcal{O}\big((\omega_{\max} + \tfrac{L}{\mu} + \tfrac{\mathcal{L}_{\max}}{n\mu})\log\tfrac{1}{\varepsilon}\big). \tag{7}$$

143 Notice that the cost of removing the neighborhood is the extra $\mathcal{O}(\omega_{\max}\log\frac{1}{\varepsilon})$ iterations, which is
144 negligible in the overall complexity (7) above. Another interesting observation is the second order
145 flavor of the gradient learning technique employed by DIANA+. Let, for concreteness, matrices $\mathbf{L}_i$ be
146 invertible and $\mathcal{C}_i^k(-x) = -\mathcal{C}_i^k(x)$ for all $x \in \mathbb{R}^d$ (both random sparsification and quantization satisfy
147 this). Typically, the learning procedure of the original DIANA method, $u_i^{k+1} = u_i^k - \alpha\mathcal{C}_i^k(u_i^k -$
148 $\nabla f_i(x^k))$, can be interpreted as a single step of CGD applied to the problem of minimizing the
149 convex quadratic function $\varphi_i^k(u) \stackrel{\text{def}}{=} \frac{1}{2}\left\|u - \nabla f_i(x^k)\right\|^2$, which changes in each iteration because
150 the gradient changes. In contrast, we observe that the learning mechanism of DIANA+ can be
151 interpreted as a single step of a (damped) Newton's method with compressed gradients and with
152 the true Hessian. Indeed, fix the iteration counter k and denote $\varphi_i^k(u) \stackrel{\text{def}}{=} \frac{1}{2}\left\|u - \nabla f_i(x^k)\right\|^2_{\mathbf{L}_i^{-1/2}}$.
153 Then, the update rule of shifts u_i^k in DIANA+ can be rewritten as $u_i^{k+1} = u_i^k - \alpha\mathbf{L}_i^{1/2}\mathcal{C}(\mathbf{L}_i^{-1/2}(u_i^k -$
154 $\nabla f_i(x^k))) = u_i^k - \alpha\left[\nabla^2\varphi_i(u_i^k)\right]^{-1}\mathcal{C}_i^k(\nabla\varphi_i(u_i^k))$. This might serve as an extra explanation on why
155 incorporating smoothness matrices properly can improve the performance of first order methods with
156 communication compression.

157 **3.3. Baselines for the original methods.** To make the theoretical comparison against DCGD and
158 DIANA more transparent, we fix the following baselines using the standard quantization scheme.

159 ● **Baseline for DCGD.** Based on the iteration complexity $\widetilde{\mathcal{O}}(\frac{L}{\mu} + \frac{\omega L_{\max}}{n\mu})$ of DCGD (in case
160 $\nabla f_i(x^*) = 0$ for all $i \in [n]$) the optimal level of compression variance $\omega = \mathcal{O}(n)$ results in
161 $\widetilde{\mathcal{O}}(\frac{L_{\max}}{\mu})$ iterations complexity. From the estimate of quantization variance $\omega = \min\left(\frac{d}{s^2}, \frac{\sqrt{d}}{s}\right)$ we
162 conclude that $s = \mathcal{O}(\frac{\sqrt{d}}{n})$ number of levels should be used. Finally, with this choice of s, each node
163 communicates $\mathcal{O}(s^2 + s\sqrt{d}) = \mathcal{O}(\frac{d}{n})$ amount of bits. Thus, total communication complexity (i.e.
164 how many bits flows through the central server) of DCGD is $\widetilde{\mathcal{O}}(\frac{dL_{\max}}{\mu})$.

165 ● **Baseline for DIANA.** Based on the iteration complexity $\widetilde{\mathcal{O}}(\omega + \frac{L_{\max}}{\mu} + \frac{\omega L_{\max}}{n\mu})$ of DIANA method,
166 we fix the same level of compression with $\omega = \mathcal{O}(n)$. With a similar argument, this leads us to
167 $\widetilde{\mathcal{O}}(n + \frac{L_{\max}}{\mu})$ iteration complexity and $\mathcal{O}(\frac{d}{n})$ bits of communication per node in each iteration.
168 Whence, total communication complexity becomes $\widetilde{\mathcal{O}}(dn + \frac{dL_{\max}}{\mu})$.

169 To compare the proposed methods with these baselines and highlight improvement factors, define
170 parameters ν and ν_1 describing local smoothness matrices $\mathbf{L}_i$ as follows

$$\nu \stackrel{\text{def}}{=} \frac{\sum_{i=1}^n L_i}{\max_{i\in[n]} L_i}, \quad \nu_1 \stackrel{\text{def}}{=} \max_{i\in[n]} \frac{\sum_{j=1}^d \mathbf{L}_{i;j}}{\max_{j\in[d]} \mathbf{L}_{i;j}}, \tag{8}$$

171 where $L_i = \lambda_{\max}(\mathbf{L}_i)$, $L_{\max} \stackrel{\text{def}}{=} \max_{1 \leq i \leq n} L_i$ and $\mathbf{L}_{i;j}$ is the jth diagonal element of matrix
172 $\mathbf{L}_i$. Parameters $\nu \in [1, n]$ and $\nu_1 \in [1, d]$ describe the level of heterogeneity over the nodes and

173 coordinates respectively. If $\mathbf{L}_i$ matrices coincide, then $\nu = n$ and $\nu_1 = d$. On the other extreme,
174 when the values of $\mathbf{L}_i$ are extremely non-uniform, we have $\nu \ll n$ and $\nu_1 \ll d$.

175 Notice that the quantity $\frac{\mathcal{L}_{\max}}{\mu n}$ in (6) and the quantity $\omega_{\max} + \frac{\mathcal{L}_{\max}}{\mu n}$ in (7) depend on compression
176 operators $\mathcal{C}_i^k$ applied by the nodes. For the rest of the paper we are going to minimize these quantities
177 with respect to the choice of $\mathcal{C}_i^k$ in such a way to minimize total communication complexity of the
178 proposed distributed methods. We specialize compressors $\mathcal{C}_i$ to two different extensions of standard
179 quantization and optimize with respect to compression parameters.

180 4 Block Quantization

181 We now present our first extension to standard quantization in order to properly capture the matrix
182 smoothness information. Instead of having a single quantization parameter (e.g. number of levels)
183 for all coordinates, here we divide the space $\mathbb{R}^d$ into $B \in \{1, 2, \dots, d\}$ blocks as $\mathbb{R}^d = \mathbb{R}^{d_1} \times \mathbb{R}^{d_2} \times$
184 $\cdots \times \mathbb{R}^{d_B}$ and for each subspace $\mathbb{R}^{d_l}$, $l \in [B]$ we apply standard quantization independently from
185 other blocks with different number of levels s_l. Thus, for any $l \in [B]$ we allocate one parameter s_l for
186 l^{th} block of $x \in \mathbb{R}^d$. Hence quantization is applied block-wise: for each block we send the norm $\|x^l\|$
187 of the block $x^l \in \mathbb{R}^{d_l}$ and all entries within this block are quantized with levels $\{0, \frac{1}{s_l}, \frac{2}{s_l}, \dots, 1\}$. In
188 the special case of $B = 1$, we get the standard quantization of Alistarh et al. [2017].

189 To get rid of the constraints on s_l to be integers, instead of working with the number of levels s_l, we
190 introduce the size of the quantization step $h_l = \frac{1}{s_l}$ and allow them to take any positive values (even
191 bigger than 1). Thus, for each block $l \in [B]$ we quantize with respect to levels $\{0, h_l, 2h_l, \dots\}$.

192 **Definition 3** (Block Quantization). For a given number of blocks $B \in [d]$ and fixed quantization
193 steps $h = (h_1, \dots, h_B)$, define block-wise quantization operator $\mathcal{Q}_h^B : \mathbb{R}^d \to \mathbb{R}^d$ as follows:

$$\left[\mathcal{Q}_h^B(x)\right]_t \quad \overset{\text{def}}{=} \quad \|x^l\| \cdot \text{sign}(x_t) \cdot \xi_l\left(\frac{|x_t|}{\|x^l\|}\right),$$

194 where $t = (l-1)B + j$, $x \in \mathbb{R}^d$, $j \in [d_l]$, $l \in [B]$ and $\xi_l(v)$ for $v \geq 0$ is defined via the quantization
195 levels $\{0, h_l, 2h_l, \dots\}$ as follows: if $kh_l \leq v < (k+1)h_l$ for some $k \in \{0, 1, 2, \dots\}$, then

$$\xi_l(v) \overset{\text{def}}{=} \begin{cases} kh_l & \text{with probability} \quad k+1 - \frac{v}{h_l}, \\ (k+1)h_l & \text{with probability} \quad \frac{v}{h_l} - k. \end{cases} \tag{9}$$

196 Note that $\mathcal{Q}_h^B$ is an unbiased compression operator as $\mathbb{E}[\xi_j(v)] = v$ for any $v \geq 0$. To communicate
197 a vector of the form $\mathcal{Q}_h^B(x)$, we encode each block $\left[\mathcal{Q}_h^B(x)\right]^l \in \mathbb{R}^{d_l}$ using Elias ω-coding as in
198 the standard quantization scheme [Alistarh et al., 2017]. Hence, for each block $l \in [B]$ we need to
199 send $\widetilde{\mathcal{O}}(\frac{1}{h_l^2} + \frac{\sqrt{d_l}}{h_l})$ bits and one floating point number for $\|x^l\|$. Overall, the number of encoding
200 bits for $\mathcal{Q}_h^B(x)$ (up to constant and log factors) can be given by $\sum_{l=1}^B (\frac{1}{h_l^2} + \frac{\sqrt{d_l}}{h_l}) + B$. As for the
201 compression noise, we prove in the Appendix the following upper bound for $\mathcal{L}(\mathcal{Q}_h^B, \mathbf{L})$:

$$\mathcal{L}(\mathcal{Q}_h^B, \mathbf{L}) \leq \max_{1 \leq l \leq B} h_l \|\mathbf{Diag}(\mathbf{L}^{ll})\|, \tag{10}$$

202 where $\mathbf{L}^{ll}$ is the l^{th} diagonal block matrix of $\mathbf{L}$ with sizes $d_l \times d_l$. Next, we are going to minimize
203 communication complexity of DCGD+ and DIANA+ by optimizing parameters of block quantization.

204 **4.1. DCGD+ with block quantization.** We fix the number of blocks $B \in [d]$ for all nodes $i \in [n]$
205 and allow each node to apply different block quantization operator $\mathcal{Q}_{h_i}^B$ with quantization steps
206 $h_i = (h_{i,1}, \dots, h_{i,B})$. To minimize communication complexity of DCGD+, we need to minimize
207 $\mathcal{L}_{\max}$ subject to the communication constraint mentioned above. Since $\mathcal{L}_{\max} = \max_{i \in [n]} \mathcal{L}(\mathcal{C}_i, \mathbf{L}_i)$,
208 each node $i \in [n]$ can minimize the impact of its own compression by minimizing $\mathcal{L}(\mathcal{C}_i, \mathbf{L}_i)$ based
209 on local smoothness matrix $\mathbf{L}_i$. This leads to the following optimization problem for finding optimal
210 values of h_i for each node $i \in [n]$:

$$\min_{h \in \mathbb{R}^B} \max_{1 \leq l \leq B} h_l \|\mathbf{Diag}(\mathbf{L}_i^{ll})\|, \quad s.t. \sum_{l=1}^B (\frac{1}{h_l^2} + \frac{\sqrt{d_l}}{h_l}) + B = \beta, \ h_l > 0, \ l \in [B]. \tag{11}$$

211 The solution to this problem is given by $h_{i,l} = \frac{\delta_{i,B}}{\|\mathbf{Diag}(\mathbf{L}_i^{ll})\|}$, where $\delta_{i,B} \geq 0$ is uniquely determined
212 by the constraint equality of (11) as the only positive solution of $\delta_{i,B}^2 - \delta_{i,B} \frac{dT_{i,B}}{\beta - B} - \frac{dT_{1,B}^2}{\beta - B} = 0$,

which implies $\delta_{i,B} = \frac{dT_{i,B}}{2(\beta-B)} + \sqrt{\frac{d^2 T_{i,B}^2}{4(\beta-B)^2} + \frac{dT_{i,1}^2}{\beta-B}} \leq \frac{d}{\beta-B}T_{i,B} + \sqrt{\frac{d}{\beta-B}}T_{i,1}$, where $T_{i,B} \stackrel{\text{def}}{=} \frac{1}{d}\sum_{l=1}^{B}\sqrt{d_l}\|\mathbf{Diag}(\mathbf{L}_i^{ll})\|$. If this solution of quantization steps h_i is used by all nodes $i \in [n]$, then we show reduction in communication complexity by a factor of $\mathcal{O}(n)$.

Theorem 3. *Assume $n = \mathcal{O}(\sqrt{d})$ and both ν, ν_1 are $\mathcal{O}(1)$. Then DCGD+ using block quantization with $B = n$ blocks, $d_l = \mathcal{O}(d/n)$ block sizes for all $l \in [n]$ and quantization steps $h_{i,l} = \delta_{i,B}/\|\mathbf{Diag}(\mathbf{L}_i^{ll})\|$ with $\beta = \mathcal{O}(d/n)$ reduces overall communication complexity by a factor of $\mathcal{O}(n)$ compared to DCGD using $B = 1$ single block quantization. Formally, to guarantee $\varepsilon > 0$ accuracy, the communication complexity of DCGD+ is $\mathcal{O}\left(\frac{d}{n}\frac{L_{\max}}{\mu}\log\frac{1}{\varepsilon}\right)$, which is $\mathcal{O}(n)$ times smaller over DCGD.*

4.2. DIANA+ with block quantization. For the rate (7) of DIANA+, we need to optimize $\omega_{\max} + \frac{\mathcal{L}_{\max}}{n\mu}$ part of the complexity under the same communication constraint used in (11). Since

$$\max_{i\in[n]}\left(\omega_i + \frac{\mathcal{L}_i}{n\mu}\right) \leq \omega_{\max} + \frac{\mathcal{L}_{\max}}{n\mu} \leq 2\max_{i\in[n]}\left(\omega_i + \frac{\mathcal{L}_i}{n\mu}\right), \tag{12}$$

we can decompose the problem into subproblems for each node i to optimize $\omega_i + \frac{\mathcal{L}_i}{n\mu}$ with respect to its own quantization parameters h_i. Analogously, this leads to the following optimization problem for finding optimal values of h_i for each node $i \in [n]$:

$$\min_{h\in\mathbb{R}^B}\max_{1\leq l\leq B} h_l\left(\sqrt{d_l} + \frac{1}{\mu n}\|\mathbf{Diag}(\mathbf{L}_i^{ll})\|\right), \; s.t. \; \sum_{l=1}^{B}\left(\frac{1}{h_l^2} + \frac{\sqrt{d_l}}{h_l}\right) + B = \beta, \; h_l > 0, \tag{13}$$

which can be solved with a similar argument as done for (11). Details are deferred to the Appendix.

Theorem 4. *Assume $n = \mathcal{O}(\sqrt{d})$ and both ν, ν_1 are $\mathcal{O}(1)$. Then DIANA+ using block quantization with $B = n$ blocks, $d_l = \mathcal{O}(d/n)$ block sizes for all $l \in [n]$ and $h_{i,l}$ quantization steps (solution to (13)) with $\beta = \mathcal{O}(d/n)$ reduces overall communication complexity by a factor of $\mathcal{O}(n)$ compared to DIANA using $B = 1$ single block quantization. Formally, to guarantee $\varepsilon > 0$ accuracy, the communication complexity of DIANA+ is $\mathcal{O}\left((nd + \sqrt{\frac{d}{n}\frac{L_{\max}}{\mu}})\log\frac{1}{\varepsilon}\right)$, which (ignoring n summand in the complexity) is $\mathcal{O}(n)$ times smaller over DIANA.*

5 Quantization with Varying Steps

Our second extension of standard quantization scheme is to allow different quantization steps for all coordinates $\{1, 2, \ldots, d\}$. In other words, for each coordinate $j \in [d]$ we quantize with respect to levels $\{0, h_j, 2h_j, \ldots\}$. The standard quantization [Alistarh et al., 2017] is the special case when $h_j = \frac{1}{s}$ for all $j \in [d]$, where s is the number of quantization levels.

Definition 4 (Quantization with varying steps)**.** For fixed quantization steps $h = (h_1, \ldots, h_d)^\top \in \mathbb{R}^d$, define quantization operator $\mathcal{Q}_h: \mathbb{R}^d \to \mathbb{R}^d$ as follows:

$$[\mathcal{Q}_h(x)]_j = \|x\| \cdot \text{sign}(x_j) \cdot \xi_j\left(\frac{|x_j|}{\|x\|}\right), \quad x \in \mathbb{R}^d, \; j = 1, 2, \ldots, d,$$

where ξ_j is defined via the quantization levels $\{0, h_j, 2h_j, \ldots\}$ as in (9).

Note that compression operator $\mathcal{Q}_h$ is unbiased as $\mathbb{E}[\xi_j(v)] = v$ for any $v \geq 0$. To understand how the number of encoding bits of $\mathcal{Q}_h(x)$ depends on h exactly seems challenging, since it depends on the actual encoding scheme (i.e. binary representation of compressed information). Besides, even if we fix binary mapping, the closed form expression of total amount of bits is complicated enough to be utilized in the further analysis. We provide theoretical arguments and clear numerical evidence that $\|h^{-1}\| = \sqrt{\sum_{j=1}^{d}h_j^{-2}}$ is a reasonable proxy for the number of encoding bits for compressor $\mathcal{Q}_h$.

Assumption 3. For any input vector $x \in \mathbb{R}^d$ and quantization steps $h \in \mathbb{R}^d$, compressed vector $\mathcal{Q}_h(x)$ can be encoded with $\mathcal{O}(\|h^{-1}\|)$ number of bits.

First, consider the special case when all quantization steps are the same, i.e. $h_j = \frac{1}{s}$. Then $\|h^{-1}\| = s\sqrt{d}$ recovers the dominant part (provided $s = \mathcal{O}(\sqrt{d})$) in $\widetilde{\mathcal{O}}(s^2 + s\sqrt{d})$ showing total

amount of bits for standard quantization scheme. Second, in the Appendix we present an encoding
scheme which (up to constant and $\log d$ factors) requires $\mathbb{E}\left[\psi(\|\hat{x}\|_0)\right] + \|h^{-1}\|$ number of bits in
expectation to communicate $\hat{x} = \mathcal{Q}_h(x)$, where $\psi(\tau) \overset{\text{def}}{=} dH_2(\tau/d) + \tau \leq d\log 3$, if $\tau \in [0, d]$ and
H_2 is the binary entropy function. Note that, based on the definition (9), increasing quantization steps
h_j forces more sparsity in $\hat{x}$ and hence reduces $\|\hat{x}\|_0$. Thus, $\|\hat{x}\|_0$ and hence $\psi(\|\hat{x}\|_0)$ (notice that
$\psi(0) = 0$) are proportional to $\|h^{-1}\|$. Furthermore, we present a numerical experiment which shows
that the number of encoding bits of $\mathcal{Q}_h(x)$ and $\|h^{-1}\|$ are positively correlated.

Hence, in the further analysis, we fix the number of encoding bits of $\mathcal{Q}_h(x)$ by the constraint
$\|h^{-1}\| = \beta$ for some parameter $\beta > 0$. As for the variance induced by the compression operator $\mathcal{Q}_h$,
we prove the following upper bound for $\mathcal{L}(\mathcal{Q}_h, \mathbf{L})$:

$$\mathcal{L}(\mathcal{Q}_h, \mathbf{L}) \leq \|\mathbf{Diag}(\mathbf{L})h\|. \tag{14}$$

5.1. DCGD+ with varying quantization steps. Now, we optimize the rate (6) of DCGD+ with
respect to quantization steps $h_i = (h_{i;1}, h_{i;2}, \ldots, h_{i;d})$ of compressor $\mathcal{Q}_{h_i}$ controlled by i^{th} node
for all $i \in [n]$. The term in (6) affected by the compression is $\mathcal{L}_{\max} = \max_{i \in [n]} \mathcal{L}(\mathcal{C}_i, \mathbf{L}_i)$, which
implies that each node $i \in [n]$ can minimize the impact of its own compression by minimizing
$\mathcal{L}(\mathcal{C}_i, \mathbf{L}_i)$ based on local smoothness matrix $\mathbf{L}_i$. Based on the upper bound (14) and communication
constraint given by $\|h^{-1}\| = \beta$ for some $\beta > 0$, we get the following optimization problem to choose
the optimal quantization parameters h_i for node $i \in [n]$:

$$\min_{h \in \mathbb{R}^d} \|\mathbf{Diag}(\mathbf{L}_i)h\|, \quad s.t. \ \|h^{-1}\| = \beta, \ h_j > 0, \ j \in [d]. \tag{15}$$

This problem has the following closed form solution due to KKT conditions (see Appendix):

$$h_{i;j} = \frac{1}{\beta}\sqrt{\frac{\sum_{t=1}^d \mathbf{L}_{i;t}}{\mathbf{L}_{i;j}}}, \quad i \in [n], \ j \in [d]. \tag{16}$$

With this choice of quantization steps we save $\mathcal{O}(\min(n, d))$ times in communication.

Theorem 5. *Assume both ν, ν_1 are $\mathcal{O}(1)$ and $\beta = \mathcal{O}(d/n)$. Then DCGD+ using quantization
with varying steps (25) for all $i \in [n]$ reduces overall communication complexity by a factor of
$\mathcal{O}(\min(n, d))$ compared to the baseline of DCGD. Formally, the iteration complexity (6) can be
upper bounded as $\frac{L}{\mu} + \frac{\mathcal{L}_{\max}}{n\mu} \leq \frac{\nu}{n}\frac{L_{\max}}{\mu} + \frac{\nu_1}{\beta}\frac{L_{\max}}{n\mu} = \mathcal{O}\left(\frac{1}{n}\frac{L_{\max}}{\mu} + \frac{1}{d}\frac{L_{\max}}{\mu}\right)$, which is $\min(n, d)$
times smaller than the one for DCGD. As both methods communicate $\mathcal{O}(d/n)$ bits per node per
iteration, we get $\min(n, d)$ times savings in communication complexity.*

5.2. DIANA+ with varying quantization steps. Based on (12), each node $i \in [n]$ optimizes $\omega_i + \frac{\mathcal{L}_i}{n\mu}$
with respect to its quantization parameters h_i, which is equivalent to the problem

$$\min_{h \in \mathbb{R}^d} \sum_{j=1}^d \left(1 + A_{ij}^2\right)h_j^2, \quad s.t. \ \|h^{-1}\| = \beta, \ h_j > 0, j \in [d] \tag{17}$$

where $A_{ij} \overset{\text{def}}{=} \mathbf{L}_{i;j}/n\mu$. Due to the KKT conditions (see Appendix), we get the following solution

$$h_{i;j} = \frac{1}{\beta}\sqrt{\frac{\sum_{t=1}^d \sqrt{1 + A_{it}^2}}{\sqrt{1 + A_{ij}^2}}}. \tag{18}$$

With this choice of quantization steps we save $\mathcal{O}(\min(n, d))$ times in communication.

Theorem 6. *Assume both ν, ν_1 are $\mathcal{O}(1)$ and $\beta = \mathcal{O}(d/n)$. Then DIANA+ using quantization
with varying steps (18) for all $i \in [n]$ reduces overall communication complexity by a factor of
$\mathcal{O}(\min(n, d))$ compared to the baseline of DIANA. Formally, the iteration complexity (7) can be
upper bounded as $\omega_{\max} + \frac{L}{\mu} + \frac{\mathcal{L}_{\max}}{n\mu} \leq \frac{\sqrt{2}d}{\beta} + \frac{\nu}{n}\frac{L_{\max}}{\mu} + \frac{\sqrt{2}\nu_1}{\beta n}\frac{L_{\max}}{\mu} = \mathcal{O}\left(n + \frac{1}{n}\frac{L_{\max}}{\mu} + \frac{1}{d}\frac{L_{\max}}{\mu}\right)$,
which is $\min(n, d)$ times smaller than the one for DIANA (ignoring negligible term n).*

6 Experiments

6.1. Setup. In this section we present two key experiments. Additional experiments can be found in
the Appendix. We conduct a range of experiments with several datasets from the LibSVM repository
[Chang and Lin, 2011] on the ℓ_2-regularized logistic regression problem (1):

$$\min_{x \in \mathbb{R}^d} \frac{1}{n}\sum_{i=1}^n f_i(x), \quad f_i(x) = \frac{1}{m}\sum_{t=1}^m \log(1 + \exp(-b_{i,t}\mathbf{A}_{i,t}^\top x)) + \frac{\lambda}{2}\|x\|^2,$$

287 where $\mathbf{A}_{i,t}$ are data points randomly shuffled before allocating to local workers. The experiments are
288 performed on a workstation with Intel(R) Xeon(R) Gold 6246 CPU @ 3.30GHz cores. The `gather`
289 and `broadcast` operations for the communications between master and workers are implemented
290 based on the MPI4PY library [Dalcín et al., 2005] and each CPU core is treated as a local worker.
291 For each dataset, we run each algorithm multiples times with 5 random seeds for each worker. Due to
292 space limitations, we present only two of our experiments here deferring the remaining experiments
293 along with experimental details in the Appendix.

294 **6.2. Comparison to standard quantization techniques.** In our first experiment, we compare
295 smoothness-aware DCGD+ and DIANA+ methods with our varying-step quantization technique
296 (`quant+`) to the original DCGD [Khirirat et al., 2018] and DIANA [Mishchenko et al., 2019] methods
297 with the standard quantization technique (`quant`) of Alistarh et al. [2017]. Figure 1 demonstrates
298 that DCGD+/DIANA+ with `quant+` lead to significant improvement in both transmitted megabytes
299 and wall-clock time. An ablation study to disentangle the contributions of exploiting the smoothness
300 matrix and utilizing varying number of levels can be found in Appendix B.

Figure 1: Comparison of smoothness-aware DCGD+/DIANA+ methods with varying-step quantization (`quant+`) to original DCGD/DIANA methods with standard quantization (`quant`). Note that in `quant+` workers need to send $\mathbf{L}_i^{1/2} \in \mathbb{R}^{d \times d}$ and quantization steps $h_i \in \mathbb{R}^d$ to the master before the training. This leads to extra costs in communication bits and time, which are taken into consideration.

301 **6.3. Comparison to matrix-smoothness-aware sparsification.** Second experiment is devoted to
302 the performance of three smoothness-aware compression techniques —block quantization (`block`
303 `quant+`) of Section 4, varying-step quantization (`quant+`) of Section 5 and smoothness-aware
304 sparsification strategy (`rand-τ+`) of Safaryan et al. [2021]. All three compression techniques are
305 shown to outperform the standard compression strategies by at most $\mathcal{O}(n)$ times in theory. For
306 the sparsification, we use the optimal probabilities and the sampling size $\tau = d/n$ as suggested in
307 Section 5.3 of [Safaryan et al., 2021]. The empirical results in Figure 2 illustrate that the varying-step
308 quantization technique (`quant+`) is always better than the smoothness-aware sparsification [Safaryan
309 et al., 2021], in terms of both communication cost and wall-clock time. Our block quantization
310 technique also beats sparsification when the dimension of the model is relatively high.

Figure 2: Comparison of three matrix-smoothness-aware compression techniques employed in DIANA+ method: varying-step quantization `quant+`, our variant of block quantization `block` `quant+`, and smoothness-aware sparsification `rand-τ+` of Safaryan et al. [2021].

References

Alyazeed Albasyoni, Mher Safaryan, Laurent Condat, and Peter Richtárik. Optimal gradient compression for distributed and federated learning. *arXiv preprint arXiv:2010.03246*, 2020.

Dan Alistarh, Demjan Grubic, Jerry Li, Ryota Tomioka, and Milan Vojnovic. QSGD: Communication-efficient SGD via gradient quantization and encoding. In *Advances in Neural Information Processing Systems*, pages 1709–1720, 2017.

Dan Alistarh, Torsten Hoefler, Mikael Johansson, Nikola Konstantinov, Sarit Khirirat, and Cédric Renggli. The convergence of sparsified gradient methods. In *Advances in Neural Information Processing Systems (NeurIPS)*, pages 5977–5987, 2018.

Ron Bekkerman, Mikhail Bilenko, and John Langford. *Scaling up machine learning: Parallel and distributed approaches*. Cambridge University Press, 2011.

Jeremy Bernstein, Yu-Xiang Wang, Kamyar Azizzadenesheli, and Animashree Anandkumar. SignSGD: Compressed optimisation for non-convex problems. In *International Conference on Machine Learning (ICML)*, 2018.

Tom B. Brown et al. Language models are few-shot learners. *arXiv preprint arXiv:2005.14165*, 2020.

Chih-Chung Chang and Chih-Jen Lin. LibSVM: a library for support vector machines. *ACM Transactions on Intelligent Systems and Technology (TIST)*, 2(3):1–27, 2011.

Lisandro Dalcín, Rodrigo Paz, and Mario Storti. MPI for Python. *Journal of Parallel and Distributed Computing*, 65(9):1108–1115, 2005.

Fartash Faghri, Iman Tabrizian, Ilia Markov, Dan Alistarh, Daniel Roy, and Ali Ramezani-Kebrya. Adaptive gradient quantization for data-parallel SGD. In *Advances in Neural Information Processing Systems (NeurIPS)*, 2020.

W. M. Goodall. Television by pulse code modulation. *The Bell System Technical Journal*, 30(1): 33–49, Jan 1951. ISSN 0005-8580. doi: 10.1002/j.1538-7305.1951.tb01365.x.

Eduard Gorbunov, Filip Hanzely, and Peter Richtárik. A unified theory of SGD: Variance reduction, sampling, quantization and coordinate descent. In *International Conference on Artificial Intelligence and Statistics (AISTATS)*, 2020.

Eduard Gorbunov, Konstantin Burlachenko, Zhize Li, and Peter Richtárik. MARINA: faster non-convex distributed learning with compression. In *International Conference on Machine Learning (ICML)*, 2021. arXiv preprint arXiv:2102.07845.

Filip Hanzely and Peter Richtárik. One method to rule them all: Variance reduction for data, parameters and many new methods. *arXiv preprint arXiv:1905.11266*, 2019.

Samuel Horváth, Dmitry Kovalev, Konstantin Mishchenko, Sebastian Stich, and Peter Richtárik. Stochastic distributed learning with gradient quantization and variance reduction. *arXiv preprint arXiv:1904.05115*, 2019.

Sarit Khirirat, Hamid Reza Feyzmahdavian, and Mikael Johansson. Distributed learning with compressed gradients. *arXiv preprint arXiv:1806.06573*, 2018.

Jakub Konečný and Peter Richtárik. Randomized distributed mean estimation: accuracy vs communication. *Frontiers in Applied Mathematics and Statistics*, 4(62):1–11, 2018.

Zhize Li, Dmitry Kovalev, Xun Qian, and Peter Richtárik. Acceleration for compressed gradient descent in distributed and federated optimization. In *International Conference on Machine Learning (ICML)*, 2020.

Yujun Lin, Song Han, Huizi Mao, Yu Wang, and William J. Dally. Deep gradient compression: Reducing the communication bandwidth for distributed training. In *International Conference on Learning Representations (ICLR)*, 2018.

Konstantin Mishchenko, Eduard Gorbunov, Martin Takáč, and Peter Richtárik. Distributed learning with compressed gradient differences. *arXiv preprint arXiv:1901.09269*, 2019.

Konstantin Mishchenko, Bokun Wang, Dmitry Kovalev, and Peter Richtárik. IntSGD: Floatless compression of stochastic gradients. *arXiv preprint arXiv:2102.08374*, 2021.

Deepak Narayanan, Mohammad Shoeybi, Jared Casper, Patrick LeGresley, Mostofa Patwary, Vijay Korthikanti, Dmitri Vainbrand, and Bryan Catanzaro. Scaling language model training to a trillion parameters using megatron. https://developer.nvidia.com/blog/scaling-language-model-training-to-a-trillion-parameters-using-megatron/, 2021.

Yurii Nesterov. *Introductory lectures on convex optimization: a basic course.* Kluwer Academic Publishers, 2004.

Ali Ramezani-Kebrya, Fartash Faghri, Ilya Markov, Vitalii Aksenov, Dan Alistarh, and Daniel M. Roy. NUQSGD: Provably communication-efficient data-parallel SGD via nonuniform quantization. *arXiv preprint arXiv:2104.13818*, 2021.

Peter Richtárik, Igor Sokolov, Ilyas Fatkhullin, Elnur Gasanov, Zhize Li, and Eduard Gorbunov. 3pc: Three point compressors for communication-efficient distributed training and a better theory for lazy aggregation. *39th International Conference on Machine Learning (ICML)*, 2022.

L. Roberts. Picture coding using pseudo-random noise. *IRE Transactions on Information Theory*, 8 (2):145–154, February 1962. ISSN 0096-1000. doi: 10.1109/TIT.1962.1057702.

Mher Safaryan and Peter Richtárik. Stochastic sign descent methods: New algorithms and better theory. In *International Conference on Machine Learning (ICML)*, 2021.

Mher Safaryan, Filip Hanzely, and Peter Richtárik. Smoothness matrices beat smoothness constants: Better communication compression techniques for distributed optimization. *Advances in Neural Information Processing Systems (NeurIPS)*, 2021.

Jürgen Schmidhuber. Deep learning in neural networks: An overview. In *Neural Networks*, volume 61, page 85–117, 2015.

Sharan Vaswani, Francis Bach, and Mark Schmidt. Fast and faster convergence of SGD for over-parameterized models and an accelerated perceptron. In *International Conference on Artificial Intelligence and Statistics (AISTATS)*, 2019.

Thijs Vogels, Sai Praneeth Karimireddy, and Martin Jaggi. PowerSGD: Practical low-rank gradient compression for distributed optimization. In *Advances in Neural Information Processing Systems (NeurIPS)*, 2019. arXiv prepring arXiv:1905.13727.

Jianqiao Wangni, Jialei Wang, Ji Liu, and Tong Zhang. Gradient sparsification for communication-efficient distributed optimization. In *Advances in Neural Information Processing Systems (NeurIPS)*, 2018.

Hantian Zhang, Jerry Li, Kaan Kara, Dan Alistarh, Ji Liu, and Ce Zhang. ZipML: Training linear models with end-to-end low precision, and a little bit of deep learning. In *International Conference on Machine Learning (ICML)*, 2017.