Ultra-Low Accumulation Precision Inference with Block Floating Point Arithmetic

Abstract

Block Floating Point (BFP) quantization offers a hardware-efficient numerical range trade-off. Previous studies have quantized weights and activations to an extremely low precision using the BFP arithmetic. However, as the precision of weights and activations diminishes, we identify that accumulation becomes a hardware bottleneck in the BFP MAC. Nevertheless, existing attempts to decrease the precision of accumulation in matrix multiplication generally preserve model performance through training with a pre-selected, fixed accumulation precision. Nonetheless, selecting an unduly low precision leads to notable performance degradation, and these studies lack an effective approach to establish the lower precision limit, potentially incurring considerable training costs. Hence, we propose a statistical method to analyze the impact of reduced accumulation precision on the inference of deep learning applications. Due to the presence of fixed-point accumulation and floating-point accumulation in BFP matrix multiplication, we formulate a set of equations to relate the data range of fixed-point multiply-accumulate operations and the effects of floating-point swamping to the parameters of BFP quantization, the length of accumulation, model weights, and the minimum number of bits required for accumulation, thereby determining the appropriate accumulation precision. Applied to MMLU Llama2-7B, SQuAD-v1.1 BERT-Large and BERT-Base and CIFAR-10 ResNet-50, our precision settings yield performance close to the FP32 baseline. Meanwhile, further precision reduction degrades performance, indicating our approach's proximity to precision limits. Guided by our equations, the hardware exhibits a 13.7%-28.7% enhancement in area and power efficiency over high-precision accumulation under identical quantization configuration, and it demonstrated a $10.3\times$ area reduction and an $11.0\times$ power reduction compared to traditional BFP implementations.

1 Introduction

Deep learning technology has achieved significant success in a wide range of applications through the training of large-scale deep models with extensive datasets. Concurrently, this approach has imposed substantial storage and computational burdens. Quantization emerges as a promising method to reduce the cost of deep learning by diminishing the bit-width of data flow within models, thereby reducing storage and computational overhead (Deng et al., 2020). As an effective numerical system for deep learning, Block Floating Point (BFP) strikes a favorable balance between dynamic range and hardware cost (Drumond et al., 2018). Specifically, previous studies have demonstrated that low-precision BFP formats can achieve accuracy comparable to FP32 under various deep learning workloads (Darvish Rouhani et al., 2020; Drumond et al., 2018; Soloveychik et al., 2022; Köster et al., 2017; Zhang et al., 2022). However, it is observed that as the quantization precision decreases, accumulation becomes a hardware bottleneck in BFP MAC. As illustrated in Figure 1(b), the area occupied by the accumulation component accounts for 17.8%, 33.7%, and 64.4% for BFP16, BFP8, and BFP4, respectively. Therefore, reducing accumulation precision can further enhance hardware efficiency on top of lowering quantization precision.

In BFP MAC, both fixed-point and floating-point accumulations are present. For fixed-point accumulation, a decrease in precision is accompanied by an increased likelihood of overflow. Previous works have focused on avoiding overflow occurrences or mitigating their impact (Colbert et al., 2023; Ni et al., 2020; Xie et al., 2020; Li et al., 2022). Nevertheless, methods to mitigate the impact

of overflow are not guaranteed to maintain accuracy when overflows occur frequently. Hence, we employ the 3σ principle to predict data ranges and select accumulation precision to prevent overflow permanently. For floating-point accumulation, the phenomenon of swamping (Higham, 1993) becomes more pronounced as precision decreases. Previous work has attempted to correlate the numerical precision loss and model performance degradation due to saturation through variance (Wang et al., 2018; Sakr et al., 2019). Differently, our focus is on the inference process, and we establish an analytical connection between accumulation bit-width and model performance loss using the Frobenius norm (Suh et al., 2022; Yuan et al., 2020) as a bridge.

Based on the derived formula, we analyze and determine the appropriate floating-point accumulation precision. In our investigation of the formula for floating-point accumulation precision, we identify the accumulation length as the most critical factor. Drawing on this observation, we propose a segmented accumulation method to further reduce accumulation precision. Through experimentation, we validate the effectiveness of the determined accumulation precision under various model and quantization configurations. Moreover, we have implemented the theoretically derived accumulation precision in hardware, achieving up to 13.7%-28.7% improvement in area and power compared to high-precision accumulation under the same quantization setting and nearly $10\times$ improvement in area and power consumption compared to high-precision accumulation in BFP16 MAC.

Our work presents theoretical and practical advancements. Firstly, we introduce a theoretical approach for establishing the minimum fixed-point accumulation bit-width based on variance and mean, prioritizing overflow avoidance. Secondly, we define the Frobenius norm retention rate (FnRR) as a metric linking floating-point accumulation precision to model performance. Our analysis indicates that the accumulation length serves as a pivotal determinant in the precision selection process. Consequently, we employ a segmented accumulation technique to further reduce precision. Thirdly, we demonstrate the validity of the accumulation precision boundary through experiments. Following this, we design BFP multiply-accumulators in accordance with the established boundaries and assess the enhancements in area and power efficiency.

(a) BFP MAC   (b) Area Analysis   (c) Three Varieties of Swamping

(d) BFP format and BFP matrix multipication

Figure 1: (a)A schematic diagram of the BFP MAC unit, (b)Area Analysis of Baseline BFP-MAC. (c)The distinctions among three swamping phenomena When $m_{acc} = 5$ and $m_p = 4$. (d) illustrates a simple demonstration of the data flow in BFP matrix multiplication with a block size of 2.

2   RELATED WORK AND BACKGROUND

2.1   RELATED WORK

Our work endeavors to establish a theoretical framework for determining the boundary of accumulator bit-width for the BFP format. Although this topic has not been previously discussed, there has been extensive exploration of fixed-point accumulator bit-width and floating-point accumulator bit-width.

Fixed-point accumulator bit-width WrapNet (Ni et al., 2020) leverages the cyclic nature of integer computer arithmetic by inserting a differentiable cyclic activation function, rendering neural networks robust to integer overflow. This allows for the selection of ultra-low-precision fixed-point accumulator bit-width. However, they also note that high overflow rates can lead to training instability. A2Q (Colbert et al., 2023) adheres to the principle of avoiding overflow and approach the determination of fixed-point accumulator bit-width boundaries from both the data type and weight perspectives. Xie et al. introduce a quantization range mapping factor α to maximize data representation capabilities while avoiding overflow under a specified accumulator bit-width (Xie et al., 2020). While their training method can ensure model accuracy at an appropriate accumulator bit-width, they do not provide an efficient approach to determine the boundary of the accumulator bit-width.

Floating-point accumulation bit-width Wang et al. illustrate that the phenomenon of swamping significantly limits the potential for reducing accumulation precision (Wang et al., 2018). To address this issue, they propose two novel techniques: chunk-based accumulation and floating-point stochastic rounding. These methods allow for the training of Deep Neural Networks (DNNs) even when the accumulation bit-width is decreased to FP16, thereby circumventing the constraints imposed by swamping. Additionally, Sakr et al. establish a connection between the decrease in accumulation precision and the training efficiency of DNNs by examining how the exacerbation of swamping phenomena, due to reducing accumulation precision, affects the variance of matrix multiplication outcomes (Sakr et al., 2019). Based on this analysis, they select an appropriate accumulation bit-width.

2.2 BFP Format, BFP Quantization and BFP MAC

BFP format is a numerical representation method wherein a group of data shares one exponent. Quantization methods that adhere to this data format can be classified as fixed-point uniform quantization (Jacob et al., 2018). Fixed-point uniform quantization can be categorized into multiple levels of methods based on the granularity of quantization. Quantization granularity varies, with per-tensor being the coarsest, using a single scaling factor for the entire matrix. Finer granularity is achieved through per-channel or per-token scaling. Block-wise quantization further refines this by dividing channels or tokens into blocks with a step size, yielding BFP quantization as a distinct variant with scaling factors as powers of two. Therefore, BFP quantization (Rouhani et al., 2023; Darvish Rouhani et al., 2023) can be expressed as:

$$\mathbf{X}_q = \lceil \frac{\mathbf{X}}{2^s} \rfloor, s = max(\lfloor \log_2^{|\mathbf{X}|} \rfloor) - N + 1 \tag{1}$$

where $\lceil \cdot \rfloor$ is the rounding function, $\mathbf{X}$ is the object to be quantized, $\mathbf{X}_q$ is the corresponding quantized result, s is the scaling factor obtained through quantization, and N is the number of bits used for the low-precision representation.

The BFP multiplier-accumulator architecture is bifurcated into two primary modules: the INT-MAC (Integer Multiply and Accumulate) and the FP-ACC (Floating Point Accumulate). The INT-MAC comprises a set of signed fixed-point multipliers, an addition tree, and an exponent summing adder, corresponding to the fixed-point multiplication and accumulation within the BFP inner product. This phase is termed **intra-block** computation. Conversely, the FP-ACC module includes normalization, an exponent alignment unit, an adder, and a fixed-to-floating-point conversion block, handling the floating-point accumulation of the BFP inner product. This stage is identified as **inter-block** computation. In Figure 1(d), we elucidate the implications of BFP format, intra-block and inter-block operations using a straightforward example. SE denotes the shared exponent, A and B represent the two matrices involved in the matrix multiplication computation, respectively, C denotes the resulting matrix, INT signifies the fixed-point result after intra-block fixed-point accumulation, and F indicates the number that has been normalized and is ready for floating-point accumulation.

3 Motivation

3.1 Hardware Bottleneck Analysis

The BFP MAC can be broadly categorized into fixed-point multiplication, fixed-point addition, and floating-point addition, corresponding to INT-MUL, INT-ACC, and FP-ACC as depicted in Figure

1(d). When weights and activations are quantized at a higher precision, INT-MUL constitutes the predominant area due to the inclusion of K (where K represents the block size) high-precision fixed-point multipliers. However, when weights and activations are quantized at an ultra-low precision, INT-MUL requires only ultra-low precision fixed-point multipliers, whereas the high-precision INT-ACC and FP-ACC become the primary area overhead. As illustrated in the Figure 1(b), in the BFP4 MAC with K=16, the area allocated to accumulation reaches 64.4%, indicating that reducing the precision of accumulation could yield significant hardware efficiency gains in this scenario.

3.2 MEAN, VARIANCE AND THE FROBENIUS NORM

Accumulation overflow is a critical issue to be addressed in the context of fixed-point quantization, which can have a significant impact on model performance. As shown in the Table 1, we observe that minor overflow rates cause slight performance decline, but increased rates lead to significant degradation in model performance. In the design of the MAC unit, it is common practice to calculate the theoretical maximum data range that the partial sums can reach based on the input data format to prevent overflow. Equation 2 is a formula for calculating the maximum bit width required for the partial sums based on the input data format. Here, both A and W are signed numbers.

$$K(2^{min(A_{width}-1, W_{width}-1)} - 2^{A_{width}+W_{width}-2}) \leq Partial\,Sum \leq K2^{A_{width}+W_{width}-2} \quad (2)$$

In deep learning models, partial sums rarely reach the theoretical extreme values because it is nearly impossible for all input tensors to be quantized to the extreme values. Consequently, the range derived from Equation 2 typically exceeds the actual data distribution. By the 3σ principle, the vast majority of data falls within $(\mu - 3\sigma, \mu + 3\sigma)$. Thus, bounding the partial sums by their mean and variance can mitigate data range wastage.

In the inference phase of deep learning models, the FP32 precision matrix multiplication is regarded as the benchmark for state-of-the-art performance. The inference quality is inferred to be superior when the outcomes of matrix multiplications using alternative precisions are closer to the FP32 results. Consequently, the challenge of correlating data precision with model accuracy can be reframed as one of determining the proximity between the reduced-precision result matrix and the FP32 precision result matrix. For this purpose, we focus on numerical approximation and employ the Frobenius norm (Suh et al., 2022; Yuan et al., 2020) as the metric for comparison.

Table 1: Average overflow rate for BERTbase in different accumulation widths and corresponding EM and F1-score on the SQuAD-v1.1 question-answering task

Bit(A/W)	Accumulation Width	Average Overflow Rate	EM	F1
6/6	10	6.710%	2.4976	10.939
6/6	12	0.017%	75.639	83.938
6/6	24	0	78.978	86.667
8/8	14	7.894%	2.6584	11.302
8/8	16	0.025%	78.912	86.653
8/8	24	0	78.836	86.664

4 ACCUMULATION PRECISION ANALYSIS

In BFP format inner product computations, the process is divided into intra-block and inter-block stages. We ensure ample allocation for both the intra-block shared exponent width and the inter-block floating-point exponent width(We chose to allocate 8 bits like Microscaling(Rouhani et al., 2023)). Our research focuses on estimating the mean and variance of block-wise partial sums to determine the bit width for fixed-point multiplication and accumulation, and on relating the Frobenius norm to the mantissa precision of inter-block accumulations.

4.1 INTRA-BLOCK PARTIAL SUM MEAN AND VARIANCE ANALYSIS

Intra-block multiplication and accumulation refers to the process of performing multiplication and accumulation operations on weight elements(W_e) and input elements(I_e) that have been quantized using the BFP format. We note (with observations detailed in Appendix E) that the weights and

inputs participating in matrix multiplication are approximately distributed according to a Laplace distribution. To facilitate analysis, we hypothesize that the inputs conform to a Laplace distribution with a location parameter of 0 and a scale parameter of 1(The W and I below represent the original weights and inputs, respectively). Hence, we have $\mathbb{E}[I] = 0$. Furthermore, since BFP quantization is an unbiased estimator, it follows that $\mathbb{E}[I_e] = \mathbb{E}[I] = 0$. Additionally, W_e and I_e are independent of each other, and thus $\mathbb{E}[I_e \cdot W_e] = \mathbb{E}[I_e] \cdot \mathbb{E}[W_e] = 0$. Consequently, we can estimate the mean of the partial sums within the block to be 0. The variance calculation formula for the dot product terms within the block is as follows:

$$\mathrm{Var}[I_e \cdot W_e] = \mathbb{E}[I_e^2] \cdot \mathbb{E}[W_e^2] - \mathbb{E}[I_e]^2 \cdot \mathbb{E}[W_e]^2 \tag{3}$$

From the aforementioned analysis, we know that $\mathbb{E}[I_e] = 0$, thus we can express the variance as

$$\mathrm{Var}[I_e \cdot W_e] = \mathrm{Var}[I_e] \cdot \mathbb{E}[W_e^2] \tag{4}$$

According to the assumptions made in the preceding text, we can determine $\mathrm{Var}[I]$, $\mathbb{E}[W^2]$ and the mean of the shared exponent(How to calculate $\mathbb{E}[exp]$ is provided in the appendix A).

$$\mathrm{Var}[I_e] = \frac{\mathrm{Var}[I]}{2^{2(\mathbb{E}[I_{exp}]-bit+1)}}, \quad \mathbb{E}[W_e^2] = \frac{\mathbb{E}[W^2]}{2^{2(\mathbb{E}[W_{exp}]-bit+1)}} \tag{5}$$

With the mean and variance of the partial sums within the block, according to the 3σ principle, we consider each inner product term obtained from the intra-block inner product to fall within the range of $(-3\sigma, 3\sigma)$. Consequently, the range of the partial sums is $(-3K\sigma, 3K\sigma)$, where K is the number of terms in the sum. At this point, we can estimate the bit width required for fixed-point multiplication and accumulation. We have visualized the estimated bit width in the Figure 2.

Figure 2: Intra-block Fixed-Point Accumulation Precisions for Llama2-7B

Figure 3: Intra-block Fixed-Point Accumulation Precisions for Llama2-7B

4.2 Inter-Block Accumulation Mantissa Precision Analysis

Let p_i represent the i-th term for inter-block accumulation, s_i denote the partial sum obtained from the i-th inter-block accumulation, m_p and m_{acc} correspond to the mantissa bit widths for p_i and s_i, respectively, and n denotes the length of the accumulation. Our key contribution lies in the proposal of a formula,

$$FnRR = \sqrt{\frac{\mathbb{E}[S_{n\,swamping}^2]}{\mathbb{E}[S_{n\,ideal}^2]}} \tag{6}$$

which correlates mantissa precision with model performance, where FnRR is a function of n, m_p, m_{acc}, $\mathbb{E}[W]$, $\mathrm{Var}[W]$ and K, all precomputable parameters. In order to maintain performance under reduced precision, we aim for $FnRR \to 1$. As illustrated in the Figure 3, it can be observed intuitively that once m_p, $\mathbb{E}[W]$, $\mathrm{Var}[W]$, and K are determined, the FnRR at a fixed mantissa precision is a waterfall-like curve with respect to the accumulation length n. The accumulation length for FnRR is limited due to potential mantissa truncation caused by floating-point alignment during addition. This overflow leads to loss of significant digits, necessitating the introduction of

"swamping" to analyze its impact on FnRR performance. As illustrated in the Figure 1(c), a single floating-point addition can be categorized into three scenarios: 1) "no swamping", which occurs when $|s_i| \leq 2^{m_{acc}-m_p}|p_{i+1}|$. 2) "full swamping," which occurs when $|s_i| > 2^{m_{acc}}|p_{i+1}|$. 3) "partial swamping," which occurs when $2^{m_{acc}-m_p}|p_{i+1}| < |s_i| \leq 2^{m_{acc}}|p_{i+1}|$. Subsequently, we will establish a connection between the Frobenius norm and the mantissa precision of inter-block summation from the perspective of swamping.

Theorem 1. The FnRR, Using n, m_p, and m_{acc} to denote the accumulation length, the mantissa precision of accumulation terms, and the mantissa precision of the partial sum, respectively, $\sigma = \sqrt{K \text{Var}[I \cdot W]}$ where K and $\text{Var}[W]$ are the block size for BFP quantization and the average variance of the weights selected from large models participating in quantization, is given as follows:

$$
FnRR = \sqrt{\frac{\sum_{i=1}^{n} P(A_i)\mathbb{E}[S_{i\,swamping}^2] + P(B)\mathbb{E}[S_{n\,swamping}^2]}{n\sigma^2}}
$$

$$
P(A_i) = \begin{cases} 2Q(\dfrac{2^{m_{acc}+1}}{\sqrt{2\pi}}), i = 1 \\ 2Q(\dfrac{2^{m_{acc}+1}}{\sqrt{2i\pi}}) \prod_{j=1}^{i-1}(1 - 2Q(\dfrac{2^{m_{acc}+1}}{\sqrt{2j\pi}})), i = 2, 3, \ldots, n-1 \end{cases},
$$

$$
P(B) = \prod_{j=1}^{n}(1 - 2Q(\dfrac{2^{m_{acc}+1}}{\sqrt{2j\pi}})), \quad \mathbb{E}[S_{n\,swamping}^2] = n\sigma^2 - \sum_{i=1}^{n}\mathbb{E}[f_i^2],
$$

$$
\mathbb{E}[f_i^2] = \sum_{j=1}^{m_p} P(C_{ij})\mathbb{E}[f_{ij}^2], \quad P(C_{ij}) = Q(\dfrac{2^{m_{acc}-j+m_p+1}}{\sqrt{2i\pi}}) - Q(\dfrac{2^{m_{acc}-j+m_p+2}}{\sqrt{2i\pi}}),
$$

$$
\mathbb{E}[f_{ij}^2] = \dfrac{2^{-2m_p-1}}{3}(2^j - 1)(2^{j+1} - 1)\mathbb{E}[2^{exp}]^2.
$$

(7)

The proof of this theorem is provided in the appendix B. Using Theorem 1, we endeavor to analyze the relationship between the precision of accumulation and the length of the cumulative process. When we set a very large m_{acc}, $P(A_i)$ will be close to 0, while $P(B)$ will be close to 1 and $\mathbb{E}[S_{n\,swamping}^2]$ will be close to $n\sigma$, which causes $FnRR \to 1$ as expected when the mantissa is maintained at high precision. When we set a very small m_{acc}, $P(B)$ will be close to 0, and $\mathbb{E}[S_{n\,swamping}^2]$ will be approximately equal to the sum of $P[A_i]\mathbb{E}[S_{i\,swamping}^2]$. When i is large, $P[A_i]$ will be close to 0. Consequently, in this case, $\mathbb{E}[S_{n\,swamping}^2]$ will be approximately equal to the sum of the first few terms of $P[A_i]\mathbb{E}[S_{i\,swamping}^2]$ when i is small. In other words, as n increases, $\mathbb{E}[S_{n\,swamping}^2]$ will remain largely unchanged after an initial increase, leading FnRR to rapidly approach 0 as n increases. This indicates that with limited precision, there is little hope of maintaining computational accuracy when the length of accumulation is large. Similarly, because FnRR exhibits a clear trend from 1 to 0 as n increases at a fixed accumulation precision, FnRR can provide a definitive decision boundary for the accuracy of accumulation.

4.3 PARAMETER SIGNIFICANCE ANALYSIS

Within Theorem 1, the computation of FnRR is influenced by four parameters: n, m_p, m_{acc}, and σ, each exerting a distinct level of influence on the resulting calculation. Firstly, analyzing the parameter sigma reveals that $\mathbb{E}[2^{exp}]^2$ is approximately equal to σ^2, leading to $\mathbb{E}[S_{n\,swamping}^2] = f(n, m_p, m_{acc})\sigma^2$. Consequently, σ has negligible impact on the computation of FnRR. Subsequently, we observe that the parameter m_p is only employed in the calculation of $\mathbb{E}[f_i^2]$, and through scaling, we find that $\mathbb{E}[f_i^2] < \frac{\sigma^2}{6}$ (the proof of this conclusion is provided in the appendix C). Therefore, the parameter m_p can, at most, decrease $\mathbb{E}[S_{n\,swamping}^2]$ to $\frac{5}{6}\mathbb{E}[S_{n\,ideal}^2]$, which in turn reduces FnRR to around 0.913 at its lowest. The impact of m_p on the computation of FnRR is similarly insignificant. In summary, given a fixed mantissa precision, m_{acc}, n is the predominant factor influencing the calculation of FnRR.

4.4 MANTISSA PRECISION ANALYSIS IN SEGMENTED INTER-BLOCK ACCUMULATION

As established in Section 4.3, the accumulation length n is the most critical factor affecting the precision of inter-block accumulation. To achieve a lower inter-block accumulation precision while minimizing additional hardware overhead, a segmented approach to accumulation is adopted. Assuming $n = n1 \times n2$, the floating-point accumulation of length n is segmented into n2 accumulations of length n1, which are then summed to yield the final computational result. Both segments of floating-point accumulation utilize the same mantissa precision to allow for the reuse of the floating-point addition unit. The proof of the formula is provided in the appendix D.

Theorem 2. Using a segmented accumulation method with $n = n1 \times n2$, where n1 is the segment length and n2 is the number of segments, the FnRR, with m_p and m_{acc} as the mantissa precision for the accumulation terms and partial sums, respectively, is provided in the subsequent sections:

$$FnRR_{segment} = FnRR(n1, m_p, m_{acc}, \sigma_{n_1}) \times FnRR(n2, m_{acc}, m_{acc}, \sigma_{n_2}) \tag{8}$$

4.5 USAGE OF THEOREM

We can ascertain the suitability of a certain inter-block accumulation precision by calculating its FnRR and evaluating its degree of convergence to 1, thereby predicting the most appropriate accumulation precision. The results indicate that when measured as a function of the accumulation length n with a fixed precision, there exists a breakdown region for FnRR. This breakdown region is clearly observable when considering the normalized exponential loss:

$$f(n) = e^{n(1-FnRR)} \tag{9}$$

In the Figure 4, we plot the $f(n)$ values at different inter-block accumulation precisions with ac-

(a) No Segmented Accumulation   (b) Segmented Accumulation

Figure 4: (a) and (b) utilizes weight information from the Llama2-7B, with a block size of K equal to 32. The dashed line indicates the location of the breakdown point. It is readily apparent that below the dashed line, $f(n)$ rapidly approaches 1, whereas above it, $f(n)$ increases swiftly.

cumulation using segments of length 32 and no segmented accumulation. Here, we set m_p to 9 (in practical applications, we can determine the corresponding m_p value using the method described in section 4.1), and we use the weight data from Llama2-7B (Touvron et al., 2023) to calculate the FnRR. We can observe that $f(n)$ increases rapidly when it exceeds 1000, and it quickly approaches 1 when it is below 1000. Consequently, we select 1000 as the point of breakdown, such that accumulation precisions resulting in $f(n)$ values less than 1000 are considered suitable precisions.

5 EXPERIMENTS

5.1 EXPERIMENT SETUP

Through the aforementioned analysis, we predict the intra-block multiplication and accumulation bit widths, the inter-block accumulation mantissa bit widths, and the inter-block segmented accu-

mulation mantissa bit widths required for inference under different quantization configurations and segment lengths for the models (Llama2-7B, BERT-Large-Cased, BERT-Base-Cased, ResNet-50). We select these models due to their long accumulation lengths and because they belong to different applications, thereby enabling them to effectively validate our work. We aim to: 1) assess overflow occurrence in intra-block multiplication and accumulation at predicted precision, 2) evaluate and compare model performance with inter-block accumulation at predicted precision to FP32 baseline, and 3) evaluate and compare model performance with inter-block segmented accumulation at predicted precision to FP32 baseline. We employ MMLU (Hendrycks et al., 2020) testing to evaluate the performance of Llama2-7B, for BERT-Large-Cased and BERT-Base-Cased (Devlin et al., 2018), we use the SQuAD-v1.1 dataset (Rajpurkar et al., 2016) to finetuning and evaluate and for ResNet-50 (He et al., 2016), we use the CIFAR-10 (Krizhevsky et al., 2009) dataset to train and evaluate. Specifically, we utilize the Microsoft open-source MX Pytorch Emulation Library for quantization and choose 8-bit as the BFP quantization and accumulation exponent bit width.

To discuss the overflow situation of block-wise multiplication and accumulation and to implement the rounding of the partial sum during the inter-block accumulation process, we implement the BFP-format GEMM using PyTorch and CUDA, and we have inserted a rounding function at the location of partial sum accumulation to simulate the reduction in bit width.

5.2 OVERFLOW RATE IN INTRA-BLOCK OPERATIONS

We utilize the SQuAD-v1.1 to assess the model performance of BERT-Large and BERT-Base and the CIFAR-10 to assess the model performance of ResNet-50 following precision reduction. During inference, the matrix multiplication operations are then processed in BFP format, and the frequency of overflow events during computation is recorded to calculate the overflow rate. The results are presented in Table 2. BERT-Large and BERT-Base are evaluated using SQuAD-v1.1 across 48 topics, and the overflow rate is 0 in all cases. ResNet-50 is evaluated using CIFAR-10 and the overflow rate is also 0 in all cases. The experimental results confirm that no overflow occurs at the predicted fixed-point accumulation precision.

Table 2: The OR in this table represents the overflow rate. The data in the tuple is the result of BERT-Large and BERT-Base in SQuAD-v1.1 and ResNet-50 in CIFAR-10, respectively

Precision	Block Size	Baseline Bit Width	Prediction Bit Width	Average OR
BFP8	128	23	20	(0,0,0)
	64	22	20	(0,0,0)
	32	21	19	(0,0,0)
BFP4	64	14	12	(0,0,0)
	32	13	11	(0,0,0)
	16	12	11	(0,0,0)

5.3 MODEL PERFORMANCE UNDER REDUCED INTER-BLOCK ACCUMULATION PRECISION

Table 3: The predicted inter-block accumulation bit width for our considered networks. Each table entry is an ordered tuple representing the bit widths for Llama2-7B, BERT-Large and ResNet-50, respectively. '-' signifies that we do not conduct tests on this quantitative configuration.

Block Size	8	16	32	64	128
BFP4	(-,7,-)	(7,6,6)	(7,5,6)	(6,5,5)	(-,-,-)
BFP4(Seg)	(-,4,-)	(5,4,4)	(4,3,3)	(4,3,3)	(-,-,-)
BFP8	(-,-,-)	(-,-,-)	(7,5,6)	(6,5,5)	(5,4,4)
BFP8(Seg)	(-,-,-)	(-,-,-)	(4,3,3)	(4,3,3)	(3,2,2)

The predicted bit width for each network and quantization precision are listed in Table 3 for the case of BFP and BFP segmented accumulation with the segment length calculated by $\sqrt{n}$. To elucidate that the inter-block accumulation precision identified by our method is precisely at the critical point, or as close as possible to the critical point while ensuring model performance (the critical point refers to the threshold at which a significant degradation in model performance is imminent), we evaluate the model performance under multiple sets of different accumulation precisions for each selected

model under various quantization configurations. Figure 5 reveals that as the accumulation precision decreases, there is a pronounced decline in model performance at the critical point. However, it is worth noting that when the accumulation precision is higher than the precision at the critical point, the change in model performance is not monotonic; it oscillates within a narrow range. This implies that there is no linear correlation between model performance and accumulation precision, as performance fluctuates around a certain level within a specific range of accumulation precision. When the accumulation precision is reduced below the critical point, there is a marked deterioration in model performance, which is consistent with the properties of FnRR.

(a) No Segmented Accumulation results for Llama2-7B (b) Segmented Accumulation results for Llama2-7B

(c) No Segmented Accumulation results for BERTlarge (d) Segmented Accumulation results for BERTLarge

(e) No Segmented Accumulation results for ResNet-50 (f) Segmented Accumulation results for ResNet-50

Figure 5: The horizontal axis represents the inter-block accumulation precision, while the vertical axis indicates the score for the corresponding task. The dashed lines in the graphs denote the Baseline performance under the respective quantization configurations

5.4 MODEL PERFORMANCE UNDER REDUCED INTER-BLOCK SEGMENTED ACCUMULATION PRECISION

We select $\lfloor \sqrt{n} \rfloor$ as the segment length and evaluated the model performance under multiple sets of different accumulation precisions for each chosen model under every quantization configuration. Figure 5 demonstrates that as the accumulation precision decreases, there is a marked decline in model performance at the critical point. Furthermore, we can also find that employing segmented accumulation allows for at least a 1-bit reduction in precision while maintaining equivalent model performance compared to the no segmented accumulation method. In particular, the segmented

accumulation precision of 5 bits for BFP4 quantization of Llama2-7B with a block size of 16 outperforms the non-segmented method with a precision of 9 bits, achieving at least a 4-bit reduction. Both segmented and non-segmented methods at the predicted precision maintain performance close to the baseline, demonstrating the efficacy of our method in identifying minimal accumulation precision without substantial performance degradation.

5.5 HARDWARE IMPLEMENTATION

We utilize the formula derived in the preceding section to predict the accumulation precision for the Llama2-7B model with a block size of 16, for both BFP4 and BFP8 quantization precisions. The hardware design is completed based on the obtained accumulation precision, and we evaluate the area and power consumption using synthesis tools. As indicated in the evaluation, in terms of area, the BFP4 and BFP8 quantization precisions result in reductions of 28.7% and 13.8%, respectively. Notably, the reduction in area for the FP-ACC and Other components is significant. However, the area optimization for the INT-MAC is not pronounced due to the multitude of multiplier units, which do not decrease in area with the reduction in accumulation precision. Regarding power consumption, the BFP4 and BFP8 quantization precisions lead to decreases of 25.2% and 13.7%, respectively. Additionally, compared to the BFP16 Baseline, our optimized implementation of the BFP MAC at lower precision achieves significant improvements in area and power consumption, reaching up to $10.3\times$ and $11.0\times$ respectively.

Table 4: Analysis of area and power with varying quantization precisions, with the bolded segment reflecting area and power data derived from hardware design utilizing formula-predicted accumulation precision, contrasted with the non-bolded segment which is based on conventional accumulation precision for hardware design.

(a) Area Analysis

Quantization Type	INT-MAC (μm^2)	FP-ACC (μm^2)	Other (μm^2)	Total (μm^2)
BFP4	142.54	133.34	38.90	314.78
	126.20 (↓11.5 %)	**74.80 (↓44.0%)**	**23.56 (↓39.4%)**	**224.56 (↓28.7%)**
BFP8	619.07	147.84	49.09	816.00
	584.47 (↓11.4%)	**90.11 (↓39.0%)**	**28.93 (↓41.1%)**	**703.51 (↓13.8%)**

(b) Power Analysis		(c) Comparison with the BFP16 baseline		
Quantization Type	Power (mW)	Quantization Type	Area (μm^2)	Power (mW)
BFP4	0.2208	BFP4	**224.56**	**0.1652**
	0.1652 (↓25.2%)	BFP16	2311.6 (10.3×)	1.8204 (11.0×)
BFP8	0.5933	BFP8	**703.51**	**0.5122**
	0.5122 (↓13.7%)	BFP16	2311.6 (3.29×)	1.8204 (3.55×)

6 CONCLUSION

We present an analytical approach to predict the optimal accumulation precision for BFP GEMM operations in deep learning inference, balancing performance with precision. Our experiments confirm that this precision is near the limit while maintaining comparable performance to the baseline. Additionally, we demonstrate the effectiveness of segmented accumulation in further reducing floating-point precision. An interesting phenomenon is observed, where the decline in model performance with decreasing accumulation precision varies under different quantization configurations. Notably, highly quantized models exhibit a lower robustness and are more susceptible to reaching the precision boundary. Therefore, incorporating the impact of quantization on model robustness into our theoretical analysis could further improve our theoretical framework. We believe that our work provides theoretical support for the design of MAC units in deep learning inference.

REFERENCES

Ian Colbert, Alessandro Pappalardo, and Jakoba Petri-Koenig. A2q: Accumulator-aware quantization with guaranteed overflow avoidance. In *Proceedings of the IEEE/CVF International Conference on Computer Vision*, pp. 16989–16998, 2023.

Bita Darvish Rouhani, Daniel Lo, Ritchie Zhao, Ming Liu, Jeremy Fowers, Kalin Ovtcharov, Anna Vinogradsky, Sarah Massengill, Lita Yang, Ray Bittner, et al. Pushing the limits of narrow precision inferencing at cloud scale with microsoft floating point. *Advances in neural information processing systems*, 33:10271–10281, 2020.

Bita Darvish Rouhani, Ritchie Zhao, Venmugil Elango, Rasoul Shafipour, Mathew Hall, Maral Mesmakhosroshahi, Ankit More, Levi Melnick, Maximilian Golub, Girish Varatkar, et al. With shared microexponents, a little shifting goes a long way. In *Proceedings of the 50th Annual International Symposium on Computer Architecture*, pp. 1–13, 2023.

Lei Deng, Guoqi Li, Song Han, Luping Shi, and Yuan Xie. Model compression and hardware acceleration for neural networks: A comprehensive survey. *Proceedings of the IEEE*, 108(4): 485–532, 2020.

Jacob Devlin, Ming-Wei Chang, Kenton Lee, and Kristina Toutanova. Bert: Pre-training of deep bidirectional transformers for language understanding. *arXiv preprint arXiv:1810.04805*, 2018.

Mario Drumond, Tao LIN, Martin Jaggi, and Babak Falsafi. Training dnns with hybrid block floating point. In S. Bengio, H. Wallach, H. Larochelle, K. Grauman, N. Cesa-Bianchi, and R. Garnett (eds.), *Advances in Neural Information Processing Systems*, volume 31. Curran Associates, Inc., 2018. URL https://proceedings.neurips.cc/paper_files/paper/2018/file/6a9aeddfc689c1d0e3b9ccc3ab651bc5-Paper.pdf.

Kaiming He, Xiangyu Zhang, Shaoqing Ren, and Jian Sun. Deep residual learning for image recognition. In *Proceedings of the IEEE conference on computer vision and pattern recognition*, pp. 770–778, 2016.

Dan Hendrycks, Collin Burns, Steven Basart, Andy Zou, Mantas Mazeika, Dawn Song, and Jacob Steinhardt. Measuring massive multitask language understanding. *arXiv preprint arXiv:2009.03300*, 2020.

Nicholas J Higham. The accuracy of floating point summation. *SIAM Journal on Scientific Computing*, 14(4):783–799, 1993.

Benoit Jacob, Skirmantas Kligys, Bo Chen, Menglong Zhu, Matthew Tang, Andrew Howard, Hartwig Adam, and Dmitry Kalenichenko. Quantization and training of neural networks for efficient integer-arithmetic-only inference. In *Proceedings of the IEEE conference on computer vision and pattern recognition*, pp. 2704–2713, 2018.

Urs Köster, Tristan Webb, Xin Wang, Marcel Nassar, Arjun K Bansal, William Constable, Oguz Elibol, Scott Gray, Stewart Hall, Luke Hornof, et al. Flexpoint: An adaptive numerical format for efficient training of deep neural networks. *Advances in neural information processing systems*, 30, 2017.

Alex Krizhevsky, Geoffrey Hinton, et al. Learning multiple layers of features from tiny images. 2009.

Haokun Li, Jing Liu, Liancheng Jia, Yun Liang, Yaowei Wang, and Mingkui Tan. Downscaling and overflow-aware model compression for efficient vision processors. In *2022 IEEE 42nd International Conference on Distributed Computing Systems Workshops (ICDCSW)*, pp. 145–150. IEEE, 2022.

Renkun Ni, Hong-min Chu, Oscar Castañeda, Ping-yeh Chiang, Christoph Studer, and Tom Goldstein. Wrapnet: Neural net inference with ultra-low-resolution arithmetic. *arXiv preprint arXiv:2007.13242*, 2020.

Pranav Rajpurkar, Jian Zhang, Konstantin Lopyrev, and Percy Liang. Squad: 100,000+ questions for machine comprehension of text. *arXiv preprint arXiv:1606.05250*, 2016.

Bita Darvish Rouhani, Ritchie Zhao, Ankit More, Mathew Hall, Alireza Khodamoradi, Summer Deng, Dhruv Choudhary, Marius Cornea, Eric Dellinger, Kristof Denolf, et al. Microscaling data formats for deep learning. *arXiv preprint arXiv:2310.10537*, 2023.

Charbel Sakr, Naigang Wang, Chia-Yu Chen, Jungwook Choi, Ankur Agrawal, Naresh Shanbhag, and Kailash Gopalakrishnan. Accumulation bit-width scaling for ultra-low precision training of deep networks. *arXiv preprint arXiv:1901.06588*, 2019.

Ilya Soloveychik, Ilya Lyubomirsky, Xin Wang, and Sudeep Bhoja. Block format error bounds and optimal block size selection. *arXiv preprint arXiv:2210.05470*, 2022.

Duckhyun Suh, Dong Kyu Lee, Jung Min Pak, and Choon Ki Ahn. Distributed frobenius-norm finite memory interacting multiple model estimation for mobile robot localization. *IEEE Access*, 10:124193–124205, 2022.

Hugo Touvron, Louis Martin, Kevin Stone, Peter Albert, Amjad Almahairi, Yasmine Babaei, Nikolay Bashlykov, Soumya Batra, Prajjwal Bhargava, Shruti Bhosale, et al. Llama 2: Open foundation and fine-tuned chat models. *arXiv preprint arXiv:2307.09288*, 2023.

Naigang Wang, Jungwook Choi, Daniel Brand, Chia-Yu Chen, and Kailash Gopalakrishnan. Training deep neural networks with 8-bit floating point numbers. *Advances in neural information processing systems*, 31, 2018.

Hongwei Xie, Shuo Zhang, Huanghao Ding, Yafei Song, Baitao Shao, Conggang Hu, Ling Cai, and Mingyang Li. Accelerating neural network inference by overflow aware quantization. *arXiv preprint arXiv:2005.13297*, 2020.

Shi-Fang Yuan, Yi-Bin Yu, Ming-Zhao Li, and Hua Jiang. A direct method to frobenius norm-based matrix regression. *International Journal of Computer Mathematics*, 97(9):1767–1780, 2020.

Sai Qian Zhang, Bradley McDanel, and HT Kung. Fast: Dnn training under variable precision block floating point with stochastic rounding. In *2022 IEEE International Symposium on High-Performance Computer Architecture (HPCA)*, pp. 846–860. IEEE, 2022.

A   THE CALCULATION METHOD FOR $\mathbb{E}[exp]$

Let K, μ, σ denote the block size, quantization precision, mean, and variance, respectively, of the matrix selected for BFP quantization. In the main text, we assume that the means of the matrices participating in quantization follow a laplace distribution. The event A_{ei} is defined as having i out of K numbers within a block whose exponent is e, while the exponents of the remaining numbers are all less than e.

$$
L(x, \mu, \gamma) = \begin{cases} 0.5 e^{\frac{x-\mu}{\gamma}}, x < \mu \\ 1 - 0.5 e^{-\frac{x-\mu}{\gamma}}, x \geq \mu \end{cases} \tag{10}
$$

$$
P(A_{ei}) = C_K^i [L(\frac{-2^{e-1}-\mu}{\sigma}) - L(\frac{2^{e-1}-\mu}{\sigma})]^{K-i}
$$
$$
\times [L(\frac{2^{e-1}-\mu}{\sigma}) - L(\frac{2^e-\mu}{\sigma}) + L(\frac{-2^e-\mu}{\sigma}) - L(\frac{-2^{e-1}-\mu}{\sigma})]^i \tag{11}
$$

$$
\mathbb{E}[exp] = \sum_{e=-\infty}^{+\infty} [2^e \sum_{i=1}^{K} P(A_{ei})] \tag{12}
$$

From Equation 12, $E[exp]$ can be calculated. Our experiments have shown that when $e \in (-\infty, -50) \bigcup (50, +\infty)$, $P(A_{ei}) \to 0$. Therefore, Equation (9) can be simplified to

$$
\mathbb{E}[exp] = \sum_{e=-50}^{50} [2^{e-bit+1} \sum_{i=1}^{K} P(A_{ei})] \tag{13}
$$

B   PROOF OF THEOREM 1

First, we present the assumptions that will be utilized in the subsequent derivations.

Assumption 1: BFP quantization does not alter the mean and variance of the matrix and the inner product terms obtained within the block are assumed to be independently and identically distributed.

This assumption is made for the convenience of determining the variance and mean of the floating-point numbers involved in the inter-block accumulation.

Assumption 2: We assume that the accumulation process stops when the first full swamping event occurs.

When full swamping occurs, the partial sum becomes sufficiently large relative to the accumulation terms. Although it is possible to recover from the full swamping event, the impact on the result is negligible.

Assumption 3: We consider that each bit of the mantissa of p_i and s_i is equally likely to be either 0 or 1.

This assumption is made for the convenience of determining the impact of discarding partial mantissa precision on Frobenius norm.

In order to calculate FnRR, we first need to compute the Frobenius norm when swamping occurs. To discuss the impact of swamping events on the Frobenius norm, we define the event A_i as the first occurrence of full swamping during the accumulation process at the i-th accumulation. This definition also implies that full swamping do not happen in the accumulations for $i = 1, 2, \ldots, i - 1$. The event A_i happens if

$$
|S_i| > 2^{m_{acc}} |p_{i+1}| \ \& \ |S_{i'}| \leq 2^{m_{acc}} |p_{i'+1}|, i' = 1, 2, \ldots, i - 1 \tag{14}
$$

To calculate the probability of event A_i occurring, we first need to determine the distribution of S_i and p_i. p_i represents the i-th term in inter-block accumulation, which is essentially the result of a single block-wise multiplication and accumulation. According to Assumption 1, we calculate that $p_i \sim \mathcal{N}(0, K \mathrm{Var}[I \cdot W])$ based on the central limit theorem. Similarly, s_i is the sum of p_i, thus $s_i \sim \mathcal{N}(0, iK \mathrm{Var}[I \cdot W])$. In the subsequent proof, we denote $K \mathrm{Var}[I \cdot W]$ as σ^2.

Next, we aim to calculate the mean of $|p_i|$ to facilitate the computation of the probability of event A_i occurring.

$$\mathbb{E}[p_i] = \int_{-\infty}^{+\infty} |x| \frac{1}{\sqrt{2\pi}\sigma} e^{-\frac{x^2}{2\sigma^2}} d\boldsymbol{x} \tag{15}$$

From Equation 15, we can compute that $\mathbb{E}[p_i] = \frac{2\sigma}{\sqrt{2\pi}}$. Therefore, we can derive the formula for calculating the probability of event A_i occurring.

$$P(A_i) = P(|S_i| > 2^{m_{acc}}\mathbb{E}[|p_i|]) \cdot P(|S_i| \le 2^{m_{acc}}\mathbb{E}[|p_i|]) \tag{16}$$

$$P(A_i) = \begin{cases} 2Q(\dfrac{2^{m_{acc}+1}}{\sqrt{2\pi}}), i = 1 \\ 2Q(\dfrac{2^{m_{acc}+1}}{\sqrt{2i\pi}}) \prod_{j=1}^{i-1}(1 - 2Q(\dfrac{2^{m_{acc}+1}}{\sqrt{2j\pi}})), i = 2, 3, \ldots, n-1 \end{cases} \tag{17}$$

Next, we calculate $\mathbb{E}[S_{n\,swamping}^2]$. First, we observe that partial swamping is possible in every accumulation, and we define the event C_{ij} as the occurrence of stage j partial swamping during the i-th accumulation. Thus, event C_{ij} happens if

$$2^{m_{acc}-j+m_p}|p_{i+1}| < |Si| \le 2^{m_{acc}-j+m_p+1}|p_{i+1}| \tag{18}$$

Similar to the method for calculating the probability of event A_i occurring, we derive the formula for calculating $P(C_{ij})$ as follows:

$$P(C_{ij}) = Q(\frac{2^{m_{acc}-j+m_p+1}}{\sqrt{2i\pi}}) - Q(\frac{2^{m_{acc}-j+m_p+2}}{\sqrt{2i\pi}}) \tag{19}$$

Subsequently, we discuss the loss in Frobenius norm caused by stage j partial swamping. According to Assumption 3, the probability of a truncated bit being either 0 or 1 is equal. Consequently, we can calculate the truncation loss $\mathbb{E}[f_{ij}^2]$ occurring at the i-th accumulation.

$$\mathbb{E}[f_{ij}^2] = 2^{-2m_p+2\mathbb{E}[exp']} \sum_{r=1}^{2^j-1} \frac{r^2}{2^j} \tag{20}$$

Here, $\mathbb{E}[exp']$ represents the mean of the exponent of pi, and its calculation method is similar to that of $\mathbb{E}[exp']$ and will not be elaborated further. Equation 20 can be simplified to:

$$\mathbb{E}[f_{ij}^2] = 2^{-2m_p+2\mathbb{E}[exp']-1} \frac{(2^j-1)(2^{j+1}-1)}{3} \tag{21}$$

After the aforementioned analysis, we can compute the loss $E[f_i^2]$ in the Frobenius norm caused by partial swamping at the i-th iteration and $\mathbb{E}[S_{i\,swamping}^2]$.

$$\mathbb{E}[f_i^2] = \sum_{j=1}^{m_p} P(C_{ij})\mathbb{E}[f_{ij}^2] \tag{22}$$

$$\mathbb{E}[S_{i\,swamping}^2] = i\sigma^2 - \sum_{l=1}^{i} \mathbb{E}[f_l^2] \tag{23}$$

We proceed to discuss the impact of full swamping on the Frobenius norm. As per Assumption 2, when full swamping occurs, the accumulation process is halted. This implies that if full swamping occurs during the i-th accumulation, then $\mathbb{E}[S_{n\,swamping}^2|A_i] = \mathbb{E}[S_{i\,swamping}^2]$. Furthermore, we must also consider the scenario where full swamping does not occur throughout the entire accumulation process. The event B is defined as the absence of full swamping in n accumulations. Event B happens if

$$|S_i| \le 2^{m_{acc}}|p_{i+1}|, i = 1, 2, \ldots, n \tag{24}$$

$$P(B) = \prod_{i=1}^{n}(1 - 2Q(\frac{2^{m_{acc}+1}}{\sqrt{2i\pi}})) \tag{25}$$

In summary,

$$\mathbb{E}[S_{n\,swamping}^2] = \sum_{i=1}^{n} P(A_i)\mathbb{E}[S_{i\,swamping}^2] + P(B)\mathbb{E}[S_{n\,swamping}^2] \tag{26}$$

C   THE CALCULATION OF THE UPPER BOUND OF $\mathbb{E}[f_i^2]$

As indicated by Equation 22, $\mathbb{E}[f_i^2] = \sum_{j=1}^{m_p} P(C_{ij})\mathbb{E}[f_{ij}^2]$. Firstly, we analyze $\mathbb{E}[f_{ij}^2]$, where we observe that $2^{\mathbb{E}[exp']}$ and σ^2 are approximately equal, thus leading to the conclusion that $\mathbb{E}[f_{ij}^2]$ will reach its maximum value $\frac{1-2^{-m_p-1}-2^{-m_p}+2^{-2m_p-1}}{3}\sigma^2$ at $j = m_p$. Therefore, we can infer that $\mathbb{E}[f_i^2] < \frac{\sigma^2}{3}\sum_{j=1}^{m_p} P(C_{ij})$. Furthermore, from Equation 19, we can deduce that $\sum_{j=1}^{m_p} P(C_{ij}) = Q(\frac{2^{m_{acc}+1}}{\sqrt{2i\pi}}) - Q(\frac{2^{m_{acc}++m_p+1}}{\sqrt{2i\pi}})$. Due to $\frac{2^{m_{acc}+1}}{\sqrt{2i\pi}} > 0$, then $Q(\frac{2^{m_{acc}+1}}{\sqrt{2i\pi}}) < \frac{1}{2}$. Therefore,

$$\mathbb{E}[f_i^2] < \frac{\sigma^2}{3}\sum_{j=1}^{m_p} P(C_{ij}) < \frac{\sigma^2}{6} \tag{27}$$

D   PROOF OF THEOREM 2

As readily apparent from Appendix B, the Frobenius norm for an accumulation segment of length n_1 is $\mathbb{E}[S_{n_1\,swamping}^2]$. Let the variance of the data for an accumulation of length n_1 be denoted as σ_{n_1}. Then, the variance σ_{n_2} of the data participating in the accumulation of length n_2 is $n_1\sigma_{n_1}^2[FnRR(n_1, m_p, m_{acc}, \sigma_{n_1})]^2$. Furthermore, since $\mathbb{E}[S_{n_2\,swamping}^2]$ can be approximated as $f(n_2, m_p, m_{acc})\sigma_{n_2}^2$.

Therefore, when employing segmented processing, the calculated result FnRR is:

$$
\begin{aligned}
FnRR_{segment} &= \sqrt{\frac{\mathbb{E}[S_{n_2\,swamping}^2]}{n_1 n_2 \sigma_{n_1}^2}} \\
&= \sqrt{\frac{f(n_2, m_p, m_{acc})n_1\sigma_{n_1}^2[FnRR(n_1, m_p, m_{acc}, \sigma_{n_1})]^2}{n_1 n_2 \sigma_{n_1}^2}} \\
&= FnRR(n1, m_p, m_{acc}, \sigma_{n_1}) \times FnRR(n2, m_{acc}, m_{acc}, \sigma_{n_2})
\end{aligned} \tag{28}
$$

E   DISTRIBUTION OF WEIGHTS AND INPUTS ENGAGED IN MATRIX MULTIPLICATION

Figure 6: Each subplot visually represents the distribution of inputs and weights involved in matrix multiplication, randomly sampled from BERT-Large and ResNet-50, respectively.

F EXPERIMENTAL DATA DETAILS

The following section provides detailed experimental results for the Llama2-7B model and the BERT-Large model.

Table 5: Experimental results of BERT-Large

Accumulation Type	Quantization Precision	Block size	MACC	EM	F1
Segmented	Int8	128	1	26.7833491	38.87238547
			2	82.59224219	89.83467333
			3	83.0179754	90.17436216
			4	82.99905393	90.0823776
			5	83.02743614	90.15831688
			baseline	83.07473983	90.24806709
		64	2	81.1731315	88.76644966
			3	83.31125828	90.47422802
			4	83.11258278	90.26468859
			5	83.12204352	90.17531153
			baseline	83.00851466	90.14101486
		32	2	80.08514664	87.85991477
			3	83.00851466	90.17600147
			4	82.98959319	90.17578653
			5	83.07473983	90.21952718
			baseline	82.9422895	90.13687096
	Int4	64	2	75.97918638	84.91149044
			3	79.65941343	87.93871597
			4	79.98107852	87.91951769
			5	80.01892148	88.02584002
			baseline	80.21759697	88.04287399
		32	2	77.5307474	86.00685635
			3	81.05014191	88.76773415
			4	81.04068117	88.85515301
			5	81.18259224	88.74837737
			baseline	80.76631977	88.3953108
		16	3	81.38126774	89.07330911
			4	81.89214759	89.31319864
			5	82.09082308	89.35924713
			6	81.78807947	89.33690702
			baseline	81.9205298	89.24148335
No Segmented	Int8	128	2	80.66225166	88.54197033
			3	82.96121097	90.13992802
			4	82.85714286	90.10981381
			5	83.19772942	90.27249646
			6	83.07473983	90.16693299
			baseline	83.07473983	90.24806709
		64	2	68.17407758	78.34952856
			3	83.20719016	90.2162814
			4	83.13150426	90.22209627
			5	83.03689688	90.18009902
			6	83.05581835	90.15458593
			baseline	83.00851466	90.14101486
		32	3	81.40964995	89.00883392
			4	83.18826868	90.22166107
			5	83.23557237	90.30179041
			6	83.0179754	90.15239831
			7	82.95175024	90.10275076
			baseline	82.9422895	90.13687096
	Int4	32	3	79.89593188	87.91187527
			4	81.13528855	88.73624887

Table 5: Experimental results of BERT-Large

Accumulation Type	Quantization Precision	Block size	MACC	EM	F1
No Segmented	Int4	32	5	81.39072848	89.14670902
			6	81.22989593	88.91816976
			7	81.25827815	88.8771247
			baseline	80.76631977	88.3953108
		16	3	76.06433302	84.96533694
			4	81.60832545	89.20004361
			5	81.49479659	89.06459835
			6	81.8448439	89.37870505
			7	82.03405866	89.51293669
			baseline	81.9205298	89.24148335
		8	6	81.63670766	89.23406472
			7	82.33680227	89.75195921
			8	82.28949858	89.70555447
			9	82.28949858	89.70555447
			baseline	82.17596973	89.56697393

Table 6: Experimental results of Llama2-7B

Accumulation Type	Quantization Precision	Block size	MACC	MMLU	MMLU-weighted
Segmented	Int8	128	2	29.64	29.45
			3	34.31	33.77
			4	35.11	34.52
			5	35.29	34.82
			baseline	35.25	34.89
		64	3	33.21	32.87
			4	34.39	33.93
			5	35.01	34.49
			6	35.24	34.95
			baseline	35.46	35.07
		32	3	33.04	32.38
			4	34.94	34.72
			5	34.76	34.38
			6	35.27	34.8
			baseline	35.53	35.1
	Int4	64	3	28.31	28.2
			4	29.49	29.31
			5	30.28	30.07
			6	29.54	29.04
			baseline	29.4	28.99
		32	3	28.31	27.92
			4	30.34	29.9
			5	29.71	29.96
			6	31.5	30.76
			baseline	31.13	30.95
		16	4	30.75	30.39
			5	31.85	31.63
			6	32.16	31.63
			7	32.11	31.51
			baseline	31.96	31.7
No Segmented	Int8	128	4	33.6	33.31
			5	35.34	34.89
			6	34.92	34.49
			7	35.04	34.72
			baseline	35.25	34.89
		64	5	34.59	34.11

Table 6: Experimental results of Llama2-7B

Accumulation Type	Quantization Precision	Block size	MACC	MMLU	MMLU-weighted
No Segmented	Int8	64	6	35.48	35.21
			7	35.38	35.02
			8	35.37	35.02
			baseline	35.46	35.07
		32	6	35.08	34.57
			7	35.39	34.93
			8	35.52	35.02
			9	35.51	35.01
			baseline	35.53	35.1
	Int4	64	5	28.21	28.01
			6	28.7	28.34
			7	29.44	29.55
			8	29.63	29.8
			baseline	29.4	28.99
		32	6	28.29	28.3
			7	30.25	30.02
			8	30.72	29.92
			9	30.72	29.92
			baseline	31.13	30.95
		16	6	26.04	25.79
			7	29.31	29.3
			8	31.23	30.52
			9	31.3	30.57
			baseline	31.96	31.7

Table 7: Experimental results of ResNet-50

Accumulation Type	Quantization Precision	Block size	MACC	Top1 ACC
Segmented	Int8	128	1	0.138
			2	0.8905
			3	0.912
			4	0.9135
			baseline	0.9132
		64	2	0.8324
			3	0.9127
			4	0.9126
			5	0.9141
			baseline	0.9135
		32	2	0.6762
			3	0.9104
			4	0.9141
			5	0.9145
			baseline	0.9142
	Int4	64	2	0.8039
			3	0.8722
			4	0.8693
			5	0.8705
			baseline	0.875
		32	2	0.6407
			3	0.8847
			4	0.8832
			5	0.8837
			baseline	0.8868
		16	2	0.2078
			3	0.8823

Table 7: Experimental results of ResNet-50

Accumulation Type	Quantization Precision	Block size	MACC	Top1 ACC
Segmented	Int4	16	4	0.8898
			5	0.8891
			baseline	0.8841
No Segmented	Int8	128	2	0.6714
			3	0.9062
			4	0.9135
			5	0.9135
			baseline	0.9132
		64	3	0.869
			4	0.9122
			5	0.9142
			6	0.9134
			baseline	0.9135
		32	3	0.6962
			4	0.9041
			5	0.9127
			6	0.9139
			7	0.9143
			baseline	0.9142
	Int4	64	2	0.1694
			3	0.8465
			4	0.8736
			5	0.8738
			6	0.8748
			baseline	0.875
		32	3	0.6905
			4	0.8813
			5	0.8845
			6	0.885
			7	0.8878
			baseline	0.8868
		16	3	0.2776
			4	0.8604
			5	0.8851
			6	0.8868
			7	0.8887
			baseline	0.8841