# Efficient coding explains neural response homeostasis and stimulus-specific adaptation

## Abstract

Empirical studies have demonstrated that across changes in their sensory environment or input statistics, cortical neurons display a homeostasis or equalisation of firing rates [2, 10, 8, 7]. We present a normative explanation of such firing rate homeostasis grounded in efficient coding theory and the infomax principle [6]. We further demonstrate how homeostatic coding, coupled with Bayesian theories of neural representation [11] can explain stimulus-specific adaptation effects, which is widely observed in the nervous system (*e.g.*, in the visual cortex [2]), and how it can be achieved by divisive normalisation with adaptive weights [3, 12].

## 1 Problem statement and framework

Figure 1: Illustration of the basic framework. The gain $g$ scales the tuning curves of individual neurons (left). As $g$ increases, the information content of neurons increases sub-linearly, while their firing rates and metabolic cost increase linearly (right). We look to find the optimal trade-off $g_{\text{opt}}$

We consider a population of $N$ neurons, responding to the (possibly high-dimensional) sensory input or stimulus, $\boldsymbol{s}$, with marginal distribution $Z(\boldsymbol{s})$ that can vary across environments. Assuming rate coding in time bins of a fixed duration, we denote the vector of population spike counts in a time bin by $\boldsymbol{n}$. Neural tuning curves (Fig. 1), $h_i(\boldsymbol{s})$, are factorised into a *representational curve*, $\Omega_i(\boldsymbol{s})$, and an adaptive response *gain*, $g_i$:

$$h_i(\boldsymbol{s}) = g_i \Omega_i(\boldsymbol{s}).$$

Approximating the spike counts as continuous, we adopt a Gaussian noise model with constant Fano factor scaling of variance: conditional on $\boldsymbol{s}$, $n_i$ are independent with distribution $n_i | \boldsymbol{s} \sim \mathcal{N}(h_i(\boldsymbol{s}), h_i(\boldsymbol{s}))$.

Submitted to Information-Theoretic Principles in Cognitive Systems Workshop at the 36th Conference on Neural Information Processing Systems (NeurIPS 2022). Do not distribute.

18 We suggest that neurons adapt their gains (Fig. 1) to maximise an objective function, $\mathcal{L}^0(\boldsymbol{g})$, that
19 trades off the metabolic cost of neural activity with the information conveyed by the population [5, 4]:

$$\mathcal{L}^0(\boldsymbol{g}) = 2\mu I(\boldsymbol{s}, \boldsymbol{n}) - \sum_{i=1}^{N} \mathbb{E}[n_i].$$

20 Here, $I(\boldsymbol{s}, \boldsymbol{n})$ is the mutual information between the stimulus and response, the second term penalises
21 the average population spike count, and $\mu$ is a positive constant controlling the information-energy
22 trade-off.

23 Note that $\Omega_i$ (which in our framework constitute input data for the gain optimisation problem) can
24 be complex functions of the stimulus, representing *any* general computation. Allowing for the
25 free adjustment of gains does not restrict the computations performed by this population either,
26 as adjustments in gains can in principle always be compensated for by reciprocal adjustments in
27 readout weights. Thus, our framework can apply to neural populations located deep in the sensory
28 processing pathway which code for high-level latent variables. In this sense our treatment is more
29 general than other efficient coding frameworks (*e.g.* [4]), which place tight constraints on the neural
30 representation, via constraints on the shape and configuration of the tuning curves.

## 2 Information-energy trade-off leads to homeostasis

32 Analytic maximisation of mutual information is intractable. We therefore make two approximations
33 to allow us to derive a closed form expression for the optimal gains (see App. A.1 for details). For
34 the Gaussian noise model, the conditional entropy is given by

$$2H[\boldsymbol{n}|\boldsymbol{s}] = \sum_{j=1}^{N} \ln(g_i) + \text{const. in } \boldsymbol{g}. \tag{1}$$

35 The marginal entropy, $H[\boldsymbol{n}]$, however, is intractable, and we replace it by an upper bound, namely
36 the entropy of a Gaussian with the same covariance:

$$2H[\boldsymbol{n}] \leq \ln(\det(2\pi e \operatorname{Cov}[\boldsymbol{n}])). \tag{2}$$

37 Using $I(\boldsymbol{s}, \boldsymbol{n}) = H[\boldsymbol{n}] - H[\boldsymbol{n}|\boldsymbol{s}]$, this yields the upper bound $2I(\boldsymbol{n}, \boldsymbol{s}) \leq$
38 $\ln\left(\det\left(I + P\operatorname{diag}(\boldsymbol{g} \odot \boldsymbol{\omega})\right)\right) +$ const. in $\boldsymbol{g}$, where $\odot$ denotes element-wise product, and we
39 define

$$P \equiv \operatorname{diag}(\boldsymbol{\omega})^{-1}\operatorname{Cov}[\boldsymbol{\Omega}(\boldsymbol{s})]\operatorname{diag}(\boldsymbol{\omega})^{-1} = \operatorname{diag}(\text{CV})\,\rho\,\operatorname{diag}(\text{CV}), \tag{3}$$

$$\boldsymbol{\omega} \equiv \mathbb{E}[\boldsymbol{\Omega}(\boldsymbol{s})], \qquad \rho \equiv \operatorname{Corr}[\boldsymbol{\Omega}(\boldsymbol{s})] = \operatorname{Corr}[\boldsymbol{h}(\boldsymbol{s})]. \tag{4}$$

40 Here $\operatorname{Corr}[\cdot]$ denotes the Pearson correlation matrix, and $\text{CV}_i$ is the coefficient of variation of $\Omega_i(\boldsymbol{s})$
41 (or equivalently $h_i(\boldsymbol{s})$). This in turn yields (up to additive constants) the upper bound

$$\mathcal{L}(\boldsymbol{g}) = \mu \ln\left(\det\left(I + P\operatorname{diag}(\boldsymbol{g} \odot \boldsymbol{\omega})\right)\right) - \sum_{i=1}^{N} g_i \omega_i, \tag{5}$$

42 which we will optimise (see App. A.2 for details). The maximum satisfies $\frac{d\mathcal{L}}{dg_i} = \frac{\mu}{g_i}(I + (P\operatorname{diag}(\boldsymbol{g} \odot$
43 $\boldsymbol{\omega}))^{-1})_{ii}^{-1} - \omega_i = 0$. Under the condition (see below for empirical justification)

$$\mu \text{CV}_i^2 \gg [\rho^{-1}]_{ii}, \tag{6}$$

44 a first-order Neumann expansion in $(P\operatorname{diag}(\boldsymbol{g} \odot \boldsymbol{\omega}))^{-1}$ yields $\frac{d\mathcal{L}}{dg_i} \approx \frac{\mu}{g_i}(1 - \frac{[P^{-1}]_{ii}}{\omega_i g_i}) - \omega_i$. Setting
45 this to zero and reusing Eq. (6) yields the following first-order approximation for the optimal gains

$$g_i \approx g_i^{(1)} \equiv \frac{\mu}{\omega_i}\left(1 - \frac{[\rho^{-1}]_{ii}}{\mu \text{CV}_i^2}\right). \tag{7}$$

46 The corresponding zeroth-order solution, $g_i^{(0)} \equiv \mu/\omega_i$, gives exact *homeostasis*, as under these gains

$$\text{average rate of neuron } i = \mathbb{E}[h_i(\boldsymbol{s})] = g_i^{(0)}\omega_i = \mu$$

47 which is constant, both between neurons and across environments (as specified by $Z(\boldsymbol{s})$). Since
48 $[\rho^{-1}]_{ii} \geq 0$, $g_i^{(1)} \leq g_i^{(0)}$. Averaging the factor in parentheses in Eq. 7 over neurons, we additionally
49 define $\bar{g}_i^{(1)} = \frac{\mu}{\omega_i}\left(1 - \frac{1}{N}\sum_j(\mu \text{CV}_j^2)^{-1}[\rho^{-1}]_{jj}\right)$, which yields uniform mean rates across neurons
50 and, as long as $\sum_j(\mu \text{CV}_j^2)^{-1}[\rho^{-1}]_{jj}$ is constant across environments, homeostasis as defined above.

## 3   Validation of results

In our first-order expansion above, we used the condition (6). How likely is this to hold in the cortex?

- We see from the solution that $\mu$ scales the average spike count of the neurons over the rate coding time-interval. Typical cortical firing rates are 10 Hz [1], so if neurons are coding over an interval of 0.1 sec., we obtain $\mu \approx 1$. If we take our model neurons to represent a cluster of $m$ cortical neurons with similar tuning, $\mu$ can be further scaled up by $m$.

- $\rho$ is the *signal correlation matrix* of neurons. Stringer *et al.* [9] have found that in the primary visual cortex (V1), we can expect the eigenvalues of $\rho$ to obey a power law decay, approximately as $1/n$. This leads to an average value of $[\rho^{-1}]_{ii}$ of approximately $\ln(N)/2$. Even for very large values of $N = \mathcal{O}(10^8)$ this remains bounded above by 10

- The coefficient of variation CV can be seen as a measure of coding level or sparseness of neural responses. Consider the toy-model $\Omega_i(\boldsymbol{s}) \sim \mathrm{Bern}(p_i)$ (for an $\Omega_i(\boldsymbol{s})$ with two output levels: 0 and 1). In this case, $\mathrm{CV}_i^2 = (1 - p_i)/p_i$, which is large for small $p_i$. At $p_i = 0.1$ we obtain $\mathrm{CV}_i^2 = 9$. Values of $p_i$ in this range have been observed in empirical studies [1].

This makes it clear when we should expect homeostasis – when firing rates are high but selective, and signal correlation structure corresponds to a high-dimensional geometry, as *e.g.* observed in [9]. When these conditions are violated, homeostasis deviates from optimally.

We numerically compare the performance of the zeroth-order homeostatic code with gains $g_i^{(0)} = \mu/\omega_i$, the first order correction, $g_i^{(1)}$, and the homeostatic approximation to the latter, $\bar{g}_i^{(1)}$, against numerically optimised gains, $g_i^{opt}$, on the objective $\mathcal{L}(\boldsymbol{g})$. An environment (originally specified by the stimulus $Z(\boldsymbol{s})$ density) is specified by $\rho$, $\omega_i$, and $\mathrm{CV}_i$. We consider a sequence of environments parameterised by $\epsilon \in [0, 1]$. In environment $\epsilon$, $\omega_j(\epsilon) = 4 - \epsilon \cos(2\pi j/N)$; this can be thought of as an environmental shift in which some stimuli become up to $25\%$ more or less prevalent. We took $N = 100$, $\mu = 10$, and $\mathrm{CV}_i(\epsilon) = 3$ for all environments and neurons.

$\rho(\epsilon)$ is obtained by normalising a positive-definite matrix $\Sigma_\epsilon$ which has a $1/n$ eigen-spectrum, in line with the findings of [9]. The eigen-bases of the end points $\Sigma_0$ and $\Sigma_1$ are sampled randomly and independently, and we smoothly interpolate between these to obtain the eigen-bases for $\Sigma_\epsilon, \epsilon \in (0, 1)$. (see App. A.3 for details).

To compare the performance of each approximate solution, $\boldsymbol{g}^{app}(\epsilon)$, we use the measure

$$C(\epsilon) = \frac{\mathcal{L}(\boldsymbol{g}^{app}(\epsilon); \epsilon) - \mathcal{L}(\boldsymbol{g}^{opt}(0); \epsilon)}{\mathcal{L}(\boldsymbol{g}^{opt}(\epsilon); \epsilon) - \mathcal{L}(\boldsymbol{g}^{opt}(0); \epsilon)}$$

which can be interpreted as the improvement in $\mathcal{L}(\cdot; \epsilon)$ achieved by the adaptive $\boldsymbol{g}^{app}(\epsilon)$ over the unadapted optimal gains in the original environment $\boldsymbol{g}^{opt}(0)$, relative to the same improvement obtained by the optimally adaptive gains. $C(\epsilon)$ for different approximations are plotted in Fig. 2.

Figure 2: Left: Profiles of rates unmodulated by gains, $\boldsymbol{\omega}$, for the $\epsilon = 0$ (red) and $\epsilon = 1$ (brown) environments. Right: $C(\epsilon)$ as a function of $\epsilon$ (averaged across 50 realisations of $\rho(\epsilon)$) for the three approximations $\boldsymbol{g}^{(0)}(\epsilon)$ (blue), $\boldsymbol{g}^{(1)}(\epsilon)$ (orange), and $\bar{\boldsymbol{g}}^{(1)}(\epsilon)$ (green).

We first note that the first order approximation (7) performs essentially as well as numerical optimisation of $\mathcal{L}$. The homeostatic correction $\bar{g}^{(1)}(\epsilon)$ also performs close to optimally for $\epsilon \geq 0.1$. Moreover, as soon as $\epsilon$ exceeds about 0.2, exact homeostasis $g^{(0)}$ is superior to no adaptation. For very small changes in the sensory environment, exact homeostasis performs worse than the (constant) numerically optimised code for $\epsilon = 0$, because $g^{(0)}$ lacks knowledge of the signal correlation structure of responses. Finally, we also computed the mean relative errors $\frac{1}{N} \sum_j |g_j^{app} - g_j^{opt}|/g_j^{opt}$ of the approximate solutions. These were approximately constant in $\epsilon$ to 3 significant figures, and took the values 0.0294, 0.000291, 0.00615, for $g^{(0)}$, $g^{(1)}$, and $\bar{g}^{(1)}$, respectively.

## 4 Bayes-ratio coding

In this section, we neglect correction terms and work with the homeostatic approximation $g_i^{(0)} = \mu/\omega_i$, which yields $h_i(s) = \mu\Omega_i(s)/\mathbb{E}[\Omega_i(S)]$. So far we have been silent on the computation encoded by the representational curves $\Omega(s)$. Here, we apply the homeostatic code to a form of Bayesian encoding, the distributed distributional code (DDC) [11]. In a DDC, which is based on an internal generative model of stimuli with latent variables $z$, $\Omega_i(s)$ is the posterior expectation (given the observed $s$) of a so-called kernel function $k_i(z)$. We make an ideal-observer assumption, wherein the internal generative model generates the true stimulus distribution, $Z(s)$. In this case, the homeostatic adaptation yields $h_i(s) = \mu\frac{\mathbb{E}[k_i(z)|s]}{\mathbb{E}[k_i(z)]}$. For the special case $k_i(z) = \delta(z^i - z)$, this yields *Bayes-ratio coding*:

$$h_i(s) = \mu\frac{\Pi(z^i|s)}{\pi(z^i)} = \mu\frac{f(s|z^i)}{Z(s)}, \tag{8}$$

where $\Pi$ and $\pi$ denote the posterior and prior distributions over $z$, and $f(s|z)$ is the generative model's likelihood. As shown in App. A.4, Bayes-ratio coding can be achieved via divisive normalisation, a canonical cortical operation [3], with adaptive normalisation weights proportional to the prior $\pi(z^i)$ (allowed to vary across environments) and feedforward inputs given by the likelihood function.

Additionally, Bayes-ratio coding can be used to explain certain stimulus-specific adaptation effects. It is typical of stimulus specific adaptation in V1 [2] that orientation tuning curves display a repulsion and suppression around the over-represented orientation of the adaptor stimulus. To model the findings of [2] with Bayes-ratio coding, we took stimulus and latent variable spaces to be the orientation space $[-90, 90)$, and the likelihood $f(s|z^i) = \psi(s - z^i; 10)$ where $\psi(\cdot; k)$ is a von Mises density with precision $k$, with $z^i$ uniformly spaced over $[-90, 90)$. We consider a uniform pre-adaptation prior $\pi^{pre}$, and a post-adaptation prior $\pi^{post}(z) = \frac{0.6}{180} + 0.4\psi(z; 2)$ which represents an adaptor stimulus with orientation $z = 0°$. The pre- and post-adaptation tuning curves are plotted in figure 3, and exhibit the suppression and repulsion of the adapted tuning curves around the over-represented stimulus. This result generalises to a homeostatic DDC with finite-width unimodal kernel functions.

Figure 3: Left: The tuning curves pre- (blue) and post-adaptation (red). Right: The displacement of the preferred orientation of neurons (in degrees) as a function of the pre-adaptation preferred orientation, demonstrating the repulsion of tuning curves from the adaptor orientation.

# References

[1] David Attwell and Simon B. Laughlin. "An Energy Budget for Signaling in the Grey Matter of the Brain". In: *Journal of Cerebral Blood Flow & Metabolism* 21.10 (Oct. 2001). Publisher: SAGE Publications Ltd STM, pp. 1133–1145. ISSN: 0271-678X. DOI: 10.1097/00004647-200110000-00001. URL: https://doi.org/10.1097/00004647-200110000-00001 (visited on 07/30/2022).

[2] Andrea Benucci, Aman B. Saleem, and Matteo Carandini. "Adaptation maintains population homeostasis in primary visual cortex". eng. In: *Nature Neuroscience* 16.6 (June 2013), pp. 724–729. ISSN: 1546-1726. DOI: 10.1038/nn.3382.

[3] Matteo Carandini and David J. Heeger. "Normalization as a canonical neural computation". en. In: *Nature Reviews Neuroscience* 13.1 (Jan. 2012). Number: 1 Publisher: Nature Publishing Group, pp. 51–62. ISSN: 1471-0048. DOI: 10.1038/nrn3136. URL: https://www.nature.com/articles/nrn3136 (visited on 08/09/2022).

[4] Deep Ganguli and Eero P. Simoncelli. "Efficient Sensory Encoding and Bayesian Inference with Heterogeneous Neural Populations". en. In: *Neural Computation* 26.10 (Oct. 2014), pp. 2103–2134. ISSN: 0899-7667, 1530-888X. DOI: 10.1162/NECO_a_00638. URL: https://direct.mit.edu/neco/article/26/10/2103-2134/8022 (visited on 08/21/2022).

[5] William Levy and Robert Baxter. "Energy Efficient Neural Codes". In: *Neural computation* 8 (May 1996), pp. 531–43. DOI: 10.1162/neco.1996.8.3.531.

[6] R. Linsker. "Self-organization in a perceptual network". In: *Computer* 21.3 (Mar. 1988). Conference Name: Computer, pp. 105–117. ISSN: 1558-0814. DOI: 10.1109/2.36.

[7] Timothy O'Leary et al. "Cell Types, Network Homeostasis, and Pathological Compensation from a Biologically Plausible Ion Channel Expression Model". In: *Neuron* 82.4 (May 2014), pp. 809–821. ISSN: 0896-6273. DOI: 10.1016/j.neuron.2014.04.002. URL: https://www.ncbi.nlm.nih.gov/pmc/articles/PMC4109293/ (visited on 08/21/2022).

[8] Zahid Padamsey et al. "Neocortex saves energy by reducing coding precision during food scarcity". In: *Neuron* 110 (Nov. 2021). DOI: 10.1016/j.neuron.2021.10.024.

[9] Carsen Stringer et al. "High-dimensional geometry of population responses in visual cortex". en. In: *Nature* 571.7765 (July 2019). Number: 7765 Publisher: Nature Publishing Group, pp. 361–365. ISSN: 1476-4687. DOI: 10.1038/s41586-019-1346-5. URL: https://www.nature.com/articles/s41586-019-1346-5 (visited on 07/07/2022).

[10] Gina G. Turrigiano and Sacha B. Nelson. "Homeostatic plasticity in the developing nervous system". en. In: *Nature Reviews Neuroscience* 5.2 (Feb. 2004). Number: 2 Publisher: Nature Publishing Group, pp. 97–107. ISSN: 1471-0048. DOI: 10.1038/nrn1327. URL: http://www.nature.com/articles/nrn1327 (visited on 08/21/2022).

[11] Eszter Vertes and Maneesh Sahani. *Flexible and accurate inference and learning for deep generative models*. arXiv:1805.11051 [cs, stat]. May 2018. DOI: 10.48550/arXiv.1805.11051. URL: http://arxiv.org/abs/1805.11051 (visited on 08/20/2022).

[12] Zachary M. Westrick, David J. Heeger, and Michael S. Landy. "Pattern Adaptation and Normalization Reweighting". en. In: *Journal of Neuroscience* 36.38 (Sept. 2016). Publisher: Society for Neuroscience Section: Articles, pp. 9805–9816. ISSN: 0270-6474, 1529-2401. DOI: 10.1523/JNEUROSCI.1067-16.2016. URL: https://www.jneurosci.org/content/36/38/9805 (visited on 08/20/2022).

 # A Appendix

 ## A.1 Upper bound on $\mathcal{L}^0$

 Recall that $n_i | \boldsymbol{s} \sim N(h_i(\boldsymbol{s}), h_i(\boldsymbol{s}))$. In this case,

$$
\begin{aligned}
H[n_i | \boldsymbol{s}] &= \int H[N(h_i(\boldsymbol{s}), h_i(\boldsymbol{s}))] Z(\boldsymbol{s}) d\boldsymbol{s} \\
&= \int \frac{1}{2} \ln(2\pi e h_i(\boldsymbol{s})) Z(\boldsymbol{s}) d\boldsymbol{s} \\
&= \frac{1}{2} \ln(2\pi e) + \frac{1}{2} \ln(g_i) + \frac{1}{2} \mathbb{E}[\ln(\Omega_i(\boldsymbol{s}))] \\
H[\boldsymbol{n} | \boldsymbol{s}] &= \sum_{j=1}^{N} H[n_j | \boldsymbol{s}] \\
&= \frac{N}{2} \ln(2\pi e) + \frac{1}{2} \sum_{j=1}^{N} \ln(g_i) + \sum_{j=1}^{N} \frac{1}{2} \mathbb{E}\left[\ln(\Omega_j(\boldsymbol{s}))\right]
\end{aligned}
$$

 This gives us equation (1). We now use the fact that the entropy of any continuous distribution can
 be upper bounded by the entropy of a Gaussian with with the same covariance. The entropy of a
 $N(\boldsymbol{\mu}, \Sigma)$ random variable is

$$
H[N(\boldsymbol{\mu}, \Sigma)] = \frac{N}{2} \ln(2\pi e) + \frac{1}{2} \ln(\det(\Sigma))
$$

 It therefore suffices to find the covariance of $\boldsymbol{n}$. We use the decomposition $\mathrm{Cov}(\boldsymbol{n}) = \mathbb{E}[\mathrm{Cov}(\boldsymbol{n}|\boldsymbol{s})] +$
 $\mathrm{Cov}(\mathbb{E}[\boldsymbol{n}|\boldsymbol{s}])$ and compute

$$
\begin{aligned}
\mathrm{Cov}(\boldsymbol{n}|\boldsymbol{s}) &= \mathrm{diag}(\mathrm{Var}(\boldsymbol{n}|\boldsymbol{s})) \\
&= \mathrm{diag}(\boldsymbol{h}(\boldsymbol{s})) \\
\mathbb{E}[\mathrm{Cov}(\boldsymbol{n}|\boldsymbol{s})] &= \mathrm{diag}(\mathbb{E}[\boldsymbol{h}(\boldsymbol{s})]) \\
&= \mathrm{diag}(\boldsymbol{g} \odot \boldsymbol{\omega}) \\
&= \mathrm{diag}(\boldsymbol{g}) \mathrm{diag}(\boldsymbol{\omega}) \\
\mathrm{Cov}(\mathbb{E}[\boldsymbol{n}|\boldsymbol{s}]) &= \mathrm{Cov}(\boldsymbol{h}(\boldsymbol{s})) \\
&= \mathrm{diag}(\boldsymbol{g}) \mathrm{Cov}(\boldsymbol{\Omega}(\boldsymbol{s})) \mathrm{diag}(\boldsymbol{g})
\end{aligned}
$$

 Thus

$$
\begin{aligned}
\mathrm{Cov}(\boldsymbol{n}) &= \mathrm{diag}(\boldsymbol{g}) \mathrm{diag}(\boldsymbol{\omega}) + \mathrm{diag}(\boldsymbol{g}) \mathrm{Cov}(\boldsymbol{\Omega}(\boldsymbol{s})) \mathrm{diag}(\boldsymbol{g}) \\
&= \mathrm{diag}(\boldsymbol{g}) \mathrm{diag}(\boldsymbol{\omega})[I + \mathrm{diag}(\boldsymbol{\omega})^{-1} \mathrm{Cov}(\Omega(s)) \mathrm{diag}(\boldsymbol{\omega})^{-1} \mathrm{diag}(\boldsymbol{\omega}) \mathrm{diag}(\boldsymbol{g})] \\
&= \mathrm{diag}(\boldsymbol{g}) \mathrm{diag}(\boldsymbol{\omega})[I + P \mathrm{diag}(\boldsymbol{\omega} \odot \boldsymbol{g})] \\
\ln(\det(\mathrm{Cov}(\boldsymbol{n}))) &= \ln(\det(\mathrm{diag}(\boldsymbol{g}))) + \ln(\det(\mathrm{diag}(\boldsymbol{\omega}))) + \ln(\det(I + P \mathrm{diag}(\boldsymbol{\omega} \odot \boldsymbol{g}))) \\
&= \sum_{i=1}^{N} \ln(g_i) + \sum_{i=1}^{N} \ln(\omega_i) + \ln\left(\det\left(I + P \mathrm{diag}(\boldsymbol{\omega} \odot \boldsymbol{g})\right)\right)
\end{aligned}
$$

 where $P = \mathrm{diag}(\boldsymbol{\omega})^{-1} \mathrm{Cov}(\boldsymbol{\Omega}(\boldsymbol{s})) \mathrm{diag}(\boldsymbol{\omega})^{-1}$. Putting this together, we obtain:

$$
H[\boldsymbol{n}] \leq \frac{N}{2} \ln(2\pi e) + \frac{1}{2} \sum_{j=1}^{N} \ln(g_i) + \frac{1}{2} \sum_{i=1}^{N} \ln(\omega_i) + \frac{1}{2} \ln\left(\det\left(I + P \mathrm{diag}(\boldsymbol{\omega} \odot \boldsymbol{g})\right)\right)
$$

168   We now insert the above expressions to obtain the bound on mutual information:

$$I(\boldsymbol{n}, \boldsymbol{s}) = H[\boldsymbol{n}] - H[\boldsymbol{n}|\boldsymbol{s}]$$

$$\leq \frac{N}{2}\ln(2\pi e) + \frac{1}{2}\sum_{j=1}^{N}\ln(g_i) + \frac{1}{2}\sum_{i=1}^{N}\ln(\omega_i) + \frac{1}{2}\ln\left(\det\left(I + P\mathrm{diag}(\boldsymbol{\omega}\odot\boldsymbol{g})\right)\right)$$

$$- \frac{N}{2}\ln(2\pi e) - \frac{1}{2}\sum_{j=1}^{N}\ln(g_i) - \sum_{j=1}^{N}\frac{1}{2}\mathbb{E}\left[\ln(\Omega_j(\boldsymbol{s}))\right]$$

$$= \frac{1}{2}\sum_{i=1}^{N}\ln(\omega_i) - \mathbb{E}\left[\ln(\Omega_j(\boldsymbol{s}))\right] + \frac{1}{2}\ln\left(\det\left(I + P\mathrm{diag}(\boldsymbol{\omega}\odot\boldsymbol{g})\right)\right)$$

$$= -\frac{1}{2}\sum_{i=1}^{N}\mathbb{E}\left[\ln\left(\frac{\Omega_i(\boldsymbol{s})}{\omega_i}\right)\right] + \frac{1}{2}\ln\left(\det\left(I + P\mathrm{diag}(\boldsymbol{\omega}\odot\boldsymbol{g})\right)\right),$$

169   or

$$2I(\boldsymbol{n}, \boldsymbol{s}) \leq \ln\left(\det\left(I + P\mathrm{diag}(\boldsymbol{\omega}\odot\boldsymbol{g})\right)\right) + \text{ const. in } \boldsymbol{g}$$

## A.2   Approximate maximisation of $\mathcal{L}$

171   We now consider optimising

$$\mathcal{L}(\boldsymbol{g}) = \mu\ln\left(\det\left(I + P\mathrm{diag}(\boldsymbol{\omega}\odot\boldsymbol{g})\right)\right) - \sum_{i=1}^{N}g_i\omega_i$$

172   Taking the derivative with respect to $g_i$, we obtain

$$\frac{d\mathcal{L}}{dg_i} = \frac{\mu}{g_i}(I + (P\mathrm{diag}(\boldsymbol{\omega}\odot\boldsymbol{g}))^{-1})_{ii}^{-1} - \omega_i$$

173   To obtain an approximate solution for this we use a first order Neumann expansion for $(I + 
174   (P\mathrm{diag}(\boldsymbol{\omega}\odot\boldsymbol{g}))^{-1})^{-1}$. This requires that $(P\mathrm{diag}(\boldsymbol{\omega}\odot\boldsymbol{g}))^{-1}$ has a small norm, i.e. $P\mathrm{diag}(\boldsymbol{\omega}\odot\boldsymbol{g})$
175   is large in norm. The Neumann expansion gives:

$$(I + (P\mathrm{diag}(\boldsymbol{\omega}\odot\boldsymbol{g}))^{-1})^{-1} \approx 1 - \mathrm{diag}(\boldsymbol{\omega}\odot\boldsymbol{g})^{-1}P^{-1}$$

176   Plugging this in, we obtain

$$\frac{d\mathcal{L}}{dg_i} \approx \frac{\mu}{g_i}(1 - \frac{[P^{-1}]_{ii}}{\omega_i g_i}) - \omega_i \tag{9}$$

177   Setting equation (9) to zero, and solving to find the approximate maximiser of $\mathcal{L}(\boldsymbol{g})$, we get:

$$g_i = \frac{\mu}{2\omega_i}\left(1 + \sqrt{1 - \frac{4[P^{-1}]_{ii}}{\mu}}\right) \tag{10}$$

178   We further approximate by taking a first order Taylor expansion of the square root to obtain equation
179   (7):

$$g_i \approx \frac{\mu}{\omega_i}\left(1 - \frac{\rho_{ii}^{-1}}{\mu\mathrm{CV}_i^2}\right)$$

180   where $\rho$ is the correlation matrix $\mathrm{Corr}(\boldsymbol{\Omega}(\boldsymbol{s}))$ and $\mathrm{CV}_i$ is the coefficient of variation, $\frac{\sqrt{\mathrm{Var}(\Omega_i(\boldsymbol{s}))}}{\omega_i}$

181   The expansions employed in this argument require that $(P\mathrm{diag}(\boldsymbol{\omega}\odot\boldsymbol{g}))^{-1}$ is small in norm, and that
182   $\rho_{ii}^{-1} \ll \mu\mathrm{CV}_i^2$. Note that $(P\mathrm{diag}(\boldsymbol{\omega}\odot\boldsymbol{g}))_{ij} = \mathrm{CV}_i\rho_{ij}\mathrm{CV}_j g_j\omega_j$. But we know that $g_j = \mathcal{O}(\mu/\omega_j)$
183   and therefore $g_j\omega_j = \mathcal{O}(\mu)$. Accordingly, we obtain that $(P\mathrm{diag}(\boldsymbol{\omega}\odot\boldsymbol{g}))^{-1} = \mathcal{O}\left(\frac{\rho^{-1}}{\mu\mathrm{CV}^2}\right)$. This
184   means that the condition for truncating the Neumann expansion is indeed Eq. (6).

### A.3 Specification of environment for $\epsilon$

To generate $\rho(\epsilon)$, we first generate a covariance matrix $\Sigma_\epsilon$, and let $\rho(\epsilon)$ be the corresponding correlation matrix. The procedure for generating $\Sigma_\epsilon$ is as follows.

We randomly and independently sample two $N \times N$ random Gaussian matrices $A_0, A_1 \sim \mathcal{N}_{N \times N}(0, I_{N \times N})$ and obtain symmetric matrices $S_0 = A_0 + A_0^T$ and $S_1 = A_1 + A_1^T$. As is well known, the eigen-basis (represented by an orthogonal matrix) of such a random Gaussian matrix is distributed uniformly (*i.e.*, according to the corresponding Haar measure) over the orthogonal group $O(N)$.

Now let $S_\epsilon = (1 - \epsilon)S_0 + \epsilon S_1$. Almost surely these matrices have a non-degenerate spectrum, and hence a unique representation as $S_\epsilon = U(\epsilon)\Lambda(\epsilon)U(\epsilon)^T$ where $\Lambda(\epsilon)$ is diagonal with strictly decreasing eigenvalues and $U(\epsilon)$ is orthogonal. Moreover, $U(\epsilon)$ depends continuously on $\epsilon$.

Let $D = \mathrm{diag}(1, 1/2, 1/3, \ldots, 1/N)$. Then we define $\Sigma_\epsilon = U(\epsilon)DU(\epsilon)^T$.

### A.4 Bayes-ratio coding and divisive normalisation

Given a collection of feed-forward inputs, $F_i(\boldsymbol{s})$, divisive normalisation computes the response (and thus the tuning curve) of neuron $i$ as

$$h_i(\boldsymbol{s}) = \gamma \frac{F_i(\boldsymbol{s})^n}{\sigma^n + \sum_j w_j F_j(\boldsymbol{s})^n} \tag{11}$$

where $w_j$ are a collection of *normalisation weights*, and $\gamma, \sigma \geq 0$ and $n \geq 1$ are constants.

Bayes-ratio coding can be achieved naturally by a divisive normalisation model in which $n = 1$ and the feed-forward inputs are given by the generative model's likelihood function $f(\boldsymbol{s}|\boldsymbol{z}^i)$. We then choose the normalisation weights $w_i$ to encode prior probabilities, $w_i = \pi(\boldsymbol{z}^i)\delta\boldsymbol{z}^i$, where the volume element $\delta\boldsymbol{z}^i$ is chosen such that the latent variable space is the disjoint union of volumes of size $\delta\boldsymbol{z}^i$ each containing their corresponding sample point $\boldsymbol{z}^i$. Then we have:

$$\sum_j w_j F_j(\boldsymbol{s}) = \sum_j f(\boldsymbol{s}|\boldsymbol{z}^{(j)})\pi(\boldsymbol{z}^{(j)})\delta\boldsymbol{z}^{(j)}$$
$$\approx \int f(\boldsymbol{s}|\boldsymbol{z})\pi(\boldsymbol{z})d\boldsymbol{z}$$
$$= Z(\boldsymbol{s})$$

hence

$$h_i(\boldsymbol{s}) = \mu \frac{F_i(\boldsymbol{s})}{\sigma + \sum_{j=1}^N w_j F_j(\boldsymbol{s})}$$
$$\approx \mu \frac{f(\boldsymbol{s}|\boldsymbol{z}^i)}{\sigma + Z(\boldsymbol{s})}$$

Taking the limit as $\sigma \to 0$, we obtain Eq. 8:

$$h_i(\boldsymbol{s}) = \mu \frac{f(\boldsymbol{s}|\boldsymbol{z}^i)}{Z(\boldsymbol{s})}.$$

Therefore, provided $\sigma$ is small compared to $Z(\boldsymbol{s})$, divisive normalisation can be used to approximate Bayes-ratio coding. Not only does this show that implementing Bayes-ratio coding is biologically plausible, this framework gives a normative interpretation to both the feedforward inputs (as the generative model likelihoods) and the normalisation weights (as the prior probabilities).