Temporally Efficient Deep Learning with Spikes

Abstract

The vast majority of natural sensory data is temporally redundant. For instance, video frames or audio samples which are sampled at nearby points in time tend to have similar values. Typically, deep learning algorithms take no advantage of this redundancy to reduce computations. This can be an obscene waste of energy. We present a variant on backpropagation for neural networks in which computation scales with the rate of change of the data - not the rate at which we process the data. We do this by having neurons communicate a combination of their state, and their temporal change in state. Intriguingly, this simple communication rule give rise to units that resemble biologically-inspired leaky integrate-and-fire neurons, and to a weight-update rule that is equivalent to a form of Spike-Timing Dependent Plasticity (STDP), a synaptic learning rule observed in the brain. We demonstrate that on MNIST, on a temporal variant of MNIST, and on Youtube-BB, a dataset with videos in the wild, our algorithm performs about as well as a standard deep network trained with backpropagation, despite only communicating discrete values between layers.

1 Introduction

Currently, most algorithms used in Machine Learning work under the assumption that data points are independent and identically distributed, as this assumption provides good statistical guarantees for convergence. This is very different from the way data enters our brains. Our eyes receive a single, never-ending stream of temporally correlated data. We get to use this data once, and then it's gone. Moreover, most sensors produce sequential, highly overlapping, and redundant streams of data. This can be both a blessing and a curse. From a statistical learning point of view this redundancy may lead to biased estimators and eventually unnecessarily bad predictions. However, this temporal redundancy also implies that intuitively not all computations are necessary.

Online Learning is the study of how to learn in this domain - where data becomes available in sequential order and is given to the model only once. Given the enormous amount of sequential data, mainly videos, that are being produced nowadays, it seems desirable to develop learning systems that simply consume data on-the-fly as it is being generated, rather than collect it into datasets for offline-training. There is, however a problem of efficiency, which we hope to illustrate with two examples:

1. *CCTV feeds.* CCTV Cameras collect an enormous amount of data from mostly-static scenes. The amount of new information in a frame, given the previous frame, tends to be low. That is to say, data tends to be temporally redundant. If we want to train a model from of this data (for example a pedestrian detector), we need process a large amount of mostly-static frames. If the frame rate doubles, so does the amount of computation. Intuitively, it feels that this should not be necessary. It would be nice to still be able to use all this data, but have the amount of computation scale with the amount of new information in each frame, not just the number of frames and dimensions of the data.

2. *Robot perception*. Robots have no choice but to learn online - their future input data (*e.g.* camera frames) are dependent on their previous predictions (*i.e.* motor actions). Not only does their data come in nonstationary temporal streams, but it typically comes from several sensor running at different rates. The camera may produce 1MB images at 30

frames/s, while the gyro might produce 1-byte readings 1000 frames/s. It's not obvious, using current methods in deep learning, how we can integrate asynchronous sensory signals into a unified, trainable, latent representation, without undergoing the horribly inefficient process of recomputing the function of the network every time a new signal arrives.

These examples point to the need for a training method where the amount of computation required to update the model scales with the amount of new information in the data, and not just the dimensionality of the data.

There has been a lot of work on increasing the computational efficiency of neural networks by quantizing neural weights or activations (see Section 4), but comparatively little work on exploiting redundancies in the data to reduce the amount of computation. O'Connor and Welling (2016b), set out to exploit the temporal redundancy in video, by having neurons only send their quantized *changes* in activation to downstream neurons, and having the downstream neurons integrate these changes over time. This approach works for efficiently approximating the function of the network, but fails for training, because when the weights are changing with time, this approach (take the temporal difference, multiply by weights, temporally integrate) fails to reconstruct the correct activation for the next layer. In other words, $\sum_{\tau=0}^{t}(x_\tau - x_{\tau-1}) \cdot w_\tau \neq x_t \cdot w_t$ unless $w_t = w_0 \forall t$. Figure 2 describes the problem visually.

In this paper, we correct for this problem by encoding a mixture of two components of the layers activation x_t: the *proportional* component $k_p x_t$, and the *derivative* component $k_d(x_t - x_{t-1})$. When we invert this encoding scheme, we get get a decoding scheme which corresponds to taking an exponentially decaying temporal average of past inputs. Interestingly, the resulting neurons begin to resemble models of biological spiking neurons, whose membrane potentials can approximately be modeled as an exponentially decaying temporal average of past inputs.

In this work, we present a scheme wherein the temporal redundancy of input data is used to reduce the computation required to train a neural network. We demonstrate this on the MNIST and Youtube-BB datasets. To our knowledge we are the first to create a neural network training algorithm which uses less computation as data becomes more temporally redundant.

2 METHODS

We propose a coding scheme where neurons can represent their activations as a temporally sparse series of impulses. The impulses from a given neuron encode a combination of the value and the rate of change of the neuron's activation.

While our algorithm is designed to work efficiently with *temporal data*, we do not aim to learn *temporal sequences* in this work. We aim to efficiently approximate a function $y_t = f(x_t)$, where the current target y_t is solely a function of the current input x_t, and not previous inputs $x_0...x_{t-1}$. The temporal redundancy between neighbouring inputs x_{t-1}, x_t will however be used to make our approximate computation of this function more efficient.

2.1 PRELIMINARY

Throughout this paper we will use the notation $(f_3 \circ f_2 \circ f_1)(x) = f_3(f_2(f_1(x)))$ to denote function composition. We slightly abuse the notion of functions by allowing them to have an internal state which persists between calls. For example, we define the Δ function in Equation 1 as being the difference between the inputs in two consecutive calls (where persistent variable x_{last} is initialized to 0). The Σ function, defined in Equation 2, returns a running sum of the inputs over calls. So we can write, for example, that when our composition of functions $(\Sigma \circ \Delta)$ is called with a sequence of input variables $x_\tau : \tau = [1..t]$, then $(\Sigma \circ \Delta)(x_t) = x_t$, because $y_0 + (x_1 - x_0) + (x_2 - x_1) + ... + (x_t - x_{t-1})|_{x_0=0,y_0=0} = x_t$.

In general, when we write $y_t = f(x_t)$, where f is a function with persistent state, it will be implied that we have previously called $f(x_\tau)$ for $\tau \in [1,..,t-1]$ in sequence. Variable definitions that are used later will be highlighted in blue.

2.2 PD ENCODING

Suppose a neuron has time-varying activation $x_\tau : \tau \in [1..t]$. Taking inspiration from Proportional-Integral-Derivative (PID) controllers, we can "encode" this activation at each time step as a combination of its current activation and change in activation as $a_t \triangleq enc(x_t) = k_p x_t + k_d(x_t - x_{t-1})$, (see Equation 4). The parameters k_p and k_d determine what portion of our encoding represents the value of the activation and the rate of change of that value, respectively. In Section D, we will discuss the effect our choices for these parameters have on the network.

To get our decoding formula, we can simply solve for x_t as $x_t = \frac{a_t + k_d x_{t-1}}{k_p + k_d}$ (Equation 5), such that $(dec \circ enc)(x_t) = x_t$. Notice that Equation 5 corresponds to decaying the previous decoder state by some constant $k_d/(k_p+k_d)$ and then adding the input $a_t/(k_p + k_d)$. We can expand this recursively to see that this corresponds to a temporal convolution $a * \kappa$ where κ is a causal exponential kernel $\kappa_\tau = \left\{ \frac{1}{k_p+k_d} \left(\frac{k_d}{k_d+k_p} \right)^\tau \text{ if } \tau \geq 0 \text{ otherwise } 0 \right\}$.

$$\Delta : x \mapsto y; \text{ Persistent: } x_{last} \leftarrow 0$$
$$y \leftarrow x - x_{last} \tag{1}$$
$$x_{last} \leftarrow x$$

$$\Sigma : x \mapsto y; \text{ Persistent: } y \leftarrow 0$$
$$y \leftarrow y + x \tag{2}$$

$$Q : x \mapsto y; \text{ Persistent: } \phi \leftarrow 0$$
$$\phi' \leftarrow \phi + x$$
$$y \leftarrow round(\phi') \tag{3}$$
$$\phi \leftarrow \phi' - y$$

$$enc : x \mapsto y; \text{ Persistent: } x_{last} \leftarrow 0$$
$$y \leftarrow k_p x + k_d(x - x_{last}) \tag{4}$$
$$x_{last} \leftarrow x$$

$$dec : x \mapsto y; \text{ Persistent: } y \leftarrow 0$$
$$y \leftarrow \frac{x + k_d y}{k_p + k_d} \tag{5}$$

$$R : x \mapsto round(x) \tag{6}$$

2.3 QUANTIZATION

Our motivation for the aforementioned encoding scheme is that we want a sparse signal which can be quantized into a low-bitrate discrete signal. This will later be used to reduce computation.

We can quantize our signal a_t into a sparse, integer signal $s_t \triangleq Q(a_t)$, where the quantizer Q is defined in Equation 3. Equation 3 implements a form of Sigma-Delta modulation, a method widely used in signal processing to approximately communicate signals at low bit-rates (Candy and Temes, 1962). We can show that that $Q(x_t) = (\Delta \circ R \circ \Sigma)(x_t)$ (See Supplementary Material Section A), where $\Delta \circ R \circ \Sigma$ indicates applying a temporal summation, a rounding, and a temporal difference, in series. If x_t is temporally redundant, then $|a_t| \ll 1 \forall t$, and we can expect s_t to consist of mostly zeros with a few 1's and -1's.

We can now approximately reconstruct our original signal x_t as $\hat{x}_t \triangleq dec(s_t)$ by applying our decoder, as defined in Equation 5. As our coefficients k_p, k_d become larger, our reconstructed signal $\hat{x}_t$ should become closer to the original signal x_t. We illustrate examples of encoded signals and their reconstructions for different k_p, k_d in Figure 1.

2.3.1 SPECIAL CASES

We can compactly write the entire reconstruction function as $\hat{x} = (dec \circ \Delta \circ R \circ \Sigma \circ enc)(x_t)$.

$k_p = 0$: When $k_p = 0$, we get $dec(x_t) = (k_d^{-1} \circ \Sigma)(x_t)$ and $enc(x_t) = (k_d \circ \Delta)(x_t)$, so our reconstruction reduces to $\hat{x} = (k_d^{-1} \circ \Sigma \circ \Delta \circ R \circ \Sigma \circ k_d \circ \Delta)(x_t)$. Because $\Sigma \circ k_d \circ \Delta$ all commute with one another, we can simplify this to $\hat{x}_t = (k_d^{-1} \circ R \circ k_d)(x_t)$. so our decoded signal is $\hat{x}_t = round(x_t \cdot k_d)/k_d$, with no dependence on x_{t-1}. This is visible in the bottom row of Figure 1. This was the encoding scheme used in O'Connor and Welling (2016b).

$k_d = 0$: In this case, $dec(x_t) = k_p^{-1} x_t$ and $enc(x_t) = k_p x_t$ so our encoding-decoding process becomes $\hat{x} = (k_p^{-1} \circ \Delta \circ R \circ \Sigma \circ k_p)(x_t)$. In this case neither our encoder nor our decoder have any memory, and we take not advantage of temporal redundancy.

Figure 1: An example signal x_t (blue), encoded with k_p varying across rows and k_d varying across columns. s_t (black) is the quantized signal produced by the successive application of encoding (Equation 4) and quantization (Equation 3). $\hat{x}_t$ (orange) is the reconstruction of x_t produced by applying Equation 5 to s_t. One might, after a careful look at this figure, ask why we bother with the proportional (k_p) term at all? Figure 2 anticipates this question and answers it visually.

Figure 2: The problem with *only* sending changes in activation (i.e. $k_p = 0$) is that during training, weights change over time. In this example we generate random signals for a single scalar activation x_t and scalar weight w_t. We efficiently approximate z_t with $\hat{z}_t$, as described in Section 2.4. As the w_t changes over time, our estimate $\hat{z}$ diverges from the correct value. Introducing k_p allows us to bring our reconstruction back in line with the correct signal.

2.4 SPARSE COMMUNICATION BETWEEN LAYERS

The purpose of our encoding scheme is to reduce computation by sparsifying communication between layers of a neural network. Suppose we are trying to compute the pre-nonlinearity activation of the first hidden layer, $z_t \in \mathbb{R}^{d_{out}}$, given the input activation, $x_t \in \mathbb{R}^{d_{in}}$. We approximate z_t as:

$$z_t \triangleq x_t \cdot w_t \approx \hat{x}_t \cdot w_t \triangleq dec(Q(enc(x_t))) \cdot w_t \triangleq dec(s_t) \cdot w_t \approx dec(s_t \cdot w_t) \triangleq \hat{z}_t \tag{7}$$
$$\text{where: } x_t, \hat{x}_t \in \mathbb{R}^{d_{in}}; s_t \in \mathbb{I}^{d_{in}}; w \in \mathbb{R}^{d_{in} \times d_{out}}; z_t, \hat{z}_t \in \mathbb{R}^{d_{out}}$$

The first approximation comes from the quantization (Q) of the encoded signal, and the second from the fact that the weights change over time, as explained in Figure 2. The effects of these approximations are further explored in Section B of the Supplementary Material.

Computing z_t takes $d_{in} \cdot d_{out}$ multiplications and $(d_{in} - 1) \cdot d_{out}$ additions. The cost of computing $\hat{z}_t$, on the other hand, depends on the contents of s_t. If the data is temporally redundant, $s_t \in \mathbb{I}^{d_{in}}$

should be sparse, with total magnitude $S \triangleq \sum_i |s_{t,i}|$. s_t can be decomposed into a sum of one-hot vectors $s_t = \sum_{n=1}^{S} sign(s_{t,i_n})\gamma_{i_n} : i_n \in [1..d_{in}]$ where $\gamma_{i_n} \in \mathbb{I}^{d_{in}}$ is a onehot vector with element $\gamma_{i_n} = 1$. The matrix product $s_t \cdot w$ can then be decomposed into a series of row additions:

$$s_t \cdot w = \left(\sum_{n=1}^{N} \text{sign}(s_{t,i_n}) \cdot \gamma_{i_n} \right) \cdot w = \sum_{n=1}^{N} \text{sign}(s_{t,i_n})\gamma_{i_n} \cdot w = \sum_{n=1}^{N} \text{sign}(s_{t,i_n}) \cdot w_{i_n,}. \quad (8)$$

If we include the encoding, quantization, and decoding operations, our matrix product takes a total of $2d_{in} + 2d_{out}$ multiplications, and $\sum_n |s_{t,n}| \cdot d_{out} + 3d_{in} + d_{out}$ additions. Assuming the $\sum_n |s_{t,n}| \cdot d_{out}$ term dominates, we can say that the relative cost of computing $\hat{z}_t$ vs z_t is:

$$\frac{cost(\hat{z})}{cost(z)} \approx \frac{\sum_n |s_{t,n}| \cdot cost(add)}{d_{in} \cdot (cost(add) + cost(mult))} \quad (9)$$

2.5 A Neural Network

We can implement this encoding scheme on every layer of a neural network. Given a standard neural net f_{nn} consisting of alternating linear ($\cdot w_l$) and nonlinear (h_l) operations, our network function f_{pdnn} can then be written as:

$$f_{nn}(x) = (h_L \circ \cdot w_L \circ ... \circ h_1 \circ w_1)(x) \quad (10)$$
$$f_{pdnn}(x) = (h_L \circ w_L \circ Q_L \circ enc_L \circ ... \circ h_1 \circ dec_1 \circ \cdot w_1 \circ Q_1 \circ enc_1)(x) \quad (11)$$

We can use the same approach to approximately calculate our gradients to use in training. If we define our layer activations as $\hat{z}_l \triangleq (dec \circ \cdot w_l \circ Q \circ enc)(x)$ if $l = 1$ otherwise $(dec \circ \cdot w_l \circ Q \circ enc)(\hat{z}_{l-1})$, and $\mathcal{L} \triangleq \ell(f_{pdnn}(x), y)$, where ℓ is some loss function and y is a target, we can backpropagate the approximate gradients as:

$$\widehat{\frac{\partial \mathcal{L}}{\partial \hat{z}_l}} = \begin{cases} \frac{\partial \mathcal{L}}{\partial z_L} & \text{if } l = L \\ \left(\odot h_l'(\hat{z}_l) \circ dec \circ \cdot w_{l+1}^T \circ Q \circ enc \right) \left(\widehat{\frac{\partial \mathcal{L}}{\partial \hat{z}_{l+1}}} \right) & \text{otherwise} \end{cases} \quad (12)$$

On every layer of the forward and backward pass, our quantization scheme corrupts the signals that are being sent between layers. Nevertheless we find experimentally that this does not matter much to the performance of the network.

2.6 Parameter Updates

There's no use having an efficient backward pass if the parameter updates aren't also efficient. In a normal neural network trained with backpropagation and simple stochastic gradient descent, the parameter update for weight matrix w has the form $w \leftarrow w - \eta \frac{\partial \mathcal{L}}{\partial w}$ where η is the learning rate. If w connects layer $l - 1$ to layer l, we can write $\frac{\partial \mathcal{L}}{\partial w} = x_t \otimes e_t$ where $x_t \triangleq h_{l-1}(z_{l-1,t}) \in \mathbb{R}^{d_{in}}$ is the presynaptic activation, $e_t \triangleq \frac{\partial \mathcal{L}}{\partial z_{l,t}} \in \mathbb{R}^{d_{out}}$ is the postsynaptic (pre-nonlinearity) activation and $\otimes$ is the outer product. So we pay $d_{in} \cdot d_{out}$ multiplications to update the parameters for each sample.

We want a more efficient way to compute this product, which takes advantage of the sparsity of our encoded signals to reduce computation. We can start by applying our encoding-quantizing-decoding scheme to our input and error signals as $\bar{x}_t \triangleq (Q \circ enc)(x_t) \in \mathbb{I}^{d_{in}}$ and $\bar{e}_t \triangleq (Q \circ enc)(e_t) \in \mathbb{I}^{d_{out}}$, and approximate our true update update as $\widehat{\frac{\partial \mathcal{L}}{\partial w}}_{recon,t} \triangleq \hat{x}_t \otimes \hat{e}_t$ where $\hat{x}_t \triangleq dec(\bar{x}_t)$ and $\hat{e}_t \triangleq dec(\bar{e}_t)$. This doesn't do any good by itself, because the update rule still is not sparse. But, we can exactly compute the sum of this value over time using one of two sparse update schemes - *past updates* and *future updates* - which are depicted in Figure 3.

Past Updates: For a given synapse $w_{i,j}$, if either the presynaptic neuron spikes ($\bar{x}_{t_i} \neq 0$) or the postsynaptic neuron spikes ($\bar{e}_{t_i} \neq 0$), we increment the $w_{i,j}$ by the total area under $\hat{x}_{\tau,i}\hat{e}_{\tau,j}$ since the

Figure 3: A visualization of our efficient update schemes from Section 2.6. **Top**: A scalar signal representing a presynaptic neuron activation $x_t = h_{l-1}(z_l - 1)$, its quantized version, $\bar{x}_t = (Q \circ enc)(x_t)$, and its reconstruction $\hat{x}_t = dec(\bar{x}_t)$. **Middle**: Another signal, representing the postsynaptic gradient of the error $e = \frac{\partial \mathcal{L}}{\partial z_l}$, along with its quantized ($\bar{e}$) and reconstructed ($\hat{e}$) variants. **Bottom**: The true weight gradient $\frac{\partial \mathcal{L}}{\partial w_t}$, the reconstruction gradient $\frac{\hat{\partial \mathcal{L}}}{\partial w_t}$. At the time of the spike in $\bar{e}_t$, we have two schemes for efficiently computing the weight gradient that will be used to increment weight (see Section 2.6). The *past* scheme computes the area under $\hat{x} \cdot \hat{e}$ since the last spike, and the *future* scheme computes the total future additional area due to the current spike.

last spike. We can do this efficiently because between the current time and the time of the previous spike, $\hat{x}_{\tau,i} \hat{e}_{\tau,j}$ is a geometric sequence. Given a known initial value u, final value v, and decay rate r, a geometric sequence sums to $\frac{u-v}{1-r}$. The area calculated is shown in pink on the bottom row of Figure 3, and one algorithm to calculate it is in Equation 15.

Future Updates: Another approach is to calculate the Present Value of the future area under the integral from the current spike. This is depicted in the blue-gray area in Figure 3, and the formula is in Equation 16.

We give the formula for the Past and Future update rules in Appendix C.

Finally, because the magnitude of our gradient varies greatly over training, we create a scheme for adaptively tuning k_β to match the running magnitude of the data. This is described in detail in Appendix D.

2.7 RELATION TO STDP

An extremely attentive reader might have noted that Equation 16 has the form of an online implementation of Spike-Timing Dependent Plasticity (STDP). STDP (Markram et al., 2012) emerged from neuroscience, where it was observed that synaptic weight changes appeared to be functions of the relative timing of pre- and post-synaptic spikes. The empirically observed function usually has the double-exponential form seen on the rightmost plot of Figure 4.

Using the quantized input signal $\bar{x}$ and error signal $\bar{e}$, and their reconstructions $\hat{x}_t$ and $\hat{e}_t$ as defined in the last section, we define a causal convolutional kernel $\kappa_t = \left\{ k_\beta \left(k_\alpha \right)^t \text{ if } t \geq 0 \text{ otherwise } 0 \right\}$ and $g_t = \{\kappa_t \text{ if } t \geq 0 \text{ otherwise } \kappa_{-t}\} = k_\beta (k_\alpha)^{|t|}$ where $t \in I$. The middle plot of Figure 4 is a plot of g. We define our STDP update rule as:

$$\frac{\widehat{\partial \mathcal{L}}}{\partial w}_{t,STDP} = \left(\sum_{\tau=-\infty}^{\infty} \bar{x}_{t-\tau} g_\tau \right) \otimes \bar{e}_t \tag{13}$$

We note that while our version of STDP has the same double-exponential form as the classic STDP rule observed in neuroscience (Markram et al., 2012), we do not have the property that sign of the weight change depends on whether the presynaptic spike preceded the postsynaptic spike.

Figure 4: **Left**: Our STDP rule, when both the input and error spikes have the same sign. **Middle**: Our STDP rule, when the input and error spikes have opposite signs. **Right**: The classic STDP rule Markram et al. (2012), where the weight update is positive when a presynaptic spike preceeds a postsynaptic spike, and negative otherwise.

In Section C in the supplementary material we show experimentally that while Equations $\widehat{\frac{\partial \mathcal{L}}{\partial w}}_{recon}$, $\widehat{\frac{\partial \mathcal{L}}{\partial w}}_{past}$, $\widehat{\frac{\partial \mathcal{L}}{\partial w}}_{future}$, $\widehat{\frac{\partial \mathcal{L}}{\partial w}}_{stdp}$ may all result in different updates at different times, the rules are equivalent in that for a given set of pre/post-synaptic spikes $\bar{x}, \bar{e}$, the cumulative sum of their updates over time converges exactly.

3 EXPERIMENTS

3.1 TEMPORAL MNIST

To evaluate our network's ability to learn, we run it on the standard MNIST dataset, as well as a variant we created called "Temporal MNIST". Temporal MNIST is simply a reshuffling of the MNIST dataset so that so that similar inputs (in terms of L2-pixel distance), are put together. Figure 6 shows several snippets of consecutive frames in the temporal MNIST dataset. We compare our Proportional-Derivative Net against a conventional Multi-Layer Perceptron with the same architecture (one hidden layer of 200 ReLU hidden units and a softmax output). The results are shown in Figure 5. Somewhat surprisingly, our predictor slightly outperformed the MLP, getting 98.36% on the test set vs 98.25% for the MLP. We assume this improvement is due to the regularizing effect of the quantization. On Temporal MNIST, our network was able to converge with less computation than it required for MNIST (It used $32 \cdot 10^{12}$ operations for MNIST vs $15 \cdot 10^{12}$ for Temporal MNIST), but ended up with a slightly worse test score when compared with the MLP (the PDNN got 97.99% vs 98.28% for the MLP).

3.2 YOUTUBE VIDEO DATASET

Next, we want to simulate the setting of CCTV cameras, discussed in 1, where we have a lot of data with only a small amount of new information per frame. In the absence of large enough public CCTV video datasets, we investigate the surrogate task of frame-based object classification on wild YouTube videos from the large, recently released Youtube-BB dataset Real et al. (2017). Our subset consists of 358 Training Videos and 89 Test videos with 758,033 frames in total. Each video is labeled with an object in one of 24 categories.

We start from a VGG19 network (Simonyan and Zisserman, 2014): a 19-layer convolutional network pre-trained on imagenet. We replace the top three layer with three of our own randomly initialized layers, and train the network both as a spiking network, and as a regular network with backpropagation. While training the entire spiking network end-to-end works, we choose to only train the top layers, in order to speed up our training time.

We compare our training scores and computation between a spiking and non-spiking implementation. Figure 7 shows that our spiking network performs comparably to a non-spiking network, and Figure 8 shows how the computation per frame of our spiking network decreases as we increase the frame rate (i.e. as the input data becomes more temporally redundant). Because our spiking network uses only additions, while a regular deep network does multiply-adds, we use the estimated energy-costs per op of Horowitz (2014) to compare computations to a single scale, which estimates the amount of energy required to do multiplies and adds in fixed-point arithmetic.

Figure 5: Top Row: Results on MNIST. Bottom Row: Results on Temporal MNIST. Left Column: the training and test scores as a function of epoch. Middle: We now put the number of computational operations on the x-axis. We see that as a result our PDNN shifts to the left. Right: Because our network computes primarily with additions rather than multiplications. When we multiply our operation counts with the estimates of Horowitz (2014) for the computational costs of arithmethic operations (0.1pJ for 32-bit fixed-point addition vs 32pJ for multiplication), we can see that our algorithm would be at an advantage on any hardware where arithmetic operations were the computational bottleneck.

Figure 6: Some samples from the Temporal-MNIST dataset. Each column shows a snippet of adjacent frames.

Figure 7: Left: Learning Curves on the Youtube Dataset. Right: Learning curves with respect to computational energy using the conversion of Horowitz (2014). The spiking network slightly outperforms the non-spiking baseline - we suspect that this is because the added noise of spiking acts as a regularizer.

Figure 8: We simulate different frame-rates by selecting every n'th frame. This plot shows our network's total computation averaged over several snippets of video, at varying frame rates. As our frame rate increases, the computation per-frame of our spiking network goes down, while with a normal network it remains fixed.

4 RELATED WORK

There has been sparse but interesting work on merging the notions of spiking neural networks and deep learning. Diehl et al. (2015) found a way to efficiently map a trained neural network onto a spiking network. Lee et al. (2016) devised a method for training spiking of integrate-and-fire spiking neurons with backpropagation - though their neurons did not send a temporal difference of their activations. O'Connor and Welling (2016a) created a method for training event-based neural networks - but their method took no advantage of temporal redundancy in the data. Binas et al. (2016) and (O'Connor and Welling, 2016b) both took the approach of sending quantized temporal changes reduce computation on temporally redundant data, but their schemes could not be used to train a neural network. Bohte et al. (2000) showed how could apply backpropagation for training spiking neural networks, but it was not obvious how to apply the method to non-spiking data. Zambrano and Bohte (2016) developed a spiking network with an adaptive scale of quantization (which bears some resemblance to our tuning scheme described in Section D), and show that the spiking mechanism is a form of Sigma-Delta modulation, which we also use here. Similarly, Yoon (2017) found standard spiking neuron models actually implement a form of Sigma-Delta modulation. Courbariaux et al. (2015) showed that neural networks could be trained with binary weights and activations (we just quantize activations). Bengio et al. (2015) found a connection between the classic STDP rule (Figure 4, right) and optimizing a dynamical neural network, although the way they arrived at an STDP-like rule was quite different from ours.

5 DISCUSSION

We set out with the objective of reducing the computation in deep networks by taking advantage of temporal redundancy in data. We described a simple rule (Equation 4) for sparsifying the communication between layers of a neural network by having our neurons communicate a combination of their temporal change in activation, and the current value of their activation. We show that it follows from this scheme that neurons should behave as leaky integrators (Equation 5). When we quantize our neural activations with Sigma-Delta modulation, a common quantization scheme in signal processing, we get something resembling a leaky integrate-and-fire neuron. We derive efficient update rules for the weights of our network, and show these to be equivalent to a form of STDP - a learning rule first observed in neuroscience. Finally, we train our network, verify that it does indeed compute more efficiently on temporal data, and show that it performs about as well as a traditional deep network of the same architecture, but with significantly reduced computation. Finally, we show that our network can train on real video data.

The efficiency of our approach hinges on the temporal redundancy of our input data and neural activations. There is an interesting synergy here with the concept of slow-features (Wiskott, 1999). Slow-Feature learning aims to discover latent objects that persist over time. If the hidden units were to specifically learn to respond to slowly-varying features of the input, the layers in a spiking implementation of such a network would have to communicate less often. In such a network, the tasks of feature-learning and reducing inter-layer communication may be one and the same.

REFERENCES

Yoshua Bengio, Thomas Mesnard, Asja Fischer, Saizheng Zhang, and Yuhai Wu. An objective function for stdp. *arXiv preprint arXiv:1509.05936*, 2015.

Jonathan Binas, Giacomo Indiveri, and Michael Pfeiffer. Deep counter networks for asynchronous event-based processing. *CoRR*, abs/1611.00710, 2016. URL http://arxiv.org/abs/1611.00710.

Sander M Bohte, Joost N Kok, and Johannes A La Poutré. Spikeprop: backpropagation for networks of spiking neurons. In *ESANN*, pages 419–424, 2000.

James C Candy and Gabor C Temes. *Oversampling delta-sigma data converters: theory, design, and simulation*. University of Texas Press, 1962.

Matthieu Courbariaux, Yoshua Bengio, and Jean-Pierre David. Binaryconnect: Training deep neural networks with binary weights during propagations. *CoRR*, abs/1511.00363, 2015. URL http://arxiv.org/abs/1511.00363.

Peter U Diehl, Daniel Neil, Jonathan Binas, Matthew Cook, Shih-Chii Liu, and Michael Pfeiffer. Fast-classifying, high-accuracy spiking deep networks through weight and threshold balancing. In *2015 International Joint Conference on Neural Networks (IJCNN)*, pages 1–8. IEEE, 2015.

Mark Horowitz. 1.1 computing's energy problem (and what we can do about it). In *2014 IEEE International Solid-State Circuits Conference Digest of Technical Papers (ISSCC)*, pages 10–14. IEEE, 2014.

Jun Haeng Lee, Tobi Delbruck, and Michael Pfeiffer. Training deep spiking neural networks using backpropagation. *arXiv preprint arXiv:1608.08782*, 2016.

Henry Markram, Wulfram Gerstner, and Per Jesper Sjöström. Spike-timing-dependent plasticity: a comprehensive overview. *Frontiers in synaptic neuroscience*, 4, 2012.

Peter O'Connor and Max Welling. Deep spiking networks. *arXiv preprint arXiv:1602.08323*, 2016a.

Peter O'Connor and Max Welling. Sigma delta quantized networks. *arXiv preprint arXiv:1611.02024*, 2016b.

Esteban Real, Jonathon Shlens, Stefano Mazzocchi, Xin Pan, and Vincent Vanhoucke. Youtube-boundingboxes: A large high-precision human-annotated data set for object detection in video. *arXiv preprint arXiv:1702.00824*, 2017.

Karen Simonyan and Andrew Zisserman. Very deep convolutional networks for large-scale image recognition. *arXiv preprint arXiv:1409.1556*, 2014.

Laurenz Wiskott. Learning invariance manifolds. *Neurocomputing*, 26:925–932, 1999.

Young C Yoon. Lif and simplified srm neurons encode signals into spikes via a form of asynchronous pulse sigma–delta modulation. *IEEE transactions on neural networks and learning systems*, 28(5): 1192–1205, 2017.

Davide Zambrano and Sander M Bohte. Fast and efficient asynchronous neural computation with adapting spiking neural networks. *arXiv preprint arXiv:1609.02053*, 2016.

A SIGMA-DELTA UNWRAPPING

Here we show that $Q = \Delta \circ R \circ \Sigma$, where Q, Δ, R, Σ are defined in Equations 3, 2, 6, 1, respectively.

From Equation 3 (Q) we can see that

$$y_t \leftarrow round(x_t + \phi_{t-1}) \in \mathbb{I}$$
$$\phi_t \leftarrow \phi_{t-1} + x_t - y_t \in \mathbb{R}$$

Now we can unroll for y_t and observe use the fact that if $s \in \mathbb{I}$ then $round(a+s) = round(a) + s$, to say:

$$
\begin{aligned}
y_t &= round(x_t + \phi_{t-1}) \\
&= round(x_t + \phi_{t-2} + x_{t-1} - y_{t-1}) \\
&= round(x_t + x_{t-1} + \phi_{t-2}) - y_{t-1} \\
&= round(x_t + x_{t-1} + \phi_{t-2}) - round(x_{t-1} + \phi_{t-2}) \\
&= \left(round(\sum_{\tau=1}^{t} x_\tau + \cancel{\phi_0}^{\,0}) - \sum_{\tau=0}^{t-2} y_\tau \right) - \left(round(\sum_{\tau=1}^{t-1} x_\tau + \cancel{\phi_0}^{\,0}) - \sum_{\tau=0}^{t-2} y_\tau \right) \\
&= round(\sum_{\tau=1}^{t} x_\tau) - round(\sum_{\tau=1}^{t-1} x_\tau)
\end{aligned}
\tag{14}
$$

At which point it is clear that Q is identical to a successive application of a temporal summation, a rounding, and a temporal difference. That is why we say $Q = \Delta \circ R \circ \Sigma$.

B SCANNING THE K-SPACE

Equation 7 shows how we make two approximations when approximating $z_t = x_t \cdot w_t$ with $\hat{z}_t = (dec \circ w \circ Q \circ enc)(x_t)$. The first is the "nonstationary weight" approximation - arising from the fact that w changes in time, the second is the "quantization" approximation, arising from the quantization of x. Here do a small experiment in which we multiply a time-varying scalar signal x_t with a time-varying weight w_t for many different values of k_p, k_d to understand the effects of k_p, k_d on our approximation error.

Figure 9: **Top Left**: A time varying signal x_t, the quantized signal $Q(enc(x_t))$, and the time-varying "weight" w_t. **Bottom Left**: Compare the true product of these signals $x_t \cdot w_t$ with the $dec(enc(x_t) \cdot w_t)$, which shows the effects of the non-stationary weight approximation, and $dec(Q(enc(x_t)) \cdot w)$ which shows both approximations. **Top Middle**: The Cosine distance between the "true" signal $x \odot w$ and the approximation due to the nonstationary w, scanned over a grid of k_p, k_d values. **Top Right**: The cosine distance between the "true" signal and the approximation due to the quantization of x. **Bottom Middle**: The Cosine Distance between the "true" signal and the full approximation described in Equation 7. This shows why we need both k_p and k_d to be nonzero. **Bottom Right**: The Number of weight-lookups required for the to compute the full approximation. $dec(Q(enc(x)) \odot w)$.

C UPDATE ALGORITHMS

In Section 2.6, we visually describe what we call the "Past" and "Future" parameters updates. Here we give the algorithms for implementing these schemes.

To simplify our expressions in the update algorithms, we re-parametrize our k_p, k_d coefficients as $k_\alpha \triangleq= \frac{k_d}{k_p+k_d}$, $k_\beta \triangleq \frac{1}{k_p+k_d}$.

Figure 10: A comparison of our different update methods. **Top**: A randomly generated presynaptic quantized signal $\bar{x}$, along with its reconstruction $\hat{x}$. **Middle**: A randomly generated postsynaptic quantized error signal $\bar{e}$, along with its reconstruction $\hat{e}$. **Bottom**: The cumulative weight update arising from our four updates methods. "*recon*" is just $\sum_{\tau=1}^{t} \hat{x}_\tau \hat{e}_\tau$, "*past*" and "*future*" are described in Section 2.6 and "*STDP*" is described in Section 2.7

In Section 2.6 and 2.7, we described 4 different update rules, and stated that while they do not necessarily produce the same updates at the same times, they produce the same result in the end. Here we demonstrate this empirically. We generate two random spike-trains representing the input and the error signal to a single synapse. The plot on the bottom shows our weight as a function of time as it drifts from its initial value.

$$past : (\bar{x} \in \mathbb{I}^{d_{in}}, \bar{e} \in \mathbb{I}^{d_{out}}) \mapsto \widehat{\frac{\partial \mathcal{L}}{\partial w}}_{past}$$

$$\text{Persistent: } w, u \in \mathbb{R}^{d_{in} \times d_{out}},$$
$$\hat{x} \leftarrow 0^{d_{in}}, \hat{e} \leftarrow 0^{d_{out}}$$
$$i \leftarrow \bar{x} \neq 0, \quad j \leftarrow \bar{e} \neq 0$$
$$\hat{x} \leftarrow k_\alpha \hat{x} \quad , \quad \hat{e} \leftarrow k_\alpha \hat{e}$$
$$v \leftarrow \hat{x}_i \otimes \hat{e}_j \in \mathbb{R}^{\sum_{i'} [\bar{x}_{i'} \neq 0] \times \sum_{j'} [\bar{e}_{j'} \neq 0]}$$
$$\widehat{\frac{\partial \mathcal{L}}{\partial w}}_{past,i,j} \leftarrow \frac{u_{i,j} - v}{1 - k_\alpha^2}$$
$$\hat{x} \leftarrow \hat{x} + k_\beta \bar{x}, \quad \hat{e} \leftarrow \hat{e} + k_\beta \bar{e}$$
$$u_{i,j} \leftarrow v$$

$$(15)$$

$$future : (\bar{x} \in \mathbb{I}^{d_{in}}, \bar{e} \in \mathbb{I}^{d_{out}}) \mapsto \widehat{\frac{\partial \mathcal{L}}{\partial w}}_{future}$$

$$\text{Persistent: } w \in \mathbb{R}^{d_{in} \times d_{out}},$$
$$\hat{x} \leftarrow 0^{d_{in}}, \hat{e} \leftarrow 0^{d_{out}}$$
$$\hat{x} \leftarrow k_\alpha \hat{x}$$
$$\hat{e} \leftarrow k_\alpha \hat{e} + k_\beta \bar{e}$$
$$\widehat{\frac{\partial \mathcal{L}}{\partial w}}_{future} \leftarrow \frac{\bar{x} \otimes \hat{e} + \hat{x} \otimes \bar{e}}{k_\alpha^2 - 1}$$
$$\hat{x} \leftarrow \hat{x} + k_\beta \bar{x}$$

$$(16)$$

D TUNING k_p, k_d

The smaller the magnitude of a signal, the more severely distorted it is by our quantization-reconstruction scheme. We can see that scaling a signal by K has the same effect on the quantized version of the signal, s_t, as scaling k_p and k_d by K: $s_t = (Q \circ enc_{k_p,k_d})(Kx_t) = Q(k_p K x_t + k_d(K x_t - K x_{t-1})) = Q(K k_p x_t + K k_d(x_t - x_{t-1})) = (Q \circ enc_{K k_p, K k_d})(x_t)$. The fact that the reconstruction quality depends on the signal magnitude presents a problem when training our network, because the error gradients tend to change in magnitude throughout training (they start large, and become smaller as the network learns). To keep our signal within the useful dynamic range of the quantizer, we apply simple scheme to heuristically adjust k_p and k_d for the forward and backward passes separately, for each layer of the network. Instead of directly setting k_p, k_d as hyperparameters, we fix the ratio $k_\alpha \triangleq \frac{k_d}{k_p + k_d}$, and adapt the scale $k_\beta \triangleq \frac{1}{k_p + k_d}$ to the magnitude of the signal. Our update rule for k_β is:

$$\mu_t = (1 - \eta_k)\mu_{t-1} + \eta_k \cdot |x_t|_{L_1}$$
$$k_\beta = k_\beta + \eta_k(k_\beta^{rel} \cdot \mu_t - k_\beta)$$

$$(17)$$

Where η_k is the scale-adaptation learning rate, μ_t is a rolling average of the L_1 magnitude of signal x_t, and k_β^{rel} defines how coarse our quantization should be relative to the signal magnitude (higher means coarser). We can recover k_p, k_d for use in the encoders and decoders as $k_p = (1 - k_\alpha)/k_\beta$ and $k_d = k_\alpha/k_\beta$. In our experiments, we choose $\eta_k = 0.001, k_\beta^{rel} = 0.91, k_{alpha} = 0.91$, and initialize $\mu_0 = 1$.

E   THE YOUTUBE DATASET

Figure 11: 16 Frames from the Youtube-BB dataset. The dataset consists videos, with each video annotated as having one of 24 objects in it. It also comes with annotated bounding-boxes, which we do not use in this study.

F   INSTABILITY IN NEURAL NETWORK REPRESENTATIONS

Figure 8 seems to show that computation doesn't quite approach zero as our frame-rate increases, but flat-lines at a certain point. We think this may have to do with the fact that hidden layer activations are not necessarily smoother in time than the input.

We demonstrate this with a figure, which, using 5 video snippets from the Youtube-BB dataset, measures how much the average relative change in layer activation: $\frac{|a_t - a_{t-1}|}{2(|a_t| + |a_{t-1}|)}$ varies as we increase our frame-rate. (Note that we vary our frame-rate artificially by sub-sampling frames).

Figure 12: The average relative change in layer activation between frames, as frame-rate increases. For increasing network depth (red=shallow, violet=deep)