Tractable Latent State Inference for Hidden Continuous-Time semi-Markov Chains

Abstract

Hidden semi-Markov Models (HSMM's) - while broadly in use - are restricted to a discrete and uniform time grid. They are thus not well suited to explain often irregularly spaced discrete event data from continuous-time phenomena. We show that non-sampling-based latent state inference used in HSMM's can be generalized to latent Continuous-Time semi-Markov Chains (CTSMC's). We formulate integro-differential forward and backward equations adjusted to the observation likelihood and introduce an exact integral equation for the Bayesian posterior marginals and a scalable Viterbi-type algorithm for posterior path estimates. All presented equations can be efficiently solved using existing numerical methods. We evaluate our approaches in latent state inference scenarios in comparison to classical HSMM's.

1   Introduction

Continuous-Time semi-Markov Chains (CTSMC's) comprise the continuous time analogue of (discrete-time) semi-Markov chains. In comparison to Markov chains, semi-Markov chains allow to model non-exponential, arbitrary waiting times between state changes. This more accurately matches such times occurring in many scientific fields [11]. Hidden semi-Markov Models (HSMM's) on finite state spaces have seen wide application and thorough research [22]. However, confronted with measurements from continuous-time systems, their adaptivity is limited and computation might become unnecessarily expensive. Because of that, continuous-time analogues of HSMM's have seen increased research interest lately [17, 1, 6, 7]. However, latent state inference is hard in continuous time, since the usual methods demand a reformulation of the process to obtain the Markov property. Markovianization by state space expansion as used for HSMM's demands propagation of a semi-infinite uncountable state for latent CTSMC's even if the original state space is finite. Thus, besides ad-hoc discretization, two classes of solution methods have emerged. First, a variety of sampling-based solutions has been published, often targeted at even generalized problems [7, 2, 1, 9]. Second, if non-sampling based solutions are sought, state-space expansions based on approximations of waiting time measures are available [16]. This second class, by detour, essentially tries to approximate Kolmogorov's (forward/backward) equations. However, a general framework - not tailored to specific families of waiting time measures - is still lacking. Kolmogorov's equations in integro-differential form have been studied recently [20]. Although initial or terminal states are given, the equations rely on specific boundary conditions to restrict the non-Markovian process to the considered time-window. Fixed conditions hinder the equations' usage in latent state inference which typically spans many such time-windows. To alleviate this restriction, we show how to adjust the memory terms in Kolmogorov's equations to include observations. As a consequence, we provide general forward and a backward algorithms, each encoded in a single inhomogeneous integro-differential equation. We also provide a method for exact Bayesian smoothing which uses the quantities obtained from the forward and backward algorithms. As a corollary, we propose a Viterbi-type approach for maximum-a-posteriori path estimation and sketch a method to implement adaptive step-size HSMM's

that keep their homogenous properties. The resulting general framework may incorporate arbitrary numerical solvers or make use of approximations by the mentioned second class of solution methods.

Related Work. Continuous-time HMM's and their inference has recently been compiled by [14]). Although tailored to a specific problem, an interesting MAP path estimation method for CT-HSMM's based on stochastic state classes has been published in [5]. Neural ODE's for the progression of memory variables have been investigated in [7]). An application of CT-HSMM's including parameter inference using a discretized waiting time variable [6, 17]. Generalized HSMM's that are lossless continuous discretizations but the transitions are observable has been proposed in [21]. An elaborate forward-filtering-backward-sampling for a HASMM [1]. To our knowledge, we are the first to introduce a "traditional" form of a forward-backward algorithm for a latent CTSMC. Also, while [5] is able to do MAP estimates of trajectories as well, their method is very different to our approach.

Notation. To maintain readability, we use the symbol P to denote density and mass functions alike. Which kind is needed should be clear from the context. Nonetheless, we refer to appendix section A for derivations and proofs using a stricter notation style.

1.1 Continuous-Time semi-Markov Chains

A continuous-time semi-Markov chain (CTSMC) $\{X(t)\}_{t\geq 0}$ on a countable state space $\mathcal{X}$ is a stochastic jump process. The general process is described by transition rates $\lambda : \mathcal{X} \times \mathbb{R}_{\geq 0} \times \mathbb{R}_{\geq 0} \times \mathcal{X} \to \mathbb{R}_{\geq 0}$. Conditioned on the current state $x \in \mathcal{X}$ at time $t \in \mathbb{R}_{\geq 0}$ and the time τ since the last transition at $t - \tau < t$, the rates $\lambda(x, \tau, t; x')$ describe the probability per unit time of transitioning shortly after time t to state x'. These transition rates suffice to resolve the waiting times and jump directions for each tuple (x, τ) at all times t. In this work, we restrict ourselves to CTSMC's which are homogeneous and direction-time independent. The former means that $\lambda(x, \tau, t; x') \equiv \lambda(x, \tau; x')$ at all times t. The latter additionally implies the factorization $\lambda(x, \tau; x') \equiv m(x' \mid x)\lambda(x, \tau)$ with the exit rate $\lambda(x, \tau) \equiv \sum_{x' \neq x} \lambda(x, \tau; x')$ and the transition probabilities of the embedded Markov chain $m(x' \mid x)$. Satisfying $\sum_{x' \neq x} m(x' \mid x) = 1$, i.e., excluding self-transitions, they form a categorical distribution over next states $x' \neq x$. Under direction-time independence, the waiting time in each state is thus statistically independent of the jump direction.

In this setting, for each state x, we have the waiting time measures $F(\tau \mid x) = 1 - \Lambda(\tau \mid x)$ with survival/tail functions $\Lambda(\tau \mid x) = \exp\left(-\int_0^\tau \mathrm{d}\tau'\, \lambda(x, \tau')\right)$ and their densities $f(\tau \mid x) = \lambda(x, \tau)\Lambda(\tau \mid x)$. For convenience of notation, we also introduce the forward transition operator of the embedded Markov chain M acting on a test-function g by $\mathsf{M}g(x, t) \equiv \sum_{x' \neq x} m(x \mid x')g(x', t)$ and its backward adjoint $\mathsf{M}^\dagger$, for which $\mathsf{M}^\dagger g(x, t) \equiv \sum_{x' \neq x} m(x' \mid x)g(x', t)$ holds.

Further, a homogeneous continuous-time Markov chain (CTMC) is a homogeneous and direction-time independent CTSMC which has constant rates in each state. As such, the rates $\lambda(x, \tau) \equiv \lambda(x)$ are left dependent only on the current state. Thus, the waiting time measures are strictly exponential and so $F(\tau \mid x) = 1 - \exp(-\lambda(x)\tau)$ and $f(\tau \mid x) = \lambda(x)\exp(-\lambda(x)\tau)$. Though significantly less expressive, inference in CTMC's is by large parts available analytically [18].

1.2 Observation Model

In this work, we consider a hidden continuous-time semi-Markov model, where the latent process is a CTSMC $\{X(t)\}_{t\geq 0}$. Its state $X(t)$ is observable indirectly by means of a dependent random variable $Y(t) \in \mathcal{Y}$ on an observation space $\mathcal{Y}$ available only at discrete time instances $t_0 < t_1 < \cdots < t_K$ assuming events $y_0, y_1, \ldots, y_K$. The conditional $P(Y(t_k) = y_k \mid X(t_k) = x)$ (understood as a likelihood in x) is assumed to be known at observation instances. Finally, we will often write events in the form $\mathbf{y}_{[t', t)}$ denoting the joint event obtained by intersecting single observation events, i.e., $\mathbf{y}_{[t', t)} \equiv \bigcap_{t_k \in [t', t)} \{Y(t_k) = y_k\}$.

1.3 General Idea

Latent state inference in Markov processes generally relies on the exploitation of their Markov property. It allows to describe the posterior latent state probability as a product of a forward and backward term. While the forward terms account for the probability of past observations at any time instance t, the backward terms describe the likelihood of future observations starting from t. In the

semi-Markov case, such a factorization is generally not possible, i.e. for a state $X(t) = x_t$

$$\underbrace{P\left(x_t \mid \mathbf{y}_{[0,T)}\right)}_{\text{posterior}} \underset{\not\propto}{\not\propto} \underbrace{P\left(x_t \mid \mathbf{y}_{[0,t)}\right)}_{\text{forward}} \times \underbrace{P\left(\mathbf{y}_{[t,T)} \mid x_t\right)}_{\text{backward}}. \tag{1}$$

However, as the name suggests, semi-Markov processes do not always violate the Markov property. In particular, the process is Markov at jump instances [13]. Thus, with respect to state changes, we can again find a factorization similar to (1). To be made precise later, let Δ_t denote the event of $X(t)$ transitioning to a state $x \in \mathcal{X}$ from a different state $X(t^-) \neq x$ at time instance t. Then, in contrast to (1) it holds that

$$\underbrace{P\left(\Delta_t \mid \mathbf{y}_{[0,T)}\right)}_{\text{posterior}} \underset{\propto}{\propto} \underbrace{P\left(\Delta_t \mid \mathbf{y}_{[0,t)}\right)}_{\text{forward}} \times \underbrace{P\left(\mathbf{y}_{[t,T)} \mid \Delta_t\right)}_{\text{backward}}, \tag{2}$$

where P now takes on the form of a density instead of the mass functions in (1). The term $P(\Delta_t \mid \mathbf{y}_{[0,t)})$ in (2) can be calculated under history dependence while the term $P(\mathbf{y}_{[t,T)} \mid \Delta_t)$ is by definition independent of any past trajectory up to t since it is conditioned on the state change at t. In the following, we refer to such quantities like those occuring on the right-hand side of (2) as "currents".

2 Forward and Backward Currents

Probability currents - in the context of Markov chains - are known from the balance equation [19]. They also occur in the description of other stochastic processes [12], CTSMC's in particular as well [15, 3]. In this section, we establish a general framework of input and output probability and likelihood currents under observations which is needed for the inference methods afterwards.

2.1 Input and Output Currents in Continuous-Time semi-Markov Chains

Consider again a CTSMC $\{X(t)\}_{t \geq 0}$ on a countable state space $\mathcal{X}$. Let a state $x \in \mathcal{X}$ of the chain and a time instance $t \in \mathbb{R}_{\geq 0}$ be given. The following events form the core of the following section. Let $\nabla_h(x, t) \equiv \{X(t) = x, X(t+h) \neq x\}$ denote the joint event of being in two different states x and some $x' \neq x$ at the beginning and end of a time-window of length h past t, i.e. the event of leaving state x between t and $t+h$. Let in contrast further $\Delta_h(x, t) \equiv \{X(t) \neq x, X(t+h) = x\}$ denote the joint event of being in state $x' \neq x$ at the beginning of the window and in state x at the end, i.e. entering state x between t and $t+h$. Then, we can quantify the flow of probability into x per unit time with $\phi(x, t) \equiv \lim_{h \to 0} \frac{1}{h} P(\Delta_h(x, t))$. We call the quantity $\phi(x, t)$ the input current of state x at t. Analogously, we define the output current by $\psi(x, t) \equiv \lim_{h \to 0} \frac{1}{h} P(\nabla_h(x, t))$.

In the following, we may omit function arguments if they are the same for all functions. Let the marginal probability of being in state x at t be denoted by $p(x, t) \equiv P(X(t) = x)$. Then, p is related to the input and output currents by

$$\frac{\mathrm{d}}{\mathrm{d}t} p = \phi - \psi = (\mathsf{M} - \mathsf{I}) \psi \quad \Leftrightarrow \quad \frac{\mathrm{d}}{\mathrm{d}t} p(x, t) = \sum_{x' \neq x} m(x \mid x') \psi(x', t) - \psi(x, t), \tag{3}$$

where $\mathsf{I}\psi \equiv \psi$ is the identity operator. This equation is equivalent to the forward equation in an inhomogeneous CTMC and the currents $\phi(x, t)$, $\psi(x, t)$ can directly be derived from it (see appendix section A). The input and output currents are related by the forward transition operator of the embedded Markov chain $\phi = \mathsf{M}\psi$. The following Markov property makes the currents important w.r.t.. (2). Let $\mathbf{x}_{[t, t')}$ denote the trajectory of $X(t)$ in the interval $[t', t)$. Then, $\lim_{h \to 0} P\left(\mathbf{x}_{[t,T)} \mid \Delta_h(x, t), \mathbf{x}_{[0,t)}\right) = \lim_{h \to 0} P\left(\mathbf{x}_{[t,T)} \mid \Delta_h(x, t)\right)$ for any x and t. Thus, the current $\phi(x, t)$ specifies the probability per unit time of the CTSMC having the Markov property at t next to entering state x. On the other hand $\psi(x, t)$ specifies the likelihood of being Markov at t and entering an arbitrary state $x' \neq x$. An illustration of input and output currents is given in Fig. 1.

In this work, we talk about forward or filtered currents specifically if we condition on past observations. For these, we write $\phi_\alpha(x, t) \equiv \lim_{h \to 0} \frac{1}{h} P\left(\Delta_h(x, t) \mid \mathbf{y}_{[0,t)}\right)$ and $\psi_\alpha(x, t) \equiv \lim_{h \to 0} \frac{1}{h} P\left(\nabla_h(x, t) \mid \mathbf{y}_{[0,t)}\right)$. We use the notation $\alpha(x, t) = P\left(X(t) = x \mid \mathbf{y}_{[0,t)}\right)$ for the

Figure 1: *a)* Illustration of input and output currents to and from state x in a 3-state chain. Like an electric current quantifying the flow of charge across a set of wires, a probability current quantifies the flow of probability across a set of edges in the graph for an infinitesimal duration. Particularly, currents describing probability (and likelihood) flow into and out of single states are important in this work; *b)*, *c)*, *d)* Exemplary calculations of forward α *(b)*, backward β *(c)* and posterior $\hat{p}$ *(d)* marginals from equations (10) and (12) for only start- and endpoint constraints (Kolmogorov equations) for a three-state chain with Gamma waiting time distributions. The markers show a HSMM approximation with a step-size $h = 10^{-3}$.

forward marginals. For the forward currents and marginals (3) holds unaltered. We comple-
ment the forward currents with backward currents $\phi_\beta (x, t) \equiv \lim_{h \to 0} P \left(\mathbf{y}_{[t, T)} \mid \Delta_h (x, t) \right)$ and
$\psi_\beta (x, t) \equiv \lim_{h \to 0} P \left(\mathbf{y}_{[t, T)} \mid \nabla_h (x, t) \right)$. We also assume a terminal condition to be fixed at T.
Forward and backward currents share important properties. Let $\beta (x, t) = P \left(\mathbf{y}_{[t, T)} \mid X (t) = x \right)$
be a marginal likelihood complementing $\alpha (x, t)$. Then, we have for α, β and the both currents

$$\frac{\mathrm{d}}{\mathrm{d}t}\alpha = \phi_\alpha - \psi_\alpha = (\mathsf{M} - \mathsf{I}) \psi_\alpha \qquad \Big| \qquad \frac{\mathrm{d}}{\mathrm{d}t}\beta = \psi_\beta - \phi_\beta = \left(\mathsf{I} - \mathsf{M}^\dagger \right) \phi_\beta \tag{4}$$

while the backward currents are related by $\psi_\beta = \mathsf{M}^\dagger \phi_\beta$. Like (3), a resemblance to classical forward
and backward equations in a CTMC is not coincidental in (4). We have seen that knowledge of
the currents ϕ_α, ψ_α and ψ_β, ϕ_β fully enables calculation of forward and backward terms. In the
following, we will outline the necessary equations to determine them.

2.2 Obtaining the Forward and Backward Currents through Integral Equations

The input and output currents have an interpretation as a marginalization over paths. This, and
their relation to the forward and backward terms (4), enables us to determine how the observations
contribute to α and β in the history dependent CTSMC. In the following, we will use the shorthand
$\mathbf{x}_{[t', t)} = x$ to denote the event of the trajectory $\mathbf{x}_{[t', t)}$ being constant in $X (\tau) = x$, $\forall \tau \in [t', t)$.
We begin by resolving a relationship between p and ϕ fundamental to CTSMC's. Note, that the
probability per unit time of $X (t)$ entering state x at $t - \tau$, $\tau > 0$, and staying in x at least until
t, can be given by $\Lambda (\tau \mid x) \phi (x, t - \tau) = \lim_{h \to 0} \frac{1}{h} P \left(\mathbf{x}_{[t-\tau, t)} = x, \Delta_h (x, t - \tau) \right)$. To obtain
$p (x, t)$, we need to marginalize over all trajectories $\mathbf{x}_{[t-\tau, t)}$ having state x at time t. Because of the
Markov property at $t - \tau$, we only need to marginalize over all constant trajectories $\mathbf{x}_{[0, t-\tau)} = x$.
Thus, we are left to integrate over all $\tau > 0$ to obtain $p (x, t)$. We stop at $\tau = t$ and insert an initial
condition from there. Doing this, we obtain the fundamental relationship

$$p = \mathsf{L}\phi + g_p \quad \Leftrightarrow \quad p (x, t) = \int_0^t \mathrm{d}\tau \, \Lambda (t - \tau \mid x) \phi (x, \tau) + g_p (x, t) \tag{5}$$

where L is a convolutional integral operator defined by $\mathsf{L}\phi (x, t) \equiv \int_0^t \mathrm{d}\tau \, \Lambda (t - \tau \mid x) \phi (x, \tau)$.
The inhomogeneity $g_p : \mathcal{X} \times \mathbb{R}_{\geq 0} \to \mathbb{R}_{\geq 0}$ is a known general function and implements the initial
condition. Choices for g_p will be discussed in section 4. Instead of asking for x to be kept from $t - \tau$
at least until t, we may also demand a transition shortly after t to another state to obtain an expres-
sion for ψ. This probability per unit time can then be given by $\lambda (x, \tau) \Lambda (\tau \mid x) \phi (x, t - \tau) = f (\tau) \phi (x, t - \tau) = \lim_{h \to 0} \frac{1}{h} P \left(\nabla_h (x, t - \tau), \mathbf{x}_{[t-\tau, t)} = x, \Delta_h (x, t - \tau) \right)$. As the result of a
marginalization over trajectories similar to (5), i.e. integration over $\tau > 0$, we then obtain

$$\psi = \mathsf{F}\phi + g_\phi \tag{6}$$

with the integral operator $\mathsf{F}\phi (x, t) \equiv \int_0^t \mathrm{d}\tau \, f (t - \tau \mid x) \phi (x, \tau)$. Again, g_ϕ implements the initial
condition. Note, that we can understand this as an expectation $\psi (x, t) = \mathsf{E} [\phi (x, t - \cdot)]$ over the

159 waiting time in state x. Differentiating (5) w.r.t. time t and comparing the result with (3) and (6), we
160 get the relation of the inhomogeneities $\frac{\mathrm{d}}{\mathrm{d}t}g_p + g_\phi = 0$. Remembering that $\phi = \mathsf{M}\psi$, we can obtain
161 the two identities $\psi = \mathsf{FM}\psi + \mathsf{M}g_\psi$ and $\phi = \mathsf{MF}\phi + g_\phi$ where $g_\phi = \mathsf{M}g_\psi$.

162 In the following, we account for observations and then close with the backward currents. Let
163 $\upsilon\left(x, t', t\right) \equiv P\left(\mathbf{y}_{[t', t)} \mid \mathbf{x}_{[t', t)} = x\right) / P\left(\mathbf{y}_{[t', t)} \mid \mathbf{y}_{[0, t')}\right)$ be the normalized joint observation
164 likelihood of the constant latent trajectory $\mathbf{x}_{[t', t)} = x$. The normalizer $P\left(\mathbf{y}_{[t', t)} \mid \mathbf{y}_{[0, t')}\right)$ is the
165 same as implicitly used when normalizing in a CTMC filtering update. The $\upsilon\left(x, t', t\right)$ is then a
166 t-family of piece-wise constant functions with discontinuities in the t'-direction (or vice-versa). For
167 convenience, we define the modified integral operator $\mathsf{F}_\alpha\phi\left(x, t\right) \equiv \int_0^t \mathrm{d}\tau\, f_\upsilon\left(\tau, t \mid x\right)\phi\left(x, \tau\right)$,
168 where $f_\upsilon\left(\tau, t \mid x\right) \equiv \upsilon\left(x, \tau, t\right) f\left(t - \tau \mid x\right)$. We also define $\mathsf{L}_\alpha\phi\left(x, t\right)$ for $\Lambda_\upsilon\left(\tau, t \mid x\right) \equiv$
169 $\upsilon\left(x, \tau, t\right)\Lambda\left(t - \tau \mid x\right)$ analoguously. Let further $\upsilon_0\left(x, t\right) \equiv \upsilon\left(x, 0, t\right)$ be a shorthand for υ in the
170 interval $[0, t)$. Then, we can generalize (5) and (6) to obtain

$$\alpha = \mathsf{L}_\alpha\phi_\alpha + \upsilon_0 g_p \quad \text{and} \quad \psi_\alpha = \mathsf{F}_\alpha\phi + \upsilon_0 g_\phi. \tag{7}$$

171 From (7) immediately follow the identities $\psi_\alpha = \mathsf{F}_\alpha\mathsf{M}\psi_\alpha + \upsilon_0\mathsf{M}g_\psi$ and $\phi_\alpha = \mathsf{MF}_\alpha\phi_\alpha +$
172 $\upsilon_0 g_\phi$. The backward currents obey relations analogous to (7). In the following, we
173 will perform the similar construction. Consider the product $f\left(\tau \mid x\right)\psi_\beta\left(x, t+\tau\right) =$
174 $\lim_{h\to 0} P(\mathbf{y}_{[t, T)}, \nabla_h\left(x, t+\tau\right), \mathbf{x}_{[t, t+\tau)} = x \mid \Delta_h\left(x, t\right))$. It gives the likelihood of keeping
175 state x in the interval $[t, t+\tau)$, then leaving, and along the path encountering any future observa-
176 tions, given an entry in state x at t. Thus, $\phi_\beta\left(x, t\right)$ can be obtained again by marginalization over
177 future trajectories. The marginal likelihood $\beta\left(x, t\right)$ can also be shown to maintain an analogous
178 relationship with $\Lambda\left(\tau \mid x\right)\psi_\beta\left(x, t+\tau\right)$. This is obtained by a two-side marginalization along state
179 entry $\Delta_h\left(x, t-\tau\right)$ and exit $\nabla_h\left(x, t+\tau'\right)$ while implying no information on the time of entry $t-\tau$.
180 We refer to appendix section A for the derivation, since it takes more steps. In the reverse direction
181 as we did for the forward case (7), we similarly normalize β and the backwards currents ψ_β, ϕ_β
182 by $P\left(\mathbf{y}_{[t, t')} \mid \mathbf{y}_{[0, t)}\right)$. This requires a full forward pass to be performed before the backward cal-
183 culations. Define the integral operators $\mathsf{F}_\beta\psi\left(x, t\right) \equiv \int_t^T \mathrm{d}\tau\, f_\upsilon\left(t, \tau \mid x\right)\psi\left(x, \tau\right)$ and $\mathsf{L}_\beta\psi\left(x, t\right)$
184 for $\Lambda_\upsilon\left(t, \tau \mid x\right)$ analogously. Let further again $\upsilon_T\left(x, t\right) \equiv \upsilon\left(x, t, T\right)$ be a shorthand for υ in the
185 interval $[t, T)$. As a conclusion, we obtain the relations

$$\beta = \mathsf{L}_\beta\psi_\beta + \upsilon_T\gamma_p \quad \text{and} \quad \phi_\beta = \mathsf{F}_\beta\psi_\beta + \upsilon_T\gamma_\psi, \tag{8}$$

186 where the inhomogeneities γ_p and γ_ψ implement the terminal condition. Note, that we write γ to
187 distinguish from the g for the initial conditions. Again by differentiation and consultation of (4),
188 we can find $\frac{\mathrm{d}}{\mathrm{d}t}\gamma_p + \gamma_\phi = 0$. Like before, the recurrence relations $\phi_\beta = \mathsf{M}^\dagger\mathsf{F}_\beta\phi_\beta + \upsilon_T\gamma_\psi$ and
189 $\phi_\beta = \mathsf{F}_\beta\mathsf{M}^\dagger\phi_\beta + \upsilon_T\mathsf{M}^\dagger\gamma_\phi$ follow. Also, $\gamma_\psi = \mathsf{M}^\dagger\gamma_\phi$. Note, that if there are no observations and we
190 only keep the terminal condition, a particular case of both equations in (8) similar to (5) and (6) is
191 obtained.

3 Integro-Differential Forward and Backward Equations

193 We first briefly sketch the derivation of Kolmogorov's forward equation. Our goal is a direct relation
194 between $\frac{\mathrm{d}}{\mathrm{d}t}p$ and p. We start out with (3) relating $\frac{\mathrm{d}}{\mathrm{d}t}p$ and ψ. We then have (6) expressing ψ in terms
195 of ϕ and we also have (5) expressing p in terms of ϕ. Convolutional equations can be conveniently
196 treated using the Laplace transform. We use it on (5) to express ϕ by a convolution of p, then plug
197 the result into (6) to express ψ in terms of p. The latter result is then inserted into (3) to express $\frac{\mathrm{d}}{\mathrm{d}t}p$
198 in terms of p. The result in the time domain is then

$$\frac{\mathrm{d}}{\mathrm{d}t}p = (\mathsf{M} - \mathsf{I})\,\mathsf{K}p + g \tag{9}$$

$$\Leftrightarrow \frac{\mathrm{d}}{\mathrm{d}t}p\left(x, t\right) = \int_0^t \mathrm{d}\tau \sum_{x' \neq x} m\left(x \mid x'\right)\kappa\left(x', t-\tau\right)p\left(x', \tau\right) - \kappa\left(x, t-\tau\right)p\left(x, \tau\right) + g\left(x, t\right)$$

199 with the integral operator $\mathsf{K}p\left(x, t\right) \equiv \int_0^t \mathrm{d}\tau\, \kappa\left(x, t-\tau\right)p\left(x, \tau\right)$. The memory kernel κ is then
200 given by $\mathcal{L}\left\{\kappa\right\}\left(x, s\right) \equiv \mathcal{L}\left\{f\right\}\left(s \mid x\right)\big/\mathcal{L}\left\{\Lambda\right\}\left(s \mid x\right)$ with the symbol $\mathcal{L}$ denoting the Laplace
201 transform with the Laplace variable s. The inhomogeneity g will be discussed at the end of the
202 section.

In the following, we implement observations and introduce the backward case. Equation (9) is not simply understood as a path marginalization like (5) or (6). However, the path-wise contribution of the observation likelihood carries over from (7) and (8) to equation (9) if the likelihood function $\upsilon(x, t', t)$ is piecewise constant. The analogue can be shown for the backward case. The rationale is to subdivide the time-domain into intervals where $\upsilon(x, t', t)$ is constant under variation of either t in the forward case or t' in the backward case. The two-argument functions $\bar{\upsilon}(x, \tau) \equiv \upsilon(x, \tau, t)$ (forward) and $\underline{\upsilon}(x, \tau) \equiv \upsilon(x, t', \tau)$ (backward) are then simple stepped functions under application of $\mathcal{L}$. The following derivations are executed in detail in Appendix section A.

To obtain the forward equation, we repeat the steps to obtain (9) but instead use our extended equations (7) for each time interval. For the backward equation, we do the following steps. With (4) and the two equations in (8) we have a similar toolset to the forward case. Thus, we apply the Laplace transform to the left equation of (8). We then insert ψ_β expressed through β into the right equation of (8) which gets us ϕ_β in terms of β. Inserting this expression into (4) yields the backward equation valid for the considered time-interval. Joining the obtained sequences of equations back together in both cases yields the forward and backward equations

$$\frac{\mathrm{d}}{\mathrm{d}t}\alpha = (\mathsf{M} - \mathsf{I})\,\mathsf{K}_\alpha\alpha + \upsilon_0 g \qquad \text{and} \qquad \frac{\mathrm{d}}{\mathrm{d}t}\beta = \left(\mathsf{I} - \mathsf{M}^\dagger\right)\mathsf{K}_\beta\beta + \upsilon_T\gamma \qquad (10)$$

with the modified integral operators $\mathsf{K}_\alpha\alpha(x, t) \equiv \int_0^t \mathrm{d}\tau \; \kappa_\upsilon(\tau, t, x)\, p(x, \tau)$ and $\mathsf{K}_\beta\beta(x, t) \equiv \int_t^T \mathrm{d}\tau \; \kappa_\upsilon(x, t, \tau)\, \beta(x, \tau)$ where $\kappa_\upsilon(x, t', t) \equiv \upsilon(x, t', t)\, \kappa(x, t - t')$. Both inhomogeneities g and γ can be built from the inhomogeneities g_p, g_ϕ and γ_p, γ_ψ from section 2.2. They satisfy the equations $g \equiv (\mathsf{M} - \mathsf{I})(g_\phi - \mathsf{K}_\alpha g_p)$ and $\gamma \equiv \left(\mathsf{I} - \mathsf{M}^\dagger\right)(\mathsf{K}_\beta\gamma_p - \gamma_\psi)$. We will consider these in the next section. Finally, note that α and β can not simply be multiplied to obtain the full Bayesian posterior w.r.t. the observations.

4   Latent State Inference

There are two possibilities to realize the forward and backward algorithms. We exemplify this on the forward algorithm in the following. In popular HSMM literature [22], the discrete-time equivalent of the products ϕ_α and/or ψ_α are fully calculated and α is derived from them using (3). This general procedure poses the computationally most efficient overall solution under two circumstances. First, if we also aim to calculate the full Bayesian posterior $P\left(X(t) = x \mid \mathbf{y}_{[0, T)}\right)$ for all t we need ϕ_α and/or ψ_α anyway. Second, if the classical memory kernel K and thus K_α is hard to evaluate (e.g. by numerical inverse Laplace transform), an evaluation of F and thus F_α might be computationally preferable, even if we need to perform an integration afterwards. In this work, we chose to evaluate α and β directly from (10) using a finite-element approach. Thus, we introduce a time-mesh $t_0 < t_1 < \cdots < t_K$, where we set each t_k exactly at the times of observation.

Initial and Terminal Conditions. Until now, we assumed the boundary conditions g and γ to be known but didn't specify them. Compared to CTMC's, the boundary conditions are not single states but semi-infinite trajectories. In HSMM literature [22], there are two popular boundary conditions. The first assumes, a transition occures both before t_0 and after t_K. The second assumes a steady state before t_0 and an uninformed progression after t_K. The latter corresponds to the case that is classically expressed by a vector of ones in HMM's when the backward term is initialized. More on boundary conditions and their exact expression are found in appendix section A.

4.1   Unidirectional Forward and Backward Algorithms

We formulate the general forward and backward algorithms in appendix section C. The interpolants α_k and β_k valid in the k-th time interval $t \in [t_k, t_{k+1})$ obey the following integral equations

$$\frac{\mathrm{d}}{\mathrm{d}t}\alpha_k = (\mathsf{M} - \mathsf{I})\,\mathsf{K}_{[t_k, t)}\alpha_k + g_k \qquad \Big| \qquad \frac{\mathrm{d}}{\mathrm{d}t}\beta_k = \left(\mathsf{I} - \mathsf{M}^\dagger\right)\mathsf{K}_{(t, t_{k+1}]}\beta_k + \gamma_k \qquad (11)$$

where we introduce the truncated integral operators $\mathsf{K}_{[a, b)}\alpha_k \equiv \int_a^b \mathrm{d}\tau \; \kappa(t - \tau, x)\, \alpha_k(x, \tau)$ and $\mathsf{K}_{(a, b]}\beta_k \equiv \int_a^b \mathrm{d}\tau \; \kappa(\tau - t, x)\, \beta_k(x, \tau)$. The inhomogeneities g_k and γ_k are built during runtime from the overall boundary condition g_0, the previous interpolants $\alpha_{k'}$, $k' < k$, and the scaling function υ. The analogue with γ_K and $\beta_{k'}$, $k' > k$ holds for the backward case.

4.2 Forward-Backward Algorithm - Posterior Marginals

Obtaining the posterior marginals is possible on the level of currents. Since they mark times when the CTSMC has the Markov property, we can build products of the two normalized currents $\psi_\alpha(x, t) = \lim_{h\to 0} \frac{1}{h} P(\nabla_h(x, t) \mid \mathbf{y}_{[0, t)})$ and $\psi_\beta(x, t) = \lim_{h\to 0} \frac{1}{h} P(\mathbf{y}_{[t, T)} \mid \nabla_h(x, t))/P(\mathbf{y}_{[t, T)} \mid \mathbf{y}_{[0, t)})$ to obtain the posterior current $\hat{\psi}(x, t) = \lim_{h\to 0} \frac{1}{h} P(\nabla_h(x, t) \mid \mathbf{y}_{[0, T)})$. which we can use in (3) to obtain the derivative $\frac{\mathrm{d}}{\mathrm{d}t}\hat{p}$. However, we discuss this approach in appendix section A. Although it being preferable from a runtime perspective, an more classical approach popular in discrete-time HSMM literature [22] uses a two-sided path marginalization which allows usage of interpolation-based numerical methods. In this work, we calculate the posterior marginals using

$$\hat{p}(x, t) \propto \int_0^t \mathrm{d}\tau \int_t^T \mathrm{d}\tau' \, \phi_\alpha(x, t - \tau) f(\tau + \tau' \mid x) \psi_\beta(x, t + \tau') \upsilon(t - \tau, t + \tau) \quad (12)$$

We need to add that both currents ϕ_α and ψ_β are obtained as by-products without additional computation from the unidirectional forward and backward algorithms introduced in section 4.1. Although (12) is a two-dimensional integral and therefor scales quadratically with T, it is linear in $|\mathcal{X}|$ since only components of one state occur. An algorithmic description and an explanation how ϕ_α and ψ_β are obtained as by-products can be found in appendix section C.

4.3 Viterbi-type Algorithm - Latent Trajectory Point Estimation

Besides latent state marginals, point estimates of whole posterior paths are as well important in further inference tasks. Originally stemming from HMM's, the Viterbi algorithm which calculates MAP path estimates has been successfully adopted to HSMM's [22]. However, like in hidden CTMC's, the unknown chain length, i.e. the number of state changes until the terminal state is reached, makes the algorithm hard to translate to continuous time. One is therefor often content with knowing the MAP state only at observation times [14]. The latter can in principle be calculated for hidden CTSMC's using our forward equation (9). Nonetheless, for a finite number of jumps, the framework of currents allows the formulation of a scalable full-path algorithm. A max-product-type reformulation of (7) allows an introduction of a max-input current

$$\phi_{\max}(x, t; n) \equiv \sup_{\mathbf{x}_{[0, t)}} \lim_{h\to 0} \frac{1}{h} P\left(\Delta_h(x, t), \mathbf{x}_{[0, t)}, \mathbf{y}_{[0, t)} \mid n\right)$$

which - bluntly speaking - substitutes the marginalization in ϕ_α with a supremum. To keep track of the jump count, we equip this current with an additional parameter n. We also introduce a maximizing transition operator $\mathsf{M}_{\max}$ for the embedded Markov chain $\mathsf{M}_{\max} g(x, t) \equiv \max_{x'\neq x} m(x \mid x') g(x', t)$. The transition operator $\mathsf{M}_{\max}$ resembles M where the sum over the set $\mathcal{X} \setminus \{x\}$ is exchanged by a maximization. The constituting recursion for $\phi_{\max}(x, t; n)$ is then given by

$$\phi_{\max}(x, t; n+1) = \sup_{x'\neq x, \tau\in\mathbb{R}_+} m(x \mid x') f(t - \tau \mid x') \upsilon(x', t - \tau, t) \phi_{\max}(x', \tau; n) \quad (13)$$

which calculates the max-currents $\phi_{\max}(x, t; n+1)$ associated with the incremented chain length $n + 1$. A detailed description is found in appendix section A. The MAP terminal state x is related to the currents by

$$\sup_{\mathbf{x}_{[0, T)}} P\left(\mathbf{x}_{[0, T)}, \mathbf{y}_{[0, T)}\right) \propto \sup_{x, \tau, n} \Lambda(t - \tau \mid x) \upsilon(x, t - \tau, t) \phi_{\max}(x, \tau; n) P(n)$$

Let us ignore the chain length marginal $P(n)$ for now and assume we found a maximizing tuple (x^*, τ^*, n^*). Then, if $n^* > 0$, we can insert $\phi_{\max}(x^*, \tau^*; n^*)$ in (13) and proceed to trace back states and transition instances until the jump counter reaches zero. However, to find the tuple (x^*, τ^*, n^*), we need knowledge of at least some scaling factor $L(n) \propto P(n)$. Proper normalization to get $P(n)$ requires knowledge of n up to infinity, which is intractable. However, a scaling factor $L(n)$ can be found recursively. To do this, two more sets of input currents $\phi_n(x, t) \equiv \lim_{h\to 0} \frac{1}{h} P\left(\Delta_h(x, t), \mathbf{y}_{[0, t)}, n\right)$ and marginals $p_n(x, T) \equiv P\left(X(T) = x, \mathbf{y}_{[0, t)}, n\right)$ are introduced. The $\phi_n(x, t)$ and $p_n(x, T)$ are then updated by

$$\phi_{n+1} = \mathsf{MF}_\alpha \phi_n \qquad \text{and} \qquad p_n(x, T) = \int_0^T \mathrm{d}\tau \, \Lambda(T - \tau \mid x) \upsilon(x, \tau, T) \phi_n(x, \tau) \quad (14)$$

The currents are initialized by $\phi_0(x, t) = \upsilon(x, 0, t)\, g_\phi(x, t)$. Note that the left equation in (14) does not converge to the fixed-point ϕ_α but instead will vanish for $n \to \infty$. The factors $L(n) \equiv P\big(\mathbf{y}_{[0, t)}, n\big) = \sum_x p_n(x, T)$ can then be obtained by marginalization. Again, we refer to appendix section A. Unfortunately, to obtain an exact result, we still need to evaluate all equations for arbitrarily large n. For most practical scenarios, however, the most likely number of transitions n^* might be manageable. We stress that the bottleneck of our algorithm is the number of transitions, not their temporal closeness.

5 Adaptive Step-Size HSMM

One of the major advantages of continuous-time formulations is the availability of adaptive discretization [8, 4]. Although many continuous problems eventually need to be solved numerically on a discrete grid, adaptive step size methods can bound the discretization error and allow a reduction of the amount of function evaluations. While much more elaborate techniques with tight error bounds are available for integral equations [10], we briefly sketch a simple adaptive discretization strategy to close with a practical perspective on the contributions in this work.

This strategy consists of maintaining a time-dependent set of samples of approximate currents and their timestamps $\Phi_\alpha(t) \equiv \{(\phi_{\alpha,k}, t_k) \mid t_K - t_0 < \Delta_{\max}, t_0 < \cdots < t_K, k = 0, \ldots, K\}$. An analogue set is built for ψ_β. Then, by inserting polynomial interpolants (e.g. affine combinations of adjacent $(\phi_{\alpha,k}, t_k)$ and $(\phi_{\alpha,k+1}, t_{k+1})$), we can reformulate (7) so that it only contains the $\phi_{\alpha,k}$, t_k and definite integrals of the $f(\cdot \mid x)$. For these integrals, look-up tables are easily generated for speedup. The resulting linear system can then be solved to calculate the next step $\phi_\alpha^{(1)}(x, t_K + h)$. As a commonly adapted update rule for step size h, we use half step checks $\phi_\alpha^{(0.5)}(x, t_K + h)$, where we do two steps using $\frac{h}{2}$ as step size and then calculate $E \equiv |\phi_\alpha^{(1)}(x, t_K + h) - \phi_\alpha^{(0.5)}(x, t_K + h)|$. The integration error E is then used in the update $h \to \max\{\min\{hs, h_{\max}, t' - t_K - h\}, h_{\min}\}$ with the scaling $s = \max\{\min\{\frac{\text{tol}}{E}, s_{\max}\}, s_{\min}\}$ for some pre-specified $h_{\min}, h_{\max}, s_{\min}, s_{\max}$ and the next observation time t'.

The resulting HSMM is then only dependent on time-differences, i.e. still homogeneous, but adapts its step-size. In appendix section C, we provide the resulting update equation if affine combinations are used as interpolants between the points $(\phi_{\alpha,k}, t_k)$ and an implicit Euler step rule is chosen.

6 Evaluation

Calculation of Integral Equations. Our algorithms demand the solution of integral equations of the second kind. For each time interval $[t, t']$ between observations, we used a backward Euler method to solve the possibly stiff equations in (7), (8) or (10) with a fixed number of steps calculated by $N \equiv \lfloor \frac{t'-t}{h} \rfloor + 1$. Then, all steps are of equal length h except the one at the end of the interval which scales dependent on t'. The integration involved in each step is performed by interpolation between the steps, where the trapezoidal rule has been used. This method is outlined in detail in Appendix section B. An exception is the evaluation of the adaptive step-size HSMM. As described in section 5, there the step size is initialized by a smallest value 10^{-4} and then the adaptive procedure generates any further grid positions. The integration at each step is also more precise. The details are outlined in Appendix B. For forward and backward passes, each interval is alculated consecutively while the inhomogeneities g and γ are updated upon entering each new interval as outline in the algorithm section in Appendix C. The resulting continuous functions α, β, $\hat{p}$ and the currents are then generated for each interval using cubic spline interpolation on the calculated steps.

Experiments. We calculated several randomly generated hidden CTSMC's. The number of states has been given, but waiting time distributions and transition probabilities were drawn randomly. For each state, we drew a randomly parametrized waiting time distribution from a specified family of distributions (we allowed Gamma and Weibull). The random parameters, were drawn from Gamma distributions with per-parameter calibrated hyperparameters. The transition probabilities of the embedded Markov chains were sampled as sets of random categorical distributions while prohibiting self-transitions. The categorical distributions were sampled by first drawing a vector uniformly from the $|\mathcal{X}|$-hypercube and then projecting it to the $(|\mathcal{X}| - 1)$-simplex via normalization. The observation times were drawn from a point process with Gamma inter-arrival times with fixed shape and rate

Figure 2: *a)* Normalized forward and backward currents (ϕ_α, ψ_β) of a latent CTSMC in presence of observations (vertical gray dotted lines). The areas outside the actual trajectory show the initial and terminal conditions (extending to infinity); *b)* Mean and variance progression of the posterior latent state marginals $\hat{p}$ inferred from the shown trajectory as the original CTSMC (blue) the optimal steady-state CTMC approximation (orange); *c)* Time grid generated by an adaptive step-size HSMM in a forward pass as proposed in section 5 (orange markers). The continuous blue line was generated by a discrete HSMM with step size $h = 10^{-3}$; *d)* MAP latent trajectory estimate for a sample trajectory from a four-state hidden CTSMC. Left: estimated trajectory (blue), second-best candidate (orange). Right: the scaling function $L(n) \propto P(n)$ for different chain lengths,

hyperparameters. The observation values were noisy observations of a function $b : \mathcal{X} \to \mathbb{R}$ mapping the latent states to fixed values in a real observation space $\mathcal{Y} \equiv \mathbb{R}$. Thus, $Y(t) \sim \mathcal{N}(b(X(t)), \sigma)$ with the standard deviation σ as a hyperparameter.

The calculated α, β, $\hat{p}$ were compared to those calculated by a HSMM. With a step-size of $h_{\text{HSMM}} = 10^{-4}$ and $h_{\text{CTSMC}} = 10^{-3}$ (backward Euler step-size), no difference was visible anymore on any calculated trajectory. In Fig. 2a, we show an exemplary progression of the forward input and backward output currents. In Fig. 2b the smoothed marginals $\hat{p}$ of a four-state CTSMC are compared to those obtained from its steady-state CTMC approximation [13]. For this, smoothed mean and variance of $b(X(t))$ are shown. The full trajectory of $b(X(t))$ by the original CTSMC which generated the observations is shown as a ground truth. We built the adaptive step-size HSMM using our proposed method and ran it over the sampled trajectories as well. While quickly enlarging its step-size, it remained within the margins of a total error of 10^{-3} compared to a fine-grained HSMM, although this is not guaranteed by the method. An example run is shown in Fig. 2c. Finally, we tested our Viterbi MAP estimator on the trajectories. An example run is shown in 2d. The chain length scaling factor $L(n) \propto P(n)$ had a comparably sharp peak in all trajectories. We assume, this came from the observations greatly narrowing down the amount of candidate transition counts.

7   Conclusion

We have presented a forward-backward framework applicable to hidden CTSMC's. Avoidîng state space augmentation to enforce the Markov property, it gives rise to integral and integro-differential forward and backward equations and a scalable Viterbi algorithm. Adaptive step-size HSMM's can be derived, overcoming discrete-time core problems: out-of-grid observations and steady-state over-computation. We didn't consider CTSMC's not satisfying direction-time independence which are especially interesting for coarse-graining of large Markovian systems. Also, specific classes of waiting times could allow efficient computation of currents, e.g. power-law waiting times related to fractional calculus being of recent interest in physics. Possible solutions would then fit naturally in our framework which handles observation likelihood of past events.

References

[1] Ahmed M. Alaa and Mihaela Van Der Schaar. A hidden absorbing semi-markov model for informatively censored temporal data: Learning and inference. *J. Mach. Learn. Res.*, 19(1): 108–169, jan 2018. ISSN 1532-4435.

[2] Ahmed M. Alaa, Scott Hu, and Mihaela van der Schaar. Learning from clinical judgments: Semi-Markov-modulated marked Hawkes processes for risk prognosis. In Doina Precup and Yee Whye Teh, editors, *Proceedings of the 34th International Conference on Machine Learning*, volume 70 of *Proceedings of Machine Learning Research*, pages 60–69. PMLR, 06–11 Aug 2017.

[3] David Andrieux and Pierre Gaspard. The fluctuation theorem for currents in semi-markov processes. *Journal of Statistical Mechanics: Theory and Experiment*, 2008(11):P11007, nov 2008. doi: 10.1088/1742-5468/2008/11/p11007.

[4] Christopher T.H. Baker. A perspective on the numerical treatment of volterra equations. *Journal of Computational and Applied Mathematics*, 125(1):217–249, 2000. ISSN 0377-0427. doi: https://doi.org/10.1016/S0377-0427(00)00470-2. Numerical Analysis 2000. Vol. VI: Ordinary Differential Equations and Integral Equations.

[5] Marco Biagi, Laura Carnevali, Marco Paolieri, Fulvio Patara, and Enrico Vicario. A continuous-time model-based approach for activity recognition in pervasive environments. *IEEE Transactions on Human-Machine Systems*, 49(4):293–303, 2019. doi: 10.1109/THMS.2019.2903091.

[6] Francesco Cannarile, Michele Compare, Piero Baraldi, Francesco Di Maio, and Enrico Zio. Homogeneous continuous-time, finite-state hidden semi-markov modeling for enhancing empirical classification system diagnostics of industrial components. *Machines*, 6(3), 2018. ISSN 2075-1702. doi: 10.3390/machines6030034.

[7] Jianzhun Du, Joseph Futoma, and Finale Doshi-Velez. Model-based reinforcement learning for semi-markov decision processes with neural odes. In H. Larochelle, M. Ranzato, R. Hadsell, M.F. Balcan, and H. Lin, editors, *Advances in Neural Information Processing Systems*, volume 33, pages 19805–19816. Curran Associates, Inc., 2020.

[8] Raymond Holsapple, Ram Iyer, and David Doman. A variable step-size selection method for implicit integration schemes. In *2006 American Control Conference*, pages 6–pp. IEEE, 2006.

[9] Matthew Johnson and Alan Willsky. Stochastic variational inference for bayesian time series models. In Eric P. Xing and Tony Jebara, editors, *Proceedings of the 31st International Conference on Machine Learning*, volume 32 of *Proceedings of Machine Learning Research*, pages 1854–1862, Bejing, China, 22–24 Jun 2014. PMLR.

[10] HM Jones and S McKee. Variable step size predictor-corrector schemes for second kind volterra integral equations. *Mathematics of computation*, 44(170):391–404, 1985.

[11] Michael Klann and Heinz Koeppl. Spatial simulations in systems biology: from molecules to cells. *International Journal of Molecular Sciences*, 13(6):7798–7827, 2012. ISSN 1422-0067. doi: 10.3390/ijms13067798.

[12] Mikko Laine and Aleksi Vuorinen. Basics of thermal field theory. *Lect. Notes Phys*, 925(1): 1701–01554, 2016.

[13] Nikolaos Limnios and Gheorghe Oprisan. *Semi-Markov processes and reliability*. Springer Science & Business Media, 2001.

[14] Yu-Ying Liu, Shuang Li, Fuxin Li, Le Song, and James M. Rehg. Efficient learning of continuous-time hidden markov models for disease progression. In *Proceedings of the 28th International Conference on Neural Information Processing Systems - Volume 2*, NIPS'15, page 3600–3608, Cambridge, MA, USA, 2015. MIT Press.

[15] Christian Maes, Karel Netočný, and Bram Wynants. Dynamical fluctuations for semi-markov processes. *Journal of Physics A: Mathematical and Theoretical*, 42(36):365002, 2009.

[16] Manish Malhotra and Andrew Reibman. Selecting and implementing phase approximations for semi-markov models. *Stochastic Models*, 9(4):473–506, 1993.

[17] Ramin Moghaddass and Ming J. Zuo. A parameter estimation method for a condition-monitored device under multi-state deterioration. *Reliability Engineering System Safety*, 106:94–103, 2012. ISSN 0951-8320. doi: https://doi.org/10.1016/j.ress.2012.05.004.

[18] J. R. Norris. *Markov Chains*. Cambridge Series in Statistical and Probabilistic Mathematics. Cambridge University Press, 1997. doi: 10.1017/CBO9780511810633.

[19] Masayuki Ohzeki and Akihisa Ichiki. Mathematical understanding of detailed balance condition violation and its application to langevin dynamics. *Journal of Physics: Conference Series*, 638: 012003, sep 2015. doi: 10.1088/1742-6596/638/1/012003.

[20] Enzo Orsingher, Costantino Ricciuti, and Bruno Toaldo. On semi-markov processes and their kolmogorov's integro-differential equations. *Journal of Functional Analysis*, 275(4):830–868, 2018. ISSN 0022-1236. doi: https://doi.org/10.1016/j.jfa.2018.02.011.

[21] Felix Salfner. Modeling event-driven time series with generalized hidden semi-markov models. 2006.

[22] Shun-Zheng Yu. Hidden semi-markov models. *Artificial Intelligence*, 174(2):215–243, 2010. ISSN 0004-3702. doi: https://doi.org/10.1016/j.artint.2009.11.011. Special Review Issue.