BDDM: BILATERAL DENOISING DIFFUSION MODELS FOR FAST AND HIGH-QUALITY SPEECH SYNTHESIS

ABSTRACT

Diffusion probabilistic models (DPMs) and their extensions have emerged as competitive generative models yet confront challenges of efficient sampling. We propose a new bilateral denoising diffusion model (BDDM) that parameterizes both the forward and reverse processes with a schedule network and a score network, which can train with a novel bilateral modeling objective. We show that the new surrogate objective can achieve a lower bound of the log marginal likelihood tighter than a conventional surrogate. We also find that BDDM allows inheriting pre-trained score network parameters from any DPMs and consequently enables speedy and stable learning of the schedule network and optimization of a noise schedule for sampling. Our experiments demonstrate that BDDMs can generate high-fidelity audio samples with as few as 3 sampling steps. Moreover, comparing to other state-of-the-art diffusion-based neural vocoders, BDDMs produce comparable or higher quality samples indistinguishable from human speech, notably with only 7 sampling steps (143x faster than Wdifferent aspect of WaveGrad and 28.6x faster than DiffWave).

1 INTRODUCTION

Deep generative models have shown a tremendous advancement in speech synthesis (van den Oord et al., 2016; Kalchbrenner et al., 2018; Prenger et al., 2019; Kumar et al., 2019a; Kong et al., 2020b; Chen et al., 2020; Kong et al., 2021). Successful generative models can be mainly divided into two branches – the GAN (Goodfellow et al., 2014) based approach and the likelihood-based approach. The former uses an adversarial training procedure, but the training is sometimes unstable, and the relevant training objectives are not suitable to compare different GAN models; the latter uses log-likelihood or surrogate objectives for training, but they also have intrinsic limitations. For example, the autoregressive models (van den Oord et al., 2016; Kalchbrenner et al., 2018) have exceedingly slow sampling speed, and poor scaling properties on high-dimensional data, as its sampling is inherently a sequential process. Likewise, the flow-based models (Dinh et al., 2016; Kingma & Dhariwal, 2018; Chen et al., 2018; Papamakarios et al., 2021) rely on specialized architectures to build a normalized probability model so that the model training is less parameter-efficient and typically more difficult than other likelihood-based generative models (Bond-Taylor et al., 2021). On the other hand, for those using the surrogate objectives, such as the evidence lower bound in variational auto-encoders (Kingma & Welling, 2013; Rezende et al., 2014; Maaløe et al., 2019) and the contrastive divergence in energy-based models (Hinton, 2002; Carreira-Perpinan & Hinton, 2005), they improve inference speed but often yield lower-quality samples than autoregressive and GAN-based models and typically only work well for low-dimensional data (Bond-Taylor et al., 2021).

An up-and-coming class of likelihood-based models is the diffusion probabilistic models (DPMs) (Sohl-Dickstein et al., 2015), which shed light on the generation of high-quality samples comparable or even superior (Dhariwal & Nichol, 2021) to the state-of-the-art (SOTA) GAN-based models. Sohl-Dickstein et al. (2015) introduced the idea of using an iterative forward process for destroying the structure of a given distribution while learning the reverse process for restoring the structure in the data. With a different modeling objective, the score-based generative models (Song & Ermon, 2019) used a neural network trained with the score matching (Hyvarinen & Dayan, 2005) to produce samples via Langevin dynamics. As a seminal work of DPMs, Ho et al. (2020) proposed the denoising diffusion probabilistic models (DDPMs), which exploited a connection (Vincent, 2011) between

the above two ideas that the diffusion framework can be viewed as a specific approach to provide support to score matching. For the first time, DDPMs present high-quality image synthesis results on par with GAN models, especially on several higher-resolution image benchmarks. Subsequently, score matching and denoising diffusion models were applied to speech syntheses, such as Wavegrad (Chen et al., 2020) and a parallel contribution Diffwave (Kong et al., 2021), and demonstrated the capability of generating high fidelity audio samples outperforming non-autoregressive GAN-based models (Yamamoto et al., 2020; Kumar et al., 2019b; Yang et al., 2020; Bińkowski et al., 2020) meanwhile matching the quality of SOTA autoregressive methods (Chen et al., 2020).

Despite the compelling results, the diffusion generative models are two to three orders of magnitude slower than other generative models such as GANs and VAEs. Their major limitation is that they require up to thousands of diffusion steps during training to learn the target distribution, and therefore a large number of reverse steps are often required at sampling time. Recently, extensive investigations have been conducted to reduce the sampling steps for efficiently generating high-quality samples, which we will discuss in the related work in Section 2. Distinctively, we conceived that we may train a neural network to efficiently and adaptively estimate a much shorter noise schedule for sampling that achieves generation performances comparable or even superior to the conventional DPMs. With such an incentive, after introducing the conventional DPMs as our background in Section 3, we propose in Section 4 bilateral denoising diffusion models (BDDMs), named after a bilateral modeling perspective – parameterizing the forward and reverse processes with a schedule network and a score network, respectively. We theoretically derive that the schedule network should be trained after the score network is optimized. For training the schedule network, we propose a novel objective to minimize the gap between a newly derived lower bound and the log marginal likelihood. We describe the training algorithm as well as the fast and high-quality sampling algorithm in Section 5. The training of the schedule network converges very fast using our newly derived objective, and its training only adds negligible overhead to DDPM's. In Section 6, our neural vocoding experiments demonstrated that BDDMs can generate high-fidelity samples with as few as 3 sampling steps, and produce speech samples indistinguishable from human speech with only 7 sampling steps (143x faster than WaveGrad and 28.6x faster than DiffWave).

2 RELATED WORK

Prior works showed that noise scheduling is crucial for efficient and high-fidelity sample generation in diffusion probabilistic models. DDPMs (Ho et al., 2020) shared a linear noise schedule for both training and sampling, which, however, requires thousands of sampling iterations to obtain competitive results. To speed up the sampling process, one class of related work, including (Chen et al., 2020; Kong et al., 2021; Nichol & Dhariwal, 2021), attempts to use a separate, shorter noise schedule for sampling. For clarity, we thereafter denote the training noise schedule as $\boldsymbol{\beta} \in \mathbb{R}^T$ and the sampling noise schedule as $\hat{\boldsymbol{\beta}} \in \mathbb{R}^N$ with $N < T$. In particular, Chen et al. (2020) applied a grid search (GS) algorithm to select $\hat{\boldsymbol{\beta}}$. Unfortunately, GS becomes prohibitively slow when N grows large, e.g., $N = 6$ took more than a day on a single NVIDIA Tesla P40 GPU. This is because the time costs of GS algorithm grow exponentially with N, i.e., $\mathcal{O}(9^N)$ with 9 bins as the default setting in Chen et al. (2020). Instead of searching, Kong et al. (2021) devised a fast sampling (FS) algorithm based on an expert-defined 6-step noise schedule for their score network. However, this specifically tuned noise schedule is hard to generalize to other score networks, tasks, or datasets.

Another class of noise scheduling methods searches for a subsequence of time indices of the training noise schedule, which we called the *time schedule*. DDIMs (Song et al., 2021a) introduced an accelerated reverse process that relies on a pre-specified time schedule. A linear and a quadratic time schedule were used in DDIMs and showed superior generation quality over DDPMs within 10 to 100 sampling steps. Nichol & Dhariwal (2021) proposed a re-scaled noise schedule for fast sampling, but this also requires pre-specifying the time schedule and the training noise schedule. Nichol & Dhariwal (2021) also proposed learning variances for the reverse processes, whereas the variances of the forward processes, i.e., the noise schedule, which affected both the means and variances of the reverse processes, were not learnable. According to the results in (Song et al., 2021a; Nichol & Dhariwal, 2021), using a linear or quadratic time schedule resulted in quite different performances in different datasets, implying that the optimal choice of schedule varies with the datasets. So, there remains a challenge in finding a short and effective schedule for fast sampling on different datasets. Notably, Kong & Ping (2021) proposed a method to map a noise schedule to a time schedule for

fast sampling. In this sense, searching for a time schedule becomes a sub-set of the noise scheduling problem, which resembles the above category of methods.

Although DPMs (Sohl-Dickstein et al., 2015) and DDPMs (Ho et al., 2019) mentioned that the noise schedule could possibly be learned by re-parameterization, the approach was not investigated in their works. Closely related works that learn a noise schedule emerged until very recently. San-Roman et al. (2021) proposed a noise estimation (NE) method, which trained a neural net with a regression loss to estimate the noise scale from the noisy sample at each time point, and then predicted the next noise scale. However, NE requires a prior assumption of the noise schedule following a linear or Fibonacci rule. Most recently, a concurrent work to ours by Kingma et al. (2021) jointly trained a neural net to predict the signal-to-noise ratio (SNR) by maximizing the variational lower bound. The SNR was then used for noise scheduling. Different from ours, this scheduling neural net only took t as input and is independent to the noisy sample generated during the loop of sampling process. Intrinsically, with limited information about the sampled data, the predicted SNR could deviate from the actual SNR of the noisy data during sampling.

3 BACKGROUND

3.1 DIFFUSION PROBABILISTIC MODELS (DPMS)

Given i.i.d. samples $\{\boldsymbol{x}_0 \in \mathbb{R}^D\}$ from an unknown data distribution $p_{\text{data}}(\boldsymbol{x}_0)$, diffusion probabilistic models (DPMs) (Sohl-Dickstein et al., 2015) define a forward process $q(\boldsymbol{x}_{1:T}|\boldsymbol{x}_0) = \prod_{t=1}^{T} q(\boldsymbol{x}_t|\boldsymbol{x}_{t-1})$ that converts any complex data distribution into a simple, tractable distribution after T steps of diffusion. A reverse process $p_\theta(\boldsymbol{x}_{t-1}|\boldsymbol{x}_t)$ parameterized by θ is used to model the data distribution: $p_\theta(\boldsymbol{x}_0) = \int \pi(\boldsymbol{x}_T) \prod_{t=1}^{T} p_\theta(\boldsymbol{x}_{t-1}|\boldsymbol{x}_t) d\boldsymbol{x}_{1:T}$, where $\pi(\boldsymbol{x}_T)$ is the prior distribution for starting the reverse process. Then, the variational parameters θ can be learned by maximizing the standard log evidence lower bound (ELBO):

$$\mathcal{F}_{\text{elbo}} := \mathbb{E}_q \left[\log p_\theta(\boldsymbol{x}_0|\boldsymbol{x}_1) - \sum_{t=2}^{T} D_{\text{KL}} \left(q(\boldsymbol{x}_{t-1}|\boldsymbol{x}_t, \boldsymbol{x}_0) || p_\theta(\boldsymbol{x}_{t-1}|\boldsymbol{x}_t) \right) - D_{\text{KL}} \left(q(\boldsymbol{x}_T|\boldsymbol{x}_0) || \pi(\boldsymbol{x}_T) \right) \right].$$

$$(1)$$

3.2 DENOISING DIFFUSION PROBABILISTIC MODELS (DDPMS)

As an extension to DPMs, de-noising diffusion probabilistic models (DDPMs) (Ho et al., 2020) applied the score matching technique (Hyvarinen & Dayan, 2005; Song & Ermon, 2019) to define the reverse process. In particular, DDPMs considered a Gaussian diffusion process parameterized by a *noise schedule* $\boldsymbol{\beta} \in \mathbb{R}^T$ with $0 < \beta_1, \ldots, \beta_T < 1$:

$$q_{\boldsymbol{\beta}}(\boldsymbol{x}_{1:T}|\boldsymbol{x}_0) := \prod_{t=1}^{T} q_{\beta_t}(\boldsymbol{x}_t|\boldsymbol{x}_{t-1}), \quad \text{where} \quad q_{\beta_t}(\boldsymbol{x}_t|\boldsymbol{x}_{t-1}) := \mathcal{N}(\sqrt{1-\beta_t}\boldsymbol{x}_{t-1}, \beta_t \boldsymbol{I}). \quad (2)$$

Based on the nice property of isotropic Gaussians, one can express $\boldsymbol{x}_t$ directly conditioned on $\boldsymbol{x}_0$:

$$q_{\boldsymbol{\beta}}(\boldsymbol{x}_t|\boldsymbol{x}_0) = \mathcal{N}(\alpha_t \boldsymbol{x}_0, (1-\alpha_t^2)\boldsymbol{I}), \quad \text{where} \quad \alpha_t = \prod_{i=1}^{t} \sqrt{1-\beta_i}. \quad (3)$$

To revert this forward process, DDPMs employ a score network[1] $\boldsymbol{\epsilon}_\theta(\boldsymbol{x}_t, \alpha_t)$ to define

$$p_\theta(\boldsymbol{x}_{t-1}|\boldsymbol{x}_t) := \mathcal{N} \left(\frac{1}{\sqrt{1-\beta_t}} \left(\boldsymbol{x}_t - \frac{\beta_t}{\sqrt{1-\alpha_t^2}} \boldsymbol{\epsilon}_\theta(\boldsymbol{x}_t, \alpha_t) \right), \Sigma_t \right), \quad (4)$$

---

[1] Here, $\boldsymbol{\epsilon}_\theta(\boldsymbol{x}_t, \alpha_t)$ is conditioned on the continuous noise scale α_t, as in (Song et al., 2021b; Chen et al., 2020). Alternatively, the score network can also be conditioned on a discrete time index $\boldsymbol{\epsilon}_\theta(\boldsymbol{x}_t, t)$, as in (Song et al., 2021a; Ho et al., 2020). An approximate mapping of a noise schedule to a time schedule (Kong & Ping, 2021) exists, therefore we consider conditioning on noise scales as the general case.

Figure 1: A block diagram for a bilateral denoising diffusion model (BDDM)

where Σ_t is the co-variance matrix defined for the reverse process. Ho et al. (2020) showed that setting $\Sigma_t = \tilde{\beta}_t \boldsymbol{I} = \frac{1-\alpha_{t-1}^2}{1-\alpha_t^2}\beta_t \boldsymbol{I}$ is optimal for a deterministic $\boldsymbol{x}_0$, while setting $\Sigma_t = \beta_t \boldsymbol{I}$ is optimal for a white noise $\boldsymbol{x}_0 \sim \mathcal{N}(\boldsymbol{0}, \boldsymbol{I})$. Alternatively, Nichol & Dhariwal (2021) proposed learnable variances by interpolating the two optimals with a jointly trained neural network, i.e., $\Sigma_{t,\theta}(\boldsymbol{x}) :=$ $\mathrm{diag}(\exp(\boldsymbol{v}_\theta(\boldsymbol{x})\log\beta_t + (1 - \boldsymbol{v}_\theta(\boldsymbol{x}))\log\tilde{\beta}_t))$, where $\boldsymbol{v}_\theta(\boldsymbol{x}) \in \mathbb{R}^D$ is a trainable network.

Note that the calculation of the complete ELBO in Eq. (1) requires T forward passes of the score network, which would make the training computationally prohibitive for a large T. To feasibly train the score network, instead of computing the complete ELBO, Ho et al. (2020) proposed an efficient training mechanism by sampling from a discrete uniform distribution: $t \sim \mathcal{U}\{1, ..., T\}$, $\boldsymbol{x}_0 \sim p_{\mathrm{data}}(\boldsymbol{x}_0)$, $\boldsymbol{\epsilon}_t \sim \mathcal{N}(\boldsymbol{0}, \boldsymbol{I})$ at each training iteration to compute the training loss:

$$\mathcal{L}_{\mathrm{ddpm}}^{(t)}(\theta) := \left\| \boldsymbol{\epsilon}_t - \boldsymbol{\epsilon}_\theta \left(\alpha_t \boldsymbol{x}_0 + \sqrt{1 - \alpha_t^2}\boldsymbol{\epsilon}_t, \alpha_t \right) \right\|_2^2, \tag{5}$$

which is a re-weighted form of $D_{\mathrm{KL}}\left(q_{\boldsymbol{\beta}}(\boldsymbol{x}_{t-1}|\boldsymbol{x}_t, \boldsymbol{x}_0)||p_\theta(\boldsymbol{x}_{t-1}|\boldsymbol{x}_t)\right)$. Ho et al. (2020) reported that the re-weighting effectively worked for learning θ, yet we demonstrate it is deficient for learning the noise schedule $\boldsymbol{\beta}$ in our ablation experiment in Section 6.2.

4 BILATERAL DENOISING DIFFUSION MODELS (BDDMS)

4.1 PROBLEM FORMULATION

For fast sampling with DPMs, we strive for a much shorter noise schedule $\hat{\boldsymbol{\beta}}$ for sampling than the noise schedule $\boldsymbol{\beta}$ for training. As shown in Fig. 1, we specifically define two separate diffusion processes corresponding to the two noise schedules, $\boldsymbol{\beta}$ and $\hat{\boldsymbol{\beta}}$, respectively. The upper diffusion process parameterized by $\boldsymbol{\beta}$ is the same as the one defined in Eq. 2, whereas the lower process is defined as $q_{\hat{\boldsymbol{\beta}}}(\hat{\boldsymbol{x}}_{1:N}|\hat{\boldsymbol{x}}_0) = \prod_{n=1}^N q_{\hat{\boldsymbol{\beta}}}(\hat{\boldsymbol{x}}_n|\hat{\boldsymbol{x}}_{n-1})$ with much fewer diffusion steps ($N \ll T$). In our considered problem, $\boldsymbol{\beta}$ is given while $\hat{\boldsymbol{\beta}}$ is unknown. The goal is to find a $\hat{\boldsymbol{\beta}}$ for the reverse process $p_\theta(\hat{\boldsymbol{x}}_{n-1}|\hat{\boldsymbol{x}}_n; \hat{\boldsymbol{\beta}})$ such that $\hat{\boldsymbol{x}}_0$ can be effectively recovered from $\hat{\boldsymbol{x}}_N$ with N reverse steps.

4.2 MODEL DESCRIPTION

Although many prior arts (Ho et al., 2020; Chen et al., 2020; Song et al., 2021a; San-Roman et al., 2021) directly applied the shortened linear noise schedule to the reverse process, we argue that these are sub-optimal solutions. Theoretically, the diffusion process specified by a new shortened noise schedule $\hat{\boldsymbol{\beta}}$ is fundamentally different from the one we used to train the score network θ. Therefore, we are not guaranteed whether θ still works in reverting the new diffusion process. The above issue motivated a novel modeling perspective to establish a link between $\hat{\boldsymbol{\beta}}$ and the score network θ.

As a starting point, we consider an $N = \lfloor T/\tau \rfloor$, where $1 \leq \tau < T$ is a hyperparameter controlling the step size such that each diffusion step between two consecutive variables in the lower diffusion process corresponds to τ diffusion steps in the upper one. Based on Eq. (2), we define the following:

$$q_{\hat{\beta}_{n+1}}(\hat{\boldsymbol{x}}_{n+1}|\hat{\boldsymbol{x}}_n = \boldsymbol{x}_t) := q_{\boldsymbol{\beta}}(\boldsymbol{x}_{t+\tau}|\boldsymbol{x}_t) = \mathcal{N}\left(\sqrt{1 - \hat{\beta}_{n+1}}\boldsymbol{x}_t, \hat{\beta}_{n+1}\boldsymbol{I}\right), \tag{6}$$

where $\hat{\beta}_{n+1} = 1 - \frac{\alpha_{t+\tau}^2}{\alpha_t^2}$, and $\boldsymbol{x}_t$ is an intermediate diffused variable we introduced to link the two differently indexed diffusion sequences. We call it a *junctional* variable, which can be easily generated during training as we have $\boldsymbol{x}_0$ and $\boldsymbol{\beta}$ given.

Unfortunately, for the reverse process where $\boldsymbol{x}_0$ is not given, the junctional variable is intractable. Then, the proposed bilateral denoising diffusion model (BDDM) introduces a schedule network ϕ. We will demonstrate that if we can ideally estimate the score for the $\boldsymbol{\beta}$-parameterized diffusion process using the score network θ^*, the schedule network ϕ can be trained to learn an optimal noise schedule $\hat{\boldsymbol{\beta}}(\phi)$, in which, by optimality, we mean to maximize the data likelihood of generated samples given the score estimated by θ^*, i.e., $p_{\theta^*}(\hat{\boldsymbol{x}}_0)$. Next, we present a formal definition of a BDDM and derive the relevant training losses in more detail.

4.2.1 SCORE NETWORK

We recall that a DDPM starts the reverse process with a white noise $\boldsymbol{x}_T \sim \mathcal{N}(\boldsymbol{0}, \boldsymbol{I})$ and takes T steps to recover the data distribution:

$$p_\theta^{\text{ddpm}}(\boldsymbol{x}_0) := \mathbb{E}_{\mathcal{N}(\boldsymbol{0},\boldsymbol{I})} \left[\mathbb{E}_{p_\theta(\boldsymbol{x}_{1:T-1}|\boldsymbol{x}_T)} \left[p_\theta(\boldsymbol{x}_0|\boldsymbol{x}_{1:T}) \right] \right]. \tag{7}$$

a BDDM, in contrast, reverts a shorter sequence of diffusion random variables with only n steps, starting from a *junctional* variable $\boldsymbol{x}_t$:

$$p_\theta^{\text{bddm}}(\hat{\boldsymbol{x}}_0) := \mathbb{E}_{q_{\hat{\boldsymbol{\beta}}}(\hat{\boldsymbol{x}}_{n-1}|\boldsymbol{x}_t;\boldsymbol{\epsilon}_n)} \left[\mathbb{E}_{p_\theta(\hat{\boldsymbol{x}}_{1:n-2}|\hat{\boldsymbol{x}}_{n-1})} \left[p_\theta(\hat{\boldsymbol{x}}_0|\hat{\boldsymbol{x}}_{1:n-1}) \right] \right], \tag{8}$$

where $2 \leq n \leq N$, and $q_{\hat{\boldsymbol{\beta}}}(\hat{\boldsymbol{x}}_{n-1}|\boldsymbol{x}_t;\boldsymbol{\epsilon}_n)$ comes from a reparameterization defined as the following:

$$q_{\hat{\boldsymbol{\beta}}}(\hat{\boldsymbol{x}}_{n-1}|\boldsymbol{x}_t;\boldsymbol{\epsilon}_n) := q_{\hat{\boldsymbol{\beta}}} \left(\hat{\boldsymbol{x}}_{n-1} \middle| \hat{\boldsymbol{x}}_n = \boldsymbol{x}_t, \hat{\boldsymbol{x}}_0 = \frac{\boldsymbol{x}_t - \sqrt{1-\hat{\alpha}_n^2}\boldsymbol{\epsilon}_n}{\hat{\alpha}_n} ; \boldsymbol{\epsilon}_n \right) \tag{9}$$

$$= \mathcal{N} \left(\frac{1}{\sqrt{1-\hat{\beta}_n}}\boldsymbol{x}_t - \frac{\hat{\beta}_n}{\sqrt{(1-\hat{\beta}_n)(1-\hat{\alpha}_n^2)}}\boldsymbol{\epsilon}_n, \frac{1-\hat{\alpha}_{n-1}^2}{1-\hat{\alpha}_n^2}\hat{\beta}_n \boldsymbol{I} \right), \tag{10}$$

where $\hat{\alpha}_n = \prod_{i=1}^n \sqrt{1-\hat{\beta}_i}$, $\boldsymbol{\epsilon}_n = \frac{\boldsymbol{x}_t - \hat{\alpha}_n \boldsymbol{x}_0}{\sqrt{1-\hat{\alpha}_n^2}}$, and $\boldsymbol{x}_t \sim q_{\boldsymbol{\beta}}(\boldsymbol{x}_t|\boldsymbol{x}_0)$ is the *junctional* variable that maps $\boldsymbol{x}_t$ to $\hat{\boldsymbol{x}}_n$ with an approximate index $t \sim \mathcal{U}\{(n-1)\tau, ..., n\tau\}$.

With this definition, we show in Appendix A.2 that a new form of lower bound to the log marginal likelihood can be derived: $\log p_\theta(\hat{\boldsymbol{x}}_0) \geq \mathcal{F}_{\text{score}}^{(n)}(\theta) := -\mathcal{L}_{\text{score}}^{(n)}(\theta) - \mathcal{R}_\theta(\hat{\boldsymbol{x}}_0, \boldsymbol{x}_t)$, where

$$\mathcal{L}_{\text{score}}^{(n)}(\theta) := D_{\text{KL}} \left(p_\theta(\hat{\boldsymbol{x}}_{n-1}|\hat{\boldsymbol{x}}_n = \boldsymbol{x}_t) || q_{\hat{\boldsymbol{\beta}}}(\hat{\boldsymbol{x}}_{n-1}|\boldsymbol{x}_t;\boldsymbol{\epsilon}_n) \right), \tag{11}$$

$$\mathcal{R}_\theta(\hat{\boldsymbol{x}}_0, \boldsymbol{x}_t) := -\mathbb{E}_{p_\theta(\hat{\boldsymbol{x}}_1|\hat{\boldsymbol{x}}_n = \boldsymbol{x}_t)} \left[\log p_\theta(\hat{\boldsymbol{x}}_0|\hat{\boldsymbol{x}}_1) \right]. \tag{12}$$

Then, we show that the score network θ for reverting the diffusion process over $\hat{\boldsymbol{x}}_{0:N}$ can also be trained with $\mathcal{L}_{\text{ddpm}}^{(t)}(\theta)$ even without knowing $\hat{\boldsymbol{\beta}}$. Essentially, although the newly derived lower bound does not modify the loss for training the score network, it explains the relationship between the score network θ and $\hat{\boldsymbol{x}}_{0:N}$. This can be further exploited for learning $\hat{\boldsymbol{\beta}}$, as presented below.

4.2.2 SCHEDULE NETWORK

In BDDMs, a schedule network is introduced to the forward process by re-parameterizing $\hat{\beta}_n$ as $\hat{\beta}_n(\phi) = f_\phi \left(\boldsymbol{x}_t, \hat{\beta}_{n+1} \right)$ such that Eq. (9) becomes as follows:

$$q_\phi(\hat{\boldsymbol{x}}_n|\hat{\boldsymbol{x}}_{n-1}; \hat{\beta}_n(\phi)) := \mathcal{N} \left(\sqrt{1 - f_\phi \left(\boldsymbol{x}_t, \hat{\beta}_{n+1} \right)}\hat{\boldsymbol{x}}_{n-1}, f_\phi \left(\boldsymbol{x}_t, \hat{\beta}_{n+1} \right) \boldsymbol{I} \right), \tag{13}$$

where at each training step, by sampling $t \sim \mathcal{U}\{(n-1)\tau, ..., n\tau\}$, we have $\boldsymbol{x}_t \sim q_{\boldsymbol{\beta}}(\boldsymbol{x}_t|\boldsymbol{x}_0)$ and $\hat{\beta}_{n+1} = 1 - \frac{\alpha_{t+\tau}^2}{\alpha_t^2}$. Through the re-parameterization, the task of noise scheduling, i.e., searching

for $\hat{\boldsymbol{\beta}}$, can now be reformulated as training a schedule network f_ϕ that recursively estimates data-dependent variances. The schedule network lets $\hat{\beta}_n$ be fully dependent on the current noisy sample $\boldsymbol{x}_t$ and the $\hat{\beta}_{n+1}$, which is beneficial for noise scheduling from a reverse direction at inference time. We expect f_ϕ to be able not only to estimate the absolute noise scale of the inputted sample $\boldsymbol{x}_t$, but also to predict the relative change of noisiness comparable to τ steps of diffusion specified by $\boldsymbol{\beta}$ in the reverse direction. These challenge a proper definition of f_ϕ and an effective training objective for learning ϕ, which will both be discussed in the following.

Monotonic noise schedules have been successfully applied to in prior arts including DPMs (Ho et al., 2020; Kingma et al., 2021) and score-based methods (Song et al., 2020; Song & Ermon, 2020). We also follow the monotonic assumption and derive an upper bound for $\hat{\beta}_n$ as below:

Remark 1. *Suppose the noise schedule for sampling is monotonic, i.e., $0 < \hat{\beta}_1 < \ldots < \hat{\beta}_N < 1$, then, for $1 \le n < N$, $\hat{\beta}_n$ satisfies the following inequality:*

$$0 < \hat{\beta}_n < \min\left\{1 - \frac{\hat{\alpha}_{n+1}^2}{1 - \hat{\beta}_{n+1}}, \hat{\beta}_{n+1}\right\}. \tag{14}$$

The proof is presented in Appendix A.1. By multiplying the upper bound by a ratio estimated by a network $\sigma_\phi : \mathbb{R}^D \mapsto (0, 1)$, we then define $f_\phi(\boldsymbol{x}_t, \hat{\beta}_{n+1}) := \min\left\{1 - \frac{\hat{\alpha}_{n+1}^2}{1 - \hat{\beta}_{n+1}}, \hat{\beta}_{n+1}\right\}\sigma_\phi(\boldsymbol{x}_t)$, where the network parameter set ϕ is learned to estimate the ratio between two consecutive noise scales ($\hat{\beta}_n$ and $\hat{\beta}_{n+1}$) from the current noisy observation $\boldsymbol{x}_t$.

Consequently, at inference time for noise scheduling, starting from a maximum reverse steps (N) and two hyperparameters ($\hat{\alpha}_N, \hat{\beta}_N$), we ancestrally, for n from N to 1, predict the noise scale $\hat{\beta}_n = f_\phi\left(\hat{\boldsymbol{x}}_n, \hat{\beta}_{n+1}\right)$ and cumulatively update the product $\hat{\alpha}_n = \frac{\hat{\alpha}_{n+1}}{\sqrt{1-\hat{\beta}_{n+1}}}$.

4.2.3 TRAINING OBJECTIVE

Since we show, in Appendix A.2, that the score network parameters θ can be trained similarly to DDPMs with $\mathcal{L}_{\mathrm{ddpm}}^{(t)}(\theta)$, the remaining challenge would be the training of the schedule network f_ϕ. In Appendix A.3, the theoretical results suggest that ϕ should be trained after θ is well-optimized. In a realistic setting, we assume the optimized θ^* to be closed to the hypothetically optimal values. Given a well-optimized θ^*, we optimize the following loss w.r.t ϕ:

$$\mathcal{L}_{\mathrm{step}}^{(n)}(\phi; \theta^*) = \frac{\delta_t^2}{2(\delta_t^2 - \hat{\beta}_n(\phi))}\left\|\boldsymbol{\epsilon}_n - \frac{\hat{\beta}_n(\phi)}{\delta_t^2}\boldsymbol{\epsilon}_{\theta^*}(\boldsymbol{x}_t, \alpha_t)\right\|_2^2 + \frac{1}{4}\log\frac{\delta_t^2}{\hat{\beta}_n(\phi)} + \frac{D}{2}\left(\frac{\hat{\beta}_n(\phi)}{1 - \alpha_t^2} - 1\right). \tag{15}$$

where $\delta_t = \sqrt{1 - \alpha_t^2}$. For training, we use $\hat{\beta}_n(\phi) = f_\phi\left(\alpha_t\boldsymbol{x}_0 + \sqrt{1 - \alpha_t^2}\boldsymbol{\epsilon}_n, 1 - \frac{\alpha_{t+\tau}^2}{\alpha_t^2}\right)$, and draw $t \in \mathcal{U}\{(n-1)\tau, \ldots, n\tau\}$. The derivation for $\mathcal{L}_{\mathrm{step}}^{(n)}(\phi; \theta^*)$ is described in Appendix A.3.

5 ALGORITHMS: TRAINING, NOISE SCHEDULING, AND SAMPLING

5.1 TRAINING SCORE AND SCHEDULE NETWORKS

Following the theoretical result in Appendix A.3, θ should be optimized before learning ϕ. To train the score network $\boldsymbol{\epsilon}_\theta$, we refer to the settings in (Ho et al., 2020; Chen et al., 2020; Song et al., 2021a) to define $\boldsymbol{\beta}$ as a linear noise schedule: $\beta_t = \beta_{\mathrm{start}} + \frac{t}{T}(\beta_{\mathrm{end}} - \beta_{\mathrm{start}})$, for $1 \le t \le T$, where β_{start} and β_{end} are two hyperparameter that specifies the start value and the end value. This results in Algorithm 1, which resembles the training algorithm in (Ho et al., 2020).

Next, based on the converged score network θ^*, we train the schedule network ϕ. Similar to the training of the score network, we draw an $n \sim \mathcal{U}\{2, \ldots, N\}$ at each training step, and then draw a $t \sim \mathcal{U}\{(n-1)\tau, \ldots, n\tau\}$. These together can be simplified into directly drawing $t \sim \mathcal{U}\{2, \ldots, T-\tau\}$. Then, we sequentially compute the variables needed for calculating $\mathcal{L}_{\mathrm{step}}^{(n)}(\phi; \theta^*)$, as presented in

Algorithm 1 Training Score Network (θ)

1: Given $T, \{\beta_t\}_{t=1}^T$
2: $\{\alpha_t\}_{t=1}^T = \{\prod_{i=1}^t \sqrt{1-\beta_t}\}_{t=1}^T$
3: **repeat**
4:   $\boldsymbol{x}_0 \sim p_{\text{data}}(\boldsymbol{x}_0)$
5:   $t \sim \mathcal{U}\{1,\ldots,T\}$
6:   $\boldsymbol{\epsilon}_t \sim \mathcal{N}(\boldsymbol{0}, \boldsymbol{I})$
7:   $\boldsymbol{x}_t = \hat{\alpha}_t \boldsymbol{x}_0 + \sqrt{1-\hat{\alpha}_t^2}\boldsymbol{\epsilon}_t$
8:   $\mathcal{L}_{\text{ddpm}}^{(t)} = \|\boldsymbol{\epsilon}_t - \boldsymbol{\epsilon}_\theta(\boldsymbol{x}_t, \alpha_t)\|_2^2$
9:   Take a gradient descent step on $\nabla_\theta \mathcal{L}_{\text{ddpm}}^{(t)}$
10: **until** converged

Algorithm 3 Noise Scheduling

1: Given $\theta^*, \hat{\alpha}_N, \hat{\beta}_N, \boldsymbol{x}_N \sim \mathcal{N}(\boldsymbol{0}, \boldsymbol{I})$
2: **for** $n = N$ to 2 **do**
3:   $\hat{\boldsymbol{x}}_{n-1} \sim p_{\theta^*}(\hat{\boldsymbol{x}}_{n-1}|\hat{\boldsymbol{x}}_n; \hat{\alpha}_n, \hat{\beta}_n)$
4:   $\hat{\alpha}_{n-1} = \frac{\hat{\alpha}_n}{\sqrt{1-\hat{\beta}_n}}$
5:   $\hat{\beta}_{n-1} = \min\{1-\hat{\alpha}_{n-1}^2, \hat{\beta}_n\}\sigma_\phi(\hat{\boldsymbol{x}}_{n-1})$
6:   **if** $\hat{\beta}_{n-1} < \beta_1$ **then**
7:     **return** $\hat{\beta}_n, \ldots, \hat{\beta}_N$
8:   **end if**
9: **end for**
10: **return** $\hat{\beta}_1, \ldots, \hat{\beta}_N$

Algorithm 2 Training Scheduling Network (ϕ)

1: Given $\theta^*, \tau, T, \{\alpha_t, \beta_t\}_{t=1}^T$
2: **repeat**
3:   $\boldsymbol{x}_0 \sim p_{\text{data}}(\boldsymbol{x}_0)$
4:   $t \sim \mathcal{U}\{2, \ldots, T-\tau\}$
5:   $\delta_t = \sqrt{1-\alpha_t^2}$
6:   $\boldsymbol{\epsilon}_n \sim \mathcal{N}(\boldsymbol{0}, \boldsymbol{I})$
7:   $\boldsymbol{x}_t = \alpha_t \boldsymbol{x}_0 + \delta_t \boldsymbol{\epsilon}_t$
8:   $\hat{\beta}_n = \min\left\{\delta_n^2, 1 - \frac{\alpha_{t+\tau}^2}{\alpha_t^2}\right\}\sigma_\phi(\boldsymbol{x}_t)$
9:   $C = 4^{-1}\log(\delta_n^2/\hat{\beta}_n) + 2^{-1}D\left(\hat{\beta}_n/\delta_n^2 - 1\right)$
10:   $\mathcal{L}_{\text{step}}^{(n)} = \frac{\delta_n^2}{2(\delta_n^2 - \hat{\beta}_n)}\left\|\boldsymbol{\epsilon}_n - \frac{\hat{\beta}_n}{\delta_n^2}\boldsymbol{\epsilon}_{\theta^*}(\boldsymbol{x}_t, \alpha_t)\right\|_2^2 + C$
11:   Take a gradient descent step on $\nabla_\phi \mathcal{L}_{\text{step}}^{(n)}$
12: **until** converged

Algorithm 4 Sampling

1: Given $\theta^*, \{\hat{\beta}_n\}_{n=1}^{N_s}, \hat{\boldsymbol{x}}_{N_s} \sim \mathcal{N}(\boldsymbol{0}, \boldsymbol{I})$
2: $\{\hat{\alpha}_n\}_{n=1}^{N_s} = \left\{\prod_{i=1}^n \sqrt{1-\hat{\beta}_n}\right\}_{n=1}^{N_s}$
3: **for** $n = N_s$ to 1 **do**
4:   $\hat{\boldsymbol{x}}_{n-1} \sim p_{\theta^*}(\hat{\boldsymbol{x}}_{n-1}|\hat{\boldsymbol{x}}_n; \hat{\alpha}_n, \hat{\beta}_n)$
5: **end for**
6: **return** $\hat{\boldsymbol{x}}_0$

Algorithm 2. We observed that, although a linear schedule is used to define $\boldsymbol{\beta}$, the noise schedule for sampling $\hat{\boldsymbol{\beta}}$ predicted by f_ϕ is not limited into a linear one.

5.2 NOISE SCHEDULING FOR FAST AND HIGH-QUALITY SAMPLING

After the score network and the schedule network are trained, the inference procedure can divide into two phases: (1) the noise scheduling phase and (2) the sampling phase.

First, we run the noise scheduling process similarly to a sampling process with N iterations maximum. Different from training, where α_t is forward-computed, $\hat{\alpha}_n$ is instead a backward-computed variable (from N to 1) that may deviates from the forward one because $\{\hat{\beta}_i\}_i^{n-1}$ are unknown in the noise scheduling phase during inference. To start noise scheduling, we first set two hyper-parameters: $\hat{\alpha}_N$ and $\hat{\beta}_N$. We use β_1, the smallest noise scale seen in training, as a threshold to early stop the noise scheduling process, so that we can ignore small noise scales ($< \beta_1$) that were never seen by the score network. Overall, the noise scheduling process is presented in Algorithm 3.

In practice, we apply a grid search algorithm of M bins to Algorithm 3, which takes $\mathcal{O}(M^2)$ time, to find proper values for $(\hat{\alpha}_N, \hat{\beta}_N)$. We used $M = 9$ as in (Chen et al., 2020). The grid search for our noise scheduling algorithm can be evaluated on a small subset of the training samples. Empirically, even as few as 1 sample for evaluation works well in our algorithm. Finally, given the predicted noise schedule $\hat{\boldsymbol{\beta}} \in \mathbb{R}^{N_s}$, we generate samples with N_s sampling steps, as shown in Algorithm 4.

6 EXPERIMENTS

We conducted a series of experiments on neural vocoding tasks to evaluate the proposed BDDMs. First, we compared BDDMs against several strongest models that have been published: the mixture of logistics (MoL) WaveNet (Oord et al., 2018) implemented in (Yamamoto, 2020), the WaveGlow (Prenger et al., 2019) implemented in (Valle, 2020), the MelGAN (Kumar et al., 2019a) implemented in (Kumar, 2019), the HiFi-GAN (Kong et al., 2020b) implemented in (Kong et al., 2020a) and the two most recently proposed diffusion-based vocoders, i.e., WaveGrad (Chen et al., 2020) and DiffWave (Kong et al., 2021), both re-implemented in our code. The hyperparameter settings of BDDMs and all these models are detailed in Appendix B.

In addition, we also compared BDDMs to a variety of scheduling and acceleration techniques applicable to DDPMs, including the grid search (GS) approach in WaveGrad, the fast sampling (FS) approach based on a user-defined 6-step schedule in DiffWave, the DDIMs (Song et al., 2021a) and

Table 1: Comparison of neural vocoders in terms of MOS with 95% confidence intervals, real-time factor (RTF) and model size in megabytes (MB) for inference. The MOSs showing no significant difference from the ground truth under student's t-tests (p-values ≥ 0.05) are bold-faced.

Neural Vocoder	MOS (p-value)	RTF	Size
Ground-truth	4.62 ± 0.24	—	—
WaveNet (MoL) (Oord et al., 2018)	3.63 ± 0.26 (1.05×10^{-9})	318.6	282MB
WaveGlow (Prenger et al., 2019)	3.06 ± 0.37 (1.10×10^{-10})	0.0198	645MB
MelGAN (Kumar et al., 2019a)	3.52 ± 0.35 (1.08×10^{-8})	0.00396	17MB
HiFi-GAN (Kong et al., 2020b)	4.32 ± 0.25 (3.25×10^{-3})	0.0134	54MB
WaveGrad - 1000 steps (Chen et al., 2020)	4.39 ± 0.23 (0.012)	38.2	183MB
DiffWave - 200 steps (Kong et al., 2021)	$\mathbf{4.52 \pm 0.24}$ (0.161)	7.30	27MB
BDDM - 3 steps ($\hat{\alpha}_N = 0.68, \hat{\beta}_N = 0.53$)	3.65 ± 0.23 (4.58×10^{-10})	0.110	27MB
BDDM - 7 steps ($\hat{\alpha}_N = 0.62, \hat{\beta}_N = 0.42$)	$\mathbf{4.43 \pm 0.31}$ (0.055)	0.256	27MB
BDDM - 12 steps ($\hat{\alpha}_N = 0.67, \hat{\beta}_N = 0.12$)	$\mathbf{4.47 \pm 0.33}$ (0.102)	0.438	27MB

Table 2: Comparison of sampling acceleration methods with the same score network and the same number of steps. The highest score and the scores that are not significantly different from the highest score in student's t-tests (p-values ≥ 0.05) are bold-faced.

Steps	Acceleration Method	STOI	PESQ	MOS
3	GS (Chen et al., 2020)	$\mathbf{0.965 \pm 0.009}$	$\mathbf{3.66 \pm 0.20}$	$\mathbf{3.63 \pm 0.25}$
	FS (Kong et al., 2021)	0.939 ± 0.023	3.09 ± 0.23	3.13 ± 0.29
	DDIM (Song et al., 2021a)	0.943 ± 0.015	3.42 ± 0.27	3.28 ± 0.33
	NE (San-Roman et al., 2021)	$\mathbf{0.966 \pm 0.010}$	$\mathbf{3.62 \pm 0.18}$	$\mathbf{3.56 \pm 0.30}$
	BDDM	$\mathbf{0.966 \pm 0.011}$	$\mathbf{3.63 \pm 0.24}$	$\mathbf{3.65 \pm 0.23}$
7	FS (Kong et al., 2021)	$\mathbf{0.981 \pm 0.006}$	3.68 ± 0.24	3.70 ± 0.35
	DDIM (Song et al., 2021a)	0.974 ± 0.008	3.85 ± 0.12	3.94 ± 0.28
	NE (San-Roman et al., 2021)	0.978 ± 0.007	3.75 ± 0.18	4.02 ± 0.26
	BDDM	$\mathbf{0.983 \pm 0.006}$	$\mathbf{3.96 \pm 0.09}$	$\mathbf{4.43 \pm 0.31}$
12	DDIM (Song et al., 2021a)	0.979 ± 0.006	3.90 ± 0.10	4.16 ± 0.27
	NE (San-Roman et al., 2021)	0.981 ± 0.007	3.82 ± 0.13	3.98 ± 0.35
	BDDM	$\mathbf{0.987 \pm 0.006}$	$\mathbf{3.98 \pm 0.12}$	$\mathbf{4.47 \pm 0.33}$

a noise estimation (NE) approach (San-Roman et al., 2021). For fair and reproducible comparison with other models and approaches, we used the LJSpeech dataset (Ito & Johnson, 2017), which consists of 13,100 22kHz audio clips of a female speaker. All diffusion models were trained on the same training split as in (Chen et al., 2020). We also replicated the comparative experiment of neural vocoding using a multi-speaker VCTK dataset (Yamagishi et al., 2019) as presented in Appendix C and obtained a result consistent with that obtained from the LJSpeech dataset.

6.1 SAMPLING QUALITY IN OBJECTIVE AND SUBJECTIVE METRICS

To assess the quality of each generated audio sample, we used both objective and subjective measures for comparing different neural vocoders given the same ground-truth spectrogram s as the condition, i.e., $\epsilon_\theta(x, s, \alpha_t)$. Specifically, we used two scale-invariant metrics: the perceptual evaluation of speech quality (PESQ) (Rix et al., 2001) and the short-time objective intelligibility (STOI) (Taal et al., 2010) to measure the noisiness and the distortion of the generated speech relative to the reference speech. Mean opinion score (MOS) was also used as a subjective metric for evaluating the naturalness of the generated speech. The assessment scheme of MOS is included in Appendix B.

In Table 1, we compared BDDMs against the state-of-the-art (SOTA) vocoders. To predict noise schedules with different sampling steps (3, 7, and 12), we set three pairs of $\{\hat{\alpha}_N, \hat{\beta}_N\}$ for BDDMs by running on Algorithm 3 a quick hyperparameter grid search, which is detailed in Appendix B. Among the 9 evaluated vocoders, only our proposed BDDMs with 7 and 12 steps and DiffWave with 200 steps showed no statistic-significant difference from the ground-truth in terms of MOS. Moreover, BDDMs significantly outspeeded DiffWave in terms of RTFs. Notably, previous diffusion-based vocoders achieved high MOS scores at the cost of an unacceptable RTF for industrial deploy-

Figure 2: Different training losses for σ_ϕ Figure 3: Different lower bounds to $\log p_\theta(\boldsymbol{x}_0)$

ment. In contrast, BDDMs managed to achieve a high standard of generation quality with only 7 sampling steps (143x faster than WaveGrad and 28.6x faster than DiffWave).

In Table 2, we evaluated BDDMs and alternative accelerated sampling methods, which used the same score network for a pair-to-pair comparison. The GS method performed stably when the step number was small (i.e., $N \leq 6$) but not scalable to more step numbers, which were therefore bypassed in the comparisons of 7 and 12 steps. The FS method by Song et al. (2021a) was linearly interpolated to 3 and 7 steps for a fair comparison. Comparing its 7-step and 3-step results, we observed that the FS performance degraded drastically. Both the DDIM and the NE methods were stable across all the steps but were not performing competitively enough. In comparison, BDDMs consistently attained the leading scores across all the steps. This evaluation confirmed that BDDM was superior to other acceleration methods for DPMs in terms of both stability and quality.

6.2 ABLATION STUDY AND ANALYSIS

We attribute the primary advantage of BDDMs to the newly derived objective $\mathcal{L}_{\text{step}}^{(n)}$ for learning ϕ. To better reason about this, we performed an ablation study, where we substituted the proposed loss with the standard negative ELBO for learning ϕ as mentioned by Sohl-Dickstein et al. (2015). We plotted the network outputs with different training losses in Fig. 2. It turned out that, when using $\mathcal{L}_{\text{elbo}}^{(n)}$ to learn ϕ, the network output rapidly collapsed to zero within several training steps; whereas, the network trained with $\mathcal{L}_{\text{step}}^{(n)}$ produced fluctuating outputs. The fluctuation is a desirable property showing the network properly predicts t-dependent noise scales, as t is a random time step drawn from a uniform distribution in training.

By considering $N = T$, we also empirically validated that $\mathcal{F}_{\text{bddm}}^{(t)} \geq \mathcal{F}_{\text{elbo}}^{(t)}$ with their respective values at $t \in [20, 180]$ using the same optimized theta θ^*, and each value with 95% confidence intervals, as illustrated in Fig. 3. In this experiment, we used the LJ speech dataset and set $T = 200$ and $\tau = 20$. Notably, we dropped their common entropy term $\mathcal{R}_\theta(\hat{\boldsymbol{x}}_0, \boldsymbol{x}_t) < 0$ to mainly compare their KL divergences. This explains those positive lower bound values in the plot. The graph shows that our proposed bound $\mathcal{F}_{\text{bddm}}^{(t)}$ is always a tighter lower bound than the standard one across all examined t. Moreover, we found that $\mathcal{F}_{\text{bddm}}^{(t)}$ attained low values with a relatively much lower variance around $t \in [20, 50]$, whereas $\mathcal{F}_{\text{elbo}}^{(t)}$ became highly volatile. This implies that $\mathcal{F}_{\text{bddm}}^{(t)}$ better tackles the difficult training part, when t is approaching zero such that the score becomes more challenging to estimate.

7 CONCLUSIONS

We introduced the bilateral denoising diffusion models (BDDMs), which parameterizes the forward and reverse processes with a schedule network and a score network. From a bilateral modeling perspective, we derived a new lower bound that leads to the same training loss as in DDPMs (Ho et al., 2020), which thus enables inheriting any pre-trained score networks in DDPMs. We also showed that training the schedule network after a well-optimized score network can be viewed as tightening the lower bound. Followed from the theoretical results, an efficient training algorithm and a noise scheduling algorithm were respectively designed for BDDMs. Finally, in our experiments, BDDMs showed a clear edge over the previous diffusion-based vocoders.

REFERENCES

Mikołaj Bińkowski, Jeff Donahue, Sander Dieleman, Aidan Clark, Erich Elsen, Norman Casagrande, Luis C. Cobo, and Karen Simonyan. High fidelity speech synthesis with adversarial networks. *ICLR*, 2020.

Sam Bond-Taylor, Adam Leach, Yang Long, and Chris G. Willcocks. Deep generative modelling: A comparative review of vaes, gans, normalizing flows, energy-based and autoregressive models. *https://arxiv.org/abs/2103.04922*, 2021.

Miguel A Carreira-Perpinan and Geoffrey E Hinton. On contrastive divergence learning. *AISTATS*, pp. 33–40, 2005.

Nanxin Chen, Yu Zhang, Heiga Zen, Ron J. Weiss, Mohammad Norouzi, and William Chan. Wavegrad: Estimating gradients for waveform generation. *arXiv preprint arXiv:2009.00713*, 2020.

Tian Qi Chen, Yulia Rubanova, Jesse Bettencourt, and David K Duvenaud. Neural ordinary differential equations. *NeurIPs*, pp. 6571–6583, 2018.

Prafulla Dhariwal and Alex Nichol. Diffusion models beat gans on image synthesis. *arXiv preprint arXiv:2105.05233*, 2021.

Laurent Dinh, Jascha Sohl-Dickstein, and Samy Bengio. Density estimation using real nvp. *arXiv preprint arXiv:1605.08803*, 2016.

Ian J. Goodfellow, Jean Pouget-Abadie, Mehdi Mirza, Bing Xu, David Warde-Farley, Sherjil Ozair, Aaron Courville, and Yoshua Bengio. Generative adversarial networks. *arXiv:1406.2661*, 2014.

G. E. Hinton. Training products of experts by minimizing contrastive divergence. neural computation. *Neural computation*, pp. 14(8):1771–1800, 2002.

Jonathan Ho, Xi Chen, Aravind Srinivas, Yan Duan, and Pieter Abbeel. Flow++: Improving flow-based generative models with variational dequantization and architecture design. *ICML*, 2019.

Jonathan Ho, Ajay Jain, and Pieter Abbeel. Denoising diffusion probabilistic models. *arXiv preprint arXiv:2006.11239*, 2020.

Aapo Hyvarinen and Peter Dayan. Estimation of non-normalized statistical models by score matching. *Journal of Machine Learning Research*, pp. 6(4), 2005.

Keith Ito and Linda Johnson. The lj speech dataset. *https://keithito.com/LJ-Speech-Dataset/*, 2017.

Nal Kalchbrenner, Erich Elsen, Karen Simonyan, Seb Noury, Norman Casagrande, Edward Lockhart, Florian Stimberg, Aaron Oord, Sander Dieleman, and Koray Kavukcuoglu. Efficient neural audio synthesis. In *International Conference on Machine Learning*, pp. 2410–2419. PMLR, 2018.

Diederik P Kingma and Prafulla Dhariwal. Glow: Generative flow with invertible 1x1 convolutions. *NeurIPS*, pp. 10215–10224, 2018.

Diederik P Kingma and Max Welling. Auto-encoding variational bayes. *arXiv preprint arXiv:1312.6114*, 2013.

Diederik P Kingma, Tim Salimans, Ben Poole, and Jonathan Ho. Variational diffusion models. *arXiv preprint arXiv:2107.00630*, 2021.

Jungil Kong, Jaehyeon Kim, and Jaekyoung Bae. Hifi-gan: Generative adversarial networks for efficient and high fidelity speech synthesis. `https://github.com/jik876/hifi-gan`, 2020a.

Jungil Kong, Jaehyeon Kim, and Jaekyoung Bae. Hifi-gan: Generative adversarial networks for efficient and high fidelity speech synthesis. *Advances in Neural Information Processing Systems*, 33, 2020b.

Zhifeng Kong and Wei Ping. On fast sampling of diffusion probabilistic models. *arXiv preprint arXiv:2106.00132*, 2021.

Zhifeng Kong, Wei Ping, Jiaji Huang, Kexin Zhao, and Bryan Catanzaro. Diffwave: A versatile diffusion model for audio synthesis. *ICLR*, 2021.

Kundan Kumar, Rithesh Kumar, Thibault de Boissiere, Lucas Gestin, Wei Zhen Teoh, Jose Sotelo, Alexandre de Brébisson, Yoshua Bengio, and Aaron Courville. Melgan: Generative adversarial networks for conditional waveform synthesis. *arXiv preprint arXiv:1910.06711*, 2019a.

Kundan Kumar, Rithesh Kumar, Thibault de Boissiere, Lucas Gestin, Wei Zhen Teoh, Jose Sotelo, Alexandre de Brebisson, Yoshua Bengio, and Aaron Courville. Melgan: Generative adversarial networks for conditional waveform synthesis. *NeurIPS*, 2019b.

Rithesh Kumar. Official repository for the paper melgan: Generative adversarial networks for conditional waveform synthesis. `https://github.com/descriptinc/melgan-neurips`, 2019.

Max WY Lam, Jun Wang, Dan Su, and Dong Yu. Effective low-cost time-domain audio separation using globally attentive locally recurrent networks. *arXiv preprint arXiv:2101.05014*, 2021.

Lars Maaløe, Marco Fraccaro, Valentin Liévin, and Ole Winther. Biva: A very deep hierarchy of latent variables for generative modeling. *NeurIPS*, pp. 6548–6558, 2019.

Alex Nichol and Prafulla Dhariwal. Improved denoising diffusion probabilistic models. *arXiv preprint arXiv:2102.09672*, 2021.

Aaron Oord, Yazhe Li, Igor Babuschkin, Karen Simonyan, Oriol Vinyals, Koray Kavukcuoglu, George Driessche, Edward Lockhart, Luis Cobo, Florian Stimberg, et al. Parallel wavenet: Fast high-fidelity speech synthesis. In *International conference on machine learning*, pp. 3918–3926. PMLR, 2018.

George Papamakarios, Eric Nalisnick, Danilo Jimenez Rezende, Shakir Mohamed, and Balaji Lakshminarayanan. Normalizing flows for probabilistic modeling and inference. *JMLR*, pp. 22(57):1–64, 2021.

Ryan Prenger, Rafael Valle, and Bryan Catanzaro. Waveglow: A flow-based generative network for speech synthesis. In *ICASSP 2019-2019 IEEE International Conference on Acoustics, Speech and Signal Processing (ICASSP)*, pp. 3617–3621. IEEE, 2019.

Flavio Protasio Ribeiro, Dinei Florencio, Cha Zhang, and Mike Seltzer. CROWDMOS: An approach for crowdsourcing mean opinion score studies. In *ICASSP*. IEEE, 2011. Edition: ICASSP.

Danilo Jimenez Rezende, Shakir Mohamed, and Daan Wierstra. Stochastic backpropagation and approximate inference in deep generative models. *ICML*, pp. 1278–1286, 2014.

Antony W Rix, John G Beerends, Michael P Hollier, and Andries P Hekstra. Perceptual evaluation of speech quality (pesq)-a new method for speech quality assessment of telephone networks and codecs. In *2001 IEEE International Conference on Acoustics, Speech, and Signal Processing. Proceedings (Cat. No. 01CH37221)*, volume 2, pp. 749–752. IEEE, 2001.

Robin San-Roman, Eliya Nachmani, and Lior Wolf. Noise estimation for generative diffusion models. *arXiv preprint arXiv:2104.02600*, 2021.

Karen Simonyan and Andrew Zisserman. Very deep convolutional networks for large-scale image recognition. *arXiv preprint arXiv:1409.1556*, 2014.

Jascha Sohl-Dickstein, Eric Weiss, Niru Maheswaranathan, and Surya Ganguli. Deep unsupervised learning using nonequilibrium thermodynamics. *In International Conference on Machine Learning*, pp. 2256–2265, 2015.

Jiaming Song, Chenlin Meng, and Stefano Ermon. Denoising diffusion implicit models. *ICLR*, 2021a.

Yang Song and Stefano Ermon. Generative modeling by estimating gradients of the data distribution. *NeurIPS*, 2019.

Yang Song and Stefano Ermon. Improved techniques for training score-based generative models. *arXiv preprint arXiv:2006.09011*, 2020.

Yang Song, Sahaj Garg, Jiaxin Shi, and Stefano Ermon. Sliced score matching: A scalable approach to density and score estimation. *UAI*, pp. 574–584, 2020.

Yang Song, Jascha Sohl-Dickstein, Diederik P Kingma, Abhishek Kumar, Stefano Ermon, and Ben Poole. Score-based generative modeling through stochastic differential equations. *ICLR*, 2021b.

Cees H Taal, Richard C Hendriks, Richard Heusdens, and Jesper Jensen. A short-time objective intelligibility measure for time-frequency weighted noisy speech. In *2010 IEEE international conference on acoustics, speech and signal processing*, pp. 4214–4217. IEEE, 2010.

Rafael Valle. Waveglow: a flow-based generative network for speech synthesis. `https://github.com/NVIDIA/waveglow`, 2020.

Aaron van den Oord, Sander Dieleman, Heiga Zen, Karen Simonyan, Oriol Vinyals, Alex Graves, Nal Kalchbrenner, Andrew Senior, and Koray Kavukcuoglu. Wavenet: A generative model for raw audio. *Proc. 9th ISCA Speech Synthesis Workshop*, pp. 125–125, 2016.

Pascal Vincent. A connection between score matching and denoising autoencoders. *Neural Computation*, pp. 23(7):1661–1674, 2011.

Daniel Watson, Jonathan Ho, Mohammad Norouzi, and William Chan. Learning to efficiently sample from diffusion probabilistic models. *arXiv preprint arXiv:2106.03802*, 2021.

Junichi Yamagishi, Christophe Veaux, and Kirsten MacDonald. CSTR VCTK Corpus: English multi-speaker corpus for CSTR voice cloning toolkit (version 0.92), 2019.

Ryuichi Yamamoto. Wavenet vocoder. `https://github.com/r9y9/wavenet_vocoder`, 2020.

Ryuichi Yamamoto, Eunwoo Song, and Jae-Min Kim. Parallel. Wavegan: A fast waveform generation model based on generative adversarial networks with multi-resolution spectrogram. *ICASSP*, 2020.

Geng Yang, Shan Yang, Kai Liu, Peng Fang, Wei Chen, and Lei Xie. Multi-band melgan: Faster waveform generation for high-quality text-to-speech. *arXiv preprint arXiv:2005.0510*, 2020.

A THEORETICAL DERIVATIONS FOR BDDMs

In this section, we provide the theoretical supports for the following:

- The derivation procedures for Remark 1 (see Appendix A.1).

- The score network θ trained with $\mathcal{L}_{\text{ddpm}}^{(t)}(\theta)$ for the reverse process $p_\theta(\boldsymbol{x}_{t-1}|\boldsymbol{x}_t)$ can be re-used for the reverse process $p_\theta(\hat{\boldsymbol{x}}_{n-1}|\hat{\boldsymbol{x}}_n)$ (see Appendix A.2).

- The scheduling network ϕ can be trained with $\mathcal{L}_{\text{step}}^{(n)}(\phi; \theta^*)$ after the score network θ is optimized. (see Appendix A.3).

A.1 DERIVING AN UPPER BOUND FOR NOISE SCALE

Remark 1. *Suppose the noise schedule for sampling is monotonic, i.e., $0 < \hat{\beta}_1 < \ldots < \hat{\beta}_N < 1$, then, for $1 \leq n < N$, $\hat{\beta}_n$ satisfies the following inequality:*

$$0 < \hat{\beta}_n < \min\left\{1 - \frac{\hat{\alpha}_{n+1}^2}{1 - \hat{\beta}_{n+1}}, \hat{\beta}_{n+1}\right\}. \tag{16}$$

Proof. By the general definition of noise schedule, we know that $0 < \hat{\beta}_1, \ldots, \hat{\beta}_N < 1$ (Note: no inequality sign in between). Given that $\hat{\alpha}_n = \prod_{i=1}^n \sqrt{1 - \hat{\beta}_i}$, we also have $0 < \hat{\alpha}_1, \ldots, \hat{\alpha}_t < 1$. First, we show that $\hat{\beta}_n < 1 - \frac{\hat{\alpha}_{n+1}^2}{1 - \hat{\beta}_{n+1}}$:

$$\hat{\alpha}_{n-1} = \frac{\hat{\alpha}_n}{\sqrt{1 - \hat{\beta}_n}} < 1 \iff \hat{\beta}_n < 1 - \hat{\alpha}_n^2 = 1 - \frac{\hat{\alpha}_{n+1}^2}{1 - \hat{\beta}_{n+1}}. \tag{17}$$

Next, we show that $\hat{\beta}_n < 1 - \hat{\alpha}_{n+1}$:

$$\frac{\hat{\alpha}_n}{\sqrt{1 - \hat{\beta}_n}} = \frac{\hat{\alpha}_n\sqrt{1 - \hat{\beta}_n}}{1 - \hat{\beta}_n} = \frac{\hat{\alpha}_{n+1}}{1 - \hat{\beta}_n} < 1 \iff \hat{\beta}_n < 1 - \hat{\alpha}_{n+1}. \tag{18}$$

Now, we have $\hat{\beta}_n < \min\left\{1 - \frac{\hat{\alpha}_{n+1}^2}{1 - \hat{\beta}_{n+1}}, 1 - \hat{\alpha}_{n+1}\right\}$. When $1 - \hat{\alpha}_{n+1} < 1 - \frac{\hat{\alpha}_{n+1}^2}{1 - \hat{\beta}_{n+1}}$, we can show that $\hat{\beta}_{n+1} < 1 - \hat{\alpha}_{n+1}$:

$$1 - \hat{\alpha}_{n+1} < 1 - \frac{\hat{\alpha}_{n+1}^2}{1 - \hat{\beta}_{n+1}} = 1 - \hat{\alpha}_n^2 \iff \hat{\alpha}_{n+1} > \hat{\alpha}_n^2 \iff \frac{\hat{\alpha}_{n+1}^2}{\hat{\alpha}_n^2} > \hat{\alpha}_{n+1} \tag{19}$$

$$\iff 1 - \frac{\hat{\alpha}_{n+1}^2}{\hat{\alpha}_n^2} < 1 - \hat{\alpha}_{n+1} \iff \hat{\beta}_{n+1} < 1 - \hat{\alpha}_{n+1}. \tag{20}$$

By the assumption of monotonic sequence, we also have $\hat{\beta}_n < \hat{\beta}_{n+1}$. Knowing that $\hat{\beta}_{n+1} < 1 - \hat{\alpha}_{n+1}$ is always true, we obtain a tighter bound for $\hat{\beta}_n$: $0 < \hat{\beta}_n < \min\left\{1 - \frac{\hat{\alpha}_{n+1}^2}{1 - \hat{\beta}_{n+1}}, \hat{\beta}_{n+1}\right\}$. $\square$

A.2 DERIVING THE TRAINING OBJECTIVE FOR SCORE NETWORK

First, followed from the data distribution modeling of BDDMs as proposed in Eq. (8):

$$p_\theta(\hat{\boldsymbol{x}}_0) := \mathbb{E}_{\hat{\boldsymbol{x}}_{n-1} \sim q_{\hat{\beta}}(\hat{\boldsymbol{x}}_{n-1}|\boldsymbol{x}_t; \boldsymbol{\epsilon}_n)}\left[\mathbb{E}_{\hat{\boldsymbol{x}}_{1:n-2} \sim p_\theta(\hat{\boldsymbol{x}}_{1:n-2}|\hat{\boldsymbol{x}}_{n-1})}\left[p_\theta(\hat{\boldsymbol{x}}_0|\hat{\boldsymbol{x}}_{1:n-1})\right]\right], \tag{21}$$

we can derive a new lower bound to the log marginal likelihood as follows:

Proposition 1. *Given an $\boldsymbol{x}_t \sim q_\beta(\boldsymbol{x}_t|\boldsymbol{x}_0)$, the following lower bound holds for $n \in \{2, \ldots, N\}$:*

$$\log p_\theta(\hat{\boldsymbol{x}}_0) \geq \mathcal{F}_{score}^{(n)}(\theta) := -\mathcal{L}_{score}^{(n)}(\theta) - \mathcal{R}_\theta(\hat{\boldsymbol{x}}_0, \boldsymbol{x}_t), \tag{22}$$

where

$$\mathcal{L}_{score}^{(n)}(\theta) := D_{\text{KL}}\left(p_\theta(\hat{\boldsymbol{x}}_{n-1}|\hat{\boldsymbol{x}}_n = \boldsymbol{x}_t) \| q_{\hat{\beta}}(\hat{\boldsymbol{x}}_{n-1}|\boldsymbol{x}_t; \boldsymbol{\epsilon}_n)\right), \tag{23}$$

$$\mathcal{R}_\theta(\hat{\boldsymbol{x}}_0, \boldsymbol{x}_t) := -\mathbb{E}_{p_\theta(\hat{\boldsymbol{x}}_1|\hat{\boldsymbol{x}}_n = \boldsymbol{x}_t)}\left[\log p_\theta(\hat{\boldsymbol{x}}_0|\hat{\boldsymbol{x}}_1)\right]. \tag{24}$$

Proof.

$$\log p_\theta(\hat{\boldsymbol{x}}_0) = \log \int p_\theta(\hat{\boldsymbol{x}}_{0:n-2}|\hat{\boldsymbol{x}}_{n-1})q_{\hat{\boldsymbol{\beta}}}(\hat{\boldsymbol{x}}_{n-1}|\boldsymbol{x}_t;\boldsymbol{\epsilon}_n)d\hat{\boldsymbol{x}}_{1:n-1} \tag{25}$$

$$= \log \int p_\theta(\hat{\boldsymbol{x}}_{0:n-2}|\hat{\boldsymbol{x}}_{n-1})q_{\hat{\boldsymbol{\beta}}}(\hat{\boldsymbol{x}}_{n-1}|\boldsymbol{x}_t;\boldsymbol{\epsilon}_n)\frac{p_\theta(\hat{\boldsymbol{x}}_{1:n-1}|\hat{\boldsymbol{x}}_n = \boldsymbol{x}_t)}{p_\theta(\hat{\boldsymbol{x}}_{1:n-1}|\hat{\boldsymbol{x}}_n = \boldsymbol{x}_t)}d\hat{\boldsymbol{x}}_{1:n-1} \tag{26}$$

$$= \log \mathbb{E}_{p_\theta(\hat{\boldsymbol{x}}_{1,n-1}|\hat{\boldsymbol{x}}_n = \boldsymbol{x}_t)}\left[\frac{p_\theta(\hat{\boldsymbol{x}}_0|\hat{\boldsymbol{x}}_1)q_{\hat{\boldsymbol{\beta}}}(\hat{\boldsymbol{x}}_{n-1}|\boldsymbol{x}_t;\boldsymbol{\epsilon}_n)}{p_\theta(\hat{\boldsymbol{x}}_{n-1}|\hat{\boldsymbol{x}}_n = \boldsymbol{x}_t)}\right] \tag{27}$$

$$[\text{Jensen's Inequality}] \geq \mathbb{E}_{p_\theta(\hat{\boldsymbol{x}}_1,\hat{\boldsymbol{x}}_{n-1}|\hat{\boldsymbol{x}}_n = \boldsymbol{x}_t)}\left[\log \frac{p_\theta(\hat{\boldsymbol{x}}_0|\hat{\boldsymbol{x}}_1)q_{\hat{\boldsymbol{\beta}}}(\hat{\boldsymbol{x}}_{n-1}|\boldsymbol{x}_t;\boldsymbol{\epsilon}_n)}{p_\theta(\hat{\boldsymbol{x}}_{n-1}|\hat{\boldsymbol{x}}_n = \boldsymbol{x}_t)}\right] \tag{28}$$

$$= \mathbb{E}_{p_\theta(\hat{\boldsymbol{x}}_1|\hat{\boldsymbol{x}}_n = \boldsymbol{x}_t)}\left[\log p_\theta(\hat{\boldsymbol{x}}_0|\hat{\boldsymbol{x}}_1)\right] - D_{\mathrm{KL}}\left(p_\theta(\hat{\boldsymbol{x}}_{n-1}|\hat{\boldsymbol{x}}_n = \boldsymbol{x}_t)||q_{\hat{\boldsymbol{\beta}}}(\hat{\boldsymbol{x}}_{n-1}|\boldsymbol{x}_t;\boldsymbol{\epsilon}_n)\right) \tag{29}$$

$$= -\mathcal{L}_{\text{score}}^{(n)}(\theta) - \mathcal{R}_\theta(\hat{\boldsymbol{x}}_0,\boldsymbol{x}_t) \tag{30}$$

$$\square$$

Next, we show that the score network θ trained with $\mathcal{L}_{\text{ddpm}}^{(t)}(\theta)$ can be re-used in BDDMs. We first provide the derivation for Eq. (9- 10). We have

$$q_{\hat{\boldsymbol{\beta}}}(\hat{\boldsymbol{x}}_{n-1}|\boldsymbol{x}_t;\boldsymbol{\epsilon}_n) := q_{\hat{\boldsymbol{\beta}}}\left(\hat{\boldsymbol{x}}_{n-1}|\hat{\boldsymbol{x}}_n = \boldsymbol{x}_t, \hat{\boldsymbol{x}}_0 = \frac{\boldsymbol{x}_t - \sqrt{1-\hat{\alpha}_n^2}\boldsymbol{\epsilon}_n}{\hat{\alpha}_n}\right) \tag{31}$$

$$= \mathcal{N}\left(\frac{\hat{\alpha}_{n-1}\hat{\beta}_n}{1-\hat{\alpha}_n^2}\frac{\boldsymbol{x}_t - \sqrt{1-\hat{\alpha}_n^2}\boldsymbol{\epsilon}_n}{\hat{\alpha}_n} + \frac{\sqrt{1-\hat{\beta}_n}(1-\hat{\alpha}_{n-1}^2)}{1-\hat{\alpha}_n^2}\boldsymbol{x}_t, \frac{1-\hat{\alpha}_{n-1}^2}{1-\hat{\alpha}_n^2}\hat{\beta}_n\boldsymbol{I}\right) \tag{32}$$

$$= \mathcal{N}\left(\left(\frac{\hat{\alpha}_{n-1}\hat{\beta}_n}{\hat{\alpha}_n(1-\hat{\alpha}_n^2)} + \frac{\sqrt{1-\hat{\beta}_n}(1-\hat{\alpha}_{n-1}^2)}{1-\hat{\alpha}_n^2}\right)\boldsymbol{x}_t - \frac{\hat{\alpha}_{n-1}\hat{\beta}_n}{\hat{\alpha}_n\sqrt{1-\hat{\alpha}_n^2}}\boldsymbol{\epsilon}_n, \frac{1-\hat{\alpha}_{n-1}^2}{1-\hat{\alpha}_n^2}\hat{\beta}_n\boldsymbol{I}\right) \tag{33}$$

$$= \mathcal{N}\left(\frac{1}{\sqrt{1-\hat{\beta}_n}}\boldsymbol{x}_t - \frac{\hat{\beta}_n}{\sqrt{(1-\hat{\beta}_n)(1-\hat{\alpha}_n^2)}}\boldsymbol{\epsilon}_n, \frac{1-\hat{\alpha}_{n-1}^2}{1-\hat{\alpha}_n^2}\hat{\beta}_n\boldsymbol{I}\right). \tag{34}$$

Proposition 2. *Suppose $\boldsymbol{x}_t \sim q_{\boldsymbol{\beta}}(\boldsymbol{x}_t|\boldsymbol{x}_0)$, then any solution satisfying $\theta^* = argmin_\theta\mathcal{L}_{ddpm}^{(t)}(\theta), \forall t \in \{1, ..., T\}$, also satisfies $\theta^* = argmin_\theta\mathcal{L}_{score}^{(n)}(\theta), \forall n \in \{2, ..., N\}$.*

Proof. By the definition in Eq. (4), we have

$$p_\theta(\hat{\boldsymbol{x}}_{n-1}|\hat{\boldsymbol{x}}_n = \boldsymbol{x}_t) = \mathcal{N}\left(\frac{1}{\sqrt{1-\hat{\beta}_n}}\left(\boldsymbol{x}_t - \frac{\hat{\beta}_n}{\sqrt{1-\hat{\alpha}_n^2}}\boldsymbol{\epsilon}_\theta(\boldsymbol{x}_t,\hat{\alpha}_n)\right), \frac{1-\hat{\alpha}_{n-1}^2}{1-\hat{\alpha}_n^2}\hat{\beta}_n\boldsymbol{I}\right). \tag{35}$$

Here, from the training objective in Eq. (5), since $\boldsymbol{x}_t = \alpha_t\boldsymbol{x}_0 + \sqrt{1-\alpha_t^2}\boldsymbol{\epsilon}_n$, the noise scale argument for the score network is known to be α_t. Therefore, we can use $\boldsymbol{\epsilon}_\theta(\boldsymbol{x}_t,\alpha_t)$ instead of $\boldsymbol{\epsilon}_\theta(\boldsymbol{x}_t,\hat{\alpha}_n)$ for expanding $\mathcal{L}_{\text{score}}^{(n)}(\theta)$. Since $p_\theta(\hat{\boldsymbol{x}}_{n-1}|\hat{\boldsymbol{x}}_n = \boldsymbol{x}_t)$ and $q_{\hat{\boldsymbol{\beta}}}(\hat{\boldsymbol{x}}_{n-1}|\boldsymbol{x}_t;\boldsymbol{\epsilon}_n)$ are two isotropic Gaussians

with the same variance, the KL divergence is a scaled $\ell 2$-norm of their means' difference:

$$\mathcal{L}_{\text{score}}^{(n)}(\theta) := D_{\text{KL}}\left(p_\theta(\hat{\boldsymbol{x}}_{n-1}|\hat{\boldsymbol{x}}_n = \boldsymbol{x}_t)||q_{\hat{\boldsymbol{\beta}}}(\hat{\boldsymbol{x}}_{n-1}|\boldsymbol{x}_t; \boldsymbol{\epsilon}_n)\right) \tag{36}$$

$$=\frac{1-\hat{\alpha}_n^2}{2(1-\hat{\alpha}_{n-1}^2)\hat{\beta}_n}\left\|\frac{1}{\sqrt{1-\hat{\beta}_n}}\left(\boldsymbol{x}_t - \frac{\hat{\beta}_n}{\sqrt{1-\hat{\alpha}_n^2}}\boldsymbol{\epsilon}_\theta\left(\boldsymbol{x}_t, \alpha_t\right)\right)\right. \tag{37}$$

$$\left.-\left(\frac{1}{\sqrt{1-\hat{\beta}_n}}\boldsymbol{x}_t - \frac{\hat{\beta}_n}{\sqrt{(1-\hat{\beta}_n)(1-\hat{\alpha}_n^2)}}\boldsymbol{\epsilon}_n\right)\right\|_2^2 \tag{38}$$

$$=\frac{(1-\hat{\beta}_n)(1-\hat{\alpha}_n^2)}{2(1-\hat{\beta}_n-\hat{\alpha}_n^2)\hat{\beta}_n}\left\|\frac{\hat{\beta}_n}{\sqrt{(1-\hat{\beta}_n)(1-\hat{\alpha}_n^2)}}\left(\boldsymbol{\epsilon}_n - \boldsymbol{\epsilon}_\theta\left(\boldsymbol{x}_t, \alpha_t\right)\right)\right\|_2^2 \tag{39}$$

$$=\frac{(1-\hat{\beta}_n)(1-\hat{\alpha}_n^2)}{2(1-\hat{\beta}_n-\hat{\alpha}_n^2)\hat{\beta}_n}\frac{\hat{\beta}_n^2}{(1-\hat{\alpha}_n^2)(1-\hat{\beta}_n)}\left\|\boldsymbol{\epsilon}_n - \boldsymbol{\epsilon}_\theta\left(\boldsymbol{x}_t, \alpha_t\right)\right\|_2^2 \tag{40}$$

$$=\frac{\hat{\beta}_n}{2(1-\hat{\beta}_n-\hat{\alpha}_n^2)}\left\|\boldsymbol{\epsilon}_n - \boldsymbol{\epsilon}_\theta\left(\alpha_t\boldsymbol{x}_0 + \sqrt{1-\alpha_t^2}\boldsymbol{\epsilon}_n, \alpha_t\right)\right\|_2^2, \tag{41}$$

which is proportional to $\mathcal{L}_{\text{ddpm}}^{(t)} := \left\|\boldsymbol{\epsilon}_n - \boldsymbol{\epsilon}_\theta\left(\alpha_t\boldsymbol{x}_0 + \sqrt{1-\alpha_t^2}\boldsymbol{\epsilon}_n, \alpha_t\right)\right\|_2^2$ as defined in Eq. (5). Thus,

$$\text{argmin}_\theta\mathcal{L}_{\text{ddpm}}^{(t)}(\theta) \equiv \text{argmin}_\theta\mathcal{L}_{\text{score}}^{(n)}(\theta). \tag{42}$$

$\square$

Next, we can simplify $\mathcal{R}_\theta(\hat{\boldsymbol{x}}_0, \boldsymbol{x}_t)$ to a reconstruction loss for $\hat{\boldsymbol{x}}_0$:

$$\mathcal{R}_\theta(\hat{\boldsymbol{x}}_0, \boldsymbol{x}_t) := -\mathbb{E}_{p_\theta(\hat{\boldsymbol{x}}_1|\hat{\boldsymbol{x}}_n = \boldsymbol{x}_t)}\left[\log p_\theta(\hat{\boldsymbol{x}}_0|\hat{\boldsymbol{x}}_1)\right] \tag{43}$$

$$=\mathbb{E}_{p_\theta(\hat{\boldsymbol{x}}_1|\hat{\boldsymbol{x}}_n = \boldsymbol{x}_t)}\left[\log \mathcal{N}\left(\frac{1}{\sqrt{1-\hat{\beta}_1}}\left(\hat{\boldsymbol{x}}_1 - \frac{\hat{\beta}_1}{\sqrt{1-\hat{\alpha}_1^2}}\boldsymbol{\epsilon}_\theta(\hat{\boldsymbol{x}}_1, \hat{\alpha}_1), \hat{\beta}_1\mathbf{I}\right)\right)\right] \tag{44}$$

$$=\mathbb{E}_{p_\theta(\hat{\boldsymbol{x}}_1|\hat{\boldsymbol{x}}_n = \boldsymbol{x}_t)}\left[\frac{D}{2}\log 2\pi\hat{\beta}_1 + \frac{1}{2\hat{\beta}_1}\left\|\hat{\boldsymbol{x}}_0 - \frac{1}{\sqrt{1-\hat{\beta}_1}}\left(\hat{\boldsymbol{x}}_1 - \frac{\hat{\beta}_1}{\sqrt{\hat{\beta}_1}}\boldsymbol{\epsilon}_\theta(\hat{\boldsymbol{x}}_1, \hat{\alpha}_1)\right)\right\|_2^2\right] \tag{45}$$

$$=\frac{D}{2}\log 2\pi\hat{\beta}_1 + \frac{1}{2\hat{\beta}_1}\mathbb{E}_{p_\theta(\hat{\boldsymbol{x}}_1|\hat{\boldsymbol{x}}_n = \boldsymbol{x}_t)}\left[\left\|\hat{\boldsymbol{x}}_0 - \frac{1}{\sqrt{1-\hat{\beta}_1}}\left(\hat{\boldsymbol{x}}_1 - \sqrt{\hat{\beta}_1}\boldsymbol{\epsilon}_\theta(\hat{\boldsymbol{x}}_1, \hat{\alpha}_1)\right)\right\|_2^2\right], \tag{46}$$

where $p_\theta(\hat{\boldsymbol{x}}_1|\hat{\boldsymbol{x}}_n = \boldsymbol{x}_t)$ can be efficiently sampled using the reverse process in (Song et al., 2021a). Yet, in practice, similar to the training in (Song et al., 2021a; Chen et al., 2020; Kong et al., 2021), we dropped $\mathcal{R}_\theta(\hat{\boldsymbol{x}}_0, \boldsymbol{x}_t)$ when training θ. In theory, we know that $\mathcal{R}_\theta(\hat{\boldsymbol{x}}_0, \boldsymbol{x}_t)$ achieves its optimal value at $\theta^* = \text{argmin}_\theta\|\boldsymbol{\epsilon}_\theta(\hat{\boldsymbol{x}}_1, \hat{\alpha}_1) - \boldsymbol{\epsilon}_1\|_2^2$, which shares a similar objective as $\mathcal{L}_{\text{ddpm}}^{(t)}$. By minimizing $\mathcal{L}_{\text{ddpm}}^{(t)}$, we train a score network θ^* that best minimizes $\Delta\boldsymbol{\epsilon}_t := \|\boldsymbol{\epsilon}_t - \boldsymbol{\epsilon}_{\theta^*}(\alpha_t\boldsymbol{x}_0 + \sqrt{1-\alpha_t^2}\boldsymbol{\epsilon}_t, \alpha_t)\|_2^2$ for all $1 \leq t \leq T$. Since the first diffusion step has the smallest effect on corrupting $\hat{\boldsymbol{x}}_0$ (i.e., $\beta_1 \approx 0$), it suffices to consider a $\hat{\alpha}_1 = \sqrt{1-\hat{\beta}_1} = \alpha_1$, in which case we can jointly minimize $\mathcal{R}_\theta(\hat{\boldsymbol{x}}_0, \boldsymbol{x}_t)$ by minimizing $\mathcal{L}_{\text{ddpm}}^{(1)}$.

In this sense, during training, given $\boldsymbol{x}_t \sim q_{\boldsymbol{\beta}}(\boldsymbol{x}_t|\boldsymbol{x}_0)$, we can train the score network with the same training objective as in DDPMs and DDIMs. Practically, it is beneficial for BDDMs as we can re-use the score network θ of any well-trained DDPM or DDIM.

A.3 DERIVING THE TRAINING OBJECTIVE FOR SCHEDULING NETWORK

Given that θ can be trained to maximize the log evidence with the pre-specified noise schedule β for training, the consequent question of interest in BDDMs is how to find a fast and good enough noise schedule $\hat{\beta} \in \mathbb{R}^N$ for sampling given an optimized θ^*. In BDDMs, this problem is reduced to how to effectively learn the network parameters ϕ.

Proposition 3. *Suppose θ has been optimized and hypothetically converged to the optimal θ^*, where by optimal it means that with θ^* we have $p_{\theta^*}(\hat{x}_{n-1}|\hat{x}_n = x_t) = q_{\hat{\beta}}(\hat{x}_{n-1}|x_t; \epsilon_n)$ given a $x_t \sim q_\beta(x_t|x_0)$. When $\hat{\beta}$ is unknown but we have $x_0 = \hat{x}_0$ and $\hat{\alpha}_n = \alpha_t$, we can minimize the gap between the optimal lower bound $\mathcal{F}_{score}^{(n)}(\theta^*)$ and $\log p_{\theta^*}(\hat{x}_0)$, i.e, $\log p_{\theta^*}(\hat{x}_0) - \mathcal{F}_{score}^{(n)}(\theta^*)$, by minimizing the following objective with respect to $\hat{\beta}_n$:*

$$\mathcal{L}_{step}^{(n)}(\hat{\beta}_n; \theta^*) := D_{KL}\left(p_\theta^*(\hat{x}_{n-1}|\hat{x}_n = x_t) \| q_{\hat{\beta}}(\hat{x}_{n-1}|x_0; \alpha_t)\right) \tag{47}$$

$$= \frac{\delta_t^2}{2(\delta_t^2 - \hat{\beta}_n)} \left\| \epsilon_n - \frac{\hat{\beta}_n}{\delta_t^2} \epsilon_{\theta^*}\left(\alpha_t x_0 + \sqrt{1 - \alpha_t^2}\epsilon_n, \alpha_t\right) \right\|_2^2 + C, \tag{48}$$

where

$$\delta_t = \sqrt{1 - \alpha_t^2}, \quad C = \frac{1}{4}\log\frac{\delta_t^2}{\hat{\beta}_n} + \frac{D}{2}\left(\frac{\hat{\beta}_n}{1 - \alpha_t^2} - 1\right). \tag{49}$$

Proof. Knowing that $\hat{x}_0 = x_0$, $\hat{\alpha}_n = \alpha_t$, $x_t = \alpha_t x_0 + \sqrt{1 - \alpha_t^2}\epsilon_n$ and $p_{\theta^*}(\hat{x}_{n-1}|\hat{x}_n = x_t) = q_{\hat{\beta}}(\hat{x}_{n-1}|x_t; \epsilon_n)$, we apply a re-parameterization technique as follows:

$$p_{\theta^*}(\hat{x}_{n-1}|\hat{x}_n = x_t, \hat{x}_0 = x_0) = p_{\theta^*}(\hat{x}_{n-1}|\hat{x}_n = \alpha_t x_0 + \sqrt{1 - \alpha_t^2}\epsilon_n) \tag{50}$$

$$[\text{when } x_0 \text{ is known, } x_t \text{ can use any } \epsilon_n \sim \mathcal{N}(\mathbf{0}, \boldsymbol{I})] \quad = q_{\hat{\beta}}(\hat{x}_{n-1}|x_t = \alpha_t x_0 + \sqrt{1 - \alpha_t^2}\epsilon_n) \tag{51}$$

$$= q_{\hat{\beta}}(\hat{x}_{n-1}|x_0; \alpha_t) \tag{52}$$

where the ϵ_n is sampled only once for x_t, thus we move the coefficient of ϵ_n in Eq. (34) to the variance to derive the form of $q_{\hat{\beta}}(\hat{x}_{n-1}|x_0; \alpha_t)$:

$$q_{\hat{\beta}}(\hat{x}_{n-1}|x_0; \alpha_t) = \mathcal{N}\left(\frac{1}{\sqrt{1 - \hat{\beta}_n}}\alpha_t x_0, \left(\left(\frac{\sqrt{1 - \alpha_t^2}}{\sqrt{1 - \hat{\beta}_n}} - \frac{\hat{\beta}_n}{\sqrt{(1 - \hat{\beta}_n)(1 - \hat{\alpha}_n^2)}}\right)^2 + \frac{1 - \hat{\alpha}_{n-1}^2}{1 - \hat{\alpha}_n^2}\hat{\beta}_n\right)\boldsymbol{I}\right) \tag{53}$$

$$= \mathcal{N}\left(\frac{\alpha_t x_0}{\sqrt{1 - \hat{\beta}_n}}, \left(\frac{\left(1 - \alpha_t^2 - \hat{\beta}_n\right)^2}{(1 - \hat{\beta}_n)(1 - \alpha_t^2)} + \frac{\hat{\beta}_n - \hat{\beta}_n^2 - \hat{\alpha}_n^2\hat{\beta}_n}{(1 - \hat{\beta}_n)(1 - \hat{\alpha}_n^2)}\right)\boldsymbol{I}\right) \tag{54}$$

$$= \mathcal{N}\left(\frac{\alpha_t x_0}{\sqrt{1 - \hat{\beta}_n}}, \left(\frac{(1 - \alpha_t^2)^2 - 2(1 - \alpha_t^2)\hat{\beta}_n + \hat{\beta}_n^2 + \hat{\beta}_n - \hat{\beta}_n^2 - \alpha_t^2\hat{\beta}_n}{(1 - \hat{\beta}_n)(1 - \alpha_t^2)}\right)\boldsymbol{I}\right) \tag{55}$$

$$= \mathcal{N}\left(\frac{\alpha_t x_0}{\sqrt{1 - \hat{\beta}_n}}, \frac{1 - \alpha_t^2 - \hat{\beta}_n}{1 - \hat{\beta}_n}\boldsymbol{I}\right) \tag{56}$$

Therefore, we can express the gap between $\log p_{\theta^*}(\hat{\boldsymbol{x}}_0)$ and $\mathcal{F}_{\text{score}}^{(n)}(\theta^*)$ in the following form:

$$\log p_{\theta^*}(\hat{\boldsymbol{x}}_0 = \boldsymbol{x}_0) - \mathcal{F}_{\text{score}}^{(n)}(\theta^*) \tag{57}$$

$$= \log p_{\theta^*}(\hat{\boldsymbol{x}}_0 = \boldsymbol{x}_0) - \mathbb{E}_{p_{\theta^*}(\hat{\boldsymbol{x}}_{1,n-1}|\hat{\boldsymbol{x}}_n=\boldsymbol{x}_t)} \left[\log \frac{p_\theta(\hat{\boldsymbol{x}}_0|\hat{\boldsymbol{x}}_1) q_{\hat{\boldsymbol{\beta}}}(\hat{\boldsymbol{x}}_{n-1}|\boldsymbol{x}_t; \boldsymbol{\epsilon}_n)}{p_\theta(\hat{\boldsymbol{x}}_{n-1}|\hat{\boldsymbol{x}}_n = \boldsymbol{x}_t)} \right] \tag{58}$$

$$= \log p_{\theta^*}(\hat{\boldsymbol{x}}_0 = \boldsymbol{x}_0) - \mathbb{E}_{p_{\theta^*}(\hat{\boldsymbol{x}}_{1:n-1}|\hat{\boldsymbol{x}}_n=\boldsymbol{x}_t)} \left[\log \frac{p_{\theta^*}(\hat{\boldsymbol{x}}_{0:n-1}|\hat{\boldsymbol{x}}_n = \boldsymbol{x}_t)}{p_{\theta^*}(\hat{\boldsymbol{x}}_{1:n-1}|\hat{\boldsymbol{x}}_n = \boldsymbol{x}_t)} \right] \tag{59}$$

$$= \mathbb{E}_{p_{\theta^*}(\hat{\boldsymbol{x}}_{1:n-1}|\hat{\boldsymbol{x}}_n=\boldsymbol{x}_t)} \left[\log \frac{p_{\theta^*}(\hat{\boldsymbol{x}}_{1:n-1}|\hat{\boldsymbol{x}}_n = \boldsymbol{x}_t)}{p_{\theta^*}(\hat{\boldsymbol{x}}_{1:n-1}|\hat{\boldsymbol{x}}_n = \boldsymbol{x}_t, \hat{\boldsymbol{x}}_0 = \boldsymbol{x}_0)} \right] \tag{60}$$

$$= \mathbb{E}_{p_{\theta^*}(\hat{\boldsymbol{x}}_{n-1}|\hat{\boldsymbol{x}}_n=\boldsymbol{x}_t)} \left[\log \frac{p_{\theta^*}(\hat{\boldsymbol{x}}_{n-1}|\hat{\boldsymbol{x}}_n = \boldsymbol{x}_t)}{q_{\hat{\boldsymbol{\beta}}}(\hat{\boldsymbol{x}}_{n-1}|\boldsymbol{x}_0; \alpha_t)} \right] \tag{61}$$

$$= D_{\text{KL}} \left(p_{\theta^*}(\hat{\boldsymbol{x}}_{n-1}|\hat{\boldsymbol{x}}_n = \boldsymbol{x}_t) || q_{\hat{\boldsymbol{\beta}}}(\hat{\boldsymbol{x}}_{n-1}|\boldsymbol{x}_0; \alpha_t) \right) \tag{62}$$

Next, we evaluate the above KL divergence term. By definition, we have

$$p_\theta(\hat{\boldsymbol{x}}_{n-1}|\hat{\boldsymbol{x}}_n = \boldsymbol{x}_t) = \mathcal{N}\left(\frac{1}{\sqrt{1-\hat{\beta}_n}} \left(\boldsymbol{x}_t - \frac{\hat{\beta}_n}{\sqrt{1-\hat{\alpha}_n^2}} \boldsymbol{\epsilon}_\theta(\boldsymbol{x}_t, \hat{\alpha}_n) \right), \frac{1-\hat{\alpha}_{n-1}^2}{1-\hat{\alpha}_n^2} \hat{\beta}_n \boldsymbol{I} \right) \tag{63}$$

$$q_{\hat{\boldsymbol{\beta}}}(\hat{\boldsymbol{x}}_{n-1}|\boldsymbol{x}_0; \alpha_t) = \mathcal{N}\left(\frac{\alpha_t \boldsymbol{x}_0}{\sqrt{1-\hat{\beta}_n}}, \frac{1-\alpha_t^2-\hat{\beta}_n}{1-\hat{\beta}_n} \boldsymbol{I} \right) \tag{64}$$

therefore

$$\mathcal{L}_{\text{step}}^{(n)}(\hat{\beta}_n; \theta^*) := D_{\text{KL}} \left(p_\theta(\hat{\boldsymbol{x}}_{n-1}|\hat{\boldsymbol{x}}_n = \boldsymbol{x}_t) || q_{\hat{\boldsymbol{\beta}}}(\hat{\boldsymbol{x}}_{n-1}|\boldsymbol{x}_0; \alpha_t) \right) \tag{65}$$

$$= \frac{1-\hat{\beta}_n}{2(1-\hat{\beta}_n-\alpha_t^2)} \left\| \frac{\alpha_t}{\sqrt{1-\hat{\beta}_n}} \boldsymbol{x}_0 - \frac{1}{\sqrt{1-\hat{\beta}_n}} \left(\boldsymbol{x}_t - \frac{\hat{\beta}_n}{\sqrt{1-\alpha_t^2}} \boldsymbol{\epsilon}_{\theta^*}(\boldsymbol{x}_t, \alpha_t) \right) \right\|_2^2 + C \tag{66}$$

$$= \frac{1-\hat{\beta}_n}{2(1-\hat{\beta}_n-\alpha_t^2)} \left\| \frac{\alpha_t}{\sqrt{1-\hat{\beta}_n}} \boldsymbol{x}_0 - \frac{1}{\sqrt{1-\hat{\beta}_n}} \left(\alpha_t \boldsymbol{x}_0 + \sqrt{1-\alpha_t^2} \boldsymbol{\epsilon}_n - \frac{\hat{\beta}_n}{\sqrt{1-\alpha_t^2}} \boldsymbol{\epsilon}_{\theta^*}(\boldsymbol{x}_t, \alpha_t) \right) \right\|_2^2 + C \tag{67}$$

$$= \frac{1-\hat{\beta}_n}{2(1-\hat{\beta}_n-\alpha_t^2)} \left\| \sqrt{\frac{1-\alpha_t^2}{1-\beta_n}} \boldsymbol{\epsilon}_n - \frac{\hat{\beta}_n}{\sqrt{(1-\beta_n)(1-\alpha_t^2)}} \boldsymbol{\epsilon}_{\theta^*}(\boldsymbol{x}_t, \alpha_t) \right\|_2^2 + C \tag{68}$$

$$= \frac{1-\alpha_t^2}{2(1-\hat{\beta}_n-\alpha_t^2)} \left\| \boldsymbol{\epsilon}_n - \frac{\hat{\beta}_n}{1-\alpha_t^2} \boldsymbol{\epsilon}_{\theta^*}(\boldsymbol{x}_t, \alpha_t) \right\|_2^2 + C \tag{69}$$

$$= \frac{\delta_t^2}{2(\delta_t^2-\hat{\beta}_n)} \left\| \boldsymbol{\epsilon}_n - \frac{\hat{\beta}_n}{\delta_t^2} \boldsymbol{\epsilon}_{\theta^*}\left(\alpha_t \boldsymbol{x}_0 + \sqrt{1-\alpha_t^2} \boldsymbol{\epsilon}_n, \alpha_t \right) \right\|_2^2 + C, \tag{70}$$

where

$$\delta_t = \sqrt{1-\alpha_t^2}, \quad C = \frac{1}{4} \log \frac{\delta_t^2}{\hat{\beta}_n} + \frac{D}{2} \left(\frac{\hat{\beta}_n}{1-\alpha_t^2} - 1 \right). \tag{71}$$

$\square$

As we use a scheduling network ϕ to estimate $\hat{\beta}_n$ from $(\hat{\alpha}_{n+1}, \hat{\beta}_{n+1})$ as defined in Eq. (13), we obtain the final step loss for learning ϕ:

$$\mathcal{L}_{\text{step}}^{(n)}(\phi; \theta^*) = \frac{\delta_t^2}{2(\delta_t^2 - \hat{\beta}_n(\phi))} \left\| \boldsymbol{\epsilon}_n - \frac{\hat{\beta}_n(\phi)}{\delta_t^2} \boldsymbol{\epsilon}_{\theta^*}(\boldsymbol{x}_t, \alpha_t) \right\|_2^2 + \frac{1}{4} \log \frac{\delta_t^2}{\hat{\beta}_n(\phi)} + \frac{D}{2} \left(\frac{\hat{\beta}_n(\phi)}{1 - \alpha_t^2} - 1 \right). \tag{72}$$

This proposed objective for training the scheduling network can be interpreted as to better model the data distribution (i.e., maximizing $\log p_\theta(\hat{\boldsymbol{x}}_0)$) by correcting the gradient scale $\hat{\beta}_n$ for the next reverse step (from $\hat{\boldsymbol{x}}_n$ to $\hat{\boldsymbol{x}}_{n-1}$) given the gradient vector $\boldsymbol{\epsilon}_{\theta^*}$ estimated by the score network θ^*.

B EXPERIMENTAL DETAILS

B.1 CONVENTIONAL GRID SEARCH ALGORITHM FOR DDPMS

We reproduced the grid search algorithm in (Chen et al., 2020), in which a 6-step noise schedule was searched. In our paper, we generalized the grid search algorithm by similarly sweeping the N-step noise schedule over the following possibilities with a bin width $M = 9$:

$$\{1, 2, 3, 4, 5, 6, 7, 8, 9\} \otimes \{10^{-6 \cdot N/N}, 10^{-6 \cdot (N-1)/N}, ..., 10^{-6 \cdot 1/N}\}, \tag{73}$$

where $\otimes$ denotes the cartesian product applied on two sets. LS-MSE was used as a metric to select the solution during the search. When $N = 6$, we resemble the GS algorithm in (Chen et al., 2020). Note that above searching method normally does not scale up to $N > 6$ steps for its exponential computational cost $\mathcal{O}(9^N)$.

B.2 HYPERPARAMETER SETTING IN BDDMS

Algorithm 2 took a skip factor τ to control the stride for training the scheduling network. The value of τ would affect the coverage of step sizes when training the scheduling network, hence affecting the predicted number of steps N for inference – the higher τ is, the shorter the predicted inference schedule tends to be. We set $\tau = 66$ for training the BDDM vocoders in this paper.

For initializing Algorithm 3 for noise scheduling, we could take as few as 1 training sample for validation, perform a grid search on the hyperparameters $\{(\hat{\alpha}_N = 0.1\alpha_T i, \hat{\beta}_N = 0.1j)\}$ for $i, j = 1, ..., 9$, i.e., 81 possibilities in total, and use the PESQ measure as the selection metric. Then, the predicted noise schedule corresponding to the maximum PESQ was stored and applied to the online inference afterward, as shown in Algorithm 4. Note that this searching has a complexity of only $\mathcal{O}(M^2)$ (e.g., $M = 9$ in this case), which is much more efficient than $\mathcal{O}(M^N)$ in the conventional grid search algorithm in (Chen et al., 2020), as discussed in Section B.1.

B.3 IMPLEMENTATION DETAILS

Our proposed BDDMs and the baseline methods were all implemented with the Pytorch library. The score networks for the LJ and VCTK speech datasets were trained from scratch on a single NVIDIA Tesla P40 GPU with batch size 32 for about 1M steps, which took about 3 days.

For the model architecture, we used the same architecture as in DiffWave (Kong et al., 2021) for the score network with 128 residual channels; we adopted a lightweight GALR network (Lam et al., 2021) for the scheduling network. GALR was originally proposed for speech enhancement, so we considered it well suited for predicting the noise scales. For the configuration of the GALR network, we used a window length of 8 samples for encoding, a segment size of 64 for segmentation and only two GALR blocks of 128 hidden dimensions, and other settings were inherited from (Lam et al., 2021). To make the scheduling network output with a proper range and dimension, we applied a sigmoid function to the last block's output of the GALR network. Then the result was averaged over the segments and the feature dimensions to obtain the predicted ratio: $\sigma_\phi(\boldsymbol{x}) = \text{AvgPool2D}(\sigma(\text{GALR}(\boldsymbol{x})))$, where $\text{GALR}(\cdot)$ denotes the GALR network, $\text{AvgPool2D}(\cdot)$ denotes the average pooling operation applied to the segments and the feature dimensions, and $\sigma(x) := 1/(1 + e^{-x})$. The same network architecture was used for the NE approach for estimating

Table 3: Ratings that have been used in evaluation of speech naturalness of synthetic samples.

Rating	Naturalness	Definition
1	Unsatisfactory	Very annoying, distortion is objectionable.
2	Poor	Annoying distortion, but not objectionable.
3	Fair	Perceptible distortion, slightly annoying.
4	Good	Slight perceptible level of distortion, but not annoying.
5	Excellent	Imperceptible level of distortion.

α_t^2 and was shown better than the ConvTASNet used in the original paper (San-Roman et al., 2021). It is also notable that the computational cost of a scheduling network is indeed fractional compared to the cost of a score network, as predicting a noise scalar variable is intrinsically a relatively much easier task. Our GALR-based scheduling network, while being able to produce stable and reliable results, was about 3.6 times faster than the score network. The training of scheduling networks for BDDMs took only 10k steps to converge, which consumed no more than an hour on a single GPU.

Regarding the image generation task, to demonstrate the generalizability of our method, we directly adopted a score network pre-trained on the CIFAR-10 dataset implemented by a third-party open-source repository. Regarding the scheduling network, to demonstrate that it does not have to use specialized architecture, we replaced GALR by the VGG11 (Simonyan & Zisserman, 2014), which was also used by as a noise estimator in (San-Roman et al., 2021). The output dimension (number of classes) of VGG11 was set to 1. Similar to the setting for GALR in speech synthesis, we added a sigmoid activation to the last layer to ensure a $[0, 1]$ output. Similar to the training in speech domain, we trained the VGG11-based scheduling networks while freezing the score networks for 10k steps, which normally can be finished in about two hours.

Our code for the speech vocoding and the image generation experiments will be uploaded to Github after the final decision of ICLR is released.

B.4 CROWD-SOURCED SUBJECTIVE EVALUATION

All our Mean Opinion Score (MOS) tests were crowd-sourced. We refer to the MOS scores in (Protasio Ribeiro et al., 2011), and the scoring criteria have been included in Table 3 for completeness. The samples were presented and rated one at a time by the testers.

C ADDITIONAL EXPERIMENTS

A demonstration page at https://bilateral-denoising-diffusion-model.github.io shows some samples generated by BDDMs trained on LJ speech and VCTK datasets.

C.1 MULTI-SPEAKER SPEECH SYNTHESIS

In addition to the single-speaker speech synthesis, we evaluated BDDMs on the multi-speaker speech synthesis benchmark VCTK (Yamagishi et al., 2019). VCTK consists of utterances sampled at 48 KHz by 108 native English speakers with various accents. We split the VCTK dataset for training and testing: 100 speakers were used for training the multi-speaker model and 8 speakers for testing. We trained on a 44257-utterance subset (40 hours) and evaluated on a held-out 100-utterance subset. For the score network, we used the Wavegrad architecture (Chen et al., 2020) so as to examine whether the superiority of BDDMs remains in a different dataset and with a different score network architecture.

Results are presented in Table 4. For this multi-speaker VCTK dataset, we obtained consistent observations with that for the single-speaker LJ dataset presented in the main paper. Again, the proposed BDDM with only 16 or 21 steps outperformed the DDPM with 1,000 steps. To the best of our knowledge, ours was the first work that reported this degree of superior. When reducing to 8 steps, BDDM obtained performance on par with (except for a worse PESQ) the costly grid-searched 8 steps (which were unscalable to more steps) in DDPM. For NE, we could again observe a degradation from its 16 steps to 21 steps, indicating the instability of NE for the VCTK dataset

Table 4: Performances of different noise schedules on the multi-speaker VCTK speech dataset, each of which used the same score network (Chen et al., 2020) $\epsilon_\theta(\cdot)$ that was trained on VCTK for about 1M iterations.

Noise schedule	LS-MSE ($\downarrow$)	MCD ($\downarrow$)	STOI ($\uparrow$)	PESQ ($\uparrow$)	MOS ($\uparrow$)
DDPM (Ho et al., 2020; Chen et al., 2020)					
8 steps (Grid Search)	101	**2.09**	**0.787**	**3.31**	**4.22 $\pm$ 0.04**
1,000 steps (Linear)	85.0	2.02	0.798	3.39	4.40 $\pm$ 0.05
DDIM (Song et al., 2021a)					
8 steps (Linear)	553	3.20	0.701	2.81	3.83 $\pm$ 0.04
16 steps (Linear)	412	2.90	0.724	3.04	3.88 $\pm$ 0.05
21 steps (Linear)	355	2.79	0.739	3.12	4.12 $\pm$ 0.05
100 steps (Linear)	259	2.58	0.759	3.30	4.27 $\pm$ 0.04
NE (San-Roman et al., 2021)					
8 steps (Linear)	208	2.54	0.740	3.10	4.18 $\pm$ 0.04
16 steps (Linear)	183	2.53	0.742	3.20	4.26 $\pm$ 0.04
21 steps (Linear)	852	3.57	0.699	2.66	3.70 $\pm$ 0.03
BDDM $(\hat{\alpha}_N, \hat{\beta}_N)$					
8 steps $(0.2, 0.9)$	**98.4**	2.11	0.774	3.18	4.20 $\pm$ 0.04
16 steps $(0.5, 0.5)$	**73.6**	**1.93**	**0.813**	**3.39**	**4.35 $\pm$ 0.05**
21 steps $(0.5, 0.1)$	**76.5**	**1.83**	**0.827**	**3.43**	**4.48 $\pm$ 0.06**

likewise. In contrast, BDDM gave continuously improved performance while increasing the step number.

C.2 Comparing different reverse processes for BDDMs

This section demonstrates that BDDMs do not restrict the sampling procedure to a specialized reverse process in Algorithm 4. In particular, we evaluated different reverse processes, including that of DDPMs as shown in Eq. (4) and DDIMs (Song et al., 2021a), for BDDMs and compared the objective scores on the generated samples. DDIMs (Song et al., 2021a) formulate a non-Markovian generative process that accelerates the inference while keeping the same training procedure as DDPMs. The original generative process in Eq. (4) in DDPMs is modified into

$$p_\theta^{(\tau)}(\boldsymbol{x}_{0:T}) := \pi(\boldsymbol{x}_T) \prod_{i=1}^{S} p_\theta^{(\gamma_i)}(\boldsymbol{x}_{\gamma_{i-1}}|\boldsymbol{x}_{\gamma_i}) \times \prod_{t \in \bar{\gamma}} p_\theta^{(t)}(\boldsymbol{x}_0|\boldsymbol{x}_t), \tag{74}$$

where $\boldsymbol{\gamma}$ is a sub-sequence of length N of $[1, ..., T]$ with $\gamma_N = T$, and $\bar{\boldsymbol{\gamma}} := \{1, ..., T\} \setminus \boldsymbol{\gamma}$ is defined as its complement; Therefore, only part of the models are used in the sampling process.

To achieve the above, DDIMs defined a prediction function $f_\theta^{(t)}(\boldsymbol{x}_t)$ that depends on ϵ_θ to predict the observation $\boldsymbol{x}_0$ given $\boldsymbol{x}_t$ directly:

$$f_\theta^{(t)}(\boldsymbol{x}_t) := \frac{1}{\alpha_t}\left(\boldsymbol{x}_t - \sqrt{1 - \alpha_t^2}\epsilon_\theta(\boldsymbol{x}_t, \alpha_t)\right). \tag{75}$$

By leveraging this prediction function, the conditionals in Eq. (74) are formulated as

$$p_\theta^{(\gamma_i)}(\boldsymbol{x}_{\gamma_{i-1}}|\boldsymbol{x}_{\gamma_i}) = \mathcal{N}\left(\frac{\alpha_{\gamma_{i-1}}}{\alpha_{\gamma_i}}\left(\boldsymbol{x}_{\gamma_i} - \varsigma\epsilon_\theta(\boldsymbol{x}_{\gamma_i}, \alpha_{\gamma_i})\right), \sigma_{\gamma_i}^2 \boldsymbol{I}\right) \quad \text{if } i \in [N], i > 1 \tag{76}$$

$$p_\theta^{(t)}(\boldsymbol{x}_0|\boldsymbol{x}_t) = \mathcal{N}(f_\theta^{(t)}(\boldsymbol{x}_t), \sigma_t^2 \boldsymbol{I}) \quad \text{otherwise}, \tag{77}$$

where the detailed derivation of σ_t and ς can be referred to (Song et al., 2021a). In the original DDIMs, the accelerated reverse process produces samples over the subsequence of $\boldsymbol{\beta}$ indexed by $\boldsymbol{\gamma}$: $\hat{\boldsymbol{\beta}} = \{\beta_n | n \in \boldsymbol{\gamma}\}$. In BDDMs, to apply the DDIM reverse process, we use the $\hat{\boldsymbol{\beta}}$ predicted by the scheduling network in place of a subsequence of the training schedule $\boldsymbol{\beta}$.

Table 5: Performances of different reverse processes for BDDMs on the VCTK speech dataset, each of which used the same score network (Chen et al., 2020) $\epsilon_\theta(\cdot)$ and the same noise schedule.

Noise schedule	LS-MSE ($\downarrow$)	MCD ($\downarrow$)	STOI ($\uparrow$)	PESQ ($\uparrow$)
BDDM (DDPM reverse process)				
8 steps $(0.3, 0.9, 1e^{-5})$	**91.3**	**2.19**	0.936	3.22
16 steps $(0.7, 0.1, 1e^{-6})$	**73.3**	**1.88**	0.949	3.32
21 steps $(0.5, 0.1, 1e^{-6})$	**72.2**	**1.91**	0.950	3.33
BDDM (DDIM reverse process)				
8 steps $(0.3, 0.9, 1e^{-5})$	91.8	**2.19**	**0.938**	**3.26**
16 steps $(0.7, 0.1, 1e^{-6})$	77.7	1.96	**0.953**	**3.37**
21 steps $(0.5, 0.1, 1e^{-6})$	77.6	1.96	**0.954**	**3.39**

Table 6: Comparing sampling methods for DDPM with different number of sampling steps in terms of FIDs in CIFAR10.

Sampling method	Sampling steps	FID
DDPM (baseline) (Ho et al., 2020)	1000	3.17
DDPM (sub-VP) (Song et al., 2021b)	~ 100	3.69
DDPM (DP + reweighting) (Watson et al., 2021)	128	5.24
	64	6.74
DDIM (quadratic) (Song et al., 2021a)	100	4.16
	50	4.67
FastDPM (approx. STEP) (Kong & Ping, 2021)	100	2.86
	50	3.20
[2]Improved DDPM (hybrid) (Nichol & Dhariwal, 2021)	100	4.63
	50	5.09
VDM (augmented) (Kingma et al., 2021)	1000	7.41[3]
Ours BDDM	100	**2.38**
	50	**2.93**

Finally. the objective scores are given in Table 5. Note that the subjective evaluation (MOS) is omitted here since the other assessments above have shown that the MOS scores are highly correlated with the objective measures, including STOI and PESQ. They indicate that applying BDDMs to either DDPM or DDIM reverse process leads to comparable and competitive results. Meanwhile, the results show some subtle differences: BDDMs over a DDPM reverse process gave slightly better samples in terms of signal error and consistency metrics (i.e., LS-MSE and MCD), while BDDM over a DDIM reverse process tended to generate better samples in terms of intelligibility and perceptual metrics (i.e., STOI and PESQ).

C.3 UNCONDITIONAL IMAGE GENERATION

For the unconditional image generation task, we evaluated the proposed BDDMs on the benchmark CIFAR-10 (32×32) dataset. The score functions, including those initially proposed in DDPMs (Ho et al., 2020) or DDIMs (Song et al., 2021a) and those pre-trained in the above third-party implementations, are all conditioned on a discrete step-index. We estimated the noise schedule $\hat{\beta}$ in continuous space using the VGG11 scheduling network and then mapped it to discrete time schedule using the approximation method in (Kong & Ping, 2021).

---

[2]Our implementation was based on `https://github.com/openai/improved-diffusion`

[3]The authors of VDM claimed that they tuned the hyper-parameters only for minimizing the likelihood and did not pursue further tuning of the model to improve FID.

Table 6 shows the performances of different sampling methods for DDPMs in CIFAR-10. By setting the maximum number of sampling steps (N) for noise scheduling, we can fairly compare the improvements achieved by BDDMs against related methods in the literature in terms of FID. Remarkably, BDDMs with 100 sampling steps not only surpassed the 1000-step DDPM baseline, but also produced the SOTA FID performance amongst all generative models using less than or equal to 100 sampling steps.

Figure 4: Spectrum plots of the speech samples produced by BDDM within 3 sampling steps. The first row shows the spectrum of a random signal for starting the reverse process. Then, from the top to the bottom, we show the spectrum of the resultant signal after each step of the reverse process performed by the BDDM. We also provide the corresponding WAV files on our demo page.