BinSGDM: Extreme One-bit Quantization for Communication Efficient Large-Scale Distributed Training

Abstract

To alleviate the communication bottleneck of large-scale distributed training, a rich body of prior communication-compression optimizers have been proposed. These methods focus mainly on high compression ratio to expect acceleration. However, some recent works pointed out, when running with distributed training frameworks (*e.g.*, *DistributedDataParallel* in pytorch), these methods provide no acceleration over the off-the-shelve uncompressed *SGD/Adam* in the typical settings, due to heavy compression/decompression computation or incompatibility with efficient communication primitives or the requirement of uncompressed warmup at the early stage. For these reasons, we propose a novel extreme one-bit quantization optimizer, dubbed *BinSGDM*. The quantization of *BinSGDM* is computed easily and lightly, and it does not need to resort to uncompressed optimizers for warmup. We also theoretically prove that it promises the same convergence speed as the original *Adam*. Moreover, we specially present a hierarchical 1-bit *All-Reduce* technique to further lower the communication volume. Extensive experiments are conducted on 8 to 64 GPUs (1 to 8 nodes) for distributed training with *DistributedDataParallel*, and the experimental results demonstrates that *BinSGDM* with the communication scheme can achieve up to $2.5\times$ speedup for training ResNet-50 and $6.3\times$ speedup for training BERT-Base, compared to the full-precision optimizers.

1 Introduction

With the rapid development of computational power, "bigger" and "bigger" deep neural network (DNN) models are proposed for expecting better performance, from the early classical models, such as AlexNet(61M parameters) (Krizhevsky et al. (2017)), and ResNet (ResNet-50: 20.5M parameters) (He et al. (2016)) to the current foundation models, such as BERT (BERT-Lagre: 340M parameters)(Devlin et al. (2018)), and GPT (GPT-3: 176B parameters)(Brown et al. (2020)). Scalable parallelism across distributed computing workers for training these large-scale models becomes a necessity. During training, millions to billions of parameters neede to communicate among workers at every iteration, and the expensive communication cost become a bottleneck.

To tackle the problem of communication bottleneck , a wide variety of lossy gradient compression optimizers are proposed to lower the volume of communication. These algorithms can be typically divided into three groups, including low-precision approximation (*e.g.*, *1-bit SGD*(Seide et al. (2014)), *SignSGD*(Bernstein et al. (2018)), *TernGrad* (Wen et al. (2017)), and *QSGD*) (Alistarh et al. (2017)), *1-Bit Adam* (Tang et al. (2021))), low-rank simplification (*e.g.*, *ATOMO*(Wang et al. (2018)), *PowerSGD* (Vogels et al. (2019)), and *GradZip* (Cho et al. (2019))), and sparsification (*e.g.*, *Random-k* (Stich et al. (2018)), *Top-k* (Aji & Heafield (2017)), and *MSTop-k* (Shi et al. (2021))). They commonly ensure substantial reduction in communication volume at a slight performance cost on certain tasks.

While much of the research into gradient compression algorithms focuses mainly on the high compression ratio, a more important yet underexplored problem is how to decrease the actual system-level runtime and increase the distributed scaling efficiency. Actually, some recent works (Xu et al. (2020),Agarwal et al. (2022)) pointed out, when distributedly training typical models (*e.g.*, ResNet-

50 and BERT-Base) with off-the-shelf *DistributedDataParallel (DDP)* at typical bandwidths (*e.g.*, 10Gbps), these existing gradient compression algorithms with high compression ratio are still **slower** than the original uncompressed optimizers. This is because they exhibit one or more of the following weaknesses (Xu et al. (2020),Agarwal et al. (2022)): (i) Some gradient compression algorithms should perform compression/decompression and communication within the limited time-frame, and the time cost of compression/decompression, in some cases, is close to and even larger than the savings by the reduces communications; (ii) Some gradient compression algorithms cannot take fully advantage of overlapping between gradient computation and communication. Because if the gradient computation and compression/decompression are overlapping, their intensive computation will mutually compete for GPU resources, which may result in overall slowdown; (iii) Due to inherent structures, some algorithms can only use inefficient collective communication primitive, such as *All-Gather*; (iv) Some gradient compression algorithms need to harness uncompressed optimizers to warm up at the early stage. The warmup time is commonly nontrivial that will to some extent renders their high compression ratio vacuous. Therefore, from a system-level standpoint, the design ethos of a system-efficient communication-compression algorithm is that we should guarantee compression/decompression of the algorithm to compute lightly and take less time, and the corresponding communication should be also friendly to efficient primitive communication primitives. Additionally, there is no need to resort to uncompressed optimizers for warmup.

To this end, we propose a communication-compression optimization algorithm, referred to as Binary SGD-Momentum (*BinSGDM*), and the update step is $Q\left(\frac{\mathcal{M}_{\beta_1}(g_t)}{\mathcal{M}_{\beta_1}(|g_t|)}\right)$ where $Q(\cdot)$ is a binary quantization operator. Like Adam, the proposed algorithm adaptively preconditions gradients, which is the key to guaranteeing a fast convergence speed for training a wide variety of DNNs. More importantly, unlike existing algorithm that compress the gradient, we streamline the compression and directly quantize the entire update. Due to $-1 \leq \frac{\mathcal{M}_{\beta_1}(g_t)}{\mathcal{M}_{\beta_1}(|g_t|)} \leq 1$, the entire update is easy to be quantized to binary 1 or -1, and the compression/decompression is thus computationally light. Meanwhile, warmup with a full-precision optimizer early does not need. We also provide theoretically demonstrate *BinSGDM*'s convergence rate can match that of the original*Adam*. Moreover, according to the nature of *BinSGDM*, we specifically devise an efficient hierarchical communication scheme to further speed up communication, which sufficiently leverages the intra ultra-high bandwidth among GPUs within the same node and efficient commutation primitives rather than *All-Gather*.

In particular, we make the following key **contributions**:

- We propose a novel communication-compress distributed optimizer, dubbed *BinSGDM*. **To the best of our knowledge, it is the first algorithm that quantizes the entire update of an adaptive optimizer and does not need to leverage uncompressed optimizers to warm up to address the convergence issue**, which makes compression/decompression computationally light and the extreme quantization ratio exert its best function (Section 2).

- We theoretically prove that even though extreme 1-bit quantization is employed, ***BinSGDM*** **still promise the same convergence speed as the full-precision *Adam*** (Section 3).

- We present a new hierarchial communication scheme for 1-bit communication, called *Hierarchical 1-bit All-Reduce*, **which sufficiently harnesses the the intra ultra-fast connects to accelerate the local communication, and utilize more efficient commutation primitives to further reduce the communication overhead** (Section 4).

- We perform extensive distributed training experiments to demonstrate the effectiveness of the proposed algorithm. **As far as we know, our algorithm is the first work to consistently trump the uncompressed optimizers with the highly system-level optimized *DDP* in overall running time at no inference performance cost**, reaching up $2.47\times$ speedup for Resnet50 and $6.26\times$ speedup for BERT on 64 GPUs. The better scalability make *BinSGDM* is promising to train more large-scale models (Section 5).

2   EXTREMELY ONE-BIT QUANTIZED BINSGDM

In this section, we focus on solving the following problem when distributedly training a DNN model:

$$\min_{x \in \mathbb{R}^d} f(x) = \frac{1}{n} \sum_{i=1}^{n} f_i(x; \xi^{(i)}) \tag{1}$$

where x is the d-dimensional model parameter, n is the number of distributed workers. $\xi^{(i)}$ is the sampled min-batch data on the i-the worker. The sampled min-batch data on all the workers is independent identically distributed (*i.i.d.*). $f_i(x; \xi^{(i)})$ is the loss function. Note that $f_i(x; \xi_i)$ is commonly abbreviated as $f_i(x)$ in the following.

When we directly employ vallina full-precision and dense-computation optimizers to train a large-scale DNN model on distributed workers, the gradients communication among workers at every iteration will become a bottleneck. An elegant form of optimizer, called *SignSGD*, that merely takes the sign of each coordinates of the gradients, was proposed to alleviate the bottleneck problem. Although it can substantially reduce the communication overhead, its practical performance is still inferior to popular optimizers, such as *Adam*. Fortunately, we observe that the mathematical formulations of *SignSGD* and *Adam* have close connections, so it leaves us an opportunity to propose a new optimizer that can combine their merits, *i.e.*, considerably reducing the communication volume with light computation yet maintaining fast convergence speed and high inference performance.

The mathematical update step of *SignSGD* can be formulated as:

$$x_{t+1} \leftarrow x_t - \alpha_t \text{Sign}(g_t) = x_t - \alpha_t \frac{g_t}{|g_t|} \tag{2}$$

where α_t is the learning rate, g_t denotes the random gradient of $f(x_t)$.

Whereas the update rule of vallina *Adam* can be expressed as:

$$
\begin{aligned}
m_t &\leftarrow \beta_1 m_{t-1} + (1 - \beta_1) g_t, \\
v_t &\leftarrow \beta_2 v_{t-1} + (1 - \beta_2) g_t^2, \\
x_{t+1} &\leftarrow x_t - \alpha_t \frac{m_t}{\sqrt{v_t}},
\end{aligned}
\tag{3}
$$

where β_1 and β_2 represents the exponential moving average factors [1].

If taking the exponential moving average factors to zero, $\beta_1, \beta_2 \rightarrow 0$, in Eq. (3), *Adam* will be equal to *SignSGD*.

Given the above observation, we propose a new optimizer that is an intermediate between *SignSGD* and *Adam*, referred to as *BinSGDM*, *i.e.*,

$$
\begin{aligned}
m_t &\leftarrow \beta m_{t-1} + (1 - \beta) g_t, \\
b_t &\leftarrow \beta b_{t-1} + (1 - \beta) |g_t|, \\
x_{t+1} &\leftarrow x_t - \alpha_t \mathcal{Q}\left(\frac{m_t}{b_t}\right),
\end{aligned}
\tag{4}
$$

where the j-th elements of m_t, b_t rigorously satisfies $-1 \leq \frac{m_t[j]}{b_t[j]} \leq 1$, $\mathcal{Q}(\cdot)$ is an element-wise quantization operator, and it quantizes the j-th element of $\frac{m_t}{b_t}$ as follows :

$$
\mathcal{Q}\left(\frac{m_t[j]}{b_t[j]}\right) = \begin{cases} 1, & \text{with probability } p = \frac{1}{2}(\frac{m_t[j]}{b_t[j]} + 1) \\ -1, & \text{with probability } 1 - p \end{cases}, \tag{5}
$$

where $\mathbb{E}\left(\mathcal{Q}\left(\frac{m_t}{b_t}\right)\right) = \frac{m_t}{b_t}$, so $\mathcal{Q}(\cdot)$ is unbiased.

The detailed implementation of *BinSGDM* in a parameter-server model is illustrated in Algorithm 1. Some appealing characters of *BinSGDM* are summarized in the following:

- All the existing communication-efficiency optimizers are built upon gradient compression. In contrast, to the best of our knowledge, we are the first to directly quantize the entire update, which will streamline the quantization. Moreover, each element of $\frac{m_t}{b_t}$ bounds in the range $[-1, 1]$, and then it is extremely quantized to binary 1 or -1. Thus, the quantization

---

[1]For simplicity, we omit the bias correction for m_t and v_t and the small constant in the numerator.

Algorithm 1. BinSGDM

1: **Initialize**: i^{th} worker model parameter $x_0^{(i)}$, learning rate α_i^T, momentum $m_0 = 0$, $b_0 = 0$, i^{th} worker's local error $e_0^{(i)} = 0$, server's global error $\bar{e}_0 = 0$, exponential moving average factor β.

2: **for** $t = 1, ..., T$ **do**

3:     (**On i^{th} worker**)

4:     Randomly sample $\xi_t^{(i)}$ and compute local gradient: $g_t^{(i)} = \nabla f_i(x; \xi_t^{(i)})$

5:     Update the local $m_t^{(i)}$: $m_t^{(i)} = \beta m_{t-1}^{(i)} + (1 - \beta) g_t^{(i)}$

6:     Update the local $b_t^{(i)}$: $\hat{b}_t^{(i)} = \beta \hat{b}_{t-1}^{(i)} + (1 - \beta)|g_t^{(i)}|$

7:     Update the local $b_t^{(i)}$: $b_t^{(i)} = \max(b_{t-1}^{(i)}, \hat{b}_t^{(i)})$

8:     Quantize the local update: $u_t^{(i)} = \mathcal{Q}(\frac{m_t^{(i)}}{b_t^{(i)}} + e_{t-1}^{(i)})$

9:     Update the local error feedback $e_t^{(i)}$: $e_t^{(i)} = e_{t-1}^{(i)} + \frac{m_t^{(i)}}{b_t^{(i)}} - u_t^{(i)}$

10:     Send $u_t^{(i)}$ to the server

11:    (**On server**)

12:     Average all received q_t and quantize it: $\bar{u}_t = \mathcal{Q}(\frac{1}{n} \sum_{i=1}^n u_t^{(i)} + \bar{e}_{t-1})$

13:     Update the global error feedback $\bar{e}_t$: $\bar{e}_t = \bar{e}_{t-1} + \frac{1}{n} \sum_{i=1}^n u_t^{(i)} - \bar{u}_t$

14:     Send back $\bar{u}_t$ to all workers

15:    (**On i^{th} worker**)

16:     Update the local model parameter $x_{t+1}^{(i)}$: $x_{t+1}^{(i)} = x_t^{(i)} - \alpha_t \bar{u}_t$

17: **end for**

---

in *BinSGDM* is computed easily and lightly, compared to the existing gradient-quantized optimizers [2] .

- Unlike *SignSGD*, *Adam* leverages the adaptively preconditions the gradients via v_t, which is the key to ensure a fast convergence rate in practice. *BinSGDM* also inherits the character of adaptive preconditioning from *Adam* to accelerate the convergence speed. The difference is that we keep the exponential moving average factor for m_t and b_t the same, so that each element of $\frac{m_t}{b_t}$ bounding in the range $[-1, 1]$ can be strictly guaranteed, which is crucial to perform light quantization.

- When the model parameter x_t is close to a local optimal value during training, an ideal optimizer should make sure the updates gradually decay to zero, otherwise x_t will oscillate around the optimum and cannot indeed approach to it. *SignSGD* and *Adam* do not have this appealing property, while, as for *BinSGDM* , the gradient g_t will continually change its sign around the optimum of which the gradient is zero, so that the update $\frac{m_t}{b_t}$ will damp to zero.

Remark. We have noticed that the prior works *1-bit Adam* (Tang et al. (2021)) and its variants (Li et al. (2021), Lu et al. (2022)) also quantize the communication data to 1-bit. However, the design ethos of *1-bit Adam* and the proposed *BinSGDM* are completely different. *1-bit Adam* is still built on gradient compression rather than the entire update. The motivation of *1-bit Adam* is to harness the error feedback (EF) technique (Seide et al. (2014), Stich et al. (2018)) to compensate the gradient information lost to alleviate the convergence issue. However, unlike *SGD*, the parameter update in *Adam* no longer linearly depends on the gradient, so that the EF technique cannot be directly employed. The authors of *1-bit Adam* observed that Adam's variance (non-linear term) becomes stable after the early stage, *1-bit Adam* runs full-precision Adam in the beginning (warmup phase) and utilizes it as a precondition for *SGDM* during the rest of training (compression phase), and then EF in the compression phase help *1-bit Adam* to converge as fast as uncompressed Adam. There are two aspects that influence *1-bit Adam* to indeed accelerate communication. *First*, the warmup steps commonly make up 15%-25% of the total steps in *1-bit Adam*, which to some extent discounts

---

[2]The typical gradient-quantized optimizer *QSGD* quantizes the gradient as follows:

$$\mathcal{Q}\left(g_t[j]\right) = \begin{cases} \|g_t\|_2 \text{sign}(g_t[j]) \cdot \frac{r}{s}, & \text{with probability } p_i = \frac{s|g_t[j]|}{\|g_t\|_2} - r \\ \|g_t\|_2 \text{sign}(g_t[j]) \cdot \frac{r+1}{s}, & \text{with probability } 1 - p_i \end{cases}$$

where $0 \le r < s$ $(r, l \in \mathbb{N})$ and $\frac{s|g_t[j]|}{\|g_t\|_2} \in [\frac{r}{s}, \frac{r+1}{s}]$.

the high quantization ratio. *Second*, in the compression phase, 1-bit Adam should communicate the signs of the gradients of each layer as well as the average scale of all the gradients in this layer, while in *DDP*, raising communication efficiency, the gradients from many layers should be flatted to 1-dimension and concatenated together, and then packed to one bucket to communicate, which means the scale factor of each layer cannot be computed. Therefore, *1-bit Adam* is not compatible with *DDP*, which will also lower the communication efficiency.

3 THEORETICAL ANALYSIS

In this subsection, we present the theoretical convergence guarantee for *BinSGDM* (Algorithm 1). We first introduce some necessary assumptions.

Assumption 1. [Bounded infimum] *For any x and a constant f^*, we have objective value $f(x) \geq f^*$.*

Assumption 2. [Lipschitz continuous gradient] *The gradient $\nabla f(\cdot)$ is L-Lipschitz continuous, i.e., , $\|\nabla f(x) - \nabla f(y)\| \leq L\|x - y\|_2, \quad \forall x, y \in \mathbb{R}^d$.*

Assumption 3. [Unbias and indpendent noisy gradient] *The gradient with respect to the random samples on each worker and at different time is independent identically distributed (i.i.d.), i.e., $\mathbb{E}[g_t^{(i)}] = \nabla f(x_t), \forall t \geq 1$, $g_t^{(i)}$ is independent of $g_t^{(j)}$ for $i \neq j$, and $g_{t_1}^{(i)}$ is independent of $g_{t_2}^{(j)}$ for $t_1 \neq t_2$.*

Assumption 4. [Bounded gradient] *The noisy gradient and the full-set gradient are bounded i.e., $\|g_t^{(i)}\| \leq G, \quad \|\nabla f_t(x)\| \leq G, \quad \forall t \geq 1$.*

Under assumptions above, we then present the theoretical convergence for BinSGDM in Algorithm 1,

Theorem 1. *For BinSGDM in Algorithm 1, under Assumption 1-4, assuming $b_t^{[i]} \succeq \rho I$[3] and choosing $\alpha_t = \frac{c}{\sqrt{t}}$, we then have the following*

$$\mathbb{E}\left[\frac{1}{T}\sum_{t=1}^{T}\|\nabla f(x_t)\|\right]^2 \leq \frac{C_1}{\sqrt{T}} + \frac{C_2(1 + \log T)}{\sqrt{T}}, \tag{6}$$

where

$$C_1 = cG\left(\mathbb{E}[f(z_1) - f^*] + \frac{5L}{6} + \frac{\beta\alpha_1 d}{(1-\beta)\rho}G^2 + \frac{4G^2\alpha_1 d}{\rho} + \frac{\beta^2 LG^2 d}{\rho^2(1-\beta)^2}\right),$$
$$C_2 = cG\left(\frac{(8\beta^2 + 10\beta + 5)L^2 d}{(1-\beta)^2} + \frac{G^2(1+L)}{2\rho^2} + 2L\right).$$

4 HIERARCHIAL 1-BIT ALL-REDUCE

The data in *BinSGDM* to communicate is one-bit, so it cannot be directly aggregated through the efficient *All-Reduce*. Moreover, the intra-node bandwidth and inter-node bandwidth is seriously imbalanced. If we uniformly aggregate the data from intra nodes and inter nodes, the communication will be slowed down by the inter-node data exchange.

In light of the problems above, we propose a hierarchical communication scheme, called *Hierarchial 1-bit All-Reduce*, to efficiently aggregate our 1-bit data, which can hierarchically take advantage of the ultra-high intra-node bandwidth and reduce the inter-node communication overhead. Assuming we have n nodes and each nodes contains m GPUs, and the overall volume for each GPU need to communicate is P. As visually illustrated in Figure 1, the steps of *Hierarchial 1-bit All-Reduce* is as follows: (i) Each GPU conducts *Reduce-Scatter* to locally aggregate the scatter the data within a node, and the communication volume for each GPU is $\frac{(m-1)P}{m}$; (ii) Each GPU performs *BinSGDM*

---
[3]We commonly add a small constant to b_t to avoid zero denominator for numerical stability, which guarantees this assumption holds in practice.

Figure 1: Paradigm of Hierarchial 1-bit All-Reduce

to quantize the data, and then volume becomes $\frac{P}{32m}$ on each GPU. (iii) Each GPUs conducts *1-bit All-Reduce* to inter-aggregate data. This step includes two sub-steps: 1) Each GPU performs *All-to-All* to collect the data of corresponding GPUs in other nodes, and the communication volume is $\frac{(n-1)P}{32mn}$; 2) Each GPU averages and re-quantizes the data, and then conducts *All-Gather* to gather the data, and the communication volume is also $\frac{(n-1)P}{32mn}$; (iv) Each GPU performs *All-Gather* to intra-aggregate data, and the communication volume is $\frac{(m-1)P}{32m}$.

Compared to the time cost of inter-node communication, the time cost of inter-node communication is trivial. Hence, when leveraging *Hierarchial 1-bit All-Reduce*, the most communication cost comes from *1-bit All-Reduce* in Step (iii), and then the communication volume across nodes for all GPUs is approximately $\frac{2(n-1)P}{32}$. In contrast, if we simply utilize the original *All-Gather* to aggregate data, the communication volume across nodes for all GPUs for is approximately $\frac{m^2n(n-1)P}{32}$. Therefore, *Hierarchial 1-bit All-Reduce* is much efficient than the original *All-Gather*.

5 EXPERIMENTS

Table 1: System throughput and Test Accuracy of *SGDM*, *1-bit Adam* and *BinSGDM* for training ResNet-50 on ILSVRC2012 from scratch with $8, 16, 32, 64$ GPUs.

Optimizer	#GPUs	32 samples per GPU		128 samples per GPU	
		Throughput (samples / s)	Top-1 Acc. (%)	Throughput (samples / s)	Top-1 Acc.(%)
SGDM	8	3693 (1.00×)	76.19	5272 (1.00×)	75.05
1-bit Adam		3243 (0.83×)	75.55	5229 (0.99×)	75.42
BinSGDM		3462 (0.94×)	75.98	5251 (0.99×)	75.45
SGDM	16	2959 (1.00×)	75.96	6189 (1.00×)	74.61
1-bit Adam		4745 (1.60×)	75.33	8836 (1.42×)	75.05
BinSGDM		6015 (2.03×)	75.53	9633 (1.56×)	75.09
SGDM	32	4270 (1.00×)	75.47	9909 (1.00×)	74.54
1-bit Adam		7268 (1.70×)	75.18	13827 (1.40×)	74.82
BinSGDM		9416 (2.21×)	75.27	15950 (**1.61×**)	74.82
SGDM	64	6189 (1.00×)	75.37	16640 (1.00×)	74.22
1-bit Adam		5546 (0.89×)	75.54	16426 (0.99×)	74.34
BinSGDM		15253 (**2.47×**)	75.30	23727 (1.43×)	74.24

Recently, some recent works [Xu et al. (2020),Agarwal et al. (2022)] have demonstrated that when running with the system-level optimized distributed data parallel frameworks(*e.g.*, *DDP*), the ex-

Figure 2: Epoch-wise and time-wise convergence speed for training ResNet-50 with 32 samples per GPU, ResNet-50 with 128 samples per GPU, and fine tuning BERT-Base with 3 samples per GPU with 64 GPUs.

Table 2: System throughput and F1-Score / Excat-Match of *AdamW*, *1-bit Adam* and *BinSGDM* for fine tuning ResNet-50 on SQuAD 1.1 with 8, 16, 32, 64 GPUs.

Optimizer	#GPUs	Throughput (samples/s)	F1-Score (%)	Exact Match (%)
AdamW		413 (1.00×)	88.13	80.59
1-bit Adam	8	358 (0.87×)	88.05	80.06
BinSGDM		412 (1.00×)	88.71	81.18
AdamW		84 (1.00×)	88.47	81.07
1-bit Adam	16	213 (2.54×)	87.87	80.31
BinSGDM		431 (5.13×)	88.31	80.80
AdamW		119 (1.00×)	88.38	80.94
1-bit Adam	32	274 (2.30×)	87.78	80.08
BinSGDM		730 (6.13×)	88.08	80.50
AdamW		158 (1.00×)	88.13	80.94
1-bit Adam	64	252 (1.59×)	87.33	79.67
BinSGDM		990 (**6.26×**)	88.28	80.75

isting typical communication-compression optimizers (not including *1-bit Adam*) runs still slower than the full-precision original *SGD/Adam* (the reasons please refer to the section of Introduction). Hence, we only evaluate the performances of *BinSGDM*, the uncompressed original *SGDM /AdamW*, and the closely relevant 1-bit Adam based on performing distributed training experiments with the benchmark model ResNet-50 (CNN) and BERT-Base (Transformer). We show that, running with the distributed data parallel framework *DDP* in pytorch, *BinSGDM* with the proposed specific commutation scheme is up to 2.47 times faster for ResNet-50 and 6.23 times faster for BERT-Base than the uncompressed optimizers with highly system-level optimized *all-reduce* at no accuracy cost.

(a) ResNet-50, 32 samples / GPU (b) ResNet-50, 128 samples / GPU (c) BERT-Base, 3 samples / GPU

Figure 3: System throughput of optimizers for training (a) ResNet-50 with 32 samples per GPU, (b)ResNet-50 with 128 samples per GPU, and (c) fine tuning BERT-Base with 3 samples per GPU with 8, 16, 32, 64 GPUs.

5.1 EXPERIMENTAL SETTINGS

Testbed. Our experiments are implemented on $\{1, 2, 4, 8\}$ nodes connected with 10Gbps Ethernet, and each node is equipped with 8 Nvidia Tesla A100-80GB GPUs. The hardware and software are the same in all instances. The OS in each node is Ubuntu 20.04.4 LTS. Our experiments are performed in Pytorch 1.11.0, and other related libraries are: CUDA-11.6, cuDNN-8.2, NCCL-2.10.3, Pytorch 1.11.0. Notably, to be compatible with *DDP* of Pytorch, parts of *BinSGDM* and our hierarchial communication scheme are implemented in the customized communication hook of *DDP* in Pytorch.

Training details. For the experiments over ResNet-50, we evaluate the convergence and performance of *SGDM*, *1-bit Adam* and *BinSGDM* on ILSVRC2012. The batch size per GPU is set to 32 or 128 with the standard input resolution 224×224. When employing *SGDM (baseline)*, the learning rate starts at $0.1 \times \frac{batch\ size}{256}$ with momentum of 0.9 and weight decay of 0.0001. When employing *1-bit Adam* and *BinSGDM*, the learning rate starts at $0.001 \times \frac{batch\ size}{256}$ with weight decay of 0.0001, and $[\beta_1, \beta_2]$ for *1-bit Adam* is set to $[0.9, 0.999]$ and β for *BinSGDM* is set to 0.95. Then, the learning rate is divided by 10 after 30, 60 and 90 epochs, and training is finally terminated after 100 epochs. Specifically, the first 15 epoches are used as the warmup stage for *1-bit Adam*. For the experiments over BERT-Base, we access the convergence and performance of *AdamW* (baseline), *1-bit Adam* and *BinSGDM* for SQuAD 1.1 fine-tuning task using a pre-trained BERT-Base model checkpoint from HuggingFace [4]. The batch size per GPU is set to 3. We perform the fine-tuning for 2 epochs. The learning rate linearly increase to $0.3 \times$ steps in the early 500 steps and then linearly decrease to 0 in the rest iteration. Specifically, the first $0.2 \times$ steps are used as the warmup stage for *1-bit Adam*. $[\beta_1, \beta_2]$ for *AdamW*, and *1-bit Adam* is set to $[0.9, 0.999]$ and β for *BinSGDM* is set to 0.9.

5.2 EXPERIMENTAL RESULTS

Figure 2 shows the sample-wise and time-wise training convergence behaviors for *SGDM / AdamW* (baseline), *1-bit Adam* and *BinSGDM* with ResNet-50 and BERT-Base running on 64 GPUs. The experimental results demonstrate that *BinSGD* can achieve similar sample-wise convergence rate to the baseline, while its actual speed is substantially faster than the baseline and *1-bit Adam*, up to about $2.5 \times$ speedup for ResNet-50 with batch size 32 per GPU on and about $6.3 \times$ speedup for BERT-Base fine-tuning on SQuAD 1.1.

Figure 3 presents the system throughput for different optimizers with ResNet-50 and BERT-Base running on from 8 GPUs to 64 GPUs. When training on 8 GPUs, since computation rather than communication dominates the running time, the throughput performance for *BinSGDM* is slightly inferior to *SGDM* and *AdamW*, but when the number of GPU is growing, *BinSGDM* consistently outperforms the counterparts, and the more the number of GPUs is, the more the superiority becomes obvious. Furthermore, the system throughout for *SGDM*, *AdamW* and *1-bit Adam* even decreases with GPUs increasing in some cases, whereas the throughout for *BinSGDM* steadily grows, which indicates that *BinSGDM* can offer better scalability efficiency.

In terms of inference performance for ResNet-50, we evaluate the Top-1 accuracy after training on ILSVRC2012 from scratch. As the inference performance for BERT-Base, we measure the F1-score

[4]https://github.com/huggingface/transformers

(a) ResNet-50, 32 samples / GPU   (b) ResNet-50, 128 samples / GPU   (c) BERT-Base, 3 samples / GPU

Figure 4: Computation time, communication time and compression/decompression time per iteration of optimizers for training (a) ResNet-50 with 32 samples per GPU, (b)ResNet-50 with 128 samples per GPU, and (c) fine tuning BERT-Base with 3 samples per GPU with 8, 16, 32, 64 GPUs.

and exact-match score of after fine-tuning on SQuAD 1.1. As shown in Table 1, when the batch size is set to 32 samples per GPU, the accuracy for *BinSGDM* is slightly lower than *SGDM*. For CNN architecture, some works (Keskar & Socher (2017), Zhou et al. (2020)) pointed out adaptive optimizers commonly generalizes worse than *SGDM*. However, when the batch size becomes larger (Table2), *1-bit Adam* and *BinSGDM* achieves better accuracy. The reason for it is that a certain level of noise can be good for generalization (Smith & Le (2018)), biasing the optimizer towards wider valleys. Large batch sice will reduce the randomness, while quantization errors in *BinSGDM* increase the randomness. Table 2 exhibits *BinSGDM* obtains similar or higher F1-score and exact-match score, compared to *AdamW* and *1-bit Adam*, which validates the inferencing effectiveness of the proposed *BinSGDM*.

5.3 COMMUNICATION EFFICIENCY ANALYSIS

As illustrated in Figure 4, when we perform training on a single nodes, the baseline full-precision *SGDM* and *Adam* is slightly faster than *BinSGDM* and *1-bit Adam*. Since the bandwidth among GPUs within a node is ultra high, and communication time becomes trivial, and the newly introduced compression/decompression by communication-compression optimizers takes up more time. Due to the light-computation quantization, *BinSGDM* with ResNet-50 and BERT-Base only takes about $15ms$ and $8ms$ respectively for compression/decompression. When we perform distributed training on two nodes, the bandwidth between nodes in limited (10Gbps in our experimental testbed), the communication time should be reckoned with. For the uncompressed *SGDM* and *Adam*, the communication time considerably exceeds the computation time for ResNet with 32 samples per GPU and BERT-Base, which makes the system throughput even is lower than that on a singe node (shown in Figure 2). Since extremely quantization in *BinSGDM* substantially reduces the communication overhead (up to $32\times$ reduction), the compunction time for *BinSGDM* increase slightly. When the number of nodes is further increasing, a good communication scheme becomes significant. Leveraging our proposed *Hierarchial 1-bit All-Reduce*, the overall inter-node communication volume exchanged is proportional to number of nodes, while, for *CompressedAllreduce* utilized by *1-bit Adam*, the overall communication volume exchanged among nodes is proportional to number of GPUs (8 times number of nodes in our experiment). Therefore, with the number of nodes increasing, the communication time for *BinSGDM* raises gently, but the communication time for *1-bit Adam* grows abruptly.

6 CONCLUSION

In this work, we present a new communication-subtilization optimizers for distributed training. The optimizer is not only computed easily and lightly, but also quantize the communization data to extreme one bit. We also theoretically demonstrate that *BinSGDM* can converge as fast as the original Adam. To further accelerate the communication. will specifically present a novel communication scheme for *BinSGDM* to replace the inefficient naive *All-Gather*. Extensive experiments on training the benchmark ResNet-50 and BERT-Base have validated the effectiveness and efficiency of *BinSGDM* over the uncompressed *SGD,Adam* and the most relevant *1-bit Adam*.

REFERENCES

Saurabh Agarwal, Hongyi Wang, Shivaram Venkataraman, and Dimitris Papailiopoulos. On the utility of gradient compression in distributed training systems. In *Proceedings of Machine Learning and Systems*, volume 4, pp. 652–672, 2022.

Alham Fikri Aji and Kenneth Heafield. Sparse communication for distributed gradient descent. *arXiv preprint arXiv:1704.05021*, 2017.

Dan Alistarh, Demjan Grubic, Jerry Li, Ryota Tomioka, and Milan Vojnovic. Qsgd: Communication-efficient sgd via gradient quantization and encoding. In *Advances in neural information processing systems*, volume 30, 2017.

Jeremy Bernstein, Yu-Xiang Wang, Kamyar Azizzadenesheli, and Animashree Anandkumar. Signsgd: Compressed optimisation for non-convex problems. In *International Conference on Machine Learning*, pp. 560–569, 2018.

Tom Brown, Benjamin Mann, Nick Ryder, Melanie Subbiah, Jared D Kaplan, Prafulla Dhariwal, Arvind Neelakantan, Pranav Shyam, Girish Sastry, Amanda Askell, et al. Language models are few-shot learners. *Advances in Neural Information Processing Systems*, 33:1877–1901, 2020.

Minsik Cho, Vinod Muthusamy, Brad Nemanich, and Ruchir Puri. Gradzip: Gradient compression using alternating matrix factorization for large-scale deep learning. In *Advances in Neural Information Processing Systems*, 2019.

Jacob Devlin, Ming-Wei Chang, Kenton Lee, and Kristina Toutanova. Bert: Pre-training of deep bidirectional transformers for language understanding. *arXiv preprint arXiv:1810.04805*, 2018.

Kaiming He, Xiangyu Zhang, Shaoqing Ren, and Jian Sun. Deep residual learning for image recognition. In *IEEE Conference on Computer Vision and Pattern Recognition*, pp. 770–778, 2016.

Nitish Shirish Keskar and Richard Socher. Improving generalization performance by switching from adam to sgd. *arXiv preprint arXiv:1712.07628*, 2017.

Alex Krizhevsky, Ilya Sutskever, and Geoffrey E Hinton. Imagenet classification with deep convolutional neural networks. *Communications of the ACM*, 60(6):84–90, 2017.

Conglong Li, Ammar Ahmad Awan, Hanlin Tang, Samyam Rajbhandari, and Yuxiong He. 1-bit lamb: Communication efficient large-scale large-batch training with lamb's convergence speed. *arXiv preprint arXiv:2104.06069*, 2021.

Yucheng Lu, Conglong Li, Minjia Zhang, Christopher De Sa, and Yuxiong He. Maximizing communication efficiency for large-scale training via 0/1 adam. *arXiv preprint arXiv:2202.06009*, 2022.

Frank Seide, Hao Fu, Jasha Droppo, Gang Li, and Dong Yu. 1-bit stochastic gradient descent and its application to data-parallel distributed training of speech dnns. In *Fifteenth annual conference of the international speech communication association*, 2014.

Shaohuai Shi, Xianhao Zhou, Shutao Song, Xingyao Wang, Zilin Zhu, Xue Huang, Xinan Jiang, Feihu Zhou, Zhenyu Guo, Liqiang Xie, et al. Towards scalable distributed training of deep learning on public cloud clusters. In *Proceedings of Machine Learning and Systems*, volume 3, pp. 401–412, 2021.

Samuel L Smith and Quoc V Le. A bayesian perspective on generalization and stochastic gradient descent. In *International Conference on Learning Representations (ICLR)*, 2018.

Sebastian U Stich, Jean-Baptiste Cordonnier, and Martin Jaggi. Sparsified sgd with memory. In *Advances in Neural Information Processing Systems*, volume 31, 2018.

Hanlin Tang, Shaoduo Gan, Ammar Ahmad Awan, Samyam Rajbhandari, Conglong Li, Xiangru Lian, Ji Liu, Ce Zhang, and Yuxiong He. 1-bit adam: Communication efficient large-scale training with adams convergence speed. In *International Conference on Machine Learning*, pp. 10118–10129, 2021.

Thijs Vogels, Sai Praneeth Karimireddy, and Martin Jaggi. Powersgd: Practical low-rank gradient compression for distributed optimization. In *Advances in Neural Information Processing Systems*, volume 32, 2019.

Hongyi Wang, Scott Sievert, Shengchao Liu, Zachary Charles, Dimitris Papailiopoulos, and Stephen Wright. Atomo: Communication-efficient learning via atomic sparsification. In *Advances in Neural Information Processing Systems*, volume 31, 2018.

Wei Wen, Cong Xu, Feng Yan, Chunpeng Wu, Yandan Wang, Yiran Chen, and Hai Li. Terngrad: Ternary gradients to reduce communication in distributed deep learning. In *Advances in neural information processing systems*, volume 30, 2017.

Hang Xu, Chen-Yu Ho, Ahmed M Abdelmoniem, Aritra Dutta, El Houcine Bergou, Konstantinos Karatsenidis, Marco Canini, and Panos Kalnis. Compressed communication for distributed deep learning: Survey and quantitative evaluation. Technical report, 2020.

Pan Zhou, Jiashi Feng, Chao Ma, Caiming Xiong, Steven Chu Hong Hoi, et al. Towards theoretically understanding why sgd generalizes better than adam in deep learning. *Advances in Neural Information Processing Systems*, 33:21285–21296, 2020.

A   THEORETICAL ANALYSIS FOR ALGORITHM 1

In practice, we implement *BinSGDM* in a non-parameter-server model to further reduce the communication overhead , but the data exchange is essentially equivalent to that in a parameter-server prototype. Hence, we provide the theoretically analysis for *BinSGDM* in a parameter-server model as shown in Algorithm 1.

According to Algorithm 1, the update $\bar{u}_t$ can be recursively formulated as

$$
\begin{aligned}
\bar{u}_t =& \mathcal{Q}\left(\frac{1}{n}\sum_{i=1}^{n}u_t^{(i)} + \bar{e}_t\right) \\
=& \frac{1}{n}\sum_{i=1}^{n}u_t^{(i)} + \bar{e}_t - \bar{e}_{t+1} \\
=& \frac{1}{n}\sum_{i=1}^{n}\mathcal{Q}\left(\frac{m_t^{(i)}}{b_t^{(i)}} + e_t^{(i)}\right) + \bar{e}_t - \bar{e}_{t+1} \\
=& \frac{1}{n}\sum_{i=1}^{n}\left(\frac{m_t^{(i)}}{b_t^{(i)}} + e_t^{(i)} - e_{t+1}^{(i)}\right) + \bar{e}_t - \bar{e}_{t+1} \\
=& \frac{1}{n}\sum_{i=1}^{n}\frac{m_t^{(i)}}{b_t^{(i)}} + \frac{1}{n}\sum_{i=1}^{n}\left(e_t^{(i)} - e_{t+1}^{(i)}\right) + \bar{e}_t - \bar{e}_{t+1}
\end{aligned}
\tag{7}
$$

Denote

$$g_t \triangleq \frac{1}{n} \sum_{i=1}^{n} g_t^{(i)}, \tag{8}$$

$$m_t \triangleq \frac{1}{n} \sum_{i=1}^{n} m_t^{(i)} = \beta m_{t-1} + (1-\beta) g_t, \tag{9}$$

$$b_t \triangleq \frac{1}{n} \sum_{i=1}^{n} b_t^{(i)} = \beta b_{t-1} + (1-\beta)|g_t|, \tag{10}$$

$$\delta_t \triangleq \frac{1}{n} \sum_{i=1}^{n} \frac{m_t^{(i)}}{b_t^{(i)}} - \frac{m_t}{b_t}, \tag{11}$$

$$e_t \triangleq \frac{1}{n} \sum_{i=1}^{n} e_t^{(i)} + \bar{e}_t \tag{12}$$

$$\tag{13}$$

Hence, the update rule can be summarized as

$$x_{t+1} = x_t - \alpha_t \bar{u}_t$$
$$= x_t - \alpha_t \left(\frac{m_t}{b_t} + \delta + e_t - e_{t+1} \right) \tag{14}$$

A.1 AUXILIARY LEMMAS

Lemma 1. *Let* $u_t = \frac{m_t}{b_t}$, *the element-wise quantization function is defined in Eq.(5) can be reformulated as*

$$\mathcal{Q}(u_t[j]) = \begin{cases} 1, & \text{with probability } p = \frac{u_t[j]+1}{2} \\ -1, & \text{with probability } 1-p \end{cases} \quad (j \in \{1,2,...,d\}, \ -1 \le u_t[j] \le 1). \tag{15}$$

We have $e_t = u_t - \mathcal{Q}(u_t)$, *and then the following holds true*

$$\mathbb{E}[e_t] = 0, \ \mathbb{E}\left[\|e_t\|^2\right] \le d. \tag{16}$$

Proof. From Eq.(15), we know

$$\mathbb{E}[e_t[j]] = \mathbb{E}[u_t - \mathcal{Q}(u_t)]$$
$$= \frac{1}{2}(u_t[j]+1)(u_t[j]-1) + (1 - \frac{1}{2}(u_t[j]+1))(u_t[j]+1) = 0, \tag{17}$$

and,

$$\mathbb{E}\left[(e_t[j])^2\right] = \mathbb{E}\left[(u_t[j] - \mathcal{Q}(u_t[j]))^2\right]$$
$$= \frac{1}{2}(u_t[j]+1)(u_t[j]-1)^2 + (1 - \frac{1}{2}(u_t[j]+1))(u_t[j]+1)^2 \tag{18}$$
$$= 1 - (u_t[j])^2 \le 1.$$

Hence,

$$\mathbb{E}[e_t] = 0, \ \mathbb{E}\left[\|e_t\|^2\right] \le d. \tag{19}$$

Lemma 2. *Let* $x_1 = x_0$ *in Algorithm 1, introducing the sequence*

$$z_t = x_t + \frac{\beta}{1-\beta}(x_t - x_{t-1}) + \frac{\alpha_{t-1}}{1-\beta}(\delta_{t-1} + \beta e_{t-1} - e_t), \forall t \ge 1. \tag{20}$$

Then the following equality will hold, i.e.,

$$z_{t+1} = z_t + \frac{\beta}{1-\beta}\left(\frac{\alpha_{t-1}}{b_{t-1}} - \frac{\alpha_t}{b_t}\right) \odot m_{t-1} - \alpha_t \frac{g_t}{b_t} - \alpha_{t-1}\delta_{t-1} - (\alpha_t - \alpha_{t-1})e_t. \tag{21}$$

Proof. Following Eq. (14), we have

$$
\begin{aligned}
x_{t+1} - x_t + \alpha_t(\delta_t + e_t - e_{t+1}) &= -\alpha_t \frac{m_t}{b_t} \\
&= -\alpha_t \frac{\beta m_{t-1} + (1-\beta)g_t}{b_t} \\
&= \beta\left(x_t - x_{t-1} + \alpha_{t-1}(\delta_t + e_{t-1} - e_t)\right) \\
&\quad + \beta\left(\frac{\alpha_{t-1}}{b_{t-1}} - \frac{\alpha_t}{b_t}\right) \odot m_{t-1} - (1-\beta)\alpha_t \frac{g_t}{b_t}
\end{aligned}
\tag{22}
$$

We know $x_{t+1} - x_t + \alpha_t(e_t - e_{t+1}) = (1-\beta)(x_{t+1} + -\alpha_t(e_{t+1} - \delta_t)) - (1-\beta)(x_t - \alpha_t e_t) + \beta(x_{t+1} - x_t + \alpha_t(\delta_t + e_t - e_{t+1}))$, so Eq. (22) can be rearranged as

$$
\begin{aligned}
&(1-\beta)(x_{t+1} + \alpha_t(\delta_t - e_{t+1})) + \beta(x_{t+1} - x_t + \alpha_t(\delta_t + e_t - e_{t+1})) \\
={}&(1-\beta)(x_t - \alpha_t e_t) + \beta\left(x_t - x_{t-1} + \alpha_{t-1}(\delta_{t-1} + e_{t-1} - e_t)\right) \\
&+ \beta\left(\frac{\alpha_{t-1}}{b_{t-1}} - \frac{\alpha_t}{b_t}\right) \odot m_{t-1} - (1-\beta)\alpha_t \frac{g_t}{b_t}
\end{aligned}
\tag{23}
$$

Divided both sides by $1 - \beta$, we obtain

$$
\begin{aligned}
&x_{t+1} + \alpha_t(\delta_t - e_{t+1}) + \frac{\beta}{1-\beta}(x_{t+1} - x_t + \alpha_t(\delta_t + e_t - e_{t+1})) \\
={}&x_t + \alpha_{t-1}(\delta_{t-1} - e_t) + \frac{\beta}{1-\beta}\left(x_t - x_{t-1} + \alpha_{t-1}(\delta_{t-1} + e_{t-1} - e_t)\right) \\
&+ \frac{\beta}{1-\beta}\left(\frac{\alpha_{t-1}}{b_{t-1}} - \frac{\alpha_t}{b_t}\right) \odot m_{t-1} \\
&- \alpha_t \frac{g_t}{b_t} - \alpha_{t-1}\delta_{t-1} - (\alpha_t - \alpha_{t-1})e_t
\end{aligned}
\tag{24}
$$

Rearranging Eq. (24), we have

$$
\begin{aligned}
&x_{t+1} + \frac{\beta}{1-\beta}(x_{t+1} - x_t) + \frac{\alpha_t}{1-\beta}(\delta_t + \beta e_t - e_{t+1}) \\
={}&x_t + \frac{\beta}{1-\beta}(x_t - x_{t-1}) + \frac{\alpha_{t-1}}{1-\beta}(\delta_{t-1} + \beta e_{t-1} - e_t) \\
&+ \frac{\beta}{1-\beta}\left(\frac{\alpha_{t-1}}{b_{t-1}} - \frac{\alpha_t}{b_t}\right) \odot m_{t-1} \\
&- \alpha_t \frac{g_t}{b_t} - \alpha_{t-1}\delta_{t-1} - (\alpha_t - \alpha_{t-1})e_t
\end{aligned}
\tag{25}
$$

Define the sequence

$$
z_t = x_t + \frac{\beta}{1-\beta}(x_t - x_{t-1}) + \frac{\alpha_{t-1}}{1-\beta}(\delta_{t-1} + \beta e_{t-1} - e_t)
\tag{26}
$$

We finally obtain

$$
z_{t+1} = z_t + \frac{\beta}{1-\beta}\left(\frac{\alpha_{t-1}}{b_{t-1}} - \frac{\alpha_t}{b_t}\right) \odot m_{t-1} - \alpha_t \frac{g_t}{b_t} - \alpha_{t-1}\delta_{t-1} - (\alpha_t - \alpha_{t-1})e_t.
\tag{27}
$$

A.2 PROOF OF THEOREM 1

Proof. By the the gradient Lipschitz continuous in Assumption 2 and Lemma 2, we obtain

$$
\begin{aligned}
\mathbb{E}[f(z_{t+1}) - f(z_t)] &\leq \mathbb{E}\langle \nabla f(z_t), z_{t+1} - z_t \rangle + \frac{L}{2}\mathbb{E}\|z_{t+1} - z_t\|^2 \\
&= \mathbb{E}\left[\frac{\beta}{1-\beta}\langle \nabla f(z_t), \left(\frac{\alpha_{t-1}}{b_{t-1}} - \frac{\alpha_t}{b_t}\right) \odot m_{t-1}\rangle \right] - \mathbb{E}\left[\langle \nabla f(z_t), \alpha_t \frac{g_t}{b_t}\rangle \right] \\
&\quad - \mathbb{E}\left[\langle \nabla f(z_t), \alpha_{t-1}\delta_{t-1}\rangle \right] - \mathbb{E}\left[\langle \nabla f(z_t), (\alpha_t - \alpha_t)e_{t-1}\rangle \right] \\
&\quad + \mathbb{E}\left[\frac{L}{2}\left\| \frac{\beta}{1-\beta}\left(\frac{\alpha_{t-1}}{b_{t-1}} - \frac{\alpha_t}{b_t}\right) \odot m_{t-1} - \alpha_t \frac{g_t}{b_t} - \alpha_{t-1}\delta_{t-1} - (\alpha_t - \alpha_{t-1})e_{t-1} \right\|^2 \right] \\
&= \mathbb{E}\left[\frac{\beta}{1-\beta}\langle \nabla f(z_t), \left(\frac{\alpha_{t-1}}{b_{t-1}} - \frac{\alpha_t}{b_t}\right) \odot m_{t-1}\rangle \right] - \mathbb{E}\left[\langle \nabla f(z_t), \alpha_t \frac{g_t}{b_t}\rangle \right] \\
&\quad + \mathbb{E}\left[\frac{L}{2}\left\| \frac{\beta}{1-\beta}\left(\frac{\alpha_{t-1}}{b_{t-1}} - \frac{\alpha_t}{b_t}\right) \odot m_{t-1} - \alpha_t \frac{g_t}{b_t} - \alpha_{t-1}\delta_{t-1} - (\alpha_t - \alpha_{t-1})e_{t-1} \right\|^2 \right] \\
&\leq \mathbb{E}\left[\frac{\beta}{1-\beta}\langle \nabla f(z_t), \left(\frac{\alpha_{t-1}}{b_{t-1}} - \frac{\alpha_t}{b_t}\right) \odot m_{t-1}\rangle \right] - \mathbb{E}\left[\langle \nabla f(z_t), \alpha_t \frac{g_t}{b_t}\rangle \right] \\
&\quad + L\mathbb{E}\left[\left\| \frac{\beta}{1-\beta}\left(\frac{\alpha_{t-1}}{b_{t-1}} - \frac{\alpha_t}{b_t}\right) \odot m_{t-1} \right\|^2 \right] + L\mathbb{E}\left[\alpha_t^2 \left\| \frac{g_t}{b_t} \right\|^2 \right] \\
&\quad + \frac{L}{2}\mathbb{E}\left[\|\alpha_{t-1}\delta_{t-1}\|^2 \right] + \frac{L}{2}\mathbb{E}\left[\|(\alpha_{t-1} - \alpha_t)e_t\|^2 \right]
\end{aligned}
\tag{28}
$$

where the second equality holds due to $\mathbb{E}[\delta_{t-1}] = 0$ and $\mathbb{E}[e_{t-1}] = 0$. The last inequality holds owing to $\mathbb{E}[\|a + b\|^2] = \mathbb{E}[\|a\|^2] + \mathbb{E}[\|b\|^2]$ if $\mathbb{E}[a] = 0$ or $\mathbb{E}[b] = 0$, and $\mathbb{E}[\|a + b\|^2] \leq 2\mathbb{E}[\|a\|^2] + 2\mathbb{E}[\|b\|^2]$ if $\mathbb{E}[a] \neq 0$ and $\mathbb{E}[b] \neq 0$.

Taking telescope sum from 1 to T on the both sides of Eq.(28) , we then have

$$
\begin{aligned}
\mathbb{E}[f(z_T) - f(z_1)] &\leq \underbrace{\frac{\beta}{1-\beta}\mathbb{E}\left[\sum_{t=1}^{T}\langle \nabla f(z_t), \left(\frac{\alpha_{t-1}}{b_{t-1}} - \frac{\alpha_t}{b_t}\right) \odot m_{t-1}\rangle \right]}_{T_1} \underbrace{- \mathbb{E}\left[\sum_{t=1}^{T}\langle \nabla f(z_t), \alpha_t \frac{g_t}{b_t}\rangle \right]}_{T_2} \\
&\quad + \underbrace{L\mathbb{E}\left[\sum_{t=1}^{T}\left\| \frac{\beta}{1-\beta}\left(\frac{\alpha_{t-1}}{b_{t-1}} - \frac{\alpha_t}{b_t}\right) \odot m_{t-1} \right\|^2 \right]}_{T_3} \\
&\quad + \underbrace{L\mathbb{E}\left[\sum_{t=1}^{T}\alpha_t^2 \left\| \frac{g_t}{b_t} \right\|^2 \right] + \frac{L}{2}\mathbb{E}[\sum_{t=1}^{T}\|\alpha_{t-1}\delta_{t-1}\|^2] + \frac{L}{2}\mathbb{E}[\sum_{t=1}^{T}\|(\alpha_{t-1} - \alpha_t)e_t\|^2]}_{T_4}
\end{aligned}
\tag{29}
$$

Now we focus on bounding T_1 below. From Assumption 4, we know $\|g_t\| \leq G$ ($t = 1, 2, ..., T$) and $\|\nabla f(z_t)\| \leq G$. Due to $m_t = \beta m_{t-1} + (1 - \beta)g_t$ and $m_1 = g_1$, it is easy to obtain $\|m_t\| \leq G$ by complete induction.

Since $\|\nabla f(z_t)\| \leq G$ and $\|m_t\| \leq G$, we have

$$
\begin{aligned}
T_1 &= \frac{\beta}{1-\beta}\mathbb{E}\left[\sum_{i=1}^{T}\langle\nabla f(z_i), \left(\frac{\alpha_{t-1}}{b_{t-1}} - \frac{\alpha_t}{b_t}\right)\odot m_{i-1}\rangle\right] \\
&\overset{(i)}{\leq} \frac{\beta}{1-\beta}\mathbb{E}\left[\sum_{i=1}^{T}\|\nabla f(z_t)\|\|m_t\|\left\|\frac{\alpha_{t-1}}{b_{t-1}} - \frac{\alpha_t}{b_t}\right\|_1\right] \\
&\overset{(ii)}{\leq} \frac{\beta}{1-\beta}G^2\mathbb{E}\left[\sum_{i=1}^{T}\left\|\frac{\alpha_{t-1}}{b_{t-1}} - \frac{\alpha_t}{b_t}\right\|_1\right] \\
&\overset{(iii)}{=} \frac{\beta}{1-\beta}G^2\mathbb{E}\left[\left\|\sum_{i=1}^{T}\left(\frac{\alpha_{t-1}}{b_{t-1}} - \frac{\alpha_t}{b_t}\right)\right\|_1\right] \\
&\leq \frac{\beta}{1-\beta}G^2\mathbb{E}\left[\left\|\frac{\alpha_1}{b_1}\right\|_1\right] \\
&\overset{(iv)}{\leq} \frac{\beta\alpha_1 d}{(1-\beta)\rho}G^2,
\end{aligned}
\tag{30}
$$

where (i) holds sice $\|a\odot b\| \leq \|a\|\max_j|b[j]| \leq \|a\|\|b\|_1$, (ii) holds due to $\|\nabla f(z_t)\| \leq G$ and $\|m_t\| \leq G$, (iii) holds because $\frac{\alpha_{t-1}}{b_{t-1}[j]} - \frac{\alpha_t}{b_t[j]} \geq 0$ for any j, (iv) holds due to $\min_j b_t[j] \geq \rho > 0$.

Let us turn to bound T_2,

$$
\begin{aligned}
T_2 &= -\mathbb{E}\left[\sum_{t=1}^{T}\langle\nabla f(z_t), \alpha_t\frac{g_t}{b_t}\rangle\right] \\
&= \underbrace{-\mathbb{E}\left[\sum_{t=1}^{T}\langle\nabla f(z_t) - f(x_t), \alpha_t\frac{g_t}{b_t}\rangle\right]}_{T_5} \underbrace{-\mathbb{E}\left[\sum_{t=1}^{T}\langle\nabla f(x_t), \alpha_t\frac{g_t}{b_t}\rangle\right]}_{T_6}
\end{aligned}
\tag{31}
$$

We now analyze T_5 below,

$$
\begin{aligned}
T_5 &= -\mathbb{E}\left[\sum_{t=1}^{T}\langle \nabla f(z_t) - f(x_t), \alpha_t \frac{g_t}{b_t}\rangle\right] \\
&\overset{(i)}{\leq} \frac{1}{2}\mathbb{E}\left[\sum_{t=1}^{T}\|f(z_t) - f(x_t)\|^2\right] + \frac{1}{2}\mathbb{E}\left[\sum_{t=1}^{T}\alpha_t^2\left\|\frac{g_t}{b_t}\right\|^2\right] \\
&\overset{(ii)}{\leq} \frac{L^2}{2}\mathbb{E}\left[\sum_{t=1}^{T}\|z_t - x_t\|^2\right] + \frac{1}{2}\mathbb{E}\left[\sum_{t=1}^{T}\alpha_t^2\left\|\frac{g_t}{b_t}\right\|^2\right] \\
&\overset{(iii)}{=} \frac{L^2}{2}\mathbb{E}\left[\sum_{t=1}^{T}\left\|\frac{\beta}{1-\beta}(x_t - x_{t-1}) + \frac{\alpha_{t-1}}{1-\beta}\left(\delta_{t-1} + \beta e_{t-1} - e_t\right)\right\|^2\right] + \frac{1}{2}\mathbb{E}\left[\sum_{t=1}^{T}\alpha_t^2\left\|\frac{g_t}{b_t}\right\|^2\right] \\
&\overset{(iv)}{\leq} \frac{\beta^2 L^2}{(1-\beta)^2}\mathbb{E}\left[\sum_{t=1}^{T}\|x_t - x_{t-1}\|^2\right] + \frac{L^2}{(1-\beta)^2}\mathbb{E}\left[\sum_{t=1}^{T}\|\alpha_{t-1}\delta_{t-1}\|^2\right] \\
&\quad + \frac{\beta^2 L^2}{(1-\beta)^2}\mathbb{E}\left[\sum_{t=1}^{T}\|\alpha_{t-1}e_{t-1}\|^2\right] + \frac{L^2}{(1-\beta)^2}\mathbb{E}\left[\sum_{t=1}^{T}\|\alpha_{t-1}e_t\|^2\right] + \frac{1}{2}\mathbb{E}\left[\sum_{t=1}^{T}\alpha_t^2\left\|\frac{g_t}{b_t}\right\|^2\right] \\
&\overset{(v)}{=} \frac{\beta^2 L^2}{(1-\beta)^2}\mathbb{E}\left[\sum_{t=1}^{T}\alpha_{t-1}^2\left\|\left(\frac{m_{t-1}}{b_{t-1}} + \delta_{t-1} + e_{t-1} - e_t\right)\right\|^2\right] + \frac{L^2}{(1-\beta)^2}\mathbb{E}\left[\sum_{t=1}^{T}\|\alpha_{t-1}\delta_{t-1}\|^2\right] \\
&\quad + \frac{\beta^2 L^2}{(1-\beta)^2}\mathbb{E}\left[\sum_{t=1}^{T}\|\alpha_{t-1}e_{t-1}\|^2\right] + \frac{L^2}{(1-\beta)^2}\mathbb{E}\left[\sum_{t=1}^{T}\|\alpha_{t-1}e_t\|^2\right] + \frac{1}{2}\mathbb{E}\left[\sum_{t=1}^{T}\alpha_t^2\left\|\frac{g_t}{b_t}\right\|^2\right] \\
&= \frac{\beta^2 L^2}{(1-\beta)^2}\mathbb{E}\left[\sum_{t=1}^{T}\left\|\frac{\alpha_{t-1}m_{t-1}}{b_{t-1}}\right\|^2\right] + \frac{\beta^2 L^2}{(1-\beta)^2}\mathbb{E}\left[\sum_{t=1}^{T}\|\alpha_{t-1}\delta_{t-1}\|^2\right] \\
&\quad + \frac{\beta^2 L^2}{(1-\beta)^2}\mathbb{E}\left[\sum_{t=1}^{T}\|\alpha_{t-1}e_{t-1}\|^2\right] + \frac{\beta^2 L^2}{(1-\beta)^2}\mathbb{E}\left[\sum_{t=1}^{T}\|\alpha_{t-1}e_t\|^2\right] + \frac{L^2}{(1-\beta)^2}\mathbb{E}\left[\sum_{t=1}^{T}\|\alpha_{t-1}\delta_{t-1}\|^2\right] \\
&\quad + \frac{\beta^2 L^2}{(1-\beta)^2}\mathbb{E}\left[\sum_{t=1}^{T}\|\alpha_{t-1}e_{t-1}\|^2\right] + \frac{L^2}{(1-\beta)^2}\mathbb{E}\left[\sum_{t=1}^{T}\|\alpha_{t-1}e_t\|^2\right] + \frac{1}{2}\mathbb{E}\left[\sum_{t=1}^{T}\alpha_t^2\left\|\frac{g_t}{b_t}\right\|^2\right] \\
&= \frac{\beta^2 L^2}{(1-\beta)^2}\mathbb{E}\left[\sum_{t=1}^{T}\alpha_{t-1}^2\left\|\frac{m_{t-1}}{b_{t-1}}\right\|^2\right] + \frac{(1+\beta^2)L^2}{(1-\beta)^2}\mathbb{E}\left[\sum_{t=1}^{T}\alpha_{t-1}^2\|\delta_{t-1}\|^2\right] \\
&\quad + \frac{2\beta^2 L^2}{(1-\beta)^2}\mathbb{E}\left[\sum_{t=1}^{T}\alpha_{t-1}^2\|e_{t-1}\|^2\right] + \frac{(1+\beta^2)L^2}{(1-\beta)^2}\mathbb{E}\left[\sum_{t=1}^{T}\alpha_{t-1}^2\|e_t\|^2\right] + \frac{1}{2}\mathbb{E}\left[\sum_{t=1}^{T}\alpha_t^2\left\|\frac{g_t}{b_t}\right\|^2\right] \\
&\overset{(vi)}{\leq} \left(\frac{\beta^2 L^2 d}{(1-\beta)^2} + \frac{4(1+\beta^2)L^2 d}{(1-\beta)^2} + \frac{2\beta^2 L^2 d}{(1-\beta)^2} + \frac{(1+\beta^2)L^2 d}{(1-\beta)^2} + \frac{G^2}{2c}\right)\sum_{t=1}^{T}\alpha_{t-1}^2 \\
&= \left(\frac{(8\beta^2 + 10\beta + 5)L^2 d}{(1-\beta)^2} + \frac{G^2}{2\rho^2}\right)\sum_{t=1}^{T}\alpha_{t-1}^2
\end{aligned}
$$

(32)

where (i) holds by following $\langle a, b\rangle \leq \frac{1}{2}\|a\|^2 + \frac{1}{2}\|a\|^2$, (ii) holds due to Assumption 1, (iii) holds due to Assumption 1 owing to Eq.(20), (iii) holds since $\mathbb{E}[\|a+b\|^2] = \mathbb{E}[\|a\|^2] + \mathbb{E}[\|b\|^2]$ if $\mathbb{E}[a] = 0$ or $\mathbb{E}[b] = 0$, (v) holds resulting from the update rule in Eq. (14), vi holds due to $\left|\frac{m_t[j]}{b_t[j]}\right| \leq 1$, $|\delta[j]| \leq 2$ (the definition of δ_t in Eq. (11)), $\mathbb{E}[\|e_t\|^2] \leq d$ in Lemma 1, $\|g_t\| \leq G$ in Assumption 2 and $\min_j b_t[j] \geq \rho > 0$.

We then bound T_6

$$
\begin{aligned}
T_6 =& -\mathbb{E}\left[\sum_{t=1}^{T}\langle\nabla f(x_t),\alpha_t\frac{g_t}{b_t}\rangle\right] \\
=& -\mathbb{E}\left[\sum_{t=1}^{T}\langle\nabla f(x_t),\alpha_t\frac{\nabla f(x_t)}{b_t}\rangle\right] - \mathbb{E}\left[\sum_{t=1}^{T}\langle\nabla f(x_t),\alpha_t\frac{g_t-\nabla f(x_t)}{b_t}\rangle\right] \\
\overset{(i)}{\leq}& -\frac{1}{G}\mathbb{E}\left[\sum_{t=1}^{T}\alpha_t\|\nabla f(x_t)\|^2\right] + \mathbb{E}\left[\sum_{t=1}^{T}\langle\nabla f(x_t),\alpha_t\frac{\nabla f(x_t)-g_t}{b_t}\rangle\right] \\
=& -\frac{1}{G}\mathbb{E}\left[\sum_{t=1}^{T}\alpha_t\|\nabla f(x_t)\|^2\right] + \mathbb{E}\left[\langle\nabla f(x_1),\alpha_1\frac{\nabla f(x_1)-g_1}{b_1}\rangle\right] \\
& + \mathbb{E}\left[\sum_{t=1}^{T}\langle\nabla f(x_t),\nabla(f(x_t)-g_t)\odot\left(\frac{\alpha_t}{b_t}-\frac{\alpha_{t-1}}{b_{t-1}}\right)\rangle\right] + \mathbb{E}\left[\sum_{t=2}^{T}\langle\nabla f(x_t),\alpha_t\frac{\nabla f(x_t)-g_t}{b_{t-1}}\rangle\right] \\
\overset{(ii)}{=}& -\frac{1}{G}\mathbb{E}\left[\sum_{t=1}^{T}\alpha_t\|\nabla f(x_t)\|^2\right] + \mathbb{E}\left[\langle\nabla f(x_1),\alpha_1\frac{\nabla f(x_1)-g_1}{b_1}\rangle\right] \\
& + \mathbb{E}\left[\sum_{t=2}^{T}\langle\nabla f(x_t),(\nabla f(x_t)-g_t)\odot\left(\frac{\alpha_t}{b_t}-\frac{\alpha_{t-1}}{b_{t-1}}\right)\rangle\right] \\
\overset{(iii)}{\leq}& -\frac{1}{G}\mathbb{E}\left[\sum_{t=1}^{T}\alpha_t\|\nabla f(x_t)\|^2\right] + \mathbb{E}\left[\|\nabla f(x_1)\|\|\nabla f(x_1)-g_1\|\left\|\frac{\alpha_1}{b_1}\right\|_1\right] \\
& + \mathbb{E}\left[\sum_{t=2}^{T}\|\nabla f(x_t)\|\|\nabla f(x_t)-g_t\|\left\|\frac{\alpha_t}{b_t}-\frac{\alpha_{t-1}}{b_{t-1}}\right\|_1\right] \\
\overset{(iv)}{\leq}& -\frac{1}{G}\mathbb{E}\left[\sum_{t=1}^{T}\alpha_t\|\nabla f(x_t)\|^2\right] + 2G^2\mathbb{E}\left[\left\|\frac{\alpha_1}{b_1}\right\|_1 + \sum_{t=2}^{T}\left\|\frac{\alpha_t}{b_t}-\frac{\alpha_{t-1}}{b_{t-1}}\right\|_1\right] \\
\overset{(v)}{=}& -\frac{1}{G}\mathbb{E}\left[\sum_{t=1}^{T}\alpha_t\|\nabla f(x_t)\|^2\right] + 2G^2\mathbb{E}\left[\left\|\frac{\alpha_1}{b_1} + \sum_{t=2}^{T}\frac{\alpha_{t-1}}{b_{t-1}}-\frac{\alpha_t}{b_t}\right\|_1\right], \\
=& -\frac{1}{G}\mathbb{E}\left[\sum_{t=1}^{T}\alpha_t\|\nabla f(x_t)\|^2\right] + 4G^2\mathbb{E}\left[\left\|\frac{\alpha_1}{b_1}\right\|_1\right], \\
\overset{(vi)}{\leq}& -\frac{1}{G}\mathbb{E}\left[\sum_{t=1}^{T}\alpha_t\|\nabla f(x_t)\|^2\right] + \frac{4G^2\alpha_1 d}{\rho}
\end{aligned}
$$
(33)

where (i) holds due to $\max_j b_t[j] \leq \|b_t\| \leq G$, (ii) holds owing to $\mathbb{E}[\nabla f(x_t)-g_t] = 0$ in Assumption 2 and g_t, b_{t-1} are independent, (iii) holds sice $\|a\odot b\| \leq \|a\|\max_j|b[j]| \leq \|a\|\|b\|_1$, (iv) holds resulting from $\|\nabla f(x_t)\| \leq G$ and $\|\nabla f(x_t)-g_t\| \leq \|\nabla f(x_t)\| + \|g_t\| \leq 2G$, and (v) holds because $\frac{\alpha_{t-1}}{b_{t-1}[j]} - \frac{\alpha_t}{b_t[j]} \geq 0$ for any j, (vi) holds due to $\min_j b_t[j] \geq \rho > 0$.

Then, we pay attention to T_3,

$$
\begin{aligned}
T_3 &= L\mathbb{E}\left[\sum_{t=1}^{T}\left\|\frac{\beta}{1-\beta}\left(\frac{\alpha_{t-1}}{b_{t-1}}-\frac{\alpha_t}{b_t}\right)\odot m_{t-1}\right\|^2\right] \\
&\leq \frac{\beta^2 L}{(1-\beta)^2}\mathbb{E}\left[\sum_{i=1}^{t}\left\|\frac{\alpha_{t-1}}{b_{t-1}}-\frac{\alpha_t}{b_t}\right\|^2\|m_{t-1}\|^2\right] \\
&\leq \frac{\beta^2 LG^2}{(1-\beta)^2}\mathbb{E}\left[\sum_{i=1}^{t}\left\|\frac{\alpha_{t-1}}{b_{t-1}}-\frac{\alpha_t}{b_t}\right\|^2\right] \\
&\leq \frac{\beta^2 LG^2}{\rho(1-\beta)^2}\mathbb{E}\left[\sum_{i=1}^{t}\left\|\frac{\alpha_{t-1}}{b_{t-1}}-\frac{\alpha_t}{b_t}\right\|_1\right] \\
&\leq \frac{\beta^2 LG^2}{\rho(1-\beta)^2}\mathbb{E}\left[\left\|\frac{\alpha_1}{b_1}\right\|_1\right] \\
&\leq \frac{\beta^2 LG^2 d}{\rho^2(1-\beta)^2},
\end{aligned}
\tag{34}
$$

where the first inequality holds due to $\|a\odot b\|\leq\|a\|\|b\|$, the second holds owing to $\|m_{t-1}\|\leq G$, the third equality holds due to $\|a\|^2\leq\max_j|a[j]|\|a\|_1$ and $\min_j b_t[j]\geq\rho>0$, and the third equality holds resulting from $\frac{\alpha_{t-1}}{b_{t-1}[j]}-\frac{\alpha_t}{b_t[j]}\geq 0$ for any j.

Now we turn attention to T_4,

$$
\begin{aligned}
T_4 &= L\mathbb{E}\left[\sum_{t=1}^{T}\alpha_t^2\left\|\frac{g_t}{b_t}\right\|^2\right]+\frac{L}{2}\mathbb{E}[\sum_{t=1}^{T}\|\alpha_{t-1}\delta_{t-1}\|^2]+\frac{L}{2}\mathbb{E}[\sum_{t=1}^{T}\|(\alpha_{t-1}-\alpha_t)e_t\|^2] \\
&\leq \left(L\frac{G^2}{\rho^2}+2L\right)\sum_{t=1}^{T}\alpha_t^2+\frac{L}{2}\sum_{t=1}^{T}(\alpha_{t-1}-\alpha_t)^2,
\end{aligned}
\tag{35}
$$

where the inequality holds owing to $\|m_{t-1}\|\leq G$ and $\min_j b_t[j]\geq\rho>0$, $|\delta_{t-1}[j]|\leq 2$, and $\mathbb{E}[\|e_t\|^2]\leq 1$.

Combining Eq.(29-35), we can obtain

$$
\begin{aligned}
\mathbb{E}[f(z_T)-f(z_1)] \leq &\frac{\beta\alpha_1 d}{(1-\beta)\rho}G^2+\left(\frac{(8\beta^2+10\beta+5)L^2 d}{(1-\beta)^2}+\frac{G^2}{2\rho^2}\right)\sum_{t=1}^{T}\alpha_{t-1}^2 \\
&-\frac{1}{G}\mathbb{E}\left[\sum_{t=1}^{T}\alpha_t\|\nabla f(x_t)\|^2\right]+\frac{4G^2\alpha_1 d}{\rho}+\frac{\beta^2 LG^2 d}{\rho^2(1-\beta)^2} \\
&+\left(L\frac{G^2}{\rho^2}+2L\right)\sum_{t=1}^{T}\alpha_t^2+\frac{L}{2}\sum_{t=1}^{T}(\alpha_{t-1}-\alpha_t)^2.
\end{aligned}
\tag{36}
$$

Reformulating Eq.(36), we then have

$$
\begin{aligned}
\frac{1}{G}\mathbb{E}\left[\sum_{t=1}^{T}\alpha_t\|\nabla f(x_t)\|^2\right] \leq &\mathbb{E}[f(z_1)-f(z_T)] \\
&+\left(\frac{(8\beta^2+10\beta+5)L^2 d}{(1-\beta)^2}+\frac{G^2(1+L)}{2\rho^2}+2L\right)\sum_{t=1}^{T}\alpha_{t-1}^2 \\
&+\frac{L}{2}\sum_{t=1}^{T}(\alpha_{t-1}-\alpha_t)^2 \\
&+\frac{\beta\alpha_1 d}{(1-\beta)\rho}G^2+\frac{4G^2\alpha_1 d}{\rho}+\frac{\beta^2 LG^2 d}{\rho^2(1-\beta)^2}
\end{aligned}
\tag{37}
$$

Utilizing the fact the learning rate $\alpha_t = \frac{c}{\sqrt{t}}$ is non-increasing and Cauchy-Schwarz inequality, we know $\mathbb{E}\left[\sum_{t=1}^{T}\alpha_t\|\nabla f(x_t)\|^2\right] \geq T\alpha_T\mathbb{E}\left[\frac{1}{T}\sum_{t=1}^{T}\|\nabla f(x_t)\|\right]^2 = \frac{\sqrt{T}}{c}\mathbb{E}\left[\frac{1}{T}\sum_{t=1}^{T}\|\nabla f(x_t)\|\right]^2$. $\sum_{t=1}^{T}\alpha_{t-1}^2 = \sum_{t=1}^{T}\frac{c^2}{t} \leq (1+\log T)c^2$, and $\sum_{t=2}^{T}(\alpha_{t-1}-\alpha_t)^2 = \sum_{t=2}^{T}(\alpha_{t-1}-\alpha_t)^2 \leq \frac{5}{3} - \frac{1}{\sqrt{t}} \leq \frac{5}{3}$, we further have

$$\mathbb{E}\left[\frac{1}{T}\sum_{t=1}^{T}\|\nabla f(x_t)\|\right]^2 \leq \frac{C_1}{\sqrt{T}} + \frac{C_2(1+\log T)}{\sqrt{T}}, \tag{38}$$

where we define

$$C_1 = cG\left(\mathbb{E}[f(z_1)-f^*] + \frac{5L}{6} + \frac{\beta\alpha_1 d}{(1-\beta)\rho}G^2 + \frac{4G^2\alpha_1 d}{\rho} + \frac{\beta^2 LG^2 d}{\rho^2(1-\beta)^2}\right), \tag{39}$$

$$C_2 = cG\left(\frac{(8\beta^2+10\beta+5)L^2 d}{(1-\beta)^2} + \frac{G^2(1+L)}{2\rho^2} + 2L\right). \tag{40}$$

B DISCUSSION

In the original 1-bit Adam paper (Tang et al. (2021)), 1-bit Adam runs significantly (up to $3.8\times$) faster than the full-precision Adam. Moreover, as the number of GPUs grows, the speed advantage is more obvious. In contrast, compared to the original Adam, 1-bit Adam does not exhibit clear speed superiorly, and when running on 64 GPUs, 1-bit Adam is not only slower than the original Adam, but also its throughput rate is even lower than that on 32 GPUs. The reasons for this phenomenon can be summarized in following. *First*, in (Tang et al. (2021)), the speedup of 1-bit Adam is obtained by comparing the throughput at compression phase with the throughput at warmup phase. The warmup phase is actually excluded for assessing throughput, while, in our experiment, we evaluate overall average throughput of the warmup phase and the compression phase for 1-bit Adam. *Second*, the baseline original Adam in (Tang et al. (2021)) does not ran with system-level efficient*DDP*. *Third*, in (Tang et al. (2021)), the authors customized highly efficient communication primitives for 1-bit Adam. For the sake of fairness, we just utilize the off-the-shelf communication primitives in Pytorch for all the optimizers.

As shown in Figure 4, when the number of GPUs continually, the communication time for *BinSGDM* also grows superlinearly. One of the reasons is that the communication primitive $All-to-All$ accounts for more and more communication time. But the native *All-to-All* and *All-Gather* in Step (iii) in *Hierarchical 1-bit All-Reduce* is not less efficient than the native $AllReduce$. Hence, we will further optimize *All-to-All* and *All-Gather* to further accelerate *BinSGDM*.

When training large-scale DNNs, the mix-precision technique is used to reduce the memory, so that we can further increase the model size. In optimizers, we still use the full-precision state and full-precision computation which commonly accounts for 33-75% of the total memory footprint (*Tim Dettmers, et al. 8-bit Optimizer via Block-wise Quantization, ICLR2022.*). Actually, *BinSGDM* does not need full-precision state and full-precision computation. Moreover, due to randomly quantizing the update to 1 or -1, *BinSGDM* may leverage lower-precision than FP16 gradients to estimate the update. Therefore, *BinSGDM* is promising to find more applications in reducing memory.