iFlow: Numerically Invertible Flows for Efficient Lossless Compression via a Uniform Coder

Abstract

It was estimated that the world produced $59ZB$ ($5.9 \times 10^{13}GB$) of data in 2020, resulting in the enormous costs of both data storage and transmission. Fortunately, recent advances in deep generative models have spearheaded a new class of so-called "neural compression" algorithms, which significantly outperform traditional codecs in terms of compression ratio. Unfortunately, the application of neural compression garners little commercial interest due to its limited bandwidth; therefore, developing highly efficient frameworks is of critical practical importance. In this paper, we discuss lossless compression using normalizing flows which have demonstrated a great capacity for achieving high compression ratios. As such, we introduce iFlow, a new method for achieving efficient lossless compression. We first develop the Uniform Base Conversion Systems (UBCS), an extremely fast coder for uniform distribution. Then by incorporating normalizing flow with UBCS, a family of numerically invertible flow transformations are proposed. iFlow achieves state-of-the-art compression ratios and is $5\times$ quicker than other high-performance schemes. Furthermore, the techniques presented in this paper can be used to accelerate coding time for a broad class of flow-based algorithms.

1 Introduction

The volume of data, measured in terms of IP traffic, is currently witnessing an exponential year-on-year growth [13]. Consequently, the cost of transmitting and storing data is rapidly becoming prohibitive for service providers, such as cloud and streaming platforms. These challenges increasingly necessitate the need for the development of high-performance lossless compression codecs.

One promising solution to this problem has been the development of a new class of so-called "neural compression" algorithms [29, 37, 18, 4, 17, 36, 25, 30, 6, 40]. These methods typically posit a deep probabilistic model of the data distribution, which, in combination with entropy coders, can be used to compress data with the minimal codelength bounded by the negative log-likelihood [28]. However, despite reliably improved compression performance compared to traditional codecs [14, 32, 9, 33], meaningful commercial applications have been limited by impractically slow coding speed.

In this paper, we focus on developing approaches with deep probabilistic models based on *normalizing flows* [11, 24, 31, 26, 7, 27, 22]. A normalizing flow admits a learnable bijective mapping between input data and a latent variable representation. In this paradigm, inputs can be compressed by first transforming data to latent variables, with the resulting output encoded by a prior distribution. Compared to other classes of generative models, normalizing flows typically perform best in both tasks of probability density estimation (as compared with variational autoencoders [23, 15, 8]) and inference speed (as compared with autoregressive factorizations [34, 38, 21]). This suggests that compression with flows can jointly achieve high compression ratios along with fast coding times.

Submitted to 35th Conference on Neural Information Processing Systems (NeurIPS 2021). Do not distribute.

Figure 1: Illustration of IDF(++), iVPF, LBB and the proposed iFlow method. Flow layers with darker color denote higher expressive power. The top-right of each model illustration shows the key procedure of exact bijections between $\bar{x}$ and $\bar{z}$. The compression ratio and bandwidth are listed below.

Unfortunately, lossless compression requires discrete data for entropy coding, and the continuous bijections of normalizing flows would not guarantee discrete latent variables. As such, transformations would require discretization, resulting in a loss of information [40, 3]. To resolve this issue, Integer Discrete Flows (IDF) [18, 4] (Fig. 1, left) proposed an invertible mapping between discrete data *and* latent variables. Similarly, iVPF [40] achieves a discrete-space bijection using *volume-preserving* flows. However, the above models must introduce constraints on flow layers to ensure a discrete-space bijection, which limits the expressivity of the transformation. Local Bits-Back Coding (LBB) [17] (Fig. 1, middle) was the first approach to succeed in lossless coding with the flexible family of continuous flows. It resolves the information loss by coding numerical errors with the rANS coder [12]. However, the coder is extraordinarily slow, making the method impractical.

In this paper, we introduce iFlow: a numerically invertible flow-based neural compression codec that bridges the gap between high-fidelity density estimators and practical coding speed. To achieve this we introduce two novelties: Modular Scale Transform (MST) and Uniform Base Conversion Systems (UBCS). MST presents a flexible family of bijections in discrete space, deriving an invertible class of flows suitable for lossless compression. UBCS, built on the uniform distribution, permits a highly efficient entropy coding compatible with MST. The main ideas are illustrated in Fig. 1(right). We test our approach across a range of image datasets against both traditional and neural compression techniques. Experimentally we demonstrate that our method achieves state-of-the-art compression ratios, with coding time $5\times$ quicker than that of the next-best scheme, LBB.

2 Numerically Invertible Flows and Lossless Compression

Let $f : \mathcal{X} \rightarrow \mathcal{Z}$ be our normalizing flow, which we build as a composition of layers such that $f = f_L \circ ... \circ f_2 \circ f_1$. Defining d-dimensional $\mathbf{y}_0 = \mathbf{x} \in \mathcal{X}$ and $\mathbf{y}_L = \mathbf{z} \in \mathcal{Z}$, the latents can be computed as $\mathbf{y}_l = f_l(\mathbf{y}_{l-1})$, with $p_X(\mathbf{x})$ calculated according to

$$\log p_X(\mathbf{x}) = \log p_Z(\mathbf{z}) + \sum_{l=1}^{L} \log | \det J_{f_l}(\mathbf{y}_{l-1})|, \qquad (1)$$

where $J_{f_l}(\mathbf{x})$ is the Jacobian matrix of the transformation f_l at $\mathbf{y}_{l-1}$. In this paper, we use log to denote *base 2 logarithms*. Training the flow should minimize the negative log-likelihood $-\log p_X(\mathbf{x})$. The inverse flow is defined as $f^{-1} = f_1^{-1} \circ ... \circ f_L^{-1}$, such that $f^{-1}(\mathbf{z}) = \mathbf{x}$. There are many types of invertible bijections, f_l. Popular choices include element-wise, autoregressive (e.g. coupling layers) [40] and 1×1 convolution transformations [24].

To perform lossless compression with normalizing flows, the input data should be transformed to latent variables, which are then encoded with a prior distribution. As data and encoded bits should be in binary format, $\mathbf{x}$ and $\mathbf{z}$ must be discrete, with a bijection between discrete inputs and outputs established. However, as discussed, this operation is usually intractable with popular classes of transformations used in continuous flows due to the numerical errors induced by discretization.

In this section, we introduce a novel algorithm derived from continuous flows that allows us to achieve an exact bijiective mapping between discrete $\mathbf{x}$ *and* discrete $\mathbf{z}$. We present the general idea of a flow layer's numerical invertibility in discrete space in Sec. 2.1. We then introduce our flow layers in Sec. 2.2 and 2.3, with their application to compression discussed in Sec. 2.4 and 2.5.

2.1 Invertibility of Flows in Discrete Space

To discretize the data, we follow [40] and adopt *k-precision quantization* to assign floating points to discretization bins such that

$$\bar{x} = \frac{\lfloor 2^k \cdot x \rfloor}{2^k}, \tag{2}$$

where $\lfloor \cdot \rfloor$ is the floor function. The associated quantization error is bounded by $|\bar{x} - x| < 2^{-k}$. Any d-dimensional $\mathbf{x}$ can be quantized into bins with volume $\delta = 2^{-kd}$. The probability mass of $\bar{\mathbf{x}}$ can then be approximated by $P(\bar{\mathbf{x}}) = p(\bar{\mathbf{x}})\delta$, such that the theoretical codelength is $-\log(p(\bar{\mathbf{x}})\delta)$.

Denote our proposed numerically invertible flow (iFlow) according to $\bar{f} = \bar{f}_L \circ ... \circ \bar{f}_1$. The input and output should be subject to k-precision quantization, where each layer should be appropriately invertible such that $\bar{\mathbf{y}}_{l-1} \equiv \bar{f}_l^{-1}(\bar{f}_l(\bar{\mathbf{y}}_{l-1}))$. Denoting $\bar{\mathbf{y}}_0 = \mathbf{x}$ and $\bar{\mathbf{z}} = \bar{\mathbf{y}}_L$, it is further expected that $\bar{\mathbf{z}} = \bar{f}(\mathbf{x})$ and $\mathbf{x} \equiv \bar{f}^{-1}(\bar{\mathbf{z}})$. We will show in the following subsections that $\bar{f}$ can be derived from *any* continuous flow f in such a way that the error between $\bar{f}(\mathbf{x})$ and $f(\mathbf{x})$ is negligible.

2.2 Numerically Invertible Element-Wise Flows

We begin by describing our approach for element-wise flows $\mathbf{z} = f(\mathbf{x})$[1], where f is a monotonic element-wise transformation. In most cases, f does not present a unique inverse in discrete space, such that $f^{-1}(\bar{\mathbf{z}}) \neq \mathbf{x}$. In what follows, we introduce an approach to derive an invertible, discrete-space operation from any element-wise flow transformation. For simplicity, we denote the inputs and output pairs of a continuous flow as x and $z = f(x)$; and we denote the k-precision quantized input-output pairs of iFlow as $\bar{x}$ and $\bar{z} = \bar{f}(\bar{x})$.

2.2.1 Scale Flow

Algorithm 1 Modular Scale Transform (MST): Numerically Invertible Scale Flow $f(x) = R/S \cdot x$.

Forward MST: $\bar{z} = \bar{f}(\bar{x})$.
1: $\hat{x} \leftarrow 2^k \cdot \bar{x}$;
2: Decode r_d from $U(0, R)$; $\hat{y} \leftarrow R \cdot \hat{x} + r_d$;
3: $\hat{z} \leftarrow \lfloor \hat{y}/S \rfloor, r_e \leftarrow \hat{y} \mod S$;
4: Encode r_e with $U(0, S)$;
5: **return** $\bar{z} \leftarrow \hat{z}/2^k$.

Inverse MST: $\bar{x} = \bar{f}^{-1}(\bar{z})$.
1: $\hat{z} \leftarrow 2^k \cdot \bar{z}$;
2: Decode r_e from $U(0, S)$; $\hat{y} \leftarrow S \cdot \hat{z} + r_e$;
3: $\hat{x} \leftarrow \lfloor \hat{y}/R \rfloor, r_d \leftarrow \hat{y} \mod R$;
4: Encode r_d with $U(0, R)$;
5: **return** $\bar{x} \leftarrow \hat{x}/2^k$.

We begin with the scale transformation defined as $z = f(x) = a \cdot x$, $(a > 0)$, from which we are able to build more complex flow layers. The input can be converted to an integer with $\hat{x} = 2^k \cdot \bar{x}$, and the latent variable $\bar{z}$ can be recovered from integer $\hat{z}$ by $\bar{z} = \hat{z}/2^k$. Inspired by MAT in iVPF [40], we first approximate a with a fractional such that $a \approx \frac{R}{S}$, where $R, S \in \mathbb{N}$. We can then obtain $\hat{z}$ with $\hat{z} = \lfloor (R \cdot \hat{x} + r_d)/S \rfloor$ where r_d is sampled uniformly from $\{0, 1, ..., R-1\}$. The remainder $r_e = (R \cdot \hat{x} + r_d) \mod R$ can be encoded to eliminate the error.

Let $U(0, A)$ be the uniform distribution such that $P(s) = \frac{1}{A}$, $s \in \{0, 1, ..., A-1\}$. The numerically invertible scale flow $\bar{f}$ is displayed in Alg. 1. As the modular operation is essential to Alg. 1, we name it the *Modular Scale Transform* (MST). Setting S and $R = \text{round}(S \cdot a)$ to be large, we observe that the following propositions hold.

Proposition 1. *[40]* $|\bar{z} - f(\bar{x})| < O(S^{-1}, 2^{-k})$.

Proposition 2. *The codelength of MST is* $L_f(\bar{x}, \bar{z}) = \log S - \log R \approx -\log |a| = -\log |f'(\bar{x})|$.

Proposition 1 establishes that the error is small if S and k are large. Proposition 2 demonstrates that the codelength is almost exactly the log-Jocabian of f. The above properties and the correctness of the

---

[1]For notation simplicity, we assume that the flow contains just one layer.

106 algorithm are discussed in the Appendix. Further note that, with the exception of the usual encoding
107 and decoding processes, MST's operations can be parallelized, resulting in minimal additional
108 overhead.

2.2.2 General Element-wise Flow

Algorithm 2 Numerically Invertible Element-wise Flows

Forward: $\bar{z} = \bar{f}(\bar{x})$.
1: Get $\bar{x}_l, \bar{x}_h, \bar{z}_l, \bar{z}_h$ given $\bar{x}$, so that $\bar{x} \in [\bar{x}_l, \bar{x}_h)$;
2: Set large S; get R with Eq. (4); $\bar{x}' \leftarrow \bar{x} - \bar{x}_l$;
3: Get $\bar{z}'$ with forward MST in Alg. 1, given input $\bar{x}'$ and coefficients R, S;
4: **return** $\bar{z} = \bar{z}' + \bar{z}_l$. $\triangleright \bar{z} \in [\bar{z}_l, \bar{z}_h)$.

Inverse: $\bar{x} = \bar{f}^{-1}(\bar{z})$.
1: Get $\bar{x}_l, \bar{x}_h, \bar{z}_l, \bar{z}_h$ given $\bar{z}$, so that $\bar{z} \in [\bar{z}_l, \bar{z}_h)$;
2: Set large S; get R with Eq. (4); $\bar{z}' \leftarrow \bar{z} - \bar{z}_l$;
3: Get $\bar{x}'$ with inverse MST in Alg. 1, given input $\bar{z}'$ and coefficients R, S;
4: **return** $\bar{x} = \bar{x}' + \bar{x}_l$. $\triangleright \bar{x} \in [\bar{x}_l, \bar{x}_h)$.

---

110 For simplicity, we assume the non-linear f is monotonically increasing. For a monotonically
111 decreasing f, we simply invert the sign: $-f$.

112 MST in Alg. 1 works with *linear* transformations, and is incompatible with *non-linear* functions.
113 Motivated by linear interpolation, we can approximate the non-linear flow with a piecewise linear
114 function. In general, consider input $\bar{x}$ to be within an interval $\bar{x} \in [\bar{x}_l, \bar{x}_h)^2$ and $\bar{z}_l = \overline{f(\bar{x}_l)}, \bar{z}_l = $
115 $\overline{f(\bar{x}_h)}$. The linear interpolation of f is then

$$f_{inp}(x) = \frac{\bar{z}_h - \bar{z}_l}{\bar{x}_h - \bar{x}_l}(\bar{x} - \bar{x}_l) + \bar{z}_l. \tag{3}$$

116 It follows that $\bar{z}$ can be derived from MST with input $\bar{x} - \bar{x}_l$ followed by adding $\bar{z}_l$. Furthermore, $\bar{z}$ and
117 $\bar{x}$ can be recovered with the corresponding inverse transformation. To preserve monotonicity, $\bar{z}$ must
118 be within interval $\bar{z} \in [\bar{z}_l, \bar{z}_h)$. Denoting the invertible linear flow derived from f_{inp} as $\bar{f}_{inp}$, it must
119 hold that $\bar{f}_{inp}(\bar{x}_l) \geq \bar{z}_l, \bar{f}_{inp}(\bar{x}_h - 2^{-k}) \leq \bar{z}_h - 2^{-k}$. As we use MST in Alg. 1, we observe that when
120 $\frac{\bar{z}_h - \bar{z}_l}{\bar{x}_h - \bar{x}_l}$ is approximated with R/S, the minimum possible value of $\bar{f}_{inp}(\bar{x}_l)$ is $\bar{z}_l$ (when $r_d = 0$ in Line
121 2) and the maximum possible value of $\bar{f}_{inp}(\bar{x}_h - 2^{-k})$ is $\lfloor (R \cdot 2^k(\bar{x}_h - \bar{x}_l - 2^{-k}) + R - 1)/(S \cdot 2^k) \rfloor + \bar{z}_l$
122 (when $r_d = R - 1$ in Line 2). Given large S, the largest possible value of R should be

$$R = \lfloor \frac{(2^k \cdot (\bar{z}_h - \bar{z}_l) - 1) \cdot S + 1}{2^k \cdot (\bar{x}_h - \bar{x}_l)} \rfloor. \tag{4}$$

123 Another difficulty is in determining the correct interpolation interval $[\bar{x}_l, \bar{x}_h)$. One simple solution is
124 to split the input domain into uniform intervals with length 2^{-h} such that $\bar{x}_l = \lfloor (2^h \cdot \bar{x})/2^h \rfloor, \bar{x}_h = $
125 $\bar{x}_l + 2^{-h}$. However, for the inverse computation given $\bar{z}$, it is not easy to recover the interpolation
126 interval as $f^{-1}(\bar{z})$ may not be within $[\bar{x}_l, \bar{x}_h)$. Instead, as $\bar{z} \in [\bar{z}_h, \bar{z}_l)$, the interval $[\bar{x}_l, \bar{x}_h)$ can be
127 obtained via a binary search in which $\bar{x}_l$ is obtained with $\bar{z} \in [\overline{f(\bar{x}_l)}, \overline{f(\bar{x}_h)})$. Another approach
128 is to split the co-domain into uniform intervals such that $\bar{z}_l = \lfloor (2^h \cdot \bar{z})/2^h \rfloor, \bar{z}_h = \bar{z}_l + 2^{-h}$, with
129 $\bar{x}_l = \overline{f^{-1}(\bar{z}_l)}, \bar{x}_h = \overline{f^{-1}(\bar{z}_h)}$. In this case, determining $[\bar{z}_l, \bar{z}_h)$ during the inverse computation
130 is simple. While for the forward pass, $[\bar{z}_l, \bar{z}_h)$ should be determined with a binary search such
131 that $\bar{x} \in [\overline{f^{-1}(\bar{z}_l)}, \overline{f^{-1}(\bar{z}_h)})$. In practice, we have simpler tricks to determine the correct interval
132 $[\bar{x}_l, \bar{x}_h), [\bar{z}_l, \bar{x}_h)$ for both the forward and inverse computation, which can be found in the Appendix.

133 The general idea of the non-linear flow adaptations are summarized in Alg. 2. Note that Alg. 2
134 can be used in any element-wise flow including linear flow. In Alg. 2, Proposition 2 holds such
135 that $L_f(\bar{x}, \bar{z}) = -\log(R/S) \approx -\log \frac{\bar{z}_h - \bar{z}_l}{\bar{x}_h - \bar{x}_l} \approx -\log |f'(\bar{x})|$. It is possible to arrive at a similar
136 conclusion in Proposition 1 where the corresponding error is $|\bar{z} - f(\bar{x})| < O(S^{-1}, 2^{-k}, 2^{-2h})$.

2.3 Practical Numerically Invertible Flow Layers

138 Whilst one can use many types of complex transformations to build richly expressive flow-based
139 models, to ensure the existence and uniqueness of the inverse computation, these layers are generally
140 constructed with element-wise transformations. In this subsection, we demonstrate the invertibility of
141 discretized analogs to some of the most widely used flow layers using the operators as described in

---

2All intervals must cover the domain, and each interval should not be intersected.

142 Sec. 2.2. Such flows include autoregressive flows [20] (including coupling flows [10, 11, 16]) and
143 1×1 convolutional flows [24].

2.3.1 Autoregressive and Coupling Flows

Algorithm 3 Numerically Invertible Autoregressive Flow

Forward: $\bar{\mathbf{z}} = \bar{f}(\bar{\mathbf{x}})$.	**Inverse:** $\bar{\mathbf{x}} = \bar{f}^{-1}(\bar{\mathbf{z}})$.
1: **for** $i = m, ..., 1$ **do**	1: **for** $i = 1, ..., m$ **do**
2: $\quad \bar{\mathbf{z}}_i \leftarrow \bar{f}_i(\bar{\mathbf{x}}_i, \bar{\mathbf{x}}_{<i})$ with Alg. 2 (forward);	2: $\quad \bar{\mathbf{x}}_i \leftarrow \bar{f}_i^{-1}(\bar{\mathbf{z}}_i, \bar{\mathbf{x}}_{<i})$ with Alg. 2 (inverse);
3: **end for**	3: **end for**
4: **return** $\bar{\mathbf{z}} = [\bar{\mathbf{z}}_1, ..., \bar{\mathbf{z}}_m]^\top$.	4: **return** $\bar{\mathbf{z}} = [\bar{\mathbf{z}}_1, ..., \bar{\mathbf{z}}_m]^\top$.

---

145 Supposing that the inputs and outputs, $\mathbf{x}$ and $\mathbf{z}$, are split into m parts $\mathbf{x} = [\mathbf{x}_1, ..., \mathbf{x}_m]^\top, \mathbf{z} =$
146 $[\mathbf{z}_1, ..., \mathbf{z}_m]^\top$, the autoregressive flow $\mathbf{z} = f(\mathbf{x})$ can be represented as $\mathbf{z}_i = f_i(\mathbf{x}_i; \mathbf{x}_{<i})$, where
147 $f_i(\cdot; \mathbf{x}_{<i})$ is the element-wise flow (discussed in Sec. 2.2), conditioned on $\mathbf{x}_{<i}$. Now let $\bar{f}_i(\cdot; \mathbf{x}_{<i})$
148 denote the invertible element-wise flow transformation as discussed in Alg. 1-2. Alg. 3 then illustrates
149 the details of an invertible autoregressive flow $\bar{f}$.

150 Propositions 1 and 2 hold in our discretized autoregressive transformation. In fact, the log-determinant
151 of Jacobian is given by $\log|\det J_f(\mathbf{x})| = \sum_{i=1}^m \log|\det J_{f_i}(\mathbf{x}_i; \mathbf{x}_{<i})|$, and the expected codelength
152 is simply $L_f(\bar{\mathbf{x}}, \bar{\mathbf{z}}) = \sum_{i=1}^m L_f(\bar{\mathbf{x}}_i, \bar{\mathbf{z}}_i) \approx -\sum_{i=1}^m \log|\det J_{f_i}(\bar{\mathbf{x}}_i; \bar{\mathbf{x}}_{<i})| = -\log|\det J_f(\bar{\mathbf{x}})|$.

153 When $m = 2$ and $f_1(\mathbf{x}_1) = \mathbf{x}_1$, the autoregressive flow is reduced to a *coupling flow*, which is
154 widely used in flow-based models [10, 11, 16]. It is therefore trivially clear that the coupling flow is
155 additionally compatible with Alg. 3.

2.3.2 1×1 Convolutional Flow

157 1×1 convolutional layers can be viewed as a matrix multiplication along a channel dimension [24].
158 Let $\bar{\mathbf{x}}, \bar{\mathbf{z}} \in \mathbb{R}^c$ be inputs and outputs along channels, and $\mathbf{W} \in \mathbb{R}^{c \times c}$ the weights of our network. The
159 objective is to obtain $\bar{\mathbf{z}} = \bar{f}(\bar{\mathbf{x}})$ where $f(\mathbf{x}) = \mathbf{W}\mathbf{x}$.

160 We use the ideas of iVPF [40] to achieve a numerically invertible 1×1 convolutional transformation.
161 In particular, we begin by performing an LU decomposition such that $\mathbf{W} = \mathbf{P}\mathbf{L}\mathbf{\Lambda}\mathbf{U}$. It then
162 follows that the 1×1 convolution is performed with successive matrix multiplications with $\mathbf{U}, \mathbf{\Lambda}, \mathbf{L}$
163 and $\mathbf{P}$. In iVPF, the authors extensively discussed matrix multiplications with factors $\mathbf{U}, \mathbf{L}$ and
164 $\mathbf{P}$ [40]. Meanwhile, one can view the matrix multiplication with $\mathbf{\Lambda}$ as a scale transform, such that
165 $f(\mathbf{x}) = \boldsymbol{\lambda} \odot \mathbf{x}$, where $\odot$ is an element-wise multiplication and $\boldsymbol{\lambda}$ are the diagonal elements of
166 $\mathbf{\Lambda}$. MST in Alg. 1 can then be applied. In such a case, it is clear that Proposition 1 and 2 hold
167 for a 1×1 convolutional flow. For Proposition 2, it is observed that $L_f(\bar{\mathbf{x}}, \bar{\mathbf{z}}) \approx -\text{sum}(\log \boldsymbol{\lambda}) =$
168 $-\log|\det \mathbf{\Lambda}| = -\log|\det \mathbf{W}| = -\log|\det J_f(\bar{\mathbf{x}})|$.

2.4 Building Numerically Invertible Flows

170 Our flow model is constructed as a composition of layers $f = f_L \circ ... \circ f_2 \circ f_1$, where each layer
171 is a transformation of the type discussed in Sec. 2.2 and 2.3. Let us represent the resulting flow
172 as $\bar{f} = \bar{f}_L \circ ... \circ \bar{f}_1$, where $\bar{f}_l$ is a discretized transformation derived from the corresponding
173 continuous f. It is clear that the quantized input $\bar{\mathbf{x}}(= \bar{\mathbf{y}}_0)$ and latent $\bar{\mathbf{z}}(= \bar{\mathbf{y}}_L)$ establish a bijection
174 with successive transformations between discrete inputs and outputs. For the forward pass, $\bar{\mathbf{z}}$ is
175 computed with $\bar{\mathbf{y}}_l = \bar{f}(\bar{\mathbf{y}}_{l-1}), l = 1, 2, ..., L$; for the inverse pass, $\bar{\mathbf{x}}$ is recovered with the inverse
176 flow $\bar{f}^{-1} = \bar{f}_1^{-1} \circ ... \circ \bar{f}_L^{-1}$ such that $\bar{\mathbf{y}}_{l-1} = f_l^{-1}(\bar{\mathbf{y}}_l)$.

177 For our resultant flow model, we can draw similar conclusions as in Propositions 1 and 2. Firstly, the
178 error of $\bar{\mathbf{z}} = \bar{f}(\bar{\mathbf{x}})$ and $\mathbf{z} = f(\bar{\mathbf{x}})$ is small, bounded by $|\bar{\mathbf{z}} - \mathbf{z}| < O(LS^{-1}, L2^{-k}, L2^{-2h})$. Secondly,
179 the codelength is approximately $L_f(\bar{\mathbf{x}}, \bar{\mathbf{z}}) = \sum_{l=1}^L L_{f_l}(\bar{\mathbf{y}}_{l-1}, \bar{\mathbf{y}}_l) \approx -\sum_{l=1}^L \log|\det J_{f_l}(\bar{\mathbf{y}}_{l-1})|$.

2.5 Lossless Compression with Flows via Bits-back Dequantization

181 Armed with our flow model $\bar{f}$, performing lossless compression is straight-forward. For the encoding
182 process, the latent is generated according to $\bar{\mathbf{z}} = \bar{f}(\bar{\mathbf{x}})$. We then encode $\bar{\mathbf{z}}$ with probability $p_Z(\bar{\mathbf{z}})\delta$.

For the decoding process, $\bar{\mathbf{z}}$ is decoded with $p_Z(\bar{\mathbf{z}})\delta$, and $\bar{\mathbf{x}}$ is recovered with $\bar{f}^{-1}(\bar{\mathbf{z}})$. The expected codelength is approximately $-\log(p_X(\bar{\mathbf{x}})\delta)$ such that

$$L(\bar{\mathbf{x}}) \approx -\log(p_Z(\bar{\mathbf{z}})\delta) - \sum_{l=1}^{L} \log|\det J_{f_l}(\bar{\mathbf{y}}_{l-1})| \approx -\log(p_X(\bar{\mathbf{x}})\delta). \tag{5}$$

However, we note that if k is large, $-\log\delta$ and the codelengths will also be large, resulting in a waste of bits. For what follows, we adopt the bits-back trick in LBB [17] to reduce the codelength. In particular, consider coding with input data $\mathbf{x}^\circ \in \mathbb{Z}^d$, where a k-precision noise vector $\bar{\mathbf{u}} \in [0,1)^d$ is decoded with $q(\bar{\mathbf{u}}|\mathbf{x}^\circ)\delta$ and added to input data such that $\bar{\mathbf{x}} = \mathbf{x}^\circ + \bar{\mathbf{u}}$. In this way, $\bar{\mathbf{x}}$ is then encoded with our flow $\bar{f}$. For the decoding process, $\mathbf{x}^\circ$ is recovered by applying the inverse transformation. We name this coding process *Bits-back Dequantization*, which is summarized in Alg. 4.

Algorithm 4 Lossless Compression with Flows.

Encode $\mathbf{x}^\circ$.
1: Decode $\bar{\mathbf{u}}$ using $q(\bar{\mathbf{u}}|\mathbf{x}^\circ)\delta$;
2: $\bar{\mathbf{z}} \leftarrow \bar{f}(\mathbf{x}^\circ + \bar{\mathbf{u}})$;
3: Encode $\bar{\mathbf{z}}$ with $p_Z(\bar{\mathbf{z}})\delta$.

Decode.
1: Decode $\bar{\mathbf{z}}$ using $p_Z(\bar{\mathbf{z}})\delta$;
2: $\bar{\mathbf{x}} \leftarrow \bar{f}^{-1}(\bar{\mathbf{z}})$, $\mathbf{x}^\circ \leftarrow \lfloor\bar{\mathbf{x}}\rfloor$;
3: Encode $\bar{\mathbf{u}} = \bar{\mathbf{x}} - \mathbf{x}^\circ$ with $q(\bar{\mathbf{u}}|\mathbf{x}^\circ)\delta$;
4: **return** $\mathbf{x}^\circ$.

In practice, $q(\mathbf{u}|\mathbf{x}^\circ)$ is constructed with a flow model such that $\mathbf{u} = g(\boldsymbol{\epsilon}; \mathbf{x}^\circ)$ where $\boldsymbol{\epsilon} \sim p(\boldsymbol{\epsilon})$. $\bar{\mathbf{u}}$ is decoded by first decoding $\bar{\boldsymbol{\epsilon}}$ with $p(\bar{\boldsymbol{\epsilon}})\delta$, and then applying $\bar{\mathbf{u}} = \bar{g}(\bar{\boldsymbol{\epsilon}}; \mathbf{x}^\circ)$. Thus decoding $\bar{\mathbf{u}}$ involves $-\log(q(\bar{\mathbf{u}}|\mathbf{x}^\circ)\delta)$ bits. Overall, the expected codelength is exactly the dequantization lower bound [19] such that

$$L(\mathbf{x}^\circ) \approx \sum_{\bar{\mathbf{u}}} q(\bar{\mathbf{u}}|\mathbf{x}^\circ)\delta[\log(q(\bar{\mathbf{u}}|\mathbf{x}^\circ)\delta) - \log(p(\mathbf{x}^\circ + \bar{\mathbf{u}})\delta)]$$
$$\approx \mathbb{E}_{q(\bar{\mathbf{u}}|\mathbf{x}^\circ)}[\log q(\bar{\mathbf{u}}|\mathbf{x}^\circ) - \log p(\mathbf{x}^\circ + \bar{\mathbf{u}})]. \tag{6}$$

3 Uniform Base Conversion Systems

Algorithm 5 Uniform Base Conversion Systems

ENCODE s with $U(0,R)(R < 2^K)$.
Input: symbol s, state c, bit-stream bs.
Output: new state c and bit-stream bs.
1: $c \leftarrow c \cdot R + s$;
2: **if** $c \geq 2^{M+K}$ **then**
3:   bs.push_back($c \mod 2^K$);   ▷ push K bits to bit-stream.
4:   $c \leftarrow \lfloor\frac{c}{2^K}\rfloor$;
5: **end if**
6: **return** c, bs.

DECODE from $U(0,R)(R < 2^K)$.
Input: state c, bit-stream bs.
Output: decoded s, new state c and bit-stream bs.
1: **if** $c < 2^M \cdot R$ **then**
2:   $c \leftarrow 2^K \cdot c + $bs.pop_back();   ▷ get last K bits from bit-stream and pop them.
3: **end if**
4: $s \leftarrow c \mod R$;
5: $c \leftarrow \lfloor c/R\rfloor$;
6: **return** s, c, bs.

The previous section demonstrates that coding with a uniform distribution is central to our algorithm. Compared to the Gaussian distribution used in LBB [17], a uniform distribution is computationally simpler, yielding improved coding speed. As follows, we introduce our *Uniform Base Conversion Systems* (UBCS), which is easy to implement and the coding bandwidth is much greater than that of rANS [12].

UBCS is implemented based on a number-base conversion. The code state c is represented as an integer. For coding some symbol $s \in \{0, 1, ..., R-1\}$ with a uniform distribution $U(0,R)$, the new state c' is obtained by converting an R-base digit s to an integer such that

$$c' = E(c,s) = c \cdot R + s. \tag{7}$$

For decoding with $U(0,R)$, given state c', the symbol s and state c are recovered by converting the integer to an R-base digit such that

$$s = c' \mod R, \qquad c = D(c',s) = \lfloor\frac{c'}{R}\rfloor. \tag{8}$$

We note, however, that c will become large when more symbols are encoded, and computing Eq. (7-8) with large c will be inefficient. Similar to rANS, we define a "normalized interval" which bounds the state c such that $c \in [2^M, 2^{K+M})$ (K, M are some integers values) after coding each symbol. For

the encoding process, if $c \geq 2^{K+M}$, the lower K bits are written to disk, and the remaining bits are reserved such that $c \leftarrow \lfloor \frac{c}{2^K} \rfloor$. For the decoding process, if $c < 2^M \cdot R$, the stored K bits should be read and appended to the state before decoding. In this way, the decoded state is contained within the interval $[2^M, 2^{K+M})$. The initial state can be set such that $c = 2^M$. We illustrate this idea in Alg. 5.

The correctness of Alg. 5 is illustrated in the following theorem. **P1** demonstrates that the symbols can be correctly decoded with a UBCS coder, with coding performed in a first-in-last-out (FILO) fashion. **P2** shows that the codelength closely approximates the entropy of a uniform distribution, subject to a large M and K. The proof of the theorem is in the Appendix.

Theorem 3. *Consider coding symbols $s_1, ... s_n$ with $s_i \sim U(0, R_i), (i = 1, 2, ..., n, R_i < 2^K)$ using Alg. 5, and then decode $s'_n, s'_{n-1}, ..., s'_1$ sequentially. Suppose (1) the initial state and bit-stream are $c_0 = 2^M, bs_0 = \texttt{empty}$ respectively; (2) After coding s_i, the state is c_i and the bit-stream is bs_i; (3) After decoding s'_{i+1}, the state is c'_i and the bit-stream is bs'_i. We have*

P1: $s'_i = s_{i+1}, c'_i = c_i, bs'_i = bs_i$ *for all $i = 0, ..., n - 1$.*

P2: *Denote by the codelength $l_i = \lceil \log c_i \rceil + \texttt{len}(bs_i)$ where $\texttt{len}$ is the total number of bits in the bit-stream. Then $l_n - l_0 < \frac{1}{1 - 1/(\ln 2 \cdot 2^{M \cdot K})} \sum_{i=1}^{n} \log R_i + 1$.*

In practice, we set $K = 32$ and $M = 4$. Compared to rANS [12], UBCS is of greater efficiency as it necessitates fewer operations. UBCS can achieve greater computational efficiency via instantiating multiple UBCS coders in parallel with multi-threading. Table 1 demonstrates that UBCS achieves coding bandwidths in excess of giga-symbol/s – speed significantly greater than rANS.

Table 1: Coding bandwidth (M symbol/s) of UBCS and rANS coder. We use the implementations in [17] for evaluating rANS.

	# threads	rANS	**UBCS**
Encoder	1	5.1	**380**
	16	21.6	**2075**
Decoder	1	0.8	**66.2**
	16	7.4	**552**

4 Experiments

In this section, we perform a number of experiments to establish the effectiveness of iFlow. We will investigate: (1) how closely the codelength matches the theoretical bound; (2) the efficiency of iFlow as compared with the LBB [17] baseline; (3) the compression performance of iFlow on a series low and high-resolution images.

4.1 Flow Architectures and Datasets

We adopt two types of flow architectures for evaluation: Flow++ [16] and iVPF [40]. Flow++ is a state-of-the-art model using complex non-linear coupling layers and variational dequantizations [19]. iVPF is derived from a volume-preserving flow in which numerically invertible discrete-space operations are introduced. The models are re-implemented or directly taken from the corresponding authors. Unless specified, we use $h = 12, k = 28$ and set large S – around 2^{16}, which we analyse further in the Appendix. To reduce the auxiliary bits in the bits-back coding scheme, we partition the d-dimensional data into b splits and perform MST (in Alg. 1 and 2) for each split sequentially. In this case, the auxiliary bits can be reduced to $1/b$ in MST. We use $b = 4$ in this experiment.

Following the lossless compression community [16, 4, 18, 36, 40], we perform evaluation using toy datasets CIFAR10, ImageNet32 and ImageNet64. Results for alternate methods are obtained via re-implementation or taken directly from the corresponding papers, where available. We further test the generalization capabilities of iFlow in which all toy datasets are compressed with a model trained on ImageNet32. For benchmarking our performance on high-resolution images, we evaluate iFlow using CLIC.mobile, CLIC.pro[3] and DIV2k [1]. For this purpose, we adopt our ImageNet32/64 model for evaluation, and process an image in terms of 32×32 or 64×64 patches, respectively. The experiment is conducted with PyTorch framework with one Tesla P100 GPU.

4.2 Compression Performance

For our experiments, we use the evaluation protocols of codelength and compression bandwidth. The codelength is defined in terms of the average bits per dimension (bpd). For no compression, the bpd

---
[3] https://www.compression.cc/challenge/

Table 2: Coding performance of iFlow, LBB and iVPF on CIFAR10 dataset. We use batch size 64.

flow architecture	compression technique	nll	bpd	auxiliary bits	encoding time (ms) inference	coding
Flow++	LBB [17]	3.116	**3.118**	39.86	16.2	116
	iFlow (Ours)		**3.118**	**34.28**		**21.0**
iVPF	iVPF [40]	3.195	3.201	**6.00**	5.5	11.4
	iFlow (Ours)		**3.196**	7.00		**7.1**

Table 3: Compression performance in bpd on benchmarking datasets. [†] denotes the generation performance in which the models are trained on ImageNet32 and tested on other datasets. [‡] denotes compression of high-resolution datasets with our ImageNet64-trained model.

	ImageNet32	ImageNet64	CIFAR10	CLIC.mobile	CLIC.pro	DIV2K
PNG [5]	6.39	5.71	5.87	3.90	4.00	3.09
FLIF [35]	4.52	4.19	4.19	2.49	2.78	2.91
JPEG-XL [2]	6.39	5.74	5.89	2.36	2.63	2.79
L3C [29]	4.76	4.42	-	2.64	2.94	3.09
RC [30]	-	-	-	2.54	2.93	3.08
Bit-Swap [25]	4.50	-	3.82	-	-	-
IDF [18]	4.18	3.90	3.34	-	-	-
IDF++ [4]	4.12	3.81	3.26	-	-	-
iVPF [40]	4.03	3.75	3.20	-	-	-
LBB [17]	**3.88**	**3.70**	**3.12**	-	-	-
iFlow (Ours)	**3.88**	**3.70**	**3.12**	-	-	-
HiLLoC [36][†]	4.20	3.90	3.56	-	-	-
IDF [18][†]	4.18	3.94	3.60	-	-	-
iVPF[†] [40]	4.03	3.79	3.49	2.47/2.39[‡]	2.63/2.54[‡]	2.77/2.68[‡]
iFlow (Ours)[†]	**3.88**	**3.65**	**3.36**	**2.26/2.26**[‡]	**2.45/2.44**[‡]	**2.60/2.57**[‡]

is assumed to be 8. The compression bandwidth evaluates coding efficiency, which we define in terms of symbols compressed per unit time.

Table 2 demonstrates the compression results on CIFAR10. Note that we only report the encoding time (results on decoding time are similar, and are available in the Appendix). For iVPF, we use settings almost identical to the original paper [40] such that $k = 14$.

Firstly, we observe that, when using both the Flow++ and iVPF architectures, iFlow achieves a bpd very close to theoretically minimal codelength. When using Flow++, iFlow achieves identical performance as that of LBB. For the iVPF architecture, iFlow outperforms the underlying iVPF as it avoids the need to store 16 bits for each data sample.

Secondly, the coding latency highlights the main advantage of iFlow: we achieve encoding $5\times$ faster than that of LBB and over $1.5\times$ that of iVPF. In fact, the use of UBCS only represents 20% of the total coding time for all symbols (4.8ms in Flow++ and 1.6ms in iVPF). In contrast, the rANS coder of LBB commands over 85% of the total coding latency, which is the principal cause of LBB's impracticality. Indeed, Table 1 demonstrates that our UBCS coder achieves a speed-up in excess of $50\times$ that of rANS (which results in a coder latency of 4.8ms in iFlow vs. 99.8ms in LBB).

Lastly, compared with LBB, iFlow necessitates fewer auxiliary bits. In fact, LBB requires crica $2k + \log\sigma$ bits per dimension (for $\delta = 2^{-k}$ and small σ in [17]). Meanwhile, iFlow requires approximately $k + \frac{1}{b}\log S$, and $\frac{1}{b}\log S$ is usually small with large b.

4.3 Comparison with the State-of-the-Art

To further demonstrate the effectiveness of iFlow, we compare the compression performance on benchmarking datasets against a variety of neural compression techniques. These include, L3C [29], Bit-swap [25], HilLoc [36], and flow-based models IDF [18], IDF++ [4], iVPF [40], LBB [17]. We additionally include a number of conventional methods, such as PNG [5], FLIF [35] and JPEG-XL [2].

Experiments on Low Resolution Images. Compression results on our described selection of datasets are available in left three columns of Table 3. Here we observe that iFlow obtains improved compression performance over all approaches with the exception of LBB on low-resolution images, for which we achieve identical results.

Generalization. The last four rows in Table 3 demonstrate the literature-standard test of generalization, in which ImageNet32 trained model are used for testing. From these results, it is clear that iFlow achieves the best generalization performance in this test. It is worth noting that we obtain an improved performance on ImageNet64 when using our ImageNet32-trained model.

Experiments on High Resolution Images. Finally, we test iFlow across a number of high-resolution image datasets. Here images are processed into non-overlapping 32×32 and 64×64 patches for our ImageNet32 and ImageNet64-trained models. The right three columns in Table 3 display the results, which is observed that iFlow outperforms all compression methods across all available benchmarks.

5 Related Work

Entropy coders, such as Arithmetic Coding (AC) [39] and Asymmetric Numerical Systems (ANS) [12], form the basis of lossless compression. However, the binary search protocol required at decode time and their comparatively high number of numerical operations make them both relatively time-consuming. Meanwhile, our proposed UBCS coder requires only two operations per symbol, producing an faster algorithm than AC and ANS.

In order to utilise entropy coders, one must estimate the data distribution. For this purpose, the wider community has employed a variety of density estimators. One of the most popular, autoregressive models [34], estimates the joint density with per-pixel autoregressive factorizations. Whilst commonly achieving state-of-the-art compression ratios, the sequential pixel-by-pixel nature of encoding and/or decoding makes them impractically time-consuming. Alternatively, variational autoencoders (VAEs) [23, 25, 36] maximise a lower bound on the marginal data likelihood (otherwise known as the *ELBO*). With the bits-back coding framework [37], the theoretical codelength is exactly equal to the ELBO. However, in most cases, VAE formulations typically produce inferior compression ratios as there exists a gap between the ELBO and the true data likelihood.

As discussed, flow-based models [16, 24, 11], which admit exact likelihood computation, represent an alternative route for density estimation. IDF [18] and IDF++ [4] proposed the titular *integer discrete flow* to preserve the existence and uniqueness of an invertible mapping between discrete data and latent variables. In a similar vein, iVPF [40] achieved a mapping with volume-preserving flows. Here the remainders of a division operation are stored as auxiliary states to eliminate the numerical error arising from discretizing latent variables. However, all of these models must introduce constraints on the underlying transform, limiting their representational power. LBB [17] was the first flow-based lossless compression approach to admit a broad class of invertible flows based on *continuous* transforms. LBB established this family of flexible bijections by introducing local bits-back coding techniques to encode numerical errors. However, LBB typical requires the coding of many such errors and does so with the ANS scheme, posing obvious challenges to computational efficiency.

6 Conclusions and Discussions

In this paper, we have proposed iFlow, a numerically invertible flow-based model for achieving efficient lossless compression with state-of-the-art compression ratios. To achieve this, we have introduced the Modular Scale Transform and Uniform Base Conversion Systems, which jointly permit an efficient bijection between discrete data and latent variables. Experiments demonstrate that the codelength comes extremely close to the theoretically minimal value, with compression achieved much faster than the next-best high-performance scheme. Moreover, iFlow is able to achieve state-of-the-art compression ratios on real-word image benchmarks.

We additionally consider the potential for extending iFlow. That is, recent advances in normalizing flows have achieved improved generation performance across various data types [27, 7, 22]. It may be possible to extend iFlow to incorporate these advancements. We discuss this possible extension further in the Appendix, and consider its application as future work. We further recognise that compression aproaches, of which iFlow is one, present significant data privacy issues. That is, the generative model used for compression may induce data leakage; therefore, the codec should be treated carefully as to observe data-privacy laws.

References

[1] Eirikur Agustsson and Radu Timofte. Ntire 2017 challenge on single image super-resolution: Dataset and study. In *Proceedings of the IEEE Conference on Computer Vision and Pattern Recognition Workshops*, pages 126–135, 2017.

[2] Jyrki Alakuijala, Ruud van Asseldonk, Sami Boukortt, Martin Bruse, Iulia-Maria Comșa, Moritz Firsching, Thomas Fischbacher, Evgenii Kliuchnikov, Sebastian Gomez, Robert Obryk, et al. Jpeg xl next-generation image compression architecture and coding tools. In *Applications of Digital Image Processing XLII*, volume 11137, page 111370K. International Society for Optics and Photonics, 2019.

[3] Jens Behrmann, Paul Vicol, Kuan-Chieh Wang, Roger Grosse, and Jörn-Henrik Jacobsen. Understanding and mitigating exploding inverses in invertible neural networks. *arXiv preprint arXiv:2006.09347*, 2020.

[4] Rianne van den Berg, Alexey A Gritsenko, Mostafa Dehghani, Casper Kaae Sønderby, and Tim Salimans. Idf++: Analyzing and improving integer discrete flows for lossless compression. *arXiv preprint arXiv:2006.12459*, 2020.

[5] Thomas Boutell and T Lane. Png (portable network graphics) specification version 1.0. *Network Working Group*, pages 1–102, 1997.

[6] Sheng Cao, Chao-Yuan Wu, and Philipp Krähenbühl. Lossless image compression through super-resolution. *arXiv preprint arXiv:2004.02872*, 2020.

[7] Jianfei Chen, Cheng Lu, Biqi Chenli, Jun Zhu, and Tian Tian. Vflow: More expressive generative flows with variational data augmentation. In *International Conference on Machine Learning*, pages 1660–1669. PMLR, 2020.

[8] Rewon Child. Very deep vaes generalize autoregressive models and can outperform them on images. *arXiv preprint arXiv:2011.10650*, 2020.

[9] Yann Collet and Chip Turner. Smaller and faster data compression with zstandard. *Facebook Code [online]*, 2016.

[10] Laurent Dinh, David Krueger, and Yoshua Bengio. Nice: Non-linear independent components estimation. *arXiv preprint arXiv:1410.8516*, 2014.

[11] Laurent Dinh, Jascha Sohl-Dickstein, and Samy Bengio. Density estimation using real nvp. *arXiv preprint arXiv:1605.08803*, 2016.

[12] Jarek Duda. Asymmetric numeral systems: entropy coding combining speed of huffman coding with compression rate of arithmetic coding. *arXiv preprint arXiv:1311.2540*, 2013.

[13] GMDT Forecast. Cisco visual networking index: global mobile data traffic forecast update, 2018–2023. *Update*, 2018:2023, 2010.

[14] Philip Gage. A new algorithm for data compression. *C Users Journal*, 12(2):23–38, 1994.

[15] Irina Higgins, Loic Matthey, Arka Pal, Christopher Burgess, Xavier Glorot, Matthew Botvinick, Shakir Mohamed, and Alexander Lerchner. beta-vae: Learning basic visual concepts with a constrained variational framework. 2016.

[16] Jonathan Ho, Xi Chen, Aravind Srinivas, Yan Duan, and Pieter Abbeel. Flow++: Improving flow-based generative models with variational dequantization and architecture design. *arXiv preprint arXiv:1902.00275*, 2019.

[17] Jonathan Ho, Evan Lohn, and Pieter Abbeel. Compression with flows via local bits-back coding. In *Advances in Neural Information Processing Systems*, pages 3879–3888, 2019.

[18] Emiel Hoogeboom, Jorn Peters, Rianne van den Berg, and Max Welling. Integer discrete flows and lossless compression. In *Advances in Neural Information Processing Systems*, pages 12134–12144, 2019.

[19] Emiel Hoogeboom, Taco S Cohen, and Jakub M Tomczak. Learning discrete distributions by dequantization. *arXiv preprint arXiv:2001.11235*, 2020.

[20] Chin-Wei Huang, David Krueger, Alexandre Lacoste, and Aaron Courville. Neural autoregressive flows. In *Proceedings of the 35th International Conference on Machine Learning*, volume 80, pages 2078–2087. PMLR, 2018.

[21] Heewoo Jun, Rewon Child, Mark Chen, John Schulman, Aditya Ramesh, Alec Radford, and Ilya Sutskever. Distribution augmentation for generative modeling. In *International Conference on Machine Learning*, pages 5006–5019. PMLR, 2020.

[22] Hyeongju Kim, Hyeonseung Lee, Woo Hyun Kang, Joun Yeop Lee, and Nam Soo Kim. Softflow: Probabilistic framework for normalizing flow on manifolds. *Advances in Neural Information Processing Systems*, 33, 2020.

[23] Diederik P Kingma and Max Welling. Auto-encoding variational bayes. *arXiv preprint arXiv:1312.6114*, 2013.

[24] Durk P Kingma and Prafulla Dhariwal. Glow: Generative flow with invertible 1x1 convolutions. In *Advances in neural information processing systems*, pages 10215–10224, 2018.

[25] Friso H Kingma, Pieter Abbeel, and Jonathan Ho. Bit-swap: Recursive bits-back coding for lossless compression with hierarchical latent variables. *arXiv preprint arXiv:1905.06845*, 2019.

[26] Manoj Kumar, Mohammad Babaeizadeh, Dumitru Erhan, Chelsea Finn, Sergey Levine, Laurent Dinh, and Durk Kingma. Videoflow: A flow-based generative model for video. *arXiv preprint arXiv:1903.01434*, 2 (5), 2019.

[27] Phillip Lippe and Efstratios Gavves. Categorical normalizing flows via continuous transformations. *arXiv preprint arXiv:2006.09790*, 2020.

[28] David JC MacKay and David JC Mac Kay. *Information theory, inference and learning algorithms*. Cambridge university press, 2003.

[29] Fabian Mentzer, Eirikur Agustsson, Michael Tschannen, Radu Timofte, and Luc Van Gool. Practical full resolution learned lossless image compression. In *Proceedings of the IEEE Conference on Computer Vision and Pattern Recognition*, pages 10629–10638, 2019.

[30] Fabian Mentzer, Luc Van Gool, and Michael Tschannen. Learning better lossless compression using lossy compression. In *Proceedings of the IEEE/CVF Conference on Computer Vision and Pattern Recognition*, pages 6638–6647, 2020.

[31] Ryan Prenger, Rafael Valle, and Bryan Catanzaro. Waveglow: A flow-based generative network for speech synthesis. In *ICASSP 2019-2019 IEEE International Conference on Acoustics, Speech and Signal Processing (ICASSP)*, pages 3617–3621. IEEE, 2019.

[32] Majid Rabbani. Jpeg2000: Image compression fundamentals, standards and practice. *Journal of Electronic Imaging*, 11(2):286, 2002.

[33] Greg Roelofs and Richard Koman. *PNG: the definitive guide*. O'Reilly & Associates, Inc., 1999.

[34] Tim Salimans, Andrej Karpathy, Xi Chen, and Diederik P Kingma. Pixelcnn++: Improving the pixelcnn with discretized logistic mixture likelihood and other modifications. *arXiv preprint arXiv:1701.05517*, 2017.

[35] Jon Sneyers and Pieter Wuille. Flif: Free lossless image format based on maniac compression. In *2016 IEEE International Conference on Image Processing (ICIP)*, pages 66–70. IEEE, 2016.

[36] James Townsend, Thomas Bird, Julius Kunze, and David Barber. Hilloc: Lossless image compression with hierarchical latent variable models. *arXiv preprint arXiv:1912.09953*, 2019.

[37] James Townsend, Tom Bird, and David Barber. Practical lossless compression with latent variables using bits back coding. *arXiv preprint arXiv:1901.04866*, 2019.

[38] Aaron Van den Oord, Nal Kalchbrenner, Lasse Espeholt, Oriol Vinyals, Alex Graves, et al. Conditional image generation with pixelcnn decoders. In *Advances in neural information processing systems*, pages 4790–4798, 2016.

[39] Ian H Witten, Radford M Neal, and John G Cleary. Arithmetic coding for data compression. *Communications of the ACM*, 30(6):520–540, 1987.

[40] Shifeng Zhang, Chen Zhang, Ning Kang, and Zhenguo Li. ivpf: Numerical invertible volume preserving flow for efficient lossless compression. *arXiv preprint arXiv:2103.16211*, 2021.