"Hey, that's not an ODE": Faster ODE Adjoints with 12 Lines of Code

Abstract

Neural differential equations may be trained by backpropagating gradients via the adjoint method, which is another differential equation typically solved using an adaptive-step-size numerical differential equation solver. A proposed step is accepted if its error, *relative to some norm*, is sufficiently small; else it is rejected, the step is shrunk, and the process is repeated. Here, we demonstrate that the particular structure of the adjoint equations makes the usual choices of norm (such as L^2) unnecessarily stringent. By replacing it with a more appropriate (semi)norm, fewer steps are unnecessarily rejected and the backpropagation is made faster. This requires only minor code modifications. Experiments on a wide range of tasks—including time series, generative modeling, and physical control—demonstrate a median improvement of 40% fewer function evaluations. On some problems we see as much as 62% fewer function evaluations, so that the overall training time is roughly halved.

1 Introduction

We begin by recalling the usual set-up for neural differential equations.

1.1 Neural ordinary differential equations

The general approach of neural ordinary differential equations (E, 2017; Chen et al., 2018) is to use ODEs as a learnable component of a differentiable framework. Typically the goal is to approximate a map $x \mapsto y$ by learning functions $\ell_1(\,\cdot\,, \phi)$, $\ell_2(\,\cdot\,, \psi)$ and $f(\,\cdot\,, \cdot\,, \theta)$, which are composed such that

$$z(\tau) = \ell_1(x, \phi), \qquad z(t) = z(\tau) + \int_\tau^t f(s, z(s), \theta)\, \mathrm{d}s \quad \text{and} \quad y \approx \ell_2(z(T), \psi). \tag{1}$$

The variables ϕ, θ, ψ denote learnable parameters and the ODE is solved over the interval $[\tau, T]$. We include the (often linear) maps $\ell_1(\,\cdot\,, \phi)$, $\ell_2(\,\cdot\,, \psi)$ for generality, as in many contexts they are important for the expressiveness of the model (Dupont et al., 2019; Zhang et al., 2020), though our contributions will be focused around the ODE component and will not depend on these maps.

Here we will consider neural differential equations that may be interpreted as a neural ODE.

1.2 Applications

Neural differential equations have to the best our knowledge three main applications:

1. Time series modeling. Rubanova et al. (2019) interleave Neural ODEs with RNNs to produce ODEs with jumps. Kidger et al. (2020) take $f(t, z, \theta) = g(z, \theta)\frac{\mathrm{d}X}{\mathrm{d}t}(t)$, dependent on some time-varying input X, to produce a neural *controlled* differential equation.

2. Continuous Normalising Flows as in Chen et al. (2018); Grathwohl et al. (2019), in which the overall model acts as coupling or transformation between probability distributions,

3. Modeling or controlling physical environments, for which a differential equation based model may be explicitly desired, see for example Zhong et al. (2020).

1.3 ADJOINT EQUATIONS

The integral in equation (1) may be backpropagated through either by backpropagating through the internal operations of a numerical solver, or by solving the backwards-in-time *adjoint equations* with respect to some (scalar) loss L.

$$a_z(T) = \frac{\mathrm{d}L}{\mathrm{d}z(T)}, \qquad a_z(t) = a_z(T) - \int_T^t a_z(s) \cdot \frac{\partial f}{\partial z}(s, z(s), \theta)\, \mathrm{d}s \qquad \text{and} \qquad \frac{\mathrm{d}L}{\mathrm{d}z(\tau)} = a_z(\tau),$$

$$a_\theta(T) = 0, \qquad a_\theta(t) = a_\theta(T) - \int_T^t a_z(s) \cdot \frac{\partial f}{\partial \theta}(s, z(s), \theta)\, \mathrm{d}s \qquad \text{and} \qquad \frac{\mathrm{d}L}{\mathrm{d}\theta} = a_\theta(\tau),$$

$$a_t(T) = \frac{\mathrm{d}L}{\mathrm{d}T}, \qquad a_t(t) = a_t(T) - \int_T^t a_z(s) \cdot \frac{\partial f}{\partial s}(s, z(s), \theta)\, \mathrm{d}s \qquad \text{and} \qquad \frac{\mathrm{d}L}{\mathrm{d}\tau} = a_t(\tau),$$

$$(2)$$

These equations are typically solved together as a joint system $a(t) = [a_z(t), a_\theta(t), a_t(t)]$. (They are already coupled; the latter two equations depend on a_z.) As additionally their integrands require $z(s)$, and as the results of the forward computation of equation (1) are usually not stored, then the adjoint equations are typically additionally augmented by recovering z by solving backwards-in-time

$$z(t) = z(T) + \int_T^t f(s, z(s), \theta)\mathrm{d}s. \tag{3}$$

1.4 CONTRIBUTIONS

We demonstrate that the particular structure of the adjoint equations implies that numerical equation solvers will typically take too many steps, that are too small, wasting time during backpropagation. Specifically, the accept/reject step of adaptive-step-size solvers is too stringent.

By applying a simple correction to account for this, we demonstrate that the number of steps needed to solve the adjoint equations may be reduced by typically about 40%. We observe improvements on some problems by as much as 62%. Factoring in the forward pass (which is unchanged), the overall training time is roughly halved.

We do not observe any change in model performance, and at least with the `torchdiffeq` package (our chosen differential equation package), this correction may be applied with only 12 lines of code.

2 METHOD

2.1 NUMERICAL SOLVERS

Both the forward pass given by equation (1), and the backward pass given by equations (2) and (3), are solved by invoking a numerical differential equation solver. Our interest here is in adaptive-step-size solvers. Indeed the default choice for solving many equations is the adaptive-step-size Runge–Kutta 5(4) scheme of Dormand–Prince (Dormand & Prince, 1980), for example as implemented by `dopri5` in the `torchdiffeq` package or `ode45` in MATLAB.

A full discussion of the internal operations of these solvers is beyond our scope here; the part of interest to us is the accept/reject scheme. Consider the case of solving the general ODE

$$y(t) = y(\tau) + \int_\tau^t f(s, y(s))\, \mathrm{d}s,$$

with $y(t) \in \mathbb{R}^d$.

Suppose for some fixed t the solver has computed some estimate $\widehat{y}(t) \approx y(t)$, and it now seeks to take a step $\Delta > 0$ to compute $\widehat{y}(t + \Delta) \approx y(t + \Delta)$. A step is made, and some candidate $\widehat{y}_{\mathrm{candidate}}(t + \Delta)$ is generated. The solver additionally produces $y_{\mathrm{err}} \in \mathbb{R}^d$ representing an estimate of the numerical error made in each channel during that step.

Given some prespecified absolute tolerance $ATOL$ (for example 10^{-9}), relative tolerance $RTOL$ (for example 10^{-6}), and (semi)norm $\|\cdot\| : \mathbb{R}^d \to [0, \infty)$ (for example $\|y\| = \sqrt{\frac{1}{d}\sum_{i=1}^d y_i^2}$ the RMS norm), then an estimate of the size of the equation is given by

$$SCALE = ATOL + RTOL \cdot \max(\widehat{y}(t), \widehat{y}_{\text{candidate}}(t+\Delta)) \in \mathbb{R}^d, \qquad (4)$$

where the maximum is taken channel-wise, and the error ratio

$$r = \left\| \frac{y_{\text{err}}}{SCALE} \right\| \in \mathbb{R} \qquad (5)$$

is then computed. If $r \leq 1$ then the error is deemed acceptable, the step is accepted and we take $\widehat{y}(t+\Delta) = \widehat{y}_{\text{candidate}}(t+\Delta)$. If $r > 1$ then the error is deemed too large, the candidate $\widehat{y}_{\text{candidate}}(t+\Delta)$ is rejected, and the procedure is repeated with a smaller Δ.

Note the dependence on the choice of norm $\|\cdot\|$: in particular this determines the relative importance of each channel towards the accept/reject criterion.

2.2 ADJOINT SEMINORMS

Not an ODE   The key observation is that a_θ (and in fact also a_t) does not appear anywhere in the vector fields of equation (2).

This means that (conditioned on knowing z and a_z), the integral corresponding to a_θ is just an integral—not an ODE. As such, it is arguably inappropriate to solve it with an ODE solver, which makes the implicit assumption that small errors now may propagate to create large errors later.

Accept/reject   This is made manifest in the accept/reject step of equation (5). Typical choices of norm $\|\cdot\|$, such as L^2, will usually weight each channel equally. But we have just established that to solve the adjoint equations accurately, it is far more important that z and a_z be accurate than it is that a_θ be accurate.

Seminorms   Thus, when solving the adjoint equations equation (2), we propose to use a $\|\cdot\|$ that scales down the effect in those channels corresponding to a_θ.

In practice, in our experiments, we scale $\|\cdot\|$ all the way down by applying zero weight to the offending channels, so that $\|\cdot\|$ is in fact a seminorm. This means that the integration steps are chosen solely for the computation of a_z and z, and the values of a_θ are computed just by integrating with respect to those steps.

Example   As an explicit example, note that $a_\theta(T) = 0$. When solving the adjoint equation numerically, this means for t close to T that the second term in equation (4) is small. As $ATOL$ is typically also small, then $SCALE$ is additionally small, and the error ratio r in equation (5) is large.

This implies that it becomes easy for the error ratio r to violate $r \leq 1$, and it is easy for the step to be rejected. Now there is nothing intrinsically bad about a step being rejected—we would like to solve the ODE accurately, after all—the problem is that this is a *spurious rejection*, as the rejection occurred to ensure the accuracy of a_θ, which is as already established unnecessary.

In practice, we observe that spurious rejections may occur for any t, not just those near T.

Other channels   In fact, essentially the same argument applies to a_t as well: this does not affect the value of the vector field either. In a continuous normalising flow, the log-probability channel is also only an integral, rather than an ODE, and again the same argument may be applied.

Does this reduce the accuracy of parameter gradients?   One obvious concern is that we are typically ultimately interested in the parameter gradients a_θ, in order to train a model; with respect to this our approach seems counter-intuitive.

However, we verify empirically that models still train without a reduction in performance. We explain this by noting that the z, a_z channels truly are ODEs, so that small errors now do propagate to create larger errors later. Thus these are likely the dominant source of error overall.

2.3 Code

Depending on the software package, the code for making this change can be trivial. For example, using PyTorch (Paszke et al., 2019) and `torchdiffeq` (Chen et al., 2018), the standard set-up

```
import torchdiffeq

func = ...
y0 = ...
t = ...
torchdiffeq.odeint_adjoint(func=func, y0=y0, t=t)
```

is just changed to

```
import torchdiffeq

def rms_norm(tensor):
    return tensor.pow(2).mean().sqrt()

def make_norm(state):
    state_size = state.numel()
    def norm(aug_state):
        y = aug_state[1:1 + state_size]
        adj_y = aug_state[1 + state_size:1 + 2 * state_size]
        return max(rms_norm(y), rms_norm(adj_y))
    return norm

func = ...
y0 = ...
t = ...
torchdiffeq.odeint_adjoint(func=func, y0=y0, t=t,
                           adjoint_options=dict(norm=make_norm(y0)))
```

and that's it. This amounts to the extra 12 lines of code stated in the title—a number that even includes the additional whitespace and visual indents.

To keep the remainder of this discussion software-agnostic, we defer further explanation of this specific code to Appendix A.

3 Experiments

We compare our proposed technique against conventionally-trained neural differential equations, across multiple tasks—time series, generative, and physics-informed. These are each drawn from the main applications of neural differential equations, discussed in Section 1.2. In every case, the differential equation solver used is the Dormand–Prince 5(4) solver "`dopri5`". The default norm is a mixed L^∞/L^2 norm used in `torchdiffeq`; see Appendix A.

In each case see Appendix B for details on hyperparameters, optimisers and so on.

The code for these experiments can be found at [redacted; see supplementary material].

3.1 Neural Controlled Differential Equations

Consider the Neural Controlled Differential Equation (Neural CDE) model of Kidger et al. (2020).

To recap, given some (potentially irregularly sampled) time series $\mathbf{x} = ((t_0, x_0), \ldots, (t_n, x_n))$, with each $t_i \in \mathbb{R}$ the timestamp of the observation $x_i \in \mathbb{R}^v$, let $X : [t_0, t_n] \to \mathbb{R}^{1+v}$ be an interpolation such that $X(t_i) = (t_i, x_i)$. For example X could be a natural cubic spline.

Then take $f(t, z, \theta) = g(z, \theta)\frac{\mathrm{d}X}{\mathrm{d}t}(t)$ in a Neural ODE model, so that changes in $\mathbf{x}$ provoke changes in the vector field, and the model incorporates the incoming information $\mathbf{x}$. This may be thought of as a continuous-time RNN; indeed Kidger et al. (2020) use this to learn functions of (irregular) time series.

Table 1: Results for Neural CDEs. The number of function evaluations (NFE) used in the adjoint equations—accumulated throughout training—are reported. Test set accuracy is additionally reported. Mean $\pm$ standard deviation over five repeats.

	Default norm		Seminorm	
RTOL, ATOL	Accuracy (%)	Bwd. NFE (10^6)	Accuracy (%)	Bwd. NFE (10^6)
$10^{-3}, 10^{-6}$	$92.6_{\pm 0.4}$	$14.36_{\pm 1.09}$	$92.5_{\pm 0.5}$	$\mathbf{8.67_{\pm 1.60}}$
$10^{-4}, 10^{-7}$	$92.8_{\pm 0.4}$	$30.67_{\pm 2.48}$	$92.5_{\pm 0.5}$	$\mathbf{12.75_{\pm 2.00}}$
$10^{-5}, 10^{-8}$	$92.4_{\pm 0.7}$	$77.95_{\pm 4.47}$	$92.9_{\pm 0.4}$	$\mathbf{29.39_{\pm 0.80}}$

Figure 1: Mean $\pm$ standard deviation, for accuracy and the number of function evaluations (NFE) for the backward pass, during training, for Neural CDEs.

We apply a Neural CDE to the Speech Commands dataset (Warden, 2020). This is a dataset of one-second audio recordings of spoken words such as 'left', 'right' and so on. We take 34975 time series corresponding to 10 words, to produce a balanced classification problem. We preprocess the dataset by computing mel-frequency cepstrum coefficients so that each time series is then regularly spaced with length 161 and 20 channels. The data was then normalised to have zero mean and unit variance. We used the `torchcde` package (Kidger, 2020), which wraps `torchdiffeq`.

The initial map ℓ_1 (of equation (1)) is taken to be linear on (t_0, x_0). The terminal map ℓ_2 is taken to be linear on $z(t_n)$.

We investigate how the effect changes for varying tolerances by varying the pair $(RTOL, ATOL)$ over $(10^{-3}, 10^{-6})$, $(10^{-4}, 10^{-7})$, and $(10^{-5}, 10^{-8})$. For each such pair we run five repeated experiments.

See Table 1 for results on accuracy and number of function evaluations. We see that the accuracy of the model is unaffected by our proposed change, whilst the backward pass uses 40%–62% fewer steps, depending on tolerance.

Next, we investigate how accuracy and function evaluations change during training. See Figure 1. We see that accuracy quickly gets close to its maximum value during training, with only incremental improvements for most of the training procedure. In particular, this statement is true of both approaches, and we do not see any discrepancy between them. Additionally, we see that the number of function evaluations is much lower for the seminorm throughout training.

Table 2: Results for Continuous Normalising Flows. The number of function evaluations (NFE) used in the adjoint equations—accumulated throughout training—are reported. Test set bits/dim is additionally reported. Mean $\pm$ standard deviation over three repeats.

		Default norm		Seminorm	
		Test bits/dim	Bwd. NFE (10^6)	Test bits/dim	Bwd. NFE (10^6)
CIFAR-10	($d_h = 64$)	$3.3492_{\pm 0.0059}$	$41.65_{\pm 1.97}$	$3.3388_{\pm 0.0082}$	$\mathbf{38.93_{\pm 1.32}}$
MNIST	($d_h = 32$)	$0.9968_{\pm 0.0020}$	$41.50_{\pm 2.35}$	$0.9942_{\pm 0.0013}$	$\mathbf{37.03_{\pm 0.96}}$
MNIST	($d_h = 64$)	$0.9637_{\pm 0.0008}$	$44.24_{\pm 1.78}$	$0.9601_{\pm 0.0025}$	$\mathbf{37.85_{\pm 0.94}}$
MNIST	($d_h = 128$)	$0.9504_{\pm 0.0036}$	$48.60_{\pm 2.30}$	$0.9501_{\pm 0.0031}$	$\mathbf{41.84_{\pm 1.92}}$

3.2 Continuous Normalising Flows

Continuous Normalising Flows (CNF) (Chen et al., 2018) are a class of generative models that define a probability distribution as the transformation of a simpler distribution by following the vector field parameterized by a Neural ODE. Let $p(z(0))$ be an arbitrary base distribution that we can efficiently sample from, and compute its density. Then let $z(t)$ be the solution of an initial value problem satisfying the ODE $\frac{dz(t)}{dt} = f(t, z(t), \theta)$ with a random initial value sampled from $p(z(0))$. As the sample is transformed through the vector field, the change in probability density can also be tracked (Chen et al., 2018). This is illustrated in the following generative process,

$$z(0) \sim p(z_0), \qquad \frac{dz(t)}{zt} = f(t, z(t), \theta), \qquad \frac{d \log p(z(t))}{dt} = -\text{tr}\left(\frac{\partial f}{\partial z}(t, z(t), \theta) \right).$$

The distribution at an arbitrary time value T can be trained with maximum likelihood to match data samples, resulting in a generative model of data with the distribution $p(z(T))$. Furthermore, Grathwohl et al. (2019) combines this with a stochastic trace estimator (Hutchinson, 1989) to create an efficient and unbiased estimator of the log probability for data samples x.

$$\log p(z(T) = x) = \log p(z(0)) + \mathbb{E}_{v \sim \mathcal{N}(0,1)} \left[\int_T^0 v^T \left(\frac{\partial f}{\partial z}(t, z(t), \theta) \right) v \, dt \right]. \qquad (6)$$

In Table 2 we show the final test performance and the total number of function evaluations (NFEs) used in the adjoint method over 100 epochs. We see substantially fewer NFEs in experiments on both MNIST and CIFAR-10. Next, we investigate changing model size, by varying the complexity of the vector field f, which is a CNN with d_h hidden channels. We find that using the seminorm, the backward NFE does not increase as much as when using the L^2 norm. In particular, we can use roughly same NFEs as the smaller ($d_h = 32$) model to train a larger ($d_h = 128$) model and in doing so achieve a substantial gain in performance ($0.997 \rightarrow 0.950$).

3.3 Hamiltonian dynamics

Finally we consider the problem of learning Hamiltonian dynamics, using the Symplectic ODE-Net model of Zhong et al. (2020). Under Hamiltonian mechanics, the vector field is parameterised as

$$f(t, z, \theta) = \begin{bmatrix} \frac{dH}{dp}(q, p, \theta) \\ g(q, \theta)u - \frac{dH}{dq}(q, p, \theta) \\ 0 \end{bmatrix},$$

where $z = (q, p, u)$ is the state decomposed into (generalised) positions q, momenta p, and control u. H is a Hamiltonian and g is an input term, both parameterised as neural networks. The input g offers a way to control the system, which can be understood via energy shaping.

This parameterisation lends itself to being interpretable. H learns to encode the physics of the system in the form of Hamiltonian mechanics, whilst g learns to encode the way in which inputs affect the system. This can then be used to construct controls u driving the system to a desired state.

Table 3: Results for Symplectic ODE-Net on a fully-actuated double pendulum. The number of function evaluations (NFE) used in the adjoint equations—accumulated throughout training—are reported. Test set loss is additionally reported. Mean $\pm$ standard deviation over five repeats.

Default norm		Seminorm	
Test L^2 loss (10^{-4})	Bwd. NFE (10^4)	Test L^2 loss (10^{-4})	Bwd. NFE (10^4)
$1.247_{\pm 0.520}$	$46.45_{\pm 0.01}$	$2.995_{\pm 2.190}$	$\mathbf{26.55_{\pm 0.01}}$

Figure 2: Frames from controlling the fully-actuated double pendulum to the full-upright position.

Figure 3: Evolution of the state $z = (q, \dot{q}, u)$ whilst controlling the fully-actuated double pendulum from the full-down to the full-upright position. q_1 denotes the angle of the first joint, and q_2 denotes the angle of the second joint.

In this context (unlike the other problems we consider here), z is not a hidden state but instead the output of the model. The evolution of z is matched against the observed state at multiple times $z(t_1)$, $z(t_2)$, ..., and trained with L^2 loss.

We consider the fully-actuated double pendulum ("acrobot") problem. Training data involves small oscillations under constant forcing. See Table 3. We see that the model successfully learns the dynamics, with very small loss in both cases. However, under our proposed change the model is trained using 43% fewer function evaluations on the backward pass.

Next, we verify that the end goal of controlling the system is achievable. See Figures 2 and 3, in which the double pendulum is controlled from the full-down to the full-upright position, using the seminorm-trained model.

Additionally, we investigate the locations of the function evaluations. See Figure 4. We see that the default norm makes consistently more evaluations for every time t. This is interesting as our initial hypothesis was that there would be more spurious rejections for t near the terminal time T, where $a_\theta(t)$ is small, as $a_\theta(T) = 0$. Instead we observe consistent improvements for all t.

Finally, we investigate the locations of the rejected steps. See Figure 5. Note that the Dormand–Prince solver makes 6 function evaluations per step, which is the reason for the difference in scale between Figures 4 and 5.

We see that the seminorm produces almost no rejected steps. This accounts for the tight grouping seen in Figure 4, as for each batch the evaluations times are typically at the same locations. Moreover, we observe an interesting structure to the the location of the rejected steps with the default norm. We suspect this is due to the time-varying physics of the problem.

Figure 4: Location of function evaluations for the adjoint equations, during training for the fully-actuated double pendulum problem. All evaluations over five runs are shown.

Figure 5: Location of rejected steps during training for the fully-actuated double pendulum problem. All steps over five runs are shown. Rejected steps for the seminorm can just barely be seen.

4 RELATED WORK

Several authors have sought techniques for speeding up training of neural differential equations. We expect the majority of these methods to be complementary to our use of seminorms.

Finlay et al. (2020) and Kelly et al. (2020) investigate regularising the higher-order derivatives of the model; the idea is that this encourages simpler trajectories that are easier to integrate. However, the speed improvement gained must be weighed against the extra cost of computing the regularisation term. Thus whilst Finlay et al. (2020) describe speed improvements for CNFs, Kelly et al. (2020) describe slower training (but faster evaluation) as a result of this extra cost.

Quaglino et al. (2020) describe speeding up training via spectral approximation. Unfortunately, this method is rather involved, and to our knowledge does not have a standard implementation.

Massaroli et al. (2020b) discuss hypersolvers, which are hybrids of neural networks and numerical differential equation solvers, trained to efficiently solve a desired Neural ODE. However the Neural ODE changes during training, making these most useful for inference.

Dupont et al. (2019) and Massaroli et al. (2020a) note that adding extra dimensions to the Neural ODE improve expressivity and training. Indeed this has arguably now become a standard part of the model; we include this via the linear ℓ_1 in equation (1).

In the context of Continuous Normalizing Flows, Grathwohl et al. (2019), Chen & Duvenaud (2019), and Onken et al. (2020) have proposed specific architectural choices to reduce training cost.

Chen et al. (2018) mention regularizing the differential equation using weight decay, which we also use throughout our experiments.

Independent of modifications to the model or training procedure, Rackauckas & Nie (2017) and Rackauckas et al. (2019) claim speed-ups simply through an improved implementation.

5 CONCLUSION

We have introduced a method for reducing the number of function evaluations required to train a neural differential equation, by reducing the number of rejected steps during the adjoint (backward) pass. The method is simple to implement, straightforward to integrate into existing codebases, and offers substantial speed-ups across a variety of applications with no observed downsides.

REFERENCES

Ricky T. Q. Chen, Yulia Rubanova, Jesse Bettencourt, and David K Duvenaud. Neural Ordinary Differential Equations. In *Advances in Neural Information Processing Systems 31*, pp. 6571–6583. Curran Associates, Inc., 2018.

Ricky TQ Chen and David K Duvenaud. Neural networks with cheap differential operators. In *Advances in Neural Information Processing Systems*, pp. 9961–9971, 2019.

J. R. Dormand and P. J. Prince. A family of embedded Runge–Kutta formulae. *J. Comp. Appl. Math*, 6:19–26, 1980.

Emilien Dupont, Arnaud Doucet, and Yee Whye Teh. Augmented neural odes. In *Advances in Neural Information Processing Systems 32*, pp. 3140–3150. Curran Associates, Inc., 2019.

Weinan E. A Proposal on Machine Learning via Dynamical Systems. *Commun. Math. Stat.*, 5(1): 1–11, 2017.

Chris Finlay, Jörn-Henrik Jacobsen, Levon Nurbekyan, and Adam M. Oberman. How to train your neural ODE: the world of Jacobian and kinetic regularization. *ICML 2020*, 2020.

Will Grathwohl, Ricky T. Q. Chen, Jesse Bettencourt, Ilya Sutskever, and David Duvenaud. Ffjord: Free-form continuous dynamics for scalable reversible generative models. *International Conference on Learning Representations*, 2019.

Michael F Hutchinson. A stochastic estimator of the trace of the influence matrix for laplacian smoothing splines. *Communications in Statistics-Simulation and Computation*, 18(3):1059–1076, 1989.

Jacob Kelly, Jesse Bettencourt, Matthew James Johnson, and David Duvenaud. Learning Differential Equations that are Easy to Solve. *arXiv:2007.04504*, 2020.

Patrick Kidger. `torchcde`, 2020. `https://github.com/patrick-kidger/torchcde`.

Patrick Kidger, James Morrill, James Foster, and Terry Lyons. Neural Controlled Differential Equations for Irregular Time Series. *arXiv:2005.08926*, 2020.

D Kingma and J Ba. Adam: A method for stochastic optimization. *ICLR*, 2015.

Stefano Massaroli, Michael Poli, Jinkyoo Park, Atsushi Yamashita, and Hajime Asama. Dissecting Neural ODEs. *arXiv:2002.08071*, 2020a.

Stefano Massaroli, Michael Poli, Atsushi Yamashita, Hajime Asama, and Jinkyoo Park. Hypersolvers: Toward Fast Continuous-Depth Models. *arXiv:2007.09601*, 2020b.

Derek Onken, Samy Wu Fung, Xingjian Li, and Lars Ruthotto. Ot-flow: Fast and accurate continuous normalizing flows via optimal transport. *arXiv preprint arXiv:2006.00104*, 2020.

Adam Paszke, Sam Gross, Francisco Massa, Adam Lerer, James Bradbury, Gregory Chanan, Trevor Killeen, Zeming Lin, Natalia Gimelshein, Luca Antiga, Alban Desmaison, Andreas Kopf, Edward Yang, Zachary DeVito, Martin Raison, Alykhan Tejani, Sasank Chilamkurthy, Benoit Steiner, Lu Fang, Junjie Bai, and Soumith Chintala. PyTorch: An Imperative Style, High-Performance Deep Learning Library. In *Advances in Neural Information Processing Systems 32*, pp. 8024–8035. Curran Associates, Inc., 2019.

Alessio Quaglino, Marco Gallieri, Jonathan Masci, and Jan Koutník. Snode: Spectral discretization of neural odes for system identification. In *International Conference on Learning Representations*, 2020.

Chris Rackauckas, Mike Innes, Yingbo Ma, Jesse Bettencourt, Lyndon White, and Vaibhav Dixit. Diffeqflux.jl-a julia library for neural differential equations. *arXiv preprint arXiv:1902.02376*, 2019.

Christopher Rackauckas and Qing Nie. Differentialequations.jl–a performant and feature-rich ecosystem for solving differential equations in julia. *Journal of Open Research Software*, 5(1), 2017.

Yulia Rubanova, Tian Qi Chen, and David K Duvenaud. Latent Ordinary Differential Equations for Irregularly-Sampled Time Series. In *Advances in Neural Information Processing Systems 32*, pp. 5320–5330. Curran Associates, Inc., 2019.

Pete Warden. Speech commands: A dataset for limited-vocabulary speech recognition. *arXiv:1804.03209*, 2020.

Han Zhang, Xi Gao, Jacob Unterman, and Tom Arodz. Approximation capabilities of neural odes and invertible residual networks. *International Conference on Machine Learning*, 2020.

Yaofeng Desmond Zhong, Biswadip Dey, and Amit Chakraborty. Symplectic ode-net: Learning hamiltonian dynamics with control. In *International Conference on Learning Representations*, 2020.