NEURAL SOLVERS FOR FAST AND ACCURATE NUMERICAL OPTIMAL CONTROL

ABSTRACT

Synthesizing optimal controllers for dynamical systems often involves solving optimization problems with hard real–time constraints. These constraints restrict the class of numerical methods that can be applied: computationally expensive but accurate numerical routines often have to be replaced with fast and inaccurate methods, trading inference time for solution accuracy. This paper provides techniques to improve the quality of optimized control policies given a fixed computational budget. We achieve the above via a *hypersolvers* (Poli et al., 2020a) approach, which hybridizes a differential equation solver and a neural network. The performance is evaluated in *direct* and *receding–horizon* optimal control tasks, where the proposed approach shows consistent Pareto improvements in solution accuracy and control performance.

1 INTRODUCTION

Optimal control of complex, high–dimensional systems requires the implementation of computationally expensive numerical methods for *differential equations* (Pytlak, 2006; Rao, 2009). Here, real–time and hardware constraints preclude the use of accurate and expensive methods, forcing instead the application of cheaper and less accurate algorithms. While the paradigm of optimal control has successfully been applied in various domains (Vadali et al., 1999; Lewis et al., 2012; Zhang et al., 2016), improving accuracy while satisfying computational budget constraints is still a great challenge (Ross & Fahroo, 2006; Baotić et al., 2008).

To alleviate such computational limitations, we detail a procedure for *offline* optimization and subsequent *online* application of hypersolvers (Poli et al., 2020a) to optimal control problems. These hybrid solvers aim to achieve the accuracy of higher–order methods by augmenting numerical results of a base solver with a learning component trained to approximate local truncation residuals. When the overhead of a single forward–pass of the learning component is kept sufficiently small, hypersolvers improve the computation–accuracy Pareto front of low–order explicit solvers (Butcher, 1997). However, direct application of hybrid solvers to controlled dynamical system involves learning truncation residuals on the higher–dimensional space of state and control inputs.

To extend the range of applicability of hypersolvers to controlled dynamical systems, we propose two pretraining strategies designed to improve, in the set of admissible control inputs, on the average or worst–case hypersolver solution. With the proposed methodology, we empirically show that Pareto front improvements of hypersolvers hold even for optimal control tasks. In particular, we then carry out performance and generalization evaluations in direct and model predictive control tasks. Here, we confirm Pareto front improvements in terms of solution accuracy and subsequent control performance, leading to higher quality control policies and lower control losses.

2 NUMERICAL OPTIMAL CONTROL

We consider control of general nonlinear systems of the form

$$\dot{x}(t) = f(t, x(t), u_\theta(t))$$
$$x(0) = x_0 \qquad\qquad (1)$$

Figure 1: Overview of the proposed method. [Left] The hypersolver is trained to approximate residuals given a distribution of control inputs and states. [Right] The pre–trained hypersolver model is then used to accelerate and improve the accuracy of numerical solutions used during optimization of control policies, leading to higher–quality controllers.

with state $x \in \mathcal{X} \subset \mathbb{R}^{n_x}$, input $u_\theta \in \mathcal{U} \subset \mathbb{R}^{n_u}$ defined on a compact time domain $\mathcal{T} := [t_0, T]$ where θ is a finite set of free parameters of the controller. Solutions of (1) are denoted with $x(t) = \Phi(x(s), s, t)$ for all $s, t \in \mathcal{T}$.

Given some objective function $J : \mathcal{X} \times \mathcal{U} \to \mathbb{R};\ x_0, u_\theta \mapsto J(x_0, u_\theta(t))$ and a distribution $\rho_0(x_0)$ of initial conditions with support in $\mathcal{X}$, we consider the following nonlinear program, constrained to the system dynamics:

$$
\begin{aligned}
\min_{u_\theta(t)} \quad & \mathbb{E}_{x_0 \sim \rho_0(x_0)} \left[J(x_0, u_\theta(t)) \right] \\
\text{subject to} \quad & \dot{x}(t) = f(t, x(t), u_\theta(t)) \\
& x(0) = x_0 \\
& t \in \mathcal{T}
\end{aligned}
\tag{2}
$$

where the controller parameters θ are optimized. We will henceforth omit the subscript θ and write $u(t) = u_\theta(t)$. Since analytic solutions of (2) exist only for limited classes of systems and objectives, numerical solvers are often applied to iteratively find a solution. For these reasons, problem 2 is often referred to as *numerical optimal control*.

Direct optimal control If the problem (2) is solved *offline* by directly optimizing over complete trajectories, we call it *direct* optimal control. The infinite–dimensional optimal control problem is time–discretized and solved numerically: the obtained control policy is then applied to the real target system without further optimization.

Model predictive control Also known in the literature as receding horizon control, Model Predictive Control (MPC) is a class of flexible control algorithms capable of taking into consideration constraints and nonlinearities (Mayne & Michalska, 1988; Garcia et al., 1989). MPC considers finite time windows which are then shifted forward in a *receding* manner. The control problem is then solved for each window by iteratively forward–propagating trajectories with numerical solvers i.e. *predicting* the set of future trajectories with a candidate controller $u(t)$ and then adjusting it iteratively to optimize the cost function J (further details on the MPC formulation in Appendix B.2). The optimization is reiterated *online* until the end of the control time horizon.

2.1 SOLVER RESIDUALS

Given nominal solutions Φ of (1) we can define the *residual* of a numerical ODE solver as the normalized error accumulated in a single step size of the method, i.e.

$$
R_k = R(t_k, x(t_k), u(t_k)) = \frac{1}{\epsilon^{p+1}} \left[\Phi(x(t_k), t_k, t_{k+1}) - x(t_k) - \epsilon \psi_\epsilon(t_k, x(t_k), u(t_k)) \right]
\tag{3}
$$

where p is the order of the numerical solver corresponding to ψ_ϵ. From the definition of residual in (3), we can define the *local truncation error* $e_k := \left\| \epsilon^{p+1} R_k \right\|_2$ which is the error accumulated in a single step; while the *global truncation error* $\mathcal{E}_k = \left\| x(t_k) - x_k \right\|_2$ represents the error accumulated in the first k steps of the numerical solution. Given a p–th order explicit solver, we have $e_k = \mathcal{O}(\epsilon^{p+1})$ and $\mathcal{E}_k = \mathcal{O}(\epsilon^p)$ (Butcher, 1997).

3 HYPERSOLVERS FOR OPTIMAL CONTROL

We extend the range of applicability of hypersolvers (Poli et al., 2020a) to controlled dynamical systems. In this Section we discuss the proposed hypersolver architectures and pre–training strategies of the proposed hypersolver methodology for numerical optimal control of controlled dynamical systems.

3.1 HYPERSOLVERS

Given a p–order base solver update map ψ_ϵ, the corresponding *hypersolver* is the discrete iteration

$$x_{k+1} = x_k + \underbrace{\epsilon \psi_\epsilon\left(t_k, x_k, u_k\right)}_{\text{base solver step}} + \epsilon^{p+1} \underbrace{g_\omega\left(t_k, x_k, u_k\right)}_{\text{approximator}} \tag{4}$$

where $g_\omega\left(t_k, x_k, u_k\right)$ is some $o(1)$ parametric function with free parameters ω. The core idea is to select g_ω as some function with *universal approximation* properties and fit the higher-order terms of the base solver by explicitly minimizing the residuals over a set of state and control input samples. This procedure leads to a reduction of the overall *local truncation error* e_k, i.e. we can improve the base solver accuracy with the only computational overhead of evaluating the function g_ω. It is also proven that, if g_ω is a δ–approximator of R, i.e. $\forall k \in \mathbb{N}_{\leq K}$

$$\left\| R\left(t_k, x(t_k), u(t_k)\right) - g_\omega\left(t_k, x(t_k), u(t_k)\right) \right\|_2 \leq \delta \tag{5}$$

then $e_k \leq o(\delta \epsilon^{p+1})$, where $\delta > 0$ depends on the hypersolver training results (Poli et al., 2020a, Theorem 1). This result practically guarantees that if g_ω is a good approximator for R, i.e. $\delta \ll 1$, then the overall local truncation error of the *hypersolved* ODE is significantly reduced with guaranteed upper bounds.

3.2 OPTIMAL CONTROL OPTIMIZATION WITH HYPERSOLVERS

Our approach relies on the pre–trained hypersolver model for obtaining solutions to the trajectories of the optimal control problem (2). After the initial training stage, control policies are numerically optimized to minimize the cost function J. Figure 1 shows an overview of the proposed approach consisting in pre–training and system control.

4 HYPERSOLVER PRE–TRAINING AND ARCHITECTURES

We introduce in Section 4.1 loss functions which are used in the proposed pre–training methods of Section 4.2 and Section 4.3. We also check the generalization properties of hypersolvers with different architectures in Section 4.4. In Section 4.5 we introduce *multi–stage hypersolvers* in which an additional first–order learned term is employed for correcting errors in the vector field.

4.1 LOSS FUNCTIONS

Residual fitting Training the hypersolver on a single nominal trajectory $\{x(t_k)\}_k$ results in a *supervised* learning problem where we minimize point–wise the Euclidean distance between the residual (3) and the output of g_ω, resulting in an optimization problem minimizing a loss function ℓ of the form

$$\ell = \frac{1}{K} \sum_{k=0}^{K-1} \left\| R\left(t_k, x(t_k), u(t_k)\right) - g_\omega\left(t_k, x(t_k), u(t_k)\right) \right\|_2 \tag{6}$$

which is also called *residual fitting* since the target of g_w is the residual R.

Figure 2: Mean local residuals of the spring–mass system of (18) as a function of control inputs at different step sizes ϵ. HyperEuler improves on the local residuals compared to the baseline Euler and even compared to higher-order ODE solvers at larger step sizes.

Trajectory fitting The optimization can also be carried out via *trajectory fitting* as following

$$\ell = \frac{1}{K} \sum_{k=0}^{K-1} \|x(t_{k+1}), x_{k+1}\|_2 \tag{7}$$

where $x(t_{k+1})$ corresponds to the exact one–step trajectory and x_{k+1} is its approximation, derived via (4) for standard hypersolvers or via (11) for their multi–stage counterparts. This method can also be used to contain the global truncation error in the $\mathcal{T}$ domain. We will refer to ℓ as a loss function of either residual or trajectory fitting types; we note that these loss functions may also be combined depending on the application.

The goal is to train the hypersolver network to explore the state–control spaces so that it can effectively minimize the truncation error. We propose two methods with different purposes: *stochastic exploration* aiming at minimizing the average truncation error and *active error minimization* whose goal is to reduce the maximum error i.e., due to control inputs yielding high losses.

4.2   STOCHASTIC EXPLORATION

Stochastic exploration aims to minimize the *average* error of the visited state–controller space i.e., to solve the following optimization problem

$$\min_{w} \quad \mathbb{E}_{(x,u) \sim \xi(x,u)} \ell(t, x, u)$$

where $\xi(x, u)$ is a distribution with support in $\mathcal{X} \times \mathcal{U}$ of the state and controller spaces and ℓ is the training loss function. In order to guarantee sufficient exploration of the state–controller space, we use Monte Carlo sampling (Robert & Casella, 2013) from the given distribution. In particular, batches of initial conditions $\{x_0^i\}$, $\{u_0^i\}$ are sampled from ξ and the loss function ℓ is calculated with the given system and step size ϵ. We then perform backpropagation for updating the parameters of the hypersolver using a *stochastic gradient descent* (SGD) algorithm e.g., Adam (Kingma & Ba, 2017) and repeat the procedure for every training epoch. Figure 2 shows pre–training results with stochastic exploration for different step sizes (see Appendix C.2). We notice how higher residual values correspond to higher absolute values of control inputs. Many systems in practice are subject to controls that are constrained in magnitude either due to physical limitations of the actuators or safety restraints of the workspace. This property allows us to design an exploration strategy that focuses on worst-case scenarios i.e. largest control inputs.

4.3   ACTIVE ERROR MINIMIZATION

The goal of active error minimization is to actively reduce the highest losses in terms of the control inputs, i.e., to solve the following optimization problem:

$$\min_{\omega} \quad \max_{u \in \mathcal{U}} \ell(t, x, u) \tag{8}$$

Figure 4: Generalization outside of the training region (red rectangle) in the state space of an inverted pendulum model with different hypersolver activation functions. Architectures containing activation functions with periodic components achieve better extrapolation properties compared to the others.

Similarly to stochastic exploration, we create distribution $\xi(x, u)$ with support in $\mathcal{X} \times \mathcal{U}$ and perform Monte Carlo sampling of batches $\{x_0^i\}, \{u_0^i\}$ from ξ. Then, losses are computed for each state x_0^i with each control input u_0^i in order to obtain a new batch of controllers $\{u_0^{i'}\}$ yielding the maximum loss for each state, i.e. with elements:

$$u_0^{i'} = \arg\max_{u_0} \ell(\epsilon, x_0^i, u_0), \ u_0 \in \{u_0^i\} \quad (9)$$

This operation can be performed efficiently in parallel. After obtaining the new batch $\{u_0^{i'}\}$, the loss is recalculated and SGD updates to hypersolver parameters are performed. Figure 3 shows a comparison of the pre–training techniques (further experimental details in Appendix C.2). The propagated error on trajectories for the hypersolver pre–trained via stochastic exploration is lower on average with random control inputs compared with the one pre–trained with active error minimization. The latter accumulates lower error for controllers yielding high residuals.

Figure 3: *Mean Absolute Error* (MAE) along trajectories with different pre–training techniques on the spring–mass system of (18). [Top] Stochastic exploration performs better on average i.e. $u \in [-100, 100]$. [Bottom] Active error minimization achieves better results in limit situations as in the case of a *bang–bang controller* i.e. $u \in \{-100, 100\}$, in which controllers yielding the highest residuals have been minimized.

4.4 GENERALIZATION PROPERTIES OF DIFFERENT ARCHITECTURES

We have assumed the state and controller spaces to be bounded and that training be performed by sampling for their known distributions. While this is sufficient for optimal control problems given *a priori* known bounds, we also investigate how the system generalizes to unseen states and control input values. In particular, we found that activation functions have an impact on the end result of generalization beyond training boundaries.

We take into consideration two commonly used activation functions, $\texttt{Tanh} : x \to \frac{e^x - e^{-x}}{e^x + e^{-x}}$ and $\texttt{ReLU} : x \to \max(0, x)$, along with network architectures which employ activation functions containing periodic components: $\texttt{SIREN} : x \to \sin(Wx + b)$ (Sitzmann et al., 2020) and $\texttt{Snake} : x \to x + \frac{1}{a}\sin^2(ax)$ (Ziyin et al., 2020). We train hypersolver models with the different activation functions for the inverted pendulum model of (19) with common experimental settings (see Appendix C.3). Figure 4 and Figure 5 show generalization outside the training states, controllers and step sizes. We notice that while $\texttt{Tanh}$ and $\texttt{ReLU}$ perform well on the training set of interest, performance

Figure 5: Generalization with different hypersolver activation functions (HyperEuler models are marked with "HE") on the inverted pendulum. [Left] Generalization for the controller space outside of the training region (red area). The architecture with Snake can to generalize better compared to other hypersolvers. [Right] Generalization for different time steps outside of the training step $\epsilon = 0.1\ [s]$ (red line). HyperEuler is able to improve the baseline Euler solver performance even for unseen ϵ.

degrades rapidly outside of it. On the other one hand, `SIREN` and `Snake` manage to extrapolate the periodicity of the residual distribution even outside of the training region, thus providing further empirical evidence of the universal extrapolation theorem (Ziyin et al., 2020, Theorem 3).

4.5 MULTI–STAGE HYPERSOLVERS

We have so far considered the case in which the vector field (1) fully characterizes the system dynamics. However, if the model does not completely describe the actual system dynamics, first–order errors are introduced. We propose `Multi-Stage Hypersolvers` to correct these errors: an additional term is introduced in order to correct the inaccurate dynamics f. The resulting procedure is a modified version of (4) in which the base solver $\psi_\epsilon\left(t_k, x_k, u_k\right)$ does not iterate over the modeled vector field f but over its corrected version $f^\star$:

$$f^\star\left(t_k, x_k, u_k\right) = \underbrace{f\left(t_k, x_k, u_k\right)}_{\text{Euler step}} + \underbrace{h_w\left(t_k, x_k, u_k\right)}_{\text{first stage}} \tag{10}$$

where h_w is a function with universal approximation properties. While the *first stage* h_w is a first order error approximator, the *second stage* g_ω further reduces errors approximating the p–th order residuals:

$$x_{k+1} = x_k + \epsilon\psi_\epsilon\left(t_k, x_k, u_k, \underbrace{f^\star\left(t_k, x_k, u_k\right)}_{\text{corrected vector field}}\right) + \epsilon^{p+1}\underbrace{g_\omega\left(t_k, x_k, u_k\right)}_{\text{second stage}} \tag{11}$$

We note that $f^\star$ is continuously adjusted due to the optimization of h_w. For this reason, it is not possible to derive the analytical expression of the residuals to train the stages with the residual fitting loss function (6). Instead, both stages can be optimized at the same time via backpropagation calculated on one–step trajectory fitting loss (7) which does not require explicit residuals calculation.

5 EXPERIMENTS

We introduce the experimental results divided for each system into hypersolver pre–training and subsequent optimal control. We use as accurate adaptive step–size solvers the Dormand/Prince method `dopri5` (Dormand & Prince, 1980) and an improved version of it by Tsitouras `tsit5` (Tsitouras, 2011) for training the hypersolvers and to test the control performance at runtime.

5.1 Direct optimal control of a Pendulum

Hypersolver pre–training   We consider the inverted pendulum model with a torsional spring described in (19). We select $\xi(x, u)$ as a uniform distribution with support in $\mathcal{X} \times \mathcal{U}$ where $\mathcal{X} = [-2\pi, 2\pi] \times [-2\pi, 2\pi]$ and $\mathcal{U} = [-5, 5]$ to guarantee sufficient exploration of the state-controller space. Nominal solutions are calculated using tsit5 with absolute and relative tolerances set to 10^{-5}. We train the hypersolver on local residuals via stochastic exploration using the Adam optimizer with learning rate of 3×10^{-4} for 3×10^5 epochs.

Direct optimal control   The goal is to stabilize the inverted pendulum in the vertical position $x^\star = [0, 0]$. We choose $t \in [0, 3]$ and a step size $\epsilon = 0.2\ s$ for the experiment. The control input is assumed continuously time–varying. The neural controller is optimized via SGD with Adam with learning rate of 3×10^{-3} for 1000 epochs. Figure 6 shows nominal controlled trajectories of HyperEuler and other baseline fixed–step size solvers. Trajectories obtained with the controller optimized with HyperEuler reach final positions $q = (1.6 \pm 17.6)\ cm$ while Midpoint and RK4 ones $q = (-0.6 \pm 12.7)\ cm$ and $q = (1.1 \pm 12.8)\ cm$ respectively. On the other hand, the controller optimized with the Euler solver fails to control some trajectories obtaining a final $q = (65.9 \pm 193.9)\ cm$. HyperEuler considerably improved on the Euler baseline while requiring only 1.2% more *Floating Point Operations* (FLOPs) and 49.5% less compared to Midpoint. Further details are available in Appendix C.3.

Figure 6: Direct optimal control of the inverted pendulum. While the controller optimized with the Euler solver fails to control the system for some trajectories, the one obtained with HyperEuler improves the performance while introducing a minimal overhead with results comparable to higher–order solvers.

5.2 Model Predictive Control of a Cart-Pole System

Hypersolver pre–training   We consider an inaccurate version of the cart–pole system of (20) with a wrong parameter for the pole mass, hence we use the multi–stage hypersolver approach to correct the first–order error in the vector field. We select $\xi(x, u)$ as a uniform distribution with support in $\mathcal{X} \times \mathcal{U}$ where $\mathcal{X} = [-2\pi, 2\pi] \times [-2\pi, 2\pi] \times [-2\pi, 2\pi] \times [-2\pi, 2\pi]$ and $\mathcal{U} = [-10, 10]$. Nominal solutions are calculated on the accurate system using tsit5 with absolute and relative tolerances set to 10^{-6}. We train multi–stage HyperEuler for the inaccurate system on nominal trajectories of the accurate system via stochastic exploration using the Adam optimizer with learning rate of 10^{-4} for 10^6 epochs.

Model predictive control   The goal is to stabilize the cart–pole system in the vertical position around the origin, e.g. $x^\star = [0, 0, 0, 0]$. We choose $t \in [0, 5]$ and a step size $\epsilon = 0.01\ s$ for the experiment. The control input is assumed piece-wise constant during MPC sampling times. The receding horizon is chosen as $2\ [s]$. The neural controller is optimized via SGD with Adam with learning rate of 3×10^{-3} for 20 iterations at each sampling time. Figure 7 shows error propagation

Figure 7: [Top] *Symmetric Mean Absolute Percentage Error* (SMAPE) propagation along controlled trajectories of the cartpole system. [Bottom] Model Predictive Control with constrained inputs on the cart–pole model. The Multi–stage HyperEuler solver with knowledge restricted to the inaccurate system manages to obtain a similar control performance compared to controllers with access to the nominal system, while MPC with the adaptive `tsit5` solver on the inaccurate model fails to reach the target position.

and nominal controlled trajectories of multi–stage HyperEuler and other solvers. The adaptive–step `tsit5` on the inaccurate system fails to stabilize the system at the origin position $x = (-31.9 \pm 8.0)\ cm$, while multi–stage HyperEuler manages to stabilize the cart–pole system and improve on final positions $x = (-5.3 \pm 6.8)\ cm$. Further details are available in Appendix C.4.

5.3   MODEL PREDICTIVE CONTROL OF A QUADCOPTER

Hypersolver pre–training   We consider the quadcopter model of (21). We select $\xi(x, u)$ as a uniform distribution with support in $\mathcal{X} \times \mathcal{U}$ where $\mathcal{X}$ is chosen as a distribution of possible visited states and each of the four motors $i \in [0, 3]$ has control inputs $u^i \in [0, 2.17] \times 10^5$ `rpm`. Nominal solutions are calculated on the accurate system using `dopri5` with relative and absolute tolerances set to 10^{-7} and 10^{-9} respectively. We train HyperEuler on local residuals via stochastic exploration using the `Adam` optimizer with learning rate of 10^{-3} for 10^5 epochs.

Model predictive control   The control goal is to reach a final positions $[x, y, z]^\star = [8, 8, 8]\ [m]$. We choose $t \in [0, 3]$ and a step size $\epsilon = 0.02\ s$ for the experiment. The control input is assumed piece–wise constant during MPC sampling times. The receding horizon is chosen as $0.5\ [s]$. The neural controller is optimized via SGD with `Adam` with learning rate of 10^{-2} for 20 iterations at each sampling time. Figure 8 shows local residual distribution and control performance on the quadcopter over 30 experiments starting at random initial conditions which are kept common for the different ODE solvers. HyperEuler requires a single function evaluation per step as for the Euler solver compared to two function evaluations per step for Midpoint and four for RK4. Controlled trajectories optimized with Euler, Midpoint and RK4 collect an error on final positions of $(1.09 \pm 0.37)\ m$, $(0.71 \pm 0.17)\ m$, $(0.70 \pm 0.19)\ m$ respectively while HyperEuler achieves the lowest terminal error value of $(0.66 \pm 0.24)\ m$. Additional experimental details are available in Appendix C.5.

6   RELATED WORK

This work is rooted in the broader literature on surrogate methods for speeding up simulations and solutions of dynamical systems (Grzeszczuk et al., 1998; James & Fatahalian, 2003; Gorissen et al., 2010). Differently from these approaches, we investigate a methodology to enable faster solution during a downstream, online optimization problem involving a potential mismatch compared to data seen during pre–training. We achieve this through the application of the *hypersolver* (Poli et al., 2020a) paradigm.

Figure 8: [Left] Local residual distribution for the quadcopter model for $\epsilon = 0.02 \ [s]$. [Center] Trajectories of controlled quadcopters with MPC whose receding horizon controller is optimized by solving the ODE with different methods. [Right] Final positions error distribution. The proposed approach with HyperEuler achieves lower average error compared to other baseline solvers, while requiring a low overhead compared to higher–order solvers due to a smaller number of dynamics function evaluations.

The synergy between machine learning and optimal control continues a long line of research on introducing neural networks in optimal control (Hunt et al., 1992), applied to modeling (Lin & Cunningham, 1995), identification (Chu et al., 1990) or parametrization of the controller itself (Lin et al., 1991). Existing surrogate methods for systems (Grzeszczuk et al., 1998; James & Fatahalian, 2003) pay a computational cost upfront to accelerate downstream simulation. However, ensuring transfer from offline optimization to the online setting is still an open problem. In our approach, we investigate several strategies for an accurate offline–online transfer of a given hypersolver, depending on desiderata on its performance in terms of average residuals and error propagation on the online application. Beyond hypersolvers, our approach further leverages the latest advances in hardware and machine learning software (Paszke et al., 2019) by solving thousands of ODEs in parallel on *graphics processing units (GPUs)*.

7 CONCLUSION

We presented a novel method for obtaining fast and accurate control policies. Hypersolver models were firstly pre–trained on distributions of states and controllers to approximate higher–order residuals of base fixed–step ODE solvers. The obtained models were then employed to improve the accuracy of trajectory solutions over which control policies were optimized. We verified that our method shows consistent improvements in the accuracy of ODE solutions and thus on the quality of control policies optimized through numerical solutions of the system. We envision the proposed approach to benefit the control field and robotics in both simulated and potentially real–world environments by efficiently solving high–dimensional space–continuous problems.

CODE OF ETHICS

We acknowledge that all the authors of this work have read and commit to adhering to the ICLR Code of Ethics.

REPRODUCIBILITY STATEMENT

We share the codes used in this paper publicly available as supplementary material for reproducibility. The following appendix also supplements the main text by providing additional clarifications. In particular, Appendix A provides further details on the considered hypersolver models. We provide additional information on optimal control policy in Appendix B while in Appendix C we provide details on on the system dynamics, architectures and other experimental details. Additional explanations are also provided in the submitted code.

REFERENCES

Mato Baotić, Francesco Borrelli, Alberto Bemporad, and Manfred Morari. Efficient on-line computation of constrained optimal control. *SIAM Journal on Control and Optimization*, 47(5):2470–2489, 2008.

Greg Brockman, Vicki Cheung, Ludwig Pettersson, Jonas Schneider, John Schulman, Jie Tang, and Wojciech Zaremba. Openai gym, 2016.

John Butcher. Numerical methods for differential equations and applications. *http://www.math.auckland.ac.nz/Research/Reports/view.php?id=370*, 22, 12 1997.

Ricky T. Q. Chen, Yulia Rubanova, Jesse Bettencourt, and David Duvenaud. Neural ordinary differential equations, 2019.

S Reynold Chu, Rahmat Shoureshi, and Manoel Tenorio. Neural networks for system identification. *IEEE Control systems magazine*, 10(3):31–35, 1990.

J. R. Dormand and P. J. Prince. A family of embedded runge-kutta formulae. *Journal of Computational and Applied Mathematics*, 6:19–26, 1980.

Răzvan Florian. Correct equations for the dynamics of the cart-pole system. 08 2005.

C. E. Garcia, D. M. Prett, and M. Morari. Model predictive control: Theory and practice - a survey. *Autom.*, 25:335–348, 1989.

Dirk Gorissen, Ivo Couckuyt, Piet Demeester, Tom Dhaene, and Karel Crombecq. A surrogate modeling and adaptive sampling toolbox for computer based design. *The Journal of Machine Learning Research*, 11:2051–2055, 2010.

Radek Grzeszczuk, Demetri Terzopoulos, and Geoffrey Hinton. Neuroanimator: Fast neural network emulation and control of physics-based models. In *Proceedings of the 25th annual conference on Computer graphics and interactive techniques*, pp. 9–20, 1998.

K.J. Hunt, D. Sbarbaro, R. Żbikowski, and P.J. Gawthrop. Neural networks for control systems—a survey. *Automatica*, 28(6):1083–1112, 1992. ISSN 0005-1098. doi: https://doi.org/10.1016/0005-1098(92)90053-I. URL https://www.sciencedirect.com/science/article/pii/000510989290053I.

Doug L James and Kayvon Fatahalian. Precomputing interactive dynamic deformable scenes. *ACM Transactions on Graphics (TOG)*, 22(3):879–887, 2003.

Diederik P. Kingma and Jimmy Ba. Adam: A method for stochastic optimization, 2017.

Frank L Lewis, Draguna Vrabie, and Vassilis L Syrmos. *Optimal control*. John Wiley & Sons, 2012.

Chin-Teng Lin, C. S. George Lee, et al. Neural-network-based fuzzy logic control and decision system. *IEEE Transactions on computers*, 40(12):1320–1336, 1991.

Yinghua Lin and George A Cunningham. A new approach to fuzzy-neural system modeling. *IEEE Transactions on Fuzzy systems*, 3(2):190–198, 1995.

David Q Mayne and Hannah Michalska. Receding horizon control of nonlinear systems. In *Proceedings of the 27th IEEE Conference on Decision and Control*, pp. 464–465. IEEE, 1988.

Jacopo Panerati, Hehui Zheng, Siqi Zhou, James Xu, Amanda Prorok, and Angela P. Schoellig. Learning to fly - a gym environment with pybullet physics for reinforcement learning of multi-agent quadcopter control. *CoRR*, abs/2103.02142, 2021. URL https://arxiv.org/abs/2103.02142.

Adam Paszke, Sam Gross, Francisco Massa, Adam Lerer, James Bradbury, Gregory Chanan, Trevor Killeen, Zeming Lin, Natalia Gimelshein, Luca Antiga, et al. Pytorch: An imperative style, high-performance deep learning library. *arXiv preprint arXiv:1912.01703*, 2019.

Michael Poli, Stefano Massaroli, Atsushi Yamashita, Hajime Asama, and Jinkyoo Park. Hypersolvers: Toward fast continuous-depth models, 2020a.

Michael Poli, Stefano Massaroli, Atsushi Yamashita, Hajime Asama, and Jinkyoo Park. Torchdyn: A neural differential equations library, 2020b.

Radoslaw Pytlak. *Numerical methods for optimal control problems with state constraints*. Springer, 2006.

Anil V Rao. A survey of numerical methods for optimal control. *Advances in the Astronautical Sciences*, 135(1):497–528, 2009.

Christian Robert and George Casella. *Monte Carlo statistical methods*. Springer Science & Business Media, 2013.

I Michael Ross and Fariba Fahroo. Issues in the real-time computation of optimal control. *Mathematical and computer modelling*, 43(9-10):1172–1188, 2006.

Vincent Sitzmann, Julien N. P. Martel, Alexander W. Bergman, David B. Lindell, and Gordon Wetzstein. Implicit neural representations with periodic activation functions, 2020.

Ch. Tsitouras. Runge–kutta pairs of order 5(4) satisfying only the first column simplifying assumption. *Computers Mathematics with Applications*, 62(2):770–775, 2011. ISSN 0898-1221. doi: https://doi.org/10.1016/j.camwa.2011.06.002. URL https://www.sciencedirect.com/science/article/pii/S0898122111004706.

S Vadali, Hanspeter Schaub, and K Alfriend. Initial conditions and fuel-optimal control for formation flying of satellites. In *Guidance, Navigation, and Control Conference and Exhibit*, pp. 4265, 1999.

Yue J Zhang, Andreas A Malikopoulos, and Christos G Cassandras. Optimal control and coordination of connected and automated vehicles at urban traffic intersections. In *2016 American Control Conference (ACC)*, pp. 6227–6232. IEEE, 2016.

Liu Ziyin, Tilman Hartwig, and Masahito Ueda. Neural networks fail to learn periodic functions and how to fix it, 2020.

A ADDITIONAL HYPERSOLVER MATERIAL

A.1 EXPLICIT HYPEREULER FORMULATION

Our analysis in the experiments takes into consideration the *hypersolved* version of the Euler scheme, namely HyperEuler. Since Euler is a first–order method, it requires the least number of function evaluations (NFE) of the vector field f in (1) and yields a second order local truncation error $e_k := \left\| \epsilon^2 R_k \right\|_2$. This error is larger than other fixed–step solvers and thus has the most room for potential improvements. The base solver scheme ψ of (4) can be written as $\psi_\epsilon(t_k, x_k, u_k) = f(t_k, x_k, u_k)$, which is approximating the next state by adding an evaluation of the vector field multiplied by the step size ϵ. We can write the HyperEuler update explicitly as

$$x_{k+1} = x_k + \epsilon f(t_k, x_k, u_k) + \epsilon^2 g_w(t_k, x_k, u_k) \tag{12}$$

while we write its residual as

$$R(x(t_k), u(t_k))) = \frac{1}{\epsilon^2} \left(\Phi(x(t_k), t_k, t_{k+1}) - x(t_k) - \epsilon f(t_k, x_k, u_k) \right) \tag{13}$$

A.2 EXPLICIT MULTI–STAGE HYPEREULER FORMULATION

Similarly to the previous section, we show the explicit multi–stage HyperEuler formulation as

$$x_{k+1} = x_k + \epsilon \left(\overbrace{\underbrace{f(t_k, x_k, u_k)}_{\text{Euler step}} + \underbrace{h_w(t_k, x_k, u_k)}_{\text{first stage}}}^{\text{corrected vector field}} \right) + \epsilon^2 \underbrace{g_\omega(t_k, x_k, u_k)}_{\text{second stage}} \tag{14}$$

We also note that in this particular case the first stage h_w and g_ω can be jointly trained; in particular, they can be chosen as outputs of a single network which is split in the two stages during the evaluation.

A.3 HYPERSOLVERS FOR TIME–INVARIANT SYSTEMS

A *time–invariant* system with time–invariant controller can be described as following

$$\begin{aligned} \dot{x}(t) &= f(x(t), u(x(t))) \\ x(0) &= x_0 \end{aligned} \tag{15}$$

in which f and u do not explicitly depend on time. The models considered in the experiments satisfy this property.

B CONTROL POLICY DETAILS

B.1 OPTIMAL CONTROL COST FUNCTION

The general form of the *integral cost functional* can be written as follows

$$J(x(t), u(t)) = [x^\top(t_f) - x^\star]\mathbf{P}[x(t_f) - x^\star] + \int_{t_0}^{t_f} \left([x^\top(t)x^\star]\mathbf{Q}[x(t) - x^\star] + u^\top(t)\mathbf{R}u(t) \right) dt \tag{16}$$

where matrix $\mathbf{P}$ is a penalty on deviations from the target $x^\star$ of the last states, $\mathbf{Q}$ penalizes all deviations from the target of intermediate states while $\mathbf{R}$ is a regulator for the control inputs. Evaluation of (16) usually requires numerical solvers such as the proposed hypersolvers of this work. Discretizations of the cost functional are also called *cost function* in the literature.

B.2 MODEL PREDICTIVE CONTROL FORMULATION

The following problem is solved *online* and iteratively until the end of the time span

$$
\begin{aligned}
\min_{u_k} \quad & \sum_{k=0}^{T-1} J\left(x_k, u_k\right) \\
\text{subject to} \quad & \dot{x}(t) = f(t, x(t), u(t)) \\
& x(0) = x_0 \\
& t \in \mathcal{T}
\end{aligned}
\tag{17}
$$

where J is a cost function and $T \in \mathcal{T}$ is the *receding horizon* over which predicted future trajectories are optimized.

C EXPERIMENTAL DETAILS

In this section we include additional modeling and experimental details divided into the different dynamical systems.

C.1 HYPERSOLVER NETWORK ARCHITECTURE

We designed the hypersolver networks g_w as feed–forward neural networks. Table 1 summarizes the parameters used for the considered controlled systems, where activation functions `SoftPlus`: $x \mapsto \log(1 + e^x)$ and `Tanh`: $x \mapsto \frac{e^x - e^{-x}}{e^x + e^{-x}}$.

Table 1: Hyper–parameters for the hypersolver networks in the experiments.

	Spring–Mass	Inverted Pendulum[1]	Cart–Pole[2]	Quadcopter
Input Layer	5	5	9	28
Hidden Layer 1	32	32	32	64
Activation Function 1	Softplus	Softplus	Softplus	Softplus
Hidden Layer 2	32	32	32	64
Activation Function 2	Tanh	Tanh	Softplus	Softplus
Hidden Layer 3	-	-	32	-
Activation Function 3	-	-	Softplus	-
Output Layer	2	2	8	12

We also used the vector field f as an input of the hypersolver, which does not require a further evaluation since it is pre–evaluated at runtime by the base solver ψ. We emphasize that the size of the network should depend on the application: a too–large neural network may require more computations than just increasing the numerical solver's order: Pareto optimality of hypersolvers also depends on their complexity. Keeping their neural network small enough guarantees that evaluating the hypersolvers is cheaper than resorting to more complex numerical routines.

C.2 SPRING-MASS SYSTEM

System Dynamics   The spring-mass system considered is described in the Hamiltonian formulation by

$$
\begin{bmatrix} \dot{q} \\ \dot{p} \end{bmatrix} = \begin{bmatrix} 0 & 1/m \\ -k & 0 \end{bmatrix} \begin{bmatrix} q \\ p \end{bmatrix} + \begin{bmatrix} 0 \\ 1 \end{bmatrix} u
\tag{18}
$$

where $m = 1\ [Kg]$ and $k = 0.5\ [N/m]$.

---

[1]This architecture refers to the optimal control experiment. Details on hypersolver models for the generalization experiment on the inverted pendulum are available in Appendix C.3.

[2]The output layer considers both the first stage h_w and the second stage g_ω of the multi–stage HyperEuler scheme which can be trained as a single neural network whose outputs are split while solving the ODE problem.

Pre-training methods comparison We select $\xi(x, u)$ as a uniform distribution with support in $\mathcal{X} \times \mathcal{U}$ where $\mathcal{X} = [-20, 20] \times [-20, 20]$ while $\mathcal{U} = [-100, 100]$. Nominal solutions are calculated on the accurate system using `dopri5` with relative and absolute tolerances set to 10^{-7} and 10^{-9} respectively. We train two separate HyperEuler models with different training methods on local residual for step size $\epsilon = 0.03\,[s]$: stochastic exploration and active error minimization. The optimizer used is `Adam` with learning rate of 10^{-3} for 10^4 epochs.

Hypersolvers with different step sizes We select $\xi(x, u)$ as a uniform distribution with support in $\mathcal{X} \times \mathcal{U}$ where $\mathcal{X} = [-5, 5] \times [-5, 5]$ while $\mathcal{U} = [-20, 20]$. Nominal solutions are calculated on the accurate system using `dopri5` with relative and absolute tolerances set to 10^{-7} and 10^{-9} respectively. We train separate HyperEuler models with stochastic exploration with different step sizes ϵ. The optimizer used is `Adam` with learning rate of 10^{-3} for 10^4 epochs.

C.3 INVERTED PENDULUM

System Dynamics We model the inverted pendulum with elastic joint with Hamiltonian dynamics via the following:

$$\begin{bmatrix} \dot{q} \\ \dot{p} \end{bmatrix} = \begin{bmatrix} 0 & 1/m \\ -k & -\beta/m \end{bmatrix} \begin{bmatrix} q \\ p \end{bmatrix} - \begin{bmatrix} 0 \\ mgl \sin q \end{bmatrix} + \begin{bmatrix} 0 \\ 1 \end{bmatrix} u \tag{19}$$

where $m = 1\,[Kg]$, $k = 0.5\,[N/\,\mathrm{rad}]$, $r = 1\,[m]$, $\beta = 0.01\,[Ns/\,\mathrm{rad}]$, $g = 9.81\,[m/s^2]$.

Pre–training for the generalization study We perform sampling via stochastic exploration from the uniform distribution $\xi(x, u)$ with support in $\mathcal{X} \times \mathcal{U}$ with $\mathcal{X} = [-2\pi, 2\pi] \times [-2\pi, 2\pi]$ and $\mathcal{U} = [-10, 10]$ for the different architectures. We choose as a common time step $\epsilon = 0.1\,[s]$; the networks are trained for 100000 epochs with the `Adam` optimizer and learning rate of 10^{-3}. The network architectures share the same parameters as the inverted pendulum ones in 1, while the activation functions are substituted by the ones in Figure 4. The SIREN architecture is chosen with 2 hidden layer of size 64.

C.4 CARTPOLE

System Dynamics We consider a continuous version of the cart-pole system in OpenAI Gym (Brockman et al., 2016), appropriately modified for PyTorch and batched training. The dynamic model is described by the four variables $x, \dot{x}, \theta, \dot{\theta}$ (Florian, 2005) and the accelerations update is as following

$$\ddot{\theta} = \frac{g \sin \theta + \cos \theta \left(\frac{-F - m_p l \dot{\theta}^2 \sin \theta}{m_c + m_p} \right)}{l \left(\frac{4}{3} - \frac{m_p \cos^2 \theta}{m_c + m_p} \right)}$$
$$\ddot{x} = \frac{F + m_p l \left(\dot{\theta}^2 \sin \theta - \ddot{\theta} \cos \theta \right)}{m_c + m_p} \tag{20}$$

where $m_c = 1\,[Kg]$, $m_p = 0.1\,[Kg]$, $l = 0.5\,[m]$ and $g = 9.81\,[m/s^2]$.

Additional experimental details For the multi–stage HyperEuler experiment, we increase the mass of the pole m_p to $1\,[Kg]$ for the nominal system while the hypersolver only has knowledge of the mass $m_p = 0.1\,[Kg]$. We also pre-train a single neural network whose first 4 outputs constitute the first stage h_w and the last 4 are g_ω. Figure 9 shows mean local residuals for the learned first stage only and for the complete multi–stage scheme.

C.5 QUADCOPTER

System Dynamics The quadcopter model is a suitably modified version of the explicit dynamics update in (Panerati et al., 2021) for batched training in PyTorch. The following accelerations update

Figure 9: Mean residuals as function of control inputs and states for the cart–pole system. Multi–stage HyperEuler was trained on the inaccurate system. The learned first stage is able to lower local residuals compared to the Euler solver baseline on the nominal system even when eliminating the second stage. Adding back the second stage further diminishes the mean residuals.

describes the dynamic model

$$
\begin{aligned}
\ddot{\mathbf{x}} &= \left(\mathbf{R} \cdot [0, 0, k_F \textstyle\sum_{i=0}^{3} \omega_i^2] - [0, 0, mg] \right) m^{-1} \\
\ddot{\boldsymbol{\psi}} &= \mathbf{J}^{-1} \left(\tau(l, k_F, k_T, [\omega_0^2, \omega_1^2, \omega_2^2, \omega_3^2]) - \dot{\boldsymbol{\psi}} \times \left(\mathbf{J}\dot{\boldsymbol{\psi}} \right) \right)
\end{aligned}
\tag{21}
$$

where $\mathbf{x} = [x, y, z]$ corresponds to the drone positions and $\boldsymbol{\psi} = [\phi, \theta, \psi]$ to its angular positions; $\boldsymbol{R}$ and $\boldsymbol{J}$ are its rotation and inertial matrices respectively, $\tau(\cdot)$ is a function calculating the torques induced by the motor speeds ω_i, while arm length l, mass m, gravity acceleration constant g along with k_F and k_T are scalar variables describing the quadcopter's physical properties.

C.6   HARDWARE AND SOFTWARE

Experiments were carried out on a machine equipped with an AMD RYZEN THREADRIPPER 3960X CPU and two NVIDIA RTX 3090 graphic cards. Software–wise, we used `PyTorch` (Paszke et al., 2019) for deep learning and the `torchdyn` (Poli et al., 2020b) and `torchdiffeq` (Chen et al., 2019) libraries for ODE solvers.