Neural Solvers for Fast and Accurate Numerical Optimal Control

Abstract

Synthesizing optimal controllers for dynamical systems often involves solving optimization problems with hard real–time constraints. These constraints restrict the class of numerical methods that can be applied: computationally expensive but accurate numerical routines often have to be replaced with fast and inaccurate methods, trading inference time for solution accuracy. This paper provides techniques to improve the quality of optimized control policies given a fixed computational budget. We achieve the above via a *hypersolvers* (Poli et al., 2020a) approach, which hybridizes a differential equation solver and a neural network. The performance is evaluated in *direct* and *receding–horizon* optimal control tasks, where the proposed approach shows consistent Pareto improvements in solution accuracy and control performance.

1 Introduction

Optimal control of complex, high–dimensional systems requires the implementation of computationally expensive numerical methods for *differential equations* (Pytlak, 2006; Rao, 2009). Here, real–time and hardware constraints preclude the use of accurate and expensive methods, forcing instead the application of cheaper and less accurate algorithms. While the paradigm of optimal control has successfully been applied in various domains (Vadali et al., 1999; Lewis et al., 2012; Zhang et al., 2016), improving accuracy while satisfying computational budget constraints is still a great challenge (Ross & Fahroo, 2006; Baotić et al., 2008).

To alleviate such computational limitations, we detail a procedure for *offline* optimization and subsequent *online* application of hypersolvers (Poli et al., 2020a) to optimal control problems. These hybrid solvers aim to achieve the accuracy of higher–order methods by augmenting numerical results of a base solver with a learning component trained to approximate local truncation residuals. When the overhead of a single forward–pass of the learning component is kept sufficiently small, hypersolvers improve the computation–accuracy Pareto front of low–order explicit solvers (Butcher, 1997). However, direct application of hybrid solvers to controlled dynamical system involves learning truncation residuals on the higher–dimensional space of state and control inputs.

To extend the range of applicability of hypersolvers to controlled dynamical systems, we propose two pretraining strategies designed to improve, in the set of admissible control inputs, on the average or worst–case hypersolver solution. With the proposed methodology, we empirically show that Pareto front improvements of hypersolvers hold even for optimal control tasks. In particular, we then carry out performance and generalization evaluations in direct and model predictive control tasks. Here, we confirm Pareto front improvements in terms of solution accuracy and subsequent control performance, leading to higher quality control policies and lower control losses.

2 Numerical Optimal Control

We consider control of general nonlinear systems of the form

$$\dot{x}(t) = f(t, x(t), u_\theta(t))$$
$$x(0) = x_0 \tag{1}$$

Figure 1: Overview of the proposed method. [Left] The hypersolver is trained to approximate residuals given a distribution of control inputs and states. [Right] The pre–trained hypersolver model is then used to accelerate and improve the accuracy of numerical solutions used during optimization of control policies, leading to higher–quality controllers.

with state $x \in \mathcal{X} \subset \mathbb{R}^{n_x}$, input $u_\theta \in \mathcal{U} \subset \mathbb{R}^{n_u}$ defined on a compact time domain $\mathcal{T} := [t_0, T]$ where θ is a finite set of free parameters of the controller. Solutions of (1) are denoted with $x(t) = \Phi(x(s), s, t)$ for all $s, t \in \mathcal{T}$.

Given some objective function $J : \mathcal{X} \times \mathcal{U} \to \mathbb{R}$; $x_0, u_\theta \mapsto J(x_0, u_\theta(t))$ and a distribution $\rho_0(x_0)$ of initial conditions with support in $\mathcal{X}$, we consider the following nonlinear program, constrained to the system dynamics:

$$
\begin{aligned}
\min_{u_\theta(t)} \quad & \mathbb{E}_{x_0 \sim \rho_0(x_0)} \left[J(x_0, u_\theta(t)) \right] \\
\text{subject to} \quad & \dot{x}(t) = f(t, x(t), u_\theta(t)) \\
& x(0) = x_0 \\
& t \in \mathcal{T}
\end{aligned}
\tag{2}
$$

where the controller parameters θ are optimized. We will henceforth omit the subscript θ and write $u(t) = u_\theta(t)$. Since analytic solutions of (2) exist only for limited classes of systems and objectives, numerical solvers are often applied to iteratively find a solution. For these reasons, problem 2 is often referred to as *numerical optimal control*.

Direct optimal control If the problem (2) is solved *offline* by directly optimizing over complete trajectories, we call it *direct* optimal control. The infinite–dimensional optimal control problem is time–discretized and solved numerically: the obtained control policy is then applied to the real target system without further optimization.

Model predictive control Also known in the literature as receding horizon control, Model Predictive Control (MPC) is a class of flexible control algorithms capable of taking into consideration constraints and nonlinearities (Mayne & Michalska, 1988; Garcia et al., 1989). MPC considers finite time windows which are then shifted forward in a *receding* manner. The control problem is then solved for each window by iteratively forward–propagating trajectories with numerical solvers i.e. *predicting* the set of future trajectories with a candidate controller $u(t)$ and then adjusting it iteratively to optimize the cost function J (further details on the MPC formulation in Appendix B.2). The optimization is reiterated *online* until the end of the control time horizon.

2.1 SOLVER RESIDUALS

Given nominal solutions Φ of (1) we can define the *residual* of a numerical ODE solver as the normalized error accumulated in a single step size of the method, i.e.

$$
R_k = R(t_k, x(t_k), u(t_k)) = \frac{1}{\epsilon^{p+1}} \left[\Phi(x(t_k), t_k, t_{k+1}) - x(t_k) - \epsilon \psi_\epsilon(t_k, x(t_k), u(t_k)) \right]
\tag{3}
$$

where ϵ is the step size and p is the order of the numerical solver corresponding to ψ_ϵ. From the definition of residual in (3), we can define the *local truncation error* $e_k := \left\| \epsilon^{p+1} R_k \right\|_2$ which is the error accumulated in a single step; while the *global truncation error* $\mathcal{E}_k = \left\| x(t_k) - x_k \right\|_2$ represents the error accumulated in the first k steps of the numerical solution. Given a p–th order explicit solver, we have $e_k = \mathcal{O}(\epsilon^{p+1})$ and $\mathcal{E}_k = \mathcal{O}(\epsilon^p)$ (Butcher, 1997).

3 HYPERSOLVERS FOR OPTIMAL CONTROL

We extend the range of applicability of hypersolvers (Poli et al., 2020a) to controlled dynamical systems. In this Section we discuss the proposed hypersolver architectures and pre–training strategies of the proposed hypersolver methodology for numerical optimal control of controlled dynamical systems.

3.1 HYPERSOLVERS

Given a p–order base solver update map ψ_ϵ, the corresponding *hypersolver* is the discrete iteration

$$x_{k+1} = x_k + \underbrace{\epsilon \psi_\epsilon \left(t_k, x_k, u_k \right)}_{\text{base solver step}} + \epsilon^{p+1} \underbrace{g_\omega \left(t_k, x_k, u_k \right)}_{\text{approximator}} \tag{4}$$

where $g_\omega \left(t_k, x_k, u_k \right)$ is some $o(1)$ parametric function with free parameters ω. The core idea is to select g_ω as some function with *universal approximation* properties and fit the higher-order terms of the base solver by explicitly minimizing the residuals over a set of state and control input samples. This procedure leads to a reduction of the overall *local truncation error* e_k, i.e. we can improve the base solver accuracy with the only computational overhead of evaluating the function g_ω. It is also proven that, if g_ω is a δ–approximator of R, i.e. $\forall k \in \mathbb{N}_{\leq K}$

$$\left\| R \left(t_k, x(t_k), u(t_k) \right) - g_\omega \left(t_k, x(t_k), u(t_k) \right) \right\|_2 \leq \delta \tag{5}$$

then $e_k \leq o(\delta \epsilon^{p+1})$, where $\delta > 0$ depends on the hypersolver training results (Poli et al., 2020a, Theorem 1). This result practically guarantees that if g_ω is a good approximator for R, i.e. $\delta \ll 1$, then the overall local truncation error of the *hypersolved* ODE is significantly reduced with guaranteed upper bounds.

3.2 OPTIMAL CONTROL OPTIMIZATION WITH HYPERSOLVERS

Our approach relies on the pre–trained hypersolver model for obtaining solutions to the trajectories of the optimal control problem (2). After the initial training stage, control policies are numerically optimized to minimize the cost function J (see Appendix B.3 for further details). Figure 1 shows an overview of the proposed approach consisting in pre–training and system control.

4 HYPERSOLVER PRE–TRAINING AND ARCHITECTURES

We introduce in Section 4.1 loss functions which are used in the proposed pre–training methods of Section 4.2 and Section 4.3. We also check the generalization properties of hypersolvers with different architectures in Section 4.4. In Section 4.5 we introduce *multi–stage hypersolvers* in which an additional first–order learned term is employed for correcting errors in the vector field.

4.1 LOSS FUNCTIONS

Residual fitting Training the hypersolver on a single nominal trajectory $\{x(t_k)\}_k$ results in a *supervised* learning problem where we minimize point–wise the Euclidean distance between the residual (3) and the output of g_ω, resulting in an optimization problem minimizing a loss function ℓ of the form

$$\ell \left(t, x, u \right) = \frac{1}{K} \sum_{k=0}^{K-1} \left\| R \left(t_k, x(t_k), u(t_k) \right) - g_\omega \left(t_k, x(t_k), u(t_k) \right) \right\|_2 \tag{6}$$

which is also called *residual fitting* since the target of g_w is the residual R.

Figure 2: Mean local residuals of the spring–mass system of (19) as a function of control inputs at different step sizes ϵ. HyperEuler (see Appendix A.1 for its explicit formulation) improves on the local residuals compared to the baseline Euler and even compared to higher-order ODE solvers at larger step sizes.

Trajectory fitting   The optimization can also be carried out via *trajectory fitting* as following

$$\ell(t, x, u) = \frac{1}{K} \sum_{k=0}^{K-1} \|x(t_{k+1}), x_{k+1}\|_2 \tag{7}$$

where $x(t_{k+1})$ corresponds to the exact one–step trajectory and x_{k+1} is its approximation, derived via (4) for standard hypersolvers or via (12) for their multi–stage counterparts. This method can also be used to contain the global truncation error in the $\mathcal{T}$ domain. We will refer to ℓ as a loss function of either residual or trajectory fitting types; we note that these loss functions may also be combined depending on the application.

The goal is to train the hypersolver network to explore the state–control spaces so that it can effectively minimize the truncation error. We propose two methods with different purposes: *stochastic exploration* aiming at minimizing the average truncation error and *active error minimization* whose goal is to reduce the maximum error i.e., due to control inputs yielding high losses.

4.2   STOCHASTIC EXPLORATION

Stochastic exploration aims to minimize the *average* error of the visited state–controller space i.e., to solve the following optimization problem

$$\min_{w} \quad \mathbb{E}_{(x,u)\sim\xi(x,u)} \ell(t, x, u) \tag{8}$$

where $\xi(x, u)$ is a distribution with support in $\mathcal{X} \times \mathcal{U}$ of the state and controller spaces and ℓ is the training loss function. In order to guarantee sufficient exploration of the state–controller space, we use Monte Carlo sampling (Robert & Casella, 2013) from the given distribution. In particular, batches of initial conditions $\{x_0^i\}$, $\{u_0^i\}$ are sampled from ξ and the loss function ℓ is calculated with the given system and step size ϵ. We then perform backpropagation for updating the parameters of the hypersolver using a *stochastic gradient descent* (SGD) algorithm e.g., Adam (Kingma & Ba, 2017) and repeat the procedure for every training epoch. Figure 2 shows pre–training results with stochastic exploration for different step sizes (see Appendix C.2). We notice how higher residual values correspond to higher absolute values of control inputs. Many systems in practice are subject to controls that are constrained in magnitude either due to physical limitations of the actuators or safety restraints of the workspace. This property allows us to design an exploration strategy that focuses on worst-case scenarios i.e. largest control inputs.

4.3   ACTIVE ERROR MINIMIZATION

The goal of active error minimization is to actively reduce the highest losses in terms of the control inputs, i.e., to solve the following optimization problem:

$$\min_{\omega} \quad \max_{u\in\mathcal{U}} \ell(t, x, u) \tag{9}$$

Figure 4: Generalization outside of the training region (red rectangle) in the state space of an inverted pendulum model with different hypersolver activation functions. Architectures containing activation functions with periodic components achieve better extrapolation properties compared to the others.

Similarly to stochastic exploration, we create distribution $\xi(x, u)$ with support in $\mathcal{X} \times \mathcal{U}$ and perform Monte Carlo sampling of batches $\{x_0^i\}, \{u_0^i\}$ from ξ. Then, losses are computed for each state x_0^i with each control input u_0^i in order to obtain a new batch of controllers $\{u_0^{i'}\}$ yielding the maximum loss for each state, i.e. with elements:

$$u_0^{i'} = \arg\max_{u_0} \ell(\epsilon, x_0^i, u_0), \ u_0 \in \{u_0^i\} \quad (10)$$

This operation can be performed efficiently in parallel. After obtaining the new batch $\{u_0^{i'}\}$, the loss is recalculated and SGD updates to hypersolver parameters are performed. Figure 3 shows a comparison of the pre–training techniques (further experimental details in Appendix C.2). The propagated error on trajectories for the hypersolver pre–trained via stochastic exploration is lower on average with random control inputs compared with the one pre–trained with active error minimization. The latter accumulates lower error for controllers yielding high residuals.

Figure 3: *Mean Absolute Error* (MAE) along trajectories with different pre–training techniques on the spring–mass system of (19). [Top] Stochastic exploration performs better on average i.e. $u \in [-100, 100]$. [Bottom] Active error minimization achieves better results in limit situations as in the case of a *bang–bang controller* i.e. $u \in \{-100, 100\}$, in which controllers yielding the highest residuals have been minimized.

4.4 GENERALIZATION PROPERTIES OF DIFFERENT ARCHITECTURES

We have assumed the state and controller spaces to be bounded and that training be performed by sampling for their known distributions. While this is sufficient for optimal control problems given *a priori* known bounds, we also investigate how the system generalizes to unseen states and control input values. In particular, we found that activation functions have an impact on the end result of generalization beyond training boundaries.

We take into consideration two commonly used activation functions, Tanh : $x \to \frac{e^x - e^{-x}}{e^x + e^{-x}}$ and ReLU : $x \to \max(0, x)$, along with network architectures which employ activation functions containing periodic components: SIREN : $x \to \sin(Wx + b)$ (Sitzmann et al., 2020) and Snake : $x \to x + \frac{1}{a}\sin^2(ax)$ (Ziyin et al., 2020). We train hypersolver models with the different activation functions for the inverted pendulum model of (20) with common experimental settings (see Appendix C.3). Figure 4 and Figure 5 show generalization outside the training states, controllers and step sizes. We notice that while Tanh and ReLU perform well on the training set of interest, performance degrades rapidly outside of it. On the other one hand, SIREN and Snake manage to extrapolate the periodicity of the residual distribution even outside of the training region, thus providing further empirical evidence of the universal extrapolation theorem (Ziyin et al., 2020, Theorem 3).

Figure 5: Generalization with different hypersolver activation functions (HyperEuler models are marked with "HE") on the inverted pendulum. [Left] Generalization for the controller space outside of the training region (red area). The architecture with Snake can to generalize better compared to other hypersolvers. [Right] Generalization for different time steps outside of the training step $\epsilon = 0.1\ s$ (red line). HyperEuler is able to improve the baseline Euler solver performance even for unseen ϵ.

4.5 MULTI–STAGE HYPERSOLVERS

We have so far considered the case in which the vector field (1) fully characterizes the system dynamics. However, if the model does not completely describe the actual system dynamics, first–order errors are introduced. We propose `Multi-Stage Hypersolvers` to correct these errors: an additional term is introduced in order to correct the inaccurate dynamics f. The resulting procedure is a modified version of (4) in which the base solver $\psi_\epsilon\left(t_k, x_k, u_k\right)$ does not iterate over the modeled vector field f but over its corrected version $f^\star$:

$$f^\star\left(t_k, x_k, u_k\right) = \underbrace{f\left(t_k, x_k, u_k\right)}_{\text{Euler step}} + \underbrace{h_w\left(t_k, x_k, u_k\right)}_{\text{first stage}} \tag{11}$$

where h_w is a function with universal approximation properties. While the *first stage* h_w is a first order error approximator, the *second stage* g_ω further reduces errors approximating the p–th order residuals:

$$x_{k+1} = x_k + \epsilon\psi_\epsilon\left(t_k, x_k, u_k, \underbrace{f^\star\left(t_k, x_k, u_k\right)}_{\text{corrected vector field}}\right) + \epsilon^{p+1}\underbrace{g_\omega\left(t_k, x_k, u_k\right)}_{\text{second stage}} \tag{12}$$

We note that $f^\star$ is continuously adjusted due to the optimization of h_w. For this reason, it is not possible to derive the analytical expression of the residuals to train the stages with the residual fitting loss function (6). Instead, both stages can be optimized at the same time via backpropagation calculated on one–step trajectory fitting loss (7) which does not require explicit residuals calculation.

5 EXPERIMENTS

We introduce the experimental results divided for each system into hypersolver pre–training and subsequent optimal control. We use as accurate adaptive step–size solvers the Dormand/Prince method `dopri5` (Dormand & Prince, 1980) and an improved version of it by Tsitouras `tsit5` (Tsitouras, 2011) for training the hypersolvers and to test the control performance at runtime.

5.1 DIRECT OPTIMAL CONTROL OF A PENDULUM

Hypersolver pre–training We consider the inverted pendulum model with a torsional spring described in (20). We select $\xi(x, u)$ as a uniform distribution with support in $\mathcal{X} \times \mathcal{U}$ where

$\mathcal{X} = [-2\pi, 2\pi] \times [-2\pi, 2\pi]$ and $\mathcal{U} = [-5, 5]$ to guarantee sufficient exploration of the state-controller space. Nominal solutions are calculated using `tsit5` with absolute and relative tolerances set to 10^{-5}. We train the hypersolver on local residuals via stochastic exploration using the `Adam` optimizer with learning rate of 3×10^{-4} for 3×10^5 epochs.

Direct optimal control The goal is to stabilize the inverted pendulum in the vertical position $x^\star = [0, 0]$. We choose $t \in [0, 3]$ and a step size $\epsilon = 0.2\ s$ for the experiment. The control input is assumed continuously time–varying. The neural controller is optimized via SGD with `Adam` with learning rate of 3×10^{-3} for 1000 epochs. Figure 6 shows nominal controlled trajectories of HyperEuler and other baseline fixed–step size solvers. Trajectories obtained with the controller optimized with HyperEuler reach final positions $q = (1.6 \pm 17.6) \times 10^{-2}$ while Midpoint and RK4 ones $q = (-0.6 \pm 12.7) \times 10^{-2}$ and $q = (1.1 \pm 12.8) \times 10^{-2}$ respectively. On the other hand, the controller optimized with the Euler solver fails to control some trajectories obtaining a final $q = (6.6 \pm 19.4) \times 10^{-1}$. HyperEuler considerably improved on the Euler baseline while requiring only 1.2% more *Floating Point Operations* (FLOPs) and 49.5% less compared to Midpoint. Further details are available in Appendix C.3.

Figure 6: Direct optimal control of the inverted pendulum in phase space. While the controller optimized with the Euler solver fails to control the system for some trajectories, the one obtained with HyperEuler improves the performance while introducing a minimal overhead with results comparable to higher–order solvers.

5.2 MODEL PREDICTIVE CONTROL OF A CART-POLE SYSTEM

Hypersolver pre–training We consider an inaccurate version of the cart–pole system of (21) with a wrong parameter for the pole mass, hence we use the multi–stage hypersolver approach to correct the first–order error in the vector field. We select $\xi(x, u)$ as a uniform distribution with support in $\mathcal{X} \times \mathcal{U}$ where $\mathcal{X} = [-2\pi, 2\pi] \times [-2\pi, 2\pi] \times [-2\pi, 2\pi] \times [-2\pi, 2\pi]$ and $\mathcal{U} = [-10, 10]$. Nominal solutions are calculated on the accurate system using `tsit5` with absolute and relative tolerances set to 10^{-6}. We train multi–stage HyperEuler (see Appendix A.2 for its explicit formulation) for the inaccurate system on nominal trajectories of the accurate system via stochastic exploration using the `Adam` optimizer with learning rate of 10^{-4} for 10^6 epochs.

Model predictive control The goal is to stabilize the cart–pole system in the vertical position around the origin, e.g. $x^\star = [0, 0, 0, 0]$. We choose $t \in [0, 5]$ and a step size $\epsilon = 0.01\ s$ for the experiment. The control input is assumed piece-wise constant during MPC sampling times. The receding horizon is chosen as $2\ s$. The neural controller is optimized via SGD with `Adam` with learning rate of 3×10^{-3} for 20 iterations at each sampling time. Figure 7 shows nominal controlled trajectories of multi–stage HyperEuler and other solvers. The adaptive–step `tsit5` on the inaccurate system fails to stabilize the system at the origin position $x = (-31.9 \pm 8.0)\ cm$, while multi–stage HyperEuler manages to stabilize the cart–pole system and improve on final positions $x = (-5.3 \pm 6.8)\ cm$. Further details are available in Appendix C.4.

5.3 MODEL PREDICTIVE CONTROL OF A QUADCOPTER

Hypersolver pre–training We consider the quadcopter model of (23). We select $\xi(x, u)$ as a uniform distribution with support in $\mathcal{X} \times \mathcal{U}$ where $\mathcal{X}$ is chosen as a distribution of possible visited states and each of the four motors $i \in [0, 3]$ has control inputs $u^i \in [0, 2.17] \times 10^5$ `rpm`. Nominal solutions are calculated on the accurate system using `dopri5` with relative and absolute tolerances set to 10^{-7} and 10^{-9} respectively. We train HyperEuler on local residuals via stochastic exploration using the `Adam` optimizer with learning rate of 10^{-3} for 10^5 epochs.

Figure 7: Model Predictive Control with constrained inputs on the cart–pole model. The Multi–stage Hyper-Euler solver with knowledge restricted to the inaccurate system manages to obtain a similar control performance compared to controllers with access to the nominal system, while MPC with the adaptive `tsit5` solver on the inaccurate model fails to reach the target position.

Model predictive control The control goal is to reach a final positions $[x, y, z]^\star = [8, 8, 8]\ m$. We choose $t \in [0, 3]$ and a step size $\epsilon = 0.02\ s$ for the experiment. The control input is assumed piece–wise constant during MPC sampling times. The receding horizon is chosen as $0.5\ s$. The neural controller is optimized via SGD with `Adam` with learning rate of 10^{-2} for 20 iterations at each sampling time. Figure 8 shows local residual distribution and control performance on the quadcopter over 30 experiments starting at random initial conditions which are kept common for the different ODE solvers. HyperEuler requires a single function evaluation per step as for the Euler solver compared to two function evaluations per step for Midpoint and four for RK4. Controlled trajectories optimized with Euler, Midpoint and RK4 collect an error on final positions of $(1.09 \pm 0.37)\ m$, $(0.71 \pm 0.17)\ m$, $(0.70 \pm 0.19)\ m$ respectively while HyperEuler achieves the lowest terminal error value of $(0.66 \pm 0.24)\ m$. Additional experimental details are available in Appendix C.5.

Figure 8: [Left] Local residual distribution for the quadcopter model for $\epsilon = 0.02\ s$. [Center] Trajectories of controlled quadcopters with MPC whose receding horizon controller is optimized by solving the ODE with different methods. [Right] Final positions error distribution. The proposed approach with HyperEuler achieves lower average error compared to other baseline solvers while requiring a low overhead compared to higher–order solvers due to a smaller number of dynamics function evaluations.

5.4 BOUNDARY CONTROL OF A TIMOSHENKO BEAM

Hypersolver pre–training We consider the finite element discretization of the Timoshenko beam of (25). We create $\xi(x, u)$ as a distribution with support in $\mathcal{X} \times \mathcal{U}$ which is generated at training time via random walks from known boundary conditions in order to guarantee both physical feasibility and sufficient exploration of the state-controller space (see Appendix C.6 for further details). Nominal solutions are calculated using `tsit5` with absolute and relative tolerances set to 10^{-5}. We train the hypersolver on local residuals via stochastic exploration using the `Adam` optimizer for 10^5 epochs, where we set the learning rate to 10^{-3} for the first 8×10^4 epochs, then decrease it to 10^{-4} for 10^4 epochs and to 10^{-5} for the last 10^4.

Boundary direct optimal control The task is to stabilize the beam in the straight position, i.e. each of its elements i have velocities v_t^i, v_r^i and displacements σ_t^i, σ_r^i equal to 0. We choose $t \in [0, 3]$ and step size $\epsilon = 5\ ms$ for the experiment. The control input is assumed continuously time–varying. The neural controller is optimized via SGD with `Adam` with learning rate of 10^{-3} for 1000 epochs. Figure 9 shows nominal controlled trajectories for HyperEuler and other baseline fixed–step size solvers. Control policies trained with Euler and Midpoint obtain averaged final states of $(-2.8 \pm 4.2) \times 10^{-1}$ and $(-0.04 \pm 4.6) \times 10^{-1}$ thus failing to stabilize the beam, while HyperEuler and RK4 obtain $(-0.6 \pm 4.9) \times 10^{-3}$ and $(-0.5 \pm 3.3) \times 10^{-3}$ respectively. HyperEuler considerably

Figure 9: Displacement variables σ_t and σ_r of the discretized Timoshenko beam as a function of position x of the finite elements and time t. The controller optimized with HyperEuler manages to stabilize the beam while the baseline solvers Euler and Midpoint fail, yet requiring less than a third in terms of runtime compared to RK4.

improves on both the Euler and Midpoint baselines obtaining a very similar performance to RK4, while requiring 72.9% less FLOPs; the mean runtime per training iteration was cut from $8.24\ s$ for RK4 to just $2.53\ s$ for HyperEuler. Further details on this experiment are available in Appendix C.6.

6 RELATED WORK

This work is rooted in the broader literature on surrogate methods for speeding up simulations and solutions of dynamical systems (Grzeszczuk et al., 1998; James & Fatahalian, 2003; Gorissen et al., 2010). Differently from these approaches, we investigate a methodology to enable faster solution during a downstream, online optimization problem involving a potential mismatch compared to data seen during pre–training. We achieve this through the application of the *hypersolver* (Poli et al., 2020a) paradigm. Modeling mismatches between approximate and nominal models is explored in (Saveriano et al., 2017) where residual dynamics are learned efficiently along with the control policy while (Fisac et al., 2018; Taylor et al., 2019) model systems uncertainties in the context of safety–critical control. In contrast to previous work, we model uncertainties with the proposed multi–stage hypersolver approach by closely interacting with the underlying ODE base solvers and their residuals to improve solution accuracy.

The synergy between machine learning and optimal control continues a long line of research on introducing neural networks in optimal control (Hunt et al., 1992), applied to modeling (Lin & Cunningham, 1995), identification (Chu et al., 1990) or parametrization of the controller itself (Lin et al., 1991). Existing surrogate methods for systems (Grzeszczuk et al., 1998; James & Fatahalian, 2003) pay a computational cost upfront to accelerate downstream simulation. However, ensuring transfer from offline optimization to the online setting is still an open problem. In our approach, we investigate several strategies for an accurate offline–online transfer of a given hypersolver, depending on desiderata on its performance in terms of average residuals and error propagation on the online application. Beyond hypersolvers, our approach further leverages the latest advances in hardware and machine learning software (Paszke et al., 2019) by solving thousands of ODEs in parallel on *graphics processing units (GPUs)*.

7 CONCLUSION

We presented a novel method for obtaining fast and accurate control policies. Hypersolver models were firstly pre–trained on distributions of states and controllers to approximate higher–order residuals of base fixed–step ODE solvers. The obtained models were then employed to improve the accuracy of trajectory solutions over which control policies were optimized. We verified that our method shows consistent improvements in the accuracy of ODE solutions and thus on the quality of control policies optimized through numerical solutions of the system. We envision the proposed approach to benefit the control field and robotics in both simulated and potentially real–world environments by efficiently solving high–dimensional space–continuous problems.

CODE OF ETHICS

We acknowledge that all the authors of this work have read and commit to adhering to the ICLR Code of Ethics.

REPRODUCIBILITY STATEMENT

We share the codes used in this paper publicly available as supplementary material for reproducibility. The following appendix also supplements the main text by providing additional clarifications. In particular, Appendix A provides further details on the considered hypersolver models. We provide additional information on optimal control policy in Appendix B while in Appendix C we provide details on on the system dynamics, architectures and other experimental details. Additional explanations are also provided in the submitted code.

REFERENCES

Martin Alnæs, Jan Blechta, Johan Hake, August Johansson, Benjamin Kehlet, Anders Logg, Chris Richardson, Johannes Ring, Marie E Rognes, and Garth N Wells. The fenics project version 1.5. *Archive of Numerical Software*, 3(100), 2015.

Mato Baotić, Francesco Borrelli, Alberto Bemporad, and Manfred Morari. Efficient on-line computation of constrained optimal control. *SIAM Journal on Control and Optimization*, 47(5):2470–2489, 2008.

Greg Brockman, Vicki Cheung, Ludwig Pettersson, Jonas Schneider, John Schulman, Jie Tang, and Wojciech Zaremba. Openai gym, 2016.

John Butcher. Numerical methods for differential equations and applications. *http://www.math.auckland.ac.nz/Research/Reports/view.php?id=370*, 22, 12 1997.

Ricky T. Q. Chen, Yulia Rubanova, Jesse Bettencourt, and David Duvenaud. Neural ordinary differential equations, 2019.

S Reynold Chu, Rahmat Shoureshi, and Manoel Tenorio. Neural networks for system identification. *IEEE Control systems magazine*, 10(3):31–35, 1990.

J. R. Dormand and P. J. Prince. A family of embedded runge-kutta formulae. *Journal of Computational and Applied Mathematics*, 6:19–26, 1980.

Jaime F. Fisac, Anayo K. Akametalu, Melanie N. Zeilinger, Shahab Kaynama, Jeremy Gillula, and Claire J. Tomlin. A general safety framework for learning-based control in uncertain robotic systems, 2018.

Răzvan Florian. Correct equations for the dynamics of the cart-pole system. 08 2005.

C. E. Garcia, D. M. Prett, and M. Morari. Model predictive control: Theory and practice - a survey. *Autom.*, 25:335–348, 1989.

Dirk Gorissen, Ivo Couckuyt, Piet Demeester, Tom Dhaene, and Karel Crombecq. A surrogate modeling and adaptive sampling toolbox for computer based design. *The Journal of Machine Learning Research*, 11:2051–2055, 2010.

Radek Grzeszczuk, Demetri Terzopoulos, and Geoffrey Hinton. Neuroanimator: Fast neural network emulation and control of physics-based models. In *Proceedings of the 25th annual conference on Computer graphics and interactive techniques*, pp. 9–20, 1998.

K.J. Hunt, D. Sbarbaro, R. Żbikowski, and P.J. Gawthrop. Neural networks for control systems—a survey. *Automatica*, 28(6):1083–1112, 1992. ISSN 0005-1098. doi: https://doi.org/10.1016/0005-1098(92)90053-I. URL https://www.sciencedirect.com/science/article/pii/000510989290053I.

Doug L James and Kayvon Fatahalian. Precomputing interactive dynamic deformable scenes. *ACM Transactions on Graphics (TOG)*, 22(3):879–887, 2003.

Diederik P. Kingma and Jimmy Ba. Adam: A method for stochastic optimization, 2017.

Frank L Lewis, Draguna Vrabie, and Vassilis L Syrmos. *Optimal control*. John Wiley & Sons, 2012.

Chin-Teng Lin, C. S. George Lee, et al. Neural-network-based fuzzy logic control and decision system. *IEEE Transactions on computers*, 40(12):1320–1336, 1991.

Yinghua Lin and George A Cunningham. A new approach to fuzzy-neural system modeling. *IEEE Transactions on Fuzzy systems*, 3(2):190–198, 1995.

Alessandro Macchelli and Claudio Melchiorri. Modeling and control of the timoshenko beam. the distributed port hamiltonian approach. *SIAM J. Control. Optim.*, 43:743–767, 2004.

David Q Mayne and Hannah Michalska. Receding horizon control of nonlinear systems. In *Proceedings of the 27th IEEE Conference on Decision and Control*, pp. 464–465. IEEE, 1988.

Jacopo Panerati, Hehui Zheng, Siqi Zhou, James Xu, Amanda Prorok, and Angela P. Schoellig. Learning to fly - a gym environment with pybullet physics for reinforcement learning of multi-agent quadcopter control. *CoRR*, abs/2103.02142, 2021. URL https://arxiv.org/abs/2103.02142.

Adam Paszke, Sam Gross, Francisco Massa, Adam Lerer, James Bradbury, Gregory Chanan, Trevor Killeen, Zeming Lin, Natalia Gimelshein, Luca Antiga, et al. Pytorch: An imperative style, high-performance deep learning library. *arXiv preprint arXiv:1912.01703*, 2019.

Michael Poli, Stefano Massaroli, Atsushi Yamashita, Hajime Asama, and Jinkyoo Park. Hypersolvers: Toward fast continuous-depth models. In H. Larochelle, M. Ranzato, R. Hadsell, M. F. Balcan, and H. Lin (eds.), *Advances in Neural Information Processing Systems*, volume 33, pp. 21105–21117. Curran Associates, Inc., 2020a. URL https://proceedings.neurips.cc/paper/2020/file/f1686b4badcf28d33ed632036c7ab0b8-Paper.pdf.

Michael Poli, Stefano Massaroli, Atsushi Yamashita, Hajime Asama, and Jinkyoo Park. Torchdyn: A neural differential equations library, 2020b.

Radoslaw Pytlak. *Numerical methods for optimal control problems with state constraints*. Springer, 2006.

Anil V Rao. A survey of numerical methods for optimal control. *Advances in the Astronautical Sciences*, 135(1):497–528, 2009.

Christian Robert and George Casella. *Monte Carlo statistical methods*. Springer Science & Business Media, 2013.

I Michael Ross and Fariba Fahroo. Issues in the real-time computation of optimal control. *Mathematical and computer modelling*, 43(9-10):1172–1188, 2006.

Matteo Saveriano, Yuchao Yin, Pietro Falco, and Dongheui Lee. Data-efficient control policy search using residual dynamics learning. In *2017 IEEE/RSJ International Conference on Intelligent Robots and Systems (IROS)*, pp. 4709–4715, 2017. doi: 10.1109/IROS.2017.8206343.

Vincent Sitzmann, Julien N. P. Martel, Alexander W. Bergman, David B. Lindell, and Gordon Wetzstein. Implicit neural representations with periodic activation functions, 2020.

Andrew Taylor, Andrew Singletary, Yisong Yue, and Aaron Ames. Learning for safety-critical control with control barrier functions, 2019.

Ch. Tsitouras. Runge–kutta pairs of order 5(4) satisfying only the first column simplifying assumption. *Computers Mathematics with Applications*, 62(2):770–775, 2011. ISSN 0898-1221. doi: https://doi.org/10.1016/j.camwa.2011.06.002. URL https://www.sciencedirect.com/science/article/pii/S0898122111004706.

S Vadali, Hanspeter Schaub, and K Alfriend. Initial conditions and fuel-optimal control for formation flying of satellites. In *Guidance, Navigation, and Control Conference and Exhibit*, pp. 4265, 1999.

Yue J Zhang, Andreas A Malikopoulos, and Christos G Cassandras. Optimal control and coordination of connected and automated vehicles at urban traffic intersections. In *2016 American Control Conference (ACC)*, pp. 6227–6232. IEEE, 2016.

Liu Ziyin, Tilman Hartwig, and Masahito Ueda. Neural networks fail to learn periodic functions and how to fix it, 2020.

A ADDITIONAL HYPERSOLVER MATERIAL

A.1 EXPLICIT HYPEREULER FORMULATION

Our analysis in the experiments takes into consideration the *hypersolved* version of the Euler scheme, namely HyperEuler. Since Euler is a first–order method, it requires the least number of function evaluations (NFE) of the vector field f in (1) and yields a second order local truncation error $e_k := \left\| \epsilon^2 R_k \right\|_2$. This error is larger than other fixed–step solvers and thus has the most room for potential improvements. The base solver scheme ψ_ϵ of (4) can be written as $\psi_\epsilon(t_k, x_k, u_k) = f(t_k, x_k, u_k)$, which is approximating the next state by adding an evaluation of the vector field multiplied by the step size ϵ. We can write the HyperEuler update explicitly as

$$x_{k+1} = x_k + \epsilon f(t_k, x_k, u_k) + \epsilon^2 g_w(t_k, x_k, u_k) \tag{13}$$

while we write its residual as

$$R(x(t_k), u(t_k))) = \frac{1}{\epsilon^2}(\Phi(x(t_k), t_k, t_{k+1}) - x(t_k) - \epsilon f(t_k, x_k, u_k)) \tag{14}$$

A.2 EXPLICIT MULTI–STAGE HYPEREULER FORMULATION

Similarly to the previous section, we show the explicit multi–stage HyperEuler formulation as

$$x_{k+1} = x_k + \epsilon \left(\overbrace{\underbrace{f(t_k, x_k, u_k)}_{\text{Euler step}} + \underbrace{h_w(t_k, x_k, u_k)}_{\text{first stage}}}^{\text{corrected vector field}} \right) + \epsilon^2 \underbrace{g_\omega(t_k, x_k, u_k)}_{\text{second stage}} \tag{15}$$

We also note that in this particular case the first stage h_w and g_ω can be jointly trained; in particular, they can be chosen as outputs of a single network which is split in the two stages during the evaluation.

A.3 HYPERSOLVERS FOR TIME–INVARIANT SYSTEMS

A *time–invariant* system with time–invariant controller can be described as following

$$\begin{aligned} \dot{x}(t) &= f(x(t), u(x(t))) \\ x(0) &= x_0 \end{aligned} \tag{16}$$

in which f and u do not explicitly depend on time. The models considered in the experiments satisfy this property.

B CONTROL POLICY DETAILS

B.1 OPTIMAL CONTROL COST FUNCTION

The general form of the *integral cost functional* can be written as follows

$$J(x(t), u(t)) = [x^\top(t_f) - x^\star]\mathbf{P}[x(t_f) - x^\star] + \int_{t_0}^{t_f} \left([x^\top(t)x^\star]\mathbf{Q}[x(t) - x^\star] + u^\top(t)\mathbf{R}u(t) \right) dt \tag{17}$$

where matrix $\mathbf{P}$ is a penalty on deviations from the target $x^\star$ of the last states, $\mathbf{Q}$ penalizes all deviations from the target of intermediate states while $\mathbf{R}$ is a regulator for the control inputs. Evaluation of (17) usually requires numerical solvers such as the proposed hypersolvers of this work. Discretizations of the cost functional are also called *cost function* in the literature.

B.2 MODEL PREDICTIVE CONTROL FORMULATION

The following problem is solved *online* and iteratively until the end of the time span

$$
\begin{aligned}
\min_{u_k} \quad & \sum_{k=0}^{T-1} J\left(x_k, u_k\right) \\
\text{subject to} \quad & \dot{x}(t) = f(t, x(t), u(t)) \\
& x(0) = x_0 \\
& t \in \mathcal{T}
\end{aligned}
\tag{18}
$$

where J is a cost function and $T \in \mathcal{T}$ is the *receding horizon* over which predicted future trajectories are optimized.

B.3 NEURAL OPTIMAL CONTROL

We parametrize the control policy of problem (2) as $u_\theta : t, x \mapsto u_\theta(t, x)$ where θ is a finite set of free parameters. Specifically, we consider the case of *neural* optimal control in which controller u_θ is a multi–layer perceptron. The optimal control task is to minimize the cost function J described in (17) and we do so by optimizing the parameters θ via SGD; in particular, we use the `Adam` (Kingma & Ba, 2017) optimizer for all the experiments.

C EXPERIMENTAL DETAILS

In this section we include additional modeling and experimental details divided into the different dynamical systems.

C.1 HYPERSOLVER NETWORK ARCHITECTURE

We design the hypersolver networks g_w as feed–forward neural networks. Table 1 summarizes the parameters used for the considered controlled systems, where *Activation* denotes the activation functions, i.e. `SoftPlus`: $x \mapsto \log(1 + e^x)$, `Tanh`: $x \mapsto \frac{e^x - e^{-x}}{e^x + e^{-x}}$ and `Snake` : $x \to x + \frac{1}{a}\sin^2(ax)$ (Ziyin et al., 2020).

Table 1: Hyper–parameters for the hypersolver networks in the experiments.

	Spring–Mass	Inverted Pendulum [1]	Cart–Pole[2]	Quadcopter	Timoshenko Beam
Input Layer	5	5	9	28	322
Hidden Layer 1	32	32	32	64	256
Activation 1	Softplus	Softplus	Softplus	Softplus	Snake
Hidden Layer 2	32	32	32	64	256
Activation 2	Tanh	Tanh	Softplus	Softplus	Snake
Hidden Layer 3	-	-	32	-	-
Activation 3	-	-	Softplus	-	-
Output Layer	2	2	8	12	160

We also used the vector field f as an input of the hypersolver, which does not require a further evaluation since it is pre–evaluated at runtime by the base solver ψ. We emphasize that the size of the network should depend on the application: a too–large neural network may require more computations than just increasing the numerical solver's order: Pareto optimality of hypersolvers also depends on their complexity. Keeping their neural network small enough guarantees that evaluating the hypersolvers is cheaper than resorting to more complex numerical routines.

---

[1]This architecture refers to the optimal control experiment. Details on hypersolver models for the generalization experiment on the inverted pendulum are available in Appendix C.3.

[2]The output layer considers both the first stage h_w and the second stage g_ω of the multi–stage HyperEuler scheme which can be trained as a single neural network whose outputs are split while solving the ODE problem.

C.2 SPRING-MASS SYSTEM

System Dynamics   The spring-mass system considered is described in the Hamiltonian formulation by

$$\begin{bmatrix} \dot{q} \\ \dot{p} \end{bmatrix} = \begin{bmatrix} 0 & 1/m \\ -k & 0 \end{bmatrix} \begin{bmatrix} q \\ p \end{bmatrix} + \begin{bmatrix} 0 \\ 1 \end{bmatrix} u \tag{19}$$

where $m = 1 \, [Kg]$ and $k = 0.5 \, [N/m]$.

Pre-training methods comparison   We select $\xi(x, u)$ as a uniform distribution with support in $\mathcal{X} \times \mathcal{U}$ where $\mathcal{X} = [-20, 20] \times [-20, 20]$ while $\mathcal{U} = [-100, 100]$. Nominal solutions are calculated on the accurate system using `dopri5` with relative and absolute tolerances set to 10^{-7} and 10^{-9} respectively. We train two separate HyperEuler models with different training methods on local residual for step size $\epsilon = 0.03 \, s$: stochastic exploration and active error minimization. The optimizer used is `Adam` with learning rate of 10^{-3} for 10^4 epochs.

Hypersolvers with different step sizes   We select $\xi(x, u)$ as a uniform distribution with support in $\mathcal{X} \times \mathcal{U}$ where $\mathcal{X} = [-5, 5] \times [-5, 5]$ while $\mathcal{U} = [-20, 20]$. Nominal solutions are calculated on the accurate system using `dopri5` with relative and absolute tolerances set to 10^{-7} and 10^{-9} respectively. We train separate HyperEuler models with stochastic exploration with different step sizes ϵ. The optimizer used is `Adam` with learning rate of 10^{-3} for 10^4 epochs.

C.3 INVERTED PENDULUM

System Dynamics   We model the inverted pendulum with elastic joint with Hamiltonian dynamics via the following:

$$\begin{bmatrix} \dot{q} \\ \dot{p} \end{bmatrix} = \begin{bmatrix} 0 & 1/m \\ -k & -\beta/m \end{bmatrix} \begin{bmatrix} q \\ p \end{bmatrix} - \begin{bmatrix} 0 \\ mgl \sin q \end{bmatrix} + \begin{bmatrix} 0 \\ 1 \end{bmatrix} u \tag{20}$$

where $m = 1 \, [Kg]$, $k = 0.5 \, [N/\mathrm{rad}]$, $r = 1 \, [m]$, $\beta = 0.01 \, [Ns/\mathrm{rad}]$, $g = 9.81 \, [m/s^2]$.

Pre–training for the generalization study   We perform sampling via stochastic exploration from the uniform distribution $\xi(x, u)$ with support in $\mathcal{X} \times \mathcal{U}$ with $\mathcal{X} = [-2\pi, 2\pi] \times [-2\pi, 2\pi]$ and $\mathcal{U} = [-10, 10]$ for the different architectures. We choose as a common time step $\epsilon = 0.1 \, s$; the networks are trained for 100000 epochs with the `Adam` optimizer and learning rate of 10^{-3}. The network architectures share the same parameters as the inverted pendulum ones in 1, while the activation functions are substituted by the ones in Figure 4. The SIREN architecture is chosen with 2 hidden layers of size 64.

Additional visualization   Figure 10 provides an additional visualization of the inverted pendulum controlled trajectories from Figure 6 with positions q and momenta p over time.

Figure 10: Controlled trajectories of the inverted pendulum with controllers optimized via different solvers.

C.4 CART-POLE

System Dynamics   We consider a continuous version of the cart-pole system in OpenAI Gym (Brockman et al., 2016), appropriately modified for PyTorch and batched training. The dynamic

model is described by the four variables $x, \dot{x}, \theta, \dot{\theta}$ (Florian, 2005) and the accelerations update is as following

$$
\ddot{\theta} = \frac{g \sin\theta + \cos\theta \left(\frac{-F - m_p l \dot{\theta}^2 \sin\theta}{m_c + m_p} \right)}{l \left(\frac{4}{3} - \frac{m_p \cos^2\theta}{m_c + m_p} \right)}
$$
$$
\ddot{x} = \frac{F + m_p l \left(\dot{\theta}^2 \sin\theta - \ddot{\theta} \cos\theta \right)}{m_c + m_p}
$$

(21)

where $m_c = 1 \, [Kg]$, $m_p = 0.1 \, [Kg]$, $l = 0.5 \, [m]$ and $g = 9.81 \, [m/s^2]$.

Figure 11: Mean residuals as function of control inputs and states for the cart–pole system. Multi–stage HyperEuler was trained on the inaccurate system. The learned first stage is able to lower local residuals compared to the Euler solver baseline on the nominal system even when eliminating the second stage. Adding back the second stage further diminishes the mean residuals.

Additional experimental details For the multi–stage HyperEuler experiment, we increase the mass of the pole m_p to $1 \, [Kg]$ for the nominal system while the hypersolver only has knowledge of the mass $m_p = 0.1 \, [Kg]$. We also pre-train a single neural network whose first 4 outputs constitute the first stage h_w and the last 4 are g_ω. Figure 11 shows mean local residuals for the learned first stage only and for the complete multi–stage scheme.

Figure 12: *Symmetric Mean Absolute Percentage Error* (SMAPE) propagation along controlled trajectories of the cartpole system. Multi–stage HyperEuler with knowledge limited to the inaccurate model manages to outperform the Euler solver iterating on the accurate dynamics.

Comparison with other baselines We additionally compare the multi–stage hypersolver approach on the inaccurate model with other baseline methods, namely the adaptive `tsit5` with knowledge of the inaccurate model only, the Euler method iterating on learned system residual dynamics, and the Euler and Midpoint solvers with the accurate (nominal) model. For the residual dynamics approach, the goal is to learn the corrected vector field $f^\star$. We parametrize the residual dynamics as a neural network with the same number of layers, hidden size and same activation functions as multi–stage HyperEuler described in Table 1. We optimize the network via SGD with the `Adam` optimizer until convergence by approximating the vector field directly by drawing batches from the same distribution $\xi(x, u)$ on which multi–stage HyperEuler is trained, i.e. by minimizing the loss function

$$\ell(t, x, u) = \frac{1}{K} \sum_{k=0}^{K-1} \|\psi_\epsilon \left(t_k, x_k, u_k, f^\star(t_k, x_k, u_k)\right), \psi_\epsilon \left(t_k, x_k, u_k, f^{nom}(t_k, x_k, u_k)\right)\|_2 \quad (22)$$

in which the corrected vector field $f^\star(\cdot) = f(\cdot) + r_w(\cdot)$ with f being the inaccurate dynamics and r_w the residual dynamics network we optimize, f^{nom} is the nominal dynamics and ψ_ϵ is the solution corresponding to the base solver tsit5 set with absolute and relative tolerances of 10^{-5}. Figure 12 shows error propagation over time of the different approaches. While propagating the corrected vector field learning the residual dynamics and multi–stage HyperEuler both improve on the baseline tsit5 solver iterating on the inaccurate model, we note that multi–stage HyperEuler manages to also outperform the Euler solver on the accurate dynamics.

C.5 QUADCOPTER

System Dynamics   The quadcopter model is a suitably modified version of the explicit dynamics update in (Panerati et al., 2021) for batched training in PyTorch. The following accelerations update describes the dynamic model

$$\ddot{\mathbf{x}} = \left(\mathbf{R} \cdot [0, 0, k_F \textstyle\sum_{i=0}^{3} \omega_i^2] - [0, 0, mg]\right) m^{-1}$$
$$\ddot{\boldsymbol{\psi}} = \mathbf{J}^{-1} \left(\tau(l, k_F, k_T, [\omega_0^2, \omega_1^2, \omega_2^2, \omega_3^2]) - \dot{\boldsymbol{\psi}} \times \left(\mathbf{J}\dot{\boldsymbol{\psi}}\right)\right)$$

$$(23)$$

mwhere $\mathbf{x} = [x, y, z]$ corresponds to the drone positions and $\boldsymbol{\psi} = [\phi, \theta, \psi]$ to its angular positions; $\boldsymbol{R}$ and $\boldsymbol{J}$ are its rotation and inertial matrices respectively, $\tau(\cdot)$ is a function calculating the torques induced by the motor speeds ω_i, while arm length l, mass m, gravity acceleration constant g along with k_F and k_T are scalar variables describing the quadcopter's physical properties.

C.6 TIMOSHENKO BEAM

System Dynamics   We consider as a system from the theory of continuum dynamics the Timoshenko beam with no dissipation described in (Macchelli & Melchiorri, 2004). The system can be described in the coenergy formulation by the following *partial differential equation* (PDE)

$$\begin{bmatrix} \rho A & 0 & 0 & 0 \\ 0 & I_\rho & 0 & 0 \\ 0 & 0 & C_b & 0 \\ 0 & 0 & 0 & C_s \end{bmatrix} \frac{\partial}{\partial t} \begin{pmatrix} v_t \\ v_r \\ \sigma_r \\ \sigma_t \end{pmatrix} = \begin{bmatrix} 0 & 0 & 0 & \partial_x \\ 0 & 0 & \partial_x & 1 \\ 0 & \partial_x & 0 & 0 \\ \partial_x & -1 & 0 & 0 \end{bmatrix} \begin{pmatrix} v_t \\ v_r \\ \sigma_r \\ \sigma_t \end{pmatrix} \quad (24)$$

where ρ is the mass density, A is the cross section area, I_ρ is the rotational inertia, C_s and C_b are the shear and bending compliance; the discretized state variables v_t, v_r represent the translational and rotational velocities respectively while σ_t, σ_r denote the translational and rotational displacements.

In order to discretize the problem, we implement a software routine based on the fenics (Alnæs et al., 2015) open–source software suite to obtain the finite–elements discretization of the Timoshenko PDE of (24) given the number of elements, physical parameters of the model and initial conditions of the beam. We choose a 40 elements discretization of the PDE for a total of 160 dimensions of the discretized state $z = [v_t, v_r, \sigma_t, \sigma_r]^\top$ and we initialize the beam at time $t = 0$ as $z(x, 0) = [\sin(\pi x), \sin(3\pi x), 0, 0]$. The system can thus be reduced to the following controlled linear system

$$\begin{bmatrix} \dot{v}_t \\ \dot{v}_r \\ \dot{\sigma}_t \\ \dot{\sigma}_r \end{bmatrix} = \begin{bmatrix} \times & \times & \times & -M_{\rho A}^{-1} D_1^\top \\ \times & \times & -M_{I_\rho}^{-1} D_2^\top & -M_{I_\rho}^{-1} D_0^\top \\ \times & M_{C_b}^{-1} D_2 & \times & \times \\ M_{C_s}^{-1} D_1 & M_{C_s}^{-1} D_0 & \times & \times \end{bmatrix} \begin{bmatrix} v_t \\ v_r \\ \sigma_t \\ \sigma_r \end{bmatrix} + \begin{bmatrix} \times & M_{\rho A}^{-1} B_F \\ M_{I_\rho}^{-1} B_T & \times \\ \times & \times \\ \times & \times \end{bmatrix} \begin{bmatrix} u_\partial^1 \\ u_\partial^2 \end{bmatrix}$$

$$(25)$$

where the mass matrices $M_{\rho A}$, M_{I_ρ}, M_{C_b}, M_{C_s}, matrices D_0, D_1, D_2, vectors B_F, B_T are computed through the fenics routine and boundary controllers u_∂^1 and u_∂^2 are the control torque and the control force applied at the free end of the beam.

Stochastic exploration strategy via random walks We pre–train the hypersolver model via stochastic exploration of the state-controller space $\mathcal{X} \times \mathcal{U}$. We restrict the boundary control input values $u = [u^1_\partial, u^2_\partial]^\top$ in $[-1, 1] \times [-1, 1]$. As for the state space, naively generating a probability distribution with box boundaries on each of the 160 dimensions of $\mathcal{X}$ would require an inefficient search over this high-dimensional space: in fact, not every combination is physically feasible due to the Timoshenko beam's structure. We solve this problem by propagating batched trajectories with RK4 from the initial boundary condition $z(x, 0) = [\sin(\pi x), \sin(3\pi x), 0, 0]$ with random control actions sampled from a uniform distribution with support in $[-1, 1] \times [-1, 1]$ applied for a time $t_1 \sim U[0.002, 1]$ s. We save the states $\{z(x, t_1)^i\}$ and forward propagate from these states again by sampling from the controller and time distributions. We repeat the process K times and obtain a sequence $[\{z(x, t_1)^i\}, \ldots, \{z(x, t_K)^i\}]$ of batched initial conditions characterized by physical feasibility. Finally, we train the hypersolver with stochastic exploration by sampling from the generated distribution $\xi(x, u)$ on local one–step residuals as described in Section 5.4. This initial state generation strategy is repeated every 100 epochs for guaranteeing an extensive exploration of all possible boundary conditions. Figure 13 shows the error propagation over controlled trajectories: the trained HyperEuler achieves the lowest error among baseline fixed–step solvers.

Figure 13: *Mean Absolute Error* (MAE) propagation on velocities v_t, v_r and displacements σ_t, σ_r for the finite elements of the discretized Timoshenko beam along controlled trajectories. While solutions from Euler and Midpoint quickly diverge due to the system's stiffness, HyperEuler manages not only to contain errors but even outperform the fourth-order RK4 whilst requiring a fraction of the number of vector field evaluations.

Additional details on the results We report additional details regarding the runtime of the experiments on the Timoshenko Beam. As for the training time, training the hypersolver for 10^5 epochs takes around 80 minutes, where the time for each training epoch slightly varies depending on the length of the sequence of initial condition batches obtained via random walks. As for the averaged runtime per training epoch during the control policy optimization, HyperEuler takes (2.53 ± 0.09) s per training iteration, Euler (2.01 ± 0.04) s, Midpoint (4.02 ± 0.08) s and RK4 (8.24 ± 0.14) s. Experiments were run on the CPU of the machine described in Section C.7.

C.7 HARDWARE AND SOFTWARE

Experiments were carried out on a machine equipped with an AMD RYZEN THREADRIPPER 3960X CPU with 48 threads and two NVIDIA RTX 3090 graphic cards. Software–wise, we used PyTorch (Paszke et al., 2019) for deep learning and the torchdyn (Poli et al., 2020b) and torchdiffeq (Chen et al., 2019) libraries for ODE solvers.