Versatile Multi-stage Graph Neural Network for Circuit Representation

Abstract

Due to the rapid growth in the scale of circuits and the desire for knowledge transfer from old designs to new ones, deep learning technologies have been widely exploited in Electronic Design Automation (EDA) to assist circuit design. In chip design cycles, we might encounter heterogeneous and diverse information sources, including the two most informative ones: the netlist and the design layout. However, handling each information source independently is sub-optimal. In this paper, we propose a novel way to integrate the multiple information sources under a unified heterogeneous graph named **Circuit Graph**, where topological and geometrical information is well integrated. Then, we propose **Circuit GNN** to fully utilize the features of vertices, edges as well as heterogeneous information during the message passing process. It is the first attempt to design a versatile circuit representation that is compatible across multiple EDA tasks and stages. Experiments on the two most representative prediction tasks in EDA show that our solution reaches state-of-the-art performance in both logic synthesis and global placement chip design stages. Besides, it achieves a 10x speed-up on congestion prediction compared to the state-of-the-art model.

1 Introduction

Integrated circuits (ICs) are extensively used in modern electronic products like computers, smartphones, and cars. Electronic Design Automation (EDA) includes a set of tools for circuit design in different development stages especially **logic synthesis** stage and **placement** stage (Fig.1). As the scale and complexity of circuits continuously grow, the design efficiency and precision of EDA tools have become an essential problem, which attracts researchers to adopt deep learning techniques to assist the circuit design process [1]. Remarkable progress has been made in predicting circuits' quality and practicability in the earlier stage of the chip design to speed up optimization and reduce design cost [2, 3]. For example, predicting congestion for circuits in physical design stage can help detect their flaws and avoid producing defective chips, and chip design production cycle time can be further saved if such prediction could be done in logic synthesis stage.

Because of the sophisticated process of circuit design, we will encounter diverse information sources from various design stages, among which logic synthesis and placement & routing determine the quality, e.g. time delay, of circuit and consume the majority of design pipeline time, as shown in Fig.2. In the logic synthesis stage, a circuit design is represented as a **Netlist** composed of *cells* and *nets*, where *cells* refer to the electronic units and *nets* refer to the connectivity (i.e. hyper-edges) among the *cells*. After the placement & routing stage, we will obtain the circuit layout with the position

Submitted to 36th Conference on Neural Information Processing Systems (NeurIPS 2022). Do not distribute.

Figure 1: Chip Design Flow

(a) Circuit Design

(b) Circuit Layout

(c) Homo. Graph
(*cell*-oriented)

(d) Homo. Graph
(*net*-oriented)

Figure 2: Convert circuit design to a grid feature matrix and a homogeneous graph.

of each electronic unit provided after they have been fully placed on the circuit board. Besides, the downstream tasks might require learning representations on both *cells* and *nets*, tailoring for specific downstream tasks. Thus, how to better organize and fuse the diverse and heterogeneous information provided in the context of circuit representation is an important research question.

Although the information underlying the circuit design varies according to the input stages, we can divide it into **geometrical information** and **topological information**. The netlists only contain the topological information (e.g. *cell* type and logical relationship between *cells* and *nets*), while some geometrical information (e.g. positions of standard *cells*) is available after placement stage. According to which information they focus on, we categorize the existing prediction methods in circuit designs into **topological methods** and **geometrical methods**. The topological methods convert circuit designs into homogeneous graphs (Fig.2(c)(d)) and solve the problems with Graph Neural Network (GNN) [4, 5, 6], while most recent geometrical models convert the circuit designs into grid feature matrices (see Def.1 and Fig.2(b)) and adopt Computer Vision (CV) technologies to predict their properties [7, 8, 9].

However, the topological methods only consider the topological information in netlists and cannot effectively perceive geometrical structure introduced after the placement stage, so their performance on circuits after placement is greatly stifled. Besides, the geometrical models heavily rely on geometrical information and neglect the topology underlying the netlists, so they cannot handle circuits in stages earlier than global placement where geometry is not available. In a word, they can only work well on circuits either in logic synthesis stage or placement stage but are not compatible with both. Moreover, most of the existing prediction methods design modules with prior knowledge to serve certain applications, so they are not flexible enough to handle diverse EDA tasks. Therefore, it is necessary to: (1) design a data structure to represent the circuit, which is adaptive to circuits in both logic synthesis and placement stages; (2) propose an efficient and effective circuit representation model which is compatible with two stages and various downstream tasks.

In this paper, we first convert the circuit design to **Circuit Graph** (see (Fig.3)), a heterogeneous graph which preserves most of the topological and geometrical information, with a linear time consumption to the scale of the design (see Appendix.B.2 for proof). A circuit graph contains two types of vertices i.e. *cells* and *nets*. We use *pins* which connect *cells* and *nets* to represent the topology, which are also

noted as *topo-edges*. When handling circuits in placement stage, we additionally link the *cells* which are geometrically close (named *geom-edges*) to represent the geometry.

Then, we design **Circuit GNN** to process Circuit Graphs with optimal efficiency and produce representations for *cells* and *nets* to handle diverse tasks on circuits in both logic synthesis stage and placement stage. To collect and enrich the topological and geometrical information, we conduct message-passing [10] on *topo-edges* and *geom-edges* individually and later fuse the messages to update *cells* and *nets* representations. Multiple layers of such "message-passing & fusion" inference further exploit the deep relationships between topology and geometry and facilitate Circuit GNN to output nutritious representations. Circuit GNN is also compatible with Circuit Graphs converted from circuits in logic synthesis stage because *geom-edges*'s absence will not disable the message-passing over *topo-edges* and the topological information can still be collected.

In summary, our contributions are:

- To address the challenge posed by the diverse and heterogeneous information source in the context of circuit representation, we propose a novel way to integrate the information named **Circuit Graph**, a heterogeneous graph where topological and geometrical information are integrated jointly, which is able to handle diverse circuit tasks on cell, nets level and on different stages. To our best knowledge, this is the first unified circuit representation approach that can be easily compatible across EDA tasks and stages.

- We propose a novel message-passing paradigm **Circuit GNN** that tailors the aforementioned graph dataset structure. We design message-passing on both topological and geometrical edges distinctively and then fuse the messages to update *cells* and *nets* representations. The efficiency and effectiveness of our design are demonstrated both methodologically and experimentally.

- Experiment results validate the superior performance and efficiency of Circuit Graph across multi-stages/tasks. For circuit congestion prediction task at logic synthesis stage, it improves the average grid-level accuracy by 16.7% against SOTA. At placement stage, it achieves 5.6% accuracy gain with 10x speed-up in congestion prediction task and 16.9% error gain in net wirelength prediction task.

2 Related Work

2.1 Topological Methods

The topological methods in EDA focus on the logic relationships between the *cells* and *nets* and usually reconstruct the circuit designs into graphs with vertices and edges. CongestionNet[5] and solutions in [6] link the *cell*-pairs connected via *nets* (Fig.2(c)) and adopt popular GNNs (e.g. GAT[11]) to generate *cell* representations for congestion prediction. To handle net length identification and net delay prediction, Net[2][12] links the *nets* connecting to one *cell* (Fig.2(d)) and designs a customized GNN to obtain *net* representations. All these methods perceive the circuit designs as homogeneous graphs and neglect the underlying heterogeneity, e.g. the interaction between *cells* and *nets* like signal input/output, so their solutions suffer from information loss and will affect the performance of downstream GNN.

2.2 Geometrical Methods

The geometrical methods in EDA focus on the spatial information of the circuit designs. A universal approach is to cut a circuit into small rectangles i.e. grids and convert it into RGB channels, where the grids are treated as pixels [8, 13]. Then, they encode the netlist structure and circuit features into green and blue channels while red channels are left for prediction targets (e.g. congestion). Finally, they use image translation methods (e.g. pix2pix [9]) to output new images with red channels filled and indirectly solve the EDA tasks.

109 The cutting-edge LHNN [14], however, converts the circuits into lattice networks [15] instead of
110 images, where each grid serves as an internal node in the network and each net, as an external node, is
111 connected to the grids it covers geometrically. LHNN successfully enhances topological information
112 in geometrical method and achieves SOTA performance, but it can only handle congestion prediction
113 task and can only work on circuits with placement information.

3 Circuit Graph

Figure 3: Convert circuit design to Circuit Graph. (b): Take *cell-net* connections i.e. *pins* as *topo-edges*. (c)(d)(e): Link the geometrically close *cell*-pairs to construct *geom-edges*.

3.1 Circuit Featurization

116 A circuit design is initially represented as a netlist composed of *cells* $\mathcal{V}$ and *nets* $\mathcal{U}$ (Fig.2(a)), and we
117 define $\boldsymbol{X}_\mathcal{V}, \boldsymbol{X}_\mathcal{U}$ to be their feature matrices. $\boldsymbol{X}_\mathcal{V}$ mainly contains the size and degree (to *net*) of the
118 cells, and $\boldsymbol{X}_\mathcal{U}$ stores the net span [14] and the degree (to *cell*).

119 Besides the basic attributes of *cells* and *nets*, the topology and geometry also play important roles in
120 featurizing the circuit designs. The *pins* $\mathcal{P} \subseteq \mathcal{V} \times \mathcal{U}$ stand for the bipartite topology between *cells*
121 $\mathcal{V}$ and *nets* $\mathcal{U}$, and $\boldsymbol{X}_\mathcal{P}$, the feature matrix of $\mathcal{P}$, preserves their interaction details e.g. the signal
122 direction (input/output). After placement, the positions of *cells* $\boldsymbol{p}_x, \boldsymbol{p}_y$ are obtained, which serve
123 as a major geometrical information. When carrying out deep learning on EDA, how to arrange the
124 features of circuit design varies according the downstream model.

125 The geometrical methods cut the circuit into smaller rectangles i.e. *grids*[1] and generate raw features
126 on them by synthesizing the positions of *cells* $\boldsymbol{p}_x, \boldsymbol{p}_y$ along with *cells'* and *nets'* features $\boldsymbol{X}_\mathcal{V}, \boldsymbol{X}_\mathcal{U}$
127 and their connections $\mathcal{P}$ (Fig.2(b)) [9, 14]:

128 **Definition 1** (Geometry-driven Circuit Featurization). $\mathcal{F}_G = \{\boldsymbol{X}_{gr}\}$, where $\boldsymbol{X}_{gr} = \mathbb{R}^{C_x \times C_y \times D_{gr}}$ is
129 *the feature matrix of grids. Note that C_x, C_y are the column and row numbers of grids and D_{gr} is*
130 *the dimension of grids' raw features.*

131 The *grid* feature $\boldsymbol{X}_{gr}$ mainly includes pin density and net density [7]. As the structure of $\boldsymbol{X}_{gr}$ is
132 similar to RGB channels of image data, CV models (e.g. CNN[9]) can be easily adopted to handle
133 EDA tasks where geometrical information are provided as input.

134 The topological methods prefer to construct the circuit design as a bipartite graph (Def.2) [12]:

135 **Definition 2** (Topology-driven Circuit Featurization). $\mathcal{F}_T = \{\mathcal{V}, \mathcal{U}, \mathcal{P}, \boldsymbol{X}_\mathcal{V}, \boldsymbol{X}_\mathcal{U}, \boldsymbol{X}_\mathcal{P}\}$, *where cells*
136 $\mathcal{V}$ *and nets* $\mathcal{U}$ *are two types of vertices, and pins* $\mathcal{P}$ *are the edges connecting them.*

137 However, $\mathcal{F}_T$ is usually simplified as a homogeneous graph, and is fed to some popular GNNs, such
138 as GAT (see Fig.2(c)(d) and Sec.2.1) [5, 6, 12], which leads to loss of heterogeneous information.

---

[1]In this paper, we use *grid* size $32\mu m \times 40\mu m$.

139 Note that the explicit raw features of *grid*, *cell*, *net* and *pin* are listed in Appendix A.

3.2 Definition of Circuit Graph

141 To better benefit from both the above two commonly used featurization system for circuit, we propose
142 a novel way to encode both the topological and geometrical information (when available) underlying
143 the circuits into a unified heterogeneous graph. As shown in Fig.3, we first take *pins* as *topo-edges*
144 ($\mathcal{E}_T = \mathcal{P}$ and $\boldsymbol{X}_{\mathcal{E}_T} = \boldsymbol{X}_{\mathcal{P}}$). Then we link the geometrically-close *cells* with *geom-edges* $\mathcal{E}_G$ and
145 store the *cell*-pair distances in feature matrix $\boldsymbol{X}_{\mathcal{E}_G}$. Finally, we define Circuit Graph as follows:

146 **Definition 3** (Circuit Graph). *A Circuit Graph $\mathcal{G} = \{\mathcal{V}, \mathcal{U}, \mathcal{E}_T, \mathcal{E}_G, \boldsymbol{X}_{\mathcal{V}}, \boldsymbol{X}_{\mathcal{U}}, \boldsymbol{X}_{\mathcal{E}_T}, \boldsymbol{X}_{\mathcal{E}_G}\}$, where*
147 *$\mathcal{V}, \mathcal{U}, \mathcal{E}_T \subseteq \mathcal{V} \times \mathcal{U}, \mathcal{E}_G \subseteq \mathcal{V} \times \mathcal{V}$ refer to the set of cells, nets, topo-edges and geom-edges, respectively,*
148 *and $\boldsymbol{X}_{\mathcal{V}}, \boldsymbol{X}_{\mathcal{U}}, \boldsymbol{X}_{\mathcal{E}_T}, \boldsymbol{X}_{\mathcal{E}_G}$ are their feature matrices.*

149 To preserve the topological information, we completely inherit $\mathcal{V}, \mathcal{U}, \mathcal{P}$ and their features from $\mathcal{F}_T$ in
150 Def.2 rather than simplify them as homogeneous graphs with loss of heterogeneity. For geometrical
151 information, to avoid calculating all $O(|\mathcal{V}|^2)$ *cell*-pairs' distances and reduce time cost to $O(|\mathcal{V}|)$, we
152 split the *cells* by shifted windows[16] with size (w_x, w_y) and link the *cells* with up to c (named "link
153 capacity") neighbouring *cells* located in the same window (see explicit steps in Appendix B.1). If
154 we need to handle the problem at the pre-placement phase such as the logic synthesis stage, we will
155 not have the *geom-edges* among the *cells* and will set $\mathcal{E}_G = \emptyset$ for the representation learning phase,
156 which shows that Circuit Graph is compatible with circuits in logic synthesis stage.

157 Note that the time consumption of converting a circuit design into a Circuit Graph is $O(|\mathcal{V}|+|\mathcal{U}|+|\mathcal{P}|)$,
158 which is linear to the scale of the circuit (see proof in Appendix B.2).

4 Circuit GNN

4.1 Overview

161 The framework of Circuit GNN is shown in Fig.4. We first input the Circuit Graph $\mathcal{G}$ and initial-
162 ize the feature of *cells* $\mathcal{V}$, *nets* $\mathcal{U}$, *topo-edges* $\mathcal{E}_T$ and *geom-edges* $\mathcal{E}_G$ to hidden representations
163 $\boldsymbol{H}_{\mathcal{V}}^{(0)}, \boldsymbol{H}_{\mathcal{U}}^{(0)}, \boldsymbol{H}_{\mathcal{E}_T}, \boldsymbol{H}_{\mathcal{E}_G}$ with Multi-Layer Perceptrons (MLPs). Then deeper representations of *cells*
164 and *nets* are generated via L layers of circuit message-passing. Finally, the output *cell* and *net*
165 representations are used for downstream tasks after passing through task-adaptive readout layers.
166 Note that Circuit GNN's model sensitivity is justified in Appendix D.

Figure 4: Framework of Circuit GNN. The topological messages between *cell* and *net* are passed
through *topo-edge*, while the geometrical messages among *cells* are passed through *geom-edge*.
Circuit GNN can be set to L layers.

4.2 Topo-Geom Message-passing

Inside each layer out of L Topo-Geom Message-passing layers, topological and geometrical information are collected by passing messages through two types of heterogeneous edges ($\mathcal{E}_T$ and $\mathcal{E}_G$). Then, the messages are used to update *cell* representations $\boldsymbol{H}_\mathcal{V}$ and *net* representations $\boldsymbol{H}_\mathcal{U}$. In Topological Message-passing, the messages between *cells* $\mathcal{V}$ and *nets* $\mathcal{U}$ are transmitted through *topo-edges* $\mathcal{E}_T$:

$$\boldsymbol{M}_\mathcal{V}^{(l),topo} = \Phi_{msg}^{\mathcal{U}\xrightarrow{\mathcal{E}_T}\mathcal{V}}(\mathcal{U}, \mathcal{E}_T, \boldsymbol{H}_\mathcal{U}^{(l)}, \boldsymbol{H}_{\mathcal{E}_T}) \qquad \boldsymbol{M}_\mathcal{U}^{(l)} = \Phi_{msg}^{\mathcal{V}\xrightarrow{\mathcal{E}_T}\mathcal{U}}(\mathcal{V}, \mathcal{E}_T, \boldsymbol{H}_\mathcal{V}^{(l)}, \boldsymbol{H}_{\mathcal{E}_T}) \qquad (1)$$

where l is the number of current layer and $\Phi_{msg}^{\mathcal{U}\xrightarrow{\mathcal{E}_T}\mathcal{V}}$ is the message function which collects topological messages from *nets* $\mathcal{U}$ and sends them to *cells* $\mathcal{V}$ via *topo-edges* $\mathcal{E}_T$ ($\Phi_{msg}^{\mathcal{V}\xrightarrow{\mathcal{E}_T}\mathcal{U}}$ similarly). In Geometrical Message-passing, we consider the *geom-edges* $\mathcal{E}_G$ and collect geometrical messages for *cells* $\mathcal{V}$:

$$\boldsymbol{M}_\mathcal{V}^{(l),geom} = \Phi_{msg}^{\mathcal{V}\xrightarrow{\mathcal{E}_G}\mathcal{V}}(\mathcal{V}, \mathcal{E}_G, \boldsymbol{H}_\mathcal{V}^{(l)}, \boldsymbol{H}_{\mathcal{E}_G}) \qquad (2)$$

Then, we fuse the topological and geometrical messages and update the representations:

$$\boldsymbol{M}_\mathcal{V}^{(l)} = \text{MaxPooling}(\boldsymbol{M}_\mathcal{V}^{(l),geom}, \boldsymbol{M}_\mathcal{V}^{(l),topo}) \qquad (3)$$

$$\boldsymbol{H}_\mathcal{V}^{(l+1)} = \Phi_{update}(\boldsymbol{H}_\mathcal{V}^{(l)}, \boldsymbol{M}_\mathcal{V}^{(l)}) \qquad \boldsymbol{H}_\mathcal{U}^{(l+1)} = \Phi_{update}(\boldsymbol{H}_\mathcal{U}^{(l)}, \boldsymbol{M}_\mathcal{U}^{(l)}) \qquad (4)$$

where the update function $\Phi_{update}(\boldsymbol{H}, \boldsymbol{M}) = \boldsymbol{H} + \text{Tanh}(\boldsymbol{M})$.

The efficiency and the capability of perceiving heterogeneous information (e.g. the edge embeddings in $\mathcal{E}_T$ and $\mathcal{E}_G$ which encode topological and geometrical information) should be considered when designing the exact message functions Φ_{msg}. In Topological Message-passing, inspired by [17], for a *net* u, we fuse the representations of surrounding *cells* $\{v|(v,u) \in \mathcal{E}_T\}$ and *topo-edges* connecting them:

$$\Phi_{msg}^{\mathcal{V}\xrightarrow{\mathcal{E}_T}\mathcal{U}}(\{(\boldsymbol{h}_v^\mathcal{V}, \boldsymbol{h}_{(v,u)}^{\mathcal{E}_T})|(v,u) \in \mathcal{E}_T\}) = \sum_{(v,u)\in\mathcal{E}_T} (\boldsymbol{W}_{\mathcal{E}_T\to\mathcal{U}}\boldsymbol{h}_{(v,u)}^{\mathcal{E}_T}) \odot (\boldsymbol{W}_{\mathcal{V}\to\mathcal{U}}\boldsymbol{h}_v^\mathcal{V}) \qquad (5)$$

where $\boldsymbol{h}_v^\mathcal{V}$ is the representation vector of *cell* v, $\boldsymbol{h}_{(v,u)}^{\mathcal{E}_T}$ is the representation vector of *topo-edge* connecting v, u, $\boldsymbol{W}_{\mathcal{V}\to\mathcal{U}}, \boldsymbol{W}_{\mathcal{E}_T\to\mathcal{U}}$ are learnable weight matrices and $\odot$ is the element-wise multiplication. As *topo-edge*'s representations have already been collected in $\Phi_{msg}^{\mathcal{V}\xrightarrow{\mathcal{E}_T}\mathcal{U}}$, we only consider *net*'s representations $\boldsymbol{h}_u^\mathcal{U}$ in the messages passed back to the *cells*, which speeds up message-passing (because of less computation) with minor topological information loss:

$$\Phi_{msg}^{\mathcal{U}\xrightarrow{\mathcal{E}_T}\mathcal{V}}(\{\boldsymbol{h}_u^\mathcal{U}|(v,u) \in \mathcal{E}_T\}) = \sum_{(v,u)\in\mathcal{E}_T} \boldsymbol{W}_{\mathcal{U}\to\mathcal{V}}\boldsymbol{h}_u^\mathcal{U} \qquad (6)$$

In Geometrical Message-passing, to enhance the geometrical information, the *geom-edge*'s representations are used to compute the edge weights when convolving the *cells*:

$$\Phi_{msg}^{\mathcal{V}\xrightarrow{\mathcal{E}_G}\mathcal{V}}(\{(\boldsymbol{h}_{v^*}^\mathcal{V}, \boldsymbol{h}_{(v,v^*)}^{\mathcal{E}_G})|(v,v^*) \in \mathcal{E}_G\}) = \sum_{(v,v^*)\in\mathcal{E}_G} (\boldsymbol{a}^\top \boldsymbol{h}_{(v,v^*)}^{\mathcal{E}_G}) \cdot \boldsymbol{W}_{\mathcal{V}\to\mathcal{V}}\boldsymbol{h}_{v^*}^\mathcal{V} \qquad (7)$$

where $\boldsymbol{a}$ is a learnable weight vector and $\boldsymbol{W}_{\mathcal{V}\to\mathcal{V}}$ is a learnable weight matrix.

Discussion of Inference Time. Assume that the hidden layer dimensions of *cell*, *net*, *topo-edge*, *geom-edge* are $F_\mathcal{V}, F_\mathcal{U}, F_{\mathcal{E}_T}, F_{\mathcal{E}_G}$. The inference times of $\Phi_{msg}^{\mathcal{V}\xrightarrow{\mathcal{E}_T}\mathcal{U}}, \Phi_{msg}^{\mathcal{U}\xrightarrow{\mathcal{E}_T}\mathcal{V}}, \Phi_{msg}^{\mathcal{V}\xrightarrow{\mathcal{E}_G}\mathcal{V}}$ are $O(|\mathcal{E}_T|(F_{\mathcal{E}_T}F_\mathcal{U} + F_\mathcal{V}F_\mathcal{U} + F_\mathcal{U})), O(|\mathcal{E}_T|F_\mathcal{U}F_\mathcal{V}), O(|\mathcal{E}_G|(F_{\mathcal{E}_G} + F_\mathcal{V}^2))$, respectively. The time complexities of fusing (MaxPooling) and updating are $O(|\mathcal{V}|F_\mathcal{V}), O(|\mathcal{V}|F_\mathcal{V} + |\mathcal{U}|F_\mathcal{U})$, respectively. As the dimensions are constant numbers and $|\mathcal{E}_T| = O(|\mathcal{P}|), |\mathcal{E}_G| = O(|\mathcal{V}|)$ (see Appendix B.2), the total inference time in one Topo-Geom Message-passing layer is $O(|\mathcal{V}| + |\mathcal{U}| + |\mathcal{P}|)$, which is linear to the scale of input Circuit Graph. Therefore, our message-passing method can handle Circuit Graph **with optimal efficiency**, and it is further demonstrated to be as fast as **CongestionNet**[5], a deep GAT architecture, in Tab.1.

4.3 Task-adaptive Readout

After L iterations of message-passing, we read out the *cell* and *net* representations $\boldsymbol{H}_{\mathcal{V}}^{(L)}, \boldsymbol{H}_{\mathcal{U}}^{(L)}$ to handle diverse downstream tasks on circuits. For tasks on Cell-level (e.g. congestion prediction for each *cell* [5]), to enhance the raw features, we concatenate the *cell* representation and its raw features and pass them through an MLP (similarly for Net-level tasks e.g. net length prediction [12]):

$$\hat{\boldsymbol{y}}_{\text{cell}} = \text{MLP}(\boldsymbol{H}_{\mathcal{V}}^{(L)} \oplus \boldsymbol{X}_{\mathcal{V}}) \qquad \hat{\boldsymbol{y}}_{\text{net}} = \text{MLP}(\boldsymbol{H}_{\mathcal{U}}^{(L)} \oplus \boldsymbol{X}_{\mathcal{U}}) \tag{8}$$

However, Grid-level tasks (e.g. congestion prediction for each *grid* in chip map [9]) assign targets on each *grid*, which our model is not aware of. To enable model's training and evaluation on these tasks, we generate an output representation on each *grid* by mean-pooling the representation of *cells* inside the *grid*:

$$\hat{\boldsymbol{y}}_{\text{grid}} = \text{MLP}(\hat{\boldsymbol{M}} \boldsymbol{H}_{\mathcal{V}}^{(L)}) \tag{9}$$

where $\hat{\boldsymbol{M}} \in \mathbb{R}^{C_x \times C_y \times |\mathcal{V}|}$ is the transformation matrix with $\sum_k \hat{\boldsymbol{M}}_{i,j,k} = 1, \forall i, j$.

5 Experiments

5.1 Tasks and Datasets

Congestion Prediction   is the task of predicting the routing congestion before the wires are routed in the detailed routing stage. It is widely used in placement tools to provide quick feedback about the quality of placement and avoid placement solutions with poor routability [18][19][20]. In order to identify and solve potential congested structures earlier, multiple works have attempted to predict cell-level congestion in logic synthesis stage, before cells are placed [6][21][22]. We conduct the experiment on ISPD2011[2], which contains 12 VLSI designs in total. We use 10 designs (1/2/3/5/6/7/9/11/14/16) for training, design #18 for validation, and #19 for testing. We use DREAMPlace[18] to place cells and initialize the raw features of *cells*, *nets* and *grids*. NCTU-GR 2.0[23], a popular global router, is used to generate the congestion targets on the grids. The congestion target of each *cell* is set as the value of the grid it is located in. For congestion prediction in logic synthesis stage, we only use the topology of the circuits and the geometry-insensitive features. For prediction in placement, we additionally use the *cells*' positions generated by DREAMPlace.

Similar to [6], we compare the prediction and ground-truth in Pearson/Spearman/Kendall correlation on both Cell-level and Grid-level. We also divide the congestion values to $[0, 0.9]$ and $(0.9, \infty)$ and use precision/recall/F1-score to further evaluate their ability of identifying congestion [14].

Net Wirelength Prediction   aims to deduce the wire length of each *net*, which is an important indicator of the eventual chip performance [24]. We use half-perimeter wirelength (HPWL) as the wirelength estimator, which is the most commonly used method for wirelength calculation [2]. We conduct the experiment on DAC2012[3], where we use 7 designs (3/6/7/9/11/12/14) for training, design #16 for validation and #19 for testing. DREAMPlace[18] is used to generate the targets for every *net*. The featurization of circuits in both stages is the same with **Congestion Prediction** mentioned above.

As the regression targets of wirelength range from 0 to about 25k, we take the $\log_{10}$ of them to make the distribution of targets more smoothing. We evaluate the results in Pearson/Spearman/Kendall correlation as well as Mean Average Error (MAE) and Root Mean Square Error (RMSE).

Transfer Task   To evaluate baselines' transferability, we conduct an experiment in Appendix G.

5.2 Baselines and Settings

When conducting the two tasks above, we compare our model with the following base-lines. Traditional machine learning methods include **MLP**, typical graph representation models

---

[2]http://www.ispd.cc/contests/11/ispd2011_contest.html
[3]http://archive.sigda.org/dac2012/contest/dac2012_contest.html

GCN[25]/**GAT**[11]/**GraphSAGE**[26] and **pix2pix**[9]/**MPNN**[10], a typical image translation model in CV. We also carry out results on EDA-customized machine learning models: (1) **CongestionNet**[5], a multi-layer graph attentive architecture designed to predict circuit congestion; (2) **Net^{2f}/Net^{2a}**[12], pre-placement net representation models with customized GNN; (3) **LHNN**[14]: a geometrical congestion prediction method supplied with topological information i.e. net span. To further validate our model's ability to fuse the topological and geometrical information, we test two variants of our model: **Ours (w/o. geom.)** which throws all *geom-edges* and **Ours (w/o. topo.)** which throws all *topo-edges* in Circuit Graph (Def.3).

For cited methods, we use their default model settings. For Circuit GNN, we set hidden layer dimensions of *cell, net, topo-edge, geom-edge* $(F_\mathcal{V}, F_\mathcal{U}, F_{\mathcal{E}_T}, F_{\mathcal{E}_G}) = (64, 128, 8, 4)$ and message passing layers $L = 2$. We have default settings of window size $(w_x, w_y) = (32, 40)$ and link capacity $c = 5$, and their parameter sensitivity is tested in Appendix C to show the robustness of our model. When training our model with `Adam Optimizer`, we use learning rate $\gamma = 0.0002$, learning rate decay $\Delta\gamma = 0.02$, weight decay $\eta = 0.0002$ and training epoch $e = 100$.

5.3 Result of Congestion Prediction

Table 1: Congestion prediction result in logic synthesis stage

Baseline	Time (s/epoch)	Cell-level			Grid-level		
		pearson	spearman	kendall	pearson	spearman	kendall
GCN	9.43	0.777	0.265	0.199	0.221	0.366	0.260
GraphSAGE	11.79	0.776	0.252	0.188	0.208	0.375	0.268
GAT	13.90	0.777	0.267	0.200	0.215	0.399	0.280
MPNN	116.24	**0.780**	**0.289**	**0.217**	0.292	0.458	0.319
CongestionNet	22.31	0.777	0.269	0.200	0.277	0.394	0.280
Ours (w/o. geom.)	21.62	0.779	**0.289**	**0.217**	**0.315**	**0.468**	**0.329**

Table 2: Congestion prediction result in placement stage (in correlation)

Baseline	Time (s/epoch)	Cell-level			Grid-level		
		pearson	spearman	kendall	pearson	spearman	kendall
GAT (w. geom.)	16.21	0.777	0.263	0.197	0.210	0.397	0.279
pix2pix	4.46	-	-	-	0.562	0.554	0.392
LHNN	305.47	-	-	-	**0.703**	0.695	0.540
Ours (w/o. topo.)	21.54	0.883	0.713	0.573	0.684	0.730	0.536
Ours	27.07	**0.887**	**0.714**	**0.575**	0.697	**0.770**	**0.577**

(a) Input   (b) pix2pix   (c) LHNN   (d) Ours   (e) Ground-truth

Figure 5: Visualization of congestion maps of circuit `ispd2011/superblue19` produced by the baselines.

We first evaluate the congestion prediction result on circuits in logic synthesis stage when geometric information is not available (Tab.1). Then we perform the same task in placement stage as shown in Tab.2 and Tab.15 (in Appendix). Note that geometrical methods **pix2pix** and **LHNN** are not aware of *cells* in circuit design, so they are not evaluated on Cell-level. **GAT (w. geom.)** is regular GAT with *cell* positions as additional features.

The results show that: (1) In logic synthesis stage, our method with only *topo-edges* achieves the best performance (16.7% over cutting-edge CongestionNet) with a similar time cost compared to traditional GNN models. (2) In placement stage, our method beats the cutting-edge **LHNN** in most metrics (5.6% on average) while taking only one-tenth of the run-time. The superior performance of our model is primarily attributed to the fusion of both topological and geometrical information contained in the circuit design.

Fig.5 visualizes the predicted congestion values using different methods. Compared to vision-based method [9] and lattice network-based method [15], our proposed method can generate finer congestion prediction with better discriminability.

5.4 Result of Net Wirelength Prediction

Table 3: Net wirelength prediction in placement stage (↓ means "lower is better")

Baseline	Time (s/epcoh)	pearson	spearman	kendall	MAE↓	RMSE↓
MLP	2.22	0.493	0.547	0.415	0.626	0.819
Net^{2f}	10.42	0.517	0.635	0.525	0.615	0.825
Net^{2a}	19.83	0.632	0.656	0.553	0.614	0.821
LHNN	260.00	0.801	0.796	0.603	0.581	0.780
Ours	14.79	**0.848**	**0.835**	**0.646**	**0.483**	**0.683**

| (a) MLP | (b) Net^{2f} | (c) Net^{2a} | (d) LHNN | (e) Ours |

Figure 6: Scattering the models' output (axis-y) and ground-truth (axis-x) in net wirelength prediction (placement stage).

The result of net wirelength prediction is shown in Tab.14 (logic synthesis stage, in Appendix), Tab.3 and Fig.6 (placement stage). We obtain LHNN's result on this task by reading out its net representations generated in the intermediate stage. The result shows that our model achieves SOTA performance (16.9% error gain) with similar time cost to **Net^{2f}** and **Net^{2a}**.

6 Conclusion and Future Work

We present a versatile graph neural network to facilitate EDA circuit design process. To this end, we design a heterogeneous graph, Circuit Graph, to integrate topological and geometrical information into a unified data structure, based on which we further propose a message-passing and fusion approach named Circuit GNN. It is the first circuit representation method applied to multiple EDA tasks and stages. By integrating multi-source information, Circuit Graph outperforms previous methods in prediction performance and computation time. Our work further supports the EDA process "shift-left", a new future direction that aims to speed-up circuit design by deeply combining artificial intelligence in all EDA tool chains.

Limitations Although AI for EDA becomes a hot research topic recently and some deep learning-driven techniques have been adopted in the main-stream EDA tools (Cadence, Synopsys, etc.), there is still a gap between the novel machine learning algorithms and their application in commercial tools. The method proposed in the paper needs to be validated with more complex constraints and extreme conditions before integrated in a commercial EDA toolbox.

Societal Impact. Our solution explores dual-stage circuit representation to serve various EDA downstream tasks, which have limited societal impact. Whatever, there is a minimal possibility of misuse that violate some ethics of life science.

References

[1] Ismail Bustany, David Chinnery, Joseph Shinnerl, and Vladimir Yutsis. Ispd 2015 benchmarks with fence regions and routing blockages for detailed-routing-driven placement. 04 2015.

[2] A. Mirhoseini, A. Goldie, M. Yazgan, and J. Jiang. A graph placement methodology for fast chip design. In *Nature 594*, page 207–212, 2021.

[3] Ruoyu Cheng and Junchi Yan. On joint learning for solving placement and routing in chip design. In M. Ranzato, A. Beygelzimer, Y. Dauphin, P.S. Liang, and J. Wortman Vaughan, editors, *Advances in Neural Information Processing Systems*, volume 34, pages 16508–16519. Curran Associates, Inc., 2021.

[4] Daniela Sánchez Lopera, Lorenzo Servadei, Gamze Naz Kiprit, Souvik Hazra, Robert Wille, and Wolfgang Ecker. A survey of graph neural networks for electronic design automation. In *2021 ACM/IEEE 3rd Workshop on Machine Learning for CAD (MLCAD)*, pages 1–6, 2021.

[5] Robert Kirby, Saad Godil, Rajarshi Roy, and Bryan Catanzaro. Congestionnet: Routing congestion prediction using deep graph neural networks. In *2019 IFIP/IEEE 27th International Conference on Very Large Scale Integration (VLSI-SoC)*, pages 217–222, 2019.

[6] Amur Ghose, Vincent Zhang, Yingxue Zhang, Dong Li, Wulong Liu, and Mark Coates. Generalizable cross-graph embedding for gnn-based congestion prediction. In *2021 IEEE/ACM International Conference On Computer Aided Design (ICCAD)*, pages 1–9, 2021.

[7] Mohamed Baker Alawieh, Wuxi Li, Yibo Lin, Love Singhal, Mahesh A. Iyer, and David Z. Pan. High-definition routing congestion prediction for large-scale fpgas. In *2020 25th Asia and South Pacific Design Automation Conference (ASP-DAC)*, pages 26–31, 2020.

[8] Cunxi Yu and Zhiru Zhang. Painting on piacement: Forecasting routing congestion using conditional generative adversarial nets. In *2019 56th ACM/IEEE Design Automation Conference (DAC)*, pages 1–6, 2019.

[9] Zhonghua Zhou, Ziran Zhu, Jianli Chen, Yuzhe Ma, Bei Yu, Tsung-Yi Ho, Guy Lemieux, and Andre Ivanov. Congestion-aware global routing using deep convolutional generative adversarial networks. In *2019 ACM/IEEE 1st Workshop on Machine Learning for CAD (MLCAD)*, pages 1–6, 2019.

[10] Justin Gilmer, Samuel S. Schoenholz, Patrick F. Riley, Oriol Vinyals, and George E. Dahl. Neural message passing for quantum chemistry. In Doina Precup and Yee Whye Teh, editors, *Proceedings of the 34th International Conference on Machine Learning*, volume 70 of *Proceedings of Machine Learning Research*, pages 1263–1272. PMLR, 06–11 Aug 2017.

[11] Petar Veličković, Guillem Cucurull, Arantxa Casanova, Adriana Romero, Pietro Liò, and Yoshua Bengio. Graph attention networks. In *International Conference on Learning Representations*, 2018.

[12] Zhiyao Xie, Rongjian Liang, Xiaoqing Xu, Jiang Hu, Chen-Chia Chang, Jingyu Pan, and Yiran Chen. Pre-placement net length and timing estimation by customized graph neural network. *IEEE Transactions on Computer-Aided Design of Integrated Circuits and Systems*, pages 1–1, 2022.

[13] Zhiyao Xie, Yu-Hung Huang, Guan-Qi Fang, Haoxing Ren, Shao-Yun Fang, Yiran Chen, and Jiang Hu. Routenet: Routability prediction for mixed-size designs using convolutional neural network. In *2018 IEEE/ACM International Conference on Computer-Aided Design (ICCAD)*, pages 1–8, 2018.

[14] Bowen Wang, Guibao Shen, Dong Li, Jianye Hao, Wulong Liu, Yu Huang, Hongzhong Wu, Yibo Lin, Guangyong Chen, and Pheng Ann Heng. Lhnn: Lattice hypergraph neural network for vlsi congestion prediction, 2022.

[15] Seungil You, David Ding, Kevin Canini, Jan Pfeifer, and Maya Gupta. Deep lattice networks and partial monotonic functions. In I. Guyon, U. Von Luxburg, S. Bengio, H. Wallach, R. Fergus, S. Vishwanathan, and R. Garnett, editors, *Advances in Neural Information Processing Systems*, volume 30. Curran Associates, Inc., 2017.

[16] Ze Liu, Yutong Lin, Yue Cao, Han Hu, Yixuan Wei, Zheng Zhang, Stephen Lin, and Baining Guo. Swin transformer: Hierarchical vision transformer using shifted windows. In *2021 IEEE/CVF International Conference on Computer Vision (ICCV)*, pages 9992–10002, 2021.

[17] K. T. Schütt, P.-J. Kindermans, H. E. Sauceda, S. Chmiela, A. Tkatchenko, and K.-R. Müller. Schnet: A continuous-filter convolutional neural network for modeling quantum interactions. NIPS'17, page 992–1002, Red Hook, NY, USA, 2017. Curran Associates Inc.

[18] Yibo Lin, Zixuan Jiang, Jiaqi Gu, Wuxi Li, Shounak Dhar, Haoxing Ren, Brucek Khailany, and David Z. Pan. Dreamplace: Deep learning toolkit-enabled gpu acceleration for modern vlsi placement. *IEEE Transactions on Computer-Aided Design of Integrated Circuits and Systems*, 40(4):748–761, 2021.

[19] Tao Lin and Chris Chu. Polar 2.0: An effective routability-driven placer. In *Proceedings of the 51st Annual Design Automation Conference*, 2014.

[20] Chen Li, Min Xie, Cheng-Kok Koh, Jason Cong, and Patrick H Madden. Routability-driven placement and white space allocation. *IEEE Transactions on Computer-aided design of Integrated Circuits and Systems*, 2007.

[21] Tanuj Jindal, Charles J Alpert, Jiang Hu, Zhuo Li, Gi-Joon Nam, and Charles B Winn. Detecting tangled logic structures in vlsi netlists. In *Proceedings of the 47th Design Automation Conference*, 2010.

[22] Prabhakar Kudva, Andrew Sullivan, and William Dougherty. Metrics for structural logic synthesis. In *IEEE/ACM International Conference on Computer Aided Design, 2002. ICCAD 2002.*, 2002.

[23] Wen-Hao Liu, Wei-Chun Kao, Yih-Lang Li, and Kai-Yuan Chao. Nctu-gr 2.0: Multithreaded collision-aware global routing with bounded-length maze routing. *IEEE Transactions on Computer-Aided Design of Integrated Circuits and Systems*, 32(5):709–722, 2013.

[24] A.E. Caldwell, A.B. Kahng, S. Mantik, I.L. Markov, and A. Zelikovsky. On wirelength estimations for row-based placement. *IEEE Transactions on Computer-Aided Design of Integrated Circuits and Systems*, 1999.

[25] Thomas Kipf and Max Welling. Semi-supervised classification with graph convolutional networks. *ArXiv*, abs/1609.02907, 2017.

[26] William L. Hamilton, Rex Ying, and Jure Leskovec. Inductive representation learning on large graphs. In *Proceedings of the 31st International Conference on Neural Information Processing Systems*, NIPS'17, page 1025–1035, Red Hook, NY, USA, 2017. Curran Associates Inc.

[27] Tong Xia, Junjie Lin, Yong Li, Jie Feng, Pan Hui, Funing Sun, Diansheng Guo, and Depeng Jin. 3dgcn: 3-dimensional dynamic graph convolutional network for citywide crowd flow prediction. *ACM Trans. Knowl. Discov. Data*, 15(6), jun 2021.

[28] Shuwen Yang, Ziyao Li, Guojie Song, and Lingsheng Cai. Deep molecular representation learning via fusing physical and chemical information. In M. Ranzato, A. Beygelzimer, Y. Dauphin, P.S. Liang, and J. Wortman Vaughan, editors, *Advances in Neural Information Processing Systems*, volume 34, pages 16346–16357. Curran Associates, Inc., 2021.

A   Featurization

The featurization of *grid*, *cell*, *net* and *pin* is shown in Tab.4/5/6/7.

Table 4: *Grid* Features

Name	Type	Description
net density	$\mathbb{R}^2$	the density of *nets* in each *grid* (horizontally and vertically) [7]
pin density	$\mathbb{R}$	the density of *pins* in each *grid* [7]
node density	$\mathbb{R}$	the density of *cells* in each *grid* [7]

Table 5: *Cell* Features

Name	Type	Description
size	$\mathbb{R}^2$	width & height of the *cell*
degree	$\mathbb{N}$	# of *nets* connected with the *cell*

When conducting experiments on circuits in placement stage, grid features in Tab.4 are borrowed to supply node features by assigning each node with the features of the grid it's located in.

Table 6: *Net* Features

Name	Type	Description
degree	$\mathbb{N}$	# of *cells* connected with the *net*
span	$\mathbb{N}^2$	# of *grids* the *net* covers horizontally and vertically [14]

Note that the feature **span** is only available in placement stage.

Table 7: *Pin* Features

Name	Type	Description
pin offset	$\mathbb{R}^2$	the offset position of the *cell* (horizontally and vertically)
signal direction	0/1	this *pin* input/output signal to the *cell*

B Graphization of Circuit Design

B.1 Graphize Geometrical Information

For circuit designs in placement stage, a universal solution of graphizing geometry is to link the *cell*-pairs whose distances are lower than a threshold δ [27]:

$$\hat{\mathcal{E}}_G = \{(i,j)|i,j \in \mathcal{V} \wedge \sqrt{(\widetilde{\boldsymbol{p}}_x[i] - \widetilde{\boldsymbol{p}}_x[j])^2 + (\widetilde{\boldsymbol{p}}_y[i] - \widetilde{\boldsymbol{p}}_y[j])^2} < \delta\}$$
$$\widetilde{\boldsymbol{p}}_x = \boldsymbol{p}_x + \boldsymbol{s}_x/2 \qquad \widetilde{\boldsymbol{p}}_y = \boldsymbol{p}_y + \boldsymbol{s}_y/2 \tag{10}$$

where $(\widetilde{\boldsymbol{p}}_x[i], \widetilde{\boldsymbol{p}}_y[i])$ is the position of i-th *cell*'s center, and $\boldsymbol{s}_x, \boldsymbol{s}_y$ are the width/height of *cells*. However, the time cost of this solution is $O(|\mathcal{V}|^2)$ and makes it unpractical for very large circuits with millions of *cells* and *nets*.

To accelerate the geometry graphization, we cut the circuit into windows with size (w_x, w_y), scatter the *cells* into the windows and link the *cells* appearing in the same window, as it shows in Fig.7. Note that every *cell* has its 2D structure and may appear in multiple windows e.g. *cell* 4 in Fig.7(b).

However, it is still possible that two adjacent *cells* are incidentally split into different windows and can't get linked e.g. *cell* 2 and 3 in Fig.7(b). To avoid this, we shift the windows by $w_x/2$ horizontally or $w_y/2$ vertically and add new links (see Fig.7(c)(d)(e)). Finally, as it shows in Fig.7(f), we get *geom-edges* $\mathcal{E}_G$:

Figure 7: Link the adjacent *cells* by scattering them into shift windows.

$$\mathcal{E}_G = \{(i,j)|i,j \in \mathcal{V} \land i,j \text{ appear in the same window}\} \tag{11}$$

$\mathcal{E}_G$ is actually a sampling of the *cell*-pairs with distance lower than $\delta = \sqrt{w_x^2 + w_y^2}$, and the possibility of being sampled is inversely proportional to their distance. However, the time consumption of constructing $\mathcal{E}_G$ is still $O(|\mathcal{V}|^2/|\mathcal{W}|)^4$. To further lower the consumption, for every *cell* i, we only link it to at most c others appearing in the same window and produce an $\mathcal{E}_G^* \subseteq \mathcal{E}_G$ to substitute $\mathcal{E}_G$. As c is a constant, the time cost of constructing $\mathcal{E}_G^*$ is $O(|\mathcal{V}|)$ (see proof in Appendix.B.2). To further enhance the information in *geom-edges*, we store the *cell*-pair distances as raw features in $\mathcal{E}_G$.

To show the robustness of our geometry graphization method, we test the sensitivity of window size (w_x, w_y) and link capacity c in Sec.C

B.2 Time Consumption

Inside a circuit design, despite of several "macros" occupying the margins (see Fig.5a for example), most *cells* are not big enough to appear in multiple windows in Fig.7, and they are normally distributed to the windows to avoid placement conflicts [2]. Therefore, we assume that the average number of *cells* appear in a window is $|\mathcal{V}|/|\mathcal{W}|$. The time consumption of constructing $\mathcal{E}_G^*$ is $4|\mathcal{W}| \cdot (\frac{|\mathcal{V}|}{|\mathcal{W}|} \cdot c) = 4c|\mathcal{V}| = O(|\mathcal{V}|)$.

Moreover, the time costs of constructing $\mathcal{V}, \mathcal{U}, \mathcal{E}_T$ are $O(|\mathcal{V}|), O(|\mathcal{U}|), O(|\mathcal{P}|)$ respectively, so we can produce circuit graph $\mathcal{G}$ in $O(|\mathcal{V}| + |\mathcal{U}| + |\mathcal{P}|)$.

---

[4] $|\mathcal{W}|$ is the average # of windows after splitting the circuit.

C Parameter Sensitivity Experiment

Table 8: Congestion prediction result in placement stage under different window size (w_x, w_y)

(w_x, w_y)	Time (s/epoch)	Cell-level			Grid-level		
		pearson	spearman	kendall	pearson	spearman	kendall
(8,10)	28.46	**0.889**	0.721	0.584	0.692	0.742	0.549
(16,20)	27.85	**0.889**	**0.729**	**0.591**	0.694	0.740	0.547
(32,40)	27.07	0.887	0.714	0.575	0.697	**0.770**	**0.577**
(64,80)	23.96	0.888	0.717	0.578	**0.698**	0.762	0.570
(128,160)	25.06	0.888	0.724	0.584	0.694	0.758	0.564

Table 9: Congestion prediction result in placement stage under different link capacity c

c	Time (s/epoch)	Cell-level			Grid-level		
		pearson	spearman	kendall	pearson	spearman	kendall
2	23.97	**0.889**	0.724	0.586	0.695	0.742	0.549
5	27.07	0.887	0.714	0.575	**0.697**	**0.770**	**0.577**
10	29.15	0.881	0.707	0.569	0.694	0.762	0.566
20	30.96	**0.889**	**0.725**	**0.587**	**0.697**	0.745	0.552

We test the sensitivity of window size (w_x, w_y) and link capacity c, as it shows in Tab.8 and Tab.9. The results indicate that the choice of these hyper-parameters has little influence on the model's function, so the robustness of Circuit GNN is claimed.

D Model Sensitivity Experiment

D.1 Message Function

The choice of $\Phi_{msg}^{\mathcal{V}\xrightarrow{\varepsilon_T}\mathcal{U}}$ and $\Phi_{msg}^{\mathcal{U}\xrightarrow{\varepsilon_T}\mathcal{V}}$ On the one hand, there are usually more geom-edges than topo-edges in Circuit Graph (3.4M geom-edges and 1.9M topo-edges in *superblue19*), so we use edge-weight summation rather than inner product, which is $F_{\mathcal{U}}$ (hidden dimension of net) times more expansive in computation. On the other hand, it is also reasonable for geom-edges to use edge-weight summation because geometrically closer cells have a stronger relationship. Still, we test the performance when topo-edges use edge-weight summation (**topo. e.**) or geom-edges use inner product (**geom. i.**):

Table 10: Result of exchanging topological and geometrical message functions.

Baseline	Time (s/epoch)	Node-level			Grid-level		
		pearson	spearman	kendall	pearson	spearman	kendall
topo. e.	25.35	0.886	0.707	0.570	0.694	0.743	0.552
geom. i.	37.71	0.886	**0.717**	**0.579**	0.689	0.734	0.542
Ours	27.07	**0.887**	0.714	0.575	**0.697**	**0.770**	**0.577**

D.2 Information Fusing Strategy

We hope to keep most of the informative values when fusing the topological and geometrical information, while sum-pooling and mean-pooling may revise them. Concatenation is not considered because we hope to keep the same hidden dimension in each layer. The results below show that

using sum-pooling and mean-pooling has worse spearman & kendall (Grid-level) and only marginal improvement in other metrics:

Table 11: Result of different information fusing functions.

Baseline	Time (s/epoch)	Node-level			Grid-level		
		pearson	spearman	kendall	pearson	spearman	kendall
Ours (sum pool)	29.00	0.887	**0.717**	**0.580**	**0.699**	0.756	0.564
Ours (mean pool)	29.38	**0.888**	0.715	0.577	0.697	0.755	0.563
Ours	27.07	0.887	0.714	0.575	0.697	**0.770**	**0.577**

D.3 Readout Representation

We concatenate the raw features to enrich the representations. The results below show that excluding raw features only causes a marginal performance drop:

Table 12: Result of removing raw features in readout representation.

Baseline	Time (s/epoch)	Node-level			Grid-level		
		pearson	spearman	kendall	pearson	spearman	kendall
Ours (w/o. raw feat.)	27.45	**0.892**	0.713	0.574	0.697	0.759	0.567
Ours	27.07	0.887	**0.714**	**0.575**	**0.697**	**0.770**	**0.577**

D.4 Position Encoding

Directly encoding the cell positions as features leads to very bad generalization because raw 3D positions do not satisfy translation and rotation invariances[28]. Here are the results: (**Ours (pos. encode)** is the modification we made which encodes the cell positions into node features instead of using *geom-edges*.)

Table 13: Result of using direct position encoding and *geom-edges*.

Baseline	Time (s/epoch)	Node-level			Grid-level		
		pearson	spearman	kendall	pearson	spearman	kendall
GAT	13.90	0.777	0.267	0.200	0.215	0.399	0.280
GAT (pos. encode)	16.21	0.777	0.263	0.197	0.210	0.397	0.279
Ours (w/o. geom.)	21.62	0.779	0.289	0.217	0.315	0.468	0.329
Ours (pos. encode)	22.55	0.766	0.328	0.292	0.228	0.475	0.411
Ours	27.07	**0.887**	**0.714**	**0.575**	**0.697**	**0.770**	**0.577**

E Additional Experiment Tables

Table 14: Net wirelength prediction in logic synthesis stage (↓ means "lower is better")

Baseline	Time (s/epcoh)	pearson	spearman	kendall	MAE↓	RMSE↓
MLP	2.16	0.150	0.192	0.096	0.633	0.854
Net[2f]	15.29	0.225	0.362	0.248	**0.606**	0.830
Net[2a]	16.75	0.172	0.227	0.153	0.614	**0.821**
Ours (w/o. geom.)	15.66	**0.484**	**0.547**	**0.418**	0.619	**0.821**

Table 15: Congestion prediction result in placement stage (in precision, recall and F1-score)

Baseline	Time (s/epoch)	Cell-level			Grid-level		
		precision	recall	F1-score	precision	recall	F1-score
GAT (w. geom.)	16.21	0.718	**1.000**	0.836	0.669	**1.000**	0.802
pix2pix	4.46	-	-	-	0.695	0.996	0.814
LHNN	305.47	-	-	-	0.807	0.907	0.855
Ours (w/o. topo.)	21.54	0.876	0.899	0.879	0.865	0.851	0.860
Ours	27.07	**0.884**	0.900	**0.892**	**0.887**	0.857	**0.872**

F   Number of Parameters and Inference Time

The # of parameters and inference time on *superblue19* are listed below:

Table 16: # of parameters and inference time on congestion prediction in logic synthesis stage.

Model	GCN	GraphSAGE	GAT	CongestionNet	Ours (w/o geom.)
# parameter	205K	204K	205K	280K	426K
Inference Time (s)	2.74	2.69	3.18	2.99	3.09

Table 17: # of parameters and inference time on congestion prediction in placement stage.

Model	pix2pix	LHNN	Ours
# parameter	992K	54K	480K
Inference Time (s)	0.35	65.21	4.09

Table 18: # of parameters and inference time on net length prediction in logic synthesis stage.

Model	MLP	Net^{2f}	Net^{2a}	Ours (w/o geom.)
# parameter	4K	12K	37K	642K
Inference Time (s)	0.45	0.69	1.35	1.61

Table 19: # of parameters and inference time on net length prediction in placement stage.

Model	MLP	Net^{2f}	Net^{2a}	LHNN	Ours
# parameter	4K	13K	39K	54K	694K
Inference Time (s)	0.6	1.13	2.39	21.41	3.51

Note that it takes 232 seconds for DREAMPlace to produce placement result of *superblue19* and 53 seconds to output congestion and net length with tools like NCTUgr.

G   Transfer Experiment

To further evaluate the representativeness of extracted GNN features, we first train Circuit GNN/LHNN with Congestion Prediction task and then evaluate/fine-tune them with Net Length Prediction. Here are the experimental settings:

- For the **evaluation** setting, a different readout module is trained from scratch, but GNN's parameters are fixed.

- For the **fine-tuning** setting, a different readout module is trained from scratch, and GNN's parameters are fine-tuned at the same time.
- For **evaluation & fine-tuning**, LHNN and Ours are only trained for 1/5 epochs of default setting, to show the transferability of learned features.

Table 20: Transfer experiment from congestion prediction to net length prediction. Results are evaluated in Grid-level.

Baseline	Time (s/epoch)	pearson	spearman	kendall
MLP	2.22	0.493	0.547	0.415
LHNN (evaluate)	192.45	0.689	0.715	0.563
Ours (evaluate)	9.55	**0.799**	**0.811**	**0.622**
LHNN (fine-tune)	248.96	0.805	0.794	0.612
Ours (fine-tune)	14.8	**0.842**	**0.829**	**0.639**
LHNN	260	0.801	0.796	0.603
Ours	14.79	0.848	0.835	0.646

The results show that the knowledge Circuit GNN learns from Congestion Prediction can be easily transferred to another task (no matter for direct use or fine-tuning), while LHNN is weak in transferability.