A time-resolved theory of information encoding in recurrent neural networks

Abstract

Mammalian brains process information by the collective dynamics of a deeply layered structure of recurrent networks. Information transmission in neural circuits depends on how well time-varying stimuli are encoded by neural populations. A dynamic balance of externally incoming currents by strong recurrent inhibition was previously proposed as a mechanism to accurately and robustly encode the information in a time-varying stimulus, but a full theory was missing. Here, we develop a non-stationary dynamic mean-field theory that transparently explains how a tight balance of excitatory currents by recurrent inhibition improves information encoding. We demonstrate that the mutual information rate of a time-varying input increases linearly with the tightness of balance, both in the presence of additive noise and with recurrently generated chaotic network fluctuations. We corroborated our findings in numerical experiments and demonstrated that recurrent networks with positive firing rates trained to transmit a time-varying stimulus generically use recurrent inhibition to increase the information rate. We also found that networks trained to transmit multiple independent time-varying signals spontaneously form multiple local inhibitory clusters, one for each input channel. Our findings suggest that feedforward excitatory input and local recurrent inhibition–as observed in many biological circuits–is a generic circuit motif for encoding and transmitting time-varying information in recurrent neural circuits.

1 Introduction

How fast and reliable time-varying incoming stimuli are encoded in the population activity of recurrent neural networks constrains information transmission between local circuits and inter-areal communication. While the brain has to respond rapidly and reliably to changes in the world, the timescales of synapses can be slow, single neurons exhibit Poisson-like temporally irregular dynamics and dynamic instability of recurrent neural circuit dynamics can be a source of chaotic variability [1, 2, 3, 4, 5].

Excitation and inhibition in biological neural networks is usually conveyed by different types of neurons with a predominance of recurrent inhibitory feedback, a property known as 'inhibition dominance' [6, 7, 8, 9]. In networks with very strong recurrent inhibition, where recurrent weights are scaled as $1/\sqrt{N}$ with network size N), a dynamic balance arises between excitatory currents and recurrent inhibitory currents that was originally proposed as a robust mechanism to describe the emergence of asynchronous irregular activity[1]. Networks of binary neurons in such a *balanced state* track time-varying signals [2]. While subsequent experimental work found evidence for a dynamic balance of input currents, the 'tightness' or 'looseness' of such a dynamic balance in cortical circuits, as well as the computational implications, are a question of active scientific debate [10]. 'Loosely' balanced networks, where excitatory and inhibitory currents are respectively $\mathcal{O}(1)$ compared to the

distance from reset to threshold, can respond in their population firing rate nonlinearly to external inputs, which was argued to be favorable for sensory processing [7].'Tight balance' refers to a more precise tracking of total excitatory and total inhibitory input currents in time originating from excitatory and inhibitory currents that are respectively $\mathcal{O}\left(\sqrt{N}\right)$ or larger compared to the distance from reset to threshold [10, 1, 2]. Such 'tight balance' was also studied in a series of works that arrived at spiking balanced networks from a normative predictive coding ansatz [11, 12, 13, 14]. It is important to investigate how such biological features such as 'tightness of balance' shape the reliability of population response to external stimuli. How the dynamic tracking of time-dependent inputs described in binary networks [1, 2] extends to firing rate models and how it affects the information encoding of time-varying stimuli in the presence of chaos and noise has not yet been addressed. Previous dynamic mean-field theory (DMFT) approaches to input-driven rate networks assumed that the mean of the external inputs across neurons does not depend on time, which facilitates DMFT [15, 16, 17, 14], but prohibits to investigate encoding of dynamic stimuli in the population firing rate. To address this gap, we study how a time-varying stimulus is encoded in the population rate of an inhibition-dominated rate network under the influence of additive noise and chaos.

We show that the accuracy of neuronal population encoding improves in more tightly balanced recurrent networks because of a speedup of the effective timescale of the population mean dynamics. Conventional methods of dynamic mean-field theory [18, 19, 20, 17] are not adequate to capture the effects of a time-varying common input. Therefore, we use a dynamic mean-field theory that is non-stationary, meaning that the order parameters are time-dependent. Beyond a similar recent approach [21], our theory can treat both time-varying common and independent external input, which is crucial to analytically treat a signal-to-noise ratio that constrains population coding. This novel technique accurately captures the statistics of the input-driven networks. Specifically, we calculate the cross-spectral density between input and output and the power spectral density of the population firing rate. Together with the knowledge of the input statistics, this allows us to calculate the mutual information between stimulus and population rate in the Gaussian channel approximation based on the spectral coherence.

We examine how the frequency-response and mutual information rate depends on the tightness of balance, added noise, network chaos, and statistics of the input stimulus, using both theory and simulation. All the analytic results match those from network simulations. We show that recurrent networks that are trained on tracking a time-dependent stimulus develop strong recurrent inhibition and strong positive input weights, a fingerprint of the balanced state. Concomitantly, the mutual information rate between their network readout and the stimulus increases, as predicted by our theory. This indicates that a more tightly balanced state is a generic solution to reliably transmitting a time-varying input in the presence of noise or chaos. Lastly, we find that networks trained on simultaneously transmitting multiple independent time-varying stimuli spontaneously break up into weakly connected subnetworks with strong local inhibition.

Our findings have important implications for information encoding in RNNs and for understanding how neural network architecture design shapes noise-robustness and information encoding.

The main contributions are the following:

- A novel non-stationary mean-field theory describing the dynamics of balanced RNNs driven by an time-varying input signal and noise (section 2 and appendix A).

- A transparent mathematical link between ti balance and the mutual information rate between a scalar input signal and the population rate (section 4 and appendix D).

- A frequency-resolved mutual information rate analysis showing the effects of noise and chaos (section 3 and appendix C).

- Numerical network simulations showing an excellent agreement with the theoretical results

- Training results indicating that vanilla networks trained on transmitting high-frequency signals become more tightly balanced throughout training (section 5 and appendix E).

- Additional training results showing that networks trained to transmit multiple independent signal exhibit a spontaneous symmetry breaking into weakly connected subnetworks with strong local inhibition (section 6 and appendix I).

- Additional training results with a nonlinear task (section 7), different activation function (appendix H) and excitatory-inhibitory architecture (G) demonstrate generality of our results.

2 Population coding in recurrent networks

We study how well a time-varying scalar input $I(t)$ is encoded in the mean population firing rate $\nu(t) = \frac{1}{N} \sum_i \phi(h_i(t))$ of a recurrent network of N nonlinear rate units ('neurons') that obey

$$\tau \frac{\mathrm{d}h_i}{\mathrm{d}t} = -h_i + \sum_{j=1}^{N} J_{ij} \phi(h_j) + bI(t) + \xi_i(t),\tag{1}$$

with the coupling weights $J_{ij} = -bJ_0/N + \tilde{J}_{ij}$. The $\tilde{J}_{ij}$ are drawn independently from a Gaussian distribution with zero mean and variance g^2/N, where g is a gain parameter that controls the heterogeneity of weights. We use a threshold-linear transfer function $\phi(x) = \max(x, 0)$. The

Figure 1: **Mutual information rate between input and population response grows with tightness of balance A)** Each neuron in the recurrent network receives an identical input stimulus $I(t)$ and additive Gaussian white noise $\xi_i(t)$ that is independent across neurons. **B)** For small values of b ('loosely' balanced networks), the population response only tracks slow fluctuations of the stimulus ($b = 10$). **C)** For large values of b ('tightly' balanced networks), the population response also tracks fast fluctuations of the stimulus ($b = 100$). **D)** The spectral coherence for different values of balance b, direct numerical simulations (shaded line) and mean-field theory (dashed line) superimposed. (For color-code, see points in figure 1E). **E)** The Mutual information rate in Gaussian channel approximation based on spectral coherence, mean-field theory (dashed line) and direct numerical simulation (squares). Model parameters: $N = 4096$, $g = 2$, $\Delta t = 1/2^{10}\tau$, $t_{\mathrm{sim}} = 2^6\tau$, $I_0 = J_0 = 1$, $\tau_S = 1.0\tau$, $\sigma = 0.1$, $I_1 = 0.1$.

external input contains a signal component $I(t)$, which is identical across neurons, and a noise term $\xi_i(t)$, which is independent across neurons. For concreteness, we choose ξ_i to be independent additive white Gaussian noise processes (AWGN) with autocorrelation function $\langle \xi_i(t)\xi_i(t+t')\rangle = \tau\sigma^2\delta(t')$ and the signal $I(t)$ to be an Ornstein-Uhlenbeck process given by

$$\tau_S \frac{\mathrm{d}I}{\mathrm{d}t}(t) = -I(t) + I_0 + \xi_S(t).\tag{2}$$

The amplitude of the AWGN $\xi_S(t)$ driving the time-varying part is denoted by I_1. The parameter b multiplies both external input and recurrent coupling strength and thus regulates the tightness of balance [14, 10, 21]. For firing-rate networks, the ability to track time-dependent input strongly

depends on the strength of balance b (Fig 1). For loosely balanced network ($b = 1$) (Fig 1B), the network population rate only tracks slow fluctuations of the input signal. In contrast, for tightly balance networks (Fig 1C), the population firing rate also tracks fast input fluctuations. To understand how this tracking arises in the model, it is useful to rewrite Eq 1 by decomposing $h_i = m + \tilde{h}_i$ into a common component and residual fluctuations. With $J_{ij} = -bJ_0/N + \tilde{J}_{ij}$, this results in

$$\tau \frac{\mathrm{d}m}{\mathrm{d}t} = -m - bJ_0\nu(t) + bI(t)\,, \tag{3a}$$

$$\tau \frac{\mathrm{d}\tilde{h}_i}{\mathrm{d}t} = -\tilde{h}_i + \sum_j \tilde{J}_{ij}\phi\left(h_j\right) + \xi_i(t)\,. \tag{3b}$$

Here, the signal $I(t)$ enters the expression for m, because it is identical across all neurons. It thus directly impacts the mean population rate $\nu(t)$ and recruits, through the negative mean coupling $-bJ_0$, strong recurrent feedback $-bJ_0\nu(t)$ that is anti-correlated with the input and cancels most of the common external input $I(t)$. Rewriting Eq 3a by solving for $\nu(t)$ gives

$$\nu(t) = \frac{I(t)}{J_0} + \frac{1}{bJ_0}\left(-\tau\frac{\mathrm{d}m}{\mathrm{d}t} - m\right)\,. \tag{4}$$

This equation is commonly referred to as the 'balance equation' [2, 19, 20] when the input is not time-dependent. For large b, the population rate approaches $\nu(t) = I(t)/J_0$, which indicates a linear relationship between input and population rate for tightly balanced networks as pointed out before in binary networks [1, 2]. On the other hand, the noise ξ_i affects only the residual fluctuations $\tilde{h}_i$.

As the balance parameter b is increased, the effective timescale of the dynamics of m becomes τ/b, as can be seen by dividing Eq 3a by b. This leads to faster and more precise tracking. In contrast, the timescale of the equation for $\tilde{h}_i$ is unchanged by b. Of course, the two equations for m and $\tilde{h}_i$ are interdependent via $\phi(h_i) = \phi(m + \tilde{h}_i)$, so for a complete treatment, the joint dynamics of m and $\tilde{h}_i$ has to be solved. In appendix A we present a non-stationary dynamic mean-field theory of temporal population coding.

3 Frequency-dependent signal encoding in the population response

Figure 2: **Frequency-resolved information rate reveals different effects of white noise and chaos A)** The normalized dynamic gain for different values of balance b, direct numerical simulations (shaded line) and mean-field theory (dashed line) superimposed for $g = 0$. Note that large values of b the dynamic gain shows an improved encoding bandwidth (For color-code, see figure 2C). **B)** The mutual information rate density in the Gaussian channel approximation based on spectral coherence, mean-field theory (dashed line) and direct numerical simulation (transparent full lines) for $g = 0$. **C)** Same as **A)** but for $g = 2$. **D)** Same as **B)** but for $g = 2$. The recurrent residual fluctuations in $\tilde{h}_i$ arising from $g > 0$ reduce the information rate for low-frequency information. For larger values of b ('tight balance'), recurrent fluctuations have weaker effect on low-frequency information rate, because of tracking of network fluctuations. Model parameters: $N = 4096$, $g = 0$ for **A)** and **B)**. $g = 2$ for **C)** and **D)**, $\Delta t = 1/2^{10}\tau$, $t_{\text{sim}} = 2^6\tau$, $I_0 = J_0 = 1$, $\tau_S = 1.0\tau$, $\sigma = 0.1$, $I_1 = 0.1$.

124 We systematically analyze how different input frequencies are encoded in the population response and
125 observe that the transmission of high frequencies stimuli is improved for large b ('tightly balanced'
126 regime) (Figure 2A and C). We calculate the dynamic gain $G(f) = |S_{I\nu}|/|S_{II}|$ of the recurrent
127 network both in direct numerical simulations and with the non-stationary DMFT. $S_{I\nu}$ is the Fourier
128 transformation of the input-output cross-correlation function between $I(t)$ and $\nu(t)$. S_{II} is the power
129 spectral density of the stimulus $I(t)$. The dynamic gain quantifies how in linear response a variation
130 in the input signal $I(t)$ affects the population rate $\nu(t)$ and is a standard analysis for characterizing
131 the response properties of individual cells [22].

132 We calculate $G(f)$ both using both direct numerical network simulations and dynamic mean-field
133 theory. (For details of the spectral analysis, see appendix C.) We observe that increasing b boosts
134 the dynamic gain for high frequencies (Figure 2A and C for $g = 0$ and $g = 2$). This is a direct
135 consequence of the speedup of the dynamics of the mean discussed above. Thus, as the network
136 becomes more tightly balanced, high-frequency signals can be encoded and transmitted more reliably.
137 To quantify the improved information encoding we turn to an information-theoretic analysis next.

4 Mutual information rate between time-varying stimulus and population response

140 With information theory, we can treat the recurrent neural network as a noisy communication channel,
141 transforming a signal embedded in a noisy current into a population rate that can be read out by
142 another population. We use a Gaussian channel approximation to the mutual information rate
143 between input current $I(t)$ and output mean population rate $\nu(t)$ based on the spectral coherence
144 [23, 24]:$R_{\mathrm{lb}}(I, \nu) = - \int_0^{f_{\mathrm{cutoff}}} df \log_2 (1 - C_{I\nu}(f))$, where $C_{I\nu}(f)$ denotes the magnitude squared
145 spectral coherence. The spectral coherence is the frequency-domain analog of the correlation and
146 measures the linear relationship between frequency components of input and output signal. Its
147 magnitude square is $C_{I\nu}(f) = \frac{|S_{I\nu}(f)|^2}{S_{II}(f)S_{\nu\nu}(f)}$. It is normalized by the power spectrum $S_{II}(f)$ of the
148 input signal (an OU process) and the power spectrum $S_{\nu\nu}(f)$ of the population rate $\nu(t)$.

149 We calculated the spectral coherence in two independent ways: firstly based on the non-stationary
150 DMFT and secondly based on direct numerical simulations. The dependence of $C_{I\nu}(f)$ on the
151 tightness of balance b is depicted in Figure 1D. DMFT and direct numerical simulations with additive
152 band-limited white noise $\xi(t)$ are in excellent agreement.

153 We find that the mutual information rate grows approximately linear with b (see Figure 1E). It saturates
154 for large b; the saturation level is determined by the band limit of the incoming signal (see figure in
155 appendix C). We use the high-frequency behavior and low-frequency limit to derive an analytical
156 approximation of the linear scaling (see appendix D). We conclude that the mutual information rate
157 scales approximately linearly with the tightness of balance b for a sufficiently high band limit. Where
158 does this linear scaling comes from? The reason is that the b determines the cutoff frequency, up
159 to which the network transmits information faithfully. Contributions from frequencies beyond this
160 cutoff are negligible to first order. This conclusion is not restricted to networks of rectified linear
161 units, a similar reasoning holds also e.g. for the threshold-power-law nonlinearities and other models
162 with non-negative firing rates (See e.g. [19, 20] for balanced rate networks with other input-output
163 transfer functions).

164 Inspired by recent work on the frequency-resolved information encoding rate in single cells [25], we
165 analyze the population rate of RNNs and study how the encoding of different frequency components
166 of the input signal depends on the tightness of balance b, the strength of added noise σ and the
167 heterogeneity of the recurrent weights g.

168 For that, we considered the mutual information rate density $r(f)$, which gives a frequency-resolved
169 quantification of the information encoding rate (See for details of definition [25]):

$$r_{\mathrm{lb}}(f) = - \log_2 (1 - C_{I\nu}(f)) \tag{5}$$

170 We observe that more tightly balanced networks can transmit more high-frequency information
171 (Figure 2B and D for both $g = 0$ and $g = 2$). Overall, the information rate for more tightly
172 balanced networks is increased because of the boost of the signal-to-noise ratio coming from the
173 fact that the signal $I(t)$ is scaled by b, while the noise is independent of b. The above-described
174 frequency-dependent effect comes on top of that.

For recurrent networks with weight heterogeneity ($g > 0$), there are additional slow residual fluctuations in $\tilde{h}$ that act as an additional source of variability, which leads to a dip in the mutual information density for low frequencies (Compare Figure 2B for $g = 0$ and D for $g = 2$). These low-frequency fluctuations have a different effect than additive Gaussian white noise (see also [14]).

For more tightly balanced networks (larger b), the residual fluctuations do not impair information encoding (see darker green lines in figure 2B), because they are canceled. A related phenomenon was observed in densely connected recurrent binary networks ([26, 27]). That variance originating from weight heterogeneity ($g > 0$) is more effectively reduced by balanced networks as a function of b compared to variance originating from added Gaussian white noise σ was already observed in rate networks with static input [14].

5 Training networks on auto-encoding results in tight balance

Figure 3: **RNNs trained on tracking time-varying input become more tightly balanced throughout training. A)** vanilla RNNs are trained to approximate a time-varying external input $I(t)$ by linear readout $\hat{I}(t) = 1/N \sum_i w_i^{\text{out}} \phi(h_i)$, by minimizing the mean squared loss $l = \int |\hat{I}(t) - I(t)|^2 \, dt$. **B)** The eigenvalue spectrum of the dynamics linearized at the fixed point without time-dependent input indicates that during training, an eigenmode with a strongly negative real part emerges. **C)** The networks become more balanced throughout training. The tightness of balanced is quantified here by the magnitude of the mean recurrent coupling $\hat{b} = |1/N \sum_i \sum_j J_{ij}|$. Inset shows that average of the external input weights $\frac{1}{N} \sum_i w_i^{\text{in}}$ becomes more positive over epochs (green line) while the average row sum of the recurrent weights (black line) become more negative. **D)** The loss across learning epochs. **E)** The normalized dynamic gain $G(f)$ before and after training indicates improving high-frequency encoding as the network becomes more tightly balanced. **F** The mutual information between the time-varying external input and the linear readout as a function of training epochs. Information rate increases throughout training. Model parameters at initialization: $N = 100$, $g = \sqrt{2}$, $\Delta t = 0.01\tau$, $t_{\text{sim}} = 1000\tau$, $b = 1$, $I_0 = J_0 = 1$, $\tau_S = 0.1$, $\sigma = 1$, epochs$= 10^5$.

We corroborate the theoretical finding that the tightness of balance has a crucial role in information encoding in numerical experiments in trained recurrent networks, which demonstrates the generality of our findings. For that, we train recurrent networks on an auto-encoder task (Fig 3). We initialize small-sized recurrent networks ($N = 100$) that follow the dynamics of Eq. 1 in a loosely balanced state, with recurrent weights drawn i.i.d. from a Gaussian $J_{ij} \sim \mathcal{N}(-1/N, g^2/N)$ and input weights w_i^{in} and output weights w_i^{out} are drawn from a Gaussian distribution with a positive mean. This initialization would correspond to $b = 1$ in our theoretically studied model (Eq. 1). The network receives the time-varying input signal $I_i(t) = w_i^{\text{in}} I(t)$, so in contrast to our theoretical setup, in

principle each neuron can receive the input signal $I(t)$ with a different scale w_i^{in}. We then trained input weights w^{in}, output weights w^{out} and recurrent weights J_{ij} using backpropagation-through-time with the ADAM optimizer with standard hyperparameters (see appendix E for additional details on training setup and additional controls of training results). We minimize the mean squared loss $l = \int |\hat{I}(t) - I(t)|^2 \, \mathrm{d}t$ between a time-varying input signal $I(t)$ and a linear readout of the recurrent network activity $\hat{I}(t) = 1/N \sum_i w_i^{\text{out}} \phi(h_i(t))$.

Initially, the network only poorly tracks the time-varying input signal, as theoretically expected for small b. However, we find that the network learns to track the time-varying input signal (Figure 3A), as the test error falls throughout training epochs (Figure 3D). Analyzing the eigenvalues of the trained network, we observe an outlier eigenvalue with a very negative real part after training that indicates an emerging strongly negative mode implementing the fast tracking (Figure 3B). This is confirmed by measuring the empirical tightness of balance $\hat{b}$ in the connectivity, which we quantify simply by the absolute value of the mean of the sum of incoming recurrent weights into each neuron $\hat{b} = |1/N \sum_i \sum_j J_{ij}|$. This definition of $\hat{b}$ is consistent with the definition of b in our theory above. We find that the trained networks that are initialized with $b = 1$ become progressively more tightly balanced (Figure 3C) over training epochs, as can be seen by a growing $\hat{b}$ and by an improving high-frequency encoding (Figure 3E). We prematurely stop after 100000 training epochs to avoid numerical instabilities for very tightly balanced networks. We note that the average of the external input weights $\frac{1}{N} \sum_i w_i^{\text{in}}$ becomes more positive over training epochs (Figure 3C inset, green line) while the average row sum of the recurrent weights (Figure 3C inset, black line) become more negative.

Consistent with our theory, we find that the mutual information rate (Gaussian channel approximations) grows over training epochs as the network becomes more tightly balanced (Fig 3F). Note that we did not train the network to maximize the mutual information rate, but to minimize the mean-squared error between target output and actual output, but the two are closely related [28]. We note that this tracking does not rely on the threshold-linear input-output function, in fact, we also successfully trained sigmoid (Fig. 9), linear (Fig. 10) and threshold-quadratic input-output function ϕ (Fig. 11) (see appendix H for additional results).

6 Training on multiple inputs results in tightly balanced subnetworks

We note that networks trained to simultaneously track multiple input Ornstein-Uhlenbeck signals by a linear readout exhibit a spontaneous symmetry breaking into weakly connected subnetworks with strong local inhibition (Fig. 4 and see appendix F for results on training on multiple signals). We note that this finding is not limited to training networks on two independent OU-processes; strongly inhibitory coupled subnetworks also emerge when training on more OU-processes (See Figure 4F for the resulting connectivity of a network trained on 3 OU-processes). For networks trained on multiple time-varying stimuli, we observed an interesting training dynamics. First, they develop a single global inhibitory mode (figure 7), similar to networks trained to track a single OU-signal. After some time, we observe the emergence of a second outlier eigenvalue. Concomitantly, the network breaks into two inhibitory subnetworks and the readouts start to track both OU-input signals independently.

7 Training on nontrivial computation results in tightly balanced network

Finally, we demonstrate the generality of our findings on two nontrivial tasks where the RNN not only copies a time-varying input but performs a computation on the input streams.

Firstly, we trained recurrent networks that receive two time-varying input signals to output a continuous extension of the XOR function $f(I_1(t), I_2(t)) = |I_1(t) - I_2(t)|$, which satisfies for $I_1, I_2 \in 0, 1$ the binary XOR function (Fig 4D). Consistent with our theory, we observe that the networks developed an outlier eigenvalue with strongly negative real part (Fig 4A). K-means clustering of the recurrent weight matrix revealed that the RNNs developed tightly balanced subnetworks throughout training (Fig 4E). See appendix F for further details.

Secondly, we trained RNNs to compute a linear transformation of time-varying vector of stochastic processes $y_i(t) = \sum_j A_{ij} I_j(t)$ at every moment in time. We observed that the RNNs develop a number of negative outlier eigenvalues and concomitantly the same number of tightly balanced

Figure 4: **Training on multiple signals and nonlinear task yields balanced subnetworks.** **A)** RNNs are trained to approximate two time-varying external inputs $I_i(t)$ by two linear readouts $\hat{I}_i(t) = 1/N \sum_j w_{ij}^{\text{out}} \phi(h_j)$, by minimizing the mean squared loss $l = \sum_i \int |\hat{I}_i(t) - I_i(t)|^2 \, dt$. **B)** Two eigenmodes with a strongly negative real part emerge. **C)** An example random recurrent network J_{ij} depicted at initialization. Note that input and output weights are also random. **D)** Same example network after trained on two independent OU-processes. The network spontaneously breaks into two balanced subnetworks that have strong local inhibition but weak connectivity in between throughout training. Clustered by k-means clustering on the input weights. **E)** Same RNNs trained to calculate on the two time-varying external inputs $I_i(t)$ the continuous-time XOR (the function $f(I_1(t), I_2(t)) = |I_1(t) - I_2(t)|$ (Green dashed line is input, black dotted line is target output $f(I_1(t), I_2(t))$, red line is actual output). **F)** For XOR one eigenmode with a strongly negative real part emerges. **G)** Recurrent weight matrix after training on XOR shows balanced subnetworks that have strong local inhibition. Clustering by k-means clustering of input weights. **F)** An example recurrent network J_{ij} that is trained to track 3 OU-processes develops three balanced subnetworks. Model parameters at initialization: $N = 100$, $g = \sqrt{2}$, $\Delta t = 0.2\tau$, $t_{\text{sim}} = 100\tau$, $b = 1$, $I_0 = J_0 = 1$, $\tau_S = 0.1$, $\sigma = 1$, epochs$= 10^5$.

inhibitory subnetworks that corresponds to the rank of the linear input-output transformation A (See Fig 12 and appendix F for further details).

8   Limitations

For mathematical tractability, we considered firing rate networks here, but for more detailed neuron models, other biophysical features shape the information encoding rate. For example, in spiking neuron models, fluctuating background input can enhance the high-frequency encoding [29]. Moreover, the spike generation mechanism [30, 31, 32, 33, 34, 35], the synaptic dynamics ([36, 37]) and other latent variables (e.g. adaptation [38]) shape the frequency-response. It remains an important future work to extend the work here by such contributions. Moreover, moving beyond point-neurons, the shape of the dendritic tree can also affect the frequency response[35].While we show that the dynamics of RNNs trained on several linear and nonlinear tasks is consistent with our DMFT, it remains an important challenge to consider tasks with more complex temporal structure, e.g. involving memory, where the task dynamics might interfere with the tightness of balance. Finally, our theory becomes exact only in the limit of large network size, and it is important to also consider finite-size effects. For finite network size, both noise and chaotic fluctuations also contribute to fluctuations of the mean m, which are also recurrently canceled.

9 Discussion

We show how a tight balance of excitatory currents by recurrent inhibition improves information encoding of a time-varying signal. We demonstrate that the mutual information rate of a time-varying signal increases linearly with the tightness of balance, both in the presence of additive noise and with recurrent chaotic network fluctuations. A non-stationary dynamic mean-field theory reveals a separation of timescale between the mean currents and the timescale of residual fluctuations. The mean dynamics become linearly faster with the tightness of balanced and enable reliable encoding of time-varying signals. In contrast, the timescale of the chaotic dynamics in the residual fluctuations are largely unaffected by the tightness of balance. We find that networks become more robust to deteriorating effects of fluctuations from noise and chaos as the network becomes more tightly balanced.

Our study is relevant in the recent debate on the functional implications of how tightly excitatory currents are tracked by recurrent inhibition [26, 27, 7, 10, 13, 14]. We address this question by building a bridge from information-theoretic measures of information encoding that were previously used in neuroscience mostly in sensory systems [39, 40, 41, 23, 24] to dynamic mean-field descriptions of recurrent network dynamics that were previously used to describe the often chaotic dynamics of recurrent rate networks [18, 19, 20, 16, 42, 17, 43, 14].

Besides the implications on information encoding of more loosely or more tightly balanced networks, of course also biophysical, energetic, and evolutionary constraints should be considered. Biological networks can naturally not be arbitrarily tight balanced, which would require arbitrary large synaptic currents. Very tight balance might also be questionable for energetic reasons, as was asked previously, "Why should the cortex simultaneously push on the accelerator and on the brake?" [44]. However, such biophysical and energetic constraints may be better addressed in biophysically more detailed models.

We found that training networks on tracking a time-dependent signal by a linear readout by minimizing the squared error make them more tightly balanced, as reflected in more negative mean recurrent weights and more positive feedforward input weights. Moreover, the training also increased the mutual information rate between the input signal and linear readout. This is consistent with our theoretical result. Furthermore, the fact that training arrives at a tightly balanced solution may suggest that this is a typical solution for a network. It is an interesting question when such balanced solutions will emerge with biologically plausible learning rules [45, 46, 47, 48])

The dynamic cancellation of time-varying input through recurrent inhibitory feedback has been previously studied in balanced networks with binary [2, 26, 27] and spiking neurons [49, 50]. Chaos in balanced firing-rate networks was studied previously [19, 20, 51, 17], but the dynamic cancellation of correlated input and its implications on information encoding in rate networks were not investigated, nor were the implications for training such networks in a machine learning setup with backpropagation through time. It would be interesting to extend our mean-field analysis to rate networks with pre-existing low-rank structures on top of the random structure [52, 53, 54, 55].

The underlying mechanisms of tracking of time-varying input we analyze here are not specific to fully-connected threshold-linear RNNs driven by Ornstein-Uhlenbeck signals with additive Gaussian white noise, which we merely chose for the sake of simplicity and analytical tractability. Rate networks with other non-negative input-output transfer functions exhibit a qualitatively similar dynamic tracking in the tightly balanced regime. Moreover, the mechanism of tracking described here is tightly related to balanced predictive coding networks [13, 14].

A testable hypothesis based on our findings is that changing the tightness of balance, e.g. by pharmacological manipulation or by a genetic knockout that affects net recurrent inhibitory strength (without generating runaway activity or pathological network states), would also affect the high-frequency stimulus encoding and information transmission. Specifically, we predict that stronger effective recurrent weights in conjunction with stronger excitatory inputs would improve both the high-frequency encoding and the mutual information rate between a stimulus and the population response. Conversely, when weakening recurrent inhibition and external input strength, we predict an impaired high-frequency encoding and a lower mutual information rate. Such predictions could not only be tested in vivo, but also by in vitro experiments, where the number of recurrent synapses can be manipulated [56].

References

[1] C. van Vreeswijk and H. Sompolinsky. Chaos in Neuronal Networks with Balanced Excitatory and Inhibitory Activity. *Science*, 274(5293):1724 –1726, December 1996.

[2] C. van Vreeswijk and H. Sompolinsky. Chaotic Balanced State in a Model of Cortical Circuits. *Neural Computation*, 10(6):1321–1371, 1998.

[3] Michael Monteforte and Fred Wolf. Dynamical Entropy Production in Spiking Neuron Networks in the Balanced State. *Physical Review Letters*, 105(26):268104, December 2010.

[4] Guillaume Lajoie, Kevin K. Lin, and Eric Shea-Brown. Chaos and reliability in balanced spiking networks with temporal drive. *Physical Review E*, 87(5):052901, May 2013.

[5] Rainer Engelken, Fred Wolf, and L. F. Abbott. Lyapunov spectra of chaotic recurrent neural networks. *arXiv:2006.02427 [nlin, q-bio]*, June 2020. arXiv: 2006.02427.

[6] Hirofumi Ozeki, Ian M. Finn, Evan S. Schaffer, Kenneth D. Miller, and David Ferster. Inhibitory Stabilization of the Cortical Network Underlies Visual Surround Suppression. *Neuron*, 62(4):578–592, May 2009.

[7] Yashar Ahmadian, Daniel B. Rubin, and Kenneth D. Miller. Analysis of the stabilized supralinear network. *Neural computation*, 25(8):1994–2037, August 2013.

[8] Fred Wolf, Rainer Engelken, Maximilian Puelma-Touzel, Juan Daniel Flórez Weidinger, and Andreas Neef. Dynamical models of cortical circuits. *Current Opinion in Neurobiology*, 25:228–236, April 2014.

[9] Alessandro Sanzeni, Bradley Akitake, Hannah C Goldbach, Caitlin E Leedy, Nicolas Brunel, and Mark H Histed. Inhibition stabilization is a widespread property of cortical networks. *eLife*, 9:e54875, June 2020.

[10] Yashar Ahmadian and Kenneth D. Miller. What is the dynamical regime of cerebral cortex? *Neuron*, 109(21):3373–3391, November 2021.

[11] David GT Barrett, Sophie Denève, and Christian K Machens. Optimal compensation for neuron loss. *eLife*, 5.

[12] Martin Boerlin, Christian K. Machens, and Sophie Denève. Predictive Coding of Dynamical Variables in Balanced Spiking Networks. *PLOS Comput Biol*, 9(11):e1003258, November 2013.

[13] Sophie Denève and Christian K. Machens. Efficient codes and balanced networks. *Nature Neuroscience*, 19(3):375–382, March 2016.

[14] J. Kadmon, J. Timcheck, and S. Ganguli. Predictive coding in balanced neural networks with noise, chaos and delays. *Advances in neural information processing systems*, 33, December 2020.

[15] L. Molgedey, J. Schuchhardt, and H. G. Schuster. Suppressing chaos in neural networks by noise. *Physical Review Letters*, 69(26):3717–3719, December 1992.

[16] Kanaka Rajan, L. F. Abbott, and Haim Sompolinsky. Stimulus-dependent suppression of chaos in recurrent neural networks. *Physical Review E*, 82(1):011903, July 2010.

[17] Jannis Schuecker, Sven Goedeke, and Moritz Helias. Optimal Sequence Memory in Driven Random Networks. *Physical Review X*, 8(4):041029, November 2018.

[18] H. Sompolinsky, A. Crisanti, and H. J. Sommers. Chaos in Random Neural Networks. *Physical Review Letters*, 61(3):259–262, July 1988.

[19] Jonathan Kadmon and Haim Sompolinsky. Transition to Chaos in Random Neuronal Networks. *Physical Review X*, 5(4):041030, November 2015.

[20] Omri Harish and David Hansel. Asynchronous Rate Chaos in Spiking Neuronal Circuits. *PLoS Comput Biol*, 11(7):e1004266, July 2015.

[21] Rainer Engelken, Alessandro Ingrosso, Ramin Khajeh, Sven Goedeke, and L. F. Abbott. Input correlations impede suppression of chaos and learning in balanced rate networks. *arXiv:2201.09916 [cond-mat, physics:nlin, q-bio]*, January 2022. arXiv: 2201.09916.

[22] Matthew H. Higgs and William J. Spain. Conditional Bursting Enhances Resonant Firing in Neocortical Layer 2–3 Pyramidal Neurons. *The Journal of Neuroscience*, 29(5):1285–1299, February 2009.

[23] Fred Rieke, David Warland, Rob de Ruyter van Steveninck, and William Bialek. *Spikes: Exploring the Neural Code*. A Bradford Book, reprint edition edition, June 1999.

[24] W. Bialek, F. Rieke, RR de Ruyter van Steveninck, and D. Warland. Reading a neural code. *Science*, 252(5014):1854–1857, June 1991.

[25] Davide Bernardi and Benjamin Lindner. A frequency-resolved mutual information rate and its application to neural systems. *Journal of Neurophysiology*, 113(5):1342–1357, March 2015.

[26] Alfonso Renart, Jaime de la Rocha, Peter Bartho, Liad Hollender, Néstor Parga, Alex Reyes, and Kenneth D. Harris. The Asynchronous State in Cortical Circuits. *Science*, 327(5965):587–590, January 2010.

[27] Tom Tetzlaff, Moritz Helias, Gaute T. Einevoll, and Markus Diesmann. Decorrelation of Neural-Network Activity by Inhibitory Feedback. *PLOS Comput Biol*, 8(8):e1002596, August 2012.

[28] Dongning Guo, S. Shamai, and S. Verdu. Mutual information and minimum mean-square error in Gaussian channels. *IEEE Transactions on Information Theory*, 51(4):1261–1282, April 2005.

[29] Bruce W. Knight. Dynamics of Encoding in a Population of Neurons. *The Journal of General Physiology*, 59(6):734–766, June 1972.

[30] Nicolas Fourcaud-Trocmé, David Hansel, Carl van Vreeswijk, and Nicolas Brunel. How Spike Generation Mechanisms Determine the Neuronal Response to Fluctuating Inputs. *The Journal of Neuroscience*, 23(37):11628–11640, December 2003.

[31] B. Naundorf, T. Geisel, and F. Wolf. Action Potential Onset Dynamics and the Response Speed of Neuronal Populations. *Journal of Computational Neuroscience*, 18(3):297–309, June 2005.

[32] Wei Wei and Fred Wolf. Spike Onset Dynamics and Response Speed in Neuronal Populations. *Physical Review Letters*, 106(8):088102, February 2011.

[33] Tatjana Tchumatchenko and Fred Wolf. Representation of Dynamical Stimuli in Populations of Threshold Neurons. *PLoS Comput Biol*, 7(10):e1002239, October 2011.

[34] Elinor Lazarov, Melanie Dannemeyer, Barbara Feulner, Jörg Enderlein, Michael J. Gutnick, Fred Wolf, and Andreas Neef. An axon initial segment is required for temporal precision in action potential encoding by neuronal populations. *Science Advances*, 4(11):eaau8621, November 2018.

[35] Chenfei Zhang, David Hofmann, Andreas Neef, and Fred Wolf. Ultrafast population coding and axo-somatic compartmentalization. *PLOS Computational Biology*, 18(1):e1009775, January 2022.

[36] Nicolas Brunel, Frances S. Chance, Nicolas Fourcaud, and L. F. Abbott. Effects of Synaptic Noise and Filtering on the Frequency Response of Spiking Neurons. *Physical Review Letters*, 86(10):2186–2189, March 2001.

[37] Tatjana Tchumatchenko, Aleksey Malyshev, Fred Wolf, and Maxim Volgushev. Ultrafast Population Encoding by Cortical Neurons. *The Journal of Neuroscience*, 31(34):12171 –12179, 2011.

[38] Maximilian Puelma Touzel and Fred Wolf. Complete Firing-Rate Response of Neurons with Complex Intrinsic Dynamics. *PLOS Computational Biology*, 11(12):e1004636, December 2015.

[39] J. H van Hateren and H. P Snippe. Information theoretical evaluation of parametric models of gain control in blowfly photoreceptor cells. *Vision Research*, 41(14):1851–1865, June 2001.

[40] J. H. van Hateren. Processing of natural time series of intensities by the visual system of the blowfly. *Vision Research*, 37(23):3407–3416, December 1997.

[41] J. H. van Hateren, L. Rüttiger, H. Sun, and B. B. Lee. Processing of Natural Temporal Stimuli by Macaque Retinal Ganglion Cells. *The Journal of Neuroscience*, 22(22):9945–9960, November 2002.

[42] M. Stern, H. Sompolinsky, and L. F. Abbott. Dynamics of random neural networks with bistable units. *Physical Review E*, 90(6):062710, December 2014.

[43] Samuel P. Muscinelli, Wulfram Gerstner, and Tilo Schwalger. How single neuron properties shape chaotic dynamics and signal transmission in random neural networks. *PLOS Computational Biology*, 15(6):e1007122, June 2019.

[44] Jeffry S. Isaacson and Massimo Scanziani. How Inhibition Shapes Cortical Activity. *Neuron*, 72(2):231–243, October 2011.

[45] Wieland Brendel, Ralph Bourdoukan, Pietro Vertechi, Christian K. Machens, and Sophie Denève. Learning to represent signals spike by spike. *PLOS Computational Biology*, 16(3):e1007692, March 2020.

[46] L. Bernáez Timón, P. Ekelmans, S. Konrad, A. Nold, and T. Tchumatchenko. Synaptic plasticity controls the emergence of population-wide invariant representations in balanced network models. *Physical Review Research*, 4(1):013162, February 2022.

[47] T. P. Vogels, H. Sprekeler, F. Zenke, C. Clopath, and W. Gerstner. Inhibitory Plasticity Balances Excitation and Inhibition in Sensory Pathways and Memory Networks. *Science*, 334(6062):1569–1573, December 2011.

[48] Pietro Vertechi, Wieland Brendel, and Christian K Machens. Unsupervised learning of an efficient short-term memory network. In *Advances in Neural Information Processing Systems*, volume 27. Curran Associates, Inc., 2014.

[49] Ran Darshan, William E. Wood, Susan Peters, Arthur Leblois, and David Hansel. A canonical neural mechanism for behavioral variability. *Nature Communications*, 8:15415, May 2017.

[50] Robert Rosenbaum, Matthew A. Smith, Adam Kohn, Jonathan E. Rubin, and Brent Doiron. The spatial structure of correlated neuronal variability. *Nature neuroscience*, 20(1):107–114, January 2017.

[51] Francesca Mastrogiuseppe and Srdjan Ostojic. Intrinsically-generated fluctuating activity in excitatory-inhibitory networks. *PLOS Computational Biology*, 13(4):e1005498, April 2017.

[52] Johnatan Aljadeff, Merav Stern, and Tatyana Sharpee. Transition to Chaos in Random Networks with Cell-Type-Specific Connectivity. *Physical Review Letters*, 114(8):088101, February 2015.

[53] Johnatan Aljadeff, David Renfrew, Marina Vegué, and Tatyana O. Sharpee. Low-dimensional dynamics of structured random networks. *Physical Review E*, 93(2):022302, February 2016.

[54] Francesca Mastrogiuseppe and Srdjan Ostojic. Linking Connectivity, Dynamics, and Computations in Low-Rank Recurrent Neural Networks. *Neuron*, 99(3):609–623.e29, August 2018.

[55] Itamar D. Landau and Haim Sompolinsky. Macroscopic fluctuations emerge in balanced networks with incomplete recurrent alignment. *Physical Review Research*, 3(2):023171, June 2021.

[56] Jérémie Barral and Alex D. Reyes. Synaptic scaling rule preserves excitatory-inhibitory balance and salient neuronal network dynamics. *Nature Neuroscience*, 19(12):1690–1696, December 2016.

[57] Andrew M. Saxe, James L. McClelland, and Surya Ganguli. Exact solutions to the nonlinear dynamics of learning in deep linear neural networks. *arXiv:1312.6120 [cond-mat, q-bio, stat]*, December 2013. arXiv: 1312.6120.

A   Non-stationary dynamic mean-field theory with both independent and common input

The core idea of dynamic mean-field theory is that for large N, the distribution of the residual recurrent input for different neurons becomes Gaussian and pairwise uncorrelated, according to the central limit theorem. To this end, we characterize the distribution of the $\tilde{h}_i(t)$ (Eq 3b) by considering the (linear) stochastic dynamics:

$$\tau \frac{\mathrm{d}\tilde{h}(t)}{\mathrm{d}t} = -\tilde{h}(t) + \eta(t) + \xi(t)\,, \tag{6}$$

where $\eta(t)$ is a Gaussian process with mean $\langle \eta(t) \rangle = 0$ and autocorrelation

$$q(t,s) = \langle \eta(t)\eta(s) \rangle = g^2 \langle \phi(m(t) + \tilde{h}(t))\phi(m(s) + \tilde{h}(s)) \rangle\,. \tag{7}$$

Here and in the following, angular brackets denote expectation values over the distribution of the stochastic process $\tilde{h}(t)$, which approximates population averages in the full network. The mean-field estimate for the mean $m(t)$ therefore evolves according to Eq 3a with $\nu(t) = \langle \phi(m(t) + \tilde{h}(t)) \rangle$, the mean-field estimate of the mean population firing rate.

We obtain an expression for the time evolution of the two-time autocorrelation function $c(t,s) = \left\langle \tilde{h}(t)\tilde{h}(s) \right\rangle$, which explicitly depends on two time points. Taking the temporal derivative of $c(t,s)$ with respect to s and using Eq 6, we obtain

$$\tau \frac{\mathrm{d}}{\mathrm{d}s} c(t,s) = -c(t,s) + r(t,s)\,, \tag{8}$$

where $r(t,s) = \left\langle \tilde{h}(t)\left(\eta(s) + \xi(s)\right) \right\rangle$, which we take as an auxiliary function. Taking the temporal derivative of $r(t,s)$ with respect to t and using Eq 6 again, we arrive at

$$\tau \frac{\mathrm{d}}{\mathrm{d}t} r(t,s) = -r(t,s) + q(t,s) + \tau\sigma^2 \delta(t-s)\,, \tag{9}$$

where $q(t,s) = g^2 \langle \phi(m(t) + \tilde{h}(t))\phi(m(s) + \tilde{h}(s)) \rangle$ (see Eq 7) and σ^2 is the variance of fluctuations driven by the independent noise input. The additional term proportional to $\delta(t-s)$ in Eq. 9 is due to this independent additive Gaussian white noise, similarly to the independent input considered previously [17, 16]. However, we consider simultaneously a time-varying common input signal $I(t)$, which renders the problem non-stationary. Such a non-stationary DMFT was recently developed [21], but without the independent input, which is crucial for meaningfully discussing information encoding rates in terms of a signal-to-noise ratio.

514 Together, the dynamic mean-field equations for $m(t)$, $c(t,s)$ and $r(t,s)$ form a closed system of self-consistent
515 dynamic equations and can be solved forward in time s and t by integrating them on a two-dimensional grid from
516 some initial condition for m, c and r. The integration requires $q(t,s)$, which can be calculated by evaluating
517 a Gaussian double integral that depends on $c(t,s)$, $c(t,t)$, $c(s,s)$, $m(t)$ and $m(s)$. For the threshold-linear
518 transfer function $\phi(x) = \max(x,0)$, one integral can be evaluated analytically, which allows for an efficient
519 numerical implementation using adaptive Gauss–Kronrod integration. The non-stationary dynamic mean-field
520 theory captures accurately the time-dependent mean population rate $\nu(t)$ and the two-time autocorrelation
521 function from numerical simulations.

522 In contrast to previous work that did not include noise [21], we consider here a network where neurons
523 simultaneously receive a time-varying input component $I(t)$ ("signal") that is identical across neurons and
524 an input component ξ_i ("noise") that is independent across neurons. This setup is necessary to meaningfully
525 quantify an information rate for a continuous channel, which requires a signal-to-noise ratio. Furthermore, we go
526 beyond the previously published non-stationary dynamic mean-field theory [21] by introducing a heuristic term
527 that emulates fluctuating input into the m-equation due to finite network size N similar to [14] (see appendix B).
528 We note that in contrast to [14], we do solve the self-consistent set of dynamic mean-field equations for m, c and
529 r to calculate dynamic gain, mutual information rate and mutual information rate density.

B   Heuristic finite-size fluctuations

531 The non-stationary dynamic mean-field theory is exact in the limit of large N. However, for the precise evaluation
532 of the spectral coherence, finite-size network corrections have to be taken into account. These corrections are
533 expected to be of order $\frac{1}{\sqrt{N}}$ and therefore have only a marginal effect on the dynamic gain. The finite-size
534 fluctuations can be heuristic accounted for by adding an additional fluctuation term to the equation of $m(t)$
535 (mean-field version of Eq. 3a), analogously to previous work [14]:

$$\tau \frac{\mathrm{d}m}{\mathrm{d}t} = -m - bJ_0\nu(t) + bI(t) + \frac{1}{\sqrt{N}}\zeta(t)\,, \tag{10}$$

536 where the mean-field estimate of the mean population firing rate $\nu(t) = \langle\phi(m(t) + \tilde{h}(t))\rangle$ is additionally
537 driven by the fluctuations $\zeta(t)$, a noise term that captures the effective finite-size fluctuations. In the case of
538 $g = 0$, $\zeta(t)$ reduces to an additive white Gaussian noise processes (AWGN) with autocorrelation function
539 $\langle\zeta(t)\zeta(t + t')\rangle = \tau\sigma^2\delta(t')$ originating from the mean across neurons of the independent input noise $\xi_i(t)$.

540 For $g > 0$, the finite size noise $\zeta(t)$ should include the effect coming from the residual fluctuations $\tilde{h}_i(t)$, which
541 adds a colored noise component to it (see also [14]). In contrast to [14], we heuristically approximate both
542 amplitude and timescale of the finite-size fluctuations from the solution of the stationary DMFT.

C   Details on numerical and analytical spectral analysis

544 We numerically solve the stochastic differential equation Eq. 1 using the Euler–Maruyama method but with a
545 distributionally-exact solution of the Ornstein-Uhlenbeck process for $I(t)$, meaning that $I(t)$ is not a solution of
546 stochastic differential equations and instead is directly generated according to its analytical distributions. To
547 calculate the spectral coherence, we used the function *coherence* from the Python package *scipy.signal* version
548 1.7.3 with a default Hann window window and default parameters except that we set the length of each segment
549 (nperseg) to 2^{11}. We calculated the integral over the mutual information density $1 - C_{I\nu}(f)$ using standard
550 trapezoidal integration. As pointed out in the main text, we find that the mutual information rate approximately
551 grows linear with tightness of balance b. In figure 5, we demonstrate that this linear scaling over several orders
552 of magnitude is also true for different levels of additive Gaussian white noise σ. We note that for low noise σ
553 and large b, the mutual information rate saturates which is an effect of finite time-resolution of the integration of
554 both dynamic mean-field theory and direct numerical simulations that result in an effective upper bound on the
555 frequencies (see figure 5), which leads to a deviation from the linear scaling of the mutual information rate. We
556 confirm this by deliberately introducing an upper cutoff frequency f_{cutoff} up to which the spectral coherence is
557 integrated:

$$R_{\text{lb}}(I, \nu) = -\int_0^{f_{\text{cutoff}}} df \log_2\left(1 - C_{I\nu}(f)\right) \tag{11}$$

558 As expected, changing this frequency cutoff directly affects the mutual information rate for large b (see figure 6).
559 For high noise σ and small b, we also observe deviation from the linear scaling. In that case, for finite simulation
560 time t_{sim} signal is so weak that spurious correlations between input and output give the illusion of mutual
561 information. This lower saturation can be ameliorated by a longer simulation time. All simulations were
562 performed on a laptop and took minutes to hours.

Figure 5: **Information rate grows linearly with** b **for different noise strength** σ**.** Same as figure 1E but with different additive white Gaussian noise of strength σ Model parameters: $N = 64$, $g = 0$, $\Delta t = 1/2^{12}\tau$, $t_{\text{sim}} = 2^6\tau$, $I_0 = J_0 = 1$, $\tau_S = 1.0\tau$, $\sigma = 0.1$, $I_1 = 0.1$.
.

D Details on analytical approximation of mutual information rate

We observed an approximately linear scaling of the mutual information rate with tightness of balance b. Where does this linear scaling originate from? The linear scaling of the mutual information rate can be obtained from the boost of the effective timescale of the network in combination with the signal-to-noise ratio that comes from the OU-input signal and the additive Gaussian white noise. The boost of the effective timescale was already noted earlier [2, 14], but we provided a non-stationary mean-field theory for nonlinear rate networks. The power spectral density of the input signal is given by

$$S_{\text{signal}}(f) = \frac{2\tau_S I_1}{1 + (2\pi\tau_S f)^2} \tag{12}$$

$S_{\text{noise}}(f)$ is the power spectrum of band-limited Gaussian white noise:

$$S_{\text{noise}}(f) = \begin{cases} \sigma^2 & f \le f_{\text{cutoff}} \\ 0 & \text{else.} \end{cases} \tag{13}$$

In a crude approximation that ignores the nonlinearity of the recurrent network dynamics and the interplay between m and $\tilde{h}$, we can approximate that the b changes the effective low-pass filtering of the network from the low-pass filtering coming from the leak-term in the dynamics

$$G_{\text{leak}}(f) = 1/\sqrt{1 + 4\pi^2 f^2 \tau^2} \tag{14}$$

to an effective filter of

$$G_{\text{effective}}(f) = 1/\sqrt{1 + 4\pi^2 f^2 (\tau/(b+1))^2}. \tag{15}$$

Thus, the characteristic timescales of the mean $m(t)$ and thus of the population firing rate $\nu(t)$ is $\tau/(b+1)$. This results from Eq. 3, when assuming a separation of timescales between the time-varying statistics of m and $\tilde{h}$. Thus, in a linear approximation, the magnitude square coherence can be approximated to be

$$C_{I\nu}(f) = \frac{|S_{I\nu}(f)|^2}{|S_{II}(f)||S_{\nu\nu}(f)|} \approx \frac{|S_{\text{signal}}(f)|^2}{|S_{\text{signal}}(f)| + |S_{\text{noise}}(f)|/b^2}. \tag{16}$$

Figure 6: **Cutoff frequency of input signal $I(t)$ limits linear scaling of mutual information.** Same as figure1E but with different cutoff frequency f_{cutoff}. Model parameters: $N = 64$, $g = 0$, $\Delta t = 1/2^{12}\tau$, $t_{\text{sim}} = 2^6\tau$, $I_0 = J_0 = 1$, $\tau_S = 1.0\tau$, $\sigma = 0.001$, $\sigma = 0.1$, $I_1 = 0.1$.
.

Using the first term of the expansion $-\log(x-1) \approx x + \frac{x^2}{2} + \frac{x^3}{3} + \frac{x^4}{4} \ldots$ this results in

$$r_{\text{lb}}(f) \approx -\log_2\left(1 - \frac{|S_{\text{signal}}(f)|^2}{|S_{\text{signal}}(f)| + |S_{\text{noise}}(f)|/b^2}\right) \approx \frac{|S_{\text{signal}}(f)|^2}{|S_{\text{signal}}(f)| + |S_{\text{noise}}(f)|/b^2} \tag{17}$$

Some algebra gives (setting $\tau = \tau_S = 1$)

$$R_{\text{lb}} \propto \int_0^\infty df \frac{\frac{2I_1}{1+(2\pi f)^2}}{\sigma^2/b^2 + \frac{2I_1}{1+(2\pi f)^2}} = \frac{2I_1 b^2}{\sigma^2}\sqrt{\frac{\sigma^2}{4I_1 b^2 + \sigma^2}} \tag{18}$$

for $b \gg \sigma^2/I_1$, i.e., tightly balanced networks and large signal-to-noise ratio this results in a linear scaling of the mutual information rate with tightness of balance:

$$\lim_{b \gg \sigma^2/I_1} R_{\text{lb}} \propto b. \tag{19}$$

E Details on training setup and additional numerical training experiments

An example implementation in Flux, a machine learning library in Julia is available at training-balanced-nets anonymously. Briefly, we trained standard rate networks (Eq. 1) to track an OU-process by a linear readout. We implemented the stochastic dynamics using the Euler–Maruyama method. We used the default ADAM hyperparameters without any additional fine-tuning and found our results to be robust with respect to choices of parameters. The parameters of the network simulations are reported in the respective figure captions.

F Details on training networks to track multiple time-varying signals

We found that training recurrent neural networks simultaneously on multiple signals yields balanced subnetworks. We investigated this in the following scenario: We trained RNNs to approximate two time-varying external

inputs $I_i(t)$ by two linear readout $\hat{I}(t) = 1/N \sum_i w_i^{\text{out}} \phi(h_i)$, by minimizing the mean squared loss $l = \int |\hat{I}(t) - I_i(t)|^2 \, dt$. The training scenario is identical to training on tracking a single OU-process, the only difference is that there exist two independent OU-input processes $I_i(t)$ and two readout vectors w_i^{out}. All parameters (recurrent weight matrix J_{ij}, input weights and output weights) are initialized with parameters drawn independently identically from Gaussian distributions as before.

We found that such randomly initialized networks trained on two OU-processes spontaneously break into two balanced subnetworks throughout training. The subnetworks have strong local inhibition among neurons belonging to one subnetwork, but weak connectivity between the subnetworks. We displayed that finding in Figure 4. We find the two subnetworks by k-means clustering on the input weights. Note that in the case of two OU-processes, the sorting can also be obtained by simply sorting the weight matrix J_{ij} according to the indices of the sorted input weight vectors, i.e. by performing 'sortperm' on one of the input vectors using the resulting indices as row- and column indices of the displayed weight matrix J_{ij}. Furthermore, we found that the entries of the input weights, which were independent Gaussian random initially also displayed symmetry breaking. We found that the entries of input and output weights associated with the same signal are strongly correlated (Figure 4D), but entries associated with different signals are anti-correlated (Figure 4E). We note that this finding is not limited to training networks on two independent OU-processes; strongly inhibitory coupled subnetworks also emerge when training on more OU-processes (See Figure 4F for the resulting connectivity of a network trained on 3 OU-processes). For networks trained on multiple time-varying stimuli, we observed an interesting training dynamics. First, they develop a single global inhibitory mode (figure 7), similar to networks trained to track a single OU-signal. After some intermediate time, we observe the emergence of a second negative outlier eigenvalue. Concomitantly, the network breaks into two inhibitory subnetworks and the readouts start to track both OU-input signals independently. An analytical analysis of this phenomenon is beyond this publication, but it can be explained in terms of the network to learn subsequent singular values of the input-output cross-correlation matrix [57], where the singular value that captures most of the variance is learned first. Indeed, tracking the average of the two OU-signals at each moment in time is favorable compared to e.g. tracking only one and ignoring the other. This can be seen by calculating the expectation of the mean squared error for the two cases. In the case where the mean is perfectly tracked, the mean squared error is by a factor of two larger in case only one is tracked and the other is ignored.

Figure 7: **Training dynamics of networks trained on multiple signals shows first tracking of global mean input. A)** RNNs are trained to approximate two time-varying external inputs $I_i(t)$ by two linear readout $\hat{I}_i(t) = 1/N \sum_j w_{ij}^{\text{out}} \phi(h_j)$, by minimizing the mean squared loss $l = \int |\hat{I}_i(t) - I_i(t)|^2 \, dt$. **B)** When trained on two independent stimuli, two outlier eigenvalues with negative real parts emerge. **C)** When observing the mean connectivity strength within the two subnetworks and between and the global mean coupling, and interesting training dynamics emerges: First, all weights become more negative and one single negative outlier eigenvalue evolves, then at some intermediate state, the network breaks up into two subnetworks, and their respective means become more negative but the weights between them on average actually become closer to zero.). Model parameters at initialization: $N = 100$, $g = \sqrt{2}$, $\Delta t = 0.2\tau$, $t_{\text{sim}} = 100\tau$, $b = 1$, $I_0 = J_0 = 1$, $\tau_S = 0.1$, $\sigma = 1$, epochs= 30000.

G Mixed excitatory-inhibitory circuits

To corroborate our training results, we also initialized the trained network with separate excitatory and inhibitory populations using the classical parametrization of [1], which for large b results in a balanced state. Consistent with [1], we chose mean couplings $J_{EE} = J_{IE} = 1.0/N$, $J_{II} = -1.8/N$, $J_{EI} = -2.0/N$. We found that training such a network on the auto-encoder task also results in a single inhibition-dominated population (See Figure 7). We did not try to constrain the weight update to maintain a separation of excitation and inhibition. This interesting scenario is left for future work.

Figure 8: **Excitatory-inhibitory initialization lost during training.** The network is initialized with excitatory and inhibitory subnetworks using the classical parametrization of [1]. **Top right:** Decay of mean squared error over epochs indicates that the network trained successfully. **Top middle:** This is confirmed visually by testing it on tracking an OU-process it was not trained on (target output dotted, actual output red). **Top right:** During training, an outlier eigenvalue with a very negative real part emerges similar to Fig.3. **Bottom left:** Typical activity of five example neurons after training. **Bottom middle:** An example recurrent connectivity matrix is displayed before training. **Bottom right:** After 50000 epochs, the initialization with separate excitatory and inhibitory subnetworks is largely lost and the network learned to track the time-varying external input. Model parameters at initialization: $N = 100$, $g = 0.01$, $\Delta t = 0.2\tau$, $t_{\text{sim}} = 100\tau$, $b = 1$, $I_0 = J_0 = 1$, $\tau_S = 0.1$, $\sigma = 1$, epochs= 10^5. Mean couplings were $J_{EE} = J_{IE} = 1.0/N$, $J_{II} = -1.8/N$, $J_{EI} = -2.0/N$.

H Training networks with other nonlinearities

To corroborate our training results and show the generality of our findings, we trained networks on the autoencoding task also using sigmoid (Figure 9), linear (Figure 10) and threshold-quadratic (Figure 11) activation function $\phi(x)$. We found that training such networks on the auto-encoder task also results in a single inhibition-dominated population (See Figure 9 - 11) that becomes progressively more tightly balanced over time, as seen from the outlier eigenvalue that emerges over time.

I Training on linear transformation on multiple input streams results in tightly balanced subnetworks

To furhter corroborate our training results and show the generality of our findings, we also trained networks on calculating a linear transformation on multiple input streams in each moment in time.

Figure 9: **RNNs with sigmoid nonlinearity trained on tracking time-varying input become more tightly balanced throughout training. Top left)** Analogous to Fig.3, RNNs are are trained to approximate a time-varying external input $I(t)$ by linear readout $\hat{I}(t) = 1/N \sum_i w_i^{\text{out}} \phi(h_i)$, by minimizing the mean squared loss $l = \int |\hat{I}(t) - I(t)|^2 \, dt$. Test loss drops throughout training. **Top middle)** Target output $I(t)$ (black dashed) and actual linear readout $\hat{I}(t)$ are plotted after training. **Top right)** The eigenvalue spectrum of the dynamics linearized at the fixed point before and after training. **Bottom left)** Typical activity $h_i(t)$ of five example neurons after training. Note that individual neurons strong slow fluctuations despite reliable network response. **Bottom middle)** The training dynamics of the minimum over the real parts of the eigenvalues indicates that during training, an eigenmode with a strongly negative real part emerges. **Bottom right)** Example network after training on independent OU-processes. After training the network has an overall strongly negative recurrent weight matrix, despite being initialized with weights drawn from a Gaussian with a mean $-bJ_0/N = -0.01$. Model parameters at initialization: $N = 100$, $g = \sqrt{2}$, $\Delta t = 0.05\tau$, $t_{\text{sim}} = 5\tau$, $b = 1$, $I_0 = J_0 = 1$, $\tau_S = 0.1$, $\sigma = 1$, epochs= 30000.

For that, analogous to Fig.4B-D, RNNs are are trained to perform a linear transformation $y_i(t) = \sum_j A_{ij} I_j(t)$ on a set of multi-dimensional time-varying external input $I_i(t)$ (Fig 12 top middle)). The training was done by minimizing the mean squared loss $l = \sum_j \int |\hat{y}(t) - \sum_{ij} A_{ij} I_j(t)|^2 \, dt$, where $\hat{y}_i$ are linear readouts of the recurrent network, $\hat{y}_i(t) = 1/N \sum_j w_{ij}^{\text{out}} \phi(h_j)$ and A is a random matrix of size $S \times R$ with entries drawn independently from a Gaussian distribution with zero mean and variance $1/R$. Here wo chose $R = S = 3$. Again, the time-varying input signals $I_j(t)$ were independent OU processes.

We observe that the test loss drops throughout training (Fig 12 top left)), concomitantly the linearized network dynamics develops three outlier with negative real part throughout the course of the training (Fig 12 top right). We observe that the number of outlier eigenvalues is determined by the rank of A (Fig 12 bottom left)) and their training dynamics seems to be shaped by the singular values of A, reminiscent of the training dynamics of multi-layer perceptrons [57]. For our case of $R = S = 3$ in figure 12 we observed that three outlier eigenvalues develop, at the same time three tightly balanced subnetworks with strong inhibition emerge (Fig 12 bottom right)). For illustration, we plotted the activity h_i for 5 example neurons in the bottom middle of Fig 12. Consistent with our theory, the network becomes more tightly balanced over the course of training. We leave an analytical description of the training dynamics for future work.

Figure 10: **Linear RNN trained on tracking time-varying input become more tightly balanced throughout training.** Everything same as Fig 9 but linear activation $\phi(x) = x$.

Figure 11: **RNNs with threshold quadratic nonlinearity trained on tracking time-varying input become more tightly balanced throughout training.** Everything same as Fig 9 but threshold quadratic activation $\phi(x) = max(x,0)^2$.

Figure 12: **RNNs trained on performing linear transformation on time-varying input become more tightly balanced throughout training. Top left)** Analogous to Fig.4B-D, RNNs are are trained to perform a linear transformation $y_i(t) = \sum_j A_{ij} I_j(t)$ on a set of multi-dimensional time-varying external input $I_i(t)$, by minimizing the mean squared loss $l = \sum_j \int |\hat{I}(t) - \sum_{ij} A_{ij} I_j|^2 \, \mathrm{d}t$. Test loss drops throughout training. **Top middle)** Target output $y(t)$ (black dashed) and actual linear readout $\hat{y}(t)$ are plotted after training. **Top right)** The eigenvalue spectrum of the dynamics linearized at the fixed point before and after training. **Bottom middle)** Typical activity $h_i(t)$ of five example neurons after training. Note that individual neurons strong slow fluctuations despite reliable network response. **Bottom middle)** The training dynamics of the minimum over the real parts of the eigenvalues indicates that during training, an eigenmode with a strongly negative real part emerges. **Bottom right)** Example network after training on independent OU-processes. After training the network has an overall strongly negative recurrent weight matrix, despite being initialized with weights drawn from a Gaussian with a mean $-bJ_0/N = -0.01$. Model parameters at initialization: $N = 100$, $g = 0.1$, $\Delta t = 0.05\tau$, $t_{\text{sim}} = 5\tau$, $b = 1$, $I_0 = J_0 = 1$, $\tau_S = 0.1$, $\sigma = 1$, epochs= 30000.