Structured Noise Adaptation for Sequential Bayesian Filtering with Embedded Latent Transfer Operators

Abstract

Kalman filters based on the Embedded Latent Transfer Operators (ELTOs) emerge as powerful statistical tools for sequential state estimation. However, a critical limitation stems from their use of a simplified noise model, which fails to dynamically adapt to non-stationary processes. To address this limitation, we introduce an ELTO-based Bayesian filtering approach with a new structured parameterization for the filter's noise model. This parameterization enables structured noise adaptation, which couples the data-driven learning of an optimal time-invariant noise model with dynamic parameter adaptation that responds to local changes in dynamics within non-stationary processes. Empirical results show that the proposed noise model improves the filter's dynamic state estimation performance in noisy, time-varying environments.

1 Introduction

Sequential state estimation is the process of continuously updating an estimate of a system's state over time based on incoming observations. It serves as a foundation for many real-world applications, including robotics, navigation, and financial modeling (Gebhardt et al., 2019; Greenberg et al., 2023; DeMiguel et al., 2024). A classical and widely used approach to state estimation is Kalman filtering (Kalman, 1960), which performs sequential Bayesian state estimation by iteratively propagating a latent state and its uncertainty forward in time (Fukumizu et al., 2013), and then updating on new observations. Achieving high state estimation performance is, however, often hindered by a fundamental problem: specifying a noise model that is robust under the non-stationarity of real-world processes (Masreliez & Martin, 2003). A common approach to this problem is, for example, down-weighting measurement outliers at the update step, which merely treats the symptom of corrupted data (Duran-Martin et al., 2024; Wang et al., 2018; Agamennoni et al., 2012). In contrast, we address the problem by improving the robustness of the filter's internal noise model in learning the underlying system dynamics from noisy data.

Our proposed method builds on the work of Gebhardt et al. (2019), which introduces a computationally efficient state estimation technique called the kernel Kalman rule (KKR). Similar to the kernel Bayes' filter (KBR) (Fukumizu et al., 2013), KKR, when combined with the kernel sum rule, uses conditional embedding operators (e.g., the transfer operator) to formulate kernel Kalman filtering (KKF) in the reproducing kernel Hilbert space (RKHS). By performing state estimation in the RKHS, KKF overcomes the explicit parametric assumptions required in the original state space.

Given high-dimensional observations, Ke et al. (2025) have recently proposed a spectral learning algorithm, derived from stochastic realization theory (Katayama, 2005), to approximate data-driven representation of the transfer operator governing the evolution of the embedded latent state in an RKHS. This resulting transfer operator is also known as the Embedded Latent Transfer Operator (ELTO). As the spectral learning algorithm enables us to perform data-driven modeling—with the ELTO—of the state-space representation for nonlinear stochastic processes, sequential state estimation using ELTOs (referred to as ELTO-KF) combines the operators identified from observation data with the Bayesian inference procedure of the KKR. Nonetheless, the ELTO-KF approach inherits a critical limitation regarding noise modeling: the reliance on fixed noise covariances that fail to adapt to non-stationary processes.

Figure 1: State-space representation of a latent variable. $\mathcal{T}$ and $\mathcal{O}$ represent the transfer and observable operators for the latent state embedded in the RKHS by μ.

Optimizing the noise models, i.e., the covariance matrices of process and measurement noise, of Kalman filters to ensure robustness against changes in the dynamics of non-stationary processes is an important challenge, because it is well known that suboptimal noise covariance matrices severely degrade filtering performance (Greenberg et al., 2023). One noteworthy model-based solution is the adaptive extended Kalman filter (AEKF), which dynamically tunes the noise matrices using the filter's residual and innovation (Wang, 1999; Akhlaghi et al., 2017). Another class of solutions is data-driven, which treats the parameters of the noise models as learnable and uses numerical optimization to obtain the best time-invariant parameters in terms of fitting performance (Greenberg et al., 2023; Becker et al., 2019). Both strategies highlight the central role of the noise model. However, to facilitate the learning of complex system dynamics in high-dimensional contexts, a research gap remains in constructing a unified approach that benefits from both parameter learning strategies to ultimately improve the filtering performance.

In this paper, we improve the ELTO-KF by incorporating a new structured parameterization for the filter's internal noise model, proposing the novel ELTO-based adaptive Kalman filtering method, called ELTO-AKF. This parameterization enables structured noise adaptation, coupling the data-driven learning of the filter's optimal time-invariant noise model with dynamic parameter adaptation to ultimately enhance dynamic state estimation performance in non-stationary processes. Our proposed method incorporates adaptive estimation—based on the filter's residual and innovation—of the noise covariance matrices into the data-driven optimization, yielding robust covariance representations for different non-stationary processes with varying noise levels. Our structured parameterization for the noise covariance matrices is implemented to reduce computational complexity compared with full-rank matrices, while preserving essential temporal correlations and providing a tractable structure for dynamic parameter adaptation. The proposed data-driven approach enables the structured noise adaptation, which integrates data-driven parameter optimization with dynamic parameter adaptation, thus addressing the aforementioned research gap. We demonstrate that ELTO-AKF is effective across a broader range of challenging scenarios, including those not previously considered before in Ke et al. (2025), such as long sequences with piecewise non-stationarity and a cross-domain denoising task for sparse identification of partial differential equations (PDEs) (Thanasutives et al., 2024; 2025).

Our contributions are summarized as follows:

1. We introduce a new structured parameterization for tractable learning of data-driven representations of noise covariance matrices and propose the ELTO-AKF method, in which the parameterization is implemented.

2. We demonstrate that the structured noise adaptation—coupling the learning of a robust, time-invariant noise model via derivative-free optimization with dynamic parameter adaptation—ultimately improves the filter's dynamic state estimation performance in non-stationary processes.

2 Background and Related Work

2.1 State Space Models

The state space model (SSM) is a mathematical framework for describing a dynamical system, consisting of a latent state process $\{\mathbf{x}(t) \in \mathbb{X}\}$ and an observation process $\{\mathbf{y}(t) \in \mathbb{Y}\}$. The system evolution is governed by a state transition density p_{tr}, which is defined for any measurable set $\mathbb{A}$ by $Pr(\mathbf{x}(t+1) \in \mathbb{A}|\mathbf{x}(t) = \boldsymbol{x}) = \int_{\mathbb{A}} p_{tr}(\boldsymbol{z}|\boldsymbol{x})d\boldsymbol{z}$, and an observation density p_{ob}, which links the latent state to the observations/measurements, defined by $Pr(\mathbf{y}(t) \in \mathbb{A}'|\mathbf{x}(t) = \boldsymbol{x}) = \int_{\mathbb{A}'} p_{ob}(\boldsymbol{y}|\boldsymbol{x})d\boldsymbol{y}$. Note that $\mathbb{A}'$ is another measurable set.

SSMs in Reproducing Kernel Hilbert Spaces. Since Hilbert-space distribution embeddings allow us to represent arbitrary probability distributions nonparametrically and perform inference entirely in the space, we embed the state densities into RKHSs. Given a measurable positive definite kernel k on $\mathbb{X}$ (e.g., $\sup_{\boldsymbol{x} \in \mathbb{X}} k(\boldsymbol{x}, \boldsymbol{x}') < \infty$) and its corresponding feature map ψ, the probability density of the state $\mathbf{x}(t)$ is represented by a kernel mean embedding $\mu_{P_{\mathbf{x}(t)}}$ into the RKHS, denoted as $\mathbb{H}$. This embedding is defined as the mapping $\mu : \mathbb{M}_+(\mathbb{X}) \to \mathbb{H}, P \mapsto \int \psi(\boldsymbol{x})dP(\boldsymbol{x})$ on measurement space $\mathbb{M}_+(\mathbb{X})$ for any probability measure P on $\mathbb{X}$. Within this embedded Hilbert space, the abstract transition and observation can be described by covariance operators. Let $(\boldsymbol{x}, \boldsymbol{y})$ be a random variable taking values in $\mathbb{X} \times \mathbb{Y}$ with a marginal distribution $P_{\mathbf{x}}$ and a joint distribution $P_{\mathbf{xy}}$, and let $\mathbb{H}$ and $\mathbb{G}$ be their corresponding RKHSs with feature maps ψ and ϕ. Following Baker (1973), the covariance operator $\mathcal{C}_{\mathbf{x}} : \mathbb{H} \to \mathbb{H}$ and cross-covariance operator $\mathcal{C}_{\mathbf{yx}} : \mathbb{H} \to \mathbb{G}$ are defined as:

$$\mathcal{C}_{\mathbf{x}} := \int \psi(\boldsymbol{x}) \otimes \psi(\boldsymbol{x})dP_{\mathbf{x}}(\boldsymbol{x}),$$

$$\mathcal{C}_{\mathbf{yx}} := \int \phi(\boldsymbol{y}) \otimes \psi(\boldsymbol{x})dP_{\mathbf{xy}}(\boldsymbol{x}, \boldsymbol{y}). \tag{1}$$

The conditional distribution is then represented by the conditional embedding operator $\mathcal{C}_{\mathbf{y}|\mathbf{x}} := \mathcal{C}_{\mathbf{yx}}\mathcal{C}_{\mathbf{x}}^{-1}$ (Song et al., 2009).

Data-driven Identification of System Operators via Spectral Learning. Ke et al. (2025) proposed a spectral learning algorithm to estimate matrix representations of system operators, namely the Embedded Latent Transfer Operator (ELTO) and the Embedded Observable Operator (EOO), which govern the evolution of the embedded latent state in the RKHS as well as its relationship to the observation. The latent state process $\{\mathbf{x}(t)\}$ is constructed in a data-driven manner based on stochastic realization theory (Katayama, 2005). Consequently, the spectral learning enables data-driven identification of the system operators, $\mathcal{T} := \mathcal{C}_{\mathbf{x}(t+1)|\mathbf{x}(t)}$ and $\mathcal{O} := \mathcal{C}_{\mathbf{y}(t)|\mathbf{x}(t)}$, from the observation process $\{\mathbf{y}(t)\}$. A detailed matrix-based derivation of this algorithm is given in Appendix A. Both operators ($\mathcal{T}$ and $\mathcal{O}$ in Figure 1) serve as necessary components for the kernel Kalman filtering described next.

2.2 Kernel Kalman Filtering

Sequential state estimation, i.e., Kalman filtering, is the primary task for the state-space models. The fundamental goal is to sequentially infer the full probability distribution of the latent state from a history of observations. Traditional Kalman filters require explicit parametric models of the system's complex dynamics; however, it is difficult to specify the prior and likelihood probability densities explicitly to complete the Bayesian inference step. Therefore, Bayesian state estimation directly in the observation space is cumbersome. To bypass these parametric constraints, the Kernel Kalman Rule (KKR) (Gebhardt et al., 2019) is adopted. This method leverages the covariance operators established in Section 2.1 to perform Bayesian updates directly in the RKHS, thereby avoiding the need for explicit density specifications (Fukumizu et al., 2013).

Kernel Kalman Rule. For a given training dataset $\{(\tilde{\boldsymbol{x}}_i, \boldsymbol{x}_i, \boldsymbol{y}_i)\}_{i=1}^N$, Gebhardt et al. (2019) formulated the KKR to compute the empirical transfer and observable operators. $\tilde{\boldsymbol{x}}_i$ represents the preceding state

(corresponding to $\mathbf{x}(t)$ in SSM) and $\boldsymbol{x}_i$ denotes the current state (corresponding to $\mathbf{x}(t+1)$ in SSM) with its associated measurement y_i [1]. Let $k_x(\cdot, \cdot)$ and $k_y(\cdot, \cdot)$ be the kernel functions for the state and observation spaces, associated with feature maps $\psi(\cdot)$ and $\phi(\cdot)$, respectively. By applying these maps, we define the feature matrices:

$$\boldsymbol{\Psi} = [\psi(\boldsymbol{x}_1), \ldots, \psi(\boldsymbol{x}_N)], \quad \boldsymbol{\Phi} = [\phi(\boldsymbol{y}_1), \ldots, \phi(\boldsymbol{y}_N)]. \tag{2}$$

Subsequently, the kernel matrices (Gram matrices) are computed as:

$$\boldsymbol{G}_x = \boldsymbol{\Psi}^\top \boldsymbol{\Psi}, \quad \boldsymbol{G}_{yx} = \boldsymbol{\Phi}^\top \boldsymbol{\Psi}, \quad \boldsymbol{G}_{\tilde{x}} = \boldsymbol{\Psi}_1^\top \boldsymbol{\Psi}_1, \quad \boldsymbol{G}_{\tilde{x}x} = \boldsymbol{\Psi}_1^\top \boldsymbol{\Psi}_2, \quad \boldsymbol{G}_y = \boldsymbol{\Phi}^\top \boldsymbol{\Phi} \tag{3}$$

where $\boldsymbol{\Psi}_1 := \boldsymbol{\Psi}_{:,1:N-1}$, $\boldsymbol{\Psi}_2 := \boldsymbol{\Psi}_{:,2:N}$. Based on these kernel matrices, the transition matrix $\boldsymbol{T}$ and observation matrix $\boldsymbol{O}$ are derived as:

$$\boldsymbol{T} = (\boldsymbol{G}_{\tilde{x}} + \epsilon_t \boldsymbol{I})^{-1} \boldsymbol{G}_{\tilde{x}x}, \quad \boldsymbol{O} = (\boldsymbol{G}_x + \epsilon_o \boldsymbol{I})^{-1} \boldsymbol{G}_{yx}^\top, \tag{4}$$

where $\epsilon_t, \epsilon_o > 0$. $\boldsymbol{T}$ and $\boldsymbol{O}$ serve as the empirical representations of the conditional embedding operators $\mathcal{C}_{\mathbf{x}|\tilde{\mathbf{x}}}$ and $\mathcal{C}_{\mathbf{y}|\mathbf{x}}$, which govern the evolution of the transition and observation densities in the RKHS.

Empirical Kernel Kalman Filters Sequential estimation is performed by recursively calculating the posterior state through iterative prediction and update steps. To implement these steps in the RKHS using the finite-dimensional operator representations derived above, the mean map $\hat{\mu}_{\mathbf{x}(t)}$ and the covariance operator $\hat{\mathcal{C}}_{\mathbf{x}(t)}$ are tracked through a weight vector $\boldsymbol{m}_t \in \mathbb{R}^N$ and a weight matrix $\boldsymbol{S}_t \in \mathbb{R}^{N \times N}$ as follows:

$$\hat{\mu}_{\mathbf{x}(t)}^- = \boldsymbol{\Upsilon}_x \boldsymbol{m}_t^- \quad \text{and} \quad \hat{\mathcal{C}}_{\mathbf{x}(t)}^- = \boldsymbol{\Upsilon}_x \boldsymbol{S}_t^- \boldsymbol{\Upsilon}_x^\top. \tag{5}$$

The a-priori and posteriori belief states are denoted as $\bullet^-$ and $\bullet^+$, respectively. The operators are updated in the RKHS map based on linear operations on these weights. The prediction step corresponds to:

$$\hat{\mu}_{\mathbf{x}(t)}^- = \hat{\mathcal{C}}_{\mathbf{x}|\tilde{\mathbf{x}}} \hat{\mu}_{\mathbf{x}(t-1)}^+ = \boldsymbol{\Upsilon}_x \boldsymbol{T} \boldsymbol{m}_{t-1}^+ \quad \Leftrightarrow \quad \boldsymbol{m}_t^- = \boldsymbol{T} \boldsymbol{m}_{t-1}^+,$$
$$\hat{\mathcal{C}}_{\mathbf{x}(t)}^- = \hat{\mathcal{C}}_{\mathbf{x}|\tilde{\mathbf{x}}} \hat{\mathcal{C}}_{\mathbf{x}(t-1)}^+ \hat{\mathcal{C}}_{\mathbf{x}|\tilde{\mathbf{x}}}^\top + \mathcal{C}_V \quad \Leftrightarrow \quad \boldsymbol{S}_t^- = \boldsymbol{T} \boldsymbol{S}_{t-1}^+ \boldsymbol{T}^\top + \boldsymbol{Q}. \tag{6}$$

Here, $\mathcal{C}_V$ and $\boldsymbol{Q}$ represent the process noise covariance in operator and matrix form, respectively. The update step, involving the Kalman gain, is similarly formulated as:

$$\hat{\mu}_{\mathbf{x}(t)}^+ = \hat{\mu}_{\mathbf{x}(t)}^- + \mathcal{G}_t(\phi(\boldsymbol{y}_t) - \mathcal{C}_{\mathbf{y}|\mathbf{x}} \hat{\mu}_{\mathbf{x}(t)}^-),$$
$$\hat{\mathcal{C}}_{\mathbf{x}(t)}^+ = \hat{\mathcal{C}}_{\mathbf{x}(t)}^- - \mathcal{G}_t \mathcal{C}_{\mathbf{y}|\mathbf{x}} \hat{\mathcal{C}}_{\mathbf{x}(t)}^-,$$
$$\mathcal{G}_t = \hat{\mathcal{C}}_{\mathbf{x}(t)}^- \mathcal{C}_{\mathbf{y}|\mathbf{x}}^\top (\mathcal{C}_{\mathbf{y}|\mathbf{x}} \hat{\mathcal{C}}_{\mathbf{x}(t)}^- \mathcal{C}_{\mathbf{y}|\mathbf{x}}^\top + \mathcal{C}_W)^{-1}. \tag{7}$$

$\mathcal{G}_t$ is the Kalman gain operator. $\mathcal{C}_W$ denotes the measurement noise covariance in operator form, whereas $\boldsymbol{R}$ (introduced later) denotes its matrix form. We provide the explicit finite-dimensional update equations in Section 3.2 (Equation 11-13), where they are integrated with our proposed structured noise parameterization.

---

[1] Note that the data-driven construction of the state pairs $(\tilde{\boldsymbol{x}}_i, \boldsymbol{x}_i)$ is performed using the spectral learning algorithm described in Appendix A.

3 Structured Noise Model Adaptation for Sequential Bayesian Filtering

The key limitation of existing Kalman filters is their reliance on dense, unstructured covariance models, which make the direct optimization ill-posed for non-stationary processes. In this paper, we incorporate structured noise model adaptation to the data-driven optimization of the KKF, proposing the ELTO-AKF. Within our proposed method, KKF formulates the sequential filtering process given the data-driven-identified system operators obtained the spectral learning. Constructed by a new sparse structure parameterization detailed in Section 3.1, the structured noise model couples the data-driven optimization for tracking global noise statistics in noisy environments (Section 3.2) with dynamic parameter adaptation for enhancing robustness in non-stationary environments (Section 3.3).

3.1 Sparse Structure Parameterization

We introduce the scalar-block (SB) structure to facilitate the tractable learning of noise covariance matrices.

Definition 1. *Let a matrix $\boldsymbol{A} \in \mathbb{R}^{N \times N}$ be partitioned into $k \times k$ sub-blocks. We define a **scalar-block Matrix** $\boldsymbol{A}_\theta^S$ as a matrix where each sub-block is a scaled identity matrix parameterized by a scalar $\theta_{ij} \in \mathbb{R}$:*

$$\boldsymbol{A}_\theta^S = \begin{pmatrix} \theta_{11} \cdot \boldsymbol{I} & \theta_{12} \cdot \boldsymbol{I} & \dots & \theta_{1k} \cdot \boldsymbol{I} \\ \theta_{21} \cdot \boldsymbol{I} & \theta_{22} \cdot \boldsymbol{I} & \dots & \theta_{2k} \cdot \boldsymbol{I} \\ \vdots & \vdots & \ddots & \vdots \\ \theta_{k1} \cdot \boldsymbol{I} & \theta_{k2} \cdot \boldsymbol{I} & \dots & \theta_{kk} \cdot \boldsymbol{I} \end{pmatrix}. \tag{8}$$

A significant challenge is to enforce the SB structure while guaranteeing the symmetric positive-definite (SPD) property of a covariance matrix. Addressing this, we adopt the Cholesky parameterization to transform a constrained covariance estimation into an unconstrained problem (Pinheiro & Bates, 1996). The technique represents the SB matrix via the factorization $\boldsymbol{A}_\theta^S = \boldsymbol{L}\boldsymbol{L}^\top$, where $\boldsymbol{L}$ is a block lower-triangular matrix whose sub-blocks are scaled identity matrices. The SPD property of this SB structure is proved in the following.

Proposition 1. *Let the factor matrix $\boldsymbol{L} \in \mathbb{R}^{N \times N}$ be a block lower-triangular matrix where each sub-block $\boldsymbol{L}_{ij} = l_{ij} \cdot \boldsymbol{I}$. If all diagonal scalars l_{ii} are non-zero, then the matrix $\boldsymbol{A}$ constructed as $\boldsymbol{A} = \boldsymbol{L}\boldsymbol{L}^\top$ is a symmetric positive-definite (SPD), scalar-block matrix.*

Proof. Symmetry and the scalar-block structure follow directly from the construction $\boldsymbol{A} = \boldsymbol{L}\boldsymbol{L}^\top$ and the properties of block matrix multiplication. For positive definiteness, we consider the quadratic form $x^\top \boldsymbol{A} x = \|\boldsymbol{L}^\top x\|_2^2$. The condition $l_{ii} \neq 0$ for all i ensures that the block lower-triangular matrix $\boldsymbol{L}$ is invertible. Since $\boldsymbol{L}$ is invertible, $\boldsymbol{L}^\top x \neq 0$ for any non-zero vector x, which guarantees that the norm $\|\boldsymbol{L}^\top x\|_2^2$ is positive. Thus, $\boldsymbol{A}$ is positive-definite. $\square$

The SB parameterization, defined by the set of learnable scalars $\{\theta_{ij}\}$, provides an expressive yet computationally tractable representation of the noise covariance matrices, serving as a crucial component for establishing the structured noise adaptation of our ELTO-AKF.

3.2 Data-driven Optimization of Kernel Kalman Filters

We detail the matrix-based implementation of our ELTO-AKF and formulate the optimization objective for learning an optimal, time-invariant noise model. The relationship between the abstract operators in Equation 6-7 and their concrete matrices is grounded in the KKF, where operators and state embeddings are represented as linear combinations of the feature mappings.

We implement the filtering process using the kernel Kalman rule (Gebhardt et al., 2019), employing the system matrices $\boldsymbol{T}$ and $\boldsymbol{O}$ derived empirically from Gram matrices via the spectral learning algorithm detailed in Appendix A. However, standard ELTO-based approaches typically derive a static/non-adaptive process noise matrix $\boldsymbol{Q}$ from the residuals of the learned operators. Such static matrices are insufficient for learning non-stationary processes. To address this problem, we therefore parameterize the noise covariance matrices as learnable, structured matrices (i.e., $\boldsymbol{Q}_\theta$ and $\boldsymbol{R}_\theta$) using the SB structure.

Figure 2: Schematic of the ELTO-AKF approach with dynamic parameter adaptation.

The sequential filtering process proceeds for $t = 1, \ldots, T$ as follows:

Prediction:

$$\boldsymbol{m}_t^- = \boldsymbol{T}\boldsymbol{m}_{t-1}^+, \tag{9}$$

$$\boldsymbol{S}_t^- = \boldsymbol{T}\boldsymbol{S}_{t-1}^+ \boldsymbol{T}^\top + \boldsymbol{Q}_\theta. \tag{10}$$

Update:

$$\boldsymbol{G}_t = \boldsymbol{S}_t^- \boldsymbol{O}^\top (\boldsymbol{G}_y \boldsymbol{O} \boldsymbol{S}_t^- \boldsymbol{O}^\top + \boldsymbol{R}_\theta)^{-1}, \tag{11}$$

$$\boldsymbol{m}_t^+ = \boldsymbol{m}_t^- + \boldsymbol{G}_t(\boldsymbol{o}(\boldsymbol{y}_t) - \boldsymbol{G}_y \boldsymbol{O} \boldsymbol{m}_t^-), \tag{12}$$

$$\boldsymbol{S}_t^+ = (\boldsymbol{I} - \boldsymbol{G}_t \boldsymbol{G}_y \boldsymbol{O})\boldsymbol{S}_t^-. \tag{13}$$

Here, we define the feature map $\boldsymbol{o}(\boldsymbol{y}_t)$ from the subsequence $\boldsymbol{Y}_{1:N}$ of the full observation $\boldsymbol{Y} = [\boldsymbol{y}_1, \ldots, \boldsymbol{y}_T]$, where $N = T - 2h + 2$ and h is the window size. This map is realized via the kernel trick as a vector of kernel evaluations: $\boldsymbol{o}(\boldsymbol{y}_t) := [k_y(\boldsymbol{y}_1, \boldsymbol{y}_t), \ldots, k_y(\boldsymbol{y}_N, \boldsymbol{y}_t)]^\top$. After obtaining the posterior state estimate $(\boldsymbol{m}_t^+, \boldsymbol{S}_t^+)$, the pre-image step maps the estimate back into the original observation space for comparison with the ground truth. The following pre-image estimate $\hat{\boldsymbol{\eta}}_t$ and $\hat{\boldsymbol{\Sigma}}_t$ can be compared with the measurement (Gebhardt et al., 2019).

$$\hat{\boldsymbol{\eta}}_t = \boldsymbol{Y}_{1:N} \boldsymbol{O} \boldsymbol{m}_t^+ \tag{14}$$

$$\hat{\boldsymbol{\Sigma}}_t = \boldsymbol{Y}_{1:N} \boldsymbol{O} \boldsymbol{S}_t^+ \boldsymbol{O}^\top \boldsymbol{Y}^\top \tag{15}$$

The sequence of estimates $\{\hat{\boldsymbol{\eta}}_t\}_{t=1}^T$ depends on the noise parameters θ through the matrices $\boldsymbol{Q}_\theta$ and $\boldsymbol{R}_\theta$, which influence the Kalman gain $\boldsymbol{G}_t$ and covariance propagation. Since filter performance is impacted by these matrices and standard estimation relies on potentially violated assumptions (Wang, 1999), directly

---

Algorithm 1 ELTO-based Kalman Filtering with Structured Noise Model Adaptation

---

1: **Input:** observation $\boldsymbol{Y} = [\boldsymbol{y}_1, \ldots, \boldsymbol{y}_T]$, ground truth $\boldsymbol{Y}^{\text{true}} = [\boldsymbol{y}_1^{\text{true}}, \ldots, \boldsymbol{y}_T^{\text{true}}]$, window size w, memory factors (α, β), and randomly initialized parameters ϵ_q, ϵ_r or ϵ_l, ϵ_m.
2: *// — Initialization based on Algorithm 3 in Appendix A —*
3: Compute transfer and observable matrices $\boldsymbol{T}$ and $\boldsymbol{O}$,
4: Initialize mean $\boldsymbol{m}_0$ and variance $\boldsymbol{S}_0$
5: *// — Initialization of noise covariance matrices —*
6: **if** $\alpha = \beta = 1$ **then**
7:      Parameterize $\boldsymbol{Q}_0, \boldsymbol{R}_0$ in SB structure with $\theta_{ij} = \epsilon_q$ or ϵ_r ▷ *See Equation 8*
8: **else**
9:      Parameterize $\boldsymbol{L}_0, \boldsymbol{M}_0$ in SB structure with $\theta_{ij} = \epsilon_l$ or ϵ_m for $i \geq j$
10:      $\boldsymbol{L} \leftarrow \boldsymbol{L}_0, \boldsymbol{M} \leftarrow \boldsymbol{M}_0$
11:      $\boldsymbol{Q} \leftarrow \boldsymbol{L}\boldsymbol{L}^\top, \ \boldsymbol{R} \leftarrow \boldsymbol{M}\boldsymbol{M}^\top$
12: **end if**
13: *// — Derivative-free optimization by CMA-ES —*
14: Compute $[\hat{\boldsymbol{\eta}}_1, \ldots, \hat{\boldsymbol{\eta}}_T]$ using Algorithm 2 ▷ Kernel Kalman filtering with dynamic parameter adaptation
15: $\theta^* = \underset{\theta}{\operatorname{argmin}} \frac{1}{T} \sum_{t=1}^{T} \|\hat{\boldsymbol{\eta}}_t - \boldsymbol{y}_t^{\text{true}}\|^2$ ▷ *This line is ablated during a test phase, as we keep θ^* after training.*
16: **Output:** θ^* and the pre-image estimates: $[\hat{\boldsymbol{\eta}}_1, \ldots, \hat{\boldsymbol{\eta}}_T], [\hat{\boldsymbol{\Sigma}}_1, \ldots, \hat{\boldsymbol{\Sigma}}_T]$

---

minimizing θ to minimize the end-to-end estimation error offers a data-driven approach to finding an optimal time-invariant model with the best overall robustness for a given distribution (Greenberg et al., 2023). Our objective is the mean squared error (MSE) between the pre-image $\hat{\boldsymbol{\eta}}_t = \hat{\boldsymbol{\eta}}_t(\theta)$ and the ground truth $\boldsymbol{y}_t^{\text{true}}$:

$$\theta^* = \underset{\theta}{\operatorname{argmin}} \frac{1}{T} \sum_{t=1}^{T} \|\hat{\boldsymbol{\eta}}_t - \boldsymbol{y}_t^{\text{true}}\|^2. \tag{16}$$

Following the monotonicity property of the RBF kernel proven in Appendix B, minimizing the squared error (Equation 16) in the observation space corresponds to minimizing the filter's innovation residual (i.e., $\boldsymbol{o}(\boldsymbol{y}_t) - \boldsymbol{G}_y \boldsymbol{O} \boldsymbol{m}_t^-$ in Equation 12) in the RKHS space. To numerically solve this optimization objective, we employ CMA-ES (Hansen, 2006), a derivative-free evolution strategy well suited minimizing non-convex functions with a small number of parameters. Algorithm 1 finds the optimal noise model for the training distribution, offering globally robust performance in non-stationary noisy environments.

3.3 Dynamic Parameter Adaptation

We now detail the dynamic parameter adaptation for non-stationary environments where the system's dynamical characteristics or noise levels change over time. We employ analytical update rules following the adaptive extended Kalman filtering (AEKF)(Akhlaghi et al., 2017). Essentially, we use the following innovation and posterior residual to adaptively estimate noise statistics:

$$\begin{aligned} \phi(\boldsymbol{y}_t) - \mathcal{C}_{\mathbf{y}|\mathbf{x}} \hat{\mu}_{\mathbf{x}(t)}^- &\Leftrightarrow d_t = \boldsymbol{o}(\boldsymbol{y}_t) - \boldsymbol{G}_y \boldsymbol{O} \boldsymbol{m}_t^-, \\ \phi(\boldsymbol{y}_t) - \mathcal{C}_{\mathbf{y}|\mathbf{x}} \hat{\mu}_{\mathbf{x}(t)}^+ &\Leftrightarrow \epsilon_t = \boldsymbol{o}(\boldsymbol{y}_t) - \boldsymbol{G}_y \boldsymbol{O} \boldsymbol{m}_t^+. \end{aligned} \tag{17}$$

The standard AEKF update uses memory factors (i.e., α, β) to adapt the estimates of $\boldsymbol{Q}$ and $\boldsymbol{R}$:

$$\begin{aligned} \boldsymbol{R}_t &= \alpha \boldsymbol{R}_{t-1} + (1-\alpha)(\epsilon_t \epsilon_t^\top + \boldsymbol{G}_y \boldsymbol{O} \boldsymbol{S}_t^+ \boldsymbol{O}^\top), \\ \boldsymbol{Q}_t &= \beta \boldsymbol{Q}_{t-1} + (1-\beta)(\boldsymbol{G}_t d_t d_t^\top \boldsymbol{G}_t^\top). \end{aligned} \tag{18}$$

However, directly updating covariance matrices faces hurdles with positive-definiteness and high dimensionality. As shown in Figure 2, our ELTO-AKF approach circumvents these issues by operating on the Cholesky

---

Algorithm 2 Kernel Kalman Filtering with Dynamic Parameter Adaptation

---

1: **Input:** $\boldsymbol{T}$, $\boldsymbol{O}$, $\boldsymbol{m}_0$, $\boldsymbol{M}$, $\boldsymbol{L}$, $\boldsymbol{S}_0$, $\boldsymbol{Q}_\theta$, $\boldsymbol{R}_\theta$ from Algorithm 1, window size w, and memory factors (α, β).

2: **for** $t = 1, \ldots, T$ **do**

3:      *//— Prediction —*

4:      $\boldsymbol{m}_t^- \leftarrow \boldsymbol{T}\boldsymbol{m}_{t-1}^+, \quad \boldsymbol{S}_t^- \leftarrow \boldsymbol{T}\boldsymbol{S}_{t-1}^+\boldsymbol{T}^\top + \boldsymbol{Q}_\theta$

5:      *//— Update —*

6:      $\boldsymbol{G}_t \leftarrow \boldsymbol{S}_t^-\boldsymbol{O}^\top(\boldsymbol{G}_y\boldsymbol{O}\boldsymbol{S}_t^-\boldsymbol{O}^\top + \boldsymbol{R}_\theta)^{-1}$ ▷ *Kalman gain*

7:      $d_t \leftarrow \boldsymbol{o}(\boldsymbol{y}_t) - \boldsymbol{G}_y\boldsymbol{O}\boldsymbol{m}_t^-$ ▷ *Innovation*

8:      $\boldsymbol{m}_t^+ \leftarrow \boldsymbol{m}_t^- + \boldsymbol{G}_t d_t, \quad \boldsymbol{S}_t^+ \leftarrow (\boldsymbol{I} - \boldsymbol{G}_t\boldsymbol{G}_y\boldsymbol{O})\boldsymbol{S}_t^-$

9:      $\epsilon_t \leftarrow \boldsymbol{o}(\boldsymbol{y}_t) - \boldsymbol{G}_y\boldsymbol{O}\boldsymbol{m}_t^+$ ▷ *Residual*

10:      *//— Dynamic Parameter Adaptation —*

11:      $k \leftarrow \lfloor t/w \rfloor, \quad r \leftarrow t \bmod w$

12:      **if** $r = 0$ and not $\alpha = \beta = 1$ **then**   ▷ *In this condition, $\boldsymbol{Q}$, $\boldsymbol{R}$ are time-variant. θ is abbreviated.*

13:          $\hat{\boldsymbol{R}}_k \leftarrow \frac{1}{w}\sum_{i=(k-1)w+1}^{kw} \epsilon_i\epsilon_i^\top + \boldsymbol{G}_y\boldsymbol{O}\boldsymbol{S}_{kw}^+\boldsymbol{O}^\top, \quad \hat{\boldsymbol{Q}}_k \leftarrow \frac{1}{w}\sum_{i=(k-1)w+1}^{kw} \boldsymbol{G}_i d_i d_i^\top \boldsymbol{G}_i^\top$

14:          $\hat{\boldsymbol{R}}_k^S \leftarrow \text{SP}(\hat{\boldsymbol{R}}_k), \quad \hat{\boldsymbol{Q}}_k^S \leftarrow \text{SP}(\hat{\boldsymbol{Q}}_k)$ ▷ *Sparse projection into SB structure*

15:          $\hat{\boldsymbol{M}}_k \leftarrow \text{Decompose}(\hat{\boldsymbol{R}}_k^S), \quad \hat{\boldsymbol{L}}_k \leftarrow \text{Decompose}(\hat{\boldsymbol{Q}}_k^S)$ ▷ *Cholesky decomposition*

16:          $\boldsymbol{M} \leftarrow \alpha\boldsymbol{M} + (1-\alpha)\hat{\boldsymbol{M}}_k, \quad \boldsymbol{L} \leftarrow \beta\boldsymbol{L} + (1-\beta)\hat{\boldsymbol{L}}_k$

17:          $\boldsymbol{R} \leftarrow \boldsymbol{M}\boldsymbol{M}^\top, \quad \boldsymbol{Q} \leftarrow \boldsymbol{L}\boldsymbol{L}^\top$

18:      **end if**

19:      *//— Projection back to the original space —*

20:      $\hat{\boldsymbol{\eta}}_t, \hat{\boldsymbol{\Sigma}}_t \leftarrow \text{pre\_image}(\boldsymbol{m}_t^+, \boldsymbol{S}_t^+)$ ▷ *$\hat{\boldsymbol{\eta}}_t$ is a short-hand notation for $\hat{\boldsymbol{\eta}}_t(\theta)$.*

21: **end for**

22: **Output:** $[\hat{\boldsymbol{\eta}}_1, \ldots, \hat{\boldsymbol{\eta}}_T]$ and $[\hat{\boldsymbol{\Sigma}}_1, \ldots, \hat{\boldsymbol{\Sigma}}_T]$

---

factors ($\boldsymbol{L}$ and $\boldsymbol{M}$), leveraging the advantages of the SB parameterization. This approach guarantees that $\boldsymbol{Q}$ and $\boldsymbol{R}$ are SPD matrices and maintains their tractability. Without the SPD guarantee for the noise covariance matrices, the performance of traditional Kalman filtering can degrade significantly (Greenberg et al., 2023).

The adaptive process begins with initial Cholesky factors $\boldsymbol{L}_0$ and $\boldsymbol{M}_0$, defining $\boldsymbol{Q}_0 = \boldsymbol{L}_0\boldsymbol{L}_0^\top$ and $\boldsymbol{R}_0 = \boldsymbol{M}_0\boldsymbol{M}_0^\top$. For the periodic updates, we employ a sparse projection operator $\text{SP}(\cdot)$, defined in two stages. First, we enforce the SB structure on the dense estimate $\boldsymbol{A}$ (representing either $\hat{\boldsymbol{Q}}_k$ or $\hat{\boldsymbol{R}}_k$) by averaging its block traces: $\theta_{ij} = \frac{\text{tr}(\boldsymbol{A}_{ij})}{\text{rank}(\boldsymbol{A}_{ij})}$, yielding an intermediate matrix $\tilde{\boldsymbol{A}}$. Second, to guarantee the SPD property required for Cholesky factorization, we perform the rectification $\boldsymbol{A}^S = \boldsymbol{V}\max(\boldsymbol{\Lambda}, \xi\boldsymbol{I})\boldsymbol{V}^\top$, where $\tilde{\boldsymbol{A}} = \boldsymbol{V}\boldsymbol{\Lambda}\boldsymbol{V}^\top$ is obtained by the eigen-decomposition. $\xi > 0$ is a minimum stability threshold. The resulting positive-definite matrix $\boldsymbol{A}^S$ is decomposed into Cholesky factors, which are then updated using the memory terms, as detailed in Algorithm 2.

4 Numerical Experiments on Sequential State Estimation

4.1 Noisy Pendulum System

To evaluate the performance of our proposed method in a standard filtering context, we first examined its denoising ability on a simulated pendulum task. The experimental setup follows the one described in (Gebhardt et al., 2019), based on a simulated single pendulum system[2]. For each simulation run, the initial angle q_0 and angular velocity $\dot{q}_0$ were uniformly sampled from the ranges $[-0.25\pi, 0.25\pi]$ and $[-2\pi, 2\pi]$ rad/s, respectively. The dynamics were simulated at 10,000 Hz with a normally distributed process noise of standard deviation n_p (default $n_p = 0.1$), while observations of the joint positions were collected at 10 Hz with an additive Gaussian noise of standard deviation n_o (default $n_o = 0.01$) centered on the true angle q_t.

---

[2]The simulation was performed using the code available at `https://github.com/gregorgebhardt/pyKKR`.

Table 1: Denoising performance on the pendulum dataset under various noise conditions.

Noise Setting	MSE ($\times 10^{-3}$)			
	SubKKR	KKR	ELTO-KF	ELTO-AKF
Default noise ($n_p = 0.1, n_o = 0.01$)	2.7574	1.1185	**0.1010**	0.1012
High process noise ($n_p = 0.2, n_o = 0.01$)	3.9321	3.4061	0.2325	**0.1123**
High observation noise ($n_p = 0.1, n_o = 0.1$)	13.192	15.797	11.278	**8.881**

The generated data was partitioned into a training sequence of 1500 and a test sequence of 300 time steps. The spectral learning architecture was trained using the Adam optimizer with a learning rate of 10^{-3} and configured with a window size of 5. For our proposed structured noise model, which used a diagonal parameterization with $k_q = k_r = 5$ blocks, the optimal noise variances were tuned using CMA-ES.

We compared the performance of our proposed ELTO-AKF ($\alpha = \beta = 1$) against other optimized methods, including the standard ELTO-KF and two other kernel-based filtering methods: the kernel Kalman rule (KKR) and the subspace KKR (SubKKR). Performance was measured by MSE between the estimated and true latent states, averaged over 5 independent trials. The results, presented in Table 1, show that our proposed method achieves comparable performance to the baseline ELTO-KF under default noise conditions but significantly outperforms all benchmark methods in scenarios with high process noise or high observation noise.

4.2 Non-Stationary Lidar Measurements

We conducted a filtering experiment on a single, long synthetic trajectory to evaluate our method's ability to handle changing dynamics. Inspired by the tracking problems in (Greenberg et al., 2023), our experimental setup is modified to test the model's ability to handle changing dynamics within a continuous data stream of Lidar measurements[3]. Each trajectory consists of multiple segments of variable length, with each segment defined by constant radial and tangential accelerations sampled from a normal distribution. This process generates a path with alternating periods of straight-line motion and coordinated turns, creating the piecewise non-stationary dynamics. The base simulation uses initial positions in [-50, 50] per axis, an initial velocity magnitude in [1, 5], and radial and tangential acceleration standard deviations of 0.1 and 0.5. The generated trajectory provides the true path and corresponding noisy observations, which are then standardized. For a comprehensive evaluation, we created distinct datasets by systematically varying two key factors: noise levels (categorized as default, high, and very high) and trajectory segment lengths (categorized as default, small, and large)[4].

The first 50% of the trajectory is used for training, and the other half is used for testing. To establish a global static baseline, we configured the ELTO-AKF ($\alpha = \beta = 1$) and optimized its initial noise parameters (i.e., $\boldsymbol{Q}_0, \boldsymbol{R}_0$) by minimizing the validation MSE using the CMA-ES algorithm. Furthermore, to evaluate the inherent online robustness of the dynamic parameter adaptation, we tested the method on the same trajectory datasets without dataset-specific tuning, simply fixing the memory factors at ($\alpha = \beta = 0.9$) based on empirical guidelines in the AEKF literature (Akhlaghi et al., 2017). The results are shown in Table 2. Other initial parameters of the stochastic realization and the Kalman filter were fixed equally.

4.3 Discovery of Burgers' equations from highly noisy data

Our ELTO-AKF approach is well-suited for denoising noisy state variables using learned noise covariance matrices, improving the quality of the observational data. The improved data quality can, in turn, support downstream tasks of data-driven partial differential equation (PDE) discovery (Rudy et al., 2017), yielding more accurate recovery of governing PDEs. We aim to identify sparse governing PDEs parameterized in the following form: $u_t = \mathcal{N}(u, u_x, u_{xx}, \dots)$; where $\mathcal{N}$ denotes a hidden nonlinear operator involving the state

---

[3]The simulation was performed using code adapted from `https://github.com/ido90/Optimized-Kalman-Filter`.

[4]The specific parameter settings for each group are as follows: Noise Levels (in terms of `noise_r`, `noise_t`): Default (1, 0.5), High (2, 1.5), and Very High (5, 2.5); Segment Lengths (in terms of `n_intervals`, `int_len`): Default ((25, 30), (20, 25)), Small ((50, 60), (10, 12)), and Large ((10, 15), (40, 50)).

Table 2: Filtering performance on the synthetic non-stationary trajectory, where the specific simulation parameters for each group are detailed in footnote 4. The "Adaptive" evaluation aims to verify that the ELTO-AKF performs well without hyperparameter tuning. This version of ELTO-AKF can be built very quickly; therefore, the results may not be directly comparable with those from the "Optimized" evaluation.

| Parameter Group | Settings | MSE($\times 10^{-2}$) Optimized (Trained) | | Adaptive (Fixed Hyperparams) | |
		ELTO-KF	ELTO-AKF ($\alpha = \beta = 1$)	ELTO-KF	ELTO-AKF ($\alpha = \beta = 0.9$)
Noise Levels	Default	8.2825	**1.9466**	20.7132	**8.8112**
	High	12.5629	**5.0497**	33.9798	**11.2288**
	Very High	24.5529	**13.0486**	81.5785	**35.0613**
Segment Lengths	Small	9.2305	**3.9511**	22.2544	**6.5787**
	Large	12.9478	**7.9840**	26.2269	**11.9133**

Table 3: Comparison of PDE discovery results with and without denoising the noisy state variables. The mean squared error (MSE) implies the L2-distance between the data used for PDE discovery and the clean state-variable data. Better scores are shown in **bold**. The ELTO-AKF algorithm is run with $\alpha = \beta = 1$, and the correct viscosity is 0.1.

Denoising	MSE ($\times 10^{-3}$)	Identified PDE	MAPE	L1 Relative Error ($\times 10^{-2}$)
N/A	8.08	$-0.959286uu_x + 0.076843u_{xx}$	13.61	5.81
ELTO-AKF	**2.48**	$-0.940588uu_x + 0.098496u_{xx}$	**3.72**	**5.54**

variable u and its spatial derivatives (e.g., $u_x, u_{xx}, \dots$). We assume $\mathcal{N}$ is expressed as a linear combination of a few active terms in the (sparse) governing equation. To identify the underlying PDE, we solve a sparse or best-subset regression problem constructed over a library of (independent) candidate terms, with the temporal derivative u_t serving as the vector response for selecting the most relevant terms. Remark that, we only have access to noisy values of $u(x, t)$ on a discretized spatiotemporal domain. By applying numerical differentiation or weak-form computation (Reinbold et al., 2020), we can construct an overcomplete candidate library, setting up a system of equations for the regression problem. The best model (optimally balancing between approximation error and model complexity) that is most likely to represent the actual governing PDE is selected using information criteria (Thanasutives et al., 2024; 2025).

We aim to demonstrate that refining the observed states using our ELTO-AKF improves the accuracy of identified PDE coefficients. The parametric Burgers' equation is used as an example. The equation reads $u_t = \begin{bmatrix} uu_x & u_{xx} \end{bmatrix} \boldsymbol{\xi}$; where $\boldsymbol{\xi}$ is the true PDE coefficient vector, containing the kinematic viscosity (or diffusion coefficient) ϑ. We study $\boldsymbol{\xi} = \begin{bmatrix} -1 & \vartheta \end{bmatrix}^T$; where $\vartheta = 0.1$ or $\frac{0.01}{\pi}$. In the latter case, the viscosity is so small that shock waves develop in the PDE solution, and hence, abrupt changes occur in the system dynamics. To generate $u(x, t)$, the clean state variable is perturbed with Gaussian noise drawn from $\frac{\epsilon \sigma}{100} \mathcal{N}(0, 1)$, where σ denotes the standard deviation of the clean state variable. The noise level is controlled by the parameter ϵ.

Our noise covariances are trained to denoise by mapping doubly noisy data to (noisy) observed data. Here, the doubly noisy $\tilde{u}(x, t) = u(x, t) + \mathcal{N}(0, \tilde{\sigma}^2)$ refers to noisy observations further perturbed with synthetic Gaussian noise, whose standard deviation $\tilde{\sigma}$ is estimated using a robust wavelet-based estimator (Donoho & Johnstone, 1994). A key practical advantage of using $\tilde{u}$ is that it does not need the clean state variable for training and validation. During the test phase, after obtaining the learned noise covariance matrices, we use them to denoise the observations. The resulting noise-reduced data are passed through the PDE discovery method to estimate a sparse vector $\hat{\boldsymbol{\xi}}$ of the PDE coefficients, for which we calculate the average of its absolute percentage errors, each defined by $\mathcal{E}_j(\boldsymbol{\xi}, \hat{\boldsymbol{\xi}}) = \left| \frac{\xi_j - \hat{\xi}_j}{\xi_j} \right|$. Another evaluation metric we consider, which is less susceptible to errors in estimating small coefficients, is the L1 relative error: $\frac{||\boldsymbol{\xi} - \hat{\boldsymbol{\xi}}||_1}{||\boldsymbol{\xi}||_1}$.

To empirically demonstrate the effectiveness of our ELTO-AKF in denoising, we first conduct experiments on discovering the canonical Burgers' equation with viscosity $\vartheta = 0.1$ under a high noise level of $\epsilon = 50$. Table 3 shows that the denoised state-variable data resemble the clean data (as illustrated in Figure 3) more closely

(a) Burgers' equation with no shock waves is simulated using a Gaussian initial condition.

(b) Burgers' equation with shock waves is simulated using a periodic initial condition.

Figure 3: The state-variable data are depicted under three conditions: the clean data, the noisy ($\epsilon = 50$) observed data, and the denoised data produced by the ELTO-AKF, which shows the smallest MSE to the clean data.

Table 4: Comparison of denoising methods based on the ELTO-KF and our proposed ELTO-AKF with varying memory factors. Here, the correct viscosity is $\frac{0.01}{\pi}$. Note that the identified PDE is incorrect when no denoising is applied; therefore, its evaluation metrics are unavailable (N/A).

Denoising	MSE ($\times 10^{-2}$)	Identified PDE	MAPE	L1 Relative Error ($\times 10^{-1}$)
N/A	N/A	$-0.464365uu_x + 0.000163u^2 u_{xx}$	N/A	N/A
ELTO-KF	2.70	$-0.677635uu_x + 0.006934u_{xx}$	75.03	3.25
ELTO-AKF ($\alpha = \beta = 1$)	2.76	$-0.742664uu_x + 0.003891u_{xx}$	**23.99**	2.57
ELTO-AKF ($\alpha = \beta = 0.7$)	**2.19**	$-0.787012uu_x + 0.004537u_{xx}$	31.92	**2.14**

than the noisy observed data, as evidenced by the decreased MSE. Therefore, a higher-quality PDE—closer to the true governing form, as indicated by the low MAPE (around 4%) and the small L1 relative error—is identified. Then, we experiment on the viscous Burgers' equation exhibiting shock waves, where the PDE solution becomes discontinuous in space after a certain time, to reveal the full ELTO-AKF's capability in adapting to local dynamics by adjusting the memory factors. As shown in Table 4, the identified governing equation is incorrect if no denoising is applied and remains of low quality when denoising is performed using the ELTO-KF approach. The ELTO-AKF with adaptation to local dynamics achieves the best performance in terms of the MSE and the L1 relative error, whereas the ELTO-AKF with full memory attains the lowest MAPE. Therefore, whether the inclusion of dynamic parameter adaptation yields better performance depends on the dataset, and currently no definitive conclusion can be drawn.

5   Conclusions

We introduced the ELTO-AKF, which addresses the limitations of the standard ELTO-KF in learning non-stationary dynamics through the novel structured noise adaptation. The computationally tractable SB parameterization is proposed, guaranteeing that the symmetric positive-definite property of the noise covariance matrices by updating their Cholesky factors during the dynamic parameter adaptation. This structured parameterization grants our proposed method the capability of structured noise adaptation: learning globally robust, time-invariant noise models through optimization, while dynamically tracking time-varying system dynamics using filter residuals. Empirical results in dynamic state estimation reveal that the ELTO-AKF significantly outperforms baseline methods in challenging non-stationary processes. Furthermore, when applied as a denoising method for data-driven PDE discovery, our ELTO-AKF method reduces the identification error for complex systems governed by the viscous Burgers' equation, whose solutions exhibit shock waves.

References

Gabriel Agamennoni, Juan I Nieto, and Eduardo M Nebot. Approximate inference in state-space models with heavy-tailed noise. *IEEE Transactions on Signal Processing*, 60(10):5024–5037, 2012.

Shahrokh Akhlaghi, Ning Zhou, and Zhenyu Huang. Adaptive adjustment of noise covariance in kalman filter for dynamic state estimation. In *2017 IEEE power & energy society general meeting*, pp. 1–5. IEEE, 2017.

Charles R Baker. Joint measures and cross-covariance operators. *Transactions of the American Mathematical Society*, 186:273–289, 1973.

P. Becker, H. Pandya, G. Gebhardt, C. Zhao, C.J. Taylor, and G. Neumann. Recurrent kalman networks: Factorized inference in high-dimensional deep feature spaces. In *Proc. of the 36th Int'l Conf. on Machine Learning*, volume PMLR 97, pp. 544–552, 2019.

Victor DeMiguel, Alberto Martín-utrera, and Raman Uppal. A multifactor perspective on volatility-managed portfolios. *The Journal of Finance*, 79(6):3859–3891, 2024.

David L Donoho and Iain M Johnstone. Ideal spatial adaptation by wavelet shrinkage. *Biometrika*, 81(3): 425–455, 09 1994. ISSN 0006-3444. doi: 10.1093/biomet/81.3.425. URL https://doi.org/10.1093/biomet/81.3.425.

Gerardo Duran-Martin, Matias Altamirano, Alexander Y Shestopaloff, Leandro Sánchez-Betancourt, Jeremias Knoblauch, Matt Jones, François-Xavier Briol, and Kevin Murphy. Outlier-robust kalman filtering through generalised bayes. *arXiv preprint arXiv:2405.05646*, 2024.

Kenji Fukumizu, Le Song, and Arthur Gretton. Kernel bayes' rule: Bayesian inference with positive definite kernels. *Journal of Machine Learning Research*, 14(118):3753–3783, 2013. URL http://jmlr.org/papers/v14/fukumizu13a.html.

G.H.W. Gebhardt, A. Kupcsik, and G. Neumann. The kernel kalman rule: Efficient nonparametric inference by recursive least-squares and subspace projections. *Machine Learning*, 108:2113–2157, 2019.

Ido Greenberg, Netanel Yannay, and Shie Mannor. Optimization or architecture: How to hack kalman filtering. *Advances in Neural Information Processing Systems*, 36:50482–50505, 2023.

Nikolaus Hansen. The CMA evolution strategy: A comparing review. *Towards a new evolutionary computation: Advances in the estimation of distribution algorithms*, pp. 75–102, 2006.

Rudolph Emil Kalman. A new approach to linear filtering and prediction problems. 1960.

T. Katayama. *Subspace Methods for System Identification*. Springer, 2005.

Naichang Ke, Ryogo Tanaka, and Yoshinobu Kawahara. Learning stochastic nonlinear dynamics with embedded latent transfer operators. In Yingzhen Li, Stephan Mandt, Shipra Agrawal, and Emtiyaz Khan (eds.), *Proceedings of The 28th International Conference on Artificial Intelligence and Statistics*, volume 258 of *Proceedings of Machine Learning Research*, pp. 4861–4869. PMLR, 03–05 May 2025. URL `https://proceedings.mlr.press/v258/ke25a.html`.

Cl Masreliez and R Martin. Robust bayesian estimation for the linear model and robustifying the kalman filter. *IEEE transactions on Automatic Control*, 22(3):361–371, 2003.

Jeff M Phillips and Suresh Venkatasubramanian. A gentle introduction to the kernel distance. *arXiv preprint arXiv:1103.1625*, 2011.

José C Pinheiro and Douglas M Bates. Unconstrained parametrizations for variance-covariance matrices. *Statistics and computing*, 6(3):289–296, 1996.

Patrick A. K. Reinbold, Daniel R. Gurevich, and Roman O. Grigoriev. Using noisy or incomplete data to discover models of spatiotemporal dynamics. *Phys. Rev. E*, 101:010203, Jan 2020. doi: 10.1103/PhysRevE.101.010203. URL `https://link.aps.org/doi/10.1103/PhysRevE.101.010203`.

Samuel H Rudy, Steven L Brunton, Joshua L Proctor, and J Nathan Kutz. Data-driven discovery of partial differential equations. *Science Advances*, 3(4):e1602614, 2017.

Bernhard Schölkopf. The kernel trick for distances. *Advances in neural information processing systems*, 13, 2000.

Le Song, Jonathan Huang, Alex Smola, and Kenji Fukumizu. Hilbert space embeddings of conditional distributions with applications to dynamical systems. In *Proceedings of the 26th annual international conference on machine learning*, pp. 961–968, 2009.

Pongpisit Thanasutives, Takashi Morita, Masayuki Numao, and Ken-ichi Fukui. Adaptive uncertainty-penalized model selection for data-driven pde discovery. *IEEE Access*, 12:13165–13182, 2024. doi: 10.1109/ACCESS.2024.3354819.

Pongpisit Thanasutives, Yoshinobu Kawahara, and Ken-ichi Fukui. Bayesian model selection for variable-coefficient partial differential equation discovery. *Results in Engineering*, 27:106930, 2025. ISSN 2590-1230. doi: https://doi.org/10.1016/j.rineng.2025.106930. URL `https://www.sciencedirect.com/science/article/pii/S2590123025029883`.

Hongwei Wang, Hongbin Li, Jun Fang, and Heping Wang. Robust gaussian kalman filter with outlier detection. *IEEE Signal Processing Letters*, 25(8):1236–1240, 2018.

Jinling Wang. Stochastic modeling for real-time kinematic gps/glonass positioning. *Navigation*, 46(4):297–305, 1999.

A Matrix-based Spectral Learning Algorithm for Operator Identification

This section summarizes the spectral learning algorithm proposed by Ke et al. (2025) for estimating the Embedded Latent Transfer Operators (ELTO). This algorithm provides a constructive method to derive the latent state estimates directly from the observation history, which enables the computation of the empirical matrices $\boldsymbol{T}$ and $\boldsymbol{O}$ used in the main text.

The empirical estimation process begins with a finite observation sequence $\boldsymbol{Y} = [\boldsymbol{y}_1, \ldots, \boldsymbol{y}_T]$ and a window size h. Vectors for the past and future, $\boldsymbol{y}_{p,n}$ and $\boldsymbol{y}_{f,n}$, are constructed for each time step $n = 1, \ldots, N$, where $N := T - 2h + 2$ is the total number of windows:

$$\boldsymbol{y}_{p,n} := [\boldsymbol{y}_{n+h-2}, ..., \boldsymbol{y}_{n-1}]^\top, \quad \boldsymbol{y}_{f,n} := [\boldsymbol{y}_{n+h-1}, ..., \boldsymbol{y}_{2h-2+n}]^\top. \tag{19}$$

These vectors are then mapped into the RKHS. For example, for the past window, this results in a feature matrix:

$$\Phi_{p,n} := [\phi_y(\boldsymbol{y}_{n+h-2}), \ldots, \phi_y(\boldsymbol{y}_{n-1})]. \tag{20}$$

The empirical covariance matrices are then computed from the features of these windows. Let $\Phi_p = [\Phi_{p,1}, \ldots, \Phi_{p,N}]$ and $\Phi_f = [\Phi_{f,1}, \ldots, \Phi_{f,N}]$ be the feature matrices for the entire sequence of past and future windows, and let $\boldsymbol{Q}_N := \boldsymbol{I}_N - \frac{1}{N}\boldsymbol{1}_N\boldsymbol{1}_N^\top$ be a centering matrix. The covariance matrices are given by:

$$\boldsymbol{C}_{pp} := \frac{1}{N}\Phi_p \boldsymbol{Q}_N \Phi_p^\top, \quad \boldsymbol{C}_{ff} := \frac{1}{N}\Phi_f \boldsymbol{Q}_N \Phi_f^\top, \quad \boldsymbol{C}_{fp} := \frac{1}{N}\Phi_f \boldsymbol{Q}_N \Phi_p^\top. \tag{21}$$

After computing the Cholesky factorizations $\boldsymbol{C}_{ff} = \boldsymbol{L}\boldsymbol{L}^\top$ and $\boldsymbol{C}_{pp} = \boldsymbol{M}\boldsymbol{M}^\top$, a singular-value decomposition (SVD) of the normalized cross-covariance is performed:

$$\boldsymbol{L}^{-1}\boldsymbol{C}_{fp}(\boldsymbol{M}^{-1})^\top \approx \hat{\boldsymbol{U}}\hat{\boldsymbol{S}}\hat{\boldsymbol{V}}^\top. \tag{22}$$

This yields a projection matrix $\boldsymbol{B} := \hat{\boldsymbol{S}}^{1/2}\hat{\boldsymbol{V}}^\top\boldsymbol{M}^{-1}$. To construct the latent state, a feature matrix $\Phi_S = [\phi_y(\boldsymbol{y}_{e_1}), \ldots, \phi_y(\boldsymbol{y}_{e_{|S|}})]$ is formed from a subset of observations $S \subseteq \{\boldsymbol{y}_0, \ldots, \boldsymbol{y}_T\}$. A vector of weights, w, is then learned by optimizing a loss function related to the canonical correlations. The latent state vector is then constructed as:

$$\boldsymbol{x}_n = \boldsymbol{B}\Phi_{p,n}^\top \Phi_S w, \tag{23}$$

where $\Phi_S w$ represents a projection into the RKHS learned via the spectral method to maximize canonical correlations.

With the latent state sequence $\{\boldsymbol{x}_n\}$ obtained, the system's dynamics are modeled. Using the feature matrices defined previously, the embedded operators $\mathcal{T}_e$ and $\mathcal{O}_e$ are empirically estimated as regularized operators:

$$\hat{\mathcal{T}}_e = \boldsymbol{\Psi}_2 \boldsymbol{\Psi}_1^\top (\boldsymbol{\Psi}_1 \boldsymbol{\Psi}_1^\top + \epsilon_t \mathcal{I})^{-1}, \tag{24}$$

$$\hat{\mathcal{O}}_e = \boldsymbol{\Phi}\boldsymbol{\Psi}^\top (\boldsymbol{\Psi}\boldsymbol{\Psi}^\top + \epsilon_o \mathcal{I})^{-1}. \tag{25}$$

where $\boldsymbol{\Psi}_1 := \boldsymbol{\Psi}_{:,1:N-1}$, $\boldsymbol{\Psi}_2 := \boldsymbol{\Psi}_{:,2:N}$, and $\epsilon_t, \epsilon_o > 0$. For the matrix-based implementation of the Kalman filter used in the main text (Section 3.2), we require the $N \times N$ matrix representations of these operators, which are derived by applying the kernel trick. Following (Gebhardt et al., 2019), we first define the necessary Gram matrices: $\boldsymbol{G}_{\tilde{x}} = \boldsymbol{\Psi}_1^\top \boldsymbol{\Psi}_1$, $\boldsymbol{G}_{\tilde{x}x} = \boldsymbol{\Psi}_1^\top \boldsymbol{\Psi}_2$, $\boldsymbol{G}_x = \boldsymbol{\Psi}^\top \boldsymbol{\Psi}$, and $\boldsymbol{G}_{yx} = \boldsymbol{\Phi}^\top \boldsymbol{\Psi}$. This allows the operator in Equation 24-25 to be re-expressed as the $N \times N$ matrices $\boldsymbol{T}$ and $\boldsymbol{O}$:

$$\boldsymbol{T} = (\boldsymbol{G}_{\tilde{x}} + \epsilon_t \boldsymbol{I}_N)^{-1}\boldsymbol{G}_{\tilde{x}x}, \tag{26}$$

$$\boldsymbol{O} = (\boldsymbol{G}_x + \epsilon_o \boldsymbol{I}_N)^{-1}\boldsymbol{G}_{yx}^\top. \tag{27}$$

These matrices $\boldsymbol{T}$ and $\boldsymbol{O}$, along with the noise matrices $\boldsymbol{Q}$ and $\boldsymbol{R}$, form the basis of the Kalman filtering process described in Section 3.2. The initialization of sequential state estimation with ELTOs is then given in Algorithm 3.

Algorithm 3 Learning system dynamics with the Embedded Latent Transfer Operator (ELTO)

1: **Input:** kernel function $k(\cdot, \cdot)$ and regularization parameters ϵ_t, ϵ_o.
2: Compute $\boldsymbol{T} = (\boldsymbol{G}_{\tilde{x}} + \epsilon_t \boldsymbol{I}_N)^{-1} \boldsymbol{G}_{\tilde{x}x}, \quad \boldsymbol{O} = (\boldsymbol{G}_x + \epsilon_o \boldsymbol{I}_N)^{-1} \boldsymbol{G}_{yx}^\top \quad\quad \triangleright$ Matrix representations of ELTO
3: Sample N basis vectors $\boldsymbol{u}_1, \ldots, \boldsymbol{u}_N$ from a multivariate Uniform distribution $\mathcal{U}(0, 1)$
4: Define the kernel matrix $\boldsymbol{K}_0$ where $(\boldsymbol{K}_0)_{i,j} = k_x(\boldsymbol{u}_i, \boldsymbol{x}_j)$ for $i = 1, \ldots, N$ and $j = 1, \ldots, N$
5: Compute the initial state embedding $\boldsymbol{C}_0 = (\boldsymbol{G}_x + \epsilon_o \boldsymbol{I}_N)^{-1} \boldsymbol{K}_0$
6: Compute mean $\boldsymbol{m}_0$ and variance $\boldsymbol{S}_0$ over the columns of $\boldsymbol{C}_0$
7: **Output:** $\boldsymbol{T}, \boldsymbol{O}, \boldsymbol{m}_0$, and $\boldsymbol{S}_0$

B Proof of Minimum-distance Preservation in RKHS

The following proof validates a general and crucial property of the radial basis function (RBF) kernel. We demonstrate that for any two arbitrary points $\mathbf{y}, \mathbf{y}' \in \mathbb{Y}$, the RBF kernel $k(\mathbf{y}, \mathbf{y}') = \exp(-\gamma \|\mathbf{y} - \mathbf{y}'\|_{\mathbb{Y}}^2)$, which is a shift-invariant kernel, guarantees a monotonic relationship between the input-space distance and the feature-space distance. This specific connection is a foundational result in kernel methods (Schölkopf, 2000), forming the basis of what is often termed the kernel distance (Phillips & Venkatasubramanian, 2011).

Proposition 2. For any two arbitrary points $\mathbf{y}, \mathbf{y}' \in \mathbb{Y}$ from the observation space, let the feature map $\phi : \mathbb{Y} \to \mathbb{H}$ be induced by the RBF kernel $(k(\mathbf{y}, \mathbf{y}') = \exp\left(-\gamma \|\mathbf{y} - \mathbf{y}'\|_{\mathbb{Y}}^2\right), \gamma > 0)$. The squared Euclidean distance in the feature space, $\|\phi(\mathbf{y}) - \phi(\mathbf{y}')\|_{\mathbb{H}}^2$, is a monotonically increasing function of the squared Euclidean distance in the observation space, $\|\mathbf{y} - \mathbf{y}'\|_{\mathbb{Y}}^2$.

Proof. We define the squared Euclidean distance in the Reproducing Kernel Hilbert Space (RKHS) $\mathbb{H}$ using the inner product $\langle \cdot, \cdot \rangle_{\mathbb{H}}$:

$$\|\phi(\mathbf{y}) - \phi(\mathbf{y}')\|_{\mathbb{H}}^2 = \langle \phi(\mathbf{y}) - \phi(\mathbf{y}'), \phi(\mathbf{y}) - \phi(\mathbf{y}') \rangle_{\mathbb{H}} \tag{28}$$

$$= \langle \phi(\mathbf{y}), \phi(\mathbf{y}) \rangle_{\mathbb{H}} + \langle \phi(\mathbf{y}'), \phi(\mathbf{y}') \rangle_{\mathbb{H}} - 2\langle \phi(\mathbf{y}), \phi(\mathbf{y}') \rangle_{\mathbb{H}}. \tag{29}$$

By the kernel trick, the inner product in the feature space can be computed by the kernel function in the input space:

$$\langle \phi(\mathbf{y}), \phi(\mathbf{y}') \rangle_{\mathbb{H}} = k(\mathbf{y}, \mathbf{y}'). \tag{30}$$

Substituting this into Equation 29, we get:

$$\|\phi(\mathbf{y}) - \phi(\mathbf{y}')\|_{\mathbb{H}}^2 = k(\mathbf{y}, \mathbf{y}) + k(\mathbf{y}', \mathbf{y}') - 2k(\mathbf{y}, \mathbf{y}'). \tag{31}$$

Specifically, the RBF kernel is shift-invariant (stationary), and $k(\mathbf{y}, \mathbf{y}) = k(\mathbf{y}', \mathbf{y}') = \exp(0) = 1$:

$$\|\phi(\mathbf{y}) - \phi(\mathbf{y}')\|_{\mathbb{H}}^2 = 2\left(1 - \exp(-\gamma \|\mathbf{y} - \mathbf{y}'\|_{\mathbb{Y}}^2)\right). \tag{32}$$

Since $\|\mathbf{y} - \mathbf{y}'\|_{\mathbb{Y}}^2 \geq 0$ and $\gamma > 0$, as d increases, the entire $\|\phi(\mathbf{y}) - \phi(\mathbf{y}')\|_{\mathbb{H}}^2$ increases. This directly proves that the feature-space squared distance is a monotonically increasing function of the input-space squared distance, confirming the property. $\square$

The significance of this general proof is that it provides the formal justification for kernel-based optimization frameworks. By proving this monotonic property, we confirm that minimizing the squared residual in the RKHS (i.e., $\|\phi(\mathbf{y}) - \phi(\mathbf{y}')\|_{\mathbb{H}}^2$) is equivalent to minimizing the squared residual in the original observation space (i.e., $\|\mathbf{y} - \mathbf{y}'\|_{\mathbb{Y}}^2$). This ensures that an optimal solution found in the RKHS also corresponds to an optimal solution in the observation space (i.e., Equation 16).

C Ablation Study on Structured Noise Parameterization

To evaluate the contribution of the proposed scalar-block (SB) parameterization in dynamic adaptation, we compare our full model with an ablated baseline that lacks the SB parameterization. We compare our

full ELTO-AKF with SB structure against an ablated baseline, ELTO-AKF without SB structure. The full model (Algorithm 2) projects noise estimates onto the SB space and updates its low-dimensional Cholesky factors $(\boldsymbol{M}_k, \boldsymbol{L}_k)$ to guarantee SPD. The ablated baseline skips this step, simulating a standard AEKF by applying updates directly to the full, dense $\boldsymbol{R}$ and $\boldsymbol{Q}$ matrices.

Both models were tested on the non-stationary trajectories (Section 4.2) using the same fixed hyperparameters ($\alpha = \beta = 0.9$) and were initialized from the same optimal $\boldsymbol{Q}_0, \boldsymbol{R}_0$ found by data-driven optimization. The specific simulation parameters for different noise levels are detailed in footnote 4.

Table 5: Performance comparison of structured (with SB Structure) vs. unstructured (without SB Structure) adaptive noise models on the non-stationary trajectory. All models use a fixed adaptation rate ($\alpha = \beta = 0.9$).

| Noise Level | MSE($\times 10^{-2}$) ELTO-AKF (Adaptive, $\alpha = \beta = 0.9$) | |
	(with SB structure)	(without SB structure)
Default	**8.8112**	26.7737
High	**11.2288**	20.1178
Very High	**35.0613**	44.8016

Table 6: Performance comparison of different adaptation rate ($\alpha = \beta = 0.3, 0.5, 0.7, 0.9$) on non-stationary trajectories (train noise = test noise).

| Noise Level | MSE($\times 10^{-2}$) ELTO-AKF | | | |
	$\alpha = \beta = 0.9$	$\alpha = \beta = 0.7$	$\alpha = \beta = 0.5$	$\alpha = \beta = 0.3$
Default	**8.8112**	10.7419	10.9886	29.4613
High	**11.2288**	11.4485	13.0108	14.2895
Very High	**35.0613**	35.8572	41.6618	41.0659

Table 7: Performance comparison of different adaptation rate ($\alpha = \beta = 0.3, 0.5, 0.7, 0.9$) on non-stationary trajectories (train noise $\neq$ test noise).

| Noise Level | | MSE($\times 10^{-1}$) ELTO-AKF | | | |
Train	Test	$\alpha = \beta = 0.9$	$\alpha = \beta = 0.7$	$\alpha = \beta = 0.5$	$\alpha = \beta = 0.3$
Default	High	**4.3350**	4.4122	5.2780	6.0676
Default	Very High	**4.9642**	6.0275	6.6339	7.1362

Table 5 clearly demonstrate that our proposed ELTO-AKF (with SB structure) consistently outperforms the ablated (without SB structure) model. The lack of a guaranteed SPD property for the unstructured model's updates leads to numerical instability and potential matrix decomposition failures. These issues cause significant performance degradation, with results often falling below its SB-structured counterpart.

We also compare the model performance on non-stationary trajectories under different adaptation rate. As shown in Tables 6 and 7, higher values of the memory factors (i.e., $\alpha = \beta = 0.9$ or $\alpha = \beta = 0.7$) lead to improved dynamic state estimation. This suggests that preserving global patterns and maintaining consistency are essential for learning non-stationary trajectories in this ablation study, particularly when combined with an appropriately lower weighting of dynamic parameter adaptation.