Regular Fourier Features for Nonstationary Gaussian Processes

Abstract

Simulating a Gaussian process requires sampling from a high-dimensional Gaussian distribution, which scales cubically with the number of sample locations. Spectral methods address this challenge by exploiting the Fourier representation and treating the spectral density as a probability distribution suitable for Monte Carlo approximation. Although this probabilistic interpretation is valid for stationary processes, it is overly restrictive for the nonstationary case, where spectral densities are generally not probability measures. We propose regular Fourier features for harmonizable processes to avoid this limitation. Our method discretizes the spectral representation directly, preserving the correlation structure among spectral weights without requiring probability assumptions. Under a finite-spectral-support assumption, this yields an efficient low-rank approximation that is consistent and positive semi-definite by construction. When the spectral density is unknown, the framework extends naturally to kernel learning from data. We demonstrate the method on locally stationary and harmonizable mixture kernels, the latter with a complex-valued spectral density, and apply the kernel-learning extension to real and synthetic data.

1 Introduction

Gaussian processes (GPs) are widely used in fields such as machine learning (Rasmussen & Williams, 2005) and geostatistics (Higdon et al., 1998). Their appeal lies in flexible nonparametric regression with principled uncertainty estimates and closed-form computations. These closed-form solutions are powerful but computationally expensive: simulating a GP at n locations requires decomposing an $n \times n$ kernel matrix, which scales as $\mathcal{O}(n^3)$ (Rasmussen & Williams, 2005).

Spectral methods offer an efficient alternative by exploiting the Fourier representation of stochastic processes. For stationary GPs, Rahimi & Recht (2007) introduced random Fourier features (RFFs), which treat the spectral density as a probability measure and approximate the kernel via Monte Carlo sampling. This yields a low-rank approximation with complexity $\mathcal{O}(nm^2)$, where $m \ll n$ is the number of features.

Extending RFFs to nonstationary processes requires treating $s(\omega, \omega')$ as a probability measure, an assumption that generally fails to hold. Existing spectral extensions (Samo & Roberts, 2015; Ton et al., 2018) make this assumption, which limits the class of representable kernels. In addition, their approximation is typically a biased and inconsistent estimator of the true kernel.

We propose regular Fourier features for harmonizable GPs that avoid these limitations. Our approach discretizes the spectral representation on a regular grid, following the classical Riemann sum approximation of Shinozuka & Jan (1972) for stationary simulation. For nonstationary processes, the spectral weights at different frequencies are correlated according to the spectral density $s(\omega_i, \omega_j)$. Preserving this correlation structure yields a low-rank approximation that is positive semi-definite by construction.

Our contributions are:

- We extend regular Fourier features to harmonizable processes without a probability interpretation; the resulting low-rank approximation is consistent and handles complex-valued spectral densities.

- We introduce a factorized spectral parametrization that guarantees a valid nonstationary kernel by construction and enables learning from data.

- We demonstrate the method on harmonizable kernels, and apply it to kernel learning on real and synthetic data.

2 Background

We consider harmonizable GPs, a broad class that includes stationary processes as a special case and encompasses many nonstationary processes of practical interest (Yaglom, 1987; Shen et al., 2019). A zero-mean GP is called harmonizable when it admits the spectral representation (Cramér, 1942; 1946; Loève, 1948)

$$Z(x) = \int_{\mathbb{R}} \exp(i\omega x) \, d\Gamma(\omega), \tag{1}$$

where $\{\Gamma(\omega)\}$ is a complex-valued zero-mean stochastic process indexed by ω, whose spectral distribution

$$S(\omega, \omega') = \mathrm{E}[\Gamma(\omega) \overline{\Gamma(\omega')}], \tag{2}$$

has bounded variation on $\mathbb{R} \times \mathbb{R}$ (Loève, 1948). The spectral distribution S is positive semi-definite and determines a positive semi-definite kernel $k(x, x') = \mathrm{E}[Z(x)\overline{Z(x')}]$ via the Fourier–Stieltjes integral (Loève, 1948)

$$k(x, x') = \iint_{\mathbb{R}^2} \exp(i(\omega x - \omega' x')) \, d^2 S(\omega, \omega'). \tag{3}$$

If the spectral distribution is differentiable, it admits a spectral density $s(\omega, \omega')$, and the integral reduces to

$$k(x, x') = \iint_{\mathbb{R}^2} \exp(i(\omega x - \omega' x')) \, s(\omega, \omega') \, d\omega \, d\omega'. \tag{4}$$

If $\{Z(x)\}$ is stationary, the spectral increments at distinct frequencies are uncorrelated, so the spectral measure concentrates on the diagonal $\omega = \omega'$. The kernel then depends only on the lag, and the double integral collapses to

$$k(x - x') = \int_{\mathbb{R}} \exp(i\omega(x - x')) \, dS(\omega), \tag{5}$$

or, when a spectral density $s(\omega)$ exists,

$$k(x - x') = \int_{\mathbb{R}} \exp(i\omega(x - x')) \, s(\omega) \, d\omega. \tag{6}$$

2.1 Random Fourier Features

For stationary processes, Rahimi & Recht (2007) observed that the spectral density $s(\omega)$, up to a scaling constant $\sigma^2 = k(0)$, is a probability density. This allows Monte Carlo approximation of the kernel:

$$
\begin{aligned}
k(x - x') &\approx \frac{\sigma^2}{m} \sum_{j=1}^{m} \exp(i\Omega_j x) \exp(-i\Omega_j x') \\
&= \boldsymbol{\Phi}(x)\boldsymbol{\Phi}(x')^{\dagger},
\end{aligned}
\tag{7}
$$

where $\Omega_j \sim p(\omega) \propto s(\omega)$, and the feature map is

$$\boldsymbol{\Phi}(x) = \frac{\sigma}{\sqrt{m}} \left(\exp(i\Omega_1 x) \quad \dots \quad \exp(i\Omega_m x) \right). \tag{8}$$

Table 1: Comparison of spectral methods for GPs. Checkmarks indicate supported features: nonstationary kernels, consistent approximation, positive semi-definiteness at finite rank, unconstrained spectral densities (no probability or real-valuedness assumption), and unbounded spectral support. Our method accepts bounded support in exchange for the remaining four features. The Samo & Roberts (2015, Th. 7) row refers to their universal density theorem; its Monte Carlo form has the same limitations as Ton et al. (2018).

Method	Nonstationary k	Consistent	Finite-rank PSD	Unconstrained s	Unbounded s
Rahimi & Recht (2007)	✗	✓	–	–	✓
Samo & Roberts (2015, Th. 7)	✓	✓	✗	✗	✓
Ton et al. (2018)	✓	✗	✓	✗	✓
This work	✓	✓	✓	✓	✗

The low-rank form $\mathbf{\Phi}(x)\mathbf{\Phi}(x')^{\dagger}$ ensures positive semi-definiteness by construction.

Generalizations to nonstationary processes (Samo & Roberts, 2015; Ton et al., 2018) require a probability interpretation of $s(\omega, \omega')$. A naïve Monte Carlo approximation would be

$$k(x, x') \approx \frac{\sigma^2}{m} \sum_{j=1}^{m} \exp(\mathrm{i}(\Omega_j x - \Omega'_j x')), \tag{9}$$

where $(\Omega_j, \Omega'_j) \sim p(\omega, \omega') \propto s(\omega, \omega')$. This approximation is not guaranteed to be positive semi-definite since $\Omega_j \neq \Omega'_j$ in general. This becomes clear by setting $m = 1$ and $x = x'$:

$$k(x, x) \approx \sigma^2 \exp(\mathrm{i}(\Omega_1 - \Omega'_1)x), \tag{10}$$

which is not guaranteed to be real, let alone nonnegative.

To address this, Samo & Roberts (2015); Ton et al. (2018) construct modified feature maps that ensure positive semi-definite approximations, but still constrain the spectral density to a probability measure. Consequently, kernel approximation or kernel learning is restricted to this class, and the low-rank approximation is biased and inconsistent (see Appendix A). For Samo & Roberts (2015), the inconsistency arises only in their Monte Carlo form: their universal density theorem is consistent, but its approximations are generally not positive semi-definite.

Alternative spectral approaches (Remes et al., 2017; Shen et al., 2019) propose parametric kernel families with structured spectral densities for nonstationary kernel learning. In contrast, our approach provides a general kernel decomposition for flexible kernel families. It requires no probability interpretation, is positive semi-definite by construction, and is consistent. Table 1 summarizes the comparison.

A complementary line of work approximates the inference rather than the model. Sparse variational GPs (Titsias, 2009; Hensman et al., 2013) introduce inducing points to approximate the posterior, leaving the kernel unchanged. Variational Fourier features (Hensman et al., 2018) replace spatial inducing points with spectral inducing variables within the same variational framework. These inference approximations are orthogonal to our kernel approximation.

3 Nonstationary Regular Fourier Features

We derive regular Fourier features for harmonizable processes by discretizing the spectral representation on an equidistant frequency grid, following the classical simulation idea of Shinozuka & Jan (1972). While the Riemann sum approximation itself is standard, its extension to harmonizable GPs has not been explored. Unlike random approaches that require a probability interpretation, our method preserves the correlation structure among spectral weights without modifying the spectral density.

Figure 1: Regular Fourier features approximate the stochastic process $Z(x)$ as a sum of complex exponentials weighted by correlated spectral increments $d\Gamma(\omega_k)$. The spectral process (top) is discretized at frequencies $\omega_1, \ldots, \omega_m$. Each harmonic (bottom) shows the contribution $d\Gamma(\omega_k)\exp(i\omega_k x)$ in the complex plane.

The spectral representation (1) is a Riemann–Stieltjes integral that can be approximated by a finite sum (Loève, 1978) (see Figure 1) on an equidistant frequency grid with spacing $\Delta\omega = \omega_{k+1} - \omega_k$

$$Z(x) \approx \sum_{k=1}^{m} \exp(i\omega_k x) W_k, \tag{11}$$

where $W_k \coloneqq \Gamma(\omega_k + \Delta\omega) - \Gamma(\omega_k)$ is the spectral increment at frequency ω_k. The random variables $W = (W_1, \ldots, W_m)^\top$ form a zero-mean complex-valued random vector with covariance

$$\mathrm{E}[WW^\dagger] \approx \boldsymbol{S}\Delta\omega^2, \quad [\boldsymbol{S}]_{ij} = s(\omega_i, \omega_j). \tag{12}$$

In the nonstationary case, the spectral weights $\{W_k\}$ are no longer independent but are correlated according to the spectral density $s(\omega_i, \omega_j)$. This off-diagonal correlation structure encodes the nonstationarity of the process.

When W is complex-valued, its distribution is not fully determined by $\mathrm{E}[WW^\dagger]$ alone; the pseudo-covariance $\mathrm{E}[WW^\top]$ is also required (Lee & Messerschmitt, 1994). We assume W is circular ($\mathrm{E}[WW^\top] = 0$) and Gaussian, so that $\mathrm{E}[WW^\dagger] \approx \boldsymbol{S}\Delta\omega^2$ fully specifies the distribution. This assumption does not restrict the class of harmonizable GPs that our method can represent (see Appendix B). Factoring $\boldsymbol{S}\Delta\omega^2 = \boldsymbol{C}\boldsymbol{C}^\dagger$, we write

$$Z(x) \approx \boldsymbol{\alpha}(x)\boldsymbol{C}E = \boldsymbol{\varphi}(x)E, \tag{13}$$

where $[\boldsymbol{\alpha}(x)]_k = \exp(i\omega_k x)$ collects the Fourier basis functions, $\boldsymbol{\varphi}(x) = \boldsymbol{\alpha}(x)\boldsymbol{C}$ is the feature map, and $E = E_{\mathrm{re}} + iE_{\mathrm{im}}$ is a circularly symmetric complex Gaussian with $E_{\mathrm{re}}, E_{\mathrm{im}} \sim \mathcal{N}(\boldsymbol{0}, \frac{1}{2}\boldsymbol{I})$.

3.1 Low-Rank Kernel Approximation

The kernel $k(x, x') = \mathrm{E}[Z(x)\overline{Z(x')}]$ admits the low-rank approximation

$$k(x, x') \approx \boldsymbol{\varphi}(x)\boldsymbol{\varphi}(x')^\dagger = \boldsymbol{\alpha}(x)\boldsymbol{C}\boldsymbol{C}^\dagger\boldsymbol{\alpha}(x')^\dagger, \tag{14}$$

which is positive semi-definite by construction since it has the form $\boldsymbol{\Phi}\boldsymbol{\Phi}^\dagger$ for any feature matrix $\boldsymbol{\Phi}$. This contrasts with the naïve Monte Carlo approximation (9), which lacks this guarantee.

For n sample locations, the kernel matrix $\boldsymbol{K} \in \mathbb{R}^{n \times n}$ is approximated as

$$\boldsymbol{K} \approx \boldsymbol{L}\boldsymbol{L}^\dagger, \quad [\boldsymbol{L}]_i = \boldsymbol{\varphi}(x_i), \quad \boldsymbol{L} \in \mathbb{C}^{n \times m}. \tag{15}$$

Real-Valued Processes For real-valued processes, the spectral weights satisfy Hermitian symmetry $W_{-k} = \overline{W}_k$. Including the spectral mass at the origin, the approximation becomes

$$Z(x) \approx W_0 + \sum_{k=1}^{m} \exp(\mathrm{i}\omega_k x) W_k + \exp(-\mathrm{i}\omega_k x) \overline{W}_k$$
$$= 2 \operatorname{Re}[\tilde{\boldsymbol{\alpha}}(x) W], \tag{16}$$

where $[\tilde{\boldsymbol{\alpha}}(x)]_k = \exp(\mathrm{i}\omega_k x)$ for $\omega_k \neq 0$ and $1/2$ otherwise. The kernel approximation is

$$k(x, x') \approx 2 \operatorname{Re}[\tilde{\boldsymbol{\varphi}}(x) \tilde{\boldsymbol{\varphi}}(x')^{\dagger}], \quad \tilde{\boldsymbol{\varphi}}(x) = \tilde{\boldsymbol{\alpha}}(x) \boldsymbol{C}. \tag{17}$$

When the spectral weights W_k are additionally real-valued ($W_{-k} = \overline{W}_k = W_k$), the positive- and negative-frequency terms combine to $2\cos(\omega_k x) W_k$. The feature map then simplifies to $[\tilde{\boldsymbol{\alpha}}(x)]_k = \cos(\omega_k x)$ for $\omega_k \neq 0$ and $1/2$ otherwise, yielding the kernel $k(x, x') \approx 4\,\tilde{\boldsymbol{\alpha}}(x) \boldsymbol{C} \boldsymbol{C}^{\top} \tilde{\boldsymbol{\alpha}}(x')^{\top}$.

The method extends to d dimensions, for example, via product kernels $k(\boldsymbol{x}, \boldsymbol{x}') = \prod_{p=1}^{d} k(x_p, x_p')$, where each dimension uses a one-dimensional spectral density. This preserves computational efficiency at $\mathcal{O}(ndm^2)$ while allowing dimension-specific nonstationarity.

Assumptions The method assumes finite spectral support: $s(\omega, \omega') = 0$ for $|\omega| > \omega_m$ or $|\omega'| > \omega_m$. This band-limited assumption is natural in many applications. When data are sampled at intervals Δx, the Nyquist theorem limits recoverable frequencies to $\omega_{\text{Nyquist}} = \pi/\Delta x$. Spectral content beyond this is aliased and fundamentally unidentifiable from observations. By setting $\omega_m < \omega_{\text{Nyquist}}$, our method avoids modeling high-frequency components that cannot be distinguished from the data. This is particularly relevant, for example, in surface texture measurement, where the textures are inherently band-limited (ISO 21920-2, 2021; ISO 25178-2, 2021). When the spectral support is not strictly finite, the method introduces a truncation error proportional to the spectral mass beyond ω_m.

The finite sum (11) is periodic with period $T = 2\pi/\Delta\omega$. Thus, our low-rank approximation in fact estimates $\sum_{p,q} k(x - pT, x' - qT)$, introducing aliasing error. If the kernel is not zero for $|x|, |x'| > \pi/\Delta\omega$, the periods interfere with the approximation. In practice, $\Delta\omega$ should be chosen such that $x_{\max} < \pi/\Delta\omega$, where $x_{\max} = \max_i |x_i|$.

Numerically, the Cholesky factorization $\boldsymbol{S}\Delta\omega^2 = \boldsymbol{C}\boldsymbol{C}^{\dagger}$ requires $\boldsymbol{S}\Delta\omega^2$ to be positive definite, whereas it is in general only positive semi-definite. Adding a small jitter ϵ on the diagonal restores positive definiteness but introduces a band-limited white-noise error, confined to the modeled band $[-\omega_m, \omega_m]$. This contrasts with the same jitter applied to the standard kernel matrix, which introduces full-band white noise. As ϵ is usually small, the error is negligible.

3.2 Extension to Kernel Learning

When the spectral density is unknown, the framework extends naturally to kernel learning. We focus on real-valued kernels throughout; note that the spectral density $s(\omega, \omega')$ can still be complex-valued. A valid spectral density must be positive semi-definite and fulfill

$$s(\omega, \omega') = \overline{s(\omega', \omega)} = \overline{s(-\omega, -\omega')}. \tag{18}$$

We parametrize the spectral density as

$$s(\omega, \omega') = \boldsymbol{f}(\omega)^{\dagger} \boldsymbol{f}(\omega') + \boldsymbol{f}(-\omega')^{\dagger} \boldsymbol{f}(-\omega), \tag{19}$$

which is positive semi-definite and Hermitian by construction. The second term enforces the real-kernel symmetry $s(\omega, \omega') = \overline{s(-\omega, -\omega')}$. Both properties hold for arbitrary $\boldsymbol{f} \colon \mathbb{R} \to \mathbb{C}^r$. In matrix form, the spectral matrix is

$$\boldsymbol{S} = \boldsymbol{F}\boldsymbol{F}^{\dagger} + \boldsymbol{F}_{-}\boldsymbol{F}_{-}^{\dagger}, \tag{20}$$

where $[\boldsymbol{F}]_{kj} = \overline{f_j(\omega_k)}$ and $[\boldsymbol{F}_{-}]_{kj} = f_j(-\omega_k)$, both in $\mathbb{C}^{m \times r}$. The function $\boldsymbol{f}$ can be parametrized by a neural network with $2r$ real outputs representing the real and imaginary parts.

Figure 2: Low-rank approximation of the LSK showing the sampled spectral density, true kernel, approximation, and absolute error.

Inference Given n observations $\{(x_i, z_i)\}_{i=1}^n$ and a Gaussian likelihood, we maximize, for example, the marginal log-likelihood:

$$\log p(\boldsymbol{z} \mid \Theta) \propto -\boldsymbol{z}^\top \boldsymbol{\Sigma}^{-1} \boldsymbol{z} - \log |\boldsymbol{\Sigma}|, \tag{21}$$

where $\boldsymbol{z} = (z_1, \ldots, z_n)^\top$, $\boldsymbol{\Sigma} = \boldsymbol{K} + \sigma_{\text{noise}}^2 \boldsymbol{I}$, and Θ includes the network parameters and noise variance σ_{noise}^2.

The factorized form avoids the $\mathcal{O}(m^3)$ matrix decomposition of $\boldsymbol{S}\Delta\omega^2$. Since $\boldsymbol{S}\Delta\omega^2 = \boldsymbol{F}\Delta\omega(\boldsymbol{F}\Delta\omega)^\dagger + \boldsymbol{F}_-\Delta\omega(\boldsymbol{F}_-\Delta\omega)^\dagger$, the decomposition is

$$\boldsymbol{C} = \begin{pmatrix} \boldsymbol{F} & \boldsymbol{F}_- \end{pmatrix} \Delta\omega \in \mathbb{C}^{m\times 2r}. \tag{22}$$

Then the real-valued kernel is $\boldsymbol{K} \approx 2\operatorname{Re}[(\tilde{\boldsymbol{\Phi}}\boldsymbol{C})(\tilde{\boldsymbol{\Phi}}\boldsymbol{C})^\dagger]$, where $[\tilde{\boldsymbol{\Phi}}]_{ik} = [\tilde{\boldsymbol{\alpha}}(x_i)]_k$ as in (17). Writing $\tilde{\boldsymbol{\Phi}}\boldsymbol{C} = \boldsymbol{A} + \mathrm{i}\boldsymbol{B}$ with real and imaginary parts in $\mathbb{R}^{n\times 2r}$, we obtain $\boldsymbol{K} \approx \boldsymbol{L}\boldsymbol{L}^\top$ with

$$\boldsymbol{L} = \sqrt{2}\begin{pmatrix} \boldsymbol{A} & \boldsymbol{B} \end{pmatrix} \in \mathbb{R}^{n\times 4r}, \tag{23}$$

which has rank at most $4r$. Using the Woodbury formula and matrix determinant lemma, the marginal log-likelihood costs $\mathcal{O}(nmr)$ when $r < m \ll n$.

Posterior Prediction Given t test points, the posterior mean and covariance are

$$\begin{aligned} \boldsymbol{\mu}_{t|n} &= \boldsymbol{K}_{t,n}\boldsymbol{\Sigma}^{-1}\boldsymbol{z}, \\ \boldsymbol{\Sigma}_{t|n} &= \boldsymbol{K}_{t,t} - \boldsymbol{K}_{t,n}\boldsymbol{\Sigma}^{-1}\boldsymbol{K}_{n,t}, \end{aligned} \tag{24}$$

where $\boldsymbol{K}_{t,n} \in \mathbb{R}^{t\times n}$ is the kernel between test and training points. Using the low-rank form $\boldsymbol{K}_{t,n} \approx \boldsymbol{L}_*\boldsymbol{L}^\top$ with test feature matrix $\boldsymbol{L}_* \in \mathbb{R}^{t\times 4r}$, these simplify to $\boldsymbol{\mu}_* = \boldsymbol{L}_*\boldsymbol{\beta}$ and $\boldsymbol{\Sigma}_{t|n} = \boldsymbol{L}_*\boldsymbol{Q}\boldsymbol{L}_*^\top$. Here $\boldsymbol{\beta} = \boldsymbol{L}^\top\boldsymbol{\Sigma}^{-1}\boldsymbol{z} \in \mathbb{R}^{4r}$ and $\boldsymbol{Q} = \boldsymbol{I} - \boldsymbol{L}^\top\boldsymbol{\Sigma}^{-1}\boldsymbol{L} \in \mathbb{R}^{4r\times 4r}$ are cached during training. Prediction costs $\mathcal{O}(tmr)$, dominated by constructing $\boldsymbol{L}_*$.

4 Experiments

We evaluate our approach on two tasks: (1) low-rank kernel approximation, where the spectral density is known in closed form (Section 4.1); and (2) kernel learning, where the spectral density is learned from data (Section 4.2).

4.1 Low-Rank Kernel Approximation

We test our kernel approximation on two harmonizable kernels: a locally stationary kernel (LSK) (Silverman, 1957) and a harmonizable mixture kernel (HMK) (Shen et al., 2019). The LSK, with its real-valued spectral

density, validates approximation quality on a case where existing RFF methods also apply. The HMK demonstrates a capability that existing RFF methods fundamentally cannot handle: approximating kernels with complex-valued spectral densities.

We measure approximation quality using the relative error

$$\|\boldsymbol{K}_{\text{approx}} - \boldsymbol{K}_{\text{true}}\|_{\text{F}} / \|\boldsymbol{K}_{\text{true}}\|_{\text{F}}, \tag{25}$$

where $\boldsymbol{K}_{\text{true}}$ is the true kernel matrix, $\boldsymbol{K}_{\text{approx}}$ its approximation, and $\|\cdot\|_{\text{F}}$ the Frobenius norm.

Table 2: Relative error in % on the LSK ($a = 1$, $\Delta x = 10^{-3}$, $n = 2500$) versus m. Random results are the mean with 95 % confidence intervals over 10 seeds.

m	20	50	200	500	2000
Ours	0.102	0.085	0.077	0.076	0.076
Nonstationary RFF	107.2 ± 13.4	109.9 ± 5.6	105.8 ± 4.4	106.8 ± 1.8	107.1 ± 1.6

Locally Stationary Kernel   The LSK is (Silverman, 1957)

$$k_{\text{LSK}}(x, x') = \exp(-2a\bar{x}^2) \exp(-\frac{a}{2}\tilde{x}^2), \tag{26}$$

where $\bar{x} = (x + x')/2$ is the midpoint, $\tilde{x} = x - x'$ is the lag, and a is a kernel parameter. This kernel is harmonizable with real-valued spectral density

$$s_{\text{LSK}}(\omega, \omega') = \frac{1}{4\pi a} \exp(-\frac{1}{2a}\bar{\omega}^2) \exp(-\frac{1}{8a}\tilde{\omega}^2), \tag{27}$$

with $\bar{\omega} = (\omega + \omega')/2$ and $\tilde{\omega} = \omega - \omega'$. This spectral density has the additional property $s(\omega, \omega') = s(\omega, -\omega')$, so its spectral weights are real-valued: $\overline{W}_k = W_k$.

We set $a = 1.0$ and approximate the kernel on $x_i = i\Delta x$ for $i = 0, \ldots, n-1$ with $\Delta x = 0.001$ and $n = 2500$. Using $m = 20$ features with cutoff frequency $\omega_m = 5$ yields spectral spacing $\Delta\omega = 0.25$. The aliasing condition $\Delta\omega < \pi/(n\Delta x)$ is satisfied. Figure 2 shows (left to right): the spectral density $s_{\text{LSK}}(\omega, \omega')$ with the $m \times m$ sampling grid overlaid, the true kernel, our low-rank approximation, and the absolute error. The approximation captures the kernel structure accurately, with absolute errors on the order of 10^{-3}. Table 2 compares our method with the nonstationary RFF (Samo & Roberts, 2015; Ton et al., 2018): our relative error decreases with m, whereas the nonstationary RFF stays near 107 % (see Appendix A).

Harmonizable Mixture Kernel   We consider an HMK (Shen et al., 2019). For a single component centered at the origin and no input scaling, the kernel is

$$k_{\text{HMK}}(x, x') = k_{\text{LSK}}(x, x') \sum_{i,j=1}^{Q} B_{ij} \exp\big(\mathrm{i}(\eta_i x - \eta_j x')\big), \tag{28}$$

where $\eta_1, \ldots, \eta_Q$ are angular frequencies, $\boldsymbol{B} \in \mathbb{C}^{Q \times Q}$ is a positive semi-definite matrix, and k_{LSK} is the kernel defined above. The spectral density is

$$s_{\text{HMK}}(\omega, \omega') = \sum_{i,j=1}^{Q} B_{ij} \, s_{\text{LSK}}(\omega - \eta_i, \omega' - \eta_j), \tag{29}$$

which can be complex-valued. We use $Q = 2$ with conjugate frequencies $\eta_1 = 2\pi$, $\eta_2 = -2\pi$ and a positive semi-definite matrix

$$\boldsymbol{B} = \begin{pmatrix} 2 & \frac{1}{2}\mathrm{i} \\ -\frac{1}{2}\mathrm{i} & 2 \end{pmatrix}, \tag{30}$$

Figure 3: HMK approximation with complex-valued spectral density. Top row: real, imaginary, and absolute values of $s(\omega, \omega')$. Bottom row: true kernel, approximation, and absolute error.

producing a real-valued kernel with a complex-valued spectral density.

To approximate the single-component HMK, we use $m = 100$ features with cutoff frequency $\omega_m = 20$ on $x_i = i\Delta x$ for $i = -\frac{n-1}{2}, \ldots, \frac{n-1}{2}$ with $\Delta x = 0.01$ and $n = 599$. Figure 3 shows the real, imaginary, and absolute values of the spectral density (top row) along with the true kernel, approximation, and absolute error (bottom row). The approximation accurately captures the complex oscillatory structure with absolute errors on the order of 10^{-5}.

Figure 4: Ablation studies on the LSK showing relative error versus (left) number of features m with fixed $\omega_m = 5$, and (right) cutoff frequency ω_m with fixed $m = 100$, across different problem scales n.

Ablation Studies To investigate sensitivity to the number of features m and the cutoff frequency ω_m, we perform ablation studies on the LSK ($a = 1$) across different problem scales $n \in \{1000, 2000, 4000, 8000\}$ with $\Delta x = 0.001$. We measure the approximation quality with the relative error (25).

Figure 4 shows the results. The left panel examines error versus the number of features m with fixed $\omega_m = 5$, while the right panel examines error versus cutoff frequency ω_m with fixed $m = 100$. Increasing m consistently reduces approximation error across all problem scales, with diminishing returns beyond $m \approx 160$. For the

cutoff frequency, errors decrease as ω_m increases from 4 to 6, capturing more spectral content, and plateau beyond $\omega_m \approx 8$. Larger problem scales require more features for comparable accuracy, but the overall trends remain consistent.

The value $\omega_m = 6$ observed in the ablation study corresponds to the point where the spectral density has decayed to negligible levels. For the LSK, we have $s_{\text{LSK}}(6,6) \approx 10^{-6}\, s_{\text{LSK}}(0,0)$, confirming that this cutoff captures most spectral mass. In practice, selecting ω_m is more critical than choosing the number of features m. We recommend (1) setting ω_m based on spectral content or the Nyquist limit, then (2) choosing m large enough to satisfy the aliasing condition $\Delta\omega < \pi/x_{\max}$.

4.2 Kernel Learning

We demonstrate the kernel-learning approach with a standard neural network as formulated in Section 3.2. We first address a reconstruction problem on a real-world dataset and then perform a small benchmark on synthetic datasets. All models are exact GPs with learnable noise variance and are trained with AMS-Grad (Sashank J. Reddi et al., 2018) (learning rate 10^{-2}, 2000 iterations).

To quantify our results, we use the relative error (25), negative log predictive density (NLPD), mean absolute error (MAE), and Kullback–Leibler (KL) divergence to the true posterior. We report the subset of metrics appropriate to each experiment.

Figure 5: Posterior predictions on solar irradiance data with five held-out intervals. Metrics in parentheses are NLPD / MAE on the test data. Top: RBF ($-0.09 / 0.18$). Center: NNK ($-0.07 / 0.20$). Bottom: our method ($-0.43 / 0.13$).

Solar Irradiance Reconstruction We use the solar irradiance dataset (Lean, 2004) to demonstrate our approach on real-world data. In our model, we parametrize the spectral density using the factorized form (19) with a neural network having two hidden layers of 128 units and rank $r = 8$.

To mitigate the spectral bias of the neural network toward low frequencies, we first map the input frequency ω through a random harmonics embedding $\boldsymbol{g}\colon \mathbb{R} \to \mathbb{R}^{2q}$ (Tancik et al., 2020)

$$
\begin{aligned}
\boldsymbol{g}_{\sin}(\omega) &= \big(\sin(E_1\,\omega/\omega_m), \ldots, \sin(E_q\,\omega/\omega_m)\big), \\
\boldsymbol{g}_{\cos}(\omega) &= \big(\cos(E_1\,\omega/\omega_m), \ldots, \cos(E_q\,\omega/\omega_m)\big), \\
\boldsymbol{g}(\omega) &= \big(\boldsymbol{g}_{\sin}(\omega), \boldsymbol{g}_{\cos}(\omega)\big), \quad E_i \sim \mathcal{N}(0, \sigma_{\mathrm{emb}}^2),
\end{aligned}
\tag{31}
$$

where the E_i are sampled once and held fixed. We set $q = 256$ and $\sigma_{\mathrm{emb}} = 15$.

The embedding is the input to the network $\boldsymbol{h}\colon \mathbb{R}^{2q} \to \mathbb{C}^r$, so that the feature map is the composition $\boldsymbol{f} = \boldsymbol{h} \circ \boldsymbol{g}$. We also include a learnable global scale parameter γ^2, which yields the model

$$
s(\omega, \omega') = \gamma^2 \big(\boldsymbol{f}(\omega)^\dagger \boldsymbol{f}(\omega') + \boldsymbol{f}(-\omega')^\dagger \boldsymbol{f}(-\omega)\big).
\tag{32}
$$

We use $m = 199$ features on a symmetric frequency grid with cutoff frequency $\omega_m = 32$. We place a zero-mean, unit-variance Gaussian prior on the network weights and obtain a maximum *a posteriori* (MAP) estimate.

We compare against two GP baselines: a radial basis function (RBF) kernel and a neural network kernel (NNK) (Williams, 1996). Figure 5 shows the posterior predictions. While RBF and NNK miss the high-frequency components of the data, our model recovers them through the random harmonics embedding; without this embedding, it underfits. However, this added flexibility can lead to overfitting, a known problem of overly flexible kernels (Ober et al., 2021).

Table 3: Kernel learning on synthetic data (10 datasets each from the LSK and HMK). Metrics are relative error, NLPD, and KL divergence to the true posterior, expressed as the mean with 95 % confidence intervals. The best mean in each column is in bold.

Method	LSK			HMK		
	Relative error / %	NLPD	KL	Relative error / %	NLPD	KL
RBF	94.2 ± 3.7	-1.94 ± 0.08	6.3 ± 2.6	134.5 ± 29.6	0.03 ± 0.68	704.0 ± 653.5
NNK	148.2 ± 64.8	-1.94 ± 0.08	$\mathbf{5.7} \pm 2.2$	100.0 ± 0.0	1.46 ± 0.25	4075.7 ± 2017.3
NGSM	96.1 ± 6.2	-1.84 ± 0.14	8.4 ± 2.1	$\mathbf{56.8} \pm 17.2$	-0.35 ± 0.25	13.4 ± 2.5
DKL	373.5 ± 293.7	-0.40 ± 0.55	30.4 ± 5.0	309.4 ± 55.0	1.49 ± 1.22	39.0 ± 6.8
Ours (real)	$\mathbf{77.7} \pm 17.2$	$\mathbf{-1.95} \pm 0.07$	6.5 ± 4.2	57.5 ± 14.1	$\mathbf{-0.56} \pm 0.15$	10.7 ± 2.9
Ours (complex)	81.5 ± 14.9	-1.85 ± 0.14	8.5 ± 4.0	76.9 ± 8.9	-0.55 ± 0.17	$\mathbf{10.3} \pm 2.5$

Benchmark with Synthetic Data We generate 10 synthetic datasets from the LSK (26) with $a = 0.5$ on $n = 35$ equally spaced training points in $-5 \le x \le 5$, and $t = 50$ test points drawn uniformly at random. The data follow $Z(x) = F(x) + E(x)$, where $F(x) \sim \mathcal{GP}(0, k_{\mathrm{LSK}}(x, x'))$ is a zero-mean GP and $E(x)$ is white Gaussian noise with $\sigma_{\mathrm{data}}^2 = 10^{-3}$. Similarly, we generate 10 datasets from the HMK (28) in $-2 \le x \le 2$ using the same sampling scheme ($n = 35$ training, $t = 50$ test) with $\sigma_{\mathrm{data}}^2 = 10^{-2}$. The HMK parameters are exactly those of Section 4.1.

The spectral density is again parametrized with the factorized form (19) using a neural network with two hidden layers of 128 units and rank $r = 8$, here without the random harmonics embedding. As in the solar experiment, we include a learnable global scale parameter γ^2 in the spectral density model.

Our model comes in two versions based on the network output: (1) real-valued $\boldsymbol{f}\colon \mathbb{R} \to \mathbb{R}^r$ and (2) complex-valued $\boldsymbol{f}\colon \mathbb{R} \to \mathbb{C}^r$. Both use $m = 255$ features on a symmetric frequency grid with cutoff frequency $\omega_m = 10$, and we obtain a MAP estimate by placing a Gaussian prior on the network weights.

We compare against four baselines: the RBF kernel, the NNK (Williams, 1996), deep kernel learning (DKL) (Wilson et al., 2016), and the neural generalized spectral mixture (NGSM) kernel (Remes et al., 2018). The DKL feature network and the NGSM parameter network each use two hidden layers of 128 units, matching our model. NGSM uses two mixture components and a Gaussian prior on the network weights, as in the original work.

Table 3 reports test-data metrics for all baselines on both synthetic datasets (LSK and HMK). Our models achieve the best or comparable performance on most metrics, though the gains over the baselines are rarely significant. Interestingly, the real-valued version outperforms the complex-valued one on most metrics, even though the HMK data are generated from a complex-valued spectral density. This may stem from the greater optimization difficulty of the complex-valued model, or from an inductive bias of the real-valued model toward better solutions.

While our parametrization can match or improve on the baselines, training remains prone to underfitting without the harmonics embedding and to overfitting with it. Developing more robust optimization strategies is an important direction for future work.

5 Conclusion

We presented a method for constructing regular Fourier features for harmonizable Gaussian processes by discretizing the spectral representation on a regular frequency grid. Unlike existing RFF approaches for nonstationary kernels, our method yields a consistent approximation and does not require the spectral density to be a probability measure.

By factorizing the spectral matrix as $\boldsymbol{S}\Delta\omega^2 = \boldsymbol{C}\boldsymbol{C}^\dagger$, we obtain a low-rank kernel approximation that is positive semi-definite by construction and applies to kernels with arbitrary complex-valued spectral densities. This guarantee arises directly from the factorization structure rather than from modified Monte Carlo sampling. Moreover, the parametrization $s(\omega, \omega') = \boldsymbol{f}(\omega)^\dagger \boldsymbol{f}(\omega') + \boldsymbol{f}(-\omega')^\dagger \boldsymbol{f}(-\omega)$ emerges naturally and provides a principled framework for kernel learning via marginal likelihood or MAP estimate.

We demonstrated high approximation accuracy on the LSK and the HMK (complex-valued spectral density), the latter representing a unique capability unavailable to existing RFF methods. For kernel learning, we reconstructed real-world solar irradiance data. On synthetic benchmarks, our approach matched or improved on competitive baselines, although the gains were rarely statistically significant.

The computational cost scales as $\mathcal{O}(nm^2)$ for approximation and $\mathcal{O}(nmr)$ for learning, potentially becoming prohibitive for very large datasets. For kernel learning, optimizing the general factorized form remains challenging, as the model is prone to underfitting or overfitting depending on its flexibility.

The method assumes finite spectral support, which reflects the reality of discrete sampling: the Nyquist theorem fundamentally limits recoverable frequencies. Additionally, our approach approximates a periodic repetition of the true kernel, requiring the domain to be small enough that successive periods do not overlap.

Future work could examine more general multi-dimensional settings, develop adaptive frequency selection schemes, derive error bounds, and combine our approach with approximate inference methods.

References

Harald Cramér. On harmonic analysis in certain functional spaces. *Arkiv För Matematik, Astronomi Och Fysik*, 28B(12):1–7, 1942.

Harald Cramér. On the theory of stochastic processes. In *Den Tiende Skandinaviske Matematiker Kongres*, pp. 28–39, Copenhagen, 1946. Jul. Gjellerups.

James Hensman, Nicolò Fusi, and Neil D. Lawrence. Gaussian processes for Big data. In *Proceedings of the Twenty-Ninth Conference on Uncertainty in Artificial Intelligence*, Uncertainty in Artificial Intellegence, pp. 282–290, Bellevue, WA, 2013. AUAI Press.

James Hensman, Nicolas Durrande, and Arno Solin. Variational fourier features for gaussian processes. *Journal of Machine Learning Research*, 18(151):1–52, 2018.

D. Higdon, J. Swall, and J. Kern. Non-Stationary Spatial Modeling. In *Proceedings of the Sixth Valencia International Meeting*, volume 6 of *Bayesian Statistics*, pp. 761–768. Clarendon Press, 1998.

ISO 21920-2. Geometrical product specifications (GPS)—surface texture: Profile—part 2: Terms, definitions and surface texture parameters. Technical report, International Organization for Standardization, 2021.

ISO 25178-2. Geometrical product specifications (GPS)—surface texture: Areal—part 2: Terms, definitions and surface texture parameters. Technical report, International Organization for Standardization, 2021.

Judith Lean. Solar irradiance reconstruction. IGBP PAGES/World Data Center for Paleoclimatology, Data Contribution Series # 2004-035. NOAA/NGDC Paleoclimatology Program, Boulder, CO, USA, 2004.

Edward A. Lee and David G. Messerschmitt. *Digital Communication*. Kluwer Academic Publishers, Boston, 2nd ed edition, 1994. ISBN 978-0-7923-9391-7.

Michel Loève. Fonctions aléatoires du second ordre. In *Processus stochastiques et mouvement brownien*. Gauthier-Villars, Paris, 1948.

Michel Loève. *Probability Theory II*, volume 46 of *Graduate Texts in Mathematics*. Springer, Berlin New York, 4 edition, 1978. ISBN 978-3-540-90262-1.

Sebastian W. Ober, Carl E. Rasmussen, and Mark van der Wilk. The promises and pitfalls of deep kernel learning. In Cassio de Campos and Marloes H. Maathuis (eds.), *Proceedings of the Thirty-Seventh Conference on Uncertainty in Artificial Intelligence*, volume 161 of *Proceedings of Machine Learning Research*, pp. 1206–1216. PMLR, July 2021.

Ali Rahimi and Benjamin Recht. Random Features for Large-Scale Kernel Machines. In J. Platt, D. Koller, Y. Singer, and S. Roweis (eds.), *Advances in Neural Information Processing Systems*, volume 20. Curran Associates, Inc., 2007.

Carl Edward Rasmussen and Christopher K. I. Williams. *Gaussian Processes for Machine Learning*. The MIT Press, November 2005. ISBN 978-0-262-25683-4. doi: 10.7551/mitpress/3206.001.0001.

Sami Remes, Markus Heinonen, and Samuel Kaski. Non-Stationary Spectral Kernels. In I. Guyon, U. Von Luxburg, S. Bengio, H. Wallach, R. Fergus, S. Vishwanathan, and R. Garnett (eds.), *Advances in Neural Information Processing Systems*, volume 30. Curran Associates, Inc., 2017.

Sami Remes, Markus Heinonen, and Samuel Kaski. Neural Non-Stationary Spectral Kernel, 2018.

Yves-Laurent Kom Samo and Stephen Roberts. Generalized Spectral Kernels, 2015.

Sashank J. Reddi, Satyen Kale, and Sanjiv Kumar. On the Convergence of Adam and Beyond. In *International Conference on Learning Representations (ICLR)*, 2018.

Zheyang Shen, Markus Heinonen, and Samuel Kaski. Harmonizable mixture kernels with variational Fourier features. In Kamalika Chaudhuri and Masashi Sugiyama (eds.), *Proceedings of the Twenty-Second International Conference on Artificial Intelligence and Statistics*, volume 89 of *Proceedings of Machine Learning Research*, pp. 3273–3282. PMLR, April 2019.

M. Shinozuka and C.-M. Jan. Digital simulation of random processes and its applications. *Journal of Sound and Vibration*, 25(1):111–128, November 1972. ISSN 0022460X. doi: 10.1016/0022-460X(72)90600-1.

R. Silverman. Locally stationary random processes. *IRE Transactions on Information Theory*, 3(3):182–187, September 1957. ISSN 0018-9448. doi: 10.1109/TIT.1957.1057413.

Matthew Tancik, Pratul Srinivasan, Ben Mildenhall, Sara Fridovich-Keil, Nithin Raghavan, Utkarsh Singhal, Ravi Ramamoorthi, Jonathan Barron, and Ren Ng. Fourier features let networks learn high frequency functions in low dimensional domains. In H. Larochelle, M. Ranzato, R. Hadsell, M.F. Balcan, and H. Lin (eds.), *Advances in Neural Information Processing Systems*, volume 33, pp. 7537–7547. Curran Associates, Inc., 2020.

Michalis Titsias. Variational learning of inducing variables in sparse gaussian processes. In David van Dyk and Max Welling (eds.), *Proceedings of the Twelfth International Conference on Artificial Intelligence and Statistics*, volume 5 of *Proceedings of Machine Learning Research*, pp. 567–574, Hilton Clearwater Beach Resort, Clearwater Beach, Florida USA, April 2009. PMLR.

Jean-Francois Ton, Seth Flaxman, Dino Sejdinovic, and Samir Bhatt. Spatial mapping with Gaussian processes and nonstationary Fourier features. *Spatial Statistics*, 28:59–78, December 2018. ISSN 22116753. doi: 10.1016/j.spasta.2018.02.002.

Christopher Williams. Computing with infinite networks. In M.C. Mozer, M. Jordan, and T. Petsche (eds.), *Advances in Neural Information Processing Systems*, volume 9. MIT Press, 1996.

Andrew Gordon Wilson, Zhiting Hu, Ruslan Salakhutdinov, and Eric P. Xing. Deep kernel learning. In Arthur Gretton and Christian C. Robert (eds.), *Proceedings of the 19th International Conference on Artificial Intelligence and Statistics*, volume 51 of *Proceedings of Machine Learning Research*, pp. 370–378, Cadiz, Spain, May 2016. PMLR.

A. M. Yaglom. *Correlation Theory of Stationary and Related Random Functions*. Springer Series in Statistics. Springer, New York, 1987. ISBN 978-3-540-96268-7.

For clarity, we state the proofs below in one-dimensional notation. They also hold for the multi-dimensional case.

A   Bias of Nonstationary Random Fourier Features

Let $k(x, x')$ be a harmonizable kernel on $\mathbb{R} \times \mathbb{R}$ whose spectral measure $\mu(\mathrm{d}\omega, \mathrm{d}\omega')$ is assumed to be a positive finite measure (or, when normalized, a probability measure). Note that the kernel and its spectral measure are related by (Loève, 1948; Yaglom, 1987)

$$k(x, x') = \iint_{\mathbb{R}^2} \exp(\mathrm{i}(\omega x - \omega' x')) \, \mu(\mathrm{d}\omega, \mathrm{d}\omega').$$

The naïve Monte Carlo approximation of the integral is pointwise unbiased, but its finite-sample estimates are not positive semi-definite in general; see Eq. (9). Samo & Roberts (2015); Ton et al. (2018) suggested an alternative Monte Carlo approximation that guarantees positive semi-definiteness of the finite-sample estimates.

Proposition.   If the frequency pairs (ω, ω') are sampled from the spectral measure of the target kernel (as in Samo & Roberts (2015); Ton et al. (2018)), the resulting positive semi-definite finite-sample estimates form a biased estimator of the kernel that becomes unbiased only when the kernel is stationary.

Proof.   Since the kernel is Hermitian $(k(x, x') = \overline{k(x', x)})$ and $\mu(\mathrm{d}\omega, \mathrm{d}\omega')$ is a positive finite measure, the spectral measure is symmetric, $\mu(\mathrm{d}\omega, \mathrm{d}\omega') = \mu(\mathrm{d}\omega', \mathrm{d}\omega)$.

Sampling frequency pairs from μ and averaging four terms (Samo & Roberts, 2015; Ton et al., 2018)

$$k_{\mathrm{mod}}(x, x') = \frac{1}{4} \iint_{\mathbb{R}^2} \big(\exp(\mathrm{i}(\omega x - \omega' x')) + \exp(\mathrm{i}(\omega' x - \omega x'))$$
$$+ \exp(\mathrm{i}\omega(x - x')) + \exp(\mathrm{i}\omega'(x - x')) \big) \, \mu(\mathrm{d}\omega, \mathrm{d}\omega'),$$

is equivalent to replacing μ by the modified spectral measure

$$\mu_{\mathrm{mod}}(\mathrm{d}\omega, \mathrm{d}\omega') = \frac{1}{4} (\underbrace{\mu(\mathrm{d}\omega, \mathrm{d}\omega') + \mu(\mathrm{d}\omega', \mathrm{d}\omega)}_{=2\mu(\mathrm{d}\omega, \mathrm{d}\omega')}) + \frac{1}{4} (\underbrace{\delta_\omega(\mathrm{d}\omega')\mu_1(\mathrm{d}\omega) + \delta_{\omega'}(\mathrm{d}\omega)\mu_2(\mathrm{d}\omega')}_{=2\delta_\omega(\mathrm{d}\omega')\mu_1(\mathrm{d}\omega)}),$$

$$\mu_{\mathrm{mod}}(\mathrm{d}\omega, \mathrm{d}\omega') = \frac{1}{2} \mu(\mathrm{d}\omega, \mathrm{d}\omega') + \frac{1}{2} \delta_\omega(\mathrm{d}\omega')\mu_1(\mathrm{d}\omega),$$

with marginals $\mu_1(\mathrm{d}\omega) = \mu(\mathrm{d}\omega, \mathbb{R})$ and $\mu_2(\mathrm{d}\omega') = \mu(\mathbb{R}, \mathrm{d}\omega')$, and where $\delta_\omega(\cdot)$ denotes the point mass at ω.

This modification yields a Monte Carlo approximation of the following kernel

$$k_{\mathrm{mod}}(x, x') = \frac{1}{2} \underbrace{\iint_{\mathbb{R}^2} \exp(\mathrm{i}(\omega x - \omega' x')) \, \mu(\mathrm{d}\omega, \mathrm{d}\omega')}_{k(x, x')} + \frac{1}{2} \iint_{\mathbb{R}^2} \exp(\mathrm{i}(\omega x - \omega' x')) \, \delta_\omega(\mathrm{d}\omega')\mu_1(\mathrm{d}\omega),$$

$$k_{\mathrm{mod}}(x, x') = \frac{1}{2} k(x, x') + \frac{1}{2} \underbrace{\int_{\mathbb{R}} \exp(\mathrm{i}\omega(x - x')) \, \mu_1(\mathrm{d}\omega)}_{k_{\mathrm{stat}}(x, x')},$$

$$k_{\mathrm{mod}}(x, x') = \frac{1}{2} k(x, x') + \frac{1}{2} k_{\mathrm{stat}}(x, x'),$$

which in general does not approximate $k(x, x')$. The bias vanishes only when $k(x, x') = k_{\mathrm{stat}}(x, x')$, in which case $k(x, x')$ itself is stationary.

B   The Circular-Gaussian Assumption

Proposition.   Let $\{Z(x)\}$ be a zero-mean harmonizable GP with spectral distribution $S(\omega, \omega')$. Then there exists a zero-mean harmonizable GP $\{Y(x)\}$ with circular complex spectral increments that has the same spectral distribution $S(\omega, \omega')$, and hence the same kernel, as $\{Z(x)\}$.

Proof.   Because $\{Z(x)\}$ is harmonizable, it has the spectral representation

$$Z(x) = \int_{\mathbb{R}} \exp(\mathrm{i}\omega x)\,\mathrm{d}V(\omega),$$

where $\{V(\omega)\}$ is a complex random measure with covariance $S(\omega, \omega') = \mathrm{E}[V(\omega)\,\overline{V(\omega')}]$.

There exists a circular Gaussian measure $\{\Gamma(\omega)\}$ with the properties (Loève, 1978, Sec. 37)

$$\mathrm{E}[\Gamma(\omega)\,\overline{\Gamma(\omega')}] = S(\omega, \omega'), \quad \mathrm{E}[\Gamma(\omega)\,\Gamma(\omega')] = 0.$$

We define a zero-mean harmonizable GP $Y(x) = \int_{\mathbb{R}} \exp(\mathrm{i}\omega x)\,\mathrm{d}\Gamma(\omega)$. Then $\{Y(x)\}$ has the kernel

$$\mathrm{E}[Y(x)\,\overline{Y(x')}] = \iint_{\mathbb{R}^2} \exp(\mathrm{i}(\omega x - \omega' x'))\,\mathrm{d}^2 S(\omega, \omega') = \mathrm{E}[Z(x)\,\overline{Z(x')}].$$

Hence $\{Z(x)\}$ and $\{Y(x)\}$ are both zero-mean Gaussian with the same kernel. Because $\{\Gamma(\omega)\}$ is circular Gaussian, its increments $W_i := \Gamma(\omega_i + \Delta\omega) - \Gamma(\omega_i)$ are circular Gaussian as well. Thus, for the approximation of the kernel, the circular-Gaussian assumption can be made without loss of generality.