# Noisy $\ell^0$-Sparse Subspace Clustering on Dimensionality Reduced Data

**Yingzhen Yang**

School of Computing and Augmented Intelligence
Arizona State University
699 S Mill Ave. Tempe, AZ 85281, USA
`yingzhen.yang@asu.edu`

**Ping Li**

Cognitive Computing Lab
Baidu Research
10900 NE 8th ST. Bellevue, WA 98004, USA
`pingli98@gmail.com`

## Abstract

[a]Sparse subspace clustering methods with sparsity induced by $\ell^0$-norm, such as $\ell^0$-Sparse Subspace Clustering ($\ell^0$-SSC) [Yang et al., 2018], are demonstrated to be more effective than its $\ell^1$ counterpart such as Sparse Subspace Clustering (SSC) [Elhamifar and Vidal, 2013]. However, the theoretical analysis of $\ell^0$-SSC is restricted to clean data that lie exactly in subspaces. Real data often suffer from noise and they may lie close to subspaces. In this paper, we show that an optimal solution to the optimization problem of noisy $\ell^0$-SSC achieves subspace detection property (SDP), a key element with which data from different subspaces are separated, under deterministic and semi-random model. Our results provide theoretical guarantee on the correctness of noisy $\ell^0$-SSC in terms of SDP on noisy data for the first time, which reveals the advantage of noisy $\ell^0$-SSC in terms of much less restrictive condition on subspace affinity. In order to improve the efficiency of noisy $\ell^0$-SSC, we propose Noisy-DR-$\ell^0$-SSC which provably recovers the subspaces on dimensionality reduced data. Noisy-DR-$\ell^0$-SSC first projects the data onto a lower dimensional space by random projection, then performs noisy $\ell^0$-SSC on the dimensionality reduced data for improved efficiency. Experimental results demonstrate the effectiveness of Noisy-DR-$\ell^0$-SSC.

---

[a]Yingzhen Yang's work was conducted as a consulting researcher at Baidu Research - Bellevue, WA.

## 1 INTRODUCTION

Clustering is an important unsupervised learning procedure for analyzing a broad class of scientific data. High-dimensional data, such as facial images and gene expres-

sion data, often lie in low-dimensional subspaces in many cases, and clustering in accordance to the underlying subspace structure is particularly important. Among various subspace clustering algorithms, the ones that employ sparsity prior, such as Sparse Subspace Clustering (SSC) [Elhamifar and Vidal, 2013] and $\ell^0$-Sparse Subspace Clustering ($\ell^0$-SSC) [Yang et al., 2018], have been proven to be effective in separating the data in accordance with the subspaces that the data lie in under certain assumptions.

Sparse subspace clustering methods construct the sparse similarity matrix by sparse representation of the data. Subspace detection property (SDP) defined in Section 2.2 ensures that the similarity between data from different subspaces vanishes in the sparse similarity matrix, and applying spectral clustering [Ng et al., 2001] on such sparse similarity matrix leads to compelling clustering performance. Elhamifar and Vidal [Elhamifar and Vidal, 2013] prove that when the subspaces are independent or disjoint, SDP can be satisfied by solving the canonical sparse linear representation problem using data as the dictionary, under certain conditions on the rank, or singular value of the data matrix and the principle angle between the subspaces. Under the independence assumption on the subspaces, low rank representation [Liu et al., 2010, 2013a] is also proposed to recover the subspace structures. Relaxing the assumptions on the subspaces to allowing overlapping subspaces, the Greedy Subspace Clustering [Park et al., 2014] and the Low-Rank Sparse Subspace Clustering [Wang et al., 2013] achieve subspace detection property with high probability. The geometric analysis in Soltanolkotabi and Candés [2012] shows the theoretical results on subspace recovery by SSC. In the following text, we use the term SSC or $\ell^1$-SSC exchangeably to indicate the Sparse Subspace Clustering method in Elhamifar and Vidal [2013].

Real data often suffer from noise. The correctness of noisy SSC is analyzed in Wang and Xu [2013] which handles noisy data that lie close to disjoint or overlapping subspaces, and the original optimization problem of noisy SSC is proposed in Elhamifar and Vidal [2013]. While Yang et al.

*Accepted for the 38[th] Conference on Uncertainty in Artificial Intelligence* (UAI 2022).

[2016], Yang [2018] prove the correctness of $\ell^0$-SSC or its dimensionality reduced variant on clean data based on a constrained $\ell^0$-minimization problem, it empirically solves an unconstrained $\ell^0$-regularized problem to handle noise in data, and they lack theoretical analysis on the correctness of $\ell^0$-SSC on noisy data. In this paper, the correctness of noisy $\ell^0$-SSC on noisy data in terms of the subspace detection property is established. Our analysis is under both deterministic model and semi-random model, which are the models employed in the geometric analysis of SSC [Soltanolkotabi and Candés, 2012]. Our randomized analysis demonstrates the advantage of noisy $\ell^0$-SSC over its $\ell^1$ counterpart as more general assumption on data distribution can be adopted. Moreover, we present Noisy Dimensionality Reduced $\ell^0$-Sparse Subspace Clustering (Noisy-DR-$\ell^0$-SSC), an efficient version of noisy $\ell^0$-SSC which also enjoys robustness to noise. Noisy-DR-$\ell^0$-SSC first projects the data onto a lower dimensional space by random projection, then performs noisy $\ell^0$-SSC on the dimensionality reduced data. Noisy-DR-$\ell^0$-SSC provably recovers the underlying subspace structure in the original data from the dimensionality reduced data under deterministic model. Experimental results demonstrate the effectiveness of both noisy $\ell^0$-SSC and Noisy-DR-$\ell^0$-SSC.

## 1.1 NOTATIONS

We use bold letters for matrices and vectors, and regular lower letter for scalars throughout this paper. The bold letter with superscript indicates the corresponding column of a matrix, e.g. $\mathbf{A}^i$ is the $i$-th column of matrix $\mathbf{A}$, and the bold letter with subscript indicates the corresponding element of a matrix or vector. $\|\cdot\|_F$ and $\|\cdot\|_p$ denote the Frobenius norm and the vector $\ell^p$-norm or the matrix $p$-norm, and $\|\cdot\|_0$ is the $\ell^0$-norm, that is, the number of nonzero elements of a vector. $\mathrm{diag}(\cdot)$ indicates the diagonal elements of a matrix. $\mathbf{H_T} \subseteq \mathbb{R}^d$ indicates the subspace spanned by the columns of $\mathbf{T}$, and $\mathbf{A_I}$ denotes a submatrix of $\mathbf{A}$ whose columns correspond to the nonzero elements of $\mathbf{I}$ (or with indices in $\mathbf{I}$ without confusion). $\sigma_t(\cdot)$ denotes the $t$-th largest singular value of a matrix, and $\sigma_{\min}(\cdot)$ indicates the smallest singular value of a matrix. $\mathrm{supp}(\cdot)$ is the support of a vector, $\mathbb{P}_{\mathcal{S}'}$ is the operator of orthogonal projection onto the subspace $\mathcal{S}'$. $[n]$ represents all the natural numbers between 1 and $n$ inclusively. $\mathbb{S}^{d-1}$ denotes the unit sphere in $\mathbb{R}^d$. $\Theta(a)$ denotes a number such that there exists two constants $c_1$ and $c_2$ such that $\Theta(a) \in [c_1 a, c_2 a]$.

## 1.2 CONTRIBUTIONS

First, the correctness of noisy $\ell^0$-SSC on noisy data in terms of the subspace detection property is established for the first time, which is presented in Section 3 of this paper. Our analysis is under both deterministic model and semi-random model, which are also the models employed by the geometric analysis of SSC [Soltanolkotabi2012]. Our randomized analysis demonstrates the significant advantage of noisy $\ell^0$-SSC over its $\ell^1$ counterpart and other competing subspace clustering methods in terms of much less restrictive condition on the subspace affinity. Table 1 below demonstrates the conditions under which SDP holds for representative subspace clustering methods under the semi-random model, including Greedy Subspace Clustering (GSC) [Park et al., 2014], $\ell^1$-SSC[C], Noisy SSC[G], Affine Sparse Subspace Clustering (ASSC)[K,L], Noisy $\ell^0$-SSC[I,J]. When the size of data $n$ grows exponentially in terms of the common subspace dimension $d_0$ (the dimension of every subspace is $d_0$), in particular, $n = \Theta(e^{d_0^\tau})$ for $\tau \in (0.5, 0.9)$, then all the competing subspace clustering methods other than Noisy $\ell^0$-SSC either do not allow overlapping subspaces, or require the maximum pairwise subspace affinity goes to 0 when $d_0 \to \infty$, which means that these methods require all the subspaces to be almost pairwise orthogonal when the common subspace dimension $d_0$ is very large. Instead, Noisy $\ell^0$-SSC allows that subspace affinity can be lower bounded from 0, suggesting that Noisy $\ell^0$-SSC is still able to recover subspaces which are not orthogonal when $d_0$ is very large.

In Table 1, it is preferred that a subspace clustering method requires milder conditions, which are allowing overlapping subspaces and larger upper bound for the maximum subspace affinity, denoted by $\max_{k,l \in [K]} \mathrm{aff}(\mathcal{S}_k, S_l)$ where $\{\mathcal{S}_k\}_{k=1}^K$ are $K$ subspaces, so that the underlying subspaces can be recovered for overlapping subspaces and for subspaces which are closer to each other (larger subspace affinity). Here aff denotes subspace affinity, $d_0$ is the common subspace dimension, $\delta$ is a small positive constant (see [Park et al., 2014]). $r_0 > 1$ is an upper bound for the support of an optimal solution to the noisy $\ell^0$-SSC problem for all data points. In this table, $n = \Theta(e^{d_0^\tau})$ for $\tau \in (0.5, 0.9)$ when $d_0 \to \infty$. Note that two subspaces are overlapping subspaces if the dimension of their intersection is larger than 1. When a subspace clustering method does not allow overlapping subspaces, then no condition on subspace affinity is presented in the subspace clustering literature.

Second, we propose Noisy Dimensionality Reduced $\ell^0$-Sparse Subspace Clustering (Noisy-DR-$\ell^0$-SSC) to accelerate noisy $\ell^0$-SSC with provable robustness to noise. Noisy-DR-$\ell^0$-SSC first projects the data onto a lower dimensional space by random projection, then performs noisy $\ell^0$-SSC on the dimensionality reduced data. Two types of random projections are used in Noisy-DR-$\ell^0$-SSC, which are the random projection induced by randomized low-rank approximation and the sparse random projection by Oblivious Sparse Norm-Approximating Projection (OSNAP).

It should be emphasized that Yang [2018] also studies dimensionality reduced $\ell^0$-SSC. However, the analysis of this work is performed on the following constrained $\ell^0$-

Table 1: Comparison between Different Subspace Clustering Methods in terms of Conditions Required under the Semi-Random Model. Please refer to Section 1.2 for the definition of notations.

| Methods or Assumptions | Allowing Overlapping Subspaces | Subspace Affinity |
|---|---|---|
| Greedy Subspace Clustering (GSC) [Park et al., 2014] | Yes | $\max_{k,l \in [K]} \text{aff}(\mathcal{S}_k, S_l) < \frac{C_2 \log n/K}{\log(d_0 L \delta^{-1}) \cdot \log(nd_0 \delta^{-1})} \overset{d_0 \to \infty}{\longrightarrow} 0$ |
| $\ell^1$-SSC [Elhamifar and Vidal, 2011], Noisy SSC [Wang and Xu, 2013] | Yes | $\max_{k,l \in [K]} \text{aff}(\mathcal{S}_k, S_l) < \sqrt{d_0} \cdot \frac{\bar{c}\sqrt{\log \rho}}{8\sqrt{2}\log n} \overset{d_0 \to \infty}{\longrightarrow} 0$ |
| Affine Sparse Subspace Clustering (ASSC)[Li et al., 2018, You et al., 2019] | No | NA |
| Noisy $\ell^0$-SSC [Yang et al., 2018] | Yes | $\max_{k,l \in [K]} \text{aff}(\mathcal{S}_k, S_l) < \frac{\sigma'(d_0, \frac{1}{\lambda})}{r_0 - 1} \overset{d_0 \to \infty}{\longrightarrow} \frac{1}{\sqrt{5}} \cdot \frac{1}{r_0 - 1} > 0$ |

minimization problem and only for clean data without noise,

$$\min_{\mathbf{Z}} \|\mathbf{Z}\|_0 \quad s.t. \ \tilde{\mathbf{X}} = \tilde{\mathbf{X}}\mathbf{Z}, \ \text{diag}(\mathbf{Z}) = \mathbf{0}, \qquad (1)$$

where $\tilde{\mathbf{X}}$ is the dimensionality reduced version of clean data by random projection. On the other hand, the actual optimization problem [Yang, 2018] solves the unconstrained $\ell^0$-regularized problem,

$$\min_{\mathbf{Z}} \left\| \tilde{\mathbf{X}} - \tilde{\mathbf{X}}\mathbf{Z} \right\|_2^2 + \lambda \|\mathbf{Z}\|_0 \quad s.t. \ , \ \text{diag}(\mathbf{Z}) = \mathbf{0}. \quad (2)$$

In contrast, we analyze noisy $\ell^0$-SSC on the unconstrained $\ell^0$-regularized problem with noisy data which reveals the advantage of noisy $\ell^0$ SSC over $\ell^1$-SSC. Our analysis also suggests that a larger $\lambda$ tends to guarantee the subspace detection property (Remark 3.5), which is verified by experiments. Throughout this paper, we refer to $\ell^0$-SSC for noisy data with the unconstrained $\ell^0$-regularized problem as noisy $\ell^0$-SSC.

## 2 PROBLEM SETUP

### 2.1 NOTATIONS

We hereby introduce the notations for subspace clustering on noisy data considered in this paper. The uncorrupted data matrix is denoted by $\mathbf{Y} = [\mathbf{y}_1, \dots, \mathbf{y}_n] \in \mathbb{R}^{d \times n}$, where $d$ is the dimensionality and $n$ is the size of the data. The uncorrupted data $\mathbf{Y}$ lie in a union of $K$ distinct subspaces $\{\mathcal{S}_k\}_{k=1}^K$ of dimensions $\{d_k\}_{k=1}^K$ with $d_{\max} := \max_{k \in [K]} d_k$ and $d_{\min} := \min_{k \in [K]} d_k$. The observed noisy data is $\mathbf{X} = \mathbf{Y} + \mathbf{N}$, where $\mathbf{N} = [\mathbf{n}_1, \dots, \mathbf{n}_n] \in \mathbb{R}^{d \times n}$ is the additive noise. $\mathbf{x}_i = \mathbf{y}_i + \mathbf{n}_i$ is the noisy data point that is corrupted by the noise $\mathbf{n}_i$. We let $\mathbf{Y}^{(k)} \in \mathbb{R}^{d \times n_k}$ denote the data belonging to subspace $\mathcal{S}_k$ with $\sum_{k=1}^K n_k = n$, and denote the corresponding columns in $\mathbf{X}$ by $\mathbf{X}^{(k)}$. Let $\mathbf{U}^{(k)} \in \mathbb{R}^{d \times d_k}$ be the orthogonal basis of $\mathcal{S}_k$ for all $k \in [K]$. The data $\mathbf{X}$ are normalized such that each column has unit $\ell^2$-norm in our deterministic analysis. We consider deterministic noise model where the noise $\mathbf{N}$ is fixed and $\max_{i \in [n]} \|\mathbf{n}_i\|_2 \leq \delta$. Note that our analysis can be extended to a random noise model which is common and also considered by noisy SSC [Wang and Xu, 2013], and the random noise model assumes that columns of $\mathbf{N}$ are i.i.d. samples

with maximum $\ell_2$-norm bounded by $\delta$ with high probability. Note that such random noise model does not require spherical symmetric noise as that in Wang and Xu [2013].

## 2.2 REVISITING SPARSE SUBSPACE CLUSTERING (SSC) AND $\ell^0$-SSC

Sparse Subspace Clustering (SSC) methods, such as [Elhamifar and Vidal, 2011, Soltanolkotabi and Candés, 2012], construct a sparse similarity matrix by sparse representation of the data, and then perform clustering on the sparse similarity matrix.

Formally, given observed data $\mathbf{X} \in \mathbb{R}^{d \times n}, \mathbf{X} = [\mathbf{x}_1, \dots, \mathbf{x}_n]$, where $\mathbf{x}_i \in \mathbb{R}^d$, SSC solves the following optimization problem for each $i \in [n]$:

$$\min_{\boldsymbol{\beta} \in \mathbb{R}^n} \|\boldsymbol{\beta}\|_1 \quad \text{s.t. } \mathbf{x}_i = \mathbf{X}\boldsymbol{\beta}, \boldsymbol{\beta}_i = 0. \qquad (3)$$

In order to handle noisy data, noisy SSC [Wang and Xu, 2013] was proposed to solve the $\ell^1$ regularized problem:

$$\min_{\boldsymbol{\beta} \in \mathbb{R}^n} \|\mathbf{x}_i - \mathbf{X}\boldsymbol{\beta}\|^2 + \lambda \|\boldsymbol{\beta}\|_1, \quad \text{s.t. } \boldsymbol{\beta}_i = 0. \qquad (4)$$

The sparse code $\boldsymbol{\beta}$ of the data point $\mathbf{x}_i$ is obtained by solving (3) or (4) for SSC or noisy SSC. A coefficient matrix $\mathbf{Z} \in \mathbb{R}^{n \times n}$ is then formed by concatenating the sparse codes of all the data points, and the $i$-th column of $\mathbf{Z}$ is the sparse code of $\mathbf{x}_i$. The sparse similarity matrix is then computed by $\mathbf{W} = \frac{|\mathbf{Z}| + |\mathbf{Z}^\top|}{2}$. Subspace detection property (SDP, to be formally defined later) ensures that the similarity between data from different subspaces vanishes in the sparse similarity matrix. If SDP holds, then similarity between data points from different clusters vanish in $\mathbf{W}$. As a result, performing spectral clustering on $\mathbf{W}$ leads to compelling clustering results.

Under the independence assumption on the subspaces, low rank representation [Liu et al., 2013b] is proposed to recover the subspace structures. Relaxing the assumptions on the subspaces to allowing overlapping subspaces, the Greedy Subspace Clustering [Park et al., 2014] and the Low-Rank Sparse Subspace Clustering [Liu et al., 2013b] achieve subspace detection property with high probability. The geometric analysis in Soltanolkotabi and Candés [2012] shows the theoretical results on subspace recovery by SSC. In the following text, we use the term SSC or $\ell^1$-SSC exchangeably to indicate the Sparse Subspace Clustering method

in Elhamifar and Vidal [2011], Soltanolkotabi and Candés [2012].

$\ell^0$-SSC [Yang et al., 2018] proposes to solve the following $\ell^0$ sparse representation problem

$$\min_{\mathbf{Z} \in \mathbb{R}^{n \times n}} \|\mathbf{Z}\|_0 \quad s.t. \ \mathbf{X} = \mathbf{XZ}, \ \text{diag}(\mathbf{Z}) = \mathbf{0}, \quad (5)$$

and it proves that SDP is satisfied with an globally optimal solution to problem (1). in Yang et al. [2018], the $\ell^0$ regularized sparse approximation problem below is solved so as to handle noisy data for $\ell^0$-SSC, which is the optimization problem of noisy $\ell^0$-SSC:

$$\min_{\mathbf{Z} \in \mathbb{R}^{n \times n}, \text{diag}(\mathbf{Z})=0} L(\mathbf{Z}) = \|\mathbf{X} - \mathbf{XZ}\|_F^2 + \lambda \|\mathbf{Z}\|_0, . \quad (6)$$

The optimization problem of noisy $\ell^0$-SSC (2) is separable. For each $i \in [n]$, the optimization problem with respect to the sparse code $\boldsymbol{\beta}$ of $i$-th data point is

$$\min_{\boldsymbol{\beta} \in \mathbb{R}^n, \boldsymbol{\beta}_i=0} L(\boldsymbol{\beta}) = \|\mathbf{x}_i - \mathbf{X}\boldsymbol{\beta}\|_2^2 + \lambda \|\boldsymbol{\beta}\|_0. \quad (7)$$

The sparse similarity matrix $\mathbf{W}$ is then computed in the same way as $\ell^1$-SSC by $\mathbf{W} = \frac{|\mathbf{Z}| + |\mathbf{Z}^\top|}{2}$, and the subspace clustering result of noisy $\ell^0$-SSC is achieved by performing spectral clustering on $\mathbf{W}$.

In the following text, we always use $\boldsymbol{\beta}^*$ to denote an optimal solution to (7), and define $r^* := \|\boldsymbol{\beta}^*\|_0$.

The definition of subspace detection property for noisy $\ell^0$-SSC and noiseless $\ell^0$-SSC, i.e. $\ell^0$-SSC on noiseless data, is defined in Definition 2.1 below.

**Definition 2.1.** (Subspace detection property for noisy and noiseless $\ell^0$-SSC) Let $\mathbf{Z}^*$ be an optimal solution to (6). The subspaces $\{\mathcal{S}_k\}_{k=1}^K$ and the data $\mathbf{X}$ satisfy the Subspace Detection Property (SDP) for noisy $\ell^0$-SSC if $\mathbf{Z}^i$ is a nonzero vector, and nonzero elements of $\mathbf{Z}^i$ correspond to the columns of $\mathbf{X}$ from the same subspace as $\mathbf{y}_i$ for all $1 \leq i \leq n$. We say that SDP holds for $\mathbf{x}_i$ if nonzero elements of $\mathbf{Z}^{*i}$, which is $\boldsymbol{\beta}^*$ for problem (7), correspond to the data that lie in the same subspace as $\mathbf{y}_i$, for either noisy $\ell^0$-SSC or noiseless $\ell^0$-SSC.

It should be emphasized that the theoretical analysis of $\ell^0$-SSC [Yang et al., 2018] is limited to clean data, as a result, it is not clear if SDP can hold for an optimal solution to the noisy $\ell^0$-SSC problem. In the following section, we provide theoretical analysis of

# 3 THEORETICAL ANALYSIS FOR NOISY $\ell^0$-SSC

The theoretical results on the subspace detection property for noisy $\ell^0$-SSC are presented in this section under the deterministic model and the semi-random model. These models are introduced in the following subsection.

## 3.1 MODELS

Similar to Soltanolkotabi and Candés [2012], we introduce the deterministic and the semi-random model for the analysis of noisy $\ell^0$-SSC.

- **Deterministic Model:** the subspaces and the data in each subspace are fixed.

- **Semi-Random Model:** the subspaces are fixed but the data are independent and identically distributed in each of the subspaces.

The data in the above definitions refer to clean data without noise. Both the deterministic model and the semi-random model are extensively employed to analyze the subspace detection property in the subspace learning literature [Soltanolkotabi and Candés, 2012, Wang et al., 2013, Wang and Xu, 2013, Yining Wang and Singh, 2016].

## 3.2 NOISY $\ell^0$-SSC: DETERMINISTIC ANALYSIS

We introduce the definition of general position and external subspace before our analysis on noisy $\ell^0$-SSC.

**Definition 3.1.** (General position) For any $1 \leq k \leq K$, the data $\mathbf{Y}^{(k)}$ are in general position if any subset of $L \leq d_k$ data points (columns) of $\mathbf{Y}^{(k)}$ are linearly independent. $\mathbf{Y}$ are in general position if $\mathbf{Y}^{(k)}$ are in general position for $1 \leq k \leq K$.

The assumption of general condition is rather mild. In fact, if the data points in $\mathbf{X}^{(k)}$ are independently distributed according to any continuous distribution, then they almost surely in general position.

Let the distance between a point $\mathbf{x} \in \mathbb{R}^d$ and a subspace $\mathcal{S} \subseteq \mathbb{R}^d$ be defined as $d(\mathbf{x}, \mathcal{S}) = \inf_{\mathbf{y} \in \mathcal{S}} \|\mathbf{x} - \mathbf{y}\|_2$, the definition of external subspaces is presented as follows.

**Definition 3.2.** (External subspace of limited dimension) For a point $\mathbf{y} \in \mathbf{Y}^{(k)}$, a subspace $\mathbf{H}_{\{\mathbf{y}_{i_j}\}_{j=1}^L}$ spanned by a set of linear independent points $\{\mathbf{y}_{i_j}\}_{j=1}^L \subseteq \mathbf{Y}$ is defined to be an external subspace of $\mathbf{y}$ if $\{\mathbf{y}_{i_j}\}_{j=1}^L \not\subseteq \mathbf{Y}^{(k)}$ and $\mathbf{y} \notin \{\mathbf{y}_{i_j}\}_{j=1}^L$. The set of all external subspaces of $\mathbf{y}$ of dimension no greater than $r$ with $r \geq 1$ for $\mathbf{y}$ is denoted by $\mathcal{H}_{\mathbf{y},r}$, that is, $\mathcal{H}_{\mathbf{y},r} = \{\mathbf{H} \colon \mathbf{H} = \mathbf{H}_{\{\mathbf{y}_{i_j}\}_{j=1}^L}, \dim[\mathbf{H}] = L, L \leq r, \{\mathbf{y}_{i_j}\}_{j=1}^L \not\subseteq \mathbf{Y}^{(k)}, \mathbf{y} \notin \{\mathbf{y}_{i_j}\}_{j=1}^L\}$. The point $\mathbf{y}$ is said to be away from its external subspaces of dimension $r$ if $\min_{\mathbf{H} \in \mathcal{H}_{\mathbf{y},r}} d(\mathbf{y}, \mathbf{H}) > 0$. All the data points in $\mathbf{Y}^{(k)}$ are said to be away from the external subspaces if each of them is away from the its associated external spaces.

To present our theoretical results of the correctness of noisy $\ell^0$-SSC, we need the definitions related to the spectrum of $\mathbf{X}$ and $\mathbf{Y}$, which are defined as follows. In the following

analysis, we employ $\boldsymbol{\beta}$ to denote the sparse code of datum $\mathbf{x}_i$ so that a simpler notation other than $\mathbf{Z}^i$ is dedicated to our analysis.

**Definition 3.3.** The minimum restricted eigenvalue of the uncorrupted data is defined as

$$\sigma_{\mathbf{Y},r} := \min_{\boldsymbol{\beta}: \|\boldsymbol{\beta}\|_0 = r, \mathrm{rank}(\mathbf{Y}_{\boldsymbol{\beta}}) = \|\boldsymbol{\beta}\|_0} \sigma_{\min}(\mathbf{Y}_{\boldsymbol{\beta}}) \qquad (8)$$

for $r \geq 1$. In addition, the normalized minimum restricted eigenvalue of the uncorrupted data is defined by

$$\bar{\sigma}_{\mathbf{Y},r} := \frac{\sigma_{\mathbf{Y},r}}{\sqrt{r}} \qquad (9)$$

Moreover, the following quantities are defined for our analysis. We define

$$\tau_0 := \frac{2\delta\sqrt{r^*}}{\sigma_{\mathbf{X}}^*} + \tau_1, \qquad (10)$$

where

$$\tau_1 := \frac{\delta}{\bar{\sigma}_{\mathbf{Y}}^* - \delta}, \quad \sigma_{\mathbf{X}}^* := \sigma_{\min}(\mathbf{X}_{\boldsymbol{\beta}^*}), \qquad (11)$$

with $\delta < \bar{\sigma}_{\mathbf{Y}}^*$, and $\bar{\sigma}_{\mathbf{Y}}^*$ is defined as

$$\bar{\sigma}_{\mathbf{Y}}^* := \min_{1 \leq r < r^*} \bar{\sigma}_{\mathbf{Y},r}. \qquad (12)$$

Now we present the main result on the correctness of noisy $\ell^0$-SSC.

**Theorem 3.1.** (Subspace detection property holds for noisy $\ell^0$-SSC) Let nonzero vector $\boldsymbol{\beta}^*$ be an optimal solution to the noisy $\ell^0$-SSC problem (7) for point $\mathbf{x}_i$ with $\|\boldsymbol{\beta}^*\|_0 = r^* \geq 1$, and $c^* := \|\mathbf{x}_i - \mathbf{X}\boldsymbol{\beta}^*\|_2$. Suppose $\mathbf{Y}$ is in general position, $\mathbf{y}_i \in \mathcal{S}_k$ for some $1 \leq k \leq K$, $\delta < \bar{\sigma}_{\mathbf{Y}}^*$, $\lambda > \tau_0$, $\mathbf{B}(\mathbf{y}_i, \delta + c^* + \frac{2\delta\sqrt{r^*}}{\sigma_{\mathbf{X}}^*}) \cap \mathbf{H} = \emptyset$ for any $\mathbf{H} \in \mathcal{H}_{\mathbf{y}_i,r^*}$. Then the subspace detection property holds for $\mathbf{x}_i$ with $\boldsymbol{\beta}^*$. Here $\tau_0$, $\tau_1$, $\bar{\sigma}_{\mathbf{Y}}^*$ and $\sigma_{\mathbf{X}}^*$ are defined in (10), (11) and (12).

**Remark 3.2.** When $\delta = 0$ and there is no noise in the data $\mathbf{X}$, the conditions for the correctness of noisy $\ell^0$-SSC in Theorem 3.1 almost reduce to that for noiseless $\ell^0$-SSC. To see this, the conditions are reduced to $\mathbf{B}(\mathbf{y}_i, c^*) \cap \mathbf{H} = \emptyset$, which are exactly the conditions required by noiseless $\ell^0$-SSC in Lemma 7.1 in the supplementary, namely data are away from the external subspaces by choosing $\lambda \to 0$ and it follows that $c^* = 0$.

While Theorem 3.1 establishes geometric conditions under which the subspace detection property holds for noisy $\ell^0$-SSC, it can be seen that these conditions are often coupled with an optimal solution $\boldsymbol{\beta}^*$ to the noisy $\ell^0$-SSC problem (7). In the following theorem, the correctness of noisy $\ell^0$-SSC is guaranteed in terms of $\lambda$, the weight for the $\ell^0$ regularization

term in (7), and the geometric conditions independent of an optimal solution to (7).

Let $M_i > 0$ be the minimum distance between $\mathbf{y}_i \in \mathcal{S}_k$ and its external subspaces when $\mathbf{y}_i$ is away from its external subspaces of dimension $r$, that is,

$$M_i := \min\{d(\mathbf{y}_i, \mathbf{H}): \mathbf{H} \in \mathcal{H}_{\mathbf{y}_i,d_k}\}, \qquad (13)$$

The following two quantities related to the spectrum of clean and noisy data, $\mu_r$ and $\sigma_{\mathbf{X},r}$, are defined as follows with $r > 1$ for the analysis in Theorem 3.3.

$$\mu_r := \frac{\delta}{\min_{1 \leq r' < r} \bar{\sigma}_{\mathbf{Y},r} - \delta}, \qquad (14)$$

$$\sigma_{\mathbf{X},r} := \min\{\sigma_{\min}(\mathbf{X}_{\boldsymbol{\beta}}): 1 \leq \|\boldsymbol{\beta}\|_0 \leq r\} \qquad (15)$$

**Theorem 3.3.** (Subspace detection property holds for noisy $\ell^0$-SSC under deterministic model with conditions in terms of $\lambda$) Let nonzero vector $\boldsymbol{\beta}^*$ be an optimal solution to the noisy $\ell^0$-SSC problem (7) for point $\mathbf{x}_i$ with $\|\boldsymbol{\beta}^*\|_0 = r^* > 1$, $n_k \geq d_k + 1$ for every $k \in [K]$, and there exists $1 < r_0 \leq \lfloor \frac{1}{\lambda} \rfloor$ such that $r^* \leq r_0$. Suppose $\mathbf{Y}$ is in general position, $\mathbf{y}_i \in \mathcal{S}_k$ for some $1 \leq k \leq K$, $\delta < \bar{\sigma}_{\mathbf{Y}}^*$, and $M_{i,\delta} := M_i - \delta$. Suppose

$$M_{i,\delta} > \frac{2\delta}{\sigma_{\mathbf{X},r_0}}, \qquad (16)$$

and

$$\mu_{r_0} < 1 - \frac{2\delta}{\sigma_{\mathbf{X},r_0}}. \qquad (17)$$

Then if

$$\lambda_0 < \lambda < 1, \qquad (18)$$

where $\lambda_0 := \max\{\lambda_1, \lambda_2\}$ and

$$\lambda_1 := \inf\{0 < \lambda < 1: \sqrt{1 - \lambda} + \frac{2\delta}{\sigma_{\mathbf{X},r_0}\sqrt{\lambda}} < M_{i,\delta}\}, \qquad (19)$$

$$\lambda_2 := \inf\{0 < \lambda < 1: \lambda - \frac{2\delta}{\sigma_{\mathbf{X},r_0}}\frac{1}{\sqrt{\lambda}} > \mu_{r_0}\}, \qquad (20)$$

the subspace detection property holds for $\mathbf{x}_i$ with $\boldsymbol{\beta}^*$. Here $M_i$, $\mu_{r_0}$ and $\sigma_{\mathbf{X},r_0}$ are defined in (13), (14) and (15) respectively.

**Remark 3.4.** The two conditions (16) and (17) are induced by two conditions, $\mathbf{B}(\mathbf{y}_i, \delta + c^* + \frac{2\delta\sqrt{r^*}}{\sigma_{\mathbf{X}}^*}) \cap \mathbf{H} = \emptyset$ for any $\mathbf{H} \in \mathcal{H}_{\mathbf{y}_i,d_k}$ and $\lambda > \tau_0$ respectively, which are required by Theorem 3.1. Note that when (16) and (17) hold, $\lambda_1$ and $\lambda_2$ can always be chosen in accordance with (19) and (20).

**Remark 3.5.** It can be observed from condition (18) that noisy $\ell^0$-SSC encourages sparse solution by a relatively large $\lambda$ so as to guarantee the subspace detection property. This theoretical finding is consistent with the empirical study shown in the experimental results.

## 3.3 NOISY $\ell^0$-SSC: RANDOMIZED ANALYSIS

In this subsection, the correctness of noisy $\ell^0$-SSC is analyzed under the semi-random model that the data in subspace $\mathcal{S}^{(k)}$ are i.i.d. according to the uniform distribution on the unit sphere, $\mathbb{S}^{d_k-1}$, of $\mathbb{R}^{d_k}$ centered at the origin for all $k \in [K]$. This setting is employed extensively in the subspace learning literature [Soltanolkotabi and Candés, 2012, Wang et al., 2013, Wang and Xu, 2013, Yining Wang and Singh, 2016]. We then have the major theorem below stating the theoretical guarantee of the subspace detection property of noisy $\ell^0$-SSC under the semi-random model. Before stating this theorem, we introduce the following definition of subspace affinity, which is widely used in the analysis of semi-random model in the sparse subspace clustering literature.

**Definition 3.4.** (Subspace affinity) The affinity between two subspaces, $\mathcal{S}_k$ and $\mathcal{S}_l$ with $k, l \in [K]$, is defined by

$$\mathrm{aff}(\mathcal{S}_k, \mathcal{S}_l) = \sqrt{\sum_{t=1}^{\min\{k,l\}} \cos^2 \theta_{kl}^{(t)}}, \qquad (21)$$

where $\cos \theta_{kl}^{(t)}$ is the $t$-th canonical angle between $\mathcal{S}_k$ and $\mathcal{S}_l$ defined in Soltanolkotabi and Candés [2012]. Let $\mathbf{U}^{(k)}$ and $\mathbf{U}^{(l)}$ be the orthonormal basis for $\mathcal{S}_k$ and $\mathcal{S}_l$ respectively, then

$$\cos \theta_{kl}^{(t)} = \sup_{\mathbf{u} \in \mathcal{S}_k, \mathbf{v} \in \mathcal{S}_l} \frac{\mathbf{u}^\top \mathbf{v}}{\|\mathbf{u}\|_2 \|\mathbf{v}\|_2} = \frac{\mathbf{u}^{t\top} \mathbf{v}^t}{\|\mathbf{u}^t\|_2 \|\mathbf{v}^t\|_2},$$

with the orthogonality constraints $\mathbf{u}^\top \mathbf{u}^j = 0$ and $\mathbf{v}^\top \mathbf{v}^j = 0$ with $j = 1, 2, \ldots, t-1$. It can be verified that $\mathrm{aff}(\mathcal{S}_k, \mathcal{S}_l) = \|\mathbf{U}^{(k)\top} \mathbf{U}^{(l)}\|_F$.

**Theorem 3.6.** (Subspace detection property holds for noisy $\ell^0$-SSC under semi-random model with conditions in terms of $\lambda$) Under the semi-random model, let nonzero vector $\boldsymbol{\beta}^*$ be an optimal solution to the noisy $\ell^0$-SSC problem (7) for point $\mathbf{x}_i$ with $\|\boldsymbol{\beta}^*\|_0 = r^* > 1$, $n_k \geq d_k + 1$ for every $1 \leq k \leq K$, and there exists $1 < r_0 \leq \lfloor \frac{1}{\lambda} \rfloor$ such that $r^* \leq r_0$. Let $\sigma'(d_{\min}, \frac{1}{\lambda}) := \frac{1}{\sqrt{5}} \left( 1 - 14\sqrt[3]{4}(\frac{M^2}{\lambda d_{\min}})^{2/3} \right)$, $c := \sqrt{\frac{\sigma'^2_{\min} - (r_0-1)\mathrm{aff}(\mathcal{S}_{t_1}, \mathcal{S}_{t_2})}{r_0}}$. For $t > 0$ such that $\frac{1}{d_{\max}} - 2t\sqrt{1 - \frac{1}{d_{\max}} - t^2} > 0$, suppose

$$\max_{t_1, t_1 \in [K], t_1 \neq t_2} \mathrm{aff}(\mathcal{S}_{t_1}, \mathcal{S}_{t_2}) < \frac{\sigma'(d_{\min}, \frac{1}{\lambda})}{r_0 - 1}, \qquad (22)$$

$$\delta < c, \qquad (23)$$

$$\delta + \frac{2\delta}{\sqrt{r_0}(c - \delta)} \leq \frac{1}{d_{\max}} - 2t\sqrt{1 - \frac{1}{d_{\max}} - t^2}, \qquad (24)$$

$$\frac{\delta}{c - \delta} + \frac{2\delta}{\sqrt{r_0}(c - \delta)} < 1, \qquad (25)$$

and

$$\lambda_0' < \lambda < 1, \qquad (26)$$

where $M := \sup_{0 \leq t < 1} \frac{2t^3 \arccos t}{\pi} < 1$, $\lambda_0' := \max\{\lambda_1', \lambda_2'\}$,

$$\lambda_1' := \inf\{0 < \lambda < 1 : \sqrt{1 - \lambda} + \frac{2\delta}{\sqrt{r_0}(c - \delta)\sqrt{\lambda}}$$
$$< \frac{1}{d_{\max}} - 2t\sqrt{1 - \frac{1}{d_{\max}} - t^2} - \delta\}, \qquad (27)$$

$$\lambda_2' := \inf\{0 < \lambda < 1 : \lambda - \frac{2\delta}{\sqrt{r_0}(c - \delta)}\frac{1}{\sqrt{\lambda}} > \frac{\delta}{c - \delta}\}, \qquad (28)$$

and $d_{\min} > \left(14\sqrt[3]{4}\right)^{\frac{3}{2}} \frac{M^2}{\lambda}$. Then with probability at least $1 - \sum_{k=1}^{K} \left( \exp(-d_k) + 2n_k \exp\left(-d_k^{0.9}\right) \right) - 8 \sum_{k=1}^{K} n_k \exp(-\frac{d_k t^2}{2})$, the subspace detection property holds for $\mathbf{x}_i$ with $\boldsymbol{\beta}^*$ for all $i \in [n]$.

**Remark 3.7** (Advantage of Noisy $\ell^0$-SSC in terms of Subspace Affinity). It is well known that the difficulty of achieving the subspace detection property increases with larger affinity between subspaces, that is, the subspace are closer to each other. Our analysis reveals the significant advantage of noisy $\ell^0$-SSC over $\ell^1$-SSC in terms of the maximum subspace affinity. To the best of our knowledge, the best theoretical result of $\ell^1$-SSC, including its geometrical analysis [Soltanolkotabi and Candés, 2012] and the subsequent works on noisy or dimensionality-reduced data [Wang and Xu, 2013, Wang et al., 2015], requires that the maximum subspace affinity satisfies

$$\max_{t_1, t_1 \in [K], t_1 \neq t_2} \mathrm{aff}(\mathcal{S}_{t_1}, \mathcal{S}_{t_2}) < \sqrt{d_0} \cdot \frac{\bar{c}\sqrt{\log \rho}}{8\sqrt{2}\log n}, \qquad (29)$$

under the setting in Soltanolkotabi and Candés [2012] that $d_k = d_0$ and $n_k = \rho d_0 + 1$ for all $k \in [K]$, so that $n = K(\rho d_0 + 1)$. When $n > \exp(d_0^\tau)$ for $\tau \in (0.5, 0.9)$, then (29) requires $\max_{t_1, t_1 \in [K], t_1 \neq t_2} \mathrm{aff}(\mathcal{S}_{t_1}, \mathcal{S}_{t_2}) \to 0$ when $d_0 \to \infty$, while the condition of noisy $\ell^0$-SSC, (22), only requires that $\max_{t_1, t_1 \in [K], t_1 \neq t_2} \mathrm{aff}(\mathcal{S}_{t_1}, \mathcal{S}_{t_2}) < \frac{1}{\sqrt{5}} \cdot \frac{1}{r_0 - 1}$ where $r_0$ can be set to $\lfloor \frac{1}{\lambda} \rfloor$ when $d_0 \to \infty$. Such less restive condition on the maximum subspace affinity reveals the theoretical advantage of noisy $\ell^0$-SSC over $\ell^1$-SSC.

## 4 NOISY $\ell^0$-SSC ON DIMENSIONALITY REDUCED DATA: NOISY-DR-$\ell^0$-SSC

Albeit the theoretical guarantee and compelling empirical performance of noisy $\ell^0$-SSC to be shown in the experimental results, the computational cost of noisy $\ell^0$-SSC is high with the high dimensionality of the data. In this section, we propose Noisy Dimensionality Reduced $\ell^0$-SSC (Noisy-DR-$\ell^0$-SSC) which performs noisy $\ell^0$-SSC on dimensionality reduced data. The theoretical guarantee on the correctness of Noisy-DR-$\ell^0$-SSC under the deterministic model as well as its empirical performance are presented.

## 4.1 METHOD

Noisy-DR-$\ell^0$-SSC performs subspace clustering by the following two steps: 1) obtain the dimension reduced data $\tilde{\mathbf{X}} = \mathbf{P}\mathbf{X}$ with a linear transformation $\mathbf{P} \in \mathbb{R}^{p \times d}$ ($p < d$). 2) perform noisy $\ell^0$-SSC on the compressed data $\tilde{\mathbf{X}}$:

$$\min_{\tilde{\boldsymbol{\beta}} \in \mathbb{R}^n, \tilde{\boldsymbol{\beta}}_i = 0} L(\tilde{\boldsymbol{\beta}}) = \|\tilde{\mathbf{x}}_i - \tilde{\mathbf{X}}\boldsymbol{\beta}\|_2^2 + \tilde{\lambda}\|\tilde{\boldsymbol{\beta}}\|_0. \quad (30)$$

If $p < d$, Noisy-DR-$\ell^0$-SSC operates on the compressed data $\tilde{\mathbf{X}}$ rather than on the original data, so that the efficiency is improved. We will introduce two different types of random projection for Noisy-DR-$\ell^0$-SSC in the following two subsections.

## 4.2 RANDOM PROJECT INDUCED BY RANDOMIZED LOW-RANK APPROXIMATION

High-dimensional data often exhibits low-dimensional structures, which often leads to low-rankness of the data matrix. Intuitively, if the data is low rank, then it could be safe to perform noisy $\ell^0$-SSC on its dimensionality reduced version by the linear projection $\mathbf{P}$, and it is expected that $\mathbf{P}$ can preserve the information of the subspaces contained in the original data as much as possible, while effectively removing uninformative dimensions.

To this end, we propose to choose $\mathbf{P}$ as a random projection induced by randomized low-rank approximation of the data. The key idea is to obtain an approximate low-rank decomposition of the data. Using the random projection induced by such low-rank approximation as the linear transformation $\mathbf{P}$, the clustering correctness hold for Noisy-DR-$\ell^0$-SSC with a high probability.

Randomized algorithms are efficient and they have been extensively studied in the computer science and numerical linear algebra literature. They have been employed to accelerate various numerical matrix computation and matrix optimization problems, including random projection for matrix decomposition [Frieze et al., 2004, Drineas et al., 2004, Sarlos, 2006, Drineas et al., 2006, 2008, Mahoney and Drineas, 2009, Drineas et al., 2011, Lu et al., 2013].

Formally, a random matrix $\mathbf{T} \in \mathbb{R}^{n \times p}$ is generated such that each element $\mathbf{T}_{ij}$ is sampled independently according to the Gaussian distribution $\mathcal{N}(0, 1)$. QR decomposition is then performed on $\mathbf{X}\mathbf{T}$ to obtain the basis of its column space, namely $\mathbf{X}\mathbf{T} = \mathbf{Q}\mathbf{R}$ where $\mathbf{Q} \in \mathbb{R}^{d \times p}$ is an orthogonal matrix of rank $p$ and $\mathbf{R} \in \mathbb{R}^{p \times p}$ is an upper triangle matrix. The columns of $\mathbf{Q}$ form the orthogonal basis for the sample matrix $\mathbf{X}\mathbf{T}$. An approximation of $\mathbf{X}$ is then obtained by projecting $\mathbf{X}$ onto the column space of $\mathbf{X}\mathbf{T}$: $\mathbf{Q}\mathbf{Q}^\top\mathbf{X} = \mathbf{Q}\mathbf{W} = \widehat{\mathbf{X}}$ where $\mathbf{W} = \mathbf{Q}^\top\mathbf{X} \in \mathbb{R}^{p \times n}$. In this manner, a randomized low-rank decomposition of $\mathbf{X}$ is achieved by

$$\widehat{\mathbf{X}} = \mathbf{Q}\mathbf{W}. \quad (31)$$

It is proved that the low rank approximation $\bar{\mathbf{X}}$ is close to $\mathbf{X}$ in terms of the spectral norm [Halko et al., 2011]. We present probabilistic result in Theorem 4.1 on the correctness of Noisy-DR-$\ell^0$-SSC using the random projection induced by randomized low-rank decomposition of the data $\mathbf{X}$, namely $\mathbf{P} = \mathbf{Q}^\top$. In the sequel, $\tilde{\mathbf{x}} = \mathbf{P}\mathbf{x}$ for any $\mathbf{x} \in \mathbb{R}^n$. To guarantee the subspace detection property on the dimensionality-reduced data $\tilde{\mathbf{X}}$, it is crucial to make sure that the conditions, such as (16) and (17) in Theorem 3.3, still hold after the linear transformation.

Each subspace $\mathcal{S}_k$ is transformed into $\tilde{\mathcal{S}}_k = \mathbf{P}(\mathcal{S}_k)$ with dimension $\tilde{d}_k$. We denote by $\tilde{\boldsymbol{\beta}}^*$ an optimal solution to (30), and define $C_{p,p_0} := \left(1 + 17\sqrt{1 + \frac{p_0}{p - p_0}}\right)\sigma_{p_0+1} + \frac{8\sqrt{p}}{p - p_0 + 1}\left(\sum_{j > p_0} \sigma_j^2\right)^{\frac{1}{2}}$ with $p_0 \geq 2$. We also define the following quantities for the convenience of our analysis, which correspond to $M_i$, $\bar{\sigma}_{\mathbf{Y},r}$, $\sigma_{\mathbf{X},r}$ and $\mu_r$ used in the analysis on the original data:

$$\tilde{M}_i := \min\{d(\tilde{\mathbf{y}}_i, \mathbf{H}): \mathbf{H} \in \mathcal{H}_{\tilde{\mathbf{y}}_i, \tilde{d}_k}\}, \quad (32)$$

where $\mathcal{H}_{\tilde{\mathbf{y}}_i, \tilde{d}_k}$ is all the external subspaces of $\tilde{\mathbf{y}}_i$ with dimension no greater than $\tilde{d}_k$ in the transformed space by $\mathbf{P}$,

$$\bar{\sigma}_{\tilde{\mathbf{Y}},r} := \min_{\boldsymbol{\beta}: \|\boldsymbol{\beta}\|_0 = r, \text{rank}(\tilde{\mathbf{Y}}_{\boldsymbol{\beta}}) = \|\boldsymbol{\beta}\|_0} \sigma_{\min}(\tilde{\mathbf{Y}}_{\boldsymbol{\beta}}), \quad (33)$$

$$\sigma_{\tilde{\mathbf{X}},r} := \min\{\sigma_{\min}(\tilde{\mathbf{X}}_{\boldsymbol{\beta}}): 1 \leq \|\boldsymbol{\beta}\|_0 \leq r\}, \quad (34)$$

$$\tilde{\mu}_r := \frac{\delta}{\min_{1 \leq r' < r} \bar{\sigma}_{\tilde{\mathbf{Y}},r} - \delta}. \quad (35)$$

**Theorem 4.1.** (Subspace detection property holds for Noisy-DR-$\ell^0$-SSC under deterministic model) Let nonzero vector $\boldsymbol{\beta}^*$ be an optimal solution to the noisy $\ell^0$-SSC problem (7) for point $\mathbf{x}_i$ with $\|\boldsymbol{\beta}^*\|_0 = r^* > 1$, $n_k \geq d_k + 1$ for every $1 \leq k \leq K$, and there exists $1 < r_0 \leq d_k$ such that $r^* \leq r_0 = \lfloor\frac{1}{\lambda}\rfloor$. Suppose $\mathbf{Y}$ is in general position, $\delta < \min_{1 \leq r < r_0} \bar{\sigma}_{\mathbf{Y},r}$, and $\tilde{M}_{i,\delta} := \tilde{M}_i - \delta$. Furthermore, suppose the following conditions hold:

(1)

$$C_{p,p_0} + 2\delta\sqrt{\tilde{d}_{\max}} < \min_{k=1,\dots,K} \sigma_{\mathbf{Y}}^{(k)}, \quad (36)$$

where $\tilde{d}_{\max} := \max_k \tilde{d}_k$, $\sigma_{\mathbf{Y}}^{(k)} := \min\{\sigma_{\min}(\mathbf{A}): \mathbf{A} \subseteq \mathbf{Y}^{(k)}, \mathbf{A} \in \mathbb{R}^{d \times n'}, n' \leq \tilde{d}_k\}$,

(2) $\delta(1 + 2\sqrt{r_0}) < \min_{1 \leq r < r_0} \bar{\sigma}_{\mathbf{Y},r} - C_{p,p_0}$,

(3) $\min_{1 \leq r \leq \tilde{d}_k} \sigma_{\mathbf{Y},r} > C_{p,p_0} - 2\delta\sqrt{\tilde{d}_k}$ and

$$M_i - C_{p,p_0}\left(1 + \frac{1}{\min_{1 \leq r \leq \tilde{d}_k} \sigma_{\mathbf{Y},r} - C_{p,p_0} - 2\delta\sqrt{\tilde{d}_k}}\right)$$

$$> \delta + \frac{2\delta}{\sigma_{\mathbf{X},r_0} - C_{p,p_0}}, \tag{37}$$

for all $\mathbf{y}_i \in \mathcal{S}_k$ and $1 \le k \le K$,

(4) $\min_{1 \le r < r_0} \bar{\sigma}_{\mathbf{Y},r_0} > C_{p,p_0} - 2\delta\sqrt{r_0} - \delta$ and

$$\frac{\delta}{\min_{1 \le r < r_0} \bar{\sigma}_{\mathbf{Y},r_0} - C_{p,p_0} - 2\delta\sqrt{r_0} - \delta}$$
$$< 1 - \frac{2\delta}{\sigma_{\mathbf{X},r_0} - C_{p,p_0}}. \tag{38}$$

If

$$\tilde{\lambda}_0 < \tilde{\lambda} < 1, \tag{39}$$

where $\tilde{\lambda}_0 = \max\{\tilde{\lambda}_1, \tilde{\lambda}_2\}$ and

$$\tilde{\lambda}_1 = \inf\{0 < \tilde{\lambda} < 1 \colon \sqrt{1 - \tilde{\lambda}} + \frac{2\delta}{\sigma_{\tilde{\mathbf{X}},r_0}\sqrt{\tilde{\lambda}}} < \tilde{M}_{i,\delta}\}, \tag{40}$$

$$\tilde{\lambda}_2 = \inf\{0 < \tilde{\lambda} < 1 \colon \tilde{\lambda} - \frac{2\delta}{\sigma_{\mathbf{X},r_0}}\frac{1}{\sqrt{\tilde{\lambda}}} > \tilde{\mu}_{r_0}\}, \tag{41}$$

then with probability at least $1 - 6e^{-p}$, the subspace detection property holds for $\tilde{\mathbf{x}}_i$ with $\tilde{\boldsymbol{\beta}}^*$. Here $\tilde{M}_i$, $\tilde{\mu}_r$ and $\tilde{\sigma}_{\tilde{\mathbf{X}},r_0}$ are defined in (32), (35) and (34) respectively.

## 4.3 RANDOM PROJECTION BY OBLIVIOUS SPARSE NORM-APPROXIMATING PROJECTION (OSNAP)

In this subsection, we study the case when the linear transformation $\mathbf{P}$ for the dimensionality reduced $\ell^0$-SSC problem (30) is a sparse matrix, that is, the Oblivious Sparse Norm-Approximating Projection (OSNAP) [Nelson and Nguyen, 2013]. We choose $\mathbf{P}$ as one the most efficient version of OSNAP, where each column of $\mathbf{P}$ only has 1 nonzero element. Each column of $\mathbf{P}$ is chosen to have exactly one nonzero element in a random location, and each nonzero element is $\pm 1$ uniformly at random. Such $\mathbf{P}$ enjoys $\ell^2$-norm preserving property stated as follows. Let $\varepsilon$ be a positive number such that $0 < \varepsilon \le 1$. By Theorem 3 in Nelson and Nguyen [2013], for any subspace $\mathbf{S}$ of dimension $d$ in $\mathbb{R}^n$, $\Pr\big[(1-\varepsilon)\|\mathbf{v}\|_2 \le \|\mathbf{P}\mathbf{v}\|_2 \le (1+\varepsilon)\|\mathbf{v}\|_2\big] \ge 1 - \delta'$ for all $\mathbf{v} \in \mathbf{S}$ and $\delta' \in (0,1)$ if $p \ge \frac{d^2+d}{\delta'(2\varepsilon-\varepsilon^2)^2}$. We note that while the general Johnson-Lindenstrauss transform possesses the similar $\ell^2$-norm preserving property, the sparse matrix $\mathbf{P}$ considerably speeds up the computation of $\tilde{\mathbf{X}} = \mathbf{P}\mathbf{X}$.

Using the $\ell^2$-norm preserving property of OSNAP, we have the following theorem about the correctness of Noisy-DR-$\ell^0$-SSC when $\mathbf{P}$ is the said OSNAP where each column of $\mathbf{P}$ only has 1 nonzero element.

**Theorem 4.2.** (Subspace detection property holds for Noisy-DR-$\ell^0$-SSC under deterministic model with $\mathbf{P}$ being the OSNAP) Let nonzero vector $\boldsymbol{\beta}^*$ be the optimal solution to the noisy $\ell^0$-SSC problem (7) for point $\mathbf{x}_i$ with

$\|\boldsymbol{\beta}^*\|_0 = r^*$, $n_k \ge d_k + 1$ for every $1 \le k \le K$, and there exists $1 < r_0 \le \lfloor \frac{1}{\lambda} \rfloor$ such that $1 < r^* \le r_0$. Suppose $\mathbf{Y}$ is in general position, $\mathbf{y}_i \in \mathcal{S}_k$ for some $1 \le k \le K$, $\delta < \min_{1 \le r < r_0} \bar{\sigma}_{\mathbf{Y},r}$. Let $M_{i,\delta} := M_i - \delta$, $\varepsilon$ be a positive number such that $0 < \varepsilon \le 1$. Suppose

$$M_{i,\delta} > \frac{2(1+\varepsilon)^3\delta}{\sigma_{\mathbf{X},r_0}}, \tag{42}$$

and

$$\mu_{r,\varepsilon} := \frac{\delta}{\frac{\min_{1 \le r' < r} \bar{\sigma}_{\mathbf{Y},r}}{(1+\varepsilon)^2} - \delta} < 1 - \frac{2(1+\varepsilon)^2\delta}{\sigma_{\mathbf{X},r_0}}. \tag{43}$$

Then if

$$\tilde{\lambda}_0 < \tilde{\lambda} < 1, \tag{44}$$

where $\tilde{\lambda}_0 := \max\{\lambda_1, \lambda_2\}$ and

$$\lambda_1 := \inf\{0 < \tilde{\lambda} < 1 \colon \sqrt{1 + \varepsilon - \tilde{\lambda}} + \frac{2\delta}{\sigma_{\tilde{\mathbf{X}},r_0}\sqrt{\tilde{\lambda}}} < M_{i,\delta}\}, \tag{45}$$

$$\lambda_2 := \inf\{0 < \lambda < 1 \colon \lambda - \frac{2\delta}{\sigma_{\tilde{\mathbf{X}},r_0}}\frac{1}{\sqrt{\lambda}} > \tilde{\mu}_{r_0}\}, \tag{46}$$

then with probability at least $1 - K\delta'$ for all $\delta' \in (0, \frac{1}{K})$, the subspace detection property holds for $\tilde{\mathbf{x}}_i$ with $\tilde{\boldsymbol{\beta}}^*$. Here $\tilde{\mu}_{r_0}$ and $\sigma_{\tilde{\mathbf{X}},r_0}$ are defined in (35) and (34) respectively. $\tilde{\boldsymbol{\beta}}^*$ is the optimal solution to (30) with $\mathbf{P}$ being the OSNAP described in the beginning of this subsection with $p \ge \frac{d_{\max}^2 + d_{\max}}{\delta'(2\varepsilon - \varepsilon^2)^2}$.

## 4.4 THE ALGORITHM OF NOISY-DR-$\ell^0$-SSC

We denote by Noisy-DR-$\ell^0$-SSC-LR the Noisy-DR-$\ell^0$-SSC with random projection induced by randomized low-rank approximation in Section 4.2, and denote by Noisy-DR-$\ell^0$-SSC-OSNAP the Noisy-DR-$\ell^0$-SSC with OSNAP serving as the random projection in Section 4.3. Noisy-DR-$\ell^0$-SSC-LR is described by Algorithm 1. The algorithm of Noisy-DR-$\ell^0$-SSC-OSNAP is similar to Algorithm 1 except that OSNAP serves as the random projection $\mathbf{P}$, so its details are omitted here. Algorithm 2 in Section 7.4 of the supplementary describes how to solve the noisy $\ell^0$-SSC problem (7).

---

**Algorithm 1** Noisy Dimensionality Reduced $\ell^0$-Sparse Subspace Clustering by Randomized Low-Rank Approximation (Noisy-DR-$\ell^0$-SSC-LR)

---

1: Generate a Gaussian random matrix $\mathbf{T} \in \mathbb{R}^{n \times p}$ where each element $\mathbf{T}_{ij}$ is sampled independently according to the standard Gaussian distribution $\mathcal{N}(0,1)$
2: Perform QR decomposition on $\mathbf{X}\mathbf{T}$, $\mathbf{X}\mathbf{T} = \mathbf{Q}\mathbf{R}$ where $\mathbf{Q} \in \mathbb{R}^{d \times p}$
3: Set the linear transformation $\mathbf{P} = \mathbf{Q}^\top$, and obtain the dimensionality reduced data $\tilde{\mathbf{X}} = \mathbf{P}\mathbf{X}$
4: Perform noisy $\ell^0$-SSC on $\tilde{\mathbf{X}}$ using Algorithm 2

---

Table 2: Clustering results on various data sets, with the best three results in bold

| Data Set | Measure | KM | SC | Noisy SSC | Noisy DR-SSC | SMCE | SSC-OMP | Noisy $\ell^0$-SSC | Noisy-DR-$\ell^0$-SSC-LR | Noisy-DR-$\ell^0$-SSC-OSNAP |
|---|---|---|---|---|---|---|---|---|---|---|
| COIL-20 | AC | 0.6554 | 0.4278 | 0.7854 | 0.7764 | 0.7549 | 0.3389 | **0.8472 ± 0.0031** | **0.8479 ± 0.0023** | **0.8472 ± 0.0019** |
| | NMI | 0.7630 | 0.6217 | 0.9148 | 0.9219 | 0.8754 | 0.4853 | **0.9428 ± 0.0082** | **0.9433 ± 0.0063** | **0.9429 ± 0.0037** |
| COIL-100 | AC | 0.4996 | 0.2835 | 0.5275 | 0.5013 | 0.5639 | 0.1667 | **0.7683 ± 0.0020** | **0.7039 ± 0.0087** | **0.7046 ± 0.0083** |
| | NMI | 0.7539 | 0.5923 | 0.8041 | 0.8019 | 0.8064 | 0.3757 | **0.9182 ± 0.0096** | **0.8706 ± 0.0109** | **0.8708 ± 0.0117** |
| Yale-B | AC | 0.0954 | 0.1077 | 0.7850 | 0.7255 | 0.3293 | 0.7789 | **0.8480 ± 0.0091** | **0.8231 ± 0.0173** | **0.8318 ± 0.0112** |
| | NMI | 0.1258 | 0.1485 | 0.7760 | 0.7311 | 0.3812 | 0.7024 | **0.8612 ± 0.0072** | **0.8533 ± 0.0294** | **0.8593 ± 0.0133** |
| MPIE S1 | AC | 0.1164 | 0.1285 | 0.5892 | 0.3588 | 0.1721 | 0.1695 | **0.6741 ± 0.0413** | **0.6741 ± 0.0938** | **0.6744 ± 0.0662** |
| | NMI | 0.5049 | 0.5292 | 0.7653 | 0.6806 | 0.5514 | 0.3395 | **0.8622 ± 0.0533** | **0.8622 ± 0.0834** | **0.8548 ± 0.0931** |
| MPIE S2 | AC | 0.1315 | 0.1410 | 0.6994 | 0.4611 | 0.1898 | 0.2093 | **0.7527 ± 0.0115** | **0.7533 ± 0.0596** | **0.7517 ± 0.0813** |
| | NMI | 0.4834 | 0.5128 | 0.8149 | 0.7086 | 0.5293 | 0.4292 | **0.8939 ± 0.0389** | **0.8926 ± 0.0742** | **0.8910 ± 0.0454** |
| MPIE S3 | AC | 0.1291 | 0.1459 | 0.6316 | 0.4841 | 0.1856 | 0.1787 | **0.7050 ± 0.0277** | **0.7123 ± 0.0812** | **0.7184 ± 0.1045** |
| | NMI | 0.4811 | 0.5185 | 0.7858 | 0.7340 | 0.5155 | 0.3415 | **0.8750 ± 0.0157** | **0.8455 ± 0.0693** | **0.8457 ± 0.0913** |
| MPIE S4 | AC | 0.1308 | 0.1463 | 0.6803 | 0.5511 | 0.1823 | 0.1680 | **0.7246 ± 0.0147** | **0.7137 ± 0.0605** | **0.7250 ± 0.0443** |
| | NMI | 0.4866 | 0.5280 | 0.8063 | 0.7955 | 0.5294 | 0.3345 | **0.8837 ± 0.0212** | **0.8847 ± 0.0781** | **0.8834 ± 0.0517** |
| MNIST | AC | 0.5236 | 0.3504 | 0.5714 | 0.5123 | **0.6542** | 0.5561 | 0.6259 ± 0.0249 | **0.6296 ± 0.1522** | **0.6310 ± 0.1031** |
| | NMI | 0.4770 | 0.3607 | 0.6091 | 0.5026 | **0.6796** | 0.5986 | **0.6501 ± 0.0196** | 0.6440 ± 0.0259 | **0.6497 ± 0.0313** |

## 5 EXPERIMENTAL RESULTS

We demonstrate the performance of Noisy-DR-$\ell^0$-SSC-LR and Noisy-DR-$\ell^0$-SSC-OSNAP, with comparison to other competing clustering methods including K-means (KM), Spectral Clustering (SC), noisy SSC, Sparse Manifold Clustering and Embedding (SMCE) [Elhamifar and Vidal, 2011] and SSC-OMP [Dyer et al., 2013] in this section. We will use Noisy-DR-$\ell^0$-SSC to refer to its two variants. With the coefficient matrix $\mathbf{Z}$ obtained by the optimization of noisy $\ell^0$-SSC or Noisy-DR-$\ell^0$-SSC, a sparse similarity matrix is built by $\mathbf{W} = \frac{|\mathbf{Z}| + |\mathbf{Z}^\top|}{2}$, and spectral clustering is performed on $\mathbf{W}$ to obtain the clustering results. Two measures are used to evaluate the performance of different clustering methods, i.e. the Accuracy (AC) and the Normalized Mutual Information (NMI) [Zheng et al., 2004].

We use randomized rank-$p$ decomposition of the data matrix in Noisy-DR-$\ell^0$-SSC-LR with $p = \frac{\min\{d,n\}}{10}$. It can be observed that noisy $\ell^0$-SSC and Noisy-DR-$\ell^0$-SSC always achieve better performance than other methods in Table 2, including the noisy SSC on dimensionality reduced data (Noisy DR-SSC) [Wang et al., 2015]. Note that noisy $\ell^0$-SSC has the same performance as $\ell^0$-SSC [Yang et al., 2018]. Throughout all the experiments we find that the best clustering accuracy is achieved whenever $\lambda$ is chosen by $0.5 < \lambda < 0.95$, justifying our theoretical finding claimed in Remark 3.5 and (18) in Theorem 3.3. For all the methods that involve random projection, we conduct the experiments for 30 times and report the average performance. Note that the cluster accuracy of SSC-OMP on the extended Yale-B data set is reported according to You et al. [2016]. We randomly sample 1000 images from each class of the MNIST data set so as to collect a total number of 10000 images on which clustering is performed, and the average performance of 10 random sampling is reported for this data set. The time complexity of noisy $\ell^0$-SSC and the two variants of Noisy-DR-$\ell^0$-SSC are analyzed in Section 7.3 of the supplementary. The actual running time of both algorithms confirms such time complexity, and we observe that Noisy-DR-$\ell^0$-SSC-LR is always 8.7 times faster than noisy $\ell^0$-SSC with the same number of iterations, and the acceleration is boosted to 9.6 times by Noisy-DR-$\ell^0$-SSC-OSNAP due to the sparse random projection.

### 5.1 JUSTIFICATION OF THEORETICAL ANALYSIS FOR NOISY $\ell^0$-SSC

We further demonstrates the practical implication of our theoretical Analysis for noisy $\ell^0$-SSC. As mentioned in Remark 3.5, a relatively large $\lambda$ tends to preserve the subspace detection property. This theoretical finding is consistent with the empirical study shown in this subsection. We add Gaussian noise of zero mean and different choices of variance $\sigma^2$ to the extended Yale-B data set. In Section 7.5 of the supplementary, Figure 3a to Figure 3f illustrate SDP violation with respect to $\lambda$ for different noise levels with $\sigma^2$ ranging over $10, 20, 30, 40, 50, 60$. The SDP violation is defined in Wang and Xu [2013] which is the percentage of pairs of data points which are mistakenly put in the same subspace by the similarity matrix $\mathbf{W}$, namely the percentage of pairs $(\mathbf{x}_i, \mathbf{x}_j)$ with nonzero $\mathbf{W}_{ij}$ while they are in fact not in the same subspace. It can be observed that increasing $\lambda$ effectively reduces SDP violation for noisy $\ell^0$-SSC, Noisy-DR-$\ell^0$-SSC-LR and Noisy-DR-$\ell^0$-OSNAP, confirming our theoretical prediction.

## 6 CONCLUSION

In this paper, we prove that noisy $\ell^0$-SSC recovers subspaces from noisy data through $\ell^0$-induced sparsity. We then propose Noisy-DR-$\ell^0$-SSC to improve the efficiency of noisy $\ell^0$-SSC, which performs noisy $\ell^0$-SSC on dimensionality reduced data and still provably recovers the underlying subspaces with effectiveness verified by experiments.

# References

G. Aubrun and S.J. Szarek. *Alice and Bob Meet Banach: The Interface of Asymptotic Geometric Analysis and Quantum Information Theory*. Mathematical Surveys and Monographs. American Mathematical Society, 2017.

Yan Mei Chen, Xiao Shan Chen, and Wen Li. On perturbation bounds for orthogonal projections. *Numerical Algorithms*, 73(2):433–444, Oct 2016.

P. Drineas, A. Frieze, R. Kannan, S. Vempala, and V. Vinay. Clustering large graphs via the singular value decomposition. *Machine Learning*, 56(1):9–33, 2004.

Petros Drineas, Ravi Kannan, and Michael W. Mahoney. Fast monte carlo algorithms for matrices ii: Computing a low-rank approximation to a matrix. *SIAM Journal on Computing*, 36(1):158–183, 2006.

Petros Drineas, Michael W. Mahoney, and S. Muthukrishnan. Relative-error $cur$ matrix decompositions. *SIAM Journal on Matrix Analysis and Applications*, 30(2):844–881, 2008.

Petros Drineas, Michael W. Mahoney, S. Muthukrishnan, and Tamás Sarlós. Faster least squares approximation. *Numerische Mathematik*, 117(2):219–249, 2011.

Eva L. Dyer, Aswin C. Sankaranarayanan, and Richard G. Baraniuk. Greedy feature selection for subspace clustering. *Journal of Machine Learning Research*, 14:2487–2517, 2013.

Ehsan Elhamifar and René Vidal. Sparse manifold clustering and embedding. In *NIPS*, pages 55–63, 2011.

Ehsan Elhamifar and René Vidal. Sparse subspace clustering: Algorithm, theory, and applications. *IEEE Trans. Pattern Anal. Mach. Intell.*, 35(11):2765–2781, 2013.

Alan Frieze, Ravi Kannan, and Santosh Vempala. Fast monte-carlo algorithms for finding low-rank approximations. *J. ACM*, 51(6):1025–1041, November 2004.

N. Halko, P. G. Martinsson, and J. A. Tropp. Finding structure with randomness: Probabilistic algorithms for constructing approximate matrix decompositions. *SIAM Rev.*, 53(2):217–288, May 2011. ISSN 0036-1445.

B. Laurent and P. Massart. Adaptive estimation of a quadratic functional by model selection. *The Annals of Statistics*, 28(5):1302 – 1338, 2000.

Chun-Guang Li, Chong You, and René Vidal. On geometric analysis of affine sparse subspace clustering. *IEEE Journal of Selected Topics in Signal Processing*, 12(6):1520–1533, 2018.

Guangcan Liu, Zhouchen Lin, and Yong Yu. Robust subspace segmentation by low-rank representation. In *Proceedings of the 27th International Conference on Machine Learning (ICML-10), June 21-24, 2010, Haifa, Israel*, pages 663–670, 2010.

Guangcan Liu, Zhouchen Lin, Shuicheng Yan, Ju Sun, Yong Yu, and Yi Ma. Robust recovery of subspace structures by low-rank representation. *IEEE Trans. Pattern Anal. Mach. Intell.*, 35(1):171–184, January 2013a.

Guangcan Liu, Zhouchen Lin, Shuicheng Yan, Ju Sun, Yong Yu, and Yi Ma. Robust recovery of subspace structures by low-rank representation. *IEEE Transactions on Pattern Analysis and Machine Intelligence*, 35(1):171–184, 2013b.

Yichao Lu, Paramveer S. Dhillon, Dean Foster, and Lyle Ungar. Faster ridge regression via the subsampled randomized hadamard transform. In *Proceedings of the 26th International Conference on Neural Information Processing Systems*, NIPS'13, pages 369–377, USA, 2013. Curran Associates Inc.

Michael W. Mahoney and Petros Drineas. Cur matrix decompositions for improved data analysis. *Proceedings of the National Academy of Sciences*, 106(3):697–702, 2009.

Jelani Nelson and Huy L. Nguyen. OSNAP: faster numerical linear algebra algorithms via sparser subspace embeddings. In *54th Annual IEEE Symposium on Foundations of Computer Science, FOCS 2013, 26-29 October, 2013, Berkeley, CA, USA*, pages 117–126, 2013.

Andrew Y. Ng, Michael I. Jordan, and Yair Weiss. On spectral clustering: Analysis and an algorithm. In *NIPS*, pages 849–856, 2001.

Dohyung Park, Constantine Caramanis, and Sujay Sanghavi. Greedy subspace clustering. In *Advances in Neural Information Processing Systems 27: Annual Conference on Neural Information Processing Systems 2014, December 8-13 2014, Montreal, Quebec, Canada*, pages 2753–2761, 2014.

T. Sarlos. Improved approximation algorithms for large matrices via random projections. In *2006 47th Annual IEEE Symposium on Foundations of Computer Science (FOCS'06)*, pages 143–152, Oct 2006.

Mahdi Soltanolkotabi and Emmanuel J. Candés. A geometric analysis of subspace clustering with outliers. *Ann. Statist.*, 40(4):2195–2238, 08 2012.

G. W. Stewart. On the perturbation of pseudo-inverses, projections and linear least squares problems. *SIAM Review*, 19(4):634–662, 1977. ISSN 00361445.

Yining Wang, Yu-Xiang Wang, and Aarti Singh. A deterministic analysis of noisy sparse subspace clustering for dimensionality-reduced data. In *Proceedings of the 32Nd International Conference on International Conference on Machine Learning - Volume 37*, ICML'15, pages 1422–1431. JMLR.org, 2015.

Yu-Xiang Wang and Huan Xu. Noisy sparse subspace clustering. In *Proceedings of the 30th International Conference on Machine Learning, ICML 2013, Atlanta, GA, USA, 16-21 June 2013*, pages 89–97, 2013.

Yu-Xiang Wang, Huan Xu, and Chenlei Leng. Provable subspace clustering: When lrr meets ssc. In C.J.C. Burges, L. Bottou, M. Welling, Z. Ghahramani, and K.Q. Weinberger, editors, *Advances in Neural Information Processing Systems 26*, pages 64–72. Curran Associates, Inc., 2013.

H. Weyl. Das asymptotische verteilungsgesetz der eigenwerte linearer partieller differentialgleichungen (mit einer anwendung auf die theorie der hohlraumstrahlung). *Mathematische Annalen*, 71:441–479, 1912.

Y. Yang, J. Feng, N. Jojic, J. Yang, and T. S. Huang. On the Suboptimality of Proximal Gradient Descent for $\ell^0$ Sparse Approximation. *ArXiv e-prints*, 2017.

Yingzhen Yang. Dimensionality reduced $\ell^{0}$-sparse subspace clustering. In Amos J. Storkey and Fernando Pérez-Cruz, editors, *International Conference on Artificial Intelligence and Statistics, AISTATS 2018, 9-11 April 2018, Playa Blanca, Lanzarote, Canary Islands, Spain*, volume 84 of *Proceedings of Machine Learning Research*, pages 2065–2074. PMLR, 2018.

Yingzhen Yang and Jiahui Yu. Fast proximal gradient descent for A class of non-convex and non-smooth sparse learning problems. In *Proceedings of the Thirty-Fifth Conference on Uncertainty in Artificial Intelligence, UAI 2019, Tel Aviv, Israel, July 22-25, 2019*, page 508, 2019.

Yingzhen Yang, Jiashi Feng, Nebojsa Jojic, Jianchao Yang, and Thomas S. Huang. L0-sparse subspace clustering. In *Computer Vision - ECCV 2016 - 14th European Conference, Amsterdam, The Netherlands, October 11-14, 2016, Proceedings, Part II*, pages 731–747, 2016.

Yingzhen Yang, Jiashi Feng, Nebojsa Jojic, Jianchao Yang, and Thomas S. Huang. Subspace learning by $^0$-induced sparsity. *Int. J. Comput. Vis.*, 126(10):1138–1156, 2018.

Pavel Yaskov. Sharp lower bounds on the least singular value of a random matrix without the fourth moment condition. *Electron. Commun. Probab.*, 20:9 pp., 2015. doi: 10.1214/ECP.v20-4089.

Yu-Xiang Wang Yining Wang and Aarti Singh. Parameter estimation of generalized linear models without assuming their link function. In *Proceedings of the Eighteenth International Conference on Artificial Intelligence and Statistics, AISTATS 2016, Cadiz, Spain, May 9-11, 2016*, 2016.

Chong You, Daniel P. Robinson, and René Vidal. Scalable sparse subspace clustering by orthogonal matching pursuit. In *2016 IEEE Conference on Computer Vision and Pattern Recognition, CVPR 2016, Las Vegas, NV, USA, June 27-30, 2016*, pages 3918–3927, 2016.

Chong You, Chun-Guang Li, Daniel P. Robinson, and René Vidal. Is an affine constraint needed for affine subspace clustering? In *2019 IEEE/CVF International Conference on Computer Vision, ICCV 2019, Seoul, Korea (South), October 27 - November 2, 2019*, pages 9914–9923. IEEE, 2019.

Xin Zheng, Deng Cai, Xiaofei He, Wei-Ying Ma, and Xueyin Lin. Locality preserving clustering for image database. In *Proceedings of the 12th Annual ACM International Conference on Multimedia*, MULTIMEDIA '04, pages 885–891, New York, NY, USA, 2004. ACM.