NERDS: A General Framework to Train Camera Denoisers from Raw-RGB Noisy Image Paris

Abstract

We aim to train accurate denoising networks for smartphone/digital cameras from raw-RGB noisy image pairs. Downscaling is commonly used as a practical denoiser for low-resolution images. Based on this processing, we found that the pixel variance of natural images is more robust to downscaling than the pixel variance of camera noise. Intuitively, downscaling removes high-frequency noise more easily than natural textures. To utilize this property, we can adopt noisy/clean image synthesis at low-resolution to train camera denoisers. On this basis, we propose a new solution pipeline – NERDS that estimates camera noise and synthesizes noisy-clean image pairs from only noisy images. In particular, it first models the noise in raw-sensor images as Poisson-Gaussian distributions, then estimates noise parameters using the difference of pixel variances by downscaling. We formulate the noise estimation as a gradient-descent-based optimization problem through a reparametrization trick. We further introduce a new Image Signal Processor (ISP) estimation method that enables denoiser training in a human-readable RGB space by transforming the downscaled raw images to the style of a given RGB noisy image. The noise and ISP estimations utilize rich augmentation to synthesize image pairs for denoiser training. Experiments show that NERDS can accurately train CNN-based denoisers (*e.g.*, DnCNN, ResNet-style network) outperforming previous noise-synthesis-based and self-supervision-based denoisers in real datasets.

1 Introduction

Image denoising is a conventional machine learning problem restoring original colors and patterns from noisy images. Deep-learning-based approaches have achieved breakthroughs in recent decades due to the power of neural networks. Early works (Zhang et al., 2017; Mao et al., 2016; Tai et al., 2017) have successfully removed additive white Gaussian noise (AWGN), which allows network training under supervision by synthesizing noisy-clean image pairs.

Nevertheless, denoising images captured by smartphone/digital cameras poses an obstacle, as it is difficult to obtain clean images for noisy images with pixel-level alignment. Several works (Abdelhamed et al., 2018; Brummer & De Vleeschouwer, 2019) constructed datasets with the noisy-clean pairs for real-world images. Using these pairs (Figure 1(a)), many supervised-learning-based denoisers (Yue et al., 2019; Kim et al., 2020; Yue et al., 2020; Hu et al., 2021; Cheng et al., 2021) restore crisp images on benchmarks from the datasets. However, constructing such datasets requires tightly controlled capturing environments, complicated post-processing, and massive human labor.

To overcome the drawback of plain supervised learning, two major types of research have been studied. The first line of works generates realistic noisy images from clean images to utilize supervised denoiser training as visualized in Figure 1(b). Several approaches (Chen et al., 2018; Cha et al., 2021; Hong et al., 2020; Jang et al., 2021) adopt generative models using *unpaired* noisy-clean images based on GAN (Goodfellow et al., 2014), but they achieve limited accuracy on real noise. Some other works synthesize realistic noise using existing noisy-clean image pairs (Zamir et al., 2020; Abdelhamed et al., 2019) or metadata for real cameras (Brooks et al., 2019; Guo et al., 2019), but they are limited in generalization for unseen noise. The second category aims to learn denoisers *without clean images*. The first work (Lehtinen et al., 2018) in this category proposed the learning framework using multiple noisy images. After that, many self-supervised-learning approaches (Batson & Royer, 2019; Krull et al., 2019; Byun et al., 2021) use single noisy images (Figure 1(c)), which

Figure 1: Different training schemes for CNN-based camera denoisers. (a) Traditionally, training denoisers requires pairs of noisy and clean images. However, clean target images are difficult to obtain from smartphone/digital cameras. (b) Noise Flow (Abdelhamed et al., 2019) generates realistic noise from clean images by learning real noise distributions using existing pairs of real images. (c) N2V (Krull et al., 2019) enables practical training from noisy images without clean targets but requires custom network architectures. (d) Our NERDS generates pseudo-noisy and pseudo-clean image pairs at low-resolution by utilizing image downscaling as a general denoiser and noise estimation through gradient-descent-based optimization.

enable easy data collection and denoiser adaptation to the test noise. However, they are still limited in real-world applications due to the requirements of custom network architectures and strong statistical noise assumptions.

To address the above limitations on camera denoiser training, we propose a new solution pipeline, namely Noise Estimation for RGB Denoising & Synthesis (NERDS), that generates noisy-clean image pairs from raw-RGB noisy image pairs. The pipeline composes three parts–noise estimation, ISP estimation, and denoiser training. We found that the pixel variance of natural clean images is robust to image downscaling, which is a widely-used denoiser for low-resolution images (Nah et al., 2019). The noise estimation adopts a Poisson-Gaussian noise model for raw images from sensors and optimizes its noise parameters by the pixel variances of downscaled images. The downscaled images and the estimated noise parameters enable generating pseudo-noisy and pseudo-clean image pairs at low-resolution (Figure 1(d)). Training denoisers on human-readable RGB images from real cameras has another issue: the conversion from the raw images to the RGB images is a black box. Our ISP estimation enables noise synthesis on the RGB space by learning RAW2RGB conversion using raw-RGB noisy image pairs[1]. Our denoiser training can utilize rich data augmentation based on estimated noise parameters and ISPs. Specifically, we introduce two techniques for this framework. First, a reparametrization trick allows estimating noise parameters through a gradient-descent-based optimizer. Second, a technique for style disentanglement from raw-RGB noisy image pairs. We summarize our contributions as follows:

- To the best of our knowledge, this is the first work to synthesize noisy-clean RGB image pairs at low-resolution for accurate camera denoiser training from raw-RGB noisy image pairs.

- We formulate noise estimation for Poisson-Gaussian noise as an optimization problem, and a novel reparameterization trick allows to estimate accurate noise parameters through gradient-descent.

- We propose a neural network that estimates the RAW2RGB conversions (or ISPs) used for given raw-RGB noisy image pairs. The ISP estimation generates realistic noisy-clean RGB image pairs from raw images.

- Our frameworks can train general CNN-based denoisers (*e.g.* DnCNN, ResNet-style network) accurately for given test noisy images by performing noise synthesis using them.

---

[1]Major camera manufacturers (*e.g.*, Samsung, Apple, Xiaomi, Cannon, and Sony) provide raw and RGB image pairs on their devices.

2 RELATED WORK

2.1 BLIND IMAGE DENOISING

Traditional methods Classical methods usually denoise noisy images without training data using wavelet (Donoho & Johnstone, 1995), filtering (Buades et al., 2005) including BM3D (Dabov et al., 2007), optimization (Elad & Aharon, 2006; Mairal et al., 2009; Gu et al., 2014), and effective prior (Zoran & Weiss, 2011). However, they perform limited accuracy compared to the recent deep-learning-based approaches.

Supervised-learning-based methods SIDD (Abdelhamed et al., 2018) and NIND (Brummer & De Vleeschouwer, 2019) captured real noisy-clean image pairs to enable supervised-learning for real camera denoisers. However, the capturing procedure is unacceptably expensive and cumbersome. We describe the literature on realistic noise synthesis methods for the supervised-learning. DnCNN (Zhang et al., 2017) introduced a neural network to remove additive white Gaussian noise (AWGN) for the first time. However, Guo *et al.* (Guo et al., 2019) demonstrated the limitation of AWGN denoisers to signal-dependent or spatially-correlated noise, which are known as the characteristics of real-world images. To alleviate this problem, two lines of works have been researched. The first category uses generative models for noise synthesis with stable learning (Chen et al., 2018), various noise characteristics (Jang et al., 2021), knowledge distillation (Wu et al., 2020), self-supervised-learning (Cha et al., 2021), and conditional adversarial networks (Hong et al., 2020). Nevertheless, the scene statistics mismatched between clean and noisy datasets make it difficult to train accurate denoisers in practice.

The second category investigates camera noise modeling. CBDNet (Guo et al., 2019) transforms AWGN into realistic noise by using signal-dependent noise parameters and simulating in-camera ISP functions, such as gamma correction and demosaicing. UPI (Brooks et al., 2019) converts RGB images to raw images and simulates noise using metadata of specific cameras. CycleISP (Zamir et al., 2020) trains neural networks for both RAW2RGB and RGB2RAW conversions on large-scale datasets with specific ISP and noise settings. Noise Flow (Abdelhamed et al., 2019) synthesizes raw noisy images using normalizing flow and metadata. The work on (Chang et al., 2020) proposed a GAN-based framework for noise generation in raw images which is adaptive to the camera. In (Zhang et al., 2021), the authors claimed that the noise levels in metadata are inaccurate. Recently, the method in (Kousha et al., 2022) models the RGB noise distribution using normalizing flow. SCUNet (Zhang et al., 2022) proposed a practical noise model for a general-purpose denoiser.

However, all the above methods require real noisy-clean image pairs, ISPs, metadata, or high-quality clean images which are not always available. More importantly, the noise synthesis using predetermined training datasets leads to poor denoising performances on unseen noise. In contrast, the proposed method (NERDS) synthesizes realistic noisy-clean image pairs from only noisy images, which enables accurate denoiser training specialized in the test images.

Self-supervised-learning-based methods Noise2Noise (Lehtinen et al., 2018) introduced a framework that trains denoisers using noisy images *only* for the first time. Noise2Void (Krull et al., 2019), Noise2Self (Batson & Royer, 2019), Noise2Same (Xie et al., 2020), and Neighbor2Neighbor (Huang et al., 2021) adopted advanced approaches which can train denoisers with single images corrupted by the i.i.d noise. Noisier2Noise (Moran et al., 2020), NAC (Xu et al., 2020), and R2R (Pang et al., 2021) add additive noise to the given noisy images to make auxiliary training pairs by using prior knowledge (or assumptions) of the noise distribution. Notably, the blind-spot network (BSN) in (Krull et al., 2019) has been improved by efficient architectures with small receptive fields (Laine et al., 2019) and dilated convolutions (Wu et al., 2020). Using the advanced BSNs, FBI-D (Byun et al., 2021) adopts a denoiser specialized in Poisson-Gaussian noise for real-world raw image denoising. AP-BSN (Wooseok Lee, 2022) breaks the spatially-correlated noise of real-world RGB images by pixel-shuffle downsampling.

Although the above self-supervised-learning methods use practical training datasets (only noisy images), they require custom network architectures or strong noise assumptions. In contrast, NERDS performs noise synthesis that allows training general CNN-based denoisers based on the general noise modeling for smartphone/digital cameras.

2.2 Noise Estimation

Prior knowledge of noise distribution supports accurate restoration in most methods for image denoising, but it is not generally available in practice. Noise estimation methods alleviate this problem, especially for the additive white Gaussian noise (AWGN) and the Poisson-Gaussian noise. Principal component analysis (PCA) based approaches (Liu et al., 2013; Pyatykh et al., 2012; Chen et al., 2015) perform accurate AWGN estimation. For the Poisson-Gaussian noise model, most existing methods (Abramov et al., 2010; Uss et al., 2013) including (Foi et al., 2008; Liu et al., 2014) adopt two-step approaches; estimating the local means and variances, then adopting maximum likelihood estimation (MLE) to fit the noise model. Foi *et al.*(Foi et al., 2008) proposed the Poisson-Gaussian noise model for the first time and a noise estimation algorithm based on wavelet decomposition. Liu *et al.* (Liu et al., 2014) adopted iterative patch selection for the generalized source-dependent noise. Recently, PGE-Net (Byun et al., 2021) adopted neural networks for accurate and fast optimization based on Generalized Anscombe Transformation (GAT) (Anscombe, 1948). In contrast, we proposed a noise estimation method for Poisson-Gaussian noise using natural scene statistics with gradient-descent-based optimization.

3 Preliminary: Noise Modeling

In a digital camera, an image sensor converts light into a digital signal (or a raw image), and an image signal processor (ISP) converts it into a human-readable RGB image. We regard that the noise of RGB images originates from the image sensor and is transformed by the ISP. Thus, we model noise distribution of raw images and RAW2RGB conversion including ISPs.

Raw Image: Poisson-Gaussian (P-G) Noise   A common noise model for raw images follows the Poisson-Gaussian distribution (Foi et al., 2008), defined as:

$$\boldsymbol{x} \sim \mathcal{N}(\boldsymbol{z}, \beta_1^2 \boldsymbol{z} + \beta_2^2), \tag{1}$$

which is a heteroscedastic Gaussian where $\boldsymbol{z}$ is the true signal, $\boldsymbol{x}$ is a raw noisy image observed on real image sensors, and β_1, $\beta_2 \geq 0$ are signal-dependent and signal-independent noise parameters. Real cameras provide $\boldsymbol{x}$ as well as β_1 and β_2 in metadata. However, the noise parameters in metadata are often inaccurate (Zhang et al., 2021). Section A.1.1 discusses the noise distribution of raw images and the noise parameters in metadata further.

RGB Image: Transformed Noise   ISPs transform raw images into RGB images using nonlinear functions, such as demosaicing, white balancing, color correction, and tone mapping. The transformation changes noise distribution (e.g., breaking the i.i.d property in equation 1). Moreover, users can retouch image tones and colors, altering the noise distribution further. We define such RAW2RGB conversion ($\boldsymbol{T}$) as a function of the image style ($\boldsymbol{s}$),

$$\boldsymbol{y} \equiv T(\boldsymbol{x}; \boldsymbol{s}), \tag{2}$$

where $\boldsymbol{x}$ is a raw noisy image obtained from real image sensors and $\boldsymbol{y}$ is a RGB noisy image with custom tones and colors. The real noise datasets (Abdelhamed et al., 2018; Plotz & Roth, 2017) used a simple and open-source ISP for the entire dataset without any image retouching processes. However, modern smartphones and digital cameras use custom ISPs with hidden internal functions. They provide multiple image styles depending on scenes.

The following section provides a general framework to estimate P-G noise parameters (β_1, β_2) and RAW2RGB conversion ($\boldsymbol{T}$) with image style ($\boldsymbol{s}$) using only noisy images ($\boldsymbol{x}, \boldsymbol{y}$).

4 Proposed Method

4.1 Overview

For a given noisy pair of raw ($\boldsymbol{x}$) and RGB ($\boldsymbol{y}$) images, the proposed method composes three steps to restore the RGB clean image without auxiliary training data. First, we estimate noise parameters (β_1, β_2) from $\boldsymbol{x}$ (Section 4.3). Second, we learn the conversion from $\boldsymbol{x}$ to $\boldsymbol{y}$ while disentangling image style ($\boldsymbol{s}$) (Section 4.4). Third, we synthesize diverse pairs of noisy-clean images to train arbitrary RGB denoisers with a general supervised-learning framework (Section 4.5).

Figure 2: Noise estimation from a raw noisy image with a reparametrization trick.

4.2 OBSERVATION

Figure 3: The ranked curve for the difference of pixel variances through downscaling on images from SIDD validation and the visualization of noise levels.

We first illustrate our observation on raw noisy images with downscaling. Specifically, we investigate the statistical characteristics variances of 256×256 images in the validation set of SIDD (Abdelhamed et al., 2018). To evaluate their noise levels, we downscale all raw images for each color channel with the scaling factor of 2, and rank these images according to the differences of pixel variances before and after downscaling. As visualized in Figure 3, we show these values in a blue curve and separate them into three levels –low, medium, high. It is observed that the images with high differences are very noisy, while the images with low differences present clean textures. This phenomenon indicates that the true signal z is more robust to the pixel variances through downscaling than real noise. That is why we propose the following method, which uses the difference of pixel variances to estimate noise levels without clean images.

4.3 POISSON-GAUSSIAN NOISE ESTIMATION VIA A REPARAMETERIZATION TRICK

We aim to estimate noise for $\boldsymbol{x}$ without any information other than $\boldsymbol{x}$. For this, we find an additive noise ($\boldsymbol{N}$) for the downscaled image ($\boldsymbol{x}^d$) by solving the following optimization problem,

$$\min_{\boldsymbol{N}} |Var(\boldsymbol{x}) - Var(\boldsymbol{x}^d + \boldsymbol{N})|, \tag{3}$$

where $\boldsymbol{N} \sim \mathcal{N}(0, \beta_1^2\boldsymbol{x}^d + \beta_2^2)$ is the Poisson-Gaussian noise discussed in equation 1 and $Var(\cdot)$ denotes a function that outputs the pixel variance of the input image. We can approximate β_1 and β_2 as noise parameters for $\boldsymbol{x}$, given that the difference of pixel variances through downscaling is correlated with noise levels, as discussed in Section 4.2. Section A.1.2 analyzes the downscaling effect further. However, equation 3 is difficult to optimize due to the non-differentiable process of noise sampling. To alleviate this problem, we introduce a reparameterization trick that separates noise sampling into learnable parameters and sampling from a normal distribution. Formally, we reformulate equation 3 as

$$\min_{\boldsymbol{\beta}} |Var(\boldsymbol{x}) - Var(\boldsymbol{x}^d + PG(\boldsymbol{\beta}, \boldsymbol{x}^d) \times \boldsymbol{n})|, \tag{4}$$

where $PG(\boldsymbol{\beta}, \boldsymbol{x}^d) = (\beta_1^2\boldsymbol{x}^d + \beta_2^2)^{0.5}$ denotes a Poisson-Gaussian converter and $\boldsymbol{n} \sim \mathcal{N}(0, 1)$ is additive noise with a normal distribution. Given that the only learnable parameters in equation 4 are β_1 and β_2, a gradient-descent optimizer (*e.g.*, ADAM (Kingma & Ba, 2015)) easily finds the noise parameters. Figure 2 visualizes the optimization problem used as noise estimation for $\boldsymbol{x}$.

We are surprised that such a simple optimization problem estimates accurate noise parameters, while downscaled images can contain remaining noise or over-smoothing textures. This result is because

Figure 4: ISP estimation from a pair of raw-RGB noisy images with style disentanglement.

the well-designed optimizer learns the characteristics of signal-dependent and signal-independent noise over the entire image content.

So far we have discussed noise estimation and synthesis on raw images. For more practical applications, the following section describes RGB noise synthesis by estimating RAW2RGB conversion.

4.4 ISP ESTIMATION WITH STYLE DISENTANGLEMENT

We aim to learn a RAW2RGB conversion (or an ISP) from x to y. However, a naïve network training from x to y can easily overfit to the image contents. Moreover, to generate multiple styles of RGB images, training a neural network for each style is resource intensive. For this, we disentangle the styles from RGB images, allowing a network to learn multiple-style generation.

Specifically, our ISP estimation composes two networks, the style encoder (E) and the RAW2RGB converter (T) (Figure 4). E identifies the image style as a style parameter (s) from the raw noisy image (x) and the RGB noisy image (y) while T uses x and s as input to generate an RGB image ($\hat{y}$). Then, we can recall the equation equation 2 as

$$\hat{y} = T(x; E(x, y)),\tag{5}$$

where $s = E(x, y)$ while training E and T to minimize L1 differences between $\hat{y}$ and y. E composes 6 residual blocks, global pooling, and a fully connected layer and T composes 4 residual blocks and parameterized ISP functions (Kim & Lee, 2022). We use the residual blocks of two convolutional layers and one ReLU activation with 64 filters and 3×3 kernels. The training data can compose a single pair or multiple pairs of raw-RGB noisy images. For accurate RAW2RGB conversion for downscaled images, which are unseen in training, we first adopt image scale augmentation (SA) that changes image resolution. SA generates multiple training patches for a style (or a patch) by randomly sampled scaling factors to prevent overfitting to a few training data. Formally, we redefine the style parameter (s) as follows,

$$s \equiv E(SA(x, y)).\tag{6}$$

Second, we design a bottleneck structure that lowers the dimension of s to avoid encoding of information about image contents. E reduces channels and resolutions of s ($s \in \mathbb{R}^{3 \times 1 \times 1}$ in this paper). s conditions T by channel attention and ISP parameter generation via fully connected layers.

4.5 DENOISER TRAINING WITH DATA AUGMENTATION

We synthesize noisy-clean RGB image pairs at low-resolution to train general RGB denoisers. The pseudo-noisy/pseudo-clean images are the downscaled raw image (x^d) with/without additive noise N transformed to RGB space using T. Formally, the denoiser (D) training minimizes the following objective function,

$$\min_D |T(x^d; s) - D(T(x^d + N; s))|,\tag{7}$$

where s is the style parameter in equation 6. Our denoising framework allows rich augmentation for data synthesis. First, scaling and intensity augmentation (SIA) increases content diversity by changing the image resolution and pixel values from 0.5× to 1.5×. Second, we randomly scale noise parameters, β_1 and β_2, from 0.5× to 1.5×. This augmentation alleviates the noise estimation error

in Section 4.3. Lastly, when multiple noisy images are given, we can augment the noise parameters and the style parameters across different images. Overall, the objective function of our denoiser training equation 7 becomes

$$\min_D |T(SIA(\boldsymbol{x}^d); \boldsymbol{s}') - D(T(SIA(\boldsymbol{x}^d) + \boldsymbol{N}'; \boldsymbol{s}'))|, \tag{8}$$

where SIA is the scale and intensity augmentation, $\boldsymbol{s}'$ is the augmented style parameter, and $\boldsymbol{N}'$ is the additive noise with augmented noise parameters. At testing, the denoiser takes the RGB noisy image ($\boldsymbol{y}$) as input, just like conventional CNN-based approaches.

5 EXPERIMENTS

5.1 IMPLEMENTATION DETAILS

Downscaling We downscale a raw image $\boldsymbol{x}$ to $\boldsymbol{x}^d$ by bicubic interpolation after asymmetric 2D Gaussian blurring with the kernel size of 21×21. We randomly select the standard deviation of the Gaussian blur from $0.25 \times ds$ to $0.75 \times ds$ for each dimension, where ds denotes downscaling factor randomly selected in the range of $[1.5, 2.5]$. We use the same hyper-parameters for noise estimation, ISP estimation, and denoiser training unless otherwise specified.

Optimization We use ADAM (Kingma & Ba, 2015), 128×128 image patches, and a batch size of 64 for all experiments. Noise estimation adopts 2.5×10^4 iterations with the initial learning rate of 1×10^{-4} which becomes a tenth part in every 5×10^3 iterations. We use the same initial learning rates for ISP estimation and denoiser training for 5×10^5 iterations without the learning rate decay.

Denoiser We use two simple networks as denoiser to present the generalizability of the proposed training scheme. Specifically, NERDS+DnCNN uses DnCNN (Zhang et al., 2017) and NERDS+D uses a ResNet-style architecture, composing a global skip connection and 32 residual blocks. Each block has two convolutional layers and one ReLU activation with 64 filters and 3×3 kernels.

Dataset We use BSD68 (Martin et al., 2001) which consists of 68 gray-scale images to evaluate the performance of noise estimation. For real image denoising, we use raw noisy and RGB noisy images on SIDD (Abdelhamed et al., 2018), DND (Plotz & Roth, 2017), and MIT-Adobe FiveK (Bychkovsky et al., 2011). SIDD (Abdelhamed et al., 2018) consists of training, validation, and benchmark datasets. We use 1,280 256×256 patches from 40 noisy images on the benchmark for denoiser training. In the setting of extra images, we use 50 noisy images on the training dataset with low ISO levels of 100 and downscale the noisy images with the scaling factor from 1.1 to 1.2. For DND (Plotz & Roth, 2017), we use 1,000 512×512 patches from 50 noisy images on the benchmark. We evaluate the denoising performances on the benchmarks by submitting the results to the public websites for SIDD and DND. MIT-Adobe FiveK (Bychkovsky et al., 2011) consists of 5,000 raw images and paired RGB images retouched by 5 photographers. Each RGB image has its own RAW2RGB conversion using Adobe Lightroom while the raw image contains real camera noise. We demonstrate an extreme scenario where only 5 noisy images are available for denoiser training.

5.2 RESULTS FOR NOISE ESTIMATION AND SYNTHESIS

We first validate our noise estimation on additive Poisson-Gaussian noise to images on BSD68 (Martin et al., 2001), and then visualize the noise synthesis at low-resolution from noisy images on MIT-Adobe FiveK (Bychkovsky et al., 2011).

Poisson-Gaussian noise estimation We demonstrate the effectiveness of our NERDS-raw on P-G noise estimation by comparing with Foi *et al.* (Foi et al., 2008), Liu *et al.* (Liu et al., 2014), and PGE-Net (Byun et al., 2021) which estimate P-G noise parameters from noisy images. Table 1 presents the average of the noise parameters estimated from each image on BSD68 with four different noise levels. In most cases, NERDS-raw estimates the most accurate noise parameters.

Noisy-clean RGB image synthesis Figure 5 shows noise synthesis results using NERDS. Each real image from MIT-Adobe FiveK has its own RAW2RGB conversion. NERDS-noisy contains

Table 1: The average values of $(\hat{\beta}_1, \hat{\beta}_2)$ estimated from BSD68 with additive Poisson-Gaussian noise level of (β_1, β_2). Bold denotes the best result.

Noise level (β_1, β_2)	Foi *et al.* (Foi et al., 2008) $(\hat{\beta}_1, \hat{\beta}_2)$	Liu *et al.* (Liu et al., 2014) $(\hat{\beta}_1, \hat{\beta}_2)$	PGE-Net (Byun et al., 2021) $(\hat{\beta}_1, \hat{\beta}_2)$	NERDS-raw (Ours) $(\hat{\beta}_1, \hat{\beta}_2)$
(0.100, 0.0200)	(0.096, 0.042)	(0.072, 0.045)	(0.098, 0.0030)	(**0.100**, **0.0229**)
(0.100, 0.0002)	(0.097, 0.035)	(0.071, 0.044)	(0.095, **0.0001**)	(**0.101**, **0.0001**)
(0.050, 0.0200)	(0.049, 0.031)	(0.040, 0.040)	(0.052, 0.0001)	(**0.051**, **0.0245**)
(0.050, 0.0002)	(**0.051**, 0.018)	(0.039, 0.034)	(**0.051**, 0.0001)	(0.052, **0.0002**)

Real Image   NERDS-noisy   NERDS-clean   Real Image   NERDS-noisy   NERDS-clean

Figure 5: Noise synthesis results using NERDS. NERDS can synthesize noisy-clean RGB image pairs at low-resolution from single noisy images. NERDS-noisy and NERDS-clean denote synthetic RGB images with and without noise. This example uses the downscaling factor of 2. (*Zooming-in for the best view.*)

realistic noise specialized to each real image, such as blue/dark noise in dark areas with none i.i.d characteristics. Figure 9 visualizes more pseudo-noisy and pseudo-clean image pairs on SIDD/DND datasets. To the best of our knowledge, NERDS is the first work to generate the realistic noisy images and the paired clean images for the unknown RAW2RGB conversions (or ISPs) by using only raw-RGB noisy image pairs. Existing works for noise synthesis (Brooks et al., 2019; Zhang et al., 2022; Zamir et al., 2020; Abdelhamed et al., 2019; Kousha et al., 2022) require real noisy-clean image pairs, metadata, and ISPs. Thus, naïve comparisons between NERDS and the existing methods are unfair, but we present them in Section A.2.1.

5.3 COMPARISONS TO THE SotA DENOISING METHODS

Results on benchmarks Given that NERDS trains denoisers without clean images, we compare our denoisers with the SotA denoising methods that *do not use the pairs of real noisy-clean images*. Specifically, we compare GAT+BM3D (Dabov et al., 2007), N2V (Krull et al., 2019), AP-BSN (Wooseok Lee, 2022), FBI-D (Byun et al., 2021), C2N+DIDN (Jang et al., 2021), and SCUNet (Zhang et al., 2022) on SIDD and DND benchmarks. Table 2 presents the effectiveness of the proposed denoisers, NERDS+DnCNN and NERDS+D. C2N+DIDN (Jang et al., 2021) synthesizes realistic noise using *unpaired* noisy-clean images, while our NERDS+DnCNN outperforms it with the simpler denoiser (DIDN *vs.* DnCNN). SCUNet (Zhang et al., 2022) synthesizes realistic noise using high-quality clean images and the predetermined noise models including specific noise levels and ISP pipelines. The other works require only noisy images via prior-based filtering (Dabov et al., 2007), self-supervised learning (Krull et al., 2019; Wooseok Lee, 2022; Wu et al., 2020), and noise estimation (Byun et al., 2021). The works without clean images perform denoising in raw image space and received the results in RGB image space by submitting the denoised raw images to the public websites (Abdelhamed et al., 2018; Plotz & Roth, 2017). They often fail to remove noise in RGB image space, given that they assume strong noise characteristics such as Poisson-Gaussian distributions and the i.i.d property that do not hold in the RGB image space. Section A.1.3 presents a generalization test for NERDS+D with latency analysis to denoise a test image from scratch. Section A.2.2 provides the comparisons with the noise synthesis methods which use the pairs of real noisy-clean images. Figure 10, 11, and 12 visualize more denoising results on SIDD validation, DND, and MIT-Adobe FiveK.

Ablation Study Our NERDS enables rich and effective augmentation for denoiser training. Table 3 demonstrates the ablation study on the data augmentation. The setting without image scale

Table 2: PSNR (dB)/SSIM on RGB SIDD and DND benchmarks. Bold denotes the best result. ✓denotes accessible types of images at training. Extra images denote that images other than the noisy images of the benchmark are used for training.

Dataset	GAT+BM3D	N2V	AP-BSN	FBI-D	C2N+DIDN	SCUNet	NERDS+DnCNN	NERDS+D	
Clean images	-	-	-	-	✓	✓	-	-	-
Extra images	-	-	-	✓	✓	✓	-	-	✓
Synthetic pairs	-	-	-	-	✓	✓	✓	✓	✓
SIDD	34.61/0.879	32.85/0.847	36.91/0.931	38.07/0.942	35.35/0.937	22.89/0.797	36.42/0.923	37.40/0.941	**38.28/0.949**
DND	37.98/0.920	35.82/0.902	38.09/0.937	38.98/0.945	37.28/0.924	-	38.21/0.941	**39.34/0.950**	-

Table 3: Ablation study on data augmentation for NERDS+D. PSNR (dB)/SSIM on RGB SIDD validation.

Augmentation	(1)	(2)	(3)	(4)	(5)	(6)
Image scale	-	✓	✓	✓	✓	✓
Image intensity	-	-	✓	✓	✓	✓
Noise parameter	-	-	-	✓	✓	✓
Style parameter	-	-	-	-	✓	✓
Extra images	-	-	-	-	-	✓
SIDD	35.63/0.897	36.79/0.928	37.16/0.935	37.84/0.944	38.02/0.946	**38.51/0.950**

Real Image   CycleISP   NERDS+D (Ours)   Real Image   SCUNet   NERDS+D (Ours)

Figure 6: Qualitative comparisons of denoising results on MIT-Adobe FiveK (Bychkovsky et al., 2011). Pink arrows indicate the remaining noise of CycleISP and the over-smooth textures of SCUNet while our denoiser generates crisp images. (*Zooming-in for the best view.*)

augmentation (Table 3(1)) uses a fixed downscaling factor of 2. Each component improves the restoration performances. In particular, noise parameter augmentation improves over than 0.6 dB, given that it can alleviate noise estimation error. The usage of extra images enables high-quality clean image synthesis by downscaling images with low noise levels and small scaling factors.

Results on MIT-Above FiveK We evaluate CycleISP (Zamir et al., 2020), SCUNet (Zhang et al., 2022), and NERDS+D on retouched images from MIT-Adobe FiveK (Bychkovsky et al., 2011). CycleISP (Zamir et al., 2020) employs supervised learning on SIDD training dataset with additional synthetic data using the predetermined noise levels and ISP pipeline. Nevertheless, CycleISP fails to denoise the retouched image as visualized in Figure 6. SCUNet (Zhang et al., 2022) is trained on high-quality images with practically designed additive noise, but SCUNet often generates over-smooth textures. These results are due to different noise distributions between the training images and the test images. In contrast, NERDS+D removes severe real noise while maintaining image details. We report more qualitative results in Figure 12.

6 CONCLUSION

We present a general framework to train denoisers from noisy images, called NERDS. The framework composes noise estimation, ISP estimation, and denoiser training. For noise synthesis, we estimate Poisson-Gaussian noise in raw images and ISP (or RAW2RGB conversion) for each RGB image. NERDS allows rich data augmentation for accurate denoiser training. Experimental results show the state-of-the-art restoration accuracy on real noise benchmarks.

REFERENCES

Abdelrahman Abdelhamed, Stephen Lin, and Michael S Brown. A high-quality denoising dataset for smartphone cameras. In *CVPR*, 2018.

Abdelrahman Abdelhamed, Marcus A Brubaker, and Michael S Brown. Noise Flow: Noise Modeling with Conditional Normalizing Flows. In *ICCV*, 2019.

Sergey Abramov, Victoriya Zabrodina, Vladimir Lukin, Benoit Vozel, Kacem Chehdi, and Jaakko Astola. Improved method for blind estimation of the variance of mixed noise using weighted lms line fitting algorithm. In *ISCAS*, 2010.

F. J. Anscombe. The Transformation of Poisson, Binomial, and Negative-Binomial Data. *Biometrika*, 1948.

Joshua Batson and Loic Royer. Noise2Self: Blind denoising by self-supervision. In *ICML*, 2019.

Tim Brooks, Ben Mildenhall, Tianfan Xue, Jiawen Chen, Dillon Sharlet, and Jonathan T Barron. Unprocessing images for learned raw denoising. In *CVPR*, 2019.

Benoit Brummer and Christophe De Vleeschouwer. Natural image noise dataset. In *CVPR Workshops*, 2019.

Antoni Buades, Bartomeu Coll, and Jean-Michel Morel. A review of image denoising algorithms, with a new one. *MMS*, 2005.

Vladimir Bychkovsky, Sylvain Paris, Eric Chan, and Frédo Durand. Learning photographic global tonal adjustment with a database of input / output image pairs. In *CVPR*, 2011.

Jaeseok Byun, Sungmin Cha, and Taesup Moon. Fbi-denoiser: Fast blind image denoiser for poisson-gaussian noise. In *CVPR*, 2021.

Sungmin Cha, Taeeon Park, and Taesup Moon. GAN2GAN: Generative noise learning for blind image denoising with single noisy images. In *ICLR*, 2021.

Ke-Chi Chang, Ren Wang, Hung-Jin Lin, Yu-Lun Liu, Chia-Ping Chen, Yu-Lin Chang, and Hwann-Tzong Chen. Learning camera-aware noise models. In *ECCV*, 2020.

Guangyong Chen, Fengyuan Zhu, and Pheng Ann Heng. An efficient statistical method for image noise level estimation. In *ICCV*, 2015.

Jingwen Chen, Jiawei Chen, Hongyang Chao, and Ming Yang. Image blind denoising with generative adversarial network based noise modeling. In *CVPR*, 2018.

Shen Cheng, Yuzhi Wang, Haibin Huang, Donghao Liu, Haoqiang Fan, and Shuaicheng Liu. NBNet: Noise basis learning for image denoising with subspace projection. In *CVPR*, 2021.

Kostadin Dabov, Alessandro Foi, Vladimir Katkovnik, and Karen Egiazarian. Image denoising by sparse 3-D transform-domain collaborative filtering. *IEEE TIP*, 16(8):2080–2095, 2007.

David L Donoho and Iain M Johnstone. Adapting to unknown smoothness via wavelet shrinkage. *JASA*, 1995.

Michael Elad and Michal Aharon. Image denoising via sparse and redundant representations over learned dictionaries. *TIP*, 2006.

Alessandro Foi, Mejdi Trimeche, Vladimir Katkovnik, and Karen Egiazarian. Practical Poissonian-Gaussian noise modeling and fitting for single-image raw-data. *TIP*, 17(10):1737–1754, 2008.

Ian Goodfellow, Jean Pouget-Abadie, Mehdi Mirza, Bing Xu, David Warde-Farley, Sherjil Ozair, Aaron Courville, and Yoshua Bengio. Generative adversarial nets. In *NIPS*, 2014.

Shuhang Gu, Lei Zhang, Wangmeng Zuo, and Xiangchu Feng. Weighted nuclear norm minimization with application to image denoising. In *CVPR*, 2014.

Shi Guo, Zifei Yan, Kai Zhang, Wangmeng Zuo, and Lei Zhang. Toward convolutional blind denoising of real photographs. In *CVPR*, 2019.

Zhiwei Hong, Xiaocheng Fan, Tao Jiang, and Jianxing Feng. End-to-end unpaired image denoising with conditional adversarial networks. In *AAAI*, 2020.

Xiaowan Hu, Ruijun Ma, Zhihong Liu, Yuanhao Cai, Xiaole Zhao, Yulun Zhang, and Haoqian Wang. Pseudo 3D auto-correlation network for real image denoising. In *CVPR*, 2021.

Tao Huang, Songjiang Li, Xu Jia, Huchuan Lu, and Jianzhuang Liu. Neighbor2Neighbor: Self-supervised denoising from single noisy images. In *CVPR*, 2021.

Geonwoon Jang, Wooseok Lee, Sanghyun Son, and Kyoung Mu Lee. C2N: Practical generative noise modeling for real-world denoising. In *ICCV*, 2021.

Heewon Kim and Kyoung Mu Lee. Controllable image enhancement. *arXiv preprint*, 2022.

Yoonsik Kim, Jae Woong Soh, Gu Yong Park, and Nam Ik Cho. Transfer learning from synthetic to real-noise denoising with adaptive instance normalization. In *CVPR*, 2020.

Diederik P Kingma and Jimmy Ba. Adam: A method for stochastic optimization. In *ICLR*, 2015.

Shayan Kousha, Ali Maleky, Michael S. Brown, and Marcus A. Brubaker. Modeling srgb camera noise with normalizing flows. In *CVPR*, 2022.

Alexander Krull, Tim-Oliver Buchholz, and Florian Jug. Noise2Void-learning denoising from single noisy images. In *CVPR*, 2019.

Samuli Laine, Tero Karras, Jaakko Lehtinen, and Timo Aila. High-quality self-supervised deep image denoising. In *NeurIPS*, 2019.

Jaakko Lehtinen, Jacob Munkberg, Jon Hasselgren, Samuli Laine, Tero Karras, Miika Aittala, and Timo Aila. Noise2Noise: Learning image restoration without clean data. In *ICML*, 2018.

Xinhao Liu, Masayuki Tanaka, and Masatoshi Okutomi. Single-image noise level estimation for blind denoising. *TIP*, 2013.

Xinhao Liu, Masayuki Tanaka, and Masatoshi Okutomi. Practical signal-dependent noise parameter estimation from a single noisy image. *TIP*, 2014.

Julien Mairal, Francis Bach, Jean Ponce, Guillermo Sapiro, and Andrew Zisserman. Non-local sparse models for image restoration. In *ICCV*, 2009.

Xiaojiao Mao, Chunhua Shen, and Yu-Bin Yang. Image restoration using very deep convolutional encoder-decoder networks with symmetric skip connections. In *NIPS*, 2016.

D. Martin, C. Fowlkes, D. Tal, and J. Malik. A database of human segmented natural images and its application to evaluating segmentation algorithms and measuring ecological statistics. In *ICCV*, 2001.

Nick Moran, Dan Schmidt, Yu Zhong, and Patrick Coady. Noisier2Noise: Learning to denoise from unpaired noisy data. In *CVPR*, 2020.

Seungjun Nah, Sungyong Baik, Seokil Hong, Gyeongsik Moon, Sanghyun Son, Radu Timofte, and Kyoung Mu Lee. Ntire 2019 challenge on video deblurring and super-resolution: Dataset and study. In *CVPRW*, 2019.

Tongyao Pang, Huan Zheng, Yuhui Quan, and Hui Ji. Recorrupted-to-Recorrupted: Unsupervised deep learning for image denoising. In *CVPR*, 2021.

Tobias Plotz and Stefan Roth. Benchmarking denoising algorithms with real photographs. In *CVPR*, 2017.

Stanislav Pyatykh, Jürgen Hesser, and Lei Zheng. Image noise level estimation by principal component analysis. *TIP*, 2012.

Ying Tai, Jian Yang, Xiaoming Liu, and Chunyan Xu. MemNet: A persistent memory network for image restoration. In *ICCV*, 2017.

Mikhail L Uss, Benoit Vozel, Vladimir V Lukin, and Kacem Chehdi. Image informative maps for component-wise estimating parameters of signal-dependent noise. *JEI*, 2013.

Kyoung Mu Lee Wooseok Lee, Sanghyun Son. Ap-bsn: Self-supervised denoising for real-world images via asymmetric pd and blind-spot network. In *CVPR*, 2022.

Xiaohe Wu, Ming Liu, Yue Cao, Dongwei Ren, and Wangmeng Zuo. Unpaired learning of deep image denoising. In *ECCV*, 2020.

Yaochen Xie, Zhengyang Wang, and Shuiwang Ji. Noise2Same: Optimizing a self-supervised bound for image denoising. In *NeurIPS*, 2020.

Jun Xu, Yuan Huang, Ming-Ming Cheng, Li Liu, Fan Zhu, Zhou Xu, and Ling Shao. Noisy-As-Clean: Learning self-supervised denoising from corrupted image. *IEEE TIP*, 29:9316–9329, 2020.

Songhyun Yu, Bumjun Park, and Jechang Jeong. Deep iterative down-up CNN for image denoising. In *CVPR Workshops*, 2019.

Zongsheng Yue, Hongwei Yong, Qian Zhao, Lei Zhang, and Deyu Meng. Variational denoising network: Toward blind noise modeling and removal. In *NeurIPS*, 2019.

Zongsheng Yue, Qian Zhao, Lei Zhang, and Deyu Meng. Dual adversarial network: Toward real-world noise removal and noise generation. In *ECCV*, 2020.

Syed Waqas Zamir, Aditya Arora, Salman Khan, Munawar Hayat, Fahad Shahbaz Khan, Ming-Hsuan Yang, and Ling Shao. Cycleisp: Real image restoration via improved data synthesis. In *CVPR*, 2020.

Kai Zhang, Wangmeng Zuo, Yunjin Chen, Deyu Meng, and Lei Zhang. Beyond a Gaussian denoiser: Residual learning of deep CNN for image denoising. *IEEE TIP*, 26(7):3142–3155, 2017.

Kai Zhang, Yawei Li, Jingyun Liang, Jiezhang Cao, Yulun Zhang, Hao Tang, Radu Timofte, and Luc Van Gool. Practical blind denoising via swin-conv-unet and data synthesis. *arXiv preprint*, 2022.

Yi Zhang, Hongwei Qin, Xiaogang Wang, and Hongsheng Li. Rethinking noise synthesis and modeling in raw denoising. In *ICCV*, 2021.

Daniel Zoran and Yair Weiss. From learning models of natural image patches to whole image restoration. In *ICCV*, 2011.

A APPENDIX

A.1 DISCUSSIONS

A.1.1 NOISE DISTRIBUTION OF RAW IMAGES

Our NERDS assumes that the raw images have the noise that follows Poisson-Gaussian distribution. However, the image sensor of a smartphone or a digital camera is a black box. We do not know what kind of post-processing has been applied to the raw images, or whether the noise level (parameters) in the metadata represent the proper parameters of Poisson-Gaussian distribution. For instance, one of the noise levels in the metadata of Galaxy S6 (β_2 in Figure 7) equals zero for all images, which is theoretically impossible for both shot and read noise parameters of the Poisson-Gaussian model. Nonetheless, Figure 7 presents a similar tendency between the noise levels in the metadata (β_1, β_2) and the estimated noise parameters ($\hat{\beta}_1$, $\hat{\beta}_2$). Thus, we approximate the noise distribution in raw images as Poisson-Gaussian noise and show that NERDS+D can achieve satisfactory denoising results using the estimated Poisson-Gaussian noise.

Figure 7: Noise distribution of images from Galaxy S6. β_1 and β_2 are the noise levels of metadata, while $\hat{\beta}_1$ and $\hat{\beta}_2$ are the estimated noise parameters for Poisson-Gaussian distribution using NERDS. While (β_1, β_2) have specific values at each ISO level, the radius of the circles for $\hat{\beta}_1$ and $\hat{\beta}_2$ represents the standard deviation of the estimated values for each image on SIDD training dataset.

A.1.2 CLEAN IMAGE VIA DOWNSCALING

The *optimal* clean image via downscaling is a noise-free low-resolution image that has the same statistics as the true signal (clean high-resolution image). Empirically, we regard the raw images downscaled after burring (low-pass filtering) as raw *pseudo*-clean images. However, blurring images breaks the optimal setting when image structures are too small (*e.g.*, 1-pixel dots) or the noise is too severe compared to the size of the blur. Figure 8 shows the evidence and limitations of the utility of pseudo-clean images used in NERDS. First, the images downscaled without pre-blurring have similar statistics to those of the images before downscaling. This indicates that the image scaling can be regarded as capturing an image at different distances between an object and a camera. Second, the blurring operation reduces the std values of noisy images drastically more than clean images. This is why we use downscaled images as pseudo-clean images. However, blurring also reduces the std values of clean images, making it challenging to find *optimal* clean images. To alleviate this difficulty, we estimate the noise by gradient-descent-based optimization and adopt augmentation of noise parameter scaling ($\times 0.5 \sim \times 1.5$) for accurate denoiser training.

Figure 8: Standard deviation (std) of downscaled images. Blue lines denote the std of clean images while the others denote the std of noisy images. Downscaling without pre-blurring maintains the std values through scaling on both BSD68 ((a)) and SIDD ((c)). In contrast, blurring before downscaling reduces the std values of noisy images drastically than clean images ((b) and (d)). (e) Large blur kernels ($2\times$ larger than the kernels used in NERDS) reduce the std values more steeply.

We further analyze the effectiveness of blur kernels by measuring KL divergence between synthesized noisy images and real noisy images. The lower value, the better. Table 4 visualizes ablation study on the size of blur kernels on SIDD dataset. While noise estimation w/ clean image perform the upper bound score, noise estimation w/ blur achieves comparable performances to noise estimation w/ clean image. In both cases of w/o blur and w/ large blur, KL divergence scores increase than noise estimation w/ blur. These results indicate that the downscaled images work as clean images well with the proper size of blur kernels.

Table 4: $\mathcal{D}_{KL}$ comparison. Noise estimation w/ blur achieves comparable performances to w/ clean image.

Noise Estimation	w/o blur	w/ blur	w/ large blur	w/ clean image
$\mathcal{D}_{KL}$	0.1710	0.0344	0.0535	**0.0079**

A.1.3 EFFICIENT INFERENCE AT TEST TIME

The proposed method composes three steps (noise estimation, ISP estimation, and denoiser training) and an additional step of denoiser testing. Each step described above has the latency described in Table 5. We use GeForce RTX 2080 Ti GPU and an HD image for testing.

Table 5: Latency analysis of NERDS.

	Noise Estimation	ISP Estimation	Denoiser Training	Denoiser Testing
Latency	30 m	1 h	6 h	0.1 s

The noise estimation, ISP estimation, and denoiser training using noisy test images are time-consuming. To skip the processes at test time, Table 6 presents a generalization test for NERDS+D trained on different datasets. NERDS+D trained on DND has accurate restoration performance on DND but performs 2 dB lower PSNR on SIDD than the model trained on SIDD. In contrast, NERDS+D trained on SIDD performs accurate restoration on both datasets. This phenomenon indicates that SIDD contains noise distributions similar to DND and that well-designed noisy images enable generalized denoiser training. For instance, camera manufacturers can collect training datasets of only noisy images concerning the image sensor, ISP, and expected image retouching.

Table 6: Generalization test for NERDS+D on different training datasets without clean images. PSNR (dB)/SSIM on RGB SIDD validation and DND benchmark. Bold denotes the best result.

NERDS+D		Taining	
		SIDD	DND
Testing	SIDD	**38.51/0.950**	36.26/0.923
	DND	39.14/0.949	**39.34/0.950**

A.2 COMPARISONS TO NOISE SYNTHESIS METHODS USING REAL NOISY/CLEAN IMAGE PAIRS

The recently proposed methods (Abdelhamed et al., 2019; Chang et al., 2020; Zhang et al., 2021; Kousha et al., 2022) synthesise noisy images with novel noise models. These methods use noise/clean image pairs and metadata that are not accessible at test time, such as the DND dataset. Although the proposed method is a general framework for denoising training without a clean image, we present comparisons with these methods by evaluating the noise estimation results with denoising performance and KL divergence.

A.2.1 RESULTS FOR NOISE ESTIMATION AND SYNTHESIS.

Table 7 presents the comparisons of KL divergence ($\mathcal{D}_{KL}$) between synthesized noisy images and real noisy images. The lower values, the better. The proposed method outperforms all compared methods when using clean images. We could not reproduce the results of RGB Noise Flow (Kousha et al., 2022) since the source code was not available. The score reported in the paper is 0.044 for RGB Noise Flow, where Noise Flow scores 0.198. The scores of KL divergence are dependent on hyperparameters.

Table 7: $\mathcal{D}_{KL}$ comparison. The proposed method with clean data outperforms all compared methods.

	Calibrated P-G	Noise Flow	Camera-Aware	NERDS w/ clean data (Ours)	NERDS (Ours)
Clean data	✓	✓	✓	✓	
$\mathcal{D}_{KL}$	1.5147	0.0481	0.0144	**0.0079**	0.0344

A.2.2 Results for Raw/RGB Image Denoising on the SIDD Benchmark.

Table 8 presents denoising performances for raw images on the SIDD benchmark, where we use DnCNN as the denoiser. Although NERDS does not use clean images for noise estimation, noise synthesis, and denoiser training, NERDS achieves the best PSNR score.

Table 9 presents denoising performances for RGB images on the SIDD benchmark, where all methods use DnCNN as the denoiser. NERDS achieves the best PSNR/SSIM scores. When converting the denoised raw images using NERDS to RGB images, the PSNR is 35.74 dB which is lower than RGB image denoising (36.42 dB).

Table 8: Raw image denoising on the SIDD benchmark. NERDS achieves the best PSNR score. We use DnCNN as the denoiser for NERDS.

	Gaussian	Noise Flow (Abdelhamed et al., 2019)	Camera-Aware (Chang et al., 2020)	NERDS (Ours)
PSNR (dB)/SSIM	43.63/0.968	48.52/0.992	48.71/**0.993**	**48.93**/0.985

Table 9: RGB image denoising on the SIDD benchmark. NERDS achieves the best PSNR/SSIM scores. All methods use DnCNN as the denoiser.

	Gaussian	Noise Flow	C2N	RGB Noise Flow (Kousha et al., 2022)	NERDS (Ours)
PSNR (dB)/SSIM	32.72/0.873	33.81/0.894	33.76/0.901	34.74/0.912	**36.42/0.923**

A.3 Qualitative Results
A.3.1 Synthesized Noisy-Clean Image Pairs
Figure 9 visualizes noise synthesis results using NERDS. NERDS-clean contains low-level noise while NERDS-noisy presents severe noise similar to the real noisy images. We have empirically found that denoisers *do not* learn to remove noise in NERDS-clean. This phenomenon is because the blurring and downscaling process in NERDS distorts the noise of raw images while denoisers learn to remove Poisson-Gaussian noise in the raw images. Moreover, given that NERDS does not require any clean data, NERDS successfully synthesizes noisy-clean image pairs on DND and MIT-Adobe FiveK datasets which are not available to access clean images.

A.3.2 Denoised Images
We present more images denoised by NERDS+D on SIDD (Figure 10), DND (Figure 11), and MIT-Adove FiveK (Figure 12). While AP-BSN (Wooseok Lee, 2022), FBI-D (Byun et al., 2021), SCUNet (Zhang et al., 2022), C2N (Jang et al., 2021)+DIDN (Yu et al., 2019), and CycleISP (Zamir et al., 2020) often fail to restore image patterns in GT, NERDS+D successfully recover the original structures. AP-BSN uses pixel shuffle for self-supervised learning to decorrelate spatially but also loses spatial information for denoising. FBI-D learns raw image denoising for Poisson-Gaussian noise, but denoising raw images is an indirect approach for the human visual system (or RGB space). SCUNet over-smooth or over-sharpen images. This restoration style helps to generate readable characters, but it can distort the patterns in GT (See Figure 10). C2N+DIDN is the denoiser trained by generating noisy images from clean images using both noisy and clean images on SIDD datasets. For DND benchmarks, C2N+DIDN sometimes generates artifacts or noise that significantly drops the restoration accuracy (See Figure 11). In contrast, NERDS+D uses only noisy images on DND benchmarks to generate noisy-clean image pairs for accurate denoiser training. CycleISP is the denoiser trained by paired noisy-clean images on SIDD datasets and paired images synthesized by the metadata of DND benchmarks. CycleISP performs the highest PSNR and SSIM on both SIDD and DND benchmarks compared to the methods in Table 2. However, CycleISP fails to remove the noise on MIT-Adobe FiveK (See Figure 12). This failure comes from the noise distribution of RGB images mismatched between MIT-Adobe FiveK and SIDD (or DND) datasets.

Figure 9: Examples of noisy synthesis results using NERDS. We upscale NERDS-noisy, NERDS-clean, and the green boxes with the scaling factor of 2 for visualization.

Figure 10: Qualitative results and PSNR (dB)/SSIM on SIDD validation.

Figure 11: Qualitative results and PSNR (dB)/SSIM on DND.

Figure 12: Qualitative results on MIT-Adobe FiveK. CycleISP often fails to remove noise, while FBI-D and SCUNet over-smooth or over-sharpen images. Note that NERDS+D uses only 5 test noisy images and estimated noise parameters from them for training. (*Zooming-in for the best view.*) We use T of NERDS to convert raw images denoised by FBI-D to RGB images.