SPATIAL FREQUENCY SENSITIVITY REGULARIZATION FOR ROBUSTNESS

ABSTRACT

The ability to generalize to out-of-distribution data is a major challenge for modern deep neural networks. Recent work has shown that deep neural networks latch on to superficial Fourier statistics of the training data and fail to generalize when these statistics change, such as when images are subject to common corruptions. In this paper, we study the frequency characteristics of deep neural networks in order to improve their robustness. We first propose a general measure of a model's *spatial frequency sensitivity* based on its input-Jacobian represented in the Fourier-basis. When applied to deep neural networks, we find that standard minibatch training consistently leads to increased sensitivity towards particular spatial frequencies independent of network architecture. We further propose a family of *spatial frequency regularizers* based on our proposed measure to induce specific spatial frequency sensitivities in a model. In experiments on datasets with out-of-distribution test images arising from various common image corruptions, we find that deep neural networks trained with our proposed regularizers obtain significantly improved classification accuracy while maintaining high accuracy on in-distribution clean test images.

1 INTRODUCTION

While deep neural networks (DNN) achieve remarkable performance on many challenging image classification tasks, they can suffer significant drops in performance when evaluated on many semantics-preserving corruptions such as noise, blurring and JPEG-compression artifacts (Hendrycks & Dietterich, 2019). This failure has been attributed to the frequency characteristics of these corruptions in relation to the frequency sensitivity of DNNs (Yin et al., 2019). Distinct spatial frequencies in images contain features at different spatial scales; low spatial frequencies (LSF) carry global structure and shape information in a scene whereas high spatial frequencies (HSF) carry local information such as edges and borders of objects in a scene (Kauffmann et al., 2014); in fact, spatial frequencies are differentially processed in distinct channels of the visual cortex in the brain to learn features at different scales (Appendix B). When information is destroyed or corrupted in frequency bands that a model relies on, performance suffers. Hence, understanding the spatial frequency sensitivity of a DNN can help us characterise the features it relies on to make predictions.

While DNNs have been demonstrated to be sensitive to Fourier-basis directions in the input (Tsuzuku & Sato, 2019; Yin et al., 2019), the precise definition and measurement of their spatial frequency sensitivity still lacks a rigorous approach across studies. In addition, there has been no principled method to specifically modify the frequency sensitivity of a model. Existing works have heuristically applied smoothing filters on convolution layers (Wang et al., 2020; Saikia et al., 2021) and data augmentations (Yin et al., 2019) to modify a model's frequency sensitivity.

In this work, we propose a novel and rigorous measure of a deep neural network's *spatial frequency sensitivity* using the input-Jacobian represented in the Fourier-basis and show that deep neural networks demonstrate consistent spatial frequency sensitivities across samples, an observation that suggests DNNs are more likely to consistently use some frequencies more than others, and has implications for robustness. In addition, using our proposed measure, which is differentiable with respect to model parameters, we propose a novel family of *spatial frequency regularizers* to directly induce specific frequency sensitivities in a model. We hypothesize and show in empirical evaluations that spatial frequency regularization can modify the frequency characteristics of features that mod-

els learn and that these features can be significantly more robust to common semantics-preserving corruptions such as noise, blurring, JPEG-compression as well as Fourier-filtering.

In summary, the main contributions of this work are as follows:

1. We propose a novel and rigorous measure of a model's *spatial frequency sensitivity* based on its input-Jacobian represented in the Fourier-basis

2. We propose a novel family of *spatial frequency regularizers* to directly induce specific spatial frequency sensitivities

3. We demonstrate that spatial frequency regularization can significantly improve generalization performance on **out-of-distribution** data of many common corruptions while retaining high accuracy on clean images

2 RELATED WORK

To set the stage for our work, we briefly review the literature of the Fourier-perspective of model robustness and Jacobian-regularization - two lines of work that are related to this study.

2.1 FOURIER PERSPECTIVE OF ROBUSTNESS

Characterising frequency sensitivity: Yin et al. (2019); Tsuzuku & Sato (2019) characterised the Fourier characteristics of trained CNNs using perturbation analysis of their test error under Fourier-basis noise. They showed that a naturally trained model is most sensitive to all but low frequencies whereas models adversarially trained (Madry et al., 2018) models are sensitive to low-frequency noise. They further showed that these Fourier characteristics relate to model robustness on corruptions and noise, with models biased towards low frequencies performing better under high frequency noise and vice versa. Abello et al. (2021) took a different approach by measuring the impact on accuracy of removing individual frequency components from the input using filters whereas Ortiz-Jimenez et al. (2020) computed the margin in input space along basis directions of the discrete cosine transform (DCT). Wang et al. (2020) made observations about the Fourier characteristics of CNNs in different training regimes including standard and adversarial training by evaluating accuracy on band-pass filtered data. In contrast to these disparate approaches, in this work, we propose a rigorous measure of a model's *spatial frequency sensitivity*.

Regularizing frequency sensitivity: Yin et al. (2019) proposed adversarial training (Madry et al., 2018) and gaussian noise augmentations as methods that induce a low-frequency sensitivity. Wang et al. (2020) proposed smoothing convolution filter parameters to induce a low-frequency sensitivity in models. We note that, in general, techniques that apply filters on convolutional parameters to affect a model's frequency sensitivity do not take into account complex operations such as non-linearities, pooling and other transformations that often follow convolutional layers that can modify as well as undo the effects of such filters. In addition, data augmentations do not provide precise control over frequency sensitivity of a model. In this work, we propose a family of *spatial frequency regularizers* that can precisely modify the overall spatial frequency sensitivity of any differentiable model.

2.2 JACOBIAN REGULARIZATION

Methods that regularize the Jacobian of a model's output-logits or loss with respect to its input can broadly be divided into two types; one regularizes the norm of the input-Jacobian and the other regularizes its direction or directional derivatives. Drucker & Le Cun (1991) proposed a method that penalized the norm of the input-Jacobian to improve generalization, more recently this has been explored to improve robustness to adversarial perturbations (Ross & Doshi-Velez, 2018; Jakubovitz & Giryes, 2018; Hoffman et al., 2019). Simard et al. (1992) proposed "Tangent Prop", which minimized directional derivatives of classifiers in the direction of local input-transformations (e.g. rotations, translations; called "tangent vectors") to increase model invariance to such transformations. Czarnecki et al. (2017) proposed Sobolev training of neural networks to improve model distillation by matching the input-Jacobian of the original model. Regularizing the direction of the input-Jacobian has also been used to improve adversarial robustness (Chan et al., 2020). In the present

work, we regularize Fourier-components of the input-Jacobian to modify the spatial frequency sensitivity of a model. As such, we are directly modifying the direction of the input-Jacobian instead of its norm.

3 METHODS

3.1 PRELIMINARIES

We introduce all relevant definitions and notations before describing the proposed methods. Consider an image classification task with input images x, target labels y, and the standard cross-entropy loss function $\mathcal{L}_{\mathrm{CE}}$. Let f denote any differentiable model, $\mathcal{F}(\cdot)$ the unitary 2D discrete Fourier transform (DFT), $\mathcal{F}^{-1}(\cdot)$ its inverse, and $\mathcal{F}^{-1^*}(\cdot)$ the adjoint of the inverse-Fourier transform, and let x_f denote the Fourier space representation of the input, i.e. $x_f = \mathcal{F}(x)$. We denote the input-Jacobian in the standard input basis as $\frac{\partial \mathcal{L}_{\mathrm{CE}}}{\partial x}$, and $\frac{\partial \mathcal{L}_{\mathrm{CE}}}{\partial x_f}$ as the input-Jacobian in the Fourier-basis. Let N denote the height of the input images x (although not necessary, all images used in this work are square). The zero-shifted 2D-DFT of the input-Jacobian is denoted $F = \mathcal{F}(\frac{\partial \mathcal{L}_{\mathrm{CE}}}{\partial x})$. Since the input-Jacobian typically has three color channels, they are averaged before computing the 2D-DFT. Fourier coefficients in F are complex numbers with real and imaginary components; $F(u,v) = Real(u,v) + Imag(u,v)$, where (u,v) are indices of coefficients. The *power* in a coefficient is its squared amplitude, $P(u,v) = |F(u,v)|^2 = Real(u,v)^2 + Imag(u,v)^2$ and the matrix of powers is denoted P (power-matrix). Each coefficient has a radial distance $r(u,v)$ from the centre of the matrix, $r(u,v) = d((u,v),(c_u,c_v))$, where (c_u,c_v) denotes the centroid of P and $d(\cdot,\cdot)$ is Euclidean distance. Distinct radial distances, rounded to the nearest integer, of coefficients in the matrix are the set of integers $\{1,\ldots,N/\sqrt{2}\}$ and correspond to low to high spatial frequency bands, the highest spatial frequency being limited by the Nyquist frequency. We denote P_{Total} as the total power in P, excluding the zero-frequency coefficient, $P_{Total} = \sum_{r(u,v)>=1} P(u,v)$. Similarly, we define $\tilde{P}_{Total}$ as the total power in P excluding the zero-frequency coefficient as well as coefficients with radial distance $r(u,v) > N/2$, i.e. outside the largest circle inscribed in the power-matrix P; $\tilde{P}_{Total} = \sum_{1<=r(u,v)<=N/2} P(u,v)$ (please see Figure 4 in Appendix A.1 for an illustration). We denote P_k as the total power at radial distance k normalized by P_{Total}, $P_k = \frac{1}{P_{Total}} \sum_{r(u,v)=k} P(u,v)$ and $\tilde{P}_k$ as total power at radial distance k normalized by $\tilde{P}_{Total}$ instead, $\tilde{P}_k = \frac{1}{\tilde{P}_{Total}} \sum_{r(u,v)=k} P(u,v)$.

3.2 SPATIAL FREQUENCY SENSITIVITY OF A MODEL

In this section, we define the proposed ***spatial frequency sensitivity (SFS)*** of any differentiable model using its input-Jacobian represented in the Fourier-basis. As the input-Jacobian provides the direction of highest input sensitivity, we show below that its Fourier transform, which is simply a change of basis, provides the model's sensitivities to spatial frequency components in the input. The input-Jacobian in the Fourier-basis, $\frac{\partial \mathcal{L}_{\mathrm{CE}}}{\partial x_f}$, comprises the sensitivities of the model with respect to individual frequencies in the input and we obtain this by simply computing the Fourier transform of the input-Jacobian $\frac{\partial \mathcal{L}_{\mathrm{CE}}}{\partial x}$. In order to justify this, consider the computation graph where the input x is mapped to a scalar loss via a model f and loss function $\mathcal{L}_{\mathrm{CE}}$ (Figure 2). We introduce an implicit operation (shown in red) that maps the Fourier space representation of the input, x_f, to the standard input x through the inverse Fourier-transform; $x_f \xrightarrow{\mathcal{F}^{-1}} x$, so in order to compute the input-Jacobian in the Fourier-basis, $\frac{\partial \mathcal{L}_{\mathrm{CE}}}{\partial x_f}$, we must differentiate through this *implicit* operation in the forward graph. Since the inverse-Fourier transform is a unitary operator, its adjoint is also its inverse, i.e. $\mathcal{F}^{-1^*} = (\mathcal{F}^{-1})^{-1} = \mathcal{F}$. Hence, following the chain rule for complex operators, $\frac{\partial \mathcal{L}_{\mathrm{CE}}}{\partial x_f}$ is simply the Fourier transform of the input-Jacobian $\frac{\partial \mathcal{L}_{\mathrm{CE}}}{\partial x}$.

$$\frac{\partial \mathcal{L}_{\mathrm{CE}}}{\partial x_f} = \mathcal{F}^{-1^*}(\frac{\partial \mathcal{L}_{\mathrm{CE}}}{\partial x}) = \mathcal{F}(\frac{\partial \mathcal{L}_{\mathrm{CE}}}{\partial x})$$

Figure 1: Illustration of steps to compute the *spatial frequency sensitivity* with respect to a single input image. The input-Jacobian of the model is Fourier-transformed to obtain sensitivities with respect to frequency components followed by computing the proportion of power in low to high (small to large radius) frequency bands.

Figure 2: Computation graph to obtain the input-Jacobian in Fourier-space. The symbols in red represent an implicit map of the input from Fourier-space to the standard input space. The dashed arrows denote the backward graph operations to compute the input-Jacobian in Fourier space.

Hence, even though we do not explicitly use the Fourier representation of the input, this shows that the Fourier transform of the input-Jacobian provides us the sensitivity of the model with respect to spatial frequencies of the input. In fact, similar results hold for any unitary operation on the input-Jacobian, such as the discrete cosine transform (DCT). Interested readers can replace the DFT ($\mathcal{F}$) with other such transforms if they would like to understand the sensitivity of a model with respect to other components in the input. We now define the spatial frequency sensitivity $f_{SFS}(x, y)$ with respect to an individual input (x, y) as,

$$f_{SFS}(x, y) = \{P_1, \ldots, P_{N/\sqrt{2}}\}$$

where P_k is the proportion of total power in Fourier coefficients at radial distance k in the power matrix P of the Fourier-transformed input-Jacobian. The overall spatial frequency sensitivity of a model is defined as the expectation of $f_{SFS}(x, y)$ over the data distribution, i.e. $f_{SFS}(\cdot; \theta) = \mathbb{E}_{(x,y)\sim p}[f_{SFS}(x, y)]$ (please see Figure 1 for an illustration and Algorithm 1 in Appendix A.1). We note that although we use the Jacobian of the loss function to estimate the *SFS* of a model, this formulation is valid for other output functions and tasks as well. An alternative approach that does not require image labels is to compute the Jacobian of the model's output logits or softmax probabilities. In addition, while the spatial frequency sensitivity assumes the input is spatial 2D data (e.g. images), we can extend this approach to any n-dimensional data by using the n-dimensional Fourier-transform.

3.3 SPATIAL FREQUENCY REGULARIZATION

In this section, we propose a novel family of **spatial frequency regularizers** that can modify the *spatial frequency sensitivity*, as defined in Section 3.2, of a model directly. As all computations involved in the *SFS* of a model (Algorithm 1 in Appendix A.1) are differentiable with respect to its parameters, we compute a loss function

$$\mathcal{L}(x, y) = \mathcal{L}_{\text{CE}}(x, y) + \lambda_{\text{SFS}}\mathcal{L}_{\text{SFS}}(x, y)$$

where $\mathcal{L}_{\text{SFS}}$ is the proposed loss that can be used to induce a specific *SFS* and λ_{SFS} is a hyperparameter. As $\mathcal{L}_{\text{SFS}}$ is defined on the *SFS*, which is a function of the input-Jacobian, optimizing it requires an additional backpropagation step to compute its derivatives with respect to model parameters, similar to other Jacobian-regularization methods. We now define $\mathcal{L}_{\text{SFS}}$ for three different SFS

regularizers; $SFS \in \{LSF, MSF, ASF\}$. LSF regularization trains a model to be insensitive to medium and high spatial frequencies and MSF regularization trains a model to be insensitive to low and high spatial frequencies. We achieve this by penalizing the proportion of total power, P_k, in frequency bands. ASF regularization trains a model to be equally sensitive to all spatial frequency (ASF) bands. The motivation behind ASF regularization model is to encourage a model to be sensitive to multiple frequency bands instead of being concentrated in a single frequency range. Hence, the ASF-regularizer loss is the negative entropy of the distribution of power over spatial frequency bands.

$$\mathcal{L}_{\text{SFS}}(x, y) := \begin{cases} \sum_{k > N/6} P_k, & \text{if SFS=LSF} \\ \sum_{k < N/6, k > N/3} P_k, & \text{if SFS=MSF} \\ \sum_{k=1}^{k=N/2} \tilde{P}_k \log \tilde{P}_k, & \text{if SFS=ASF} \end{cases}$$

The definitions of frequency ranges are based on equally dividing the largest circle inscribed in the power-matrix P into equal parts (Figure 4 in Appendix A.1). For ASF-regularization, very high frequency bands ($r(u, v) > N/2$ are excluded. Interested readers may modify these loss functions as they see fit for their particular application.

4 EXPERIMENTS

In this section we explore the *SFS* of models as well as explore the effects of spatial frequency regularization on feature learning by evaluating models on datasets where the Fourier-statistics of predictive features are naturally or artificially altered (Sections 4.3, 4.4). We also make some observations about the differences between spatial frequency regularization and training on Fourier-filtered training data (Section 4.6). We benchmark against methods that have been proposed to modify the frequency sensitivity of models such as adversarial training and Gaussian Noise augmentation (Yin et al., 2019) to induce low-frequency sensitivity as well as training on band-pass Fourier-filtered datasets, applying low-pass, medium-pass and high-pass filters. AugMix (Hendrycks et al., 2020) is also benchmarked as it was shown to achieve state-of-the-art performance on common corruptions.

4.1 EXPERIMENTAL SETUP

We first describe the experimental settings for all experiments that follow. All baseline and regularized models for CIFAR10 and CIFAR100 were trained with the same parameters. We trained the ResNet50 architecture, unless stated otherwise, for 150 epochs using stochastic gradient descent (SGD) with momentum (0.9), an initial learning rate of 0.1 decayed by a factor of 10 every 50 epochs, weight decay parameter equal to 5e-4 and batch size equal to 128. Standard data augmentations random-crop, random-horizontal-flip, random-rotation, and color-jitter were used during training. We train spatial frequency regularized models using Algorithm 2 2 in Appendix A.1, and $\lambda_{\text{SFS}} = 1$ for all models. For adversarial training (AT) on CIFAR10/CIFAR100, we used PGD ℓ_2 attacks ($\epsilon = 1$, attack-steps = 7 attack-lr = 1/7). To train models with Gaussian noise data augmentation, we added i.i.d. Gaussian noise $\mathcal{N}(0, \sigma^2)$ to each pixel in all the images in the training set ($\sigma = 0.1$). We used the *robustness* (Engstrom et al., 2019) library to train models as well as retrieve pre-trained ImageNet models of various architectures. We trained AugMix models using the original code shared by the authors (`https://github.com/google-research/augmix`). Please see Section D.2 in Appendix D for details about band-pass filters.

4.2 CNNs DEMONSTRATE CONSISTENT SPATIAL FREQUENCY SENSITIVITY ACROSS SAMPLES

We now visualize the *spatial frequency sensitivity (SFS)*, as defined in Section 3.2, of methods trained on CIFAR10 and ImageNet, estimated using randomly selected samples from their respective validation sets (Figure 3). Please note that spatial frequencies are listed in *cycles/image* and as such they are not directly comparable across datasets due to differences in image size. Hence, references to low, medium or high spatial frequencies are relative to image sizes in the dataset being discussed.

Figure 3: Spatial Frequency Sensitivities of ResNet50 models trained by methods on CIFAR10 and ImageNet. Computed on 1k randomly selected samples from respective validation sets. The shaded region represents two standard deviations.

We note that training biases models to be sensitive to some frequencies more than others and this bias is consistent across samples (the error bars in Figure 3 represent deviation in the *SFS* when estimated across samples). This consistency also suggests that, once trained, CNNs are more likely to use some frequencies more than others and this explains their tendency to suffer performance drops when evaluated on data with different Fourier-statistics. CIFAR100 models have very similar *SFS* to those of CIFAR10 (plots relegated to Appendix C.2) and are also most sensitive to mid-to-high spatial frequencies.

ImageNet models are sensitive to a wide range of the frequency spectrum with peak sensitivity to mid-range frequencies. We also observed consistency in the spatial frequency sensitivity of various convolutional architectures trained on ImageNet (Appendix C.1). Adversarially trained models (Madry et al., 2018) are most sensitive to low spatial frequencies across datasets and architectures which suggests they rely on coarse global features, in agreement with observations made in prior work. Training on Stylized-ImageNet, proposed by Geirhos et al. (2019) to train shape-biased in models, induces a lower peak-spatial-frequency-sensitivity and as well as lower sensitivity to high frequencies compared to training on ImageNet (Appendix C.2), which reflects the increased shape-bias of such models. Similarly, a model trained on low-pass Fourier-filtered training data correspondingly has high sensitivity to low-frequencies in comparison to the baseline model (Appendix C.2). We note that severe Gaussian-noise augmentation is needed to induce increased low-frequency sensitivity. Gaussian noise augmentation $\mathcal{N}(0, \sigma^2; \sigma = 0.1)$, as suggested in (Yin et al., 2019), does not significantly modify the spatial frequency sensitivity of the model (Figure 3) from that of baseline. The *SFS* of the AugMix (Hendrycks et al., 2020) trained model was not significantly different from baseline, which suggests it finds more robust features in similar frequency bands using data augmentations.

Interestingly, we also note that models trained on corrupted versions of the CIFAR10 training set (e.g. blurred or JPEG-compressed) can display different spatial frequency sensitivities to a model trained on clean CIFAR10 images (please see Appendix C.3 for plots). For example, models trained on images with severe noise corruptions (gaussian, shot and speckle) display increased sensitivity to lower spatial frequencies. Models trained on highly gaussian-blurred, glass-blurred, JPEG-compressed and pixelated images also display higher sensitivity to lower spatial frequencies. These changes reflect the shift in the Fourier-statistics of predictive features in corrupted images.

Finally, we note that all *spatial frequency regularized* models have the desired spatial frequency sensitivities different to that of the baseline and they retain high clean accuracy (Table 1. While regularized models do not suffer significant drops in accuracy for CIFAR10, the accuracy drops are larger for CIFAR100, which is a fine-grained classification task and may require high sensitivity to high-frequency information to perform optimally. This suggests that, in the absence of spatial frequency regularization, models tend to be most sensitive to the most predictive frequencies in the training set.

4.3 ROBUSTNESS TO FOURIER FILTERING

Jo & Bengio (2017) showed that DNNs have a tendency to rely on superficial Fourier-statistics of their training data. In the vein of generalization evaluations they performed, we generate Fourier-filtered CIFAR10 validation images using radial masking in frequency space (please see Appendix D.1 for examples). A mask radius r determines Fourier components that are preserved with larger radii preserving more components. We use (c_u, c_v) to denote the centre of the mask and $d(\cdot, \cdot)$ to denote Euclidean distance. The radial mask M_r is defined as:

$$M_r(u, v) := \begin{cases} 1, & \text{if } d((u, v), (c_u, c_v)) \leq r \\ 0, & \text{otherwise} \end{cases} \tag{1}$$

The mask is applied on the zero-shifted output of the Fourier transform of each image, denoted X, followed by the inverse transform, i.e. $X_{filtered} = \mathcal{F}^{-1}(\mathcal{F}(X) \odot M_r)$, where $\odot$ is the element-wise product. Fourier-filtering is performed on each color channel independently. A standard CNN suffers up to a 75% drop in accuracy on low-pass filtered data as it relies on high frequency information that is no longer present (Table 1). On the other hand, the LSF-REGULARIZED model performs well on both clean images as well severely low-pass filtered images. This shows that CNNs are able to exploit very low frequency features ($r \leq 5$) that are not easily recognizable even to humans, suggesting the limited spatial-frequency-sensitivity range of the human eye.

Method	Clean	$r = 11$	$r = 7$	$r = 5$
Std. Train	**94.9**	78.1	24.9	18.6
LSF-REGULARIZED	86.3	**86.2**	**84.4**	**78.3**
MSF-REGULARIZED	87.2	86.3	71.5	46.2
ASF-REGULARIZED	87.6	85.0	69.3	45.0
AT (PGD $\ell_2, \epsilon = 1$)	81.6	80.2	76.1	67.5
Gaussian Noise	94.3	73.9	18.1	14.8
AugMix	95.8	92.0	79.4	50.2

Table 1: Accuracy on Fourier-filtered CIFAR10 test set.

The MSF-REGULARIZED model performs better for mild Fourier-filtering ($r = 11$ and $r = 7$) but suffers a big drop in accuracy (71.5% to 46.2%) when all but low frequency information is left ($r = 5$). We also find that the model regularized to use multiple spatial frequency bands (ASF-REGULARIZED) is also significantly more robust than the baseline model although not as robust as the LSF-REGULARIZED model to Fourier-filtering. This shows that the ASF-REGULARIZED model can use coarse low-spatial-frequency features in addition to medium and high spatial frequencies. The low-frequency sensitivity of adversarially trained models makes it more robust than the baseline model but less so than the LSF-REGULARIZED model, while the Gaussian noise augmented model suffers large drops in accuracy. AugMix tends to be robust to mild Fourier-filtering but suffers large drops in accuracy under more severe filtering ($r = 5$) due to its reliance on mid-to-high-frequency information, as suggested by its *SFS*, in comparison to the LSF-REGULARIZED model.

4.4 ROBUSTNESS TO CORRUPTIONS

We evaluate the robustness of spatial frequency regularized models to corrupted images in the CIFAR10-C/CIFAR100-C (Hendrycks & Dietterich, 2019) datasets, which comprise a curated set of corruptions that models may encounter in the wild (please see Appendix E for examples). While methods such as AugMix (Hendrycks et al., 2020) that achieve state-of-the-art performance on these datasets use sophisticated data-augmentation approaches, we show that regularizing the *spatial frequency sensitivity* of models can also significantly improve performance on many corruption types. On CIFAR10-C, we note that the LSF-REGULARIZED model is significantly more robust than the baseline model to all *blurring* corruptions as well as *pixelate, elastic, snow and frost* corruptions (Table 2). The baseline model suffers up to 45% drop in accuracy on these corruptions, whereas the LSF-REGULARIZED model suffers at most 5% drop in accuracy. Its improved performance is likely due to the robustness of low-spatial-frequency features to corruptions such as blurring that affect high-frequency features more. While not as robust as the LSF-REGULARIZED model to these corruptions, both MSF-REGULARIZED and ASF-REGULARIZED models are also significantly more

robust than the baseline model. We note that the MSF-REGULARIZED and ASF-REGULARIZED models are more robust to *noise* corruptions as well as JPEG compression (Table 2). This suggests spatial frequencies across the spectrum maybe needed to do well on these corruptions, unlike blurring where LSF appear to be sufficient. Models with high spatial-frequency sensitivity appear to be more robust to fog and brightness as we observe that the baseline model, which is most sensitive to high-frequencies, performs best on these corruptions. Other low-frequency sensitive methods such as AT and low-pass filtering are also robust to many corruptions including blurring and noise.

Method	Clean	Noise			Blur				Weather				Digital			
		Gauss.	Shot	Impulse	Defocus	Glass	Motion	Zoom	Snow	Frost	Fog	Bright	Contrast	Elastic	Pixel	JPEG
Std. Train	94.9	31.5	37.9	33.8	54.9	49.5	67.3	65.2	75.8	65.4	74.2	92.0	56.3	73.2	41.0	73.5
LSF-REGULARIZED	86.3	29.4	32.5	20.0	**83.9**	**81.8**	**80.4**	**83.9**	**79.6**	**79.2**	60.6	82.0	28.3	**82.5**	**85.5**	65.3
MSF-REGULARIZED	87.2	**55.6**	**59.2**	**34.9**	**78.0**	**71.2**	**67.7**	**77.5**	**77.8**	**78.4**	60.4	82.8	19.5	**76.1**	**83.5**	**81.4**
ASF-REGULARIZED	87.6	**62.3**	**64.6**	**44.6**	**71.3**	**70.2**	**69.7**	**75.3**	**75.9**	**74.6**	47.3	83.6	26.5	**76.1**	**79.7**	**82.6**
Low-pass filtered	86.6	**58.0**	**60.4**	**43.5**	**86.0**	**84.0**	**82.5**	**85.5**	**81.0**	**80.3**	62.7	82.5	35.2	**83.5**	**86.0**	71.6
Medium-pass filtered	33.8	23.4	26.5	17.0	13.8	19.9	13.2	14.4	20.8	18.8	15.0	18.4	10.5	19.9	20.6	23.9
High-pass filtered	15.3	15.8	16.3	14.7	13.4	14.8	12.8	13.2	12.0	10.2	10.8	11.4	11.3	14.4	14.7	14.9
AT (PGD $\ell_2, \epsilon = 1$)	81.6	**74.6**	**75.5**	**66.7**	**74.9**	**74.2**	**73.2**	**76.5**	75.2	**70.5**	35.1	77.9	19.3	**75.8**	**78.4**	**79.7**
Gaussian Noise	94.3	**34.2**	**42.7**	31.3	46.2	**51.3**	**68.2**	57.5	75.6	65.2	**75.7**	91.6	55.3	**75.2**	**41.7**	**75.5**
AugMix	**95.8**	**66.1**	**72.7**	**75.6**	**92.6**	**75.0**	**90.8**	**91.6**	**86.6**	**85.4**	**83.2**	**93.6**	**86.6**	**85.4**	**83.2**	**93.6**

Table 2: Accuracies for CIFAR10-C corruptions of highest severity level. Accuracies higher than baseline (Std. Train) are in bold.

We observe similar results on CIFAR100-C corruptions. We note again that the LSF-REGULARIZED model is significantly more robust than the baseline for blurring corruptions (Table 3). For noise corruptions, the MSF-REGULARIZED model is more robust compared to the baseline as well as the LSF-REGULARIZED model (Table 3). Similar to CIFAR10-C, low-pass filtering and AT also lead to models robust to blurring and noise. MSF-REGULARIZED and ASF-REGULARIZED models are again more robust to noise and JPEG noise, compared to the ASF-REGULARIZED model.

Method	Clean	Noise			Blur				Weather				Digital			
		Gauss.	Shot	Impulse	Defocus	Glass	Motion	Zoom	Snow	Frost	Fog	Bright	Contrast	Elastic	Pixel	JPEG
Std. Train	76.2	10.9	12.5	8.7	30.5	18.3	41.1	37.7	46.0	30.6	40.0	69.9	29.8	49.6	21.4	48.9
LSF-REGULARIZED	61.4	**16.0**	**18.8**	8.4	**56.5**	**56.3**	**52.9**	**57.9**	**52.0**	**51.1**	29.2	54.2	13.6	**56.1**	**60.0**	36.3
MSF-REGULARIZED	62.4	**31.8**	**34.6**	**16.2**	**49.6**	**50.1**	**44.6**	**52.9**	**51.6**	**48.7**	28.0	54.3	9.2	**53.4**	**58.7**	**54.5**
ASF-REGULARIZED	67.0	**15.6**	**18.4**	8.6	**41.4**	**40.9**	**43.0**	**47.0**	**51.4**	**44.6**	26.9	58.9	11.8	**52.6**	**61.0**	**54.2**
Low-pass filtered	60.1	**32.7**	**34.9**	**18.9**	**59.3**	**56.6**	**54.8**	**58.1**	**50.2**	**49.4**	27.0	54.1	13.4	**57.0**	**59.9**	43.8
Medium-pass filtered	10.4	3.8	5.3	2.1	3.5	5.5	3.6	4.0	2.8	2.6	2.8	3.4	1.8	5.4	4.7	6.0
High-pass filtered	1.3	1.8	2.0	1.8	1.2	1.4	1.2	1.1	1.0	1.0	1.0	1.0	1.0	1.2	1.3	1.2
AT (PGD $\ell_2, \epsilon = 1$)	58.8	**44.8**	**45.9**	**26.0**	**48.8**	**49.4**	**46.3**	**50.0**	**46.6**	**40.9**	10.4	50.2	5.0	**50.7**	**54.7**	**55.5**
Gaussian noise	77.0	**11.4**	**13.3**	**9.2**	**31.4**	**20.0**	**42.6**	**38.1**	**47.5**	**33.4**	**46.8**	**70.3**	**31.4**	**49.8**	**22.2**	47.0
AugMix	**77.8**	**36.8**	**41.9**	**52.9**	**71.8**	**47.8**	**69.4**	**70.3**	**60.3**	**55.7**	**47.7**	**70.0**	**47.4**	**61.0**	**50.0**	**60.9**

Table 3: Accuracies for CIFAR100-C corruptions of highest severity level. Accuracies higher than baseline (Std. Train) are in bold.

While AugMix's *SFS* is not significantly different from that of the baseline model it performs robustly across both CIFAR10-C and CIFAR100-C due to its use of sophisticated data augmentation approach. This demonstrates that while the frequency perspective of feature learning can help improve robustness, there may still be other powerful ways to achieve robustness through the use of data augmentations, although it is not clear why the augmentations used in AugMix confer robustness to these corruptions.

4.5 EVALUATION OF GLOBAL FEATURE LEARNING BY PATCH SHUFFLING IMAGES

We demonstrate the extent to which models use global features by evaluating performance on patch-shuffled images, which have previously been used by Mummadi et al. (2021); Zhang & Zhu (2019); Wang et al. (2019). Patch-shuffling involves splitting an image into $k \times k$ squares and randomly swapping the positions of these squares. This is intended to destroy global features and retain local features with larger values of k retaining less global structure in the image (please see Appendix F for examples). As such, models that rely more on global rather than local structure suffer more from patch-shuffling. Hence, in this benchmark, lower accuracy suggests increased use of global structure. We note that the low and medium frequency sensitive models suffer larger drops in accuracy compared to the standard trained and Gaussian noise augmented models, which suggests they rely more on global features (Table 4).

Method	clean	$k = 2$	$k = 3$
Std. Train	94.9	66.5	45.8
Gaussian Noise	94.3	64.7	42.1
LSF-REGULARIZED	86.3	**43.2**	**30.6**
MSF-REGULARIZED	87.2	**46.8**	**33.1**
ASF-REGULARIZED	87.6	**46.8**	**32.6**
Low-pass filtered	86.6	**43.4**	**30.0**
AT (PGD $\ell_2, \epsilon = 1$)	81.6	**45.2**	**35.0**

Table 4: Benchmark on patch-shuffled CIFAR10 test set.

4.6 SPATIAL FREQUENCY REGULARIZATION IS NOT EQUIVALENT TO TRAINING ON FOURIER-FILTERED DATA

We note that spatial frequency regularization is not equivalent to standard training on corresponding Fourier-filtered data. In natural images, the amount of energy in frequency bands falls off rapidly as frequency increases (Hyvärinen et al., 2009), hence, medium and high-pass filtered natural images typically appear completely empty to the human eye without additional contrast maximisation. Even still, such images are not easily recognizable to the human eye due to its and reliance on low frequency information to recognize objects optimally (Appendix D.2). We observed that standard training of CNNs on medium or high-pass Fourier-filtered data did not achieve high clean accuracies (Tables 2, 3). A model trained on medium-pass Fourier-filtered CIFAR10 achieved a clean accuracy of only ∼33% on clean test samples whereas the MSF-REGULARIZED model's clean accuracy is ∼87%, and a model trained on high-pass filtered CIFAR10 training samples achieved only ∼15% accuracy on clean test samples. Due to the energy statistics over frequency bands in natural images, training on Fourier-filtered data is not successful for all but the lowest frequency bands, where most of their energy resides. In addition, we note that regularizers such as ASF-regularization cannot be recreated by Fourier-filtering the training data due to the tendency of standard training to be sensitive to particular frequencies.

5 CONCLUSION

In this work, we proposed a novel and rigorous measure of the *spatial frequency sensitivity (SFS)* of any differentiable model using its input-Jacobian represented in the Fourier-basis. We showed that trained models display consistent *SFS* across samples as well as across architectures for a given task and when there is a shift in the Fourier-statistics of features in the data relative to a model's frequency sensitivity, performance can suffer. We also proposed a novel family of spatial frequency regularizers and showed that they that can modify the frequency characteristics of features they learn and these models are robust to many corruptions. We wish to further explore spatial frequency sensitivity as well as regularization of models in other domains and applications.

REFERENCES

Antonio A. Abello, Roberto Hirata, and Zhangyang Wang. Dissecting the High-Frequency Bias in Convolutional Neural Networks. In *Proceedings of the IEEE/CVF Conference on Computer Vision and Pattern Recognition*, pp. 863–871, 2021. URL `https://openaccess.thecvf.com/content/CVPR2021W/UG2/html/Abello_Dissecting_the_High-Frequency_Bias_in_Convolutional_Neural_Networks_CVPRW_2021_paper.html`.

F W Campbell and J G Robson. Application of Fourier analysis to the visibility of gratings. *The Journal of physiology*, 197(3):551–566, August 1968. ISSN 0022-3751. doi: 10.1113/jphysiol.1968.sp008574. URL `https://pubmed.ncbi.nlm.nih.gov/5666169`.

FW Campbell and JG Robson. Application of fourier analysis to modulation response of eye. In *Journal of the Optical Society of America*, volume 54, pp. 581, 1964. Issue: 4.

Alvin Chan, Yi Tay, Yew Soon Ong, and Jie Fu. Jacobian Adversarially Regularized Networks for Robustness. *arXiv:1912.10185 [cs]*, January 2020. URL `http://arxiv.org/abs/1912.10185`. arXiv: 1912.10185.

Wojciech M. Czarnecki, Simon Osindero, Max Jaderberg, Grzegorz Swirszcz, and Razvan Pascanu. Sobolev Training for Neural Networks. In I. Guyon, U. V. Luxburg, S. Bengio, H. Wallach, R. Fergus, S. Vishwanathan, and R. Garnett (eds.), *Advances in Neural Information Processing Systems*, volume 30. Curran Associates, Inc., 2017. URL `https://proceedings.neurips.cc/paper/2017/file/758a06618c69880a6cee5314ee42d52f-Paper.pdf`.

H. Drucker and Y. Le Cun. Double backpropagation increasing generalization performance. In *IJCNN-91-Seattle International Joint Conference on Neural Networks*, volume ii, pp. 145–150 vol.2, 1991. doi: 10.1109/IJCNN.1991.155328.

Logan Engstrom, Andrew Ilyas, Hadi Salman, Shibani Santurkar, and Dimitris Tsipras. Robustness (Python Library), 2019. URL `https://github.com/MadryLab/robustness`.

Robert Geirhos, Patricia Rubisch, Claudio Michaelis, Matthias Bethge, Felix A. Wichmann, and Wieland Brendel. ImageNet-trained CNNs are biased towards texture; increasing shape bias improves accuracy and robustness. *arXiv:1811.12231 [cs, q-bio, stat]*, January 2019. URL `http://arxiv.org/abs/1811.12231`. arXiv: 1811.12231.

Dan Hendrycks and Thomas Dietterich. Benchmarking Neural Network Robustness to Common Corruptions and Perturbations. *arXiv:1903.12261 [cs, stat]*, March 2019. URL `http://arxiv.org/abs/1903.12261`. arXiv: 1903.12261.

Dan Hendrycks, Norman Mu, Ekin D. Cubuk, Barret Zoph, Justin Gilmer, and Balaji Lakshminarayanan. AugMix: A Simple Data Processing Method to Improve Robustness and Uncertainty. *arXiv:1912.02781 [cs, stat]*, February 2020. URL `http://arxiv.org/abs/1912.02781`. arXiv: 1912.02781.

Judy Hoffman, Daniel A. Roberts, and Sho Yaida. Robust Learning with Jacobian Regularization. *arXiv:1908.02729 [cs, stat]*, August 2019. URL `http://arxiv.org/abs/1908.02729`. arXiv: 1908.02729.

Aapo Hyvärinen, Jarmo Hurri, and Patrick O. Hoyer. *Natural Image Statistics: A Probabilistic Approach to Early Computational Vision.* Springer Publishing Company, Incorporated, 1st edition, 2009. ISBN 1-84882-490-4.

Daniel Jakubovitz and Raja Giryes. Improving DNN Robustness to Adversarial Attacks using Jacobian Regularization. In *Proceedings of the European Conference on Computer Vision (ECCV)*, September 2018.

Jason Jo and Yoshua Bengio. Measuring the tendency of CNNs to Learn Surface Statistical Regularities. *arXiv:1711.11561 [cs, stat]*, November 2017. URL `http://arxiv.org/abs/1711.11561`. arXiv: 1711.11561.

B. Julesz and T. V. Papathomas. On spatial-frequency channels and attention. *Perception & psychophysics*, 36(4):398–399, October 1984. ISSN 0031-5117. doi: 10.3758/bf03202795. Place: United States.

Louise Kauffmann, Stephen Ramanoël, and Carole Peyrin. The neural bases of spatial frequency processing during scene perception. *Frontiers in integrative neuroscience*, 8:37, 2014. ISSN 1662-5145. doi: 10.3389/fnint.2014.00037.

Aleksander Madry, Aleksandar Makelov, Ludwig Schmidt, Dimitris Tsipras, and Adrian Vladu. Towards Deep Learning Models Resistant to Adversarial Attacks. In *International Conference on Learning Representations*, 2018. URL `https://openreview.net/forum?id=rJzIBfZAb`.

Chaithanya Kumar Mummadi, Ranjitha Subramaniam, Robin Hutmacher, Julien Vitay, Volker Fischer, and Jan Hendrik Metzen. Does enhanced shape bias improve neural network robustness to common corruptions? In *International Conference on Learning Representations*, 2021. URL `https://openreview.net/forum?id=yUxUNaj2Sl`.

Guillermo Ortiz-Jimenez, Apostolos Modas, Seyed-Mohsen Moosavi-Dezfooli, and Pascal Frossard. Hold me tight! Influence of discriminative features on deep network boundaries. *arXiv:2002.06349 [cs, stat]*, October 2020. URL `http://arxiv.org/abs/2002.06349`. arXiv: 2002.06349.

Andrew Slavin Ross and Finale Doshi-Velez. Improving the Adversarial Robustness and Interpretability of Deep Neural Networks by Regularizing their Input Gradients. In *AAAI*, 2018.

Pia Rotshtein, Andrew Schofield, María J. Funes, and Glyn W. Humphreys. Effects of spatial frequency bands on perceptual decision: it is not the stimuli but the comparison. *Journal of vision*, 10(10):25, August 2010. ISSN 1534-7362. doi: 10.1167/10.10.25. Place: United States.

Tonmoy Saikia, Cordelia Schmid, and Thomas Brox. Improving robustness against common corruptions with frequency biased models. *arXiv:2103.16241 [cs]*, March 2021. URL `http://arxiv.org/abs/2103.16241`. arXiv: 2103.16241.

P. G. Schyns and A. Oliva. Dr. Angry and Mr. Smile: when categorization flexibly modifies the perception of faces in rapid visual presentations. *Cognition*, 69(3):243–265, January 1999. ISSN 0010-0277. doi: 10.1016/s0010-0277(98)00069-9. Place: Netherlands.

Patrice Simard, Bernard Victorri, Yann LeCun, and John Denker. Tangent Prop - A formalism for specifying selected invariances in an adaptive network. In J. Moody, S. Hanson, and R. P. Lippmann (eds.), *Advances in Neural Information Processing Systems*, volume 4. Morgan-Kaufmann, 1992. URL `https://proceedings.neurips.cc/paper/1991/file/65658fde58ab3c2b6e5132a39fae7cb9-Paper.pdf`.

Yusuke Tsuzuku and Issei Sato. On the Structural Sensitivity of Deep Convolutional Networks to the Directions of Fourier Basis Functions. In *2019 IEEE/CVF Conference on Computer Vision and Pattern Recognition (CVPR)*, pp. 51–60, Long Beach, CA, USA, June 2019. IEEE. ISBN 978-1-72813-293-8. doi: 10.1109/CVPR.2019.00014. URL `https://ieeexplore.ieee.org/document/8954086/`.

Haohan Wang, Songwei Ge, Zachary Lipton, and Eric P Xing. Learning Robust Global Representations by Penalizing Local Predictive Power. In H. Wallach, H. Larochelle, A. Beygelzimer, F. d' Alché-Buc, E. Fox, and R. Garnett (eds.), *Advances in Neural Information Processing Systems*, volume 32. Curran Associates, Inc., 2019. URL `https://proceedings.neurips.cc/paper/2019/file/3eefceb8087e964f89c2d59e8a249915-Paper.pdf`.

Haohan Wang, Xindi Wu, Zeyi Huang, and Eric P. Xing. High-Frequency Component Helps Explain the Generalization of Convolutional Neural Networks. In *2020 IEEE/CVF Conference on Computer Vision and Pattern Recognition (CVPR)*, pp. 8681–8691, Seattle, WA, USA, June 2020. IEEE. ISBN 978-1-72817-168-5. doi: 10.1109/CVPR42600.2020.00871. URL `https://ieeexplore.ieee.org/document/9156428/`.

Dong Yin, Raphael Gontijo Lopes, Jonathon Shlens, Ekin D. Cubuk, and Justin Gilmer. A Fourier Perspective on Model Robustness in Computer Vision. In *Proceedings of the 33rd International Conference on Neural Information Processing Systems*. Curran Associates Inc., Red Hook, NY, USA, 2019.

Tianyuan Zhang and Zhanxing Zhu. Interpreting Adversarially Trained Convolutional Neural Networks. *arXiv:1905.09797 [cs, stat]*, May 2019. URL `http://arxiv.org/abs/1905.09797`. arXiv: 1905.09797.

APPENDICES

A SPATIAL FREQUENCY SENSITIVITY AND REGULARIZER

A.1 PSEUDO-CODES

Algorithm 1: Spatial Frequency Sensitivity (SFS)

Input: Labeled samples $\mathbf{L} = \{(x_i, y_i)\}_{i=1}^n$; a model f with trained parameters θ
Output: Estimated Spatial Frequency Sensitivity of model, $f_{SFS}(\cdot; \theta)$

for $i = 1, \ldots, n$ **do**

    compute loss $\mathcal{L}_{\text{CE}}(f(x_i), y_i)$ // `forward pass`

    backpropagate $\mathcal{L}_{\text{CE}}$ to obtain $\frac{\partial \mathcal{L}_{\text{CE}}}{\partial x_i}$ // `input-jacobian`

    $\frac{\partial \mathcal{L}_{\text{CE}}}{\partial x_{f_i}} = \mathcal{F}(\frac{\partial \mathcal{L}_{\text{CE}}}{\partial x_i})$ // `2D DFT of input-jacobian (averaged across`
    `color channels)`

    $f_{SFS}(x_i, y_i) = [P_k; \text{for k=1 to N}/\sqrt{2}]$ // `P_k is proportion of total power`
    `(excluding DC) in coefficients at radial distance k`

end
$f_{SFS}(\cdot; \theta) = \frac{1}{n} \sum_{i=1}^n f_{SFS}(x_i, y_i)$ // `estimated SFS of model`

Algorithm 2: Spatial Frequency Regularized Minibatch Training

---

Input: Labeled samples $\mathbf{L} = \{(x_i, y_i)\}_{i=1}^n$; a model f with parameters θ; SFS $\in$
    $\{LSF, MSF, ASF\}$; hyperparameter λ_{SFS}
Output: Regularized model with updated parameters θ

for $i = 1, \ldots, n$ **do**

    compute loss $\mathcal{L}_{\text{CE}}(f(x_i), y_i)$ // `forward pass`

    $\mathcal{L}(x_i, y_i) = \mathcal{L}_{\text{CE}}(x_i, y_i) + \lambda_{\text{SFS}}\mathcal{L}_{\text{SFS}}(x_i, y_i)$ // `backpropagate L to update θ`

end

Figure 4: a) Illustration of the power-matrix P of the Fourier-transformed input-Jacobian. P_{Total}, the power in all components excluding the zero-frequency component is used to normalize the proposed SFS of the model at a particular input. b) LSF (purple), MSF (blue) and ASF (purple, blue and green) frequency bands used for spatial frequency regularization. Best viewed in color.

B SPATIAL FREQUENCY CHANNELS IN THE BRAIN

To further motivate the spatial frequency perspective of visual representation learning, we briefly describe some relevant findings from neuroscience and vision research. While the brain does not strictly perform a Fourier analysis of visual scenes, there has been mounting evidence over decades for multiple spatial frequency channels in the early human visual system that are physiologically independent and selectively responsive to distinct spatial frequency bands (Campbell & Robson, 1964; 1968). It has been posited that the use of different spatial frequency channels are determined by the demands of a given visual task through an attention mechanism (Schyns & Oliva, 1999; Rotshtein et al., 2010; Julesz & Papathomas, 1984). Spatial frequency channels enable us to attend to different spatial scales in a scene at a fixed viewing distance, similar to the focus lens in a camera (Figure 5). On the other hand, once trained, a CNN's *spatial frequency sensitivity* (Section 3.2) is inflexible and does not vary much across samples (both in and out of its training data distribution).

```
EFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEF
EFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEF
EFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEF
EFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEF
EFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEF
EFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEF
EFEFEFEFEFEFononononononononononononoEFEFEFEFEF
EFEFEFEFEFononononononononononononoEFEFEFEFEF
EFEFEFEFEFononononononononononononoEFEFEFEFEF
EFEFEFEFEFononononononononononononoEFEFEFEFEF
EFEFEFEFEFononononononononononononoEFEFEFEFEF
EFEFEFEFEFEFEFEFEFEononononEFEFEFEFEFEFEFEFE
EFEFEFEFEFEFEFEFEFEononononEFEFEFEFEFEFEFEFE
EFEFEFEFEFEFEFEFEFEononononEFEFEFEFEFEFEFEFE
EFEFEFEFEFEFEFEFEFEononononEFEFEFEFEFEFEFEFE
EFEFEFEFEFEFEFEFEFEononononEFEFEFEFEFEFEFEFE
EFEFEFEFEFEFEFEFEFEononononEFEFEFEFEFEFEFEFE
EFEFEFEFEFEFEFEFEFEononononEFEFEFEFEFEFEFEFE
EFEFEFEFEFEFEFEFEFEononononEFEFEFEFEFEFEFEFE
EFEFEFEFEFEFEFEFEFEononononEFEFEFEFEFEFEFEFE
EFEFEFEFEFEFEFEFEFEononononEFEFEFEFEFEFEFEFE
EFEFEFEFEFEFEFEFEFEononononEFEFEFEFEFEFEFEFE
EFEFEFEFEFEFEFEFEFEononononEFEFEFEFEFEFEFEFE
EFEFEFEFEFEFEFEFEFEononononEFEFEFEFEFEFEFEFE
EFEFEFEFEFEFEFEFEFEononononEFEFEFEFEFEFEFEFE
EFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEF
EFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEF
EFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEF
EFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEF
EFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEFEF
```

Figure 5: Letters at multiple spatial scales. This image comprises the letters o, n, E and F at a small spatial scale (HSF). The letter T is also visible at a larger spatial scale (LSF) formed by the specific arrangement of the letters o, n amidst letters E, F. Identifying these letters requires processing features at multiple scales, enabled by distinct spatial frequency channels in early visual cortex. Our ability to recognize only one of these scales at a time is evidence for the independence of spatial frequency channels in the brain. Image based on Julesz & Papathomas (1984).

C SUPPLEMENTARY PLOTS

C.1 SPATIAL FREQUENCY SENSITIVITIES OF POPULAR IMAGENET MODELS

Figure 6: Spatial frequency sensitivities of popular ImageNet architectures after standard training and adversarial training using PGD-ℓ_2 ($\epsilon = 3$) attacks. The *SFS* is consistent across architectures for both standard and adversarially trained models although VGG16 shows increased sensitivity to high frequencies. The shaded region represents two standard deviations.

C.2 SPATIAL FREQUENCY SENSITIVITIES OF MODELS TRAINED ON CIFAR10 AND CIFAR100

Figure 7: Various methods trained on CIFAR10 (left) and CIFAR100 (right). The shaded region represents two standard deviations.

C.3 TRAINING ON CIFAR10 CORRUPTIONS

Figure 8: *Spatial frequency sensitivities* of ResNet50 models trained on the CIFAR10 training set distorted by corruptions derived from the CIFAR10-C (severity 5) dataset. The shaded region represents two standard deviations.

D FOURIER FILTERING

D.1 RADIAL FILTERING

Figure 9: First image in each row is the mask in Fourier space (lowest frequency at centre). White pixels preserve and black pixels set Fourier components to zero. Top row are original CIFAR10 images, other rows are Fourier-filtered with different radial masks.

D.2 BAND-PASS FILTERING

Figure 10: For band-pass Fourier-filtering CIFAR10 training images, we filtered Fourier-coefficients in each color channel separately. For low-pass filtering, Fourier-coefficients with radial distance $r(u,v) > 5$ were set to zero. For medium-pass filtering, Fourier-coefficients with $r(u,v) < 5$ and $r(u,v) > 10$ were set to zero. In high-pass filtering, Fourier-coefficients with $r(u,v) < 10$ were set to zero. Images contast-maximised for viewing.

E CORRUPTION EXAMPLES FROM HENDRYCKS & DIETTERICH (2019)

Figure 11: Examples of image corruptions curated by Hendrycks & Dietterich (2019) to evaluate robustness of vision models.

F PATCH-SHUFFLING IMAGES

Figure 12: Patch-shuffling: Images are partitioned into squares whose positions are randomly exchanged. This operation destroys global structure in the image and is used to evaluate the extent to which a model relies on global information.