On Optimal Interpolation in Linear Regression

Abstract

Understanding when and why interpolating methods generalize well has recently
been a topic of interest in statistical learning theory. However, systematically
connecting interpolating methods to achievable notions of optimality has only
received partial attention. In this paper, we ask the question of what is the optimal
way to interpolate in linear regression using functions that are linear in the response
variable (as the case for the Bayes optimal estimator in ridge regression) and depend
on the data, the population covariance of the data, the signal-to-noise ratio and the
covariance of the prior for the signal, but do not depend on the value of the signal
itself nor the noise vector in the training data. We provide a closed-form expression
for the interpolator that achieves this notion of optimality and show that it can be
derived as the limit of preconditioned gradient descent with a specific initialization.
We identify a regime where the minimum-norm interpolator provably generalizes
arbitrarily worse than the optimal response-linear achievable interpolator that we
introduce, and validate with numerical experiments that the notion of optimality
we consider can be achieved by interpolating methods that only use the training
data as input in the case of an isotropic prior. Finally, we extend the notion of
optimal response-linear interpolation to random features regression under a linear
data-generating model.

1 Introduction

Establishing mathematical understanding for the good generalization properties of interpolating
methods, i.e. methods that fit the training data perfectly, has attracted significant interest in recent
years. Motivated by the quest to explain the generalization performance of neural networks which
have zero training error, for example even on randomly corrupted data (Zhang et al., 2017), this area
of research has established results for a variety of models. For instance, in kernel regression, Liang
and Rakhlin (2020) provide a data-dependent upper bound on the generalization performance of the
minimum-norm interpolator. By analyzing the upper bound, they show that small generalization
error of the minimum-norm interpolator occurs in a regime with favourable curvature of the kernel,
particular decay of the eigenvalues of the kernel and data population covariance matrices and,
importantly, in an overparametrized setting. In random features regression, Mei and Montanari (2019)
showed that for large signal-to-noise ratio, in the limit of large overparametrization, the optimal
regularization is zero – i.e. the optimal ridge regressor is an interpolator. Liang and Sur (2020)
characterized the precise high-dimensional asymptotic generalization of interpolating minimum-
ℓ_1-norm classifiers and boosting algorithms which maximize the ℓ_1 margin. Bartlett et al. (2020)
isolated a setting of benign overfitting in linear regression, dependent on notions of effective rank of
the population covariance matrix, in which the minimum-norm interpolator has small generalization
error. Similarly, this regime of benign overfitting occurs with large overparametrization.

Linear models, in particular, provide a fundamental playground to understand interpolators. On
the one hand, in overparametrized regimes, interpolators in linear models are seen to reproduce

stylized phenomena observed in more general models. For example, the double descent phenomenon, which was first empirically observed in neural networks (Belkin et al., 2019), has also featured in linear regression (Hastie et al., 2019). On the other hand, neural networks are known to be well-approximated by linear models in some regimes. For example, with specific initialization and sufficient overparametrization, two-layer neural networks trained with gradient descent methods are well-approximated by a first-order Taylor expansion around their initialization (Chizat et al., 2019). This linear approximation can be split into a random features component and a neural-tangent component. The random features model – a two-layer neural network with randomly initialized first layer which is fixed during training, shares similar generalization behavior with the full neural network (Bartlett et al., 2021), and as such, the random features model provides a natural stepping stone towards tackling a theoretical understanding of neural networks.

A major focus of the interpolation literature has so far been to theoretically study if and when interpolating methods based on classical techniques such as ridge regression and gradient descent can have optimal or near-optimal generalization (Bartlett, Montanari, and Rakhlin, 2021). However the question of understanding which interpolators are best, and designing data-dependent schemes to implement them, seems to have received only partial attention. Work investigating which interpolators are optimal in linear regression includes Muthukumar et al. (2019), where the authors constructed the best-possible interpolator, i.e. a theoretical device which uses knowledge of the true parameter and training noise vector to establish a fundamental limit on how well *any* interpolator in linear regression can generalize, which is shown to be small only in the regime of large overparametrization. While this interpolator provides the best-possible generalization error, the interpolator is not implementable in general, as one would need access to the realization of the true data-generating parameter $w^\star$ and the realization of the noise in the training data. Rangamani et al. (2020) studied generalization of interpolators in linear regression and showed that the minimum-norm interpolator minimizes an *upper* bound on the generalization error related to stability. In (Mourtada, 2020) it was shown that the minimum-norm interpolator is minimax optimal for every distribution of the covariates. In (Amari et al., 2021), the authors computed the asymptotic risk of interpolating preconditioned gradient descent in linear regression and investigated the role of its implicit bias on generalization. In particular, they identified the preconditioning which leads to optimal asymptotic (as $d/n \to \gamma > 1$ with $n, d \to \infty$) bias and variance, *separately*, among interpolators of the form $w = PX^T(XPX^T)^{-1}y$ for some matrix P, where $X \in \mathbb{R}^{n \times d}$ is the data matrix, $y \in \mathbb{R}^n$ is the response vector and n, d are the size and dimension of the data, respectively. They showed that, within this class of interpolators, using the inverse of the population covariance of the data as preconditioning achieves optimal asymptotic variance. However, the interpolator with optimal risk is not given.

In this paper, we study the question of what is the optimal way to interpolate in overparametrized linear regression by procedures that do not use the realization of the true parameter generating the data, nor the realization of the training noise. The motivation for studying this question is twofold. First, in designing new ways to interpolate that are directly related to notions of optimality, we hope to provide a stepping stone to designing new ways to interpolate in more complex models, such as neural networks. Second, our results illustrate that there can be arbitrarily large differences in the generalization performance of different interpolators, in particular considering the minimum-norm interpolator as a benchmark. This is a phenomenon that does not seem to have received close attention in the literature and may spark new interest in designing optimal interpolators.

We consider the family of interpolators that can be achieved as an arbitrary function f of the data, population covariance, signal-to-noise ratio and the prior covariance such that f is linear in the response variable y (as the case for the Bayes optimal estimator in ridge regression). We call such interpolators *response-linear achievable* (see Definition 5). We also introduce a natural notion of optimality that assumes that the realization of true data-generating parameter and the realization of the noise in the training data are unknown. In this class of interpolators and under this notion of optimality, we theoretically compute the optimal interpolator and show that this interpolator is achieved as the implicit bias of a preconditioned gradient descent with proper initialization. We refer to this interpolator as the *optimal response-linear achievable interpolator*.

Could it be that the commonly used minimum-norm interpolator is good enough so that the benefit of finding a better interpolator is negligible? We illustrate that the answer to this question is no. In particular, we construct an example in linear regression where the minimum-norm interpolator has arbitrarily worse generalization than the optimal response-linear achievable interpolator. Here, the variance (hence also generalization error) of the minimum-norm interpolator diverges to infinity as a

function of the eigenvalues of the population covariance matrix, while the generalization error of the optimal response-linear achievable interpolator stays bounded, close to the optimal interpolator, i.e. the theoretical device of (Muthukumar et al., 2019) which uses the true value of the signal and noise.

The optimal response-linear achievable interpolator uses knowledge of the population covariance matrix of the data (similarly as in Amari et al. (2021)), the signal-to-noise ratio, and the covariance of the true parameter (on which we place a prior distribution). Is it the case that the better performance of our interpolator is simply a consequence of this additional knowledge? We provide numerical evidence that shows that the answer to this question is, in general, no. In particular, we construct an algorithm to approximate the optimal response-linear achievable interpolator which does not require any prior knowledge of the population covariance or the signal-to-noise ratio and uses only the training data X and y, and we empirically observe that this new interpolator generalizes in a nearly identical way to the optimal response-linear achievable interpolator. We present a simulation study that validates our theoretical findings.

Finally, we show that the concept of optimal response-linear achievable interpolation can be extended to more complex models by providing analogous results for a random features model under the same linear data-generating regime (as also considered in (Mei and Montanari, 2019), for instance). As discussed, the random features model provides a stepping stone towards understanding neural networks and hence our results point towards a possible avenue for designing new methods of interpolation which are connected to notions of optimality.

2 Problem setup

In this paper we investigate overparametrized linear regression. We assume there exists $w^\star \in \mathbb{R}^d$ (unknown) so that $y = \langle w^\star, x_i \rangle + \xi_i$ for $i \in \{1, \ldots, n\}$, with Gaussian noise $\xi \sim \mathcal{N}(0, \sigma^2 I_n)$ and independent and identically distributed Gaussian features $x_i \sim \mathcal{N}(0, \Sigma)$ for a positive definite covariance matrix Σ. Here $I_n \in \mathbb{R}^{n \times n}$ is the identity matrix. We store the features in a random matrix $X \in \mathbb{R}^{n \times d}$ with rows $x_i \in \mathbb{R}^d$, and the response variable in a random vector $y \in \mathbb{R}^n$ with entries $y_i \in \mathbb{R}$. We consider the whitened data matrix $Z = X\Sigma^{-\frac{1}{2}} \in \mathbb{R}^{n \times d}$, whose rows satisfy $\mathbb{E}(z_i z_i^T) = I_d$. We place a prior on the true parameter in the form $w^\star \sim \mathcal{N}(0, \frac{r^2}{d}\Phi)$, where Φ is a positive definite covariance matrix and r^2 is the signal. We also define the signal-to-noise ratio $\delta = r^2/\sigma^2$ and consider the squared error loss $\ell : (x, y) \in \mathbb{R}^2 \mapsto (x - y)^2$. Our goal is to minimize the population risk,

$$r(w) = \mathbb{E}((\langle w, \widetilde{x} \rangle - \widetilde{y})^2 | X, \xi, w^\star),$$

or, equivalently, the excess risk $r(w) - r(w^\star)$. Here, $(\widetilde{x}, \widetilde{y})$ is a random variable which follows the distribution of $(x_1, y_1), \ldots, (x_n, y_n)$ and is independent of them. The population risk satisfies

$$r(w) = (w - w^\star)^T \Sigma (w - w^\star) + \sigma^2 = \|w - w^\star\|_\Sigma^2 + r(w^\star). \tag{1}$$

For any estimator $w \in \mathbb{R}^d$, we define its bias and variance by the decomposition

$$\mathbb{E}_{\xi, w^\star} r(w) = B(w) + V(w), \tag{2}$$

where

$$B(w) = \mathbb{E}_{\xi, w^\star} \|\mathbb{E}(w | w^\star, X) - w^\star\|_\Sigma^2 \qquad V(w) = \mathbb{E}_{\xi, w^\star} \|w - \mathbb{E}(w | w^\star, X)\|_\Sigma^2. \tag{3}$$

The population risk is often impossible to minimize directly. The usual approach is to instead minimize the empirical risk $R(w) = \frac{1}{n} \sum_{i=1}^n (\langle w, x_i \rangle - y)^2 = \frac{1}{n} \sum_{i=1}^n \ell(w^T x_i, y)$ (Vapnik, 1995). In linear regression, minimizing the empirical risk is equivalent to finding $w \in \mathbb{R}^d$ such that $Xw = y$.

2.1 Random matrix theory concepts

Definition 1. For a symmetric matrix $\Sigma \in \mathbb{R}^{d \times d}$ with eigenvalues $\lambda_1 \geq \lambda_2 \geq \cdots \geq \lambda_d \geq 0$ we define its spectral distribution by $\mathcal{F}_\Sigma(x) = \frac{1}{d} \sum_{i=1}^d \mathbb{1}_{[\lambda_i, \infty)}(x)$.

The following assumptions will be occasionally considered for the covariance matrix Σ.

Assumption 1. There exists $k_{\max} > 0$ such that $\lambda_{\max}(\Sigma) \leq k_{\max}$ uniformly for $d \in \mathbb{N}$.

138 **Assumption 2.** There exists $k_{\min} > 0$ such that $k_{\min} \le \lambda_{\min}(\Sigma)$ uniformly for $d \in \mathbb{N}$.

139 **Assumption 3.** The spectral distribution $\mathcal{F}_\Sigma$ of the covariance matrix Σ converges weakly to a
140 distribution $\mathcal{H}$ supported on $[0, \infty)$.

141 Marčenko and Pastur (1967) showed that there exists a distribution $\widetilde{\mathcal{F}}_\gamma$ such that $\mathcal{F}_{\frac{Z^T Z}{n}} \longrightarrow \widetilde{\mathcal{F}}_\gamma$,
142 weakly, with probability 1 as $n \to \infty, d \to \infty$ with $d/n \to \gamma$. In our discussion, $x_i = \Sigma^{\frac{1}{2}} z_i$, where
143 $z_i \sim \mathcal{N}(0, I_d)$ independently. Then, under Assumption 3, it can be shown that the spectral distribution
144 of $\widehat{\Sigma} = X^T X / n = \Sigma^{\frac{1}{2}} Z^T Z \Sigma^{\frac{1}{2}} / n$ converges weakly, with probability 1 to a distribution supported
145 on $[0, \infty)$, which we denote by F_γ (see e.g. (Silverstein and Choi, 1995)). Similar arguments also
146 show that the spectral distribution of $X X^T / n \in \mathbb{R}^{n \times n}$ converges weakly, with probability 1.

147 **Definition 2.** For a distribution $\mathcal{F}$ supported on $[0, \infty)$, we define the Stieltjes transform of $\mathcal{F}$, for
148 any $z \in \mathbb{C} \setminus \mathbb{R}^+$ by

$$m_{\mathcal{F}}(z) = \int_0^\infty \frac{1}{\lambda - z} d\mathcal{F}(\lambda).$$

149 The weak convergence of the spectral distribution of $\widehat{\Sigma}$ to $\mathcal{F}_\gamma$ is equivalent to $m_{\widehat{\Sigma}}(z) \to m(z)$ and
150 $m_{X X^T / n}(z) \to v(z)$ almost surely for all $z \in \mathbb{C} \setminus \mathbb{R}^+$, where m and v are the Stieltjes transforms
151 of $\mathcal{F}_\gamma$ and the limiting spectral distribution of $X X^T / n$, respectively (see e.g. Proposition 2.2 of
152 (Hachem et al., 2007)). We call v the companion Stieltjes transform of $\mathcal{F}_\gamma$.

2.2 Interpolators

154 We define an interpolator to be any minimizer of the empirical risk and $\mathcal{G}$ to be the set of interpolators.
155 In linear regression we can write

$$\mathcal{G} = \{w \in \mathbb{R}^d : Xw = y\}.$$

156 Because $\operatorname{rank}(X) = n$ with probability 1, we have $\mathcal{G} \ne \emptyset$ with probability 1. We want to compare
157 interpolators which are implicit biases of optimization algorithms. In linear regression, the implicit
158 bias of gradient descent initialized at 0 is the minimum-norm interpolator (Gunasekar et al., 2018).
159 We define the minimum-norm interpolator by

$$w_{\ell_2} = \underset{\{w \in \mathbb{R}^d : Xw = y\}}{\arg\min} \|w\|_2^2 = X^\dagger y,$$

160 where $X^\dagger \in \mathbb{R}^{n \times d}$ is the Moore-Penrose pseudoinverse (Penrose, 1955). If $\operatorname{rank}(X) = n$, we
161 can also write $X^\dagger = X^T (X X^T)^{-1}$. The second interpolator of interest is a purely theoretical
162 device, previously used in (Muthukumar et al., 2019) to specify a fundamental limit to how well any
163 interpolator in linear regression can generalize.

164 **Definition 3.** The best possible interpolator is defined as

$$W_b = \underset{w \in \mathcal{G}}{\arg\min} \, r(w).$$

165 We can write

$$W_b = \underset{\{w \in \mathbb{R}^d : Xw = y\}}{\arg\min} \|\Sigma^{\frac{1}{2}}(w - w^\star)\|_2^2,$$

166 and after a linear transformation followed by the result of (Penrose, 1956), we obtain

$$W_b = w^\star + \Sigma^{-\frac{1}{2}}(X \Sigma^{-\frac{1}{2}})^\dagger \xi. \tag{4}$$

167 We notice that the best possible interpolator fits the signal perfectly by having access to the true
168 parameter $w^\star$ and fits the noise through the term $\Sigma^{-\frac{1}{2}}(X \Sigma^{-\frac{1}{2}})^\dagger \xi$ by having access to the noise vector
169 in the training data. While w_b is, by definition, the optimal interpolator, we cannot hope to achieve it
170 through an algorithm because it requires access to the unknown quantities $w^\star$ and ξ. We are interested
171 in interpolators which can be achieved by some algorithm using the data X and y.

172 **Definition 4.** We define an estimator $w \in \mathbb{R}^d$ to be achievable if there exists a function f such that
173 $w = f(X, y, \Sigma, \Phi, \delta)$.

In our definition of achievability, we allow for knowledge of the data covariance, the signal-to-noise ratio and the prior covariance, because we want to study what is the best performance we can achieve given access to this information. This best performance defines a fundamental limit to what we can achieve also without the knowledge of Σ, δ and Φ. We will then approximate (see Section 4.1) this fundamental limit without the knowledge of these unknown quantities and only with the knowledge of the training data X and y.

Definition 5. We define the set of response-linear achievable estimators by

$$\mathcal{L} = \{\, w \in \mathbb{R}^d : \exists f \text{ such that } w = f(X, y, \Sigma, \Phi, \delta) \text{ where } y \in \mathbb{R}^n \mapsto f(X, y, \Sigma, \Phi, \delta) \text{ is linear } \}.$$

Linearity of $y \in \mathbb{R}^n \mapsto f(X, y, \Sigma, \Phi, \delta)$ is equivalent to $f(X, y, \Sigma, \Phi, \delta) = g(X, \Sigma, \Phi, \delta)y$, where g is any function which has image in $\mathbb{R}^{d \times n}$. The notion of optimality that we introduce is that of the optimal response-linear achievable interpolator, which is the interpolator that minimizes the expected risk in the class $\mathcal{L}$.

Definition 6. We define the optimal response-linear achievable interpolator by

$$w_O = \operatorname*{arg\,min}_{w \in \mathcal{G} \cap \mathcal{L}} \mathbb{E}_{\xi, w^\star} r(w) - r(w^\star). \tag{5}$$

3 Main results

3.1 Optimal response-linear achievable interpolator

Proposition 1. The optimal response-linear achievable interpolator satisfies

$$w_O = \left(\frac{\delta}{d} \Phi X^T + \Sigma^{-\frac{1}{2}} (X \Sigma^{-\frac{1}{2}})^\dagger \right) \left(I_n + \frac{\delta}{d} X \Phi X^T \right)^{-1} y. \tag{6}$$

By definition, this interpolator has the smallest expected risk among all response-linear achievable interpolators. This result holds for a general prior covariance matrix Φ. However, for an isotropic prior $\Phi = I_d$, w_O depends only on the population covariance Σ and the signal-to-noise ratio δ so that w_O can be approximated using estimators of these quantities, which is what we do in Section 4.

One of the motivations to consider interpolators in $\mathcal{L}$, i.e. interpolators which are a linear function of y, is technical, to overcome difficulties in the proof of Proposition 1. Without the assumption that $y \in \mathbb{R}^n \mapsto f(X, y, \Sigma, \Phi, \delta)$ is linear, it seems significantly more difficult to compute the optimal achievable interpolator. Moreover, many standard estimators such as the minimum-norm interpolator $X^\dagger y$ or any ridge-regressor $w_\lambda = (X^T X + \lambda I_d)^{-1} X^T y$, are linear functions of y.

Proposition 2. The optimal response-linear achievable interpolator is the limit of preconditioned gradient descent

$$w_{t+1} = w_t - \eta_t \Sigma^{-1} \nabla R(w_t), \tag{7}$$

provided that the algorithm converges, initialized at

$$w_0 = \frac{\delta}{d} \Phi X^T \left(I_n + \frac{\delta}{d} X \Phi X^T \right)^{-1} y. \tag{8}$$

The interpolator w_O does not have the smallest bias or the smallest variance in the bias variance decomposition $\mathbb{E}_{\xi, w^\star} r(w) = B(w) + V(w)$, but rather achieves a balance. We are also interested in studying the interpolators which have optimal bias and optimal variance separately and compare them to the optimal response-linear achievable interpolator. Lemma 1 shows that the preconditioned gradient descent (7) achieves optimal variance among all interpolators when initialized at any deterministic w_0. This is an extension of the result of (Amari et al., 2021). They show that the limit of $w_{t+1} = w_t - \eta_t \Sigma^{-1} \nabla R(w_t)$ achieves optimal asymptotic variance in the limit as $d, n \to \infty$ with $\frac{d}{n} \to \gamma > 1$ among interpolators of the form $w = PX^T (XPX^T)^{-1} y$ for some matrix P (and under assumptions of convergence of a spectral measure). Lemma 1 extends this statement about achieving optimal variance to the class of all interpolators, to any deterministic initialization w_0 of the algorithm and is non-asymptotic (i.e. holds for finite $n, d \in \mathbb{N}$).

Lemma 1. The limit of preconditioned gradient descent $w_{t+1} = w_t - \eta_t \Sigma^{-1} \nabla R(w_t)$ initialized at any deterministic $w_0 \in \mathbb{R}^d$, provided that it converges, satisfies that

$$\lim_{t \to \infty} w_t = \arg\min_{w \in \mathcal{G}} V(w). \tag{9}$$

We note that the optimal variance is achieved among all interpolators, not only among response-linear achievable interpolators.

A natural question to ask is whether the optimal response-linear achievable interpolator (6) provides a significant benefit compared to other interpolators. A second question is whether we can successfully approximate the optimal response-linear achievable interpolator without knowledge of the population covariance Σ and the signal-to-noise ratio δ. In the following section, we illustrate that both the interpolator with optimal variance and the interpolator with optimal bias (the minimum-norm interpolator in this particular case) can generalize arbitrarily badly in comparison to w_O. In the same regimes where this happens, we present numerical evidence that we can successfully approximate w_O by an empirical interpolator w_{Oe} without any prior knowledge of Σ or δ by using the Graphical Lasso estimator (Friedman et al., 2007) of the covariance matrix Σ and choosing the empirical estimate of δ by crossvalidation on a subset of the data. We do this in the regime of an isotropic prior $\Phi = I_d$.

4   Comparison of interpolators

First, we present an example where the minimum-norm interpolator w_{ℓ_2} generalizes arbitrarily worse than the best response-linear achievable interpolator w_O. Second, we give an example where an interpolator with optimal variance generalizes arbitrarily worse than w_O. Using $w_0 = 0$ in Lemma 1, we choose the interpolator with optimal variance to be (see supplementary material)

$$w_V = \Sigma^{-\frac{1}{2}} (X \Sigma^{-\frac{1}{2}})^\dagger y. \tag{10}$$

First, we discuss approximating w_O by an interpolator, w_{Oe}, which uses only the data X and y.

4.1   Empirical approximation

The interpolators w_O and w_V are limits of the algorithm

$$w_{t+1} = w_t - \eta_t \Sigma^{-1} \nabla R(w_t) \tag{11}$$

with respect to different initializations. The population covariance Σ is required to run this algorithm. However, the matrix Σ is usually unknown in practice. One may want to estimate Σ, however, replacing Σ by $\widetilde{\Sigma} = X^T X / n + \lambda I_d$ with any $\lambda \geq 0$ in (11) recovers exactly the same implicit bias as gradient descent. This is because one can check using the singular value decomposition of X that

$$\widetilde{\Sigma}^{-\frac{1}{2}} (X \widetilde{\Sigma}^{-\frac{1}{2}})^\dagger y = X^\dagger y.$$

The preconditioned gradient update needs to "escape" $\text{Im}(X^T)$ to get a different implicit bias. Hence, using $\widetilde{\Sigma} = X^T X / n + \lambda I_d$ (or, for example, also the Ledoit-Wolf shrinkage approximation (Ledoit and Wolf, 2004)) in preconditioned gradient descent removes the benefit of preconditioning.

We use the Graphical Lasso approximation (Friedman et al., 2007). We empirically observe that in the considered examples (here and in the supplementary material), using the Graphical Lasso covariance Σ_e instead of Σ has nearly no effect on generalization. Under specific assumptions, Ravikumar et al. (2011) provide some convergence guarantees of the Graphical Lasso.

In regards to approximating the signal-to-noise ratio δ, we choose δ_e that minimizes the crossvalidated error on random subsets of the data. In this way, we arrive at the interpolator

$$w_{Oe} = \left(\frac{\delta_e}{d} X^T + \Sigma_e^{-\frac{1}{2}} (X \Sigma_e^{-\frac{1}{2}})^\dagger \right) \left(I_n + \frac{\delta_e}{d} X X^T \right)^{-1} y,$$

which approximates w_O and is a function of only X and y. We note that this interpolator uses I_d as the prior covariance matrix.

In the experiments in Figures 1 and 2, we used the Graphical Lasso implementation of scikit-learn (Pedregosa et al., 2011) with parameter $\alpha = 0.25$ (α can also be crossvalidated for even better performance) and in estimating δ, for each δ_e in $\{0.1, 0.2, \ldots, 1, 2, \ldots, 10\}$, we computed the validation error on a random, unseen tenth of the data and averaged over 10 times. The δ_e with smallest crossvalidated error was chosen.

4.2 Diverging variance of interpolator with optimal bias

When $\Phi = I_d$, the interpolator with best bias among response-linear achievable interpolators is the minimum-norm interpolator (see supplementary material). We identify an example where the minimum-norm interpolator w_{ℓ_2} generalizes arbitrarily worse than the best response-linear achievable interpolator w_O. For this, we exploit results of Hastie et al. (2019) on computing the asymptotic risk of the minimum-norm interpolator. They show that if $\Phi = I_d$, under Assumptions 1, 2, 3 and if $\frac{d}{n} \to \gamma > 1$ with $n \to \infty, d \to \infty$ then with probability 1,

$$\mathbb{E}_{\xi,w^\star} r(w_{\ell_2}) - r(w^\star) \longrightarrow \frac{r^2}{\gamma v(0)} + \sigma^2 (\frac{v'(0)}{v(0)^2} - 1), \tag{12}$$

where v is the companion Stieltjes transform introduced in Section 2.1. In comparison, similarly as in (Amari et al., 2021), the asymptotic risk of the best variance estimator w_V satisfies that under Assumption 1 and 3, if $n, d \to \infty$ with $\frac{d}{n} \to \gamma > 1$ then with probability 1 we have that

$$\lim_{d \to \infty} \mathbb{E}_{\xi,w^\star} r(w_V) - r(w^\star) = r^2 \frac{\gamma - 1}{\gamma} \int_0^\infty s \, d\mathcal{H}(s) + \frac{\sigma^2}{\gamma - 1}, \tag{13}$$

An alternative way is to write $\int_0^\infty s \, d\mathcal{H}(s) = \lim_{d \to \infty} \operatorname{Tr}(\Sigma)$. This result follows by an application of Theorem 1 of (Rubio and Mestre, 2011), which is in the supplementary material for completeness.

Now we find a regime of covariance matrices Σ, for which the variance term of the minimum-norm solution, $V_{\ell_2} = \sigma^2(\frac{v'(0)}{v(0)^2} - 1)$, diverges to infinity, while the risk of w_O stays bounded and close to optimal. For this, we consider a generalization of the spike model of covariance matrices (Baik and Silverstein, 2006; Johnstone, 2001), which is a fundamental model in statistics. Here $\Sigma = \operatorname{diag}(\rho_1, \ldots, \rho_1, \rho_2, \ldots, \rho_2) \in \mathbb{R}^{d \times d}$, where the number of ρ_1s is $d \cdot \psi_1$ with $\psi_1 \in [0, 1]$. This model was also considered in (Richards et al., 2021) where it is called the strong weak features model. In this regime, it is possible to explicitly calculate the companion Stieltjes transform $v(0)$ and $v'(0)$ of (12). In the case that $\gamma = 2, \psi_1 = 1/2$ we have

$$V_{\ell_2} = \sigma^2(\frac{v'(0)}{v(0)^2} - 1) = \frac{\sigma^2}{2}(\sqrt{\frac{\rho_1}{\rho_2}} + \sqrt{\frac{\rho_2}{\rho_1}} + 2). \tag{14}$$

If we fix $\rho_1 = 1$ and take $\rho_2 \to 0$, then the variance term V_{ℓ_2} diverges to infinity. This also means that the asymptotic risk of the minimum-norm interpolator diverges to infinity. Moreover, the asymptotic risk of w_V in (13) evaluates to

$$\lim_{d \to \infty} \mathbb{E}_{\xi,w^\star} r(w_V) - r(w^\star) = (\psi_1 \rho_1 + (1 - \psi_1)\rho_2)(1 - \frac{1}{\gamma}) + \frac{\sigma^2}{\gamma - 1}. \tag{15}$$

In addition, by construction of w_O, we know that $\mathbb{E}_{\xi,w^\star} r(w_O) \leq \mathbb{E}_{\xi,w^\star} r(w_V)$ and therefore the asymptotic limit of $\mathbb{E}_{\xi,w^\star} r(w_O) - r(w^\star)$, as $d/n \to \gamma > 1$, stays bounded by (15) as $\rho_2 \to 0$. The expected generalization error in the setting described above is illustrated in Figure 1.

Figure 1: Plot of $\mathbb{E}_\xi r(w)$ (points) for $w \in \{w_{\ell_2}, w_V, w_O, w_{Oe}, w_b\}$ along with predictions (crosses) from (13) and (12) in the strong weak features model with $r^2 = 1, \sigma^2 = 1, \gamma = 2, \psi_1 = 1/2, n = 3000$ and $\rho_1 = 1, \rho_2 \to 0$.

Figure 2: Plot of $\mathbb{E}_\xi r(w)$ (points) for $w \in \{w_{\ell_2}, w_V, w_O, w_{Oe}, w_b\}$ along with predictions (crosses) from (13) and (12) in the strong weak features model with $r^2 = 1, \sigma^2 = 1, \gamma = 2, \psi_1 = 1/2, n = 3000$ and $\rho_2 = 1, \rho_1 \to \infty$.

280 We note that the fully empirical estimator w_{Oe} (yellow dots), which is a function of only the training
281 data X and y and does not use the population covariance Σ or the signal-to-noise ratio δ, performs
282 almost identically to the optimal response-linear achievable interpolator w_O (light blue dots).

283 In this example, we chose $\gamma = 2$ and $\psi_1 = 1/2$ deliberately. One does not achieve diverging variance
284 for an arbitrary choice of γ and ψ_1. However, for any $\gamma > 1$ such that $\gamma\psi_1 = 1$, the phenomenon of
285 Figure 1 holds (see supplementary material).

4.3 Diverging bias of interpolator with optimal variance

287 Now, we illustrate a regime where the best variance interpolator w_V generalizes arbitrarily worse
288 than w_O. In the same strong and weak features covariance model described above in Section 4.2,
289 when $\gamma = 2$ and $\psi_1 = 1/2$, if we instead have $\rho_1 \to \infty$ and $\rho_2 = 1$, then the asymptotic risk (15)
290 diverges to infinity linearly. However, the variance of the minimum-norm interpolator in (14) diverges
291 only like $\sqrt{\rho_1}$. Moreover, the bias term satisfies

$$B_{\ell_2} = \frac{r^2}{\gamma v(0)} = \frac{r^2}{\gamma}\sqrt{\rho_1\rho_2},$$

292 which also diverges only like $\sqrt{\rho_1}$. Now, because $\mathbb{E}_{\xi,w^\star}r(w_O) \le \mathbb{E}_{\xi,w^\star}r(w_{\ell_2})$, we have that

$$\lim_{d\to\infty}\mathbb{E}_{\xi,w^\star}r(w_O) \le \frac{r^2}{\gamma}\sqrt{\rho_1\rho_2} + \frac{\sigma^2}{2}\left(\sqrt{\frac{\rho_1}{\rho_2}} + \sqrt{\frac{\rho_2}{\rho_1}} + 3\right),$$

293 so that the asymptotic risk of w_O diverges to infinity only as $\sqrt{\rho_1}$. We illustrate this in Figure 2.

294 We notice that the empirical approximation w_{Oe} again performs in a nearly identical way to the
295 optimal response-linear achievable interpolator w_O. Moreover, importantly, we note that w_V and
296 w_O are limits of the same algorithm, $w_{t+1} = w_t - \eta_t\Sigma^{-1}\nabla R(w_t)$, only with different initialization.
297 Hence, this shows that different initialization of the same optimization algorithm can have an
298 arbitrarily large influence on generalization through implicit bias.

5 Random features regression

300 The concept of optimal interpolation, as a function which is linear in the response variable, is general
301 and can be extended beyond linear models. We present an extension of Proposition 1 to the setting of
302 random features regression. Random features models were first introduced as a random approximation
303 to kernel methods (Rahimi and Recht, 2008) and can be viewed as a two-layer neural network with
304 first layer randomly initialized and fixed as far as training is concerned. They can be shown to
305 approximate neural networks in certain regimes of training and initialization and hence are often
306 considered in the literature as a first step to address neural networks (e.g. (Jacot et al., 2018)). We
307 consider data generated in the same way as before, $y_i = \langle x_i, w^\star \rangle + \xi_i$, and the model to be a two-
308 layer neural network $f_a : \mathbb{R}^d \ni x \mapsto a^T\sigma(\Theta x/\sqrt{d})$, where the first layer $\Theta \in \mathbb{R}^{N \times d}$ is randomly
309 initialized. This setting, along with x_i and rows of Θ belonging to the sphere $\mathbb{S}^{d-1}(\sqrt{d})$ with radius
310 $\sqrt{d}$ in $\mathbb{R}^d$, is often considered in the literature on interpolation of random features models (Mei
311 and Montanari, 2019; Ghorbani et al., 2021). If we analogously define the optimal response-linear
312 achievable interpolator in random features regression by

$$a_O = \arg\min_{a \in \mathcal{G} \cap \mathcal{L}} \mathbb{E}_{\xi,w^\star} r(f_a) - r(w^\star), \tag{16}$$

313 where here $\mathcal{G} = \{a \in \mathbb{R}^N : Za = y\}$ is the set of interpolators, $Z = \sigma(X\Theta^T/\sqrt{d})$ and $\mathcal{L}$ is the
314 same as in Definition 5, then the following analogue of Proposition 1 holds.

Proposition 3. The optimal response-linear achievable interpolator (16) in random features regression
316 satisfies

$$a_O = \Sigma_z^{-1}\left(\Sigma_{zx}\Phi X^T + Z^T(Z\Sigma_z^{-1}Z^T)^{-1}(\frac{d}{\delta}I_n + X\Phi X^T - Z\Sigma_z^{-1}\Sigma_{zx}\Phi X^T)\right)\left(\frac{d}{\delta}I_n + X\Phi X^T\right)^{-1}y,$$

317 Here $\Sigma_z = \mathbb{E}_{\tilde{x}}(\sigma(\Theta\tilde{x}/\sqrt{d})\sigma(\Theta\tilde{x}/\sqrt{d})^T)$ and $\Sigma_{zx} = \mathbb{E}_{\tilde{x}}(\sigma(\Theta\tilde{x}/\sqrt{d})\tilde{x}^T)$ are covariance and cross-
318 covariance matrices, respectively. This interpolator can be again obtained as the implicit bias of
319 preconditioned gradient descent.

Proposition 4. The optimal response-linear achievable interpolator (16) in random features regression is the limit of preconditioned gradient descent on the last layer,

$$w_{t+1} = w_t - \eta_t \Sigma_z^{-1} \nabla R(w_t),$$

provided that the algorithm converges and initialized at

$$a_0 = \Sigma_z^{-1} \Sigma_{zx} \Phi X^T \left(\frac{d}{\delta} I_n + X \Phi X^T \right)^{-1} y.$$

6   Conclusion

In this paper, we investigated how to design interpolators in linear regression which have optimal generalization performance. We designed an interpolator which has optimal risk among interpolators that are a function of the training data, population covariance, signal-to-noise ratio and prior covariance, but not the true parameter or the noise, where this function is linear in the response variable. We showed that this interpolator is the implicit bias of a covariance-based preconditioned gradient descent algorithm. We computed the asymptotic risk as $\frac{d}{n} \to \gamma > 1$ with $d, n \to \infty$ to identify regimes where other interpolators are arbitrarily worse.

In particular, we found a regime where the variance term of the minimum-norm interpolator is arbitrarily large compared to our interpolator. This illustrates that implicit bias has an important influence on generalization through the choice of optimization algorithm.

We identified a second regime where the interpolator which has best variance is also arbitrarily worse than our interpolator. In this second example, both interpolators are the implicit bias of the same algorithm, but with different initialization. This illustrates that initialization has an important influence on generalization.

We also considered an empirical approximation of the optimal response-linear achievable interpolator, which uses only the training data X and y and does not assume knowledge of the population covariance matrix or the signal-to-noise ratio, and empirically observe that it generalizes in a nearly identical way to the optimal response-linear achievable interpolator in the examples that we consider when the prior is isotropic.

A limitation of this work includes a precise guarantee on the approximation error of the Graphical Lasso for a general covariance matrix Σ. Some guarantees are in (Ravikumar et al., 2011), however establishing guarantees for a general covariance matrix would be a contribution on its own.

When the prior is isotropic, we can empirically approximate the optimal response-linear interpolator to get an interpolator with nearly identical generalization. However, we did not provide a proof that this approximation will have generalization at least as good as that of the minimum-norm solution when the prior is not isotropic. This can perhaps be extended.

A natural question for future research, which also motivated our work, is whether one can systematically design new ways of interpolation, which are adapted to the distribution of the data and related to notions of optimality, for more general and complex overparametrized machine learning models such as neural networks.

References

S. Amari, J. Ba, R. B. Grosse, X. Li, A. Nitanda, T. Suzuki, D. Wu, and J. Xu. When does preconditioning help or hurt generalization? In *International Conference on Learning Representations*, 2021.

Z. Bai and J. Silverstein. *Spectral Analysis of Large Dimensional Random Matrices*. Springer Series in Statistics. Springer New York, 01 2010.

Z. D. Bai and Y. Q. Yin. Limit of the smallest eigenvalue of a large dimensional sample covariance matrix. *The Annals of Probability*, 21(3):1275–1294, 07 1993.

J. Baik and J. W. Silverstein. Eigenvalues of large sample covariance matrices of spiked population models. *Journal of Multivariate Analysis*, 97(6):1382 – 1408, 2006.

P. L. Bartlett, P. M. Long, G. Lugosi, and A. Tsigler. Benign overfitting in linear regression. *Proceedings of the National Academy of Sciences*, 117(48):30063–30070, 2020.

P. L. Bartlett, A. Montanari, and A. Rakhlin. Deep learning: a statistical viewpoint, 2021. *arXiv preprint arXiv:2103.0917*.

M. Belkin, D. Hsu, S. Ma, and S. Mandal. Reconciling modern machine-learning practice and the classical bias–variance trade-off. *Proceedings of the National Academy of Sciences*, 116(32): 15849–15854, 2019.

L. Chizat, E. Oyallon, and F. Bach. On lazy training in differentiable programming. In *Advances in Neural Information Processing Systems*, volume 32. Curran Associates, Inc., 2019.

E. Dobriban and S. Wager. High-dimensional asymptotics of prediction: Ridge regression and classification. *The Annals of Statistics*, 46(1):247–279, 07 2015.

J. Friedman, T. Hastie, and R. Tibshirani. Sparse inverse covariance estimation with the graphical lasso. *Biostatistics*, 9(3):432–441, 12 2007.

B. Ghorbani, S. Mei, T. Misiakiewicz, and A. Montanari. Linearized two-layers neural networks in high dimension. *The Annals of Statistics*, 49(2):1029 – 1054, 2021.

S. Gunasekar, J. Lee, D. Soudry, and N. Srebro. Characterizing implicit bias in terms of optimization geometry. In *Proceedings of the 35th International Conference on Machine Learning*, volume 80, pages 1832–1841, 2018.

W. Hachem, P. Loubaton, and J. Najim. Deterministic equivalents for certain functionals of large random matrices. *Ann. Appl. Probab.*, 17(3):875–930, 06 2007.

T. Hastie, A. Montanari, S. Rosset, and R. J. Tibshirani. Surprises in high-dimensional ridgeless least squares interpolation, 2019. *arXiv preprint arXiv:1903.08560*.

A. Jacot, F. Gabriel, and C. Hongler. Neural tangent kernel: Convergence and generalization in neural networks. In *Advances in Neural Information Processing Systems*, volume 31. Curran Associates, Inc., 2018.

I. M. Johnstone. On the distribution of the largest eigenvalue in principal components analysis. *Ann. Statist.*, 29(2):295–327, 04 2001.

O. Ledoit and S. Peche. Eigenvectors of some large sample covariance matrix ensembles. *Probability Theory and Related Fields*, 151(1-2):233–264, 11 2009.

O. Ledoit and M. Wolf. A well-conditioned estimator for large-dimensional covariance matrices. *Journal of Multivariate Analysis*, 88(2):365–411, 2004.

T. Liang and A. Rakhlin. Just interpolate: Kernel "ridgeless" regression can generalize. *Ann. Statist.*, 48(3):1329–1347, 06 2020.

T. Liang and P. Sur. A precise high-dimensional asymptotic theory for boosting and minimum-ℓ_1-norm interpolated classifiers, 2020. *arXiv preprint arXiv:2002.01586*.

V. Marčenko and L. Pastur. Distribution of eigenvalues for some sets of random matrices. *Mathematics of the USSR-Sbornik*, 1:457–483, 01 1967.

S. Mei and A. Montanari. The generalization error of random features regression: Precise asymptotics and double descent curve, 2019. *arXiv preprint arXiv:1908.05355*.

J. Mourtada. Exact minimax risk for linear least squares, and the lower tail of sample covariance matrices, 2020. *arXiv preprint arXiv:1912.10754*.

V. Muthukumar, K. Vodrahalli, and A. Sahai. Harmless interpolation of noisy data in regression. *2019 IEEE International Symposium on Information Theory*, pages 2299–2303, 2019.

F. Pedregosa, G. Varoquaux, A. Gramfort, V. Michel, B. Thirion, O. Grisel, M. Blondel, P. Pretten-hofer, R. Weiss, V. Dubourg, J. Vanderplas, A. Passos, D. Cournapeau, M. Brucher, M. Perrot, and E. Duchesnay. Scikit-learn: Machine learning in Python. *Journal of Machine Learning Research*, 12:2825–2830, 2011.

R. Penrose. A generalized inverse for matrices. *Mathematical Proceedings of the Cambridge Philosophical Society*, 51(3):406–413, 1955.

R. Penrose. On best approximate solutions of linear matrix equations. *Mathematical Proceedings of the Cambridge Philosophical Society*, 52(1):17–19, 1956.

A. Rahimi and B. Recht. Random features for large-scale kernel machines. In *Advances in Neural Information Processing Systems*. Curran Associates, Inc., 2008.

A. Rangamani, L. Rosasco, and T. Poggio. For interpolating kernel machines, minimizing the norm of the erm solution minimizes stability, 2020. *arXiv preprint arXiv:2006.15522*.

P. Ravikumar, M. J. Wainwright, G. Raskutti, and B. Yu. High-dimensional covariance estimation by minimizing ℓ_1-penalized log-determinant divergence. *Electronic Journal of Statistics*, 5:935 – 980, 2011.

D. Richards, J. Mourtada, and L. Rosasco. Asymptotics of ridge(less) regression under general source condition. In *Proceedings of The 24th International Conference on Artificial Intelligence and Statistics*, volume 130, pages 3889–3897, 13–15 Apr 2021.

F. Rubio and X. Mestre. Spectral convergence for a general class of random matrices. *Statistics & Probability Letters*, 81(5):592 – 602, 2011.

J. Silverstein. Strong convergence of the empirical distribution of eigenvalues of large dimensional random matrices. *Journal of Multivariate Analysis*, 55(2):331–339, 1995.

J. Silverstein and S. Choi. Analysis of the limiting spectral distribution of large dimensional random matrices. *Journal of Multivariate Analysis*, 54(2):295 – 309, 1995.

V. N. Vapnik. *The Nature of Statistical Learning Theory*. Springer-Verlag Berlin, 1995.

C. Zhang, S. Bengio, M. Hardt, B. Recht, and O. Vinyals. Understanding deep learning requires rethinking generalization. In *5th International Conference on Learning Representations*, 2017.