COMPRESSING GRADIENTS IN DISTRIBUTED SGD BY EXPLOITING THEIR TEMPORAL CORRELATION

ABSTRACT

We propose SignXOR, a novel compression scheme that exploits temporal correlation of gradients for the purpose of gradient compression. Sign-based schemes such as Scaled-sign and SignSGD (Bernstein et al., 2018; Karimireddy et al., 2019) compress gradients by storing only the sign of gradient entries. These methods, however, ignore temporal correlations between gradients. The equality or non-equality of signs of gradients in two consecutive iterations can be represented by a binary vector, which can be further compressed depending on its entropy. By implementing a rate-distortion encoder we increase the temporal correlation of gradients, lowering entropy and improving compression. We achieve theoretical convergence of SignXOR by employing the two-way error-feedback approach introduced by Zheng et al. (2019). Zheng et al. (2019) show that two-way compression with error-feedback achieves the same asymptotic convergence rate as SGD, although convergence is slower by a constant factor. We strengthen their analysis to show that the rate of convergence of two-way compression with error-feedback asymptotically is the same as that of SGD. As a corollary we prove that two-way SignXOR compression with error-feedback achieves the same asymptotic rate of convergence as SGD. We numerically evaluate our proposed method on the CIFAR-100 and ImageNet datasets and show that SignXOR requires less than 50% of communication traffic compared to sending sign of gradients. To the best of our knowledge we are the first to present a gradient compression scheme that exploits temporal correlation of gradients.

1 INTRODUCTION

Distributed optimization has become the norm for training machine learning models on large datasets. With the need to train bigger models on ever-growing datasets, scalability of distributed optimization has become a key focus in the research community. While an obvious solution to growing dataset size is to increase the number of workers, the communication among workers has proven to be a bottleneck. For popular benchmark models such as AlexNet, ResNet and BERT the communication can account for a significant portion of the overall training time (Alistarh et al., 2017; Seide et al., 2014; Lin et al., 2018). The BERT ("Bidirectional Encoder Representing from Transformers") architecture for language models (Devlin et al., 2018) comprises about 340 million parameters. If 32-bit floating-point representation is used one gradient update from a worker amounts to communicating around 1.3GB (340×10^6 parameters $\times$ 32 bits per parameter $\times 2^{-33}$ gigabytes per bit $\approx$ 1.3GB). Frequently communicating such large payloads can easily overwhelm the network resulting in prolonged training times. In addition, large payloads may increase other forms of costs in distributed optimization. Novel approaches such as federated learning employ mobile devices as worker nodes. Exchanging information with mobile devices is heavily constrained due to communication bandwidth and budget limitations. Therefore, communication remains an important bottleneck in distributed optimization and reducing communication is of utmost importance.

Gradient compression alleviates the communication bottleneck. The idea is to apply a compression scheme on gradients before sending them over the network. There has been an increasing amount of literature on gradient compression within the last few years (Seide et al., 2014; Aji & Heafield, 2017; Alistarh et al., 2017; Wen et al., 2017; Wangni et al., 2018; Wu et al., 2018; Lin et al., 2018; Wang et al., 2018). Such compression schemes have been demonstrated to work well with distributed stochastic gradient descent (SGD) and its variants. However, Karimireddy et al. (2019)

theoretically show that SGD with compression does not converge in general. The recently proposed error-feedback based algorithms (Stich et al., 2018; Karimireddy et al., 2019) circumvent the convergence issue. Error-feedback methods accumulate the compression error and feed it back to the input of the compression scheme so that the error gets transmitted over subsequent iterations. The dist-EF-SGD algorithm proposed by Zheng et al. (2019) applies error-feedback to two-way compression, in which both worker-to-master and master-to-worker communications are compressed. Theoretical guarantees provided by dist-EF-SGD are valid for all compression schemes that fall under the definition of 'δ-approximate compressors', also referred to as δ-compressors. The authors prove that error-feedback with two-way compression asymptotically achieves the $\mathcal{O}(1/\sqrt{T})$ convergence rate of SGD. However, the analysis by Zheng et al. (2019) suggests that dist-EF-SGD converges slower than SGD by a constant factor.

Our contributions in this paper are as follows. We propose SignXOR, a novel compression scheme that exploits temporal correlation of gradients. We prove that SignXOR is a δ-compressor, and we provide convergence guarantees for SignXOR by employing dist-EF-SGD. We strengthen the convergence bound by Zheng et al. (2019) to show that dist-EF-SGD asymptotically converges at the same $\mathcal{O}(1/\sqrt{T})$ rate as SGD. Consequently, we show that the proposed method asymptotically achieves the SGD convergence rate. We empirically validate the proposed method on CIFAR-100 and ImageNet datasets and demonstrate that the ratio between total communication budgets of SignXOR and Scaled-sign is less than 50%.

Notation: For $x \in \mathbb{R}^d$, $x[j]$ denotes the jth entry of x, $\|x\|_1$ denotes the ℓ_1-norm, and $\|x\|$ denotes the ℓ_2-norm. For vector inputs $\text{sgn}(\cdot)$ function outputs the sign of the input element-wise. The index set $\{1, \ldots, n\}$ is denoted by $[n]$, and $\odot$ denotes elementwise multiplication.

2 RELATED WORK

The most common gradient compression schemes can be categorized into those based on sparsification and those based on quantization. The methods based on sparsification such as Top-k (Stich et al., 2018; Lin et al., 2018) and Spectral-ATOMO (Wang et al., 2018) preserve only the most significant gradient elements, whereas the methods based on quantization such as QSGD (Alistarh et al., 2017) and SignSGD (Bernstein et al., 2018) reduce the overall floating-point precision of the gradient. Therefore, these two classes can be respectively thought of as approaches that reduce the quantity versus the quality of the gradient.

Sign-based compression schemes such as Scaled-sign, SignSGD and Signum (Bernstein et al., 2018) sit at the far end of quantization-based algorithms. Such schemes quantize real values to only two levels, $+1$ and -1. For example, the compressing function of Scaled-sign takes in a vector $x \in \mathbb{R}^d$, and the decompressing function outputs the vector $(\|x\|_1/d)\,\text{sgn}(x)$. This means that the compressed representation needs to store only the sign of each entry $x[j]$, along with the scaling constant $\|x\|_1/d$. In practice one can avoid the 'zero' output of sgn by mapping it to $+1$ or -1. This allows the two outcomes $+1$ and -1 to be represented using one bit per entry, making the size of the compressed representation $d + 32$ bits in total (assuming 32-bit single-precision representation of the scaling constant). As per Shannon's source coding theorem (MacKay, 2003, p. 81), the sequence of $+1$ and -1 can be further compressed without any information loss if the probability of encountering $+1$ is different from that for -1. However, in our experiments on Scaled-sign compression we observe that both outputs are equally likely across all iterations.

Any lossy gradient compression scheme introduces noise, also known as distortion, in addition to the measurement noise that is already present in the stochastic gradients computed by the workers. It is reasonable to expect the additional compression error hurts the convergence rate of the algorithm. However, it has been empirically observed that significant compression ratios can be achieved before observing any impact on convergence (Seide et al., 2014; Alistarh et al., 2017). One can achieve even greater compression while keeping the convergence rate nearly the same by employing error-feedback (Stich et al., 2018; Karimireddy et al., 2019; Zheng et al., 2019). Algorithms based on error-feedback accumulate the compression error in past iterations and add it to the input of the compressing function. This allows all of the gradient information to get transmitted over a sequence of iterations, albeit with a delay. For smooth functions the gradient does not change considerably, therefore, the delay does not significantly impact the rate of convergence.

The dist-EF-SGD algorithm proposed by Zheng et al. (2019) is based on error-feedback and offers two-way compression under the master-worker topology. The dist-EF-SGD algorithm provides convergence guarantees for δ-compressors. An operator $C : \mathbb{R}^d \to \mathbb{R}^d$ is a δ-compressor for all $x \in \mathbb{R}^d$ if $\|C(x) - x\|^2 \leq (1 - \delta)\|x\|^2$ for some $\delta \in (0, 1]$. The δ is a measure of the distortion due to applying C. A good compressor will have δ close to 1 and a large compression ratio. One can show that Scaled-sign is a $\frac{1}{d}$-approximate compressor. The Scaled-sign compression scheme with dist-EF-SGD offers convergence guarantees under standard assumptions even though Scaled-sign without error-feedback may not converge (Karimireddy et al., 2019). Zheng et al. (2019) generalize the dist-EF-SGD algorithm to include blockwise compression, in which the gradient is partitioned into blocks that are compressed separately. A natural partitioning method is to consider as blocks the elements of a deep neural network such as tensors, matrices and vectors. Blockwise compression allows better exploitation of redundancy that may be present only within a block.

Zheng et al. (2019) empirically demonstrate that Scaled-sign with dist-EF-SGD achieves almost the same performance of SGD with respect to training loss and test accuracy. This indicates that we can allow more distortion in the compression before observing a significant impact on training performance. The proposed SignXOR compression is based on allowing additional distortion in the interest of achieving a higher compression ratio.

3 PROPOSED ALGORITHM: SIGNXOR

Our proposal is motivated by the concept of delta encoding. Delta encoding refers to techniques that store data as the difference between successive samples, rather than directly storing the samples themselves (Smith et al., 1997). One often encounters delta encoding in applications such as integer compression and video compression. For example, it is more space efficient to store the first-order differences of a digitized audio signal than to store the values of the original signal. First-order differences have smaller magnitudes compared to the original sequence and, therefore, the differences can be represented by a comparatively smaller number of bits. A similar approach is used in the inter-picture prediction method in high efficiency video coding (HEVC) (Sze et al., 2014). Inter-picture prediction makes use of temporal correlations across video frames encoding the differences between frames. This requires less storage compared to storing each video frame.

Our SignXOR algorithm applies the delta encoding concept to gradient compression. In essence, SignXOR maintains a binary vector that indicates whether the sign of a gradient entry is equal (or not equal) to the sign of the corresponding entry in the previous gradient. The equality (or non-equality) can be represented by a binary 1 (or 0). This procedure resembles the binary XOR operation, hence the name SignXOR. We employ a generalized version of original dist-EF-SGD by Zheng et al. (2019) (the original dist-EF-SGD is specified in Algorithm 2 therein) to provide convergence guarantees for the proposed compression scheme. The generalization is to make dist-EF-SGD compatible with SignXOR. We outline the proposed method in Algorithm 1 and Algorithm 2.

Generalized dist-EF-SGD: Algorithm 1 presents generalized dist-EF-SGD for setup with a master and n workers. The three main differences between the generalized and original dist-EF-SGD versions are as follows. First, Algorithm 1 delegates compression and decompression tasks to two separate functions *encode* and *decode*. Second, Algorithm 1 maintains a vector $\bar{g}_k$ at all nodes including the master. The vector $\bar{g}_k$ is the average gradient all workers used to update the parameter vector w_k in the last iteration. Third, the *encode* and *decode* functions each take the last gradient $\bar{g}_k$ as the second argument. This is in contrast to the original dist-EF-SGD algorithm in which compression is based only on the gradient in the current iteration. Since there are no differences related to compression performance between the original and generalized dist-EF-SGD algorithms, they encompass the same theoretical guarantees.

The compressing function *encode* takes in two inputs and outputs $\mathcal{G}_k^i$. This output is the actual payload sent to master over the communication channel. In addition to $\mathcal{G}_k^i$, the ith worker also computes $\bar{g}_k^i$ which is what the master will obtain by decompressing $\mathcal{G}_k^i$. The vector $\bar{g}_k^i$ is used to update e_{k+1}^i, the compression error fed back in the next iteration. The master collects $\mathcal{G}_k^i$ from all workers and decompresses each to obtain $\bar{g}_k^i$. All workers receive the master broadcast $\mathcal{G}_k$, and input it, along with $\bar{g}_k$, to the *decode* function to decompress and obtain $\bar{g}_{k+1}$. Note that in the kth iteration all nodes use the same $\bar{g}_k$ vector as the second argument in the *encode* and *decode* functions.

Algorithm 1: Generalized dist-EF-SGD compatible with SignXOR

> **input**   : initial parameter vector w_0; step sizes $\{\eta_0, \ldots, \eta_{T-1}\}$
> **initialize:** let $\mathbf{0}$ be the all-zeros vector of dimension d ;
>   let $\bar{g}_0 \in \mathbb{R}^d$ be a vector with entries sampled uniformly from $[-1, 1]$;
>   **on ith worker** store $\bar{g}_0$; set e_0^i to $\mathbf{0}$; set parameter vector to w_0 ;
>   **on master** store $\bar{g}_0$; set e_0 to $\mathbf{0}$;

1 **for** $k \in \{0, \ldots, T-1\}$ **do**
2   **on ith worker**
3   compute $\hat{g}_k^i = g_k^i + \frac{1}{\eta_k} e_k^i$ where g_k^i is the stochastic gradient at w_k ;
4   compute $\mathcal{G}_k^i = encode(\hat{g}_k^i, \bar{g}_k)$ and $\bar{g}_k^i = decode(\mathcal{G}_k^i, \bar{g}_k)$;
5   send $\mathcal{G}_k^i$ to master and update error $e_{k+1}^i = \eta_k(\hat{g}_k^i - \bar{g}_k^i)$;
6   receive $\mathcal{G}_k$ from master and compute $\bar{g}_{k+1} = decode(\mathcal{G}_k, \bar{g}_k)$;
7   update parameter vector $w_{k+1} = w_k - \eta_k \bar{g}_{k+1}$;

8   **on master**
9   receive $\mathcal{G}_k^i$ and compute $\bar{g}_k^i = decode(\mathcal{G}_k^i, \bar{g}_k)$ for all $i \in [n]$;
10   compute $\hat{g}_k = \frac{1}{n} \sum_{i \in [n]} \bar{g}_k^i + \frac{1}{\eta_k} e_k$;
11   compute $\mathcal{G}_k = encode(\hat{g}_k, \bar{g}_k)$ and $\bar{g}_{k+1} = decode(\mathcal{G}_k, \bar{g}_k)$;
12   broadcast $\mathcal{G}_k$ to all workers and update $e_{k+1} = \eta_k(\hat{g}_k - \bar{g}_{k+1})$;

The *encode* and *decode* functions corresponding to SignXOR compression scheme are specified in Algorithm 2. For the ease of explanation we consider the specific case when the master compresses $\hat{g}_k$ to obtain $\mathcal{G}_k$, and the workers decompress $\mathcal{G}_k$ to obtain $\bar{g}_{k+1}$ as an approximation to $\hat{g}_k$.

Algorithm 2: SignXOR compression and decompression

> **input:** hyperparameter $0 \leq \alpha < \frac{1}{4}\left(1 - \sqrt{1 - \frac{1}{d}}\right)^2 < 1$;

1 **function** $encode(x \in \mathbb{R}^d, y \in \mathbb{R}^d)$**:**
2   compute r, the fraction of $+1$'s in $\text{sgn}(x)$;
3   compute q, the fraction of elements in x such that $\text{sgn}(x[j]) = \text{sgn}(y[j])$;
4   initialize binary vector $b \in \{0, 1\}^d$ to all-zeros ;
5   for all $j \in [d]$, if $\text{sgn}(x[j]) = \text{sgn}(y[j])$ set $b[j] = 1$ with probability $1 - \alpha$;
6   compute p, the fraction of 1's in b ;
7   compress b with a lossless scheme and compute scalar $a = \|x\|_1/d$;
8   **output** $\mathcal{G} = \{a, \text{compressed representation of } b\}$;

9 **function** $decode(\mathcal{G} = \{a \in \mathbb{R}, \text{compressed representation of a vector } b \in \{0, 1\}^d\}, y \in \mathbb{R}^d)$**:**
10   expand and decompress $\mathcal{G}$ to obtain a and b ;
11   **output** $a\,\text{sgn}(y) \odot (2b - 1)$;

Compressing function: We consider the case when master calls *encode* with arguments $x = \hat{g}_k$ and $y = \bar{g}_k$. Note that the scalars r, q and p are not used anywhere in Algorithm 2. These scalars help us describe the algorithm and also become useful in our theoretical analysis. The output of *encode* function is random when $\alpha \neq 0$, and deterministic when $\alpha = 0$. Let us first consider $\alpha = 0$, in which case $b[j] = 1$ if and only if $\text{sgn}(\hat{g}_k[j]) = \text{sgn}(\bar{g}_k[j])$. This implies that p is the fraction of entries in $\hat{g}_k$ and $\bar{g}_k$ that have the same signs. This is a measure of the (positive or negative) correlation between the two vectors. The core idea in the proposed compression scheme is to compress the binary vector b using a lossless compression scheme. Shannon's source coding theorem (MacKay, 2003, p. 81) states that d i.i.d. random variables each with entropy $H(p) = -p \log_2 p - (1-p) \log_2(1-p)$ can be compressed into approximately $dH(p)$ bits with negligible risk of information loss, as $d \to \infty$. In our case, while the length of the parameter vector d is well over a million for models of practical interest, the entries of b are not necessarily i.i.d.. However, we demonstrate in Section 5 that there

exist readily available lossless compression algorithms that can compress b to very close to $dH(p)$ bits, the Shannon limit. Note that binary entropy $H(p)$ is symmetric around $p = 0.5$, and satisfies $0 \leq H(p) \leq 1$ with $H(0.5) = 1$. When $p \approx 0.5$ the size of the compressed representation gets close to d, which is same as that offered by Scaled-sign. Further compression of b is only possible if p is away from 0.5. In our experiments presented in Section 5.2 we observe that when $\alpha = 0$, p remain close to but slightly lower than 0.5. This implies a low correlation between $\hat{g}_k$ and $\bar{g}_k$.

Our solution is to make $\alpha > 0$. Increasing α pushes p away from 0.5 and towards 0. A lower p decreases the entropy of b, yielding a higher compression ratio with the lossless compressor. In Section 5.2 we observe that increasing α also decreases q in subsequent iterations. Note that q is a measure of correlation of $\hat{g}_k$ and $\bar{g}_k$. The suggested upper bound for α ensures theoretical convergence of the SignXOR algorithm. We show in Section 5 that in practice α can be increased considerably more than the suggested upper bound before seeing an impact on the training performance.

Decompressing function: Let us now consider the case when a worker calls *decode* with arguments $\mathcal{G} = \mathcal{G}_k$ and $y = \bar{g}_k$. The first argument $\mathcal{G}_k$ contains the scalar a and the compressed representation of binary vector b, which can be recovered exactly as compression of b is lossless. Noting that b is computed with $\bar{g}_k$ as the second argument to the *encode* function, the output of the decoder is obtained by inverting the sign of $\bar{g}_k[j]$ whenever $b[j]$ is 0, and by scaling the result by a. One can compactly express the output of this operation as $a \, \text{sgn}(\bar{g}_k) \odot (2b - 1)$.

Remarks: Note that we can recover the Scaled-sign compression scheme by setting $\alpha = 0$ in Algorithm 2. In comparison to SignXOR, the compressed representation of Scaled-sign stores the sign of each entry in $\hat{g}_k$, and the scaling constant $a = \|\hat{g}_k\|_1 / d$. We demonstrate in Section 5.2 that r, the fraction of +1's in $\text{sgn}(\hat{g}_k)$, is approximately 0.5 across all iterations. This means that we cannot compress further the sequence of signs, and the encoded representation of Scaled-sign requires at least d bits. Algorithm 1 can be easily extended to accommodate blockwise compression as was explained by Zheng et al. (2019). In blockwise compression the gradient $\hat{g}_k$ is partitioned into blocks, and the blocks are processed separately using *encode* and *decode* functions. In our numerical experiments we employ the blockwise extension of Algorithm 1.

4 THEORETICAL GUARANTEES

In this section we prove that the combination of Algorithm 1 and Algorithm 2 converges, and the convergence rate is asymptotically the same as that of SGD. We accomplish this in two stages. First, we prove that the SignXOR compression scheme presented in Algorithm 2 is a δ-compressor. Second, we show that for any δ-compressor the generalized dist-EF-SGD scheme in Algorithm 1 converges at the same $\mathcal{O}(1/\sqrt{T})$ rate as SGD. Putting these two together yields the desired result.

SignXOR is a δ-compressor: We consider the general form of *encode* and *decode* functions, i.e., with inputs (x, y) for *encode*, and with inputs $(\mathcal{G}, y)$ for *decode*. Let us define the operator $C_\alpha^y : \mathbb{R}^d \to \mathbb{R}^d$ where $C_\alpha^y(x) = a \, \text{sgn}(y) \odot (2b - 1)$ with $a = \frac{\|x\|_1}{d}$ and the binary vector b is such that $b = 1$ with probability $1 - \alpha$ if $\text{sgn}(x) = \text{sgn}(y)$, and $b = 0$ otherwise. Note that a and b have the same meaning as in Algorithm 2. The operator $C_\alpha^y(x)$ is representative of $decode(encode(x, y), y)$, therefore, $C_\alpha^y(x)$ is the SignXOR compressor. Since C_α^y is a randomized operator, we show that it is a δ-compressor *in expectation* as stated in Theorem 4.1.

Theorem 4.1. *There exist a $\delta \in (0, 1]$ such that $\mathbb{E}[\|C_\alpha^y(x) - x\|^2] \leq (1 - \delta)\|x\|^2$ for all $y \in \mathbb{R}^d$ if $\alpha < \frac{1}{4}\left(1 - \sqrt{1 - \frac{1}{d}}\right)^2$.*

The proof is provided in Appendix A.1. Although the suggested upper bound for α is extremely small for large d, we demonstrate in Section 5 that in practice α can be set quite close to 1. Next we discuss the convergence rate of dist-EF-SGD for an arbitrary δ-compressor.

Convergence rate of dist-EF-SGD: Zheng et al. (2019) compare the convergence rates of dist-EF-SGD and vanilla SGD in their Corollary 1. As authors note, although the convergence rates of the two algorithms are same in $\mathcal{O}$ notation, the former is slower by a constant factor. The differences between the bounds for dist-EF-SGD and vanilla SGD in Corollary 1 are as follows. In both cases, for large T the dominant terms are those with $\sqrt{T}$ in denominator. The ratio between the dominant terms corresponding to dist-EF-SGD and vanilla SGD is 1.5, suggesting that the former is always

slower than the latter by a factor of 1.5. In our Theorem 4.2 we strengthen the bound for dist-EF-SGD so that the dominant terms in the two algorithms are the same. This means that dist-EF-SGD achieves same convergence rate as vanilla SGD in the limit as $T \to \infty$. Our proof is for an arbitrary δ-compressor that is not necessarily SignXOR. To this end we consider Algorithm 1 and define $C(x) = decode(encode(x, y), y)$. We assume that C is a δ-compressor for all $y \in \mathbb{R}^d$, i.e., $\mathbb{E}[\|C(x) - x\|^2] \leq (1 - \delta)\|x\|^2$ for some $\delta \in (0, 1]$. We setup the optimization problem next.

Let $F : \mathbb{R}^d \to \mathbb{R}$ be a function that is lower bounded by F_* and has a gradient ∇F. We consider a distributed optimization setup with a master and n workers. For some $w_k \in \mathbb{R}^d$ the ith worker calculates the stochastic gradient g_k^i at w_k. We assume that g_k^i is an unbiased estimate of $\nabla F(w_k)$, and that g_k^i has bounded variance. Specifically, we assume that g_k^i satisfies the two properties $\mathbb{E}[g_k^i | w_k] = \nabla F(w_k)$ and $\mathbb{E}[\|g_k^i - \nabla F(w_k)\|^2] \leq \sigma^2$. We also assume that F is L-Lipschitz smooth, and that the gradient of F is bounded. The latter implies that $\mathbb{E}[\|g_k^i\|^2] \leq G^2$ for some scalar G. The master and workers generate a sequence $\{w_0, \ldots, w_T\}$ as per Algorithm 1. Convergence results of this system is summarized in Theorem 4.2.

Theorem 4.2. *For a given w_0 and a step size schedule $\eta_k = \frac{1}{L\sqrt{T}}\left(1 - \frac{1}{2T^{1/4}}\right)$, the convergence of the system outlined in Algorithm 1 after T iterations is given by*

$$\mathbb{E}\left[\min_{k=0,\ldots,T-1}\|\nabla F(w_k)\|^2\right] < \frac{2L(F(w_0) - F_*) + \frac{\sigma^2}{n}}{2\sqrt{T} - 1}$$
$$+ \frac{2L(F(w_0) - F_*) + \frac{8(1-\delta)G^2}{\delta^2}\left(1 + \frac{1}{\delta^2}\right)}{2T^{3/4} - T^{1/4}} + \mathcal{O}\left(\frac{1}{T}\right). \quad (1)$$

We defer the proof of Theorem 4.2 to Section A.2 in the Appendix. In comparison, the bound for SGD has only the first term in (1). Note that the last two terms in (1) converge to zero faster than the first term. This means that dist-EF-SGD asymptotically achieves the same convergence rate as SGD. Since SignXOR is a δ-compressor we conclude that the proposed algorithm converges asymptotically at the same rate as SGD.

5 NUMERICAL EXPERIMENTS

We perform multi-GPU experiments on three datasets: CIFAR-100, ImageNet-32 and ImageNet. The ImageNet-32 dataset (Chrabaszcz et al., 2017) is a down-sampled version of the ImageNet dataset in which the images are of size 32×32 pixels. All other properties such as the number of images and the number of classes are the same as the original ImageNet dataset. We experiment with ImageNet-32 as an alternative to ImageNet due to the latter's heavy consumption of hardware resources. The additional experiments presented in Section 5.2 are performed with ImageNet-32. We train a wide residual network classifier (Zagoruyko & Komodakis, 2016) of depth 28 and width 2 (WRN-28-2) using the ImageNet-32 dataset. The CIFAR-100 and ImageNet datasets are used to train the ResNet-18 and ResNet-50 (He et al., 2016) models respectively. In all cases the dataset is partitioned to equal sizes and distributed among the workers.

We implement all algorithms using the TensorFlow and Horovod (Sergeev & Balso, 2018) packages. Since the communications component in Horovod is designed for a master-less setup, we simulate a master-worker environment in our implementation. We choose to use the Lempel–Ziv–Markov chain algorithm (LZMA) as the lossless scheme that compresses the binary vector b. The LZMA compression scheme is a member of the Lempel–Ziv family of compression algorithms (MacKay, 2003, p. 119). While there exist other compression schemes in which for large d the compression ratio converge to $H(p)$ much faster than the Lempel–Ziv algorithms, in our experiments we employ LZMA as its implementation is readily available in Python. We refer the reader to Appendix Section A.3 for an comparison of $H(p)$ and the compression ratio of LZMA. In our implementation the *encode* and *decode* functions are not tuned to achieve best computational performance. We, therefore, do not compare or plot measurements with respect to time. In our experimental setup, a single machine hosts four workers and each worker runs on a dedicated Tesla P100 16GB GPU.

Figure 1: The three columns present experimental results for CIFAR-100 (left), ImageNet-32 (middle), ImageNet (right). In each case the three rows present plots of training loss (top), test accuracy (middle) and B_X/B_S (bottom). The test accuracy plots indicate top-1 test accuracy for CIFAR-100, and top-5 for the other two. We run SignXOR experiments for multiple α values.

5.1 MAIN RESULTS

We compare the performance of SignXOR to SGD and dist-EF-SGD with Scaled-sign compression. For Scaled-sign we use the original dist-EF-SGD scheme as the error-feedback mechanism. For SignXOR we use the generalized dist-EF-SGD outlined in Algorithm 1. Note that there are no compression performance related differences between the original and the generalized versions of dist-EF-SGD. In both cases we use blockwise compression, in which the gradients corresponding to tensors, matrices and vectors are compressed and decompressed separately. Training is started with a learning rate of 0.1, and the learning rate is multiplied iteratively by 0.1 at certain epochs. These epochs are multiples of 8, 10 and 5 for the experiments involving the CIFAR-100, ImageNet-32, and ImageNet datasets, respectively. We use an ℓ_2 weight regularizer in all experiments. The regularizer is scaled by 10^{-3} in CIFAR-100 experiments, and by 10^{-4} in the other experiments. Table 1 summarizes some additional details of the experiments. Batch size is per worker.

We define the following measurement to help us interpret our experimental results. Recall that in Algorithm 1 $\mathcal{G}_k^i$ and $\mathcal{G}_k$ are the payloads that workers send and receive. Let s_k and s_k^i denote the number of bits required to store $\mathcal{G}_k$ and $\mathcal{G}_k^i$ in bits. Over T iterations with SignXOR, each worker on average sends and receives a total of $B_X = \frac{1}{n} \sum_{k=0}^{T-1} \sum_{i \in [n]} (s_k^i + s_k)$ bits. In contrast, if Scaled-sign compression is used each worker communicates d bits in each iteration, making the total number of bits sent and received by each worker $B_S = 2Td$. Therefore, B_X/B_S is the ratio between the total bit usage of each algorithm. We tune the hyperparameter α in Algorithm 2 so that SignXOR achieves the same test accuracy as Scaled-sign within the same number of epochs.

Figure 1 presents results from multiple runs of the experiment with different values for α. For the CIFAR-100 dataset, the SignXOR test accuracy plot corresponding to $\alpha = 0.7$ closely follows test accuracy of Scaled-sign and SGD. The same observation is true for plots corresponding to $\alpha = 0.7$ and $\alpha = 0.6$ in ImageNet-32 and ImageNet experiments respectively. For these choices of α, the plots of B_X/B_S indicate that in each case SignXOR achieves the top test accuracy with less than

Table 1: Details of experiments and summary of findings.

Dataset	Model	Parameters	Workers	Batch size	B_X/B_S
CIFAR-100	ResNet-18	12,596,388	4	32	42%
ImageNet-32	WRN-28-2	1,595,320	4	32	43%
ImageNet	ResNet-50	25,583,592	16	16	47%

Figure 2: Evolution of r, q and p in Algorithm 2 for experiments conducted using the ImageNet32 dataset. Values are collected when the master calls the *encode* function with arguments $x = \hat{g}_k$ and $y = \bar{g}_k$. The peaks at epochs 10 and 20 are due to the drop in the learning rate at these epochs.

50% of communication required by Scaled-sign. The last column in Table 1 summarizes the lowest B_X/B_S that SignXOR achieves while attaining the same test accuracy as Scaled-sign by the end of training. Figure 1 also indicates that we can make α slightly larger than the choices listed in Table 1 to achieve an even smaller B_X/B_S with some reduction in the test accuracy. For example, the ImageNet-32 experiment corresponding to $\alpha = 0.9$ achieves within 0.3 test accuracy of Scaled-sign, but only using 12% of the communications usage of Scaled-sign.

5.2 DETAILS OF SIGNXOR RESULTS

Figure 2 presents the evolution of r, q and p in Algorithm 2 for experiments related to ImageNet-32 dataset. The left-sub figure in Figure 2 demonstrates that r, the fraction of $+1$'s in $\text{sgn}(\hat{g}_k)$ is approximately 0.5 across all iterations. Consequently, the sequence of signs in $\text{sgn}(\hat{g}_k)$ cannot be further compressed. Note that this observation is true for all α. Since $\alpha = 0$ recovers the Scaled-sign compression, we conclude that the output of Scaled-sign cannot be further compressed using a lossless compression scheme. The middle-sub figure in Figure 2 plots q, the fraction of entries in $\hat{g}_k$ such that $\text{sgn}(\hat{g}_k[j]) = \text{sgn}(\bar{g}_k[j])$. Note that q remains close to 0.5 when $\alpha = 0$, and goes down as α increases. This implies that the correlation between the two vectors $\text{sgn}(\hat{g}_k)$ and $\text{sgn}(\bar{g}_k)$ increases with α. The right-sub figure includes plots of p, the fraction of 1's in b. Note that as per Algorithm 2 we have the relationship $\mathbb{E}[p] = q(1 - \alpha)$.

6 CONCLUSIONS AND FUTURE WORK

In this paper we propose SignXOR, a novel compression algorithm that exploits the temporal correlation of consecutive gradients in SGD. The proposed algorithm builds off Scaled-sign (Bernstein et al., 2018; Karimireddy et al., 2019) and dist-EF-SGD (Zheng et al., 2019). The SignXOR algorithm combines amplitude quantization with the exploitation of temporal correlation. We accomplish this in two stages. The first employs Scaled-sign which quantizes gradient entries into two levels, and the second compresses by exploiting temporal correlation of quantized gradients. It is interesting to investigate how the second stage can be improved to accommodate more elaborate compression mechanisms beyond a two-level quantizer, such as QSGD (Alistarh et al., 2017), Top-k (Stich et al., 2018; Lin et al., 2018) and Spectral-ATOMO (Wang et al., 2018). Also, we conjecture that one must be able to compress better by jointly considering the two stages. This way, one can exploit in the second stage some of the information embedded in the gradient that may have been removed in the first stage. We leave these two tasks as future work.

REFERENCES

Alham Fikri Aji and Kenneth Heafield. Sparse communication for distributed gradient descent. *arXiv preprint arXiv:1704.05021*, 2017.

Dan Alistarh, Demjan Grubic, Jerry Li, Ryota Tomioka, and Milan Vojnovic. Qsgd: Communication-efficient sgd via gradient quantization and encoding. In *Advances in Neural Inf. Proc. Sys.*, pp. 1709–1720, 2017.

Jeremy Bernstein, Yu-Xiang Wang, Kamyar Azizzadenesheli, and Anima Anandkumar. signsgd: Compressed optimisation for non-convex problems. July 2018.

Patryk Chrabaszcz, Ilya Loshchilov, and Frank Hutter. A downsampled variant of imagenet as an alternative to the cifar datasets. *arXiv preprint arXiv:1707.08819*, 2017.

Jacob Devlin, Ming-Wei Chang, Kenton Lee, and Kristina Toutanova. Bert: Pre-training of deep bidirectional transformers for language understanding. *arXiv preprint arXiv:1810.04805*, Oct 2018.

Kaiming He, Xiangyu Zhang, Shaoqing Ren, and Jian Sun. Deep residual learning for image recognition. In *Proceedings of the IEEE conference on computer vision and pattern recognition*, pp. 770–778, 2016.

Sai Praneeth Karimireddy, Quentin Rebjock, Sebastian U Stich, and Martin Jaggi. Error feedback fixes signsgd and other gradient compression schemes. *Int. Conf. Machine Learning*, Jan 2019.

Yujun Lin, Song Han, Huizi Mao, Yu Wang, and William J Dally. Deep gradient compression: Reducing the communication bandwidth for distributed training. In *Int. Conf. Learning Representations*, Vancouver, May 2018.

David JC MacKay. *Information theory, inference and learning algorithms*. Cambridge university press, 2003.

H Brendan McMahan, Eider Moore, Daniel Ramage, Seth Hampson, et al. Communication-efficient learning of deep networks from decentralized data. In *Int. Conf. Artificial Intelligence and Stat.*, Fort Lauderdale, Florida, Apr 2017.

Frank Seide, Hao Fu, Jasha Droppo, Gang Li, and Dong Yu. 1-bit stochastic gradient descent and its application to data-parallel distributed training of speech dnns. In *Conf. Int. Speech Comm. Association*, Singapore, September 2014.

Alexander Sergeev and Mike Del Balso. Horovod: fast and easy distributed deep learning in TensorFlow. *arXiv preprint arXiv:1802.05799*, 2018.

Steven W Smith et al. The scientist and engineer's guide to digital signal processing. 1997.

Sebastian U Stich, Jean-Baptiste Cordonnier, and Martin Jaggi. Sparsified sgd with memory. In *Advances in Neural Inf. Proc. Sys.*, pp. 4447–4458, 2018.

V. Sze, M. Budagavi, and G.J. Sullivan. *High Efficiency Video Coding (HEVC): Algorithms and Architectures*. Springer International Publishing, 2014.

Hongyi Wang, Scott Sievert, Shengchao Liu, Zachary Charles, Dimitris Papailiopoulos, and Stephen Wright. Atomo: Communication-efficient learning via atomic sparsification. In *Advances in Neural Inf. Proc. Sys.*, pp. 9850–9861, 2018.

Jianqiao Wangni, Jialei Wang, Ji Liu, and Tong Zhang. Gradient sparsification for communication-efficient distributed optimization. In *Advances in Neural Information Processing Systems*, pp. 1299–1309, 2018.

Wei Wen, Cong Xu, Feng Yan, Chunpeng Wu, Yandan Wang, Yiran Chen, and Hai Li. Terngrad: Ternary gradients to reduce communication in distributed deep learning. In *Advances in neural information processing systems*, pp. 1509–1519, 2017.

Jiaxiang Wu, Weidong Huang, Junzhou Huang, and Tong Zhang. Error compensated quantized sgd and its applications to large-scale distributed optimization. *Int. Conf. Machine Learning*, June 2018.

Sergey Zagoruyko and Nikos Komodakis. Wide residual networks. *arXiv preprint arXiv:1605.07146*, 2016.

Shuai Zheng, Ziyue Huang, and James Kwok. Communication-efficient distributed blockwise momentum sgd with error-feedback. In *Advances in Neural Inf. Proc. Sys.*, pp. 11446–11456, 2019.