Continuous Deep Q-Learning in Optimal Control Problems: Normalized Advantage Functions Analysis

Abstract

One of the most effective continuous deep reinforcement learning algorithms is normalized advantage functions (NAF). The main idea of NAF consists in the approximation of the Q-function by functions quadratic with respect to the action variable. This idea allows to apply the algorithm to continuous reinforcement learning problems, but on the other hand, it brings up the question of classes of problems in which this approximation is acceptable. The presented paper describes one such class. We consider reinforcement learning problems obtained by the time-discretization of certain optimal control problems. Based on the idea of NAF, we present a new family of quadratic functions and prove its suitable approximation properties. Taking these properties into account, we provide several ways to improve NAF. The experimental results confirm the efficiency of our improvements.

1   Introduction

The standard reinforcement learning (RL) [Sutton and Barto, 2018] setup consists of an agent interacting with an environment. At each step of the interaction, the agent determines an action based on its policy and its current state, gets a reward, and makes a transition to the next state. The aim of the agent is to learn the policy that maximizes the sum of rewards.

One of the most widespread approach for solving RL problems is Q-learning [Watkins and Dayan, 1992], which consist in seeking the optimal action-value function (Q-function) as a solution of the Bellman optimality equation. After the learning, the agent can act optimally by the found Q-function. Initially, Q-learning approach was applied for solving RL problems with finite state and action spaces. In this case, Q-function can be represented by a finite table. For the case of a large or continuous state space, Q-learning has later been extended to Deep Q-learning algorithm [Mnih et al., 2015] which allows to seek the approximations of Q-function in the class of neural networks by means of the stochastic gradient descent. Deep Q-learning and its modifications have shown efficiency for a range of challenging tasks [Wang et al., 2016, van Hasselt et al., 2016, Schaul et al., 2016, Hessel et al., 2018]. However, this algorithm can not be directly applied for solving RL problems with continuous action spaces. The reason is that Deep Q-learning involves maximizing of approximate Q-function by the action variable on each step of the learning, which is a complex procedure for continuous action spaces. Among various approaches to overcome this problem [Lillicrap et al., 2016, Haarnoja et al., 2017, Kalashnikov et al., 2018, Lim et al., 2019, Ryu et al., 2020, Lutter et al., 2021], we focus on the idea of the normalized advantage functions (NAF) algorithm [Gu et al., 2016], which consists in the approximation of Q-function by the function quadratic with respect to the action variable. It allows to calculate the maximum quite fast and precisely and solve some challenging control problems [Gu et al., 2017, Dong et al., 2018, Ikemoto and Ushio, 2021], but on the other hand, it brings up the

question of classes of RL problems in which this approximation is acceptable. The presented paper describes one of the possible answers to this question.

Note that the class of LQR problems [Bradtke et al., 1994] has Q-functions quadratic with respect to the action variable. However, this class, being quite special, is not suitable for the description of non-linear controlled processes. In this paper, we study a wider (in some sense) class of RL problems. We consider RL problems which are obtained by time-discretization of finite-horizon optimal control problems [Bardi and Dolcetta, 1997] in dynamical system is described by affine in control ordinary differential equations and the cost functional is quadratic in control. Note that a lot of RL problems with continuous action spaces arise from control problems for mechanical or robotic systems [Lillicrap et al., 2016, Gu et al., 2016, Haarnoja et al., 2017, Gu et al., 2017, Kalashnikov et al., 2018] which are, in fact, described by affine in control ordinary differential equations. Besides, often, the quality index in a control problem can be determined as quadratic in control. For instance, if the quality index in an initial problem does not depend on control, then one can add a small quadratic term such that, on the one hand, the quality index becomes quadratic, and on the other hand, the sense of the problem does not changed much. Thus, the class of control problems under consideration seems quite general.

For this class, based on the idea of NAF, we present a new family of quadratic functions and prove that, first, this family is sufficiently rich to approximately solve the Bellman optimality equation (Theorem 1), and second, any sufficiently accurate solution, from this family, of the Bellman optimality equation allows to approximately obtain the optimal policy in the corresponding optimal control problem (Theorem 2). Moreover, we prove that it is impossible to get the same results for the original family of functions from Gu et al. [2016] (Theorem 3). Next, we provide several ways to utilize the obtained theoretical knowledge in order to improve NAF. The experimental results confirm the efficiency of our improvements.

Note that, in contrast to LQR problems, we can not say that Q-function is quadratic in our class of problems. Moreover, it is not true in general case. Nonetheless, according to presented statements (Theorem 1,2), Q-function can be approximated by quadratic functions with sufficient order of accuracy to obtain near-optimal policy.

2 Background

The standard reinforcement learning (RL) setup consists of an agent interacting with an environment [Sutton and Barto, 2018]. This interaction is described by a Markov Decision Process (MDP), which is a tuple $(\mathcal{S}, \mathcal{U}, \mathcal{P}, \mathcal{R}, \rho_0, \gamma)$, where $\mathcal{S}$ is a state space, $\mathcal{U}$ is an action space, $\mathcal{P}(s'|s, u)$ is a transition distribution, $\mathcal{R}(s, u)$ is a reward function, $\rho_0(s)$ is an initial state distribution, and $\gamma \in [0, 1]$ is a discount factor. The aim of the agent is to learn optimal policy $\mu_*(s)$ which maximizes the value

$$J(\mu) = \mathbb{E}\left[\sum_{i=0}^{\infty} \gamma^i \mathcal{R}(s_i, u_i) \,|\, s_0 \sim \rho_0(s_0),\ u_i = \mu(s_i),\ s_{i+1} \sim \mathcal{P}(s_{i+1}|s_i, u_i), i = 0, 1, 2, \ldots \right].$$

In the general statement of reinforcement learning problems, a policy of the agent can be stochastic, however, within this paper, we assume that the policy is deterministic.

One of the most effective approach for solving RL problems is Q-learning [Watkins and Dayan, 1992], which consist in seeking the optimal action-value function

$$Q_*(s, u) = \sup_{\mu} \mathbb{E}\left[\sum_{i=0}^{\infty} \gamma^i \mathcal{R}(s_i, u_i) \,|\, s_0 = s,\ u_0 = u, \right.$$
$$\left. s_{i+1} \sim \mathcal{P}(s_{i+1}|s_i, u_i),\ u_{i+1} = \mu(s_{i+1}),\ i = 0, 1, 2, \ldots \right]$$

as a solution of the Bellman optimality equation

$$Q_*(s, u) = \mathbb{E}\left[\mathcal{R}(s, u) + \gamma \max_{u' \in \mathcal{U}} Q_*(s', u') \,|\, s' \sim P(s'|s, u) \right].$$

In other words, the agent solves the following minimization problem:

$$\sup_{s \in \mathcal{S}, u \in \mathcal{U}} \left| Q(s, u) - \mathbb{E}\left[\mathcal{R}(s, u) + \gamma \max_{u' \in \mathcal{U}} Q(s', u') \,|\, s' \sim \mathcal{P}(s'|s, u) \right] \right| \to \inf_{Q}. \tag{1}$$

If the agent knows the function $Q_*(s, a)$, it can act optimally by the greedy policy

$$\mu_*(s) \in \underset{u \in \mathcal{U}}{\arg\max}\, Q_*(s, u).$$

Initially, the Q-learning approach was applied for solving RL problems with finite state and action spaces. In this case, the Q-function is represented by a finite table and problem (1) is finite-dimensional. For the case of a large or continuous state space, Q-learning has later been extended to Deep Q-learning algorithm [Mnih et al., 2015] which allows to seek approximations of Q-function in the class of neural networks $Q(x, u|\theta^Q)$, where θ^Q is the parameter vector of the neural network. During the learning, the experiences (s_i, u_i, r_i, s_{i+1}) are stored in the buffer $\mathcal{D}$ and simultaneously the parameter vector θ^Q is updated by means of the stochastic gradient descent minimizing the loss function

$$L(\theta^Q) = \mathbb{E}\big[(Q(s, u|\theta^Q) - y)^2 \,|\, (s, u, r, s') \sim U(\mathcal{D})\big], \quad y = r + \gamma \max_{u' \in \mathcal{U}} Q(s', u'|\theta^Q). \quad (2)$$

where $U(\mathcal{D})$ is the uniform distribution on $\mathcal{D}$. Deep Q-learning and its modifications are effective for a range of challenging tasks [Wang et al., 2016, van Hasselt et al., 2016, Schaul et al., 2016, Hessel et al., 2018]. However, note that this algorithm can not be directly applied for solving RL problems with continuous action spaces. The reason is that Deep Q-learning involves the maximizing in (2) on each step of the learning, which is a complex procedure for continuous $\mathcal{U}$. Among various approaches to overcome this problem [Lillicrap et al., 2016, Haarnoja et al., 2017, Kalashnikov et al., 2018, Lim et al., 2019, Ryu et al., 2020, Lutter et al., 2021], we focus on an idea of the normalized advantage functions (NAF) algorithm [Gu et al., 2016]. This idea consists in the approximation of Q-function by the following quadratic with respect to u functions:

$$\begin{aligned} Q(s, u|\theta^Q) &= V(s|\theta^V) + A(s, u|\theta^A), \\ A(s, u|\theta^A) &= -\frac{1}{2}(u - \mu(s|\theta^\mu))^T P(s|\theta^P)(u - \mu(s|\theta^\mu)), \end{aligned} \quad (3)$$

where $V(s|\theta^V)$, $\mu(s|\theta^\mu)$, and $P(s|\theta^P)$ are neural networks with parameters θ^V, θ^μ, and θ^P, respectively; $P(s|\theta^P)$ is a positive-definite square matrix for each s and θ^P; $\theta^A = \{\theta^\mu, \theta^P\}$ and $\theta^Q = \{\theta^A, \theta^V\}$. Under the condition

$$\mu(s|\theta^\mu) \in U, \quad (4)$$

it allows to get the maximum and argmaximum values directly by values of $V(s|\theta^V)$ and $\mu(s|\theta^\mu)$:

$$\max_{u \in \mathcal{U}} Q(s, u|\theta^Q) = V(s|\theta^V), \quad \underset{u \in \mathcal{U}}{\mathrm{Argmax}}\, Q(s, u|\theta^Q) = \mu(s|\theta^\mu), \quad (5)$$

but on the other hand, it brings up the question of classes of RL problems in which quadratic approximations is acceptable. Below, we describes one such class.

3 Problem statement

In this section, we consider a certain class of optimal control problems and show that discrete approximations of these problems can be formalized as RL problems.

Consider the following optimal control problem: it is required to maximize the functional

$$J(u(\cdot)) = \sigma(x(T)) - \int_0^T \big(q(t, x(t)) + u(t)^T r(t, x(t))u(t)\big)dt, \quad (6)$$

over all $u(\cdot)$, where $x(\cdot)$ is the solution [Filippov, 1988, §1] of the differential equation

$$\frac{d}{dt}x(t) = f(t, x(t)) + g(t, x(t))u(t), \quad t \in [0, T], \quad (7)$$

under the initial condition

$$x(0) = z. \quad (8)$$

Here t is the time variable, $T > 0$ is the terminal instant of time, $x(t) \in \mathbb{R}^n$ is the current state vector, $u(t) \in U$ is the current control action vector forming the measurable function $u(\cdot)$, $U \subset \mathbb{R}^m$ is the nonempty compact set, $z \in \mathbb{R}^n$ is the fixed initial state vector, $f(t, x) \in \mathbb{R}^n$, $g(t, x) \in \mathbb{R}^{n \times m}$,

$q(t,x) \in \mathbb{R}$, $r(t,x) \in \mathbb{R}^{m \times m}$, $(t,x) \in [0,T] \times \mathbb{R}^n$ are continuous with respect to t and continuously differentiable with respect to x functions, $r(t,x)$ is the positive-definite matrix for each $(t,x) \in [0,T] \times \mathbb{R}^n$, and $\sigma(x) \in \mathbb{R}$, $x \in \mathbb{R}^n$ is the continuously differentiable function. We assume that there exists a constant $c_{fg} > 0$ such that

$$\|f(t,x) + g(t,x)u\| \leq (1 + \|x\|)c_{fg}, \quad (t,x) \in [0,T] \times \mathbb{R}^n, \quad u \in U. \tag{9}$$

Note that, under these conditions, for each function $u(\cdot)$, there exists a unique solution $x(\cdot)$ of equation (7) under the initial condition (8) [Filippov, 1988, §1].

Define the value function in optimal control problem (6), (7) by

$$V_*(t_*, x_*) = \sup_{u(\cdot)} \left(\sigma(x(T)) - \int_{t_*}^{T} \big(q(t, x(t)) + u(t)^T r(t, x(t)) u(t) \big) dt \right), \tag{10}$$
$$(t_*, x_*) \in [0,T] \times \mathbb{R}^n,$$

where, for each $u(\cdot)$, $x(\cdot)$ is the solution of equation (7) on the interval $[t_*, T]$ under the initial condition $x(t_*) = x_*$.

Define the sets

$$S = \big\{ (t,x) \in [0,T] \times \mathbb{R}^n \colon \|x\| \leq (1 + \|z\|)e^{c_{fg}t} - 1 \big\}, \quad S(t) = \big\{ x \in \mathbb{R}^n \colon (t,x) \in S \big\}. \tag{11}$$

Let $k \in \mathbb{N}$, $\Delta t_k = T/k$, and $t_i = i\Delta t_k$, $i \in \overline{0,k}$. Consider the corresponding discrete optimal control problem: it is required to maximize the function

$$J_k(u_0, u_1, \ldots u_{k-1}) = \sigma(x_k) - \Delta t_k \sum_{i=0}^{k-1} \big(q(t_i, x_i) + u_i^T r(t_i, x_i) u_i \big), \tag{12}$$

over all $u_i \in U$, $i \in \overline{0, k-1}$, where $(x_0, x_1, \ldots, x_k)$ is defined by

$$x_0 = z, \quad x_{i+1} = x_i + (f(t_i, x_i) + g(t_i, x_i)u_i)\Delta t_k, \quad i \in \overline{0, k-1}. \tag{13}$$

Let us show that problem (12), (13) can be formalized as the RL problem. First, we define the state and actions spaces, the initial state distribution, and the discount factor as follows:

$$\mathcal{S} = \cup_{i=0}^{k} \big(\{t_i\} \times S(t_i) \big) \cup s_T, \quad \mathcal{U} = U, \quad \rho_0(s_0) = \delta(s_0 = (0, z)), \quad \gamma = 1. \tag{14}$$

Here s_T is some fictional terminal state, δ is Dirac delta distribution. Next, for every $i \in \overline{0, k-1}$, $x \in S(t_i)$, and $u \in U$, we define the transition distribution and the reward function by

$$\mathcal{P}(s'|s = (t_i, x), u) = \delta(s' = (t_{i+1}, x')), \quad \mathcal{R}(s = (t_i, x), u) = -\big(q(t_i, x) + u^T r(t_i, x)u \big)\Delta t_k, \tag{15}$$

where $x' = x + (f(t_i, x) + g(t_i, x)u)\Delta t_k$. Taking into account (9) and (11), one can prove the inclusion $(t_{i+1}, x') \in \mathcal{S}$. Hence, the transition distribution $\mathcal{P}$ is well-defined. For $i = k$, we set

$$\mathcal{P}(s'|s = (t_k, x), u) = \delta(s' = s_T), \quad \mathcal{R}(s = (t_k, x), u) = \sigma(x), \quad x \in S(t_k), \quad u \in U. \tag{16}$$

In order to make dynamical processes (13) formally infinite, we put

$$\mathcal{P}(s'|s_T, u) = \delta(s' = s_T), \quad \mathcal{R}(s_T, u) = 0, \quad u \in U. \tag{17}$$

Thus, we define MDP which describes the RL problem corresponding to problem (12), (13). Next, we show that such RL problems is suitable for using quadratic approximations of the Q-function.

4 Quadratic approximations of the Q-function

Denote by $\mathbb{Q}$ the family of functions Q such that

$$Q(t, x, u) = V(t, x) + A(t, x, u), \quad (t, x, u) \in [0, T) \times \mathbb{R}^n \times U, \tag{18}$$

where

$$A(t, x, u) = -(u - \tilde{\mu}(t, x))^T P(t, x)(u - \tilde{\mu}(t, x))$$
$$+ (\mu(t, x) - \tilde{\mu}(t, x))^T P(t, x)(\mu(t, x) - \tilde{\mu}(t, x)) \tag{19}$$
$$\mu(t, x) \in \underset{u' \in U}{\operatorname{argmin}} \, (u' - \tilde{\mu}(t, x))^T P(t, x)(u' - \tilde{\mu}(t, x)).$$

125 Here $V(t, x)$, $\tilde{\mu}(t, x)$, and $P(t, x)$ are continuous functions; $P(t, x)$ is a positive-definite square
126 matrix for each $(t, x) \in [0, T) \times \mathbb{R}^n$.

127 Note that, functions Q from the family $\mathbb{Q}$ satisfy the equalities

$$\max_{u \in U} Q(t, x, u) = V(t, x), \quad \underset{u \in U}{\text{Argmax}}\, Q(t, x, u) = \mu(t, x), \tag{20}$$

128 as well as (see (5)) quadratic functions from family (3). However, these function families are different.
129 The difference is that we do not assume the inclusion $\tilde{\mu}(t, x) \in U$ as opposed to assumption (4).

130 The theorems below establish a connection between the optimal control problem (6)–(8) and mini-
131 mization problems (1) for MDP (14)–(17).

132 **Theorem 1.** Let the value function $V_*(t, x)$ be continuously differentiable. Then, for every $\varepsilon > 0$,
133 there exists $k_* > 0$ such that, for every $k \geq k_*$, the function $Q \in \mathbb{Q}$ defined by (18) and (19) where

$$V(t, x) = V_*(t, x), \quad P(t, x) = r(t, x)\Delta t_k, \quad \tilde{\mu}(t, x) = \frac{1}{2} r^{-1}(t, x) g^T(t, x) \nabla_x V_*(t, x) \tag{21}$$

134 satisfies the inequality

$$\left| Q(t_i, x, u) + \left(q(t_i, x) + u^T r(t_i, x) u \right) \Delta t_k - \max_{u' \in U} Q(t_{i+1}, x', u') \right| \leq \varepsilon \Delta t_k,$$
$$x' = x + \left(f(t_i, x) + g(t_i, x) u \right) \Delta t_k, \quad u \in U, \quad x \in S(t_i), \quad i \in \overline{0, k-1}, \tag{22}$$

135 where we assume $Q(t_k, x', u') = \sigma(x')$.

136 **Theorem 2.** Let the value function $V_*(t, x)$ be continuously differentiable. Let $\varepsilon > 0$ and $k_* > 0$ be
137 defined according to Theorem 1. Take $k \geq k_*$ and suppose that a function $Q \in \mathbb{Q}$ satisfies inequality
138 (22). Then the following estimate holds:

$$J_k(u_0, u_1, \ldots u_{k-1}) \geq \sup_{u(\cdot)} J(u(\cdot)) - 3T\varepsilon, \tag{23}$$

139 where the function $J_k(u_0, u_1, \ldots u_{k-1})$ is defined by (12) with $u_i = \mu(t_i, x_i)$, $i \in \overline{0, k-1}$ and the
140 function $\mu(t, x)$ is defined by Q according to (18) and (19).

141 Thus, Theorem 1 shows that the function family $\mathbb{Q}$ is sufficiently rich to contain approximate solutions
142 of problem (1) with a predetermined accuracy and Theorem 2 establishes that all such approximate
143 solutions contained in $\mathbb{Q}$ allow us to get the policy, which approximately provides the optimal result
144 in optimal control problem (6)–(8).

145 Now, let us consider the original family of functions from Gu et al. [2016]. Denote by $\mathbb{Q}_{NAF}$ the
146 family of functions Q such that

$$Q(t, x, u) = V(t, x) - (u - \mu(t, x))^T P(t, x)(u - \mu(t, x)), \quad (t, x, u) \in [0, T) \times \mathbb{R}^n \times U, \tag{24}$$

147 where $V(t, x)$, $\mu(t, x)$, and $P(t, x)$ are continuous functions; $P(t, x)$ is a positive-definite square
148 matrix for each $(t, x) \in [0, T) \times \mathbb{R}^n$; $\mu(t, x) \in U$ for each $(t, x) \in [0, T) \times \mathbb{R}^n$. The theorem below
149 establishes that if we take the family $\mathbb{Q}_{NAF}$ instant of $\mathbb{Q}$, then Theorem 1 can not be proved even in
150 the simplest cases of optimal control problem (6)–(8).

Theorem 3. Let $n = m = 1$, $T = 1$, $U = [-1, 1]$, $f(t, x) = q(t, x) = 0$, $g(t, x) = r(t, x) = 1$,
$\sigma(x) = -x^2$, and $z = 2$. Then, for every $k \geq 4$ and $Q \in \mathbb{Q}_{NAF}$, there exist $i \in \overline{0, k-1}$, $x \in S(t_i)$,
and $u \in U$ such that

$$\left| Q(t_i, x, u) + u^2 \Delta t_k - \max_{u' \in U} Q(t_{i+1}, x', u') \right| > \Delta t_k / 8, \quad x' = x + u\Delta t_k,$$

151 where we assume $Q(t_k, x', u') = -(x')^2$.

152 Proofs of the theorems are given in the Appendix A.

5 Experiments

We consider four examples of optimal control problems (6)–(8) described in Table 1, where

$$\sigma_1(x) = -x_1^2 - x_2^2, \quad \sigma_2(x) = -|x_1| - 0.1|x_2|, \quad \sigma_3(x) = -|x_1 - 4| - |x_2| - |x_3 - 0.75\pi|$$

$$\sigma_3(x) = -x_1^2 - x_2^2 - (x_3 - 2)^2 - (x_4 - 2)^2$$

Table 1: Parameters in the examples of optimal control problems

Name	n	m	T	U	$f(t,x)$	$g(t,x)$	$q(t,x)$	$r(t,x)$	σ	z
Van der Pol oscillator	2	1	11	$[-1,1]$	$\begin{pmatrix} x_2 \\ (1-x_1^2)x_2 \end{pmatrix}$	$\begin{pmatrix} 0 \\ -x_1 \end{pmatrix}$	0	0.05	$\sigma_1(x)$	$\begin{pmatrix} 1 \\ 0 \end{pmatrix}$
Pendulum	2	1	5	$[-2,2]$	$\begin{pmatrix} x_2 \\ 14.7\sin(x_1) \end{pmatrix}$	$\begin{pmatrix} 0 \\ 3 \end{pmatrix}$	0	0.01	$\sigma_2(x)$	$\begin{pmatrix} \pi \\ 0 \end{pmatrix}$
Dubins car	3	1	2π	$[-0.5,1]$	$\begin{pmatrix} \cos(x_3) \\ \sin(x_3) \\ 0 \end{pmatrix}$	$\begin{pmatrix} 0 \\ 0 \\ 1 \end{pmatrix}$	0	0.05	$\sigma_3(x)$	$\begin{pmatrix} 0 \\ 0 \\ 0 \end{pmatrix}$
A target problem	6	2	10	$[-1,1]^2$	$\begin{pmatrix} 0 \\ 0 \\ x_5 \\ x_6 \\ x_1-x_3 \\ x_2-x_4 \end{pmatrix}$	$\begin{pmatrix} 1 & 0 \\ 0 & 1 \\ 0 & 0 \\ 0 & 0 \\ 0 & 0 \\ 0 & 0 \end{pmatrix}$	0	0.001	$\sigma_4(x)$	$\begin{pmatrix} 0 \\ 0 \\ 0 \\ 0 \\ 0 \\ 0 \end{pmatrix}$

Van der Pol oscillator is a famous model of a non-conservative oscillator with non-linear damping. The aim of the control is to stabilize the oscillator at the terminal time.

Pendulum is a traditional problem for testing control algorithms. The aim of the control is the stabilization of the pendulum in the top position at the terminal time.

Dubins car is a quite famous model which describes a motion of the point particle moving at a constant speed on the plane. The problem is to find a control providing the closeness of the motion with a target point at the terminal time.

A target problem is an optimal control problem presented in Munos [2006]. The dynamic system describes a hand holding a spring to which is attached a mass. It is required to control the hand such that the mass achieve the target point at the terminal time.

5.1 Bounded NAF

First, we modify NAF algorithm, proposed in Gu et al. [2016], based on the function family $\mathbb{Q}$. Note that, the considered examples have $U = [\alpha, \beta]^m$. Denote $\text{clip}(\nu) = \max\{\alpha, \min\{\beta, \nu\}\}$, $\nu \in \mathbb{R}^m$, $\alpha, \beta \in \mathbb{R}^m$. Then, according to (18) and (19), we can use the following approximation of the Q-function, within NAF algorithm:

$$Q(t, x, u|\theta^Q) = V(t, x|\theta^V) + A(t, x, u|\theta^A),$$
$$A(t, x, u|\theta^A) = -\big(u - \tilde{\mu}(t, x|\theta^{\tilde{\mu}})\big)^T P(t, x|\theta^P)\big(u - \tilde{\mu}(t, x|\theta^{\tilde{\mu}})\big)$$
$$+ \big(\text{clip}(\tilde{\mu}(t, x|\theta^{\tilde{\mu}})) - \tilde{\mu}(t, x|\theta^{\tilde{\mu}})\big)^T P(t, x|\theta^P)\big(\text{clip}(\tilde{\mu}(t, x|\theta^{\tilde{\mu}})) - \tilde{\mu}(t, x|\theta^{\tilde{\mu}})\big),$$

where $V(t, x|\theta^V)$, $\tilde{\mu}(t, x|\theta^{\tilde{\mu}})$, and $P(t, x|\theta^P)$ are neural networks with parameters θ^V, $\theta^{\tilde{\mu}}$, and θ^P, respectively; $P(t, x|\theta^P)$ is a positive-definite square matrix for each (t, x) and θ^P; $\theta^A = \{\theta^{\tilde{\mu}}, \theta^P\}$ and $\theta^Q = \{\theta^A, \theta^V\}$. To be short, we call this algorithm Bounded NAF (BNAF), because it is essential for our modification of NAF that the set U is bounded.

5.2 Reward-based BNAF

If we know the function $r(t, x)$, then, according to Theorem 1, we can use the function $r(t, x)\Delta t_k$ instead of the neural network $P(t, x|\theta^P)$ to reduce the number of learning parameters. This variant of BNAF is called Reward-based BNAF (RB-BNAF).

Figure 1: Performance of NAF, BNAF, RB-BNAF, GB-BNAF, DDPG algorithms averaged over 10 seeds. The curves are averaged for 20 episode for better visualization.

5.3 Gradient-based BNAF

If we also know the function $g(t, x)$, then, according to the Theorem 1, we can use the function

$$\tilde{\mu}(t, x|\theta^V) = \frac{1}{2}r^{-1}(t, x)g^T(t, x)\nabla_x V(t, x|\theta^V)$$

instead of the neural network $\tilde{\mu}(t, x|\theta^{\tilde{\mu}})$. It also reduces the number of learning parameters. This variant of BNAF is called Gradient-based BNAF (GB-BNAF).

5.4 Experimental results

We use the same learning parameters of every our tasks. We apply neural networks with two layers of 256 and 128 rectified linear units (ReLU) and learn their used ADAM with the learning rate $lr = 1e^{-3}$. We use batch size $n_{bs} = 128$ and smoothing parameter $\tau = 1e^{-2}$. Also we take $\Delta t = 0.1$. All calculations were performed on a personal computer in a standard way.

We compare NAF, BNAF, RB-BNAF, GB-BNAF algorithms, and DDPG algorithm presented in [Lillicrap et al., 2016]. Figure 1 shows learning curves of the algorithms for the considered examples. One can note that RB-BNAF algorithm has a good performance in all examples. GB-BNAF is slightly inferior to RB-BNAF everywhere except A target problem. DDPG and BNAF have excellent results only one example out of four. NAF algorithm shows not the worst performance only in Pendulum example.

Thus, taking the presented experiments into account, we can give the following general recommendations. For solving optimal control problems (6)–(8), it is rational to use GB-BNAF and especially RB-BNAF algorithms along with NAF and DDPG algorithms. There is a high probability that they will show better results and more stable learning.

6 Related works

Many different ways to apply reinforcement learning approaches for solving optimal control problems are investigated [Baird, 1994, Doya, 1995, 2000, Munos, 2006, Tallec et al., 2019, Kim and Yang, 2020, Lutter et al., 2021]. Among them, a time-discretization is perhaps the most obvious and widely used tool [Lillicrap et al., 2016, Gu et al., 2016, Haarnoja et al., 2017, Gu et al., 2017, Kalashnikov et al., 2018]. From the theoretical point of view, it is known [Bardi and Dolcetta, 1997, p.388] that solutions of time-discrete optimal control problems converge to the solution of the initial problem as the discretization step tends to zero. In the present paper, we also use the time-discretization and study approximating solutions of Bellman equations and the corresponding greedy politics depending on the discretization step (see Theorems 1 and 2). Other studies of dependencies on the discretization step of reinforcement learning methods can be found in Munos [2006], Tallec et al. [2019].

We focus on the idea from Gu et al. [2016] to expand Q-learning algorithm to optimal control and reinforcement learning problems with continuous actions. Other approaches for solving such problems are investigated in Lillicrap et al. [2016], Haarnoja et al. [2017], Kalashnikov et al. [2018], Lim et al. [2019], Ryu et al. [2020], Lutter et al. [2021]. The paper Lutter et al. [2021] seems the closest to the presented paper. In Lutter et al. [2021], the similar optimal control problem and feedback control policy are considered, but the proposed algorithms require knowledge of the right-hand side of differential equations in contrast to algorithms suggested in presented paper.

Let us also note the family of functions (18), (19) is included, in some sense, to families of Q-functions considered in Wang et al. [2016], Tallec et al. [2019]. It seems to be expected because more general classes of problems are considered in these papers. Nevertheless, the proposed algorithms and results are very different from presented in this paper.

References

L. C. Baird. Reinforcement learning in continuous time: Advantage updating. *Proceedings of 1994 IEEE International Conference on Neural Networks*, 1994.

M. Bardi and I. C. Dolcetta. *Optimal Control and Viscosity Solutions of Hamilton-Jacobi-Bellman Equations*. Birkhauser, Boston, 1997.

S. J. Bradtke, B. E. Ydstie, and A. G. Barto. Adaptive linear quadratic control using policy iteration. *Proceedings of American Control Conference*, 1994. doi: 10.1109/ACC.1994.735224.

X. Dong, J. Shen, W. Wang, Y. Liu, L. Shao, and F. Porikli. Hyperparameter optimization for tracking with continuous deep q-learning. *Proceedings of the IEEE Conference on Computer Vision and Pattern Recognition (CVPR)*, pages 518–527, 2018. doi: 10.1109/CVPR.2018.00061.

K. Doya. Temporal difference learning in continuous time and space. *Proceedings of the 8th International Conference on Neural Information Processing Systems*, pages 1073–1079, 1995.

K. Doya. Reinforcement learning in continuous time and space. *Neural Computation*, 12:219–245, 2000. doi: 10.1162/089976600300015961.

A. F. Filippov. *Differential Equations with Discontinuous Righthand Sides*. Springer, Berlin, 1988.

S. Gu, T. Lillicrap, I. Sutskever, and S. Levine. Continuous deep q-learning with model-based acceleration. *Proceedings of the 33rd International Conference on Machine Learning*, 48:2829–2838, 2016.

S. Gu, E. Holly, T. Lillicrap, and S. Levine. Deep reinforcement learning for robotic manipulation with asynchronous off-policy updates. *Proceedings 2017 IEEE International Conference on Robotics and Automation (ICRA)*, 2017. doi: 10.1109/ICRA.2017.7989385.

T. Haarnoja, H. Tang, P. Abbeel, and S. Levine. Reinforcement learning with deep energy-based policies. *Proceedings of the 34th International Conference on Machine Learning*, 70:1352–1361, 2017.

M. Hessel, J. Modayil, H. van Hasselt, T. Schaul, G. Ostrovski, W. Dabney, D. Horgan, B. Piot, M. Azar, and D. Silver. Rainbow: Combining improvements in deep reinforcement learning. *Proceedings of The Thirty-Second AAAI Conference on Artificial Intelligence*, pages 3215–3222, 2018.

J. Ikemoto and T. Ushio. Continuous deep q-learning with simulator for stabilization of uncertain discrete-time systems. *arXiv:2101.05640*, 2021.

D. Kalashnikov, A. Irpan, P. Pastor, J. Ibarz, A. Herzog, E. Jang, D. Quillen, E. Holly, M. Kalakrishnan, V. Vanhoucke, and S. Levine. Scalable deep reinforcement learning for vision-based robotic manipulation. *2nd Conference on Robot Learning (CoRL 2018)*, 87:651–673, 2018.

J. Kim and I. Yang. Hamilton-jacobi-bellman equations for q-learning in continuous time. *Proceedings of the 2nd Conference on Learning for Dynamics and Control*, 120:739–748, 2020.

T. P. Lillicrap, J. J. Hunt, A. Pritzel, N. Heess, T. Erez, Y. Tassa, D. Silver, and D. Wierstra. Continuous control with deep reinforcement learning. *International Conference on Learning Representations (ICLR)*, 2016.

S. Lim, A. Joseph, L. Le, Y. Pan, and M. White. Actor-expert: A framework for using q-learning in continuous action spaces. *arXiv:1810.09103*, 2019.

M. Lutter, S. Mannor, J. Peters, D. Fox, and A. Garg. Value iteration in continuous actions, states and time. *Proceedings of the 38th International Conference on Machine Learning*, 139:7224–7234, 2021.

V. Mnih, K. Kavukcuoglu, D. Silver, A. A. Rusu, J. Veness, M. G. Bellemare, A. Graves, M. Riedmiller, A. K. Fidjeland, G. Ostrovski, S. Petersen, C. Beattie, A. Sadik, I. Antonoglou, H. King, D. Kumaran, D. Wierstra, S. Legg, and D. Hassabis. Human-level control through deep reinforcement learning. *Nature*, 518(7540):529–533, 2015. doi: 10.1038/nature14236.

R. Munos. Policy gradient in continuous time. *Journal of Machine Learning Research*, 7:771–791, 2006.

M. Ryu, Y. Chow, R. M. Anderson, C. Tjandraatmadja, and C. Boutilier. Caql: Continuous action q-learning. *Proceedings of the Eighth International Conference on Learning Representations*, 2020.

T. Schaul, J. Quan, I. Antonoglou, and D. Silver. Prioritized experience replay. *International Conference on Learning Representations (ICLR)*, 2016.

R. S. Sutton and A. G. Barto. *Reinforcement Learning An Introduction (Second Edition)*. The MIT Press, Cambridge, Massachusetts, 2018.

C. Tallec, L. Blier, and Y. Ollivier. Making deep q-learning methods robust to time discretization. *Proceedings of the 36th International Conference on Machine Learning*, 97:6096–6104, 2019.

H. van Hasselt, A. Guez, and D. Silver. Deep reinforcement learning with double q-learning. *Proceedings of the Thirtieth AAAI Conference on Artificial Intelligence (AAAI-16)*, 30(1):2094–2100, 2016.

Z. Wang, T. Schaul, M. Hessel, H. van Hasselt, M. Lanctot, and N. de Freitas. Dueling network architectures for deep reinforcement learning. *Proceedings of The 33rd International Conference on Machine Learning*, 48:1995–2003, 2016.

C. Watkins and P. Dayan. Q-learning. *Machine Learning*, 8:279–292, 1992. doi: 10.1007/BF00992698.