Inverse Optimal Control Adapted to the Noise Characteristics of the Human Sensorimotor System

Abstract

Computational level explanations based on optimal feedback control with signal-dependent noise have been able to account for a vast array of phenomena in human sensorimotor behavior. However, commonly a cost function is assumed for a task and the optimality of human behavior is evaluated by comparing observed and predicted trajectories. Here, we introduce inverse optimal control with signal-dependent noise, which allows inferring the cost function from observed behavior. To do so, we formalize the problem as a partially observable Markov decision process and distinguish between the agent's and the experimenter's inference problems. Specifically, we derive a probabilistic formulation of the evolution of states and belief-states and an approximation to the propagation equation in the linear-quadratic Gaussian problem with signal-dependent noise. We extend the model to the case of partial observability of state variables from the point of view of the experimenter. We show the feasibility of the approach through validation on synthetic data and application to experimental data. Our approach enables recovering the costs and benefits implicit in human sequential sensorimotor behavior thereby reconciling normative and descriptive approaches in a computational framework.

1 Introduction

Computational level theories of behavior strive to provide an answer to the questions, why a system behaves the way it does and what the goal of the system's computations is. Such goals can be formalized on the basis of the reward hypothesis. In the words of Richard Sutton, the reward hypothesis assumes, that "goals and purposes can be well thought of as maximization of the expected value of the cumulative sum of a received scalar signal" [1]. Thus, to understand human sensorimotor behavior, it is essential to characterize its goals and purposes quantitatively in terms of costs and benefits.

Stochastic optimal control allows formulating behavioral goals in terms of a cost function for tasks involving sequential actions under action variability, uncertainty in the internal model, and delayed rewards. The solution to the optimization problem entailed in the cost function is a sequence of actions, which is then compared to human movements. While early models emphasized costs related to the kinematics of movements [2], task goals were subsequently introduced as costs on the variance of the movement's endpoint [3]. Importantly, although this study considered open loop control, it revealed the importance in modeling the variability of human movements, which increases linearly with the magnitude of the control signal [4].

Including sensory feedback in optimal stochastic control leads to a computationally much more intricate problem, which can be formulated as a partially observable Markov decision process (POMDP) an which in general is intractable. One of the few tractable cases is the linear-quadratic Gaussian (LQG) setting, where dynamics are linear, costs are quadratic and variability is additive and

Gaussian, leading to sensory inference of the state and control to be decoupled [5]. However, not only is human movement variability signal dependent, but additionally the uncertainty of sensory signals increases linearly with the magnitude of the stimulus, a phenomenon known as Weber's law [6].

Todorov [7] extended the LQG case by introducing optimal stochastic feedback control with signal-dependent noise, which allows specification of noise models in line with what is known about the human sensorimotor system.This model [8] has been able to explain a broad range of phenomena in sensorimotor control [9, 10], including linear movement trajectories, smooth velocity profiles, speed-accuracy tradeoffs, and corrections of errors only if they influence attaining the behavioral goal. Particularly incorporating signal-dependent noise has been crucial in explaining experimental data, ranging from how corrections of movements during action execution depend on feedback and task goals [11], that movements consider sensory uncertainty and temporal delays in real-time [12], that movement plans in novel environments are reoptimized based on the learning of internal models to minimize implicit motor costs and maximize rewards [13], and many others [14, 15, 16, 12, 17].

Explaining human behavior in these studies usually starts by hypothesizing the cost function describing a task, obtaining the optimal feedback controller, and comparing simulated trajectories to those observed experimentally. This line of inquiry, therefore, utilizes similarity of trajectories to quantify the degree of optimality in human behaviors. In some cases [14], trajectories are simulated from the model to check for robustness with respect to changes in the model parameters. If our goal is to use optimal control models to infer such quantities, which often cannot be measured independently, from behavior, we need to invert the problem and find those parameter settings, which are consistent with the observed trajectories. While such inverse methods have been developed both in the field of reinforcement learning to infer the rewards being optimized by an agent [18, 19, 20] as well as in optimal control for the LQG case [21, 22, 23], this is currently not possible for the noise characteristics of the human sensorimotor system.

Here, we introduce a probabilistic formulation of inverse optimal feedback control under signal-dependent noise. We start from the forward problem introduced in [8]. We formulate the inference problem faced by an actor as a POMDP and distinguish it from the inference problem of an experimenter observing the actor. We proceed by deriving the likelihood of a sequence of observed states and provide an approximation to the non-Gaussian uncertainty due to the signal-dependent noise. First, this allows recovering the cost function underlying the actor's behavior from observed behavioral data. Second, we extend the inference of the cost function to the case in which the state variables are only partially observable to the experimenter, e.g. when only measuring the position of the agent's movement. Third, we show through simulated and experimental data that the cost functions can indeed be recovered. Fourth, the probabilistic formulation allows recovering the actor's belief during the experiment as well as the experimenter's uncertainty about the inferred belief.

Related Work

Inferring the cost functions underlying an agent's behavior has long been of interest in different scientific fields ranging from economics [24] and psychology [25] to neuroscience [26] and artificial intelligence, particularly reinforcement learning [18, 19, 20]. Inverse Reinforcement Learning (IRL) specifically addresses the question of inferring the cost function being optimized [18, 19] or approximately optimized [27] by an agent. Some work has particularly addressed sensorimotor behavior [28, 29, 30] and extensions to the partially observable setting have been presented [31].

More relevant to the present study are computational frameworks that invert Bayesian models of perception and decision making to infer beliefs and costs of the agent. While this literature is extensive, exemplary studies for trial based actions include cognitive tomography [32] and inference of the cost function in sensorimotor learning [33]. Extensions to sequential tasks have also been proposed, particularly considering active perception [34, 35], real world behavior [36], and general formulations [37, 38]. Very similarly, work on Bayesian theory of mind use highly related computational models [39, 40].

More specifically in the context of sensorimotor control, related work using inverse optimal feedback control based on LQR and LQG has considered different problem settings. [21] is concerned with finding the cost matrices and noise covariances given a known system with controller and Kalman gain. Similarly, [41] infers the above-mentioned cost matrices in the LQG setting based on observations but additionally takes constraints into account. The extension by [23] infers the terminal cost and the

Figure 1: The agent-experimenter loop and its formalization as POMDP together with the inference problems from the agent's point of view and from the experimenter's point of view.

state cost function together with an exponential discount factor in the LQR setting. A different line of work has been concerned with estimating the dynamics A, B, state sequence of x, and delay τ internal LQG models from neural population activity [22, 42] under the assumption that an agent might not know the dynamics, e.g. of a brain-computer interface. Other work [43] is concerned with learning a control policy from states, observations, and controls.

Our approach is different from previous research in two important ways. First, while most other approaches take different quantities, such as the filter or controller gains or the agent's observations or controls as given, we consider the setting that is typical in a behavioral experiment: The filter and controller as well as the agent's observations are internal to the experimental subject and cannot be observed. Instead, we assume that only trajectories $\boldsymbol{x}_{1:T}$ are observed. Second, other approaches to inverse optimal control in the LQG setting do not involve signal-dependent noise, which we address in this paper.

2 Background: LQG with sensorimorotor noise characterisitics

We model a human subject as an agent in a partially-observable environment as introduced by Todorov [7] and depicted in Fig. 1 A. For this we consider a discrete-time linear dynamical system with state $\boldsymbol{x}_t \in \mathbb{R}^m$ and control $\boldsymbol{u}_t \in \mathbb{R}^p$ with both control-independent and control-dependent noises

$$\boldsymbol{x}_{t+1} = A\boldsymbol{x}_t + B\boldsymbol{u}_t + V\boldsymbol{\xi}_t + \sum_{i=1}^{c} \epsilon_t^i C_i \boldsymbol{u}_t. \tag{1}$$

The noise terms $\boldsymbol{\xi}_t \in \mathbb{R}^m$ and $\epsilon_t^i \in \mathbb{R}$ are standard Gaussian random vectors and variables, respectively, resulting in control-independent noise with covariance VV^T and control-dependent noise having covariance $\sum_i C_i \boldsymbol{u}_t \boldsymbol{u}_t^T C_i^T$. The agent receives an observation $\boldsymbol{y}_t \in \mathbb{R}^k$ from the observation model

$$\boldsymbol{y}_t = H\boldsymbol{x}_t + W\boldsymbol{\omega}_t + \sum_{i=1}^{d} \varepsilon_t^i D_i \boldsymbol{x}_t. \tag{2}$$

The noise terms $\boldsymbol{\omega}_t \in \mathbb{R}^k$ and $\varepsilon_t \in \mathbb{R}$ are again standard Gaussian, so that the covariance of the state-independent observation noise is WW^T, while for the state-dependent observation noise it is $\sum_i D_i \boldsymbol{x}_t \boldsymbol{x}_t^T D_i^T$. The objective of the agent is to choose $\boldsymbol{u}_t$ to minimize a quadratic cost function,

$$J(\boldsymbol{u}_{1:T}) = \sum_{t=1}^{T} \boldsymbol{x}_t^T Q_t \boldsymbol{x}_t + \boldsymbol{u}_t^T R_t \boldsymbol{u}_t. \tag{3}$$

While the original LQG problem without control- and state-dependent noises can be solved exactly by determining an optimal linear filter and controller independently [5], this separation principle is no longer applicable in the case considered here. Todorov [7] introduced an approximate solution method in which the optimal filters K_t and controllers L_t are iteratively determined in an alternating fashion, leaving the respective other one constant. The resulting optimal filter, which minimizes the expected cost, is of the form

$$\tilde{\boldsymbol{x}}_{t+1} = A\tilde{\boldsymbol{x}}_t + B\boldsymbol{u}_t + K_t(\boldsymbol{y}_t - H\tilde{\boldsymbol{x}}_t) + E\boldsymbol{\eta}_t, \tag{4}$$

where $\boldsymbol{\eta}_t$ is a standard Gaussian random vector and represents internal estimation noise. The optimal linear control law can be formulated as

$$\boldsymbol{u}_t = -L_t \tilde{\boldsymbol{x}}_t. \tag{5}$$

For a detailed derivation and the resulting equations, the reader is referred to Todorov [7].

3 Inverse Optimal Control

In this paper, we consider the inverse problem, i.e. we observe an agent, who is acting optimally in an agent-experiment loop (Fig. 1 B) according to the model of Section 2, and want to infer properties of the agent's perceptual and action processes. These properties are represented by parameters $\boldsymbol{\theta}$, which may include for example subjective control costs (R) or parameters of the task objective (Q). Given a set of N independent trajectories $\{\boldsymbol{x}_{1:T}\}^{i=1:N}$, each of length T, we can infer $\boldsymbol{\theta}$ by maximizing the product of their individual likelihoods $p(\boldsymbol{x}_{1:T} \mid \boldsymbol{\theta})$, which decompose as

$$p(\boldsymbol{x}_{1:T} \mid \boldsymbol{\theta}) = p_{\boldsymbol{\theta}}(\boldsymbol{x}_1) \prod_{t=1}^{T-1} p_{\boldsymbol{\theta}}(\boldsymbol{x}_{t+1} \mid \boldsymbol{x}_{1:t}). \tag{6}$$

In the following, we drop the explicit dependency of the parameters $\boldsymbol{\theta}$. The graphical model from the agent's point of view (Fig. 1 A) is structurally identical to that from the experimenter's perspective (Fig. 1 C). But, since we as experimenter observe the true states $\boldsymbol{x}_{1:T}$ instead of the agent's noisy observations $\boldsymbol{y}_{1:T}$, the usual Markov property does not hold and each $\boldsymbol{x}_t$ generally depends on all previous states $\boldsymbol{x}_{1:t-1}$ via the agent's estimates and actions. To efficiently compute the likelihood factors $p(\boldsymbol{x}_t \mid \boldsymbol{x}_{1:t-1})$, we track our belief over the agent's belief $p(\tilde{\boldsymbol{x}}_t \mid \boldsymbol{x}_{1:t})$, which gives a sufficient statistic for the history. This approach allows propagating our uncertainty about the agent's beliefs and actions over time and track the agent's belief.

To compute the likelihood function for some value of $\boldsymbol{\theta}$, we first determine the control and filter gains L_t and K_t using the iterative method introduced by Todorov [7]. We then compute an approximate likelihood factor $p(\boldsymbol{x}_t \mid \boldsymbol{x}_{1:t-1})$ for each time step in the following way: First, we determine the distribution $p(\boldsymbol{x}_{t+1}, \tilde{\boldsymbol{x}}_{t+1} \mid \boldsymbol{x}_t, \tilde{\boldsymbol{x}}_t)$ which describes the joint evolution of $\boldsymbol{x}_t$ and $\tilde{\boldsymbol{x}}_t$ (Section 3.1). Second, we combine it with the belief distribution $p(\tilde{\boldsymbol{x}}_t \mid \boldsymbol{x}_{1:t})$ yielding $p(\boldsymbol{x}_{t+1}, \tilde{\boldsymbol{x}}_{t+1} \mid \boldsymbol{x}_{1:t})$ (Section 3.2). As this step cannot be done in closed-form due to the signal-dependent noise, we introduce a Gaussian approximation of this quantity. Third, marginalizing over $\tilde{\boldsymbol{x}}_{t+1}$ gives the desired likelihood factor $p(\boldsymbol{x}_{t+1} \mid \boldsymbol{x}_{1:t})$, while conditioning on the observed true states $\boldsymbol{x}_{t+1}$ gives the statistic of the history $p(\tilde{\boldsymbol{x}}_{t+1} \mid \boldsymbol{x}_{1:t+1})$, which we use for computing the likelihood factor of the following time step.

In Section 3.3, we extend this procedure to the setting, where the state $\boldsymbol{x}_t$ is only partially observed as a noisy linearly transformed version $\boldsymbol{o}_t$ (Fig. 1 D).

3.1 Joint dynamics of states and estimates

In this section, we derive the joint dynamics of states and estimates, specifying the distribution $p(\boldsymbol{x}_{t+1}, \tilde{\boldsymbol{x}}_{t+1} \mid \boldsymbol{x}_t, \tilde{\boldsymbol{x}}_t)$. To do so, we build on work by Van Den Berg et al. [44] who introduced this idea for the standard LQG case in the context of planning, and extend it to the model with state- and action-dependent noises as considered in Section 2. First, we substitute the control in the state update (1) with its law (5), giving

$$\boldsymbol{x}_{t+1} = A\boldsymbol{x}_t - BL\tilde{\boldsymbol{x}}_t + V\boldsymbol{\xi}_t - \sum_{i=1}^{d} \varepsilon_t^i C_i L_t \tilde{\boldsymbol{x}}_t, \tag{7}$$

and rewrite the filter update equation (4) as

$$\begin{aligned}
\tilde{\boldsymbol{x}}_{t+1} &= (A - BL_t)\tilde{\boldsymbol{x}}_t + K_t(\boldsymbol{y}_t - H\tilde{\boldsymbol{x}}_t) + E\boldsymbol{\eta}_t \\
&= (A - BL_t - K_t H)\tilde{\boldsymbol{x}}_t + K_t H \boldsymbol{x}_t + K_t W \boldsymbol{\omega}_t + K_t \sum_{i=1}^{c} \epsilon_t^i D_i \boldsymbol{x}_t + E\boldsymbol{\eta}_t.
\end{aligned} \tag{8}$$

Here, we have again inserted the control law (5), then the observation model (2) and rearranged terms. Equations (7) and (8) give us a representation of $\boldsymbol{x}_t$ and $\tilde{\boldsymbol{x}}_t$, which only depends on states or

estimates from the previous time step. Stacking both equations together, specifies the distribution $p(\boldsymbol{x}_{t+1}, \tilde{\boldsymbol{x}}_{t+1} \mid \boldsymbol{x}_t, \tilde{\boldsymbol{x}}_t)$, with

$$
\begin{bmatrix} \boldsymbol{x}_{t+1} \\ \tilde{\boldsymbol{x}}_{t+1} \end{bmatrix} = \begin{bmatrix} A & -(B + \sum_{i=1}^d \varepsilon_t^i C_i) L_t \\ K_t(H + \sum_{i=1}^c \epsilon_t^i D_i) & A - BL_t - K_t H \end{bmatrix} \begin{bmatrix} \boldsymbol{x}_t \\ \tilde{\boldsymbol{x}}_t \end{bmatrix} + \begin{bmatrix} V & 0 & 0 \\ 0 & K_t W & E \end{bmatrix} \begin{bmatrix} \boldsymbol{\xi}_t \\ \boldsymbol{\omega}_t \\ \boldsymbol{\eta}_t \end{bmatrix}
$$

$$
=: (F_t + M_t \sum_{i=1}^c \epsilon_t^i D_i) \boldsymbol{x}_t + (\tilde{F}_t + \sum_{i=1}^d \varepsilon_t^i C_i \tilde{M}_t) \tilde{\boldsymbol{x}} + G_t \boldsymbol{\zeta}_t, \tag{9}
$$

where $\boldsymbol{\zeta}_t \sim \mathcal{N}(0, I)$. For the exact definition of the matrices $F_t, \tilde{F}_t, M_t, \tilde{M}_t$ see Appendix B.1.

3.2 Approximate propagation

We obtain the distribution $p(\boldsymbol{x}_{t+1}, \tilde{\boldsymbol{x}}_{t+1} \mid \boldsymbol{x}_{1:t})$ by propagating $p(\tilde{\boldsymbol{x}}_t \mid \boldsymbol{x}_{1:t})$ through the joint dynamics model (9). But, since the latter involves a product of Gaussian random variables ε_t and $\tilde{\boldsymbol{x}}_t$, the result is no longer Gaussian in general. To make this distribution tractable, we approximate it by a Gaussian using moment matching. This allows us to maintain an approximate Gaussian belief over the agent's belief and gives us an approximation of the likelihood function in Eq. (6).

First, we assume that our belief over the agent's belief at time step t is given by a Gaussian distribution $p(\tilde{\boldsymbol{x}}_t \mid \boldsymbol{x}_{1:t}) = \mathcal{N}(\boldsymbol{\mu}_{\tilde{x}|x}, \Sigma_{\tilde{x}|x})$. To approximately propagate $p(\tilde{\boldsymbol{x}}_t \mid \boldsymbol{x}_{1:t})$ and the observation $\boldsymbol{x}_t$ through Eq. (9), we compute the mean and variance of the resulting distribution via moment matching (see Appendix D) and obtain the approximation

$$
p(\boldsymbol{x}_{t+1}, \tilde{\boldsymbol{x}}_{t+1} \mid \boldsymbol{x}_{1:t}) \approx \mathcal{N}\left(\begin{bmatrix} \boldsymbol{x}_{t+1} \\ \tilde{\boldsymbol{x}}_{t+1} \end{bmatrix} \,\middle|\, \hat{\boldsymbol{\mu}}_{t+1} = \begin{bmatrix} \hat{\boldsymbol{\mu}}_x \\ \hat{\boldsymbol{\mu}}_{\tilde{x}} \end{bmatrix}, \hat{\Sigma}_{t+1} = \begin{bmatrix} \hat{\Sigma}_{xx} & \hat{\Sigma}_{x\tilde{x}} \\ \hat{\Sigma}_{\tilde{x}x} & \hat{\Sigma}_{\tilde{x}\tilde{x}} \end{bmatrix} \right), \tag{10}
$$

with

$$
\hat{\boldsymbol{\mu}}_{t+1} = F_t \boldsymbol{x}_t + \tilde{F}_t \boldsymbol{\mu}_{\tilde{x}|x},
$$

$$
\hat{\Sigma}_{t+1} = M_t (\sum_{i=1}^c D_i \boldsymbol{x}_t \boldsymbol{x}_t^T D_i^T) M_t^T + \sum_{i=1}^d C_i \tilde{M}_t (\Sigma_{\tilde{x}|x} + \boldsymbol{\mu}_{\tilde{x}|x} \boldsymbol{\mu}_{\tilde{x}|x}^T) \tilde{M}_t^T C_i^T + \tilde{F}_t \Sigma_{\tilde{x}|x} \tilde{F}_t^T + GG^T.
$$

Marginalizing over $\tilde{\boldsymbol{x}}_{t+1}$ gives an approximation of the likelihood factor of time step $t + 1$, $p(\boldsymbol{x}_{t+1} \mid \boldsymbol{x}_{1:t}) \approx \mathcal{N}(\hat{\boldsymbol{\mu}}_x, \hat{\Sigma}_{xx})$. On the other hand, conditioning on observation $\boldsymbol{x}_{t+1}$ gives our belief over the agent's belief for the following time step, $p(\tilde{\boldsymbol{x}}_{t+1} \mid \boldsymbol{x}_{1:t+1}) = \mathcal{N}\left(\hat{\boldsymbol{\mu}}_{\tilde{x}|x}, \hat{\Sigma}_{\tilde{x}|x} \right)$, with

$$
\hat{\boldsymbol{\mu}}_{\tilde{x}|x} = \hat{\boldsymbol{\mu}}_{\tilde{x}} + \hat{\Sigma}_{\tilde{x}x} \hat{\Sigma}_{xx}^{-1} (\boldsymbol{x}_{t+1} - \hat{\boldsymbol{\mu}}_x), \qquad \hat{\Sigma}_{\tilde{x}|x} = \hat{\Sigma}_{\tilde{x}\tilde{x}} - \hat{\Sigma}_{\tilde{x}x} \hat{\Sigma}_{xx}^{-1} \hat{\Sigma}_{x\tilde{x}}. \tag{11}
$$

We initialize $p(\tilde{\boldsymbol{x}}_0 \mid \boldsymbol{x}_0)$ with the initial belief of the actor.

3.3 Partial observability from the observer's point of view

In practice, we often do not have access to the full state $\boldsymbol{x}_t$ in the model, e.g. if there are unmeasured quantities of the physical world such as velocity and acceleration when using a tracking system, which only provides measurements of position in time, or if we have latent variables in our model representing internal states of the observed agent. Furthermore, measurements might be noisy, e.g. due to the use of imprecise tracking hardware. We therefore consider the case where the state is partially observable for both the agent, i.e. the subject in the experiment, and the observer, i.e. the experimenter. In this case, we assume that the experimenter observes a linear transformation $\boldsymbol{o} \in \mathbb{R}^s$ of the state $\boldsymbol{x}_t$ with additive Gaussian noise

$$
\boldsymbol{o}_t = S\boldsymbol{x}_t + U\boldsymbol{\vartheta}_t, \tag{12}
$$

where $\boldsymbol{\vartheta}_t$ is a standard Gaussian random vector, resulting in the distribution $p(\boldsymbol{o}_t \mid \boldsymbol{x}_t) = \mathcal{N}\left(S\boldsymbol{x}_t, UU^T \right)$. The resulting Bayesian network is shown in Fig. 1 D. We can again formulate a

joint dynamical system of $\boldsymbol{x}_t$ and $\tilde{\boldsymbol{x}}_t$ with additional observations $\boldsymbol{o}_t$, resulting in

$$\begin{bmatrix} \boldsymbol{x}_{t+1} \\ \tilde{\boldsymbol{x}}_{t+1} \\ \boldsymbol{o}_{t+1} \end{bmatrix} = \begin{bmatrix} A & -(B + \sum_{i=1}^d \varepsilon_t^i C_i) L_t \\ K_t(H + \sum_{i=1}^c \epsilon_t^i D_i) & A - BL_t - K_t H \\ SA & -S(B + \sum_{i=1}^d \varepsilon_t^i C_i) L_t \end{bmatrix} \begin{bmatrix} \boldsymbol{x}_t \\ \tilde{\boldsymbol{x}}_t \end{bmatrix} + \begin{bmatrix} V & 0 & 0 & 0 \\ 0 & K_t W & E & 0 \\ SV & 0 & 0 & U \end{bmatrix} \begin{bmatrix} \boldsymbol{\xi}_t \\ \boldsymbol{\omega}_t \\ \boldsymbol{\eta}_t \\ \boldsymbol{\vartheta} \end{bmatrix}$$

$$=: (F_t + M_t \sum_{i=1}^c \epsilon_t^i D_i) \boldsymbol{x}_t + (\tilde{F}_t + \sum_{i=1}^d \varepsilon_t^i C_i \tilde{M}_t) \tilde{\boldsymbol{x}} + G_t \boldsymbol{\zeta}_t, \tag{13}$$

with matrices $F_t, \tilde{F}_t, M_t, \tilde{M}_t$ defined accordingly (for definitions see Appendix B.2). Note that this equation is structurally the same as for the fully-observable case (Eq. (9)) and we have overloaded the matrix definitions to highlight that both can be treated similarly.

The likelihood of an observed trajectory decomposes as $p(\boldsymbol{o}_{1:T} \mid \boldsymbol{\theta}) = p_{\boldsymbol{\theta}}(\boldsymbol{o}_1) \prod_{t=2}^T p_{\boldsymbol{\theta}}(\boldsymbol{o}_t \mid \boldsymbol{o}_{1:t-1})$. For computing the factors $p(\boldsymbol{o}_t \mid \boldsymbol{o}_{1:t-1})$, we follow structurally the same steps as for the fully-observable case, but now $p(\boldsymbol{x}_t, \tilde{\boldsymbol{x}}_t \mid \boldsymbol{o}_{1:t})$ serves as sufficient statistic of the history: We first assume the distribution $p(\boldsymbol{x}_t, \tilde{\boldsymbol{x}}_t \mid \boldsymbol{o}_{1:t})$ to be Gaussian distributed and approximately propagate it through the joint dynamics model $p(\boldsymbol{x}_{t+1}, \tilde{\boldsymbol{x}}_{t+1}, \boldsymbol{o}_{t+1} \mid \boldsymbol{x}_t, \tilde{\boldsymbol{x}}_t)$ (Eq. (13)) by computing the mean and variance. We marginalize the resulting Gaussian approximation of $p(\boldsymbol{x}_{t+1}, \tilde{\boldsymbol{x}}_{t+1}, \boldsymbol{o}_{t+1} \mid \boldsymbol{o}_{1:t})$ over $\boldsymbol{x}_{t+1}, \tilde{\boldsymbol{x}}_{t+1}$ yielding the likelihood factors $p(\boldsymbol{o}_{t+1} \mid \boldsymbol{o}_{1:t})$. On the other hand, conditioning on the observation $\boldsymbol{o}_t$ gives the history statistic $p(\boldsymbol{x}_t, \tilde{\boldsymbol{x}}_t \mid \boldsymbol{o}_{1:t})$ for the following time step. All steps are very similiar to the fully-observable case but a more detailed description is given in Appendix C.

3.4 Parameter inference

In the previous sections, we have provided an algorithm for computing an approximate likelihood of the parameters $\boldsymbol{\theta}$ for a set of observed trajectories $\{\boldsymbol{x}_{1:T}^i\}_{i=1:N}$. For determining the optimal parameters, we maximize the likelihood giving us a point estimate $\boldsymbol{\theta}_{\text{MLE}}$ of the true parameters. As one has to solve the control problem (determining L_t and K_t) by an iterative procedure [7] for every likelihood evaluation, computing gradients of the likelihood (although possible) is not very efficient. We instead use the robust gradient-free optimizer BOBYQA[1] [45] which minimizes the negative log likelihood based on a quadratic approximation. Our implementation in jax [46] is available on github[2].

4 Evaluation and applications

4.1 Validation on synthetic reaching data

We apply the introduced method to recover parameters in a single-joint reaching task with control-dependent noise (details in Appendix E.1). The goal is to bring the hand to a target while minimizing control effort. The cost function has three parameters: (i) v, the cost of the velocity at the final time step, (ii) f, the cost of the acceleration at the final timestep, (iii) r, the cost of actions at each timestep. Simulated data for the parameters $r = 10^{-5}, v = 0.2, f = 0.02$ are shown in Fig. 2 A. Visual inspection of the likelihood function (Fig. 2 B) shows that the maximum likelihood estimate (MLE) is very close to the true parameter values.

Once we have obtained the MLE, we can perform belief tracking, i.e. compute our approximate belief of the agent's belief $p(\tilde{\boldsymbol{x}}_t \mid \boldsymbol{o}_{1:t})$. As an example, we simulated $N = 20$ trajectories $\{\boldsymbol{o}_{1:T}\}^{i=1:N}$ with $T = 30$ from a partially-observed version of reaching task used above, in which we only observe the position and treat velocity and acceleration as latent variables. Fig. 2 C shows our approximate belief over the agent's belief for the MLE parameters, together with the true agent's belief. Note that we can recover the agent's belief of state, velocity, and acceleration quite accurately from noisy observations of the position only.

For the evaluation of parameter estimates, we compute their root mean squared errors (RMSE) in logarithmic space. The effect of estimation errors on the resulting trajectories is illustrated in Fig. 2 D, where we simulated trajectories as in Fig. 2 A with different mean parameter errors. To show that our

---

[1]Python implementation under GNU GPL available at PyPI
[2]A link to the implementation will be put here in the camera ready version.

Figure 2: **Validation on synthetic reaching data. A** Simulated trajectories of the reaching task. **B** Negative log likelihood for different combinations of the parameters given data and the resp. third parameter. **C** Belief tracking: During a reaching movement, the agent has a belief about the position, velocity, and acceleration (green dotted lines). The experimenter observes a noisy version of the agent's actual movements (blue) and computes an estimate of the agent's belief (orange dashed lines with shaded region representing 2 SD). **D** Mean trajectories with RMSE 0.016 (MLE), 0.1, 0.5, and 1.0. **E** RMSE of the MLEs for all parameters on pairwise grids (for one value respective third parameter). The colors are the same as in the previous subplot. **F** Distribution over 10 repetitions of RMSE for each parameter across different values for the other parameters. **G** RMSE and KL divergences (between empirical distributions of true trajectories and simulated ones based on the MLE) with 0.2 and 0.8 quantiles for different numbers of trajectories with parameters as in (A).

method yields good parameter estimates over a range of different parameter settings, we perform maximum likelihood estimations of all three parameters for different true parameters, of which two were chosen from a pairwise grid while the third one was left as in Fig. 2 A. In this analysis, we used 100 simulated trajectories and 10 repetitions each. In Fig. 2 E, which shows the resulting RMSEs for different combinations of true parameters on pairwise grids, we demonstrate that the RMSEs are small over a wide range of parameter values. The RMSEs (Fig. 2 F) across different values for the respective other two parameters and 10 repetitions were 2.4×10^{-2} (r), 2.1×10^{-2} (v) and 3.1×10^{-2} (f). Finally, we investigated the influence of the number of samples by evaluating estimates of trajectories as in Fig. 2 A for different numbers of trials (Fig. 2 G). As expected, more trials increase the accuracy of the estimates and lead to lower error. We estimated the convergence rate by fitting a line to the log-log plot and obtained 0.78 for the RMSE. An analysis using the Kullback–Leibler divergence between the empirical trajectory distributions of the true and maximum likelihood parameters as an additional evaluation metric can be found in Appendix F.1.1.

We perform a similar analysis for generated partially-observed trajectories in which we only observe the position and treat velocities, accelerations and forces as latent variables. The results are qualitatively very similar and are therefore presented in Appendix F.1.

4.2 Application to real reaching movements

To show the applicability to real data, we apply our method to reaching trajectories from a previously published experiment [47], in which a rhesus monkey had to perform center-out reaching movements and hold its hand at the target to receive a reward. Since the data contains only measurements of position (velocity and acceleration are computed using finite differences), we use the partially-observable version of the reaching model described in Section 4.1, treating velocity and acceleration as latent variables. The approximate likelihood functions with respective MLEs of the three parameters are shown in Fig. 3 A, indicating that we can determine the parameter set for which the trajectories are most likely. Fig. 3 B shows the given trajectories together with simulations using our model

Figure 3: **Application to real reaching data. A** Negative log likelihoods for the three model parameters. **B** Reaching trajectories (velocities and accelerations computed with finite differences) and simulated data from the model with MLE parameters.

with the MLE parameters. We observe that the inferred parameters produces in simulation data that convincingly look like the real data and provides smooth estimates of the latent velocity and acceleration profiles.

4.3 Application to eye movements

We also apply our method to a model of saccadic eye movements, which was presented by Crevecoeur and Kording [48]. This model captures fixating one's eyes to an initial point and then performing a saccade to fixate another point. A cost parameter (r) is used to trade off the cost of the movement and deviation from the targets. As this model is an LQG model with control-dependent noises, it directly allows the application of our method for recovering the parameter. Fig. 4 A shows simulated trajectories representing typical eye movements encountered in the experiments. The MLEs based on simulated data for a range of 20 different parameter values (100 repetitions each) are shown in Fig. 4 B. Except for very few outliers, the estimated parameters are very close to the true parameters.

Figure 4: **Saccadic eye movements. A** Generated trajectories **B** Median and quantiles of MLEs for a range of true parameter values of r

4.4 Application to random problems

To demonstrate that the inference method works on a wide range of problems defined according to the model definition (Section 2), we evaluate it on randomly-generated problems. Detailed information on the generation procedure is given in Appendix E.3. Each model has two parameters (r_1 and r_2) which again represent the cost of control effort. For each model, we sampled a true value of parameter r_2 from a uniform random distribution and estimated both parameters jointly by maximizing the approximate likelihood. In Fig. 5 A we show the errors for a range of parameter values r_1 for different random models. The median and quantiles for the results of 200 random problems are shown in Fig. 5 B. One can observe that the estimates are general very close to the true parameters. The results for the other parameter r_2 are basically identical, since the problem is symmetric w.r.t. the parameters, but we include the results in Appendix F.2.

5 Conclusion

In this paper, we investigated the inverse optimal control problem under signal dependent noise. We formalized the problem as a POMDP and introduced a first method for inferring cost parameters of

Figure 5: **Random problems. A** MLEs for a range of parameter values of r_1 for different random problems and different values of r_2 (color). **B** Aggregated results (median, percentiles) for 200 random problems.

an agent in a linear-quadratic control problem with signal-dependent noise. Numerical simulations show that accurate inference of cost parameters given synthetic data is feasible in random control problems, simulated arm movements, and simulated eye movements. Additionally, the method can be used to probabilistically infer the belief of the considered agent. Furthermore, the method was applied to real data from a macaque monkey performing reaching movements. The inferred parameters reproduces reaching data in simulation that convincingly agrees with the original data and provides smooth estimates of the latent velocity and acceleration profiles. While more recent and more general methods for optimal control in high-dimensional continuous domains exist, they rely on function approximation methods, which is useful in engineering applications, but may not provide a computational level explanation of behavior. Taken together, our method does not require designing a cost function and testing for similarity of simulated trajectories with experimental data, but allows inferring the cost functions directly from behavior, thereby reconciling normative and descriptive approaches to human sensorimotor behavior.

Limitations and Future work   The proposed algorithms are based on stochastic optimal feedback control with linear dynamics, quadratic cost functions, and signal dependent noise. As such, a first limitation lies in the restriction to problems with linear dynamics. An extension to non-linear dynamics could be achieved by linearizing the dynamics locally or more generally by using a framework that iteratively linearizes the dynamics at each time step, e.g. iLQG [49]. Similarly, while quadratic cost functions allow modeling a wide range of costs and benefits within sensorimotor control, certain cost functions such as exponential discounting may be more cumbersome to accommodate.

While the presented method was able to recover cost functions in the considered problems, higher-dimensional parameter spaces will likely pose difficulties in finding unique point estimates of parameters. This problem could be addressed by using appropriate structured prior distributions over parameters. A fully-Bayesian treatment could be realized by using Markov-chain Monte Carlo involving our likelihood model. Further research should similarly investigate the limits of the Gaussian approximation of the likelihood. In the cases considered here, the approximation of the likelihood function appeared to be unbiased up to an RMS error of approximately 2×10^{-3}, however approximating distributions by simpler ones may introduce systematic biases and noise. Possible extensions could resort to using particle filters albeit at a higher computational cost.

Another issue regarding higher-dimensional parameters spaces is that evaluation of the likelihood function becomes quite expensive by determining the optimal controller and optimal filter iteratively. Even if this procedure takes only one second on a common PC in case of the reaching task, optimization in high-dimensional spaces requires a progressively larger number function evaluations, which renders inference costly. By relying on the iterative procedure, it also becomes difficult to compute gradients, which may prevent the use of efficient gradient-based solvers. While for our applications a solver based on quadratic approximations was efficient, one could resort to Bayesian optimization in such cases.

Characterizing individual human subjects by analyzing their behavior may in principle be used with negative societal impact. In the context of scientific investigations of human sensorimotor control within cognitive science and neuroscience, only anonymized behavioral data for the understanding of the human mind and brain are employed.

References

[1] Richard S Sutton and Andrew G Barto. *Reinforcement learning: An introduction*. MIT press, 2018.

[2] Tamar Flash and Neville Hogan. The coordination of arm movements: an experimentally confirmed mathematical model. *Journal of neuroscience*, 5(7):1688–1703, 1985.

[3] Christopher M Harris and Daniel M Wolpert. Signal-dependent noise determines motor planning. *Nature*, 394(6695):780–784, 1998.

[4] Richard A Schmidt, Howard Zelaznik, Brian Hawkins, James S Frank, and John T Quinn Jr. Motor-output variability: a theory for the accuracy of rapid motor acts. *Psychological review*, 86(5):415, 1979.

[5] Robert F Stengel. *Optimal control and estimation*. Courier Corporation, 1994.

[6] Gustav Theodor Fechner. *Elemente der psychophysik*, volume 2. Breitkopf u. Härtel, 1860.

[7] Emanuel Todorov. Stochastic optimal control and estimation methods adapted to the noise characteristics of the sensorimotor system. *Neural computation*, 17(5):1084–1108, 2005.

[8] Emanuel Todorov and Michael I Jordan. Optimal feedback control as a theory of motor coordination. *Nature neuroscience*, 5(11):1226–1235, 2002.

[9] Reza Shadmehr and John W Krakauer. A computational neuroanatomy for motor control. *Experimental brain research*, 185(3):359–381, 2008.

[10] David W. Franklin and Daniel M. Wolpert. Computational Mechanisms of Sensorimotor Control. *Neuron*, 72(3):425–442, November 2011. ISSN 08966273. doi: 10.1016/j.neuron.2011.10.006. URL https://linkinghub.elsevier.com/retrieve/pii/S0896627311008919.

[11] Joseph Y Nashed, Frédéric Crevecoeur, and Stephen H Scott. Influence of the behavioral goal and environmental obstacles on rapid feedback responses. *Journal of neurophysiology*, 108(4):999–1009, 2012.

[12] Frédéric Crevecoeur, Douglas P Munoz, and Stephen H Scott. Dynamic multisensory integration: somatosensory speed trumps visual accuracy during feedback control. *Journal of Neuroscience*, 36(33):8598–8611, 2016.

[13] Jun Izawa, Tushar Rane, Opher Donchin, and Reza Shadmehr. Motor adaptation as a process of reoptimization. *Journal of Neuroscience*, 28(11):2883–2891, 2008.

[14] Sang-Hoon Yeo, David W Franklin, and Daniel M Wolpert. When optimal feedback control is not enough: Feedforward strategies are required for optimal control with active sensing. *PLoS computational biology*, 12(12):e1005190, 2016.

[15] Arne J Nagengast, Daniel A Braun, and Daniel M Wolpert. Risk-sensitive optimal feedback control accounts for sensorimotor behavior under uncertainty. *PLoS Comput Biol*, 6(7):e1000857, 2010.

[16] Vincent Ethier, David S Zee, and Reza Shadmehr. Changes in control of saccades during gain adaptation. *Journal of Neuroscience*, 28(51):13929–13937, 2008.

[17] Jörn Diedrichsen. Optimal task-dependent changes of bimanual feedback control and adaptation. *Current Biology*, 17(19):1675–1679, 2007.

[18] Andrew Y Ng, Stuart J Russell, and others. Algorithms for inverse reinforcement learning. In *Icml*, volume 1, page 2, 2000.

[19] Brian D Ziebart, Andrew L Maas, J Andrew Bagnell, and Anind K Dey. Maximum entropy inverse reinforcement learning. In *Aaai*, volume 8, pages 1433–1438. Chicago, IL, USA, 2008.

[20] Chelsea Finn, Sergey Levine, and Pieter Abbeel. Guided cost learning: Deep inverse optimal control via policy optimization. In *International conference on machine learning*, pages 49–58. PMLR, 2016.

[21] M Cody Priess, Jongeun Choi, and Clark Radcliffe. The inverse problem of continuous-time linear quadratic gaussian control with application to biological systems analysis. In *Dynamic Systems and Control Conference*, volume 46209, page V003T42A004. American Society of Mechanical Engineers, 2014.

[22] Matthew Golub, Steven Chase, and Byron Yu. Learning an internal dynamics model from control demonstration. In *International Conference on Machine Learning*, pages 606–614. PMLR, 2013.

[23] Haitham El-Hussieny and Jee-Hwan Ryu. Inverse discounted-based lqr algorithm for learning human movement behaviors. *Applied Intelligence*, 49(4):1489–1501, 2019.

[24] Daniel Kahneman and Amos Tversky. Prospect theory: An analysis of decision under risk. *Econometrica*, 47(2):263–292, 1979.

[25] Frederick Mosteller and Philip Nogee. An experimental measurement of utility. *Journal of Political Economy*, 59(5):371–404, 1951.

[26] Matthew Chalk, Gasper Tkacik, and Olivier Marre. Inferring the function performed by a recurrent neural network. *Plos one*, 16(4):e0248940, 2021.

[27] anonymized. Anonymous. .

[28] Katja Mombaur, Anh Truong, and Jean-Paul Laumond. From human to humanoid locomotion—an inverse optimal control approach. *Autonomous robots*, 28(3):369–383, 2010.

[29] anonymized. Anonymous. .

[30] Siddharth Reddy, Anca D Dragan, and Sergey Levine. Where do you think you're going?: Inferring beliefs about dynamics from behavior. *arXiv preprint arXiv:1805.08010*, 2018.

[31] JD Choi and Kee-Eung Kim. Inverse reinforcement learning in partially observable environments. *Journal of Machine Learning Research*, 12:691–730, 2011.

[32] Neil MT Houlsby, Ferenc Huszár, Mohammad M Ghassemi, Gergő Orbán, Daniel M Wolpert, and Máté Lengyel. Cognitive tomography reveals complex, task-independent mental representations. *Current Biology*, 23(21):2169–2175, 2013.

[33] Konrad Paul Körding and Daniel M Wolpert. The loss function of sensorimotor learning. *Proceedings of the National Academy of Sciences*, 101(26):9839–9842, 2004.

[34] Sheeraz Ahmad and Angela J. Yu. Active sensing as Bayes-optimal sequential decision making. *arXiv preprint arXiv:1305.6650*, 2013.

[35] anonymized. Anonymous. .

[36] anonymized. Anonymous. .

[37] Zhengwei Wu, Minhae Kwon, Saurabh Daptardar, Paul Schrater, and Xaq Pitkow. Rational thoughts in neural codes. *Proceedings of the National Academy of Sciences*, 117(47):29311–29320, 2020.

[38] Jean Daunizeau, Hanneke EM Den Ouden, Matthias Pessiglione, Stefan J Kiebel, Klaas E Stephan, and Karl J Friston. Observing the observer (i): meta-bayesian models of learning and decision-making. *PloS one*, 5(12):e15554, 2010.

[39] Chris L. Baker, Rebecca Saxe, and Joshua B. Tenenbaum. Action understanding as inverse planning. *Cognition*, 113(3):329–349, 2009. Publisher: Elsevier.

[40] Tan Zhi-Xuan, Jordyn L. Mann, Tom Silver, Joshua B. Tenenbaum, and Vikash K. Mansinghka. Online Bayesian Goal Inference for Boundedly-Rational Planning Agents. *arXiv:2006.07532 [cs]*, October 2020. URL http://arxiv.org/abs/2006.07532. arXiv: 2006.07532.

[41] Ahmed Ramadan, Jongeun Choi, and Clark J Radcliffe. Inferring human subject motor control intent using inverse mpc. In *2016 American Control Conference (ACC)*, pages 5791–5796. IEEE, 2016.

[42] Matthew D Golub, M Yu Byron, and Steven M Chase. Internal models for interpreting neural population activity during sensorimotor control. *Elife*, 4:e10015, 2015.

[43] Xiangli Chen and Brian Ziebart. Predictive inverse optimal control for linear-quadratic-gaussian systems. In *Artificial Intelligence and Statistics*, pages 165–173. PMLR, 2015.

[44] Jur Van Den Berg, Pieter Abbeel, and Ken Goldberg. Lqg-mp: Optimized path planning for robots with motion uncertainty and imperfect state information. *The International Journal of Robotics Research*, 30 (7):895–913, 2011.

[45] Coralia Cartis, Jan Fiala, Benjamin Marteau, and Lindon Roberts. Improving the flexibility and robustness of model-based derivative-free optimization solvers. *ACM Transactions on Mathematical Software (TOMS)*, 45(3):1–41, 2019.

[46] James Bradbury, Roy Frostig, Peter Hawkins, Matthew James Johnson, Chris Leary, Dougal Maclaurin, and Skye Wanderman-Milne. JAX: composable transformations of Python+NumPy programs, 2018. URL http://github.com/google/jax.

[47] Robert D Flint, Eric W Lindberg, Luke R Jordan, Lee E Miller, and Marc W Slutzky. Accurate decoding of reaching movements from field potentials in the absence of spikes. *Journal of neural engineering*, 9(4): 046006, 2012.

[48] Frederic Crevecoeur and Konrad P Kording. Saccadic suppression as a perceptual consequence of efficient sensorimotor estimation. *Elife*, 6:e25073, 2017.

[49] Emanuel Todorov and Weiwei Li. A generalized iterative lqg method for locally-optimal feedback control of constrained nonlinear stochastic systems. In *Proceedings of the 2005, American Control Conference, 2005.*, pages 300–306. IEEE, 2005.