z-SignFedAvg: A Unified Stochastic Sign-based Compression for Federated Learning

Abstract

Federated Learning (FL) is a promising privacy-preserving distributed learning paradigm but suffers from high communication cost when training large-scale machine learning models. Sign-based methods, such as SignSGD (Bernstein et al., 2018), have been proposed as a biased gradient compression technique for reducing the communication cost. However, sign-based algorithms could diverge under heterogeneous data, which thus motivated the development of advanced techniques, such as the error-feedback method and stochastic sign-based compression, to fix this issue. Nevertheless, these methods still suffer from slower convergence rates. Besides, none of them allows multiple local SGD updates like FedAvg (McMahan et al., 2017). In this paper, we propose a novel noisy perturbation scheme with a general symmetric noise distribution for sign-based compression, which not only allows one to flexibly control the tradeoff between gradient bias and convergence performance, but also provides a unified viewpoint to existing stochastic sign-based methods. More importantly, we propose the very first sign-based FedAvg algorithm (z-SignFedAvg). Theoretically, we show that z-SignFedAvg achieves a faster convergence rate than existing sign-based methods and, under the uniformly distributed noise, can enjoy the same convergence rate as its uncompressed counterpart. Last but not the least, we remark that adding random noise to the local gradients has a double benefit: it also protects the clients' privacy by, e.g., the Differential Privacy. Extensive experiments are conducted to demonstrate that the z-SignFedAvg can achieve competitive empirical performance on real datasets.

1 Introduction

We consider the Federated Learning (FL) network with one parameter server and n clients (McMahan et al., 2017; Li et al., 2020a), with the focus on solving the following distributed learning problem

$$\min_{x \in \mathbb{R}^d} f(x) = \frac{1}{n} \sum_{i=1}^{n} f_i(x), \tag{1}$$

where $f_i(\cdot)$ is the local objective function for the i-th client, for $i = 1, \ldots, n$. Throughout this paper, we assume that each f_i is smooth and possibly non-convex. The local objective functions are generated from the local dataset owned by each client. When designing distributed algorithms to solve (1), a crucial aspect is the communication efficiency since a massive number of clients need to transmit their local gradients to the server frequently (Li et al., 2020a). As one of the most popular FL algorithms, the federated averaging (FedAvg) algorithm (McMahan et al., 2017; Konečný et al., 2016) considers multiple local SGD updates with periodic communications to reduce the communication cost. Another way is to compress the local gradients before sending them to the server (Li et al., 2020a; Alistarh et al., 2017; Reisizadeh et al., 2020). Among the existing compression methods, a simple yet elegant technique is to take the sign of each coordinate of the local gradients, which requires only one bit for transmitting each coordinate. For any $x \in \mathbb{R}$, we define the sign operator as: $\text{Sign}(x) = 1$ if $x \geq 0$ and -1 otherwise.

It has been shown recently that optimization algorithms with the sign-based compression can enjoy a great communication efficiency while still achieving comparable empirical performance as uncompressed algorithms (Bernstein et al., 2018; Karimireddy et al., 2019; Safaryan & Richtárik, 2021). However, for distributed learning, especially the scenarios with heterogeneous data, i.e.,

$f_i \neq f_j$ for every $i \neq j$, a naive application of the sign-based algorithm may end up with divergence (Karimireddy et al., 2019; Chen et al., 2020a; Safaryan & Richtárik, 2021).

A counterexample for sign-based distributed gradient descent.   Consider the one-dimension problem with two clients: $\min_{x \in \mathbb{R}} (x - A)^2 + (x + A)^2$, where $A > 0$ is some constant. For any $x \in [-A, A]$, the averaged sign gradient at x is $\mathrm{Sign}(x - A) + \mathrm{Sign}(x + A) = 0$, i.e., the algorithm never moves. Similar examples are also discussed by (Chen et al., 2020a; Safaryan & Richtárik, 2021). The fundamental reason for this undesirable result is the uncontrollable bias brought by the sign-based compression.

There are mainly two approaches to fixing this issue in the existing literature. The first one is the stochastic sign-based method, which introduces stochasticity into the sign operation (Jin et al., 2020; Safaryan & Richtárik, 2021; Chen et al., 2020a), and the second one is the Error-Feedback (EF) method (Karimireddy et al., 2019; Vogels et al., 2019; Tang et al., 2019). However, these works are still unsatisfactory. Specifically, on one hand, the theoretical convergence rates of these algorithms are still worse than uncompressed algorithms like (Ghadimi & Lan, 2013; Yu et al., 2019). On the other hand, none of them allows the clients to have multiple local SGD updates within one communication round like the FedAvg. This work aims at addressing these issues and closing the gaps for sign-based methods.

Main contributions. Our contributions are summarized as follows.

(1) **A unified family of stochastic sign operators.** We show an intriguing fact: The bias brought by the sign-based compression can be flexibly controlled by injecting a proper amount of random noise before the sign operation. In particular, our analysis is based on a novel noisy perturbation scheme with a general symmetric noise distribution, which also provides a unified framework to understand existing stochastic sign-based methods including (Jin et al., 2020; Safaryan & Richtárik, 2021; Chen et al., 2020a).

(2) **The first sign-based FedAvg algorithm.**   In contrast to the existing sign-based methods which do not allow multiple local SGD updates within one communication round, based on the proposed stochastic sign-based compression, we design a novel family of sign-based federated averaging algorithms (z-SignFedAvg) that can achieve the best of both worlds: high communication efficiency and fast convergence rate.

(3) **New theoretical convergence rate analyses.**   By leveraging the asymptotic unbiasedness property of the stochastic sign-based compression, we derive a series of theoretical results for z-SignFedAvg and demonstrate its improved convergence rates over the existing sign-based methods. In particular, we show that by injecting a sufficiently large uniform noise, z-SignFedAvg can have a matching convergence rate with the uncompressed algorithms.

(4) **Application to differentially-private federated learning (DP-FL).**   We remark that adding random noise to the local gradients is also a common practice for privacy protection, especially in DP-FL (Geyer et al., 2017; Agarwal et al., 2021; 2018). With this observation, we propose a differentially-private variant of z-SignFedAvg, termed DP-SignFedAvg, and empirically show that it can even perform comparably as the uncompressed DP-FedAvg (Geyer et al., 2017; Kairouz et al., 2021) under the same privacy budget.

Organization.   In Section 2, the proposed general noisy perturbation scheme for the sign-based compression and its key property, i.e., asymptotic unbiasedness, are presented. Inspired by this result, the main algorithms are devised in Section 3 together with their convergence analyses under different noise distribution parameters. We evaluate our proposed algorithms on real datasets and benchmarks with existing sign-based methods in Section 4. Finally, conclusions are drawn in Section 5.

Notations.   For any $x \in \mathbb{R}^d$, we denote $x(j)$ as the j-th element of the vector x. We define the ℓ_p-norm for $p \geq 1$ as $\|x\|_p = (\sum_{j=1}^d |x(j)|^p)^{\frac{1}{p}}$. We denote that $\| \cdot \| = \| \cdot \|_2$, and $\|x\|_\infty = \max_{j \in \{1,...,d\}} |x(j)|$. For any function $f(x)$, we denote $f^{(k)}(x)$ as its k-th derivative, and for a vector $x = [x(1), ..., x(d)]^\top \in \mathbb{R}^d$, we define $\mathrm{Sign}(x) = [\mathrm{Sign}(x(1)), ..., \mathrm{Sign}(x(d))]^\top$.

1.1 RELATED WORKS

In this section, we review a few related works on the sign-based compression and DP-FL.

Stochastic sign-based method. Our proposed algorithm belongs to this category. Among the existing works (Safaryan & Richtárik, 2021; Jin et al., 2020; Chen et al., 2020a), the setting considered by (Safaryan & Richtárik, 2021) is closest to ours since the latter two consider gradient compression not only in the uplink but also in the downlink. Despite of this difference and the use of different convergence metrics, the algorithms therein achieve the same convergence rate $O(\tau^{-\frac{1}{4}})$, where τ is the total number of gradient queries to the local objective function. Compared to existing works, our proposed z-SignFedAvg requires a slightly stronger assumption on the mini-batch gradient noise, but achieves a faster convergence rate $O(\tau^{-\frac{1}{3}})$ or even $O(\tau^{-\frac{1}{2}})$, with the standard squared ℓ_2-norm of gradients as the convergence metric.

Error-Feedback method. The error-feedback (EF) method is first proposed by (Seide et al., 2014) and later theoretically justified by (Karimireddy et al., 2019). Then, (Vogels et al., 2019; Tang et al., 2019; 2021a) further extended this EF method into distributed and adaptive gradient schemes. The key idea of the EF-based methods is to show that the sign operator scaled by the gradient norm is a contractive compressor, and the error induced by the contractive compressor can be compensated. However, such EF-based methods cannot deal with partial client participation otherwise the error residuals cannot be correctly tracked. Besides, the EF-based methods have a convergence rate $\mathcal{O}(\tau^{-\frac{1}{2}} + d^2\tau^{-1})$, where d is the dimension of the gradients, and therefore is not competitive for high-dimension problems.

As mentioned, some of the existing methods like (Chen et al., 2020a; Safaryan & Richtárik, 2021) do not adopt the standard squared ℓ_2-norm of gradients as the metric for the convergence rate analysis. Thus, it is tricky to make a fair comparison between them and the proposed z-SignFedAvg. In Appendix A, we provide a detailed discussion and summarize the convergence rates of some representative algorithms in Table 2.

Differential Private Federated Learning. Recent works have discovered that the gradients transmitted from the clients to the server in FL could reveal the clients' privacy (Geiping et al., 2020). One way to remedy this is to consider the DP-FL, where the clients' privacy is protected through the lens of Differential Privacy (DP) (Dwork et al., 2014). In particular, to fulfill the user-level DP (Geyer et al., 2017), a common practice is to perturb the gradients by adding some random noise, e.g., the Gaussian noise (Abadi et al., 2016b; Geyer et al., 2017). Some DP-FL algorithms such as (Agarwal et al., 2018; Kairouz et al., 2021) also considered gradient compression and perturbed the compressed gradients by discrete noise . In contrast to these works, our proposed z-SignFedAvg adds (continuous valued) noise before the sign compression and therefore can benefit communication efficiency as well as users' privacy in a more straightforward manner.

2 SIGN OPERATOR WITH SYMMETRIC AND ZERO-MEAN NOISE

In this section, we introduce a general noisy perturbation scheme for the sign-based compression and analyze the asymptotic unbiasedness of compressed gradients. The results serve as the foundation for the proposed algorithms in subsequent sections.

Key observation. Let ξ be a random variable that is symmetric, zero-mean and has the p.d.f $p(t)$. If $p(0) \neq 0$ and $p(t)$ is continuous and uniformly bounded on $(-\infty, +\infty)$, then it holds that

$$\lim_{\sigma \to +\infty} \frac{\sigma}{2p(0)} \mathbb{E}[\text{Sign}(x + \sigma\xi)] = \lim_{\sigma \to +\infty} \frac{\sigma}{p(0)} \int_0^{\frac{x}{\sigma}} p(t)dt = x. \tag{2}$$

In other words, the perturbed sign operator is an asymptotically unbiased estimator of the input x when $\sigma \to \infty$. Furthermore, assume that $p(t)$ is uniformly bounded on $(-\infty, +\infty)$ and differentiable for an arbitrary order. Then, with the Taylor's expansion, we can have $\frac{\sigma}{p(0)}\int_0^{\frac{x}{\sigma}} p(t)dt = x + \frac{1}{p(0)}\sum_{k=1}^{+\infty} \frac{p^{(k)}(0)x^{k+1}}{(k+1)!\sigma^k} = x + \sum_{k=1}^{+\infty} p^{(k)}(0)\mathcal{O}(\sigma^{-k})$. Therefore, suppose that K is the largest integer such that $p^{(1)}(0) = 0, ..., p^{(K)}(0) = 0$. The LHS of (2) will converge to x with the order $\mathcal{O}(\sigma^{-(K+1)})$. This observation motivates us to propose the following family of noise distribution parameterized by a positive integer $z \in \mathbb{Z}_+$.

Definition 1 (z-distribution). *A random variable ξ_z is said to follow the z-distribution if its p.d.f is*

$$p_z(t) = \frac{1}{2\eta_z} e^{-\frac{t^{2z}}{2}}, \tag{3}$$

where $\eta_z = 2^{\frac{1}{2z}} \Gamma\left(1 + \frac{1}{2z}\right)$ and $\Gamma(z) = \int_0^{+\infty} t^{z-1} e^{-t} dt$ is the Gamma function.

It can be verified $p_z(t)$ in (3) is a valid p.d.f. When $z = 1$, it corresponds to the standard Gaussian distribution. In addition, one can also show that $p_z(t)$ converges to the p.d.f of uniform distribution on the interval $[-1, 1]$ when $z \to +\infty$ (see Lemma 2 in Appendix B). This z-distribution has a nice property that can be leveraged to bound the bias caused by the sign-based compression, as stated in the following lemma.

Lemma 1. *For any $x \in \mathbb{R}^d$ and $\sigma > 0$,*

$$\|\eta_z \sigma \mathbb{E}\left[\mathrm{Sign}(\mathrm{x} + \sigma\xi_\mathrm{z})\right] - x\|^2 \leq \frac{\|x\|_{4z+2}^{4z+2}}{4(2z+1)^2 \sigma^{4z}}, \tag{4}$$

where $\xi_z(1), ..., \xi_z(d)$ follow the i.i.d. z-distribution.

Remark 1. *One can see that the RHS of (4) involves the term $(\|x\|_{4z+2}/\sigma)^{4z}$. Thus, as long as $\sigma > \|x\|_\infty$, the LHS of (4) converges to zero when $z \to +\infty$. Since Lemma 2 implies that ξ_∞ follows the i.i.d uniform distribution on $[-1, 1]$, we obtain $\sigma \mathbb{E}[\mathrm{Sign}(\mathrm{x} + \sigma\xi_\infty)] = x$ as long as $\sigma > \|x\|_\infty$. It is interesting to remark that the stochastic sign operators proposed in (Jin et al., 2020; Safaryan & Richtárik, 2021) are exactly the sign operator injected by the uniform noise, and (Chen et al., 2020a) also considered the use of a symmetric noise for gradient perturbation. Thus, sign-based compression with the z-distribution offers a unified perspective to understand the relationship among the existing stochastic sign-based methods.*

3 z-SIGNFEDAVG ALGORITHM

In this section, based on the analysis in Section 2, we propose the following sign-based FedAvg algorithm, termed as z-SignFedAvg. The algorithm details are presented in Algorithm 1. A prominent difference between the proposed z-SignFedAvg and the existing sign-based methods lies in that the clients are allowed to perform multiple SGD updates per communication round ($E > 1$) before applying the stochastic sign-based compression. Like the FedAvg algorithm, it is anticipated that z-SignFedAvg can greatly benefit from this and has a significantly reduced communication cost.

Note that in practice we only consider $z = 1$ and $z = +\infty$ for the z-SignFedAvg since they correspond to the Gaussian distribution and uniform distribution, respectively. Nevertheless, we are interested in the convergence properties of z-SignFedAvg for a general positive integer z as it provides better insights on the role of z for the convergence rate.

Algorithm 1 z-SignFedAvg (or z-SignSGD when $E = 1$)

Require: Total communication rounds T, number of local steps E, number of clients n, clients stepsize γ, server stepsize η, noise coefficient σ, parameter of noise distribution z.
1: Initialize x_0.
2: **for** $t = 1$ to T **do**
3:     **On Clients:**
4:     **for** $i = 1$ to n **do**
5:         $x_{t-1,0}^i = x_{t-1}$
6:         **for** $s = 1$ to E **do**
7:             $g_{t-1,s}^i = g_i(x_{t-1,s-1}^i)$, where $g_i(\cdot)$ is the mini-batch gradient oracle of the i-th client.
8:             $x_{t-1,s}^i = x_{t-1,s-1}^i - \gamma g_{t-1,s}^i$.
9:         **end for**
10:         $\Delta_{t-1}^i = \mathrm{Sign}\left(\frac{x_{t-1} - x_{t-1,E}^i}{\gamma} + \sigma\xi_z\right)$, where $\xi_z(1), ..., \xi_z(d) \sim p_z(t)$ i.i.d.
11:         Send Δ_{t-1}^i to the server.
12:     **end for**
13:     **On Server:**
14:     $x_t = x_{t-1} - \eta\gamma\frac{1}{n}\sum_{i=1}^n \Delta_{t-1}^i$.
15:     Broadcast x_t to the clients.
16: **end for**
17: **return** x_T.

We first state some standard assumptions for problem (1).

Assumption 1. *We assume that each $f_i(x)$ has the following properties:*

A.1 We can access a mini-batch gradient oracle that is unbiased and has bounded variance, i.e., $\mathbb{E}[g_i(x)] = \nabla f_i(x)$ and $\mathbb{E}[\|g_i(x) - \nabla f_i(x)\|_2^2] \leq \zeta^2$.

A.2 Each f_i is smooth, i.e., for any $x, y \in \mathbb{R}^d$, there exists some non-negative constants $L_1, \ldots, L_d$, such that $f(y) - f(x) \leq \langle \nabla f(x), y - x \rangle + \frac{\sum_{j=1}^d L_j(y(j)-x(j))^2}{2}$.

A.3 There exists some constant f^* such that $f(x) \geq f^*, \forall x \in \mathbb{R}^d$.

A.4 There exists a constant $G \geq 0$ such that $\|\nabla f_i(x)\| \leq G, \forall i = 1, ..., n$, and $x \in \mathbb{R}^d$.

Assumption A.2 is a more fine-grained assumption on the function smoothness than the commonly used one and is also used by (Bernstein et al., 2018; Safaryan & Richtárik, 2021). For the convergence rate analysis, we consider two cases, namely, the case with $z < +\infty$ and the case of $z = \infty$.

3.1 CASE 1: $z < +\infty$

As we can see from Lemma 1, there always exists some gradient bias when $z < +\infty$. In order to bound it, we further assume that a higher order moment of the mini-batch gradient noise is bounded.

Assumption 2. *There exists a constant $Q_z \geq 0$ such that for any $x \in \mathbb{R}^d$, we have*

$$\mathbb{E}[\|g_i(x) - \nabla f_i(x)\|_{4z+2}^{4z+2}] \leq Q_z. \tag{5}$$

Theorem 1. *Suppose that Assumption 1 and 2 hold. Denote $\bar{x}_{t,s} = \frac{1}{n}\sum_{i=1}^n x_{t,s}^i$ and $L_{\max} = \max_j L_j$. Then, for $\eta = \eta_z \sigma$, $\gamma \leq \frac{1}{L_{\max}}$ and $z < +\infty$ in Algorithm 1, we have*

$$\mathbb{E}\left[\frac{1}{TE}\sum_{t=1}^T \sum_{s=1}^E \|\nabla f(\bar{x}_{t-1,s-1})\|^2\right] \leq \underbrace{\frac{2\mathbb{E}[f(x_0) - f^*]}{TE\gamma} + \frac{\gamma\zeta^2 L_{\max}}{n} + \frac{4\gamma^2(E-1)EL_{\max}^2(\zeta^2 + G^2)}{3}}_{\text{(a) Standard terms in FedAvg}}$$

(6a)

$$+ \underbrace{\frac{2^{2z+1}E^{2z}\sqrt{Q_z + G^{4z+2}}G}{\sqrt{2}(2z+1)\sigma^{2z}} + \frac{\gamma 2^{4z}E^{4z+1}(Q_z + G^{4z+2})L_{\max}}{2(2z+1)^2\sigma^{4z}}}_{\text{(b) Bias terms}}$$

(6b)

$$+ \underbrace{\frac{4\eta_z^2\gamma\sigma^2\sum_{j=1}^d L_j}{En}}_{\text{(c) Variance term}}. \tag{6c}$$

When is the bound non-trivial? Since we assume that the ℓ_2-norm of gradient is bounded by G, all the terms in the RHS of (6) should be no larger than G^2. For example, to have the first term in (6b) less than G^2, one requires σ to be greater than $2^{1+\frac{1}{4z}}E\left(Q_z/G + G^{4z}\right)^{\frac{1}{4z}}/(2z+1)^{\frac{1}{2z}}$.

Bias-variance trade-off. An interesting observation from Theorem 1 is that there exists a trade-off between the bias and variance terms. One can see that the terms in (6b) is caused by the gradient bias of the sign operation (see (4)) and is an infinitesimal of σ with $\mathcal{O}\left(\sigma^{-2z}\right)$, while the term in (6c) is due to the injected noise and is in the order of $\mathcal{O}\left(\gamma\sigma^2\right)$. Specifically, the first term in (6b) only depends on the noise scale σ and mostly affects the final learning accuracy. Meanwhile, the variance term in (6c) mainly affects the convergence speed because a smaller stepsize is required for it to diminish.

Theoretically, we can choose an iteration-dependent noise scale σ so as to make the algorithm converge to a stationary solution. To see this, let us denote $\tau = TE$ as the total number of gradient queries per client, and present the following corollary.

Corollary 1 (Informal). *Let $\gamma = \min\{n^{\frac{z}{2z+1}}\tau^{-\frac{z+1}{2z+1}}, L_{\max}^{-1}\}$ and $\sigma = (n\tau)^{\frac{1}{4z+2}}$ in Theorem 1, and let $E \leq n^{-\frac{3z}{4z+2}}\tau^{\frac{z+2}{4z+2}}$. We have*

$$\mathbb{E}\left[\frac{1}{\tau}\sum_{t=1}^T \sum_{s=1}^E \|\nabla f(\bar{x}_{t-1,s-1})\|^2\right] = \mathcal{O}\left((n\tau)^{-\frac{z}{2z+1}}\right). \tag{7}$$

Achieveing linear speedup. From Corollary 1, we can see that the z-SignFedAvg needs $(n\tau)^{\frac{3z}{4z+2}}$ communication rounds to achieve a linear-speedup convergence rate. Particularly, when $z = 1$, the corresponding convergence rate is $\mathcal{O}((n\tau)^{-\frac{1}{3}})$ and the required communication rounds is $(n\tau)^{\frac{1}{2}}$. To the best of our knowledge, the previous works have never shown the sign-based method can achieve a linear-speedup convergence rate.

Relationship to (Chen et al., 2020a). The work (Chen et al., 2020a) also considered the use of a symmetric and zero-mean noise for the sign-based compression and proved that the algorithm has a convergence rate $\mathcal{O}(\tau^{-\frac{1}{4}})$. However, their results have three differences from our z-SignFedAvg and Theorem 1. First, (Chen et al., 2020a) considered gradient compression both in the uplink and downlink communications. In addition, the convergence metric they used is not the standard squared ℓ_2-norm of gradients and is hard to interpret. Second, their analysis is rooted in the median-based algorithm, whereas we judiciously exploit the property of the sign operation and hence provide a general analysis framework for the stochastic sign-based methods. Last but not the least, unlike our z-SignFedAvg, (Chen et al., 2020a) cannot allow multiple local SGD updates.

3.2 CASE 2: $z = +\infty$

When $z = +\infty$, the injected noise ξ_z in the z-SignFedAvg is uniformly distributed on $[-1, 1]$. From Remark 1, we have learned that the gradient bias can vanish as long as the noise scale σ is sufficiently large. To quantify this threshold, we need the following assumption which is a limit form of Assumption 2.

Assumption 3. *There exists a constant $Q_\infty \geq 0$ such that for any $x \in \mathbb{R}^d$, with probability 1,*

$$\|g_i(x) - \nabla f_i(x)\|_\infty \leq Q_\infty. \tag{8}$$

Theorem 2. *(Informal) Suppose that Assumption 1 and 3 hold. For $\gamma = \min\{n^{\frac{1}{2}}\tau^{-\frac{1}{2}}, L_{\max}^{-1}\}$, $\eta = \sigma$, $z = +\infty$, $E \leq n^{-\frac{3}{4}}\tau^{\frac{1}{4}}$ and $\sigma > E(G + Q_\infty)$ in Algorithm 1 we have*

$$\mathbb{E}\left[\frac{1}{\tau}\sum_{t=1}^{T}\sum_{s=1}^{E}\|\nabla f(\bar{x}_{t-1,s-1})\|^2\right] = \mathcal{O}\left((n\tau)^{-\frac{1}{2}}\right). \tag{9}$$

However, if $\sigma \leq E(G+Q_\infty)$, there exists a problem instance for which Algorithm 1 cannot converge.

Remark 2. *Note that Theorem 2 implies that ∞-SignFedAvg has a matching convergence rate as the uncompressed FedAvg. The reason why ∞-SignFedAvg cannot converge when $\sigma \leq E(G + Q_\infty)$ is simply that the uniform noise has a finite support and cannot always change the sign of gradients. For example, if $\sigma < A$ for some $A > 0$, then we have $\mathrm{Sign}(x + \sigma\xi_\infty) = \mathrm{Sign}(x)$ for any $x \geq A$.*

Relationship to (Jin et al., 2020; Safaryan & Richtárik, 2021). As mentioned in Remark 1, both the stochastic sign operators in (Jin et al., 2020; Safaryan & Richtárik, 2021) are equivalent to the sign operator injected by the uniform noise. Nevertheless, there are still two distinctions when compared with our ∞-SignFedAvg. First, while (Safaryan & Richtárik, 2021) shows their algorithm has a $\mathcal{O}(\tau^{-\frac{1}{4}})$ convergence rate, it is based on the ℓ_2-norm of gradients and cannot imply the same rate as that in (9) (see Appendix A). Second, although (Safaryan & Richtárik, 2021) does not need Assumption 3, it relies on an input-dependent noise scale which, unfortunately, often slows the algorithm convergence in practice especially when the problem dimension is large.

More theoretical results and proofs are relegated to Appendix B and C.

3.3 COMPARISON OF CASE 1 AND CASE 2

Table 1: Comparison of Case 1 and Case 2.

Case	Convergence rate	Threshold on σ	Assumption on gradient noise
$z < +\infty$	$\mathcal{O}(\tau^{-\frac{z}{2z+1}})$	$\tilde{\mathcal{O}}\left(\left(\frac{Q_z}{G} + G^{4z}\right)^{\frac{1}{4z}}\right)$	Assumption 2
$z = +\infty$	$\mathcal{O}(\tau^{-\frac{1}{2}})$	$\tilde{\mathcal{O}}(Q_\infty + G)$	Assumption 3

We summarize the results of Case 1 and Case 2 in Table 1, where $\tilde{O}(\cdot)$ hides some constants that do not affect the comparison. Especially, we can see that when the mini-batch gradient noise has a long tail such that $Q_z/G \ll Q_\infty^{4z}$, Case 1 requires a less amount of noise than Case 2 for guaranteeing convergence. Despite of the difference in theory, we will see in Section 4 that z-SignFedAvg under Case 1 and Case 2 have almost the same behavior in practice.

4 EXPERIMENTS

In this section, we present the experiment results on both synthetic and real problems, and all the figures in this section are obtained by 10 independent runs and are visualized in the form of mean±std.

Noise scale as a hyperparameter. Although we explicitly characterize how the performance of z-SignFedAvg depends on the noise scale σ in the previous section, we treat σ as a tunable hyperparameter in the experiments. This is because the theoretical values for σ are either difficult to compute or are too conservative for practical applications.

4.1 A SIMPLE CONSENSUS PROBLEM

In this section, we verify our theoretical results in Section 3 by considering the simple consensus problem with 10 clients: $\min_{x \in \mathbb{R}^d} \frac{1}{2} \sum_{i=1}^{10} \|x - y_i\|^2$, where $y_1, ..., y_{10} \in \mathbb{R}^d$ are generated using i.i.d standard Gaussian distribution, and d is the problem dimension. We implemented the following algorithms: GD (Gradient descent), Sto-SignSGD (Safaryan & Richtárik, 2021), SignSGD (Algorithm 1 with $z = 1$, $E = 1$ and $\sigma = 0$), 1-SignSGD (Algorithm 1 with $z = 1$ and $E = 1$.), ∞-SignSGD (Algorithm 1 with $z = +\infty$ and $E = 1$). For all the algorithms, we considered the full gradient (no mini-batch SGD), and used the same stepsize 0.01 and initialization by a zero vector.

Results. As we can see from Figure 1, the vanilla SignSGD fails to converge to the optimal solution whereas the others can. Besides, 1-SignSGD and ∞-SignSGD have roughly the same convergence speed which is slightly slower than the uncompressed GD. It is also observed that the input-dependent noise scale adopted by (Safaryan & Richtárik, 2021) could slow the convergence when the problem dimension is high, as discussed in Section 3.2.

Figure 2 displays the results of 1-SignSGD and ∞-SignSGD with various noise scales. We can see that there is a clear bias-variance trade-off for different noise scales and it corroborates our analysis after Theorem 1. It is also worth mentioning that the best choice of σ for Algorithm 1 shown in Figure 2 is much smaller than the one predicted by the theorems.

(a) $d = 10$ (b) $d = 100$ (c) $d = 1000$

Figure 1: Performance of tested algorithms under different problem dimension.

4.2 z-SIGNSGD ON NON-I.I.D MNIST

In this section, we consider an extremely non-i.i.d setting with the MNIST dataset (Deng, 2012). Specifically, we split the dataset into 10 parts based on the labels and each client has the data of one digit only. A simple two-layer convolutional neural network (CNN) from Pytorch tutorial (Paszke et al., 2017) was used for the learning task. The following algorithms were implemented: SGDwM (Distributed SGD (Ghadimi & Lan, 2013) with momen-

(a) 1-SignSGD   (b) ∞-SignSGD

Figure 2: z-SignSGD under various noise scales.

tum), EF-SignSGDwM (Distributed SignSGD with error-feedback and momentum (Karimireddy et al., 2019; Vogels et al., 2019)), and Sto-SignSGDwM (Sto-SignSGD with momentum (Safaryan & Richtárik, 2021)). For each of the algorithms, we selected its best hyperparameters, including the stepsize, momentum coefficient and the noise scale, via grid search (see Appendix E.1).

Results. One can observe from Figure 3a-3b that again the vanilla SignSGD does not converge well. The proposed 1-SignSGD and ∞-SignSGD clearly outperform the existing EF-SignSGDwM and Sto-SignSGDw, and perform closely to the uncompressed SGDwM. The reason for the slow convergence of Sto-SignSGDw is that the injected noise is too large due to the input-dependent noise scale. Figure 3c further displays the testing accuracy of all methods versus the accumulated number

of bits transmitted from the clients to the server. One can see that the proposed algorithms achieve the state-of-the-art performance on this task. More results for 1-SignSGD and ∞-SignSGD under different noise scales are presented in Appendix E.1.

(a) Training Loss   (b) Test Accuracy   (c) Test Accuracy w.r.t bits

Figure 3: Performance of various SignSGD algorithms on non-i.i.d MNIST.

4.3 z-SIGNFEDAVG ON EMNIST AND CIFAR-10

In this section, we evaluate the performance of our proposed z-SignFedAvg on two classical datasets: EMNIST(Cohen et al., 2017) and CIFAR-10 (Krizhevsky & Hinton, 2010). In particular, the proposed z-SignFedAvg with $z = 1$ and $z = \infty$ are benchmarked against the uncompressed FedAvg (McMahan et al., 2017; Yu et al., 2019). Since 1-SignFedAvg and ∞-SignFedAvg behave similarly, we only report the results of 1-SignFedAvg in this section and relegate the others to Appendix E.2. For EMNIST, we use the same 2-layer CNN as the one in Section 4.2. For CIFAR-10, we used the ResNet18 (He et al., 2016) with group normalization (Wu & He, 2018).

Settings. For both the experiments on EMNIST and CIFAR-10, we followed a setting similar to (Reddi et al., 2020). We also considered the scenario with partial client participation. For the EMNIST dataset, there are 3579 clients in total and 100 clients were uniformly sampled in each communication round to upload their compressed gradients. For the CIFAR-10 dataset, the training samples are partitioned among 100 clients, and each client has an associated multinomial distribution over labels drawn from a symmetric Dirichlet distribution with parameter 1. In each communication round, 10 out of 100 clients were uniformly sampled. The same noise scales for 1-SignFedAvg and ∞-SignFedAvg were used: $\sigma = 0.01$ for EMNIST and $\sigma = 0.005$ for CIFAR-10. More details about the hyperparameters are referred to Appendix E.2.

Results. We can see from Figure 4 and Figure 5 that both uncompressed FedAvg and 1-SignFedAvg can benefit from multiple local SGD steps. More surprisingly, 1-SignFedAvg can even outperform the uncompressed FedAvg. This is probably because the EMNIST dataset is less heterogeneous than the one we used in Section 4.2. The results on the performance of 1-SignFedAvg and ∞-SignFedAvg under various choices of noise scales are relegated to Appendix E.2, which are also consistent with our theoretical claims in Section 3.

(a) Training Loss   (b) Test Accuracy   (c) Test Accuracy w.r.t bits

Figure 4: Performance of FedAvg and 1-SignFedAvg on the EMNIST dataset.

4.4 DIFFERENTIAL PRIVATE FEDERATED LEARNING ON EMNIST

Let us first review the definition of DP.

Definition 2 (Approximate DP (Dwork et al., 2014))**.** *A randomized algorithm M that takes as input a dataset consisting of individuals is (ε, δ)-differentially private if for any pair of datasets S, S' that differ in the record of a single individual, and for any event E,*

$$\mathbb{P}[M(S) \in E] \leqslant e^{\varepsilon} \mathbb{P}[M(S') \in E] + \delta. \tag{10}$$

Figure 5: Performance of FedAvg and 1-SignFedAvg on the CIFAR-10 dataset.

The value ε is regarded as the privacy budget, and the smaller it is the stronger privacy the algorithm provides. The quantity δ is usually set to $\frac{1}{n}$. The most popular mechanism to achieve DP is the Gaussian mechanism (Dwork et al., 2014). For more details on DP and its application in FL, we refer readers to (Dwork et al., 2014; Mironov, 2017; Abadi et al., 2016b; Geyer et al., 2017).

We state the DP version of Algorithm 1 in Appendix D which we term DP-SignFedAvg (Algorithm 2). The only difference between DP-SignFedAvg and z-SignFedAvg is that $z = 1$ is chosen (Gaussian noise), and the norm of local gradients is clipped before perturbing it by the noise and applying the sign compression. In this section, we investigate the empirical performance of the DP-SignFedAvg on EMNIST, and compared it with the uncompressed DP-FedAvg used in (Agarwal et al., 2021; Kairouz et al., 2021).

Settings. We followed a setting similar to (Kairouz et al., 2021) for the experiment on EMNIST. We adopted the user-level differential privacy, i.e., to treat each client as a single data point, and perturbed the local gradients before sending them to server. We also used the technique of privacy amplification by client sub-sampling in (Kairouz et al., 2021; Geyer et al., 2017). For both DP-FedAvg and DP-SignFedAvg, the same CNN in Section 4.2 was used, and the maximum norm for clipping was set to 0.01. We sampled 100 clients at each communication round and ran both algorithms for 500 communication rounds. More details about hyperparameters are given in Appendix E.3.

Results. It can be seen from Figure 6 that DP-SignFedAvg is only slightly inferior to the uncompressed DP-FedAvg for various levels of privacy budget. It is worthy to note that the work (Kairouz et al., 2021) conducted a similar experiment and showed that the compressed DP-FedAvg with 12 bits for each gradient coordinate can be far worse than the uncompressed DP-FedAvg. It is a strong contrast to our DP-SignFedAvg which uses only 1 bit for each coordinate.

5   CONCLUSION

In this work, we have proposed the z-SignFedAvg: a FedAvg-type algorithm with the stochastic sign-based compression. Thanks to the novel noisy perturbation scheme in Section 2, the proposed z-SignFedAvg provides a unified viewpoint to the existing sign-based methods as well as a general framework for convergence rate analysis. Through both theoreti-

Figure 6: Performance of DP-SignFedAvg and DP-FedAvg

cal analyses and empirical experiments, we have shown that the z-SignFedAvg can perform nearly the same, sometimes even better, than the uncompressed FedAvg and enjoy a significant reduction in the number of bits transmitted from clients to the server. However, the z-SignFedAvg involves a new hyperparameter, i.e., the noise scale σ, and it requires a careful selection for good convergence performance. An interesting finding from the experiments is that the less heterogeneous the clients' data are, the smaller the optimal noise scale can be. In the future, it is worthwhile to rigorously study the relationship between the data heterogeneity and the optimal noise scale.

As a final remark, the stochastic sign-based compression proposed in this work can be of independent interest and can be conveniently combined with other adaptive FL algorithms such as those in (Karimireddy et al., 2020; Reddi et al., 2020), to further improve the communication efficiency.

REFERENCES

Martín Abadi, Paul Barham, Jianmin Chen, Zhifeng Chen, Andy Davis, Jeffrey Dean, Matthieu Devin, Sanjay Ghemawat, Geoffrey Irving, Michael Isard, et al. {TensorFlow}: a system for {Large-Scale} machine learning. In *12th USENIX symposium on operating systems design and implementation (OSDI 16)*, pp. 265–283, 2016a.

Martin Abadi, Andy Chu, Ian Goodfellow, H Brendan McMahan, Ilya Mironov, Kunal Talwar, and Li Zhang. Deep learning with differential privacy. In *Proceedings of the 2016 ACM SIGSAC conference on computer and communications security*, pp. 308–318, 2016b.

Naman Agarwal, Ananda Theertha Suresh, Felix Xinnan X Yu, Sanjiv Kumar, and Brendan McMahan. cpsgd: Communication-efficient and differentially-private distributed sgd. *Advances in Neural Information Processing Systems*, 31, 2018.

Naman Agarwal, Peter Kairouz, and Ziyu Liu. The skellam mechanism for differentially private federated learning. *Advances in Neural Information Processing Systems*, 34:5052–5064, 2021.

Dan Alistarh, Demjan Grubic, Jerry Li, Ryota Tomioka, and Milan Vojnovic. Qsgd: Communication-efficient sgd via gradient quantization and encoding. *Advances in neural information processing systems*, 30, 2017.

Saba Amiri, Adam Belloum, Sander Klous, and Leon Gommans. Compressive differentially-private federated learning through universal vector quantization. 2021.

Shahab Asoodeh, Jiachun Liao, Flavio P Calmon, Oliver Kosut, and Lalitha Sankar. Three variants of differential privacy: Lossless conversion and applications. *IEEE Journal on Selected Areas in Information Theory*, 2(1):208–222, 2021.

Jeremy Bernstein, Yu-Xiang Wang, Kamyar Azizzadenesheli, and Animashree Anandkumar. signsgd: Compressed optimisation for non-convex problems. In *International Conference on Machine Learning*, pp. 560–569. PMLR, 2018.

Dimitri P Bertsekas. Nonlinear programming. *Journal of the Operational Research Society*, 48(3): 334–334, 1997.

Zhiqi Bu, Jinshuo Dong, Qi Long, and Weijie J Su. Deep learning with gaussian differential privacy. *Harvard data science review*, 2020(23), 2020.

Xiangyi Chen, Tiancong Chen, Haoran Sun, Steven Z Wu, and Mingyi Hong. Distributed training with heterogeneous data: Bridging median-and mean-based algorithms. *Advances in Neural Information Processing Systems*, 33:21616–21626, 2020a.

Xiangyi Chen, Steven Z Wu, and Mingyi Hong. Understanding gradient clipping in private sgd: A geometric perspective. *Advances in Neural Information Processing Systems*, 33:13773–13782, 2020b.

John T Chu. On bounds for the normal integral. *Biometrika*, 42(1/2):263–265, 1955.

Gregory Cohen, Saeed Afshar, Jonathan Tapson, and Andre Van Schaik. Emnist: Extending mnist to handwritten letters. In *2017 international joint conference on neural networks (IJCNN)*, pp. 2921–2926. IEEE, 2017.

Laurent Condat, Kai Yi, and Peter Richtárik. Ef-bv: A unified theory of error feedback and variance reduction mechanisms for biased and unbiased compression in distributed optimization. *arXiv preprint arXiv:2205.04180*, 2022.

Li Deng. The mnist database of handwritten digit images for machine learning research [best of the web]. *IEEE signal processing magazine*, 29(6):141–142, 2012.

Jinshuo Dong, Aaron Roth, and Weijie Su. Gaussian differential privacy. *Journal of the Royal Statistical Society*, 2021.

Cynthia Dwork, Aaron Roth, et al. The algorithmic foundations of differential privacy. *Found. Trends Theor. Comput. Sci.*, 9(3-4):211–407, 2014.

Jonas Geiping, Hartmut Bauermeister, Hannah Dröge, and Michael Moeller. Inverting gradients-how easy is it to break privacy in federated learning? *Advances in Neural Information Processing Systems*, 33:16937–16947, 2020.

Robin C Geyer, Tassilo Klein, and Moin Nabi. Differentially private federated learning: A client level perspective. *arXiv preprint arXiv:1712.07557*, 2017.

Saeed Ghadimi and Guanghui Lan. Stochastic first- and zeroth-order methods for nonconvex stochastic programming. *SIAM Journal on Optimization*, 23(4):2341–2368, 2013. doi:10.1137/120880811. URL https://doi.org/10.1137/120880811.

Kaiming He, Xiangyu Zhang, Shaoqing Ren, and Jian Sun. Deep residual learning for image recognition. In *Proceedings of the IEEE conference on computer vision and pattern recognition*, pp. 770–778, 2016.

Yangsibo Huang, Samyak Gupta, Zhao Song, Kai Li, and Sanjeev Arora. Evaluating gradient inversion attacks and defenses in federated learning. *Advances in Neural Information Processing Systems*, 34:7232–7241, 2021.

Richeng Jin, Yufan Huang, Xiaofan He, Huaiyu Dai, and Tianfu Wu. Stochastic-sign sgd for federated learning with theoretical guarantees. *arXiv preprint arXiv:2002.10940*, 2020.

Peter Kairouz, Ziyu Liu, and Thomas Steinke. The distributed discrete gaussian mechanism for federated learning with secure aggregation. In *International Conference on Machine Learning*, pp. 5201–5212. PMLR, 2021.

Leonid Vitalevich Kantorovich and Gleb Pavlovich Akilov. *Functional analysis*. Elsevier, 2016.

Sai Praneeth Karimireddy, Quentin Rebjock, Sebastian Stich, and Martin Jaggi. Error feedback fixes signsgd and other gradient compression schemes. In *International Conference on Machine Learning*, pp. 3252–3261. PMLR, 2019.

Sai Praneeth Karimireddy, Satyen Kale, Mehryar Mohri, Sashank Reddi, Sebastian Stich, and Ananda Theertha Suresh. Scaffold: Stochastic controlled averaging for federated learning. In *International Conference on Machine Learning*, pp. 5132–5143. PMLR, 2020.

Jakub Konečnỳ, H Brendan McMahan, Felix X Yu, Peter Richtárik, Ananda Theertha Suresh, and Dave Bacon. Federated learning: Strategies for improving communication efficiency. *arXiv preprint arXiv:1610.05492*, 2016.

Alex Krizhevsky and Geoff Hinton. Convolutional deep belief networks on cifar-10. *Unpublished manuscript*, 40(7):1–9, 2010.

Tian Li, Anit Kumar Sahu, Ameet Talwalkar, and Virginia Smith. Federated learning: Challenges, methods, and future directions. *IEEE Signal Processing Magazine*, 37(3):50–60, 2020a.

Yiwei Li, Tsung-Hui Chang, and Chong-Yung Chi. Secure federated averaging algorithm with differential privacy. In *2020 IEEE 30th International Workshop on Machine Learning for Signal Processing (MLSP)*, pp. 1–6. IEEE, 2020b.

Xiangru Lian, Ce Zhang, Huan Zhang, Cho-Jui Hsieh, Wei Zhang, and Ji Liu. Can decentralized algorithms outperform centralized algorithms? a case study for decentralized parallel stochastic gradient descent. *Advances in Neural Information Processing Systems*, 30, 2017.

Brendan McMahan, Eider Moore, Daniel Ramage, Seth Hampson, and Blaise Aguera y Arcas. Communication-efficient learning of deep networks from decentralized data. In *Artificial intelligence and statistics*, pp. 1273–1282. PMLR, 2017.

Ilya Mironov. Rényi differential privacy. In *2017 IEEE 30th computer security foundations symposium (CSF)*, pp. 263–275. IEEE, 2017.

Ilya Mironov, Kunal Talwar, and Li Zhang. R\'enyi differential privacy of the sampled gaussian mechanism. *arXiv preprint arXiv:1908.10530*, 2019.

Adam Paszke, Sam Gross, Soumith Chintala, Gregory Chanan, Edward Yang, Zachary DeVito, Zeming Lin, Alban Desmaison, Luca Antiga, and Adam Lerer. Automatic differentiation in pytorch. 2017.

Sashank Reddi, Zachary Charles, Manzil Zaheer, Zachary Garrett, Keith Rush, Jakub Konečnỳ, Sanjiv Kumar, and H Brendan McMahan. Adaptive federated optimization. *arXiv preprint arXiv:2003.00295*, 2020.

Amirhossein Reisizadeh, Aryan Mokhtari, Hamed Hassani, Ali Jadbabaie, and Ramtin Pedarsani. Fedpaq: A communication-efficient federated learning method with periodic averaging and quantization. In *International Conference on Artificial Intelligence and Statistics*, pp. 2021–2031. PMLR, 2020.

Mher Safaryan and Peter Richtárik. Stochastic sign descent methods: New algorithms and better theory. In *International Conference on Machine Learning*, pp. 9224–9234. PMLR, 2021.

Igal Sason and Sergio Verdú. f-divergence inequalities. *IEEE Transactions on Information Theory*, 62(11):5973–6006, 2016.

Frank Seide, Hao Fu, Jasha Droppo, Gang Li, and Dong Yu. 1-bit stochastic gradient descent and its application to data-parallel distributed training of speech dnns. In *Fifteenth annual conference of the international speech communication association*. Citeseer, 2014.

Hanlin Tang, Chen Yu, Xiangru Lian, Tong Zhang, and Ji Liu. Doublesqueeze: Parallel stochastic gradient descent with double-pass error-compensated compression. In *International Conference on Machine Learning*, pp. 6155–6165. PMLR, 2019.

Hanlin Tang, Shaoduo Gan, Ammar Ahmad Awan, Samyam Rajbhandari, Conglong Li, Xiangru Lian, Ji Liu, Ce Zhang, and Yuxiong He. 1-bit adam: Communication efficient large-scale training with adam's convergence speed. In *International Conference on Machine Learning*, pp. 10118–10129. PMLR, 2021a.

Zhiwei Tang, Tsung-Hui Chang, Xiaojing Ye, and Hongyuan Zha. Low-rank matrix recovery with unknown correspondence. *arXiv preprint arXiv:2110.07959*, 2021b.

Tim Van Erven and Peter Harremos. Rényi divergence and kullback-leibler divergence. *IEEE Transactions on Information Theory*, 60(7):3797–3820, 2014.

Thijs Vogels, Sai Praneeth Karimireddy, and Martin Jaggi. Powersgd: Practical low-rank gradient compression for distributed optimization. *Advances in Neural Information Processing Systems*, 32, 2019.

Jianyu Wang and Gauri Joshi. Cooperative sgd: A unified framework for the design and analysis of local-update sgd algorithms. *Journal of Machine Learning Research*, 22, 2021.

Lun Wang, Ruoxi Jia, and Dawn Song. D2p-fed: Differentially private federated learning with efficient communication. *arXiv preprint arXiv:2006.13039*, 2020.

Yanmeng Wang, Yanqing Xu, Qingjiang Shi, and Tsung-Hui Chang. Quantized federated learning under transmission delay and outage constraints. *IEEE Journal on Selected Areas in Communications*, 40(1):323–341, 2021.

Yuxin Wu and Kaiming He. Group normalization. In *Proceedings of the European conference on computer vision (ECCV)*, pp. 3–19, 2018.

Hao Yu, Sen Yang, and Shenghuo Zhu. Parallel restarted sgd with faster convergence and less communication: Demystifying why model averaging works for deep learning. In *Proceedings of the AAAI Conference on Artificial Intelligence*, volume 33, pp. 5693–5700, 2019.

Xinwei Zhang, Xiangyi Chen, Mingyi Hong, Zhiwei Steven Wu, and Jinfeng Yi. Understanding clipping for federated learning: Convergence and client-level differential privacy. *arXiv preprint arXiv:2106.13673*, 2021.

Qinqing Zheng, Shuxiao Chen, Qi Long, and Weijie Su. Federated f-differential privacy. In *International Conference on Artificial Intelligence and Statistics*, pp. 2251–2259. PMLR, 2021.

Shuai Zheng, Ziyue Huang, and James Kwok. Communication-efficient distributed blockwise momentum sgd with error-feedback. *Advances in Neural Information Processing Systems*, 32, 2019.

APPENDIX

A COMPARISON WITH EXISTING STOCHASTIC SIGN-BASED METHODS

Table 2 summarizes the key features of a few representative stochastic sign-based methods and the proposed z-SignFedAvg, including the convergence rate, metric used in the convergence rate analysis, extra assumptions other than A.1-A.3 in Assumption 1, and whether the algorithm can achieve linear speedup and allow multiple local SGD steps.

For communication complexity, we focus on the uplink communication cost, i.e., the number of bits transmitted from the clients to the server in each communication round. We assume that all the uncompressed algorithms use 32 bits to represent a single float number as it is the most common setting in Tensorflow (Abadi et al., 2016a) and Pytorch (Paszke et al., 2017).

While most of the existing methods use the squared ℓ_2-norm of gradients as the convergence metric, the work (Safaryan & Richtárik, 2021) adopts the ℓ_2-norm of gradients. The work (Chen et al., 2020a) uses a convergence metric mixed with squared ℓ_2-norm and ℓ_1-norm of gradients due to the compression in both uplink and downlink .

Algorithm	Convergence rate / metric	Num. of bits per commun. round	Extra Assumptions?	Can achieve linear speedup?	Can allow multiple local steps?
(Ghadimi & Lan, 2013)	$\mathcal{O}(\tau^{-\frac{1}{2}})$ squared ℓ_2	$32d$	No	✓	✗
(McMahan et al., 2017) (Yu et al., 2019)	$\mathcal{O}(\tau^{-\frac{1}{2}})$ squared ℓ_2	$32d$	• Bounded gradient	✓	✓
(Karimireddy et al., 2019)	$\mathcal{O}(\tau^{-\frac{1}{2}} + d^2\tau^{-1})$ squared ℓ_2	$d + 32$	• Bounded gradient	✗	✗
(Safaryan & Richtárik, 2021)	$\mathcal{O}(\tau^{-\frac{1}{4}})$ ℓ_2	d	No	✗	✗
(Jin et al., 2020)	$\mathcal{O}(\tau^{-\frac{1}{4}})$ squared ℓ_2	d	• Bounded gradient • n is an odd number	✗	✗
(Chen et al., 2020a)	$\mathcal{O}(\tau^{-\frac{1}{4}})$ mixed	d	• Bounded gradient • n is an odd number	✗	✗
1-SignFedAvg (ALG. 1) **This work**	$\mathcal{O}(\tau^{-\frac{1}{3}})$ squared ℓ_2	d	• Bounded gradient • Bounded 6th moment of gradient noise	✓	✓
∞-SignFedAvg (ALG. 1) **This work**	$\mathcal{O}(\tau^{-\frac{1}{2}})$ squared ℓ_2	d	• Bounded gradient • Bounded support of gradient noise	✓	✓

Table 2: Summary of representative stochastic sign-based methods.

Among the works in Table 2, the setting considered by (Safaryan & Richtárik, 2021) is closest to ours. (Safaryan & Richtárik, 2021) proposed an algorithm that can achieve the convergence rate $\mathcal{O}(\tau^{-\frac{1}{4}})$ with the ℓ_2-norm of gradients as the metric. We remark that this is inferior to the convergence rate $\mathcal{O}(\tau^{-\frac{1}{2}})$ with the squared ℓ_2-norm as the metric. To illustrate this point, we denote a series of vector

as $\{\alpha_1, ..., \alpha_\tau, ...\}$ with $\alpha_i \in \mathbb{R}^d$. If now

$$\frac{1}{\tau}\sum_{i=1}^{\tau}\|\alpha_i\| = \mathcal{O}(\tau^{-\frac{1}{4}}), \tag{11}$$

in the worst case, we can only guarantee that

$$\frac{1}{\tau}\sum_{i=1}^{\tau}\|\alpha_i\|^2 \leq \tau\left(\frac{1}{\tau}\sum_{i=1}^{\tau}\|\alpha_i\|\right)^2 = \mathcal{O}(\tau^{\frac{1}{2}}). \tag{12}$$

As a simple example, the equality in (12) holds if and only if there is exactly one non-zero term in $\{\alpha_1, ..., \alpha_\tau\}$.

On the contrary, if it holds that

$$\frac{1}{\tau}\sum_{i=1}^{\tau}\|\alpha_i\|^2 = \mathcal{O}(\tau^{-\frac{1}{2}}), \tag{13}$$

then we have

$$\frac{1}{\tau}\sum_{i=1}^{\tau}\|\alpha_i\| \leq \sqrt{\frac{1}{\tau}\sum_{i=1}^{\tau}\|\alpha_i\|^2} = \mathcal{O}(\tau^{-\frac{1}{4}}). \tag{14}$$

Thus, the convergence results in (Safaryan & Richtárik, 2021) cannot imply the rate in Theorem 2. Besides, the algorithm in (Safaryan & Richtárik, 2021) is equivalent to our Algorithm 1 with $z = \infty$, $E = 1$ and $\sigma = \|g_{t-1,s}^i\|$. This input-dependent noise scale is linearly increasing w.r.t the problem dimension and is too conservative for practical applications. From Figure 1 and Figure 3, we have already seen that this input-dependent noise scale could result in an extremely slow convergence for high-dimensional problems.

B   DETAILED THEORETICAL RESULTS

We first state the result on the limit of z-distribution.

Lemma 2. *The z-distribution weakly converges to uniform distribution on $[-1, 1]$ when $z \to +\infty$.*

The following corollary is the formal version of Corollary 1.

Corollary 2 (Formal version of Corollary 1). *For $\gamma = \min\{n^{\frac{z}{2z+1}}\tau^{-\frac{z+1}{2z+1}}, \frac{1}{L_{\max}}\}$ and $\sigma = (n\tau)^{\frac{1}{4z+2}}$ in Theorem 1, we have*

$$\mathbb{E}\left[\frac{1}{\tau}\sum_{t=1}^{T}\sum_{s=1}^{E}\|\nabla f(\bar{x}_{t-1,s-1})\|^2\right] \leq \frac{2\mathbb{E}[f(x_0) - f^*]}{(n\tau)^{\frac{z}{2z+1}}} + \frac{\zeta^2 L_{\max}}{(n\tau)^{\frac{z+1}{2z+1}}} + \frac{4(E-1)En^{\frac{2z}{2z+1}}L_{\max}^2\left(\zeta^2 + G^2\right)}{3\tau^{\frac{2z+2}{2z+1}}}$$

$$+ \frac{2^{2z+1}E^{2z}\sqrt{Q_z + G^{4z+2}}G}{\sqrt{2}(2z+1)(n\tau)^{\frac{z}{2z+1}}} + \frac{2^{4z}E^{4z+1}(Q_z + G^{4z+2})L_{\max}}{2(2z+1)^2 n^{\frac{z}{2z+1}}\tau^{\frac{3z+1}{2z+1}}}$$

$$+ \frac{4\eta_z^2\sum_{j=1}^{d}L_j}{E(n\tau)^{\frac{z}{2z+1}}}. \tag{15}$$

Furthermore, if $E \leq n^{-\frac{3z}{4z+2}}\tau^{\frac{z+2}{4z+2}}$, the upper bound above becomes

$$\mathbb{E}\left[\frac{1}{\tau}\sum_{t=1}^{T}\sum_{s=1}^{E}\|\nabla f(\bar{x}_{t-1,s-1})\|^2\right] \leq \frac{2\mathbb{E}[f(x_0) - f^*]}{(n\tau)^{\frac{z}{2z+1}}} + \frac{\zeta^2 L_{\max}}{(n\tau)^{\frac{z+1}{2z+1}}} + \frac{4L_{\max}^2\left(\zeta^2 + G^2\right)}{3(n\tau)^{\frac{z}{2z+1}}}$$

$$+ \frac{2^{2z+1}E^{2z}\sqrt{Q_z + G^{4z+2}}G}{\sqrt{2}(2z+1)(n\tau)^{\frac{z}{2z+1}}} + \frac{2^{4z}E^{4z+1}(Q_z + G^{4z+2})L_{\max}}{2(2z+1)^2 n^{\frac{z}{2z+1}}\tau^{\frac{3z+1}{2z+1}}}$$

$$+ \frac{4\eta_z^2\sum_{j=1}^{d}L_j}{E(n\tau)^{\frac{z}{2z+1}}}. \tag{16}$$

.

The formal version of Theorem 2 is given below.

Theorem 3 (Formal version of Theorem 2). *Suppose that Assumption 1 and 3 hold. For $\gamma \leq \frac{1}{L_{\max}}$, $\eta = \sigma$, $z = +\infty$ and $\sigma > E(G + Q_\infty)$ in Algorithm 1, we have*

$$\mathbb{E}\left[\frac{1}{TE}\sum_{t=1}^{T}\sum_{s=1}^{E}\|\nabla f(\bar{x}_{t-1,s-1})\|^2\right] \leq \underbrace{\frac{2\mathbb{E}[f(x_0) - f^*]}{TE\gamma} + \frac{\gamma\zeta^2 L_{\max}}{n} + \frac{4\gamma^2(E-1)EL_{\max}^2(\zeta^2 + G^2)}{3}}_{\text{Standard terms in FedAvg}}$$

$$+ \underbrace{\frac{4\gamma\sigma^2\sum_{j=1}^{d}L_j}{En}}_{\text{Variance term}}. \tag{17}$$

Otherwise, if $\sigma \leq E(G + Q_\infty)$, there exists a problem instance for which the algorithm cannot converge. If we further choose $\gamma = \min\{n^{\frac{1}{2}}\tau^{-\frac{1}{2}}, \frac{1}{L_{\max}}\}$, we have

$$\mathbb{E}\left[\frac{1}{\tau}\sum_{t=1}^{T}\sum_{s=1}^{E}\|\nabla f(\bar{x}_{t-1,s-1})\|^2\right] \leq \frac{2\mathbb{E}[f(x_0) - f^*]}{(n\tau)^{\frac{1}{2}}} + \frac{\zeta^2 L_{\max}}{(n\tau)^{\frac{1}{2}}} + \frac{4(E-1)EnL_{\max}^2(\zeta^2 + G^2)}{3\tau}$$

$$+ \frac{4\sigma^2\sum_{j=1}^{d}L_j}{E(n\tau)^{\frac{1}{2}}}. \tag{18}$$

Furthermore, if $E \leq n^{-\frac{3}{4}}\tau^{\frac{1}{4}}$, the upper bound above becomes

$$\mathbb{E}\left[\frac{1}{\tau}\sum_{t=1}^{T}\sum_{s=1}^{E}\|\nabla f(\bar{x}_{t-1,s-1})\|^2\right] \leq \frac{2\mathbb{E}[f(x_0) - f^*]}{(n\tau)^{\frac{1}{2}}} + \frac{\zeta^2 L_{\max}}{(n\tau)^{\frac{1}{2}}} + \frac{4L_{\max}^2(\zeta^2 + G^2)}{3(n\tau)^{\frac{1}{2}}}$$

$$+ \frac{4\sigma^2\sum_{j=1}^{d}L_j}{E(n\tau)^{\frac{1}{2}}}, \tag{19}$$

which recovers the convergence result of the uncompressed FedAvg algorithm (Yu et al., 2019).

C PROOFS

C.1 PROOF OF LEMMA 1

We first state a useful inequality on the c.d.f of the z-distribution:

Lemma 3. *For any $x \in \mathbb{R}$, it holds that*

$$|x| - \frac{|x|^{2z+1}}{2(2z+1)} \leq |\Psi_z(x)| \leq |x|, \tag{20}$$

where

$$\Psi_z(x) \overset{\text{def.}}{=} \int_0^x e^{-\frac{t^{2z}}{2}}\,dt.$$

Similar to the sign operator, for any vector $x = [x(1), ..., x(d)]^\top \in \mathbb{R}^d$, we define

$$\Psi_z(x) = [\Psi_z(x(1)), ..., \Psi_z(x(d))]^\top.$$

With the presence of Lemma 3, we have

$$\|\eta_z\sigma\mathbb{E}[\text{Sign}(x + \sigma\xi_z)] - x\|^2 = \left\|x - \sigma\Psi_z\left(\frac{x}{\sigma}\right)\right\|^2 = \sum_{j=1}^{d}\left(x(j) - \sigma\Psi_z\left(\frac{x(j)}{\sigma}\right)\right)^2$$

$$\leq \sum_{j=1}^{d}\frac{(x(j))^{4z+2}}{4(2z+1)^2\sigma^{4z}} = \frac{\|x\|_{4z+2}^{4z+2}}{4(2z+1)^2\sigma^{4z}}. \tag{21}$$

Proof of Lemma 3. Without loss of generality, we consider $x \geq 0$. First,

$$\int_0^x e^{-\frac{t^{2z}}{2}} dt \leq \int_0^x 1 dt \leq x. \tag{22}$$

Now we define $F(x) \stackrel{\text{def.}}{=} \int_0^x e^{-\frac{t^{2z}}{2}} dt - x + \frac{x^{2z+1}}{2(2z+1)}$. Note that $F(0) = 0$. Then, it suffices to show $F(x) \geq 0$ by

$$F'(x) = e^{-\frac{x^{2z}}{2}} - 1 + \frac{x^{2z}}{2} \geq 0. \tag{23}$$

It is true since the inequality $e^{-t} - 1 + t \geq 0$ for any $t \geq 0$. $\square$

C.2 PROOF OF LEMMA 2

Now we denote the p.d.f of the uniform distribution as

$$p_\infty(x) = \begin{cases} \frac{1}{2} & |x| \leq 1, \\ 0 & |x| > 1. \end{cases} \tag{24}$$

Without loss of generality, for any $x > 1$ and $z \in \mathbb{Z}_+$, we have

$$\left| \int_{-\infty}^x \frac{1}{2\eta_z} e^{-\frac{t^{2z}}{2}} dt - \int_{-\infty}^x p_\infty(t) dt \right| = \left| \int_0^x \left(\frac{1}{2\eta_z} e^{-\frac{t^{2z}}{2}} - p_\infty(t) \right) dt \right|$$

$$\leq \int_0^1 \left| \frac{1}{2\eta_z} e^{-\frac{t^{2z}}{2}} - \frac{1}{2} \right| dt + \int_1^x \frac{1}{2\eta_z} e^{-\frac{t^{2z}}{2}} dt. \tag{25}$$

For any $0 < \epsilon < \min\{1, x-1\}$, we have

$$\int_0^1 \left| \frac{1}{2\eta_z} e^{-\frac{t^{2z}}{2}} - \frac{1}{2} \right| dt = \int_0^{1-\epsilon} \left| \frac{1}{2\eta_z} e^{-\frac{t^{2z}}{2}} - \frac{1}{2} \right| dt + \int_{1-\epsilon}^1 \left| \frac{1}{2\eta_z} e^{-\frac{t^{2z}}{2}} - \frac{1}{2} \right| dt$$

$$\leq \left| \frac{1}{2\eta_z} e^{-\frac{(1-\epsilon)^{2z}}{2}} - \frac{1}{2} \right| + \epsilon. \tag{26}$$

Since $\lim_{z\to\infty} \frac{1}{2\eta_z} = \lim_{z\to\infty} \frac{z}{2^{\frac{1}{2z}} \Gamma(\frac{1}{2z})} = \frac{1}{2}$ and $\lim_{z\to\infty} e^{-\frac{(1-\epsilon)^{2z}}{2}} = 1$, there exists an integer $Z_1 > 0$ such that if $z > Z_1$, we have

$$\left| \frac{1}{2\eta_z} e^{-\frac{(1-\epsilon)^{2z}}{2}} - \frac{1}{2} \right| \leq \epsilon.$$

Similarly, we have

$$\int_1^x \frac{1}{2\eta_z} e^{-\frac{t^{2z}}{2}} dt = \int_1^{1+\epsilon} \frac{1}{2\eta_z} e^{-\frac{t^{2z}}{2}} dt + \int_{1+\epsilon}^x \frac{1}{2\eta_z} e^{-\frac{t^{2z}}{2}} dt$$

$$\leq \epsilon + \frac{1}{2\eta_z} e^{-\frac{(1+\epsilon)^{2z}}{2}} (x - 1 - \epsilon). \tag{27}$$

Since $\lim_{z\to\infty} e^{-\frac{(1+\epsilon)^{2z}}{2}} = 0$, there exists an integer $Z_2 > 0$ such that if $z > Z_2$, we have

$$\int_1^x \frac{1}{2\eta_z} e^{-\frac{t^{2z}}{2}} dt \leq \epsilon. \tag{28}$$

In all, for any $0 < \epsilon < \min\{1, x-1\}$, if z is sufficiently large, we have

$$\left| \int_{-\infty}^x \frac{1}{2\eta_z} e^{-\frac{t^{2z}}{2}} dt - \int_{-\infty}^x p_\infty(t) dt \right| \leq 4\epsilon. \tag{29}$$

Taking $\epsilon \to 0$ and $z \to \infty$, we have

$$\lim_{z\to\infty} \left| \int_{-\infty}^x \frac{1}{2\eta_z} e^{-\frac{t^{2z}}{2}} dt - \int_{-\infty}^x p_\infty(t) dt \right| = 0. \tag{30}$$

C.3 PROOF OF THEOREM 1

We denote the aggregated update $\bar{x}_t = \bar{x}_{t-1,E}$. First, we state two technical lemmas:

Lemma 4. *Suppose that Assumption 1 and 2 hold. For the t-th ($1 \leq t \leq T$) communication round in Algorithm 1, if $\eta = \eta_z \sigma$ and $z < +\infty$, we have*

$$
\mathbb{E}[f(x_t) - f(\bar{x}_t)] \leq \frac{\gamma 2^{2z} E^{2z+1} \sqrt{Q_z + G^{4z+2}} G}{\sqrt{2}(2z+1)\sigma^{2z}} + \frac{\gamma^2 2^{4z} E^{4z+2}(Q_z + G^{4z+2}) L_{\max}}{4(2z+1)^2 \sigma^{4z}}
$$
$$
+ \frac{2\eta_z^2 \gamma^2 \sigma^2 \sum_{j=1}^{d} L_j}{n}. \tag{31}
$$

Lemma 5. *Suppose that Assumption 1 hold. For the t-th ($1 \leq t \leq T$) communication round in Algorithm 1, if $\gamma \leq \frac{1}{L_{\max}}$, we have*

$$
\mathbb{E}[f(\bar{x}_t) - f(x_{t-1})] \leq -\frac{\gamma}{2} \sum_{s=1}^{E} \|\nabla f(\bar{x}_{t-1,s-1})\|^2 + \frac{E\gamma^2 \zeta^2 L_{\max}}{2n} + \frac{2\gamma^3 (E-1) E^2 L_{\max}^2 (\zeta^2 + G^2)}{3}. \tag{32}
$$

By combining Lemma 4 and Lemma 5, we have

$$
\mathbb{E}[f(x_t) - f(x_{t-1})] = \mathbb{E}[f(x_t) - f(\bar{x}_t)] + E[f(\bar{x}_t) - f(x_{t-1})]
$$
$$
\leq -\frac{\gamma}{2} \sum_{s=1}^{E} \|\nabla f(\bar{x}_{t-1,s-1})\|^2 + \frac{E\gamma^2 \zeta^2 L_{\max}}{2n} + \frac{2\gamma^3 (E-1) E^2 L_{\max}^2 (\zeta^2 + G^2)}{3}
$$
$$
+ \frac{\gamma 2^{2z} E^{2z+1} \sqrt{Q_z + G^{4z+2}} G}{\sqrt{2}(2z+1)\sigma^{2z}} + \frac{\gamma^2 2^{4z} E^{4z+2}(Q_z + G^{4z+2}) L_{\max}}{4(2z+1)^2 \sigma^{4z}}
$$
$$
+ \frac{2\eta_z^2 \gamma^2 \sigma^2 \sum_{j=1}^{d} L_j}{n}. \tag{33}
$$

Rearranging the inequality (33), we have

$$
\frac{1}{E} \sum_{s=1}^{E} \|\nabla f(\bar{x}_{t-1,s-1})\|^2 \leq \frac{2\mathbb{E}[f(x_{t-1}) - f(x_t)]}{E\gamma} + \frac{\gamma \zeta^2 L_{\max}}{n} + \frac{4\gamma^2 (E-1) E L_{\max}^2 (\zeta^2 + G^2)}{3}
$$
$$
+ \frac{2^{2z+1} E^{2z} \sqrt{Q_z + G^{4z+2}} G}{\sqrt{2}(2z+1)\sigma^{2z}} + \frac{\gamma 2^{4z} E^{4z+1}(Q_z + G^{4z+2}) L_{\max}}{2(2z+1)^2 \sigma^{4z}}
$$
$$
+ \frac{4\eta_z^2 \gamma \sigma^2 \sum_{j=1}^{d} L_j}{En}. \tag{34}
$$

Finally, by a telescopic sum, we obtain

$$
\mathbb{E}\left[\frac{1}{TE} \sum_{t=1}^{T} \sum_{s=1}^{E} \|\nabla f(\bar{x}_{t-1,s-1})\|^2\right] \leq \frac{2\mathbb{E}[f(x_0) - f^*]}{TE\gamma} + \frac{\gamma \zeta^2 L_{\max}}{n} + \frac{4\gamma^2 (E-1) E L_{\max}^2 (\zeta^2 + G^2)}{3}
$$
$$
+ \frac{2^{2z+1} E^{2z} \sqrt{Q_z + G^{4z+2}} G}{\sqrt{2}(2z+1)\sigma^{2z}} + \frac{\gamma 2^{4z} E^{4z+1}(Q_z + G^{4z+2}) L_{\max}}{2(2z+1)^2 \sigma^{4z}}
$$
$$
+ \frac{4\eta_z^2 \gamma \sigma^2 \sum_{j=1}^{d} L_j}{En}. \tag{35}
$$

Proof of Lemma 4. First, we know from function smoothness that

$$
f(x_t) - f(\bar{x}_t) \leq \langle \nabla f(\bar{x}_t), x_t - \bar{x}_t \rangle + \frac{\sum_{j=1}^{d} L_j \left(x_t(j) - \bar{x}_t(j)\right)^2}{2}. \tag{36}
$$

As can be seen from (36), we need to study the $x_t - \bar{x}_t$ in order to obtaining the upper bound for $f(x_t) - f(\bar{x}_t)$. Note that

$$x_t - \bar{x}_t = \frac{\gamma}{n} \sum_{i=1}^{n} \left(\eta_z \sigma \text{Sign} \left(\sum_{s=1}^{E} g_{t,s}^i + \sigma \xi_z \right) - \sum_{s=1}^{E} g_{t,s}^i \right). \tag{37}$$

For ease of presentation, we define that

$$\mathcal{A}_t^i \stackrel{\text{def.}}{=} \eta_z \sigma \text{Sign} \left(\sum_{s=1}^{E} g_{t,s}^i + \sigma \xi_z \right). \tag{38}$$

By taking the expectation over the random vector ξ_z, for any $j = 1, ..., d$, we have

$$\mathbb{E}_{\xi_z}[(x_t(j) - \bar{x}_t(j))^2] = \frac{\gamma^2}{n^2} \mathbb{E}_{\xi_z} \left[\left(\sum_{i=1}^{n} \left(\mathcal{A}_t^i - \sum_{s=1}^{E} g_{t,s}^i(j) \right) \right)^2 \right] \tag{39a}$$

$$= \frac{\gamma^2}{n^2} \mathbb{E}_{\xi_z} \left[\left(\sum_{i=1}^{n} \left(\mathcal{A}_t^i(j) - \mathbb{E}_{\xi_z} \left[\mathcal{A}_t^i(j) \right] + \mathbb{E}_{\xi_z} \left[\mathcal{A}_t^i(j) \right] - \sum_{s=1}^{E} g_{t,s}^i(j) \right) \right)^2 \right] \tag{39b}$$

$$\leq \frac{\gamma^2}{n^2} \mathbb{E}_{\xi_z} \left[\left(\sum_{i=1}^{n} \left(\mathcal{A}_t^i(j) - \mathbb{E}_{\xi_z} \left[\mathcal{A}_t^i(j) \right] \right) \right)^2 \right] \tag{39c}$$

$$+ \frac{\gamma^2}{n^2} \mathbb{E}_{\xi_z} \left[\left(\sum_{i=1}^{n} \left(\mathbb{E}_{\xi_z} \left[\mathcal{A}_t^i(j) \right] - \sum_{s=1}^{E} g_{t,s}^i(j) \right) \right)^2 \right], \tag{39d}$$

where the last inequality is obtained because $\sum_{i=1}^{n} \left(\mathcal{A}_t^i(j) - \mathbb{E}_{\xi_z} \left[\mathcal{A}_t^i(j) \right] \right)$ is zero-mean and independent of $\sum_{i=1}^{n} \left(\mathbb{E}_{\xi_z} \left[\mathcal{A}_t^i(j) \right] - \sum_{s=1}^{E} g_{t,s}^i(j) \right)$.

From (38) it is easy to check that $|\mathcal{A}_t^n(j)| \leq \eta_z^2 \sigma^2$. Hence, for the RHS of (39c), we have

$$\mathbb{E}_{\xi_z} \left[\left(\sum_{i=1}^{n} \left(\mathcal{A}_t^i(j) - \mathbb{E}_{\xi_z} \left[\mathcal{A}_t^i(j) \right] \right) \right)^2 \right] \stackrel{(a)}{=} \sum_{i=1}^{n} \mathbb{E}_{\xi_z} \left[\left(\mathcal{A}_t^i(j) - \mathbb{E}_{\xi_z} \left[\mathcal{A}_t^i(j) \right] \right)^2 \right]$$

$$\leq 2 \sum_{i=1}^{n} \left(\mathbb{E}_{\xi_z} \left[\left(\mathcal{A}_t^i(j) \right)^2 \right] + \left(\mathbb{E}_{\xi_z} \left[\mathcal{A}_t^i(j) \right] \right)^2 \right)$$

$$\leq 4n\eta_z^2 \sigma^2, \tag{40}$$

where equality (a) is true because $\mathcal{A}_t^1(j), ..., \mathcal{A}_t^n(j)$ are independent to each other.

Therefore, from (39) and (40) we have

$$\mathbb{E}_{\xi_z}\left[\sum_{j=1}^{d}L_j\left(x_t(j)-\bar{x}_t(j)\right)^2\right]=\sum_{j=1}^{d}L_j\mathbb{E}_{\xi_z}\left[\left(x_t(j)-\bar{x}_t(j)\right)^2\right] \tag{41a}$$

$$\leq\frac{4\eta_z^2\gamma^2\sigma^2\sum_{j=1}^{d}L_j}{n}$$
$$+\frac{\gamma^2}{n^2}\sum_{j=1}^{d}L_j\mathbb{E}_{\xi_z}\left[\left(\sum_{i=1}^{n}\left(\mathbb{E}_{\xi_z}\left[\mathcal{A}_t^i(j)\right]-\sum_{s=1}^{E}g_{t,s}^i(j)\right)\right)^2\right] \tag{41b}$$

$$\leq\frac{4\eta_z^2\gamma^2\sigma^2\sum_{j=1}^{d}L_j}{n}$$
$$+\frac{\gamma^2L_{\max}}{n^2}\mathbb{E}_{\xi_z}\left[\left\|\sum_{i=1}^{n}\left(\mathbb{E}_{\xi_z}\left[\mathcal{A}_t^i\right]-\sum_{s=1}^{E}g_{t,s}^i\right)\right\|^2\right]. \tag{41c}$$

To bound the RHS of (41c), we have

$$\mathbb{E}_{\xi_z}\left[\left\|\sum_{i=1}^{n}\left(\mathbb{E}_{\xi_z}\left[\mathcal{A}_t^i\right]-\sum_{s=1}^{E}g_{t,s}^i\right)\right\|^2\right]\leq n\sum_{i=1}^{n}\mathbb{E}_{\xi_z}\left[\left\|\mathbb{E}_{\xi_z}\left[\mathcal{A}_t^i\right]-\sum_{s=1}^{E}g_{t,s}^i\right\|^2\right]$$
$$\leq\frac{n}{4(2z+1)^2\sigma^{4z}}\sum_{i=1}^{n}\left\|\sum_{s=1}^{E}g_{t,s}^i\right\|_{4z+2}^{4z+2}, \tag{42}$$

where the last inequality is due to Lemma 1.

Now we need to bound

$$\mathbb{E}\left[\left\|\sum_{s=1}^{E}g_{t,s}^i\right\|_{4z+2}^{4z+2}\right],$$

where the expectation is taken over both ξ_z and the mini-batch gradient noise. To this end, we need the following lemma about the ℓ_p-norm.

Lemma 6. *For any $M\in\mathbb{Z}_+$, $p>1$ and M vectors $x_1,...,x_M\in\mathbb{R}^d$, we have*

$$\left\|\sum_{i=1}^{M}x_i\right\|_p^p\leq M^{p-1}\sum_{i=1}^{M}\|x_i\|_p^p. \tag{43}$$

As a direct application of Lemma 6, we obtain

$$\mathbb{E}\left[\left\|\sum_{s=1}^{E}g_{t,s}^i\right\|_{4z+2}^{4z+2}\right]\leq\mathbb{E}\left[E^{4z+1}\sum_{s=1}^{E}\left\|g_{t,s}^i\right\|_{4z+2}^{4z+2}\right]=E^{4z+1}\sum_{s=1}^{E}\mathbb{E}\left[\left\|g_{t,s}^i\right\|_{4z+2}^{4z+2}\right] \tag{44}$$

Then we can bound the RHS of (44) as

$$\mathbb{E}\left[\left\|g_{t,s}^i\right\|_{4z+2}^{4z+2}\right]=\mathbb{E}\left[\left\|g_{t,s}^i-\nabla f_i(x_{t,s-1}^i)+\nabla f_i(x_{t,s-1}^i)\right\|_{4z+2}^{4z+2}\right]$$
$$\overset{(a)}{\leq}\mathbb{E}\left[2^{4z+1}\left\|g_{t,s}^i-\nabla f_ti(x_{t,s-1}^i)\right\|_{4z+2}^{4z+2}+2^{4z+1}\left\|\nabla f_i(x_{t,s-1}^i)\right\|_{4z+2}^{4z+2}\right]$$
$$\overset{(b)}{\leq}2^{4z+1}Q_z+2^{4z+1}\left\|\nabla f_i(x_{t,s-1}^i)\right\|_2^{4z+2}$$
$$\overset{(c)}{\leq}2^{4z+1}(Q_z+G^{4z+2}), \tag{45}$$

where inequality (a) follows Lemma 6, inequality (b) is due to Assumption 2, and inequality (c) is due to A.4 of Assumption 1.

Combing (41), (42), (44) and (45), we have

$$
\mathbb{E}\left[\left\|\sum_{i=1}^{n}\left(\mathbb{E}_{\xi_z}\left[\mathcal{A}_t^i\right] - \sum_{s=1}^{E} g_{t,s}^i\right)\right\|\right] \leq \sqrt{\mathbb{E}\left[\left\|\sum_{i=1}^{n}\left(\mathbb{E}_{\xi_z}\left[\mathcal{A}_t^i\right] - \sum_{s=1}^{E} g_{t,s}^i\right)\right\|^2\right]}
$$

$$
\leq \sqrt{\frac{n^2 2^{4z} E^{4z+2}(Q_z + G^{4z+2})}{2(2z+1)^2 \sigma^{4z}}}
$$

$$
\leq \frac{n 2^{2z} E^{2z+1}\sqrt{(Q_z + G^{4z+2})}}{\sqrt{2}(2z+1)\sigma^{2z}} \tag{46}
$$

and

$$
\mathbb{E}\left[\sum_{j=1}^{d} L_j\left(x_t(j) - \bar{x}_t(j)\right)^2\right] \leq \frac{4\eta_z^2 \gamma^2 \sigma^2 \sum_{j=1}^{d} L_j}{n} + \frac{\gamma^2 L_{\max}}{n^2}\mathbb{E}\left[\left\|\sum_{i=1}^{n}\left(\mathbb{E}_{\xi_z}\left[\mathcal{A}_t^i\right] - \sum_{s=1}^{E} g_{t,s}^i\right)\right\|^2\right]
$$

$$
\leq \frac{4\eta_z^2 \gamma^2 \sigma^2 \sum_{j=1}^{d} L_j}{n} + \frac{\gamma^2 2^{4z+1} E^{4z+2}(Q_z + G^{4z+2})L_{\max}}{4(2z+1)^2 \sigma^{4z}}. \tag{47}
$$

Hence, we have

$$
\mathbb{E}\left[f(x_t) - f(\bar{x}_t)\right] \leq \mathbb{E}\left[\left\langle \nabla f(\bar{x}_t), \frac{\gamma}{n}\sum_{i=1}^{n}\left(\mathbb{E}_{\xi_z}\left[\mathcal{A}_t^i\right] - \sum_{s=1}^{E} g_{t,s}^i\right)\right\rangle\right]
$$

$$
+ \mathbb{E}\left[\frac{\sum_{j=1}^{d} L_j\left(x_t(j) - \bar{x}_t(j)\right)^2}{2}\right]
$$

$$
\leq \|\nabla f(\bar{x}_t)\|\mathbb{E}\left[\left\|\frac{\gamma}{n}\sum_{i=1}^{n}\left(\mathbb{E}_{\xi_z}\left[\mathcal{A}_t^i\right] - \sum_{s=1}^{E} g_{t,s}^i\right)\right\|\right]
$$

$$
+ \mathbb{E}\left[\frac{\sum_{j=1}^{d} L_j\left(x_t(j) - \bar{x}_t(j)\right)^2}{2}\right]
$$

$$
\leq \frac{\gamma 2^{2z} E^{2z+1}\sqrt{Q_z + G^{4z+2}}G}{\sqrt{2}(2z+1)\sigma^{2z}} + \frac{\gamma^2 2^{4z} E^{4z+2}(Q_z + G^{4z+2})L_{\max}}{4(2z+1)^2 \sigma^{4z}}
$$

$$
+ \frac{2\eta_z^2 \gamma^2 \sigma^2 \sum_{j=1}^{d} L_j}{n}. \tag{48}
$$

$\square$

Proof of Lemma 6. To prove this lemma, we need to use a classical result on the monotonicity of ℓ_p norm:

Lemma 7. *(Kantorovich & Akilov, 2016) For any $x \in \mathbb{R}^d$ and $1 < r < p$, we have*

$$
\|x\|_p \leq \|x\|_r \leq d^{\frac{1}{r} - \frac{1}{p}}\|x\|_p. \tag{49}
$$

Now from the definition of ℓ_p norm we have

$$
\begin{aligned}
\left\| \sum_{i=1}^{M} x_i \right\|_p^p &= \sum_{j=1}^{d} \left(\sum_{i=1}^{M} x_i(j) \right)^p \leq \sum_{j=1}^{d} \left(\sum_{i=1}^{M} |x_i(j)| \right)^p \\
&= \sum_{j=1}^{d} \left\| [x_1(j), ..., x_M(j)]^\top \right\|_1^p \\
&\stackrel{(a)}{\leq} M^{p-1} \sum_{j=1}^{d} \left\| [x_1(j), ..., x_M(j)]^\top \right\|_p^p \\
&= M^{p-1} \sum_{j=1}^{d} \sum_{i=1}^{M} (x_i(j))^p \\
&= M^{p-1} \sum_{i=1}^{M} \|x_i\|_p^p,
\end{aligned}
\tag{50}
$$

where inequality (a) is due to Lemma 7. $\qquad\square$

Proof of Lemma 5. First we unroll the difference $f(\bar{x}_t) - f(x_{t-1})$ into a telescopic sum across E local steps.

$$
f(\bar{x}_t) - f(x_{t-1}) = f(\bar{x}_{t-1,E}) - f(\bar{x}_{t-1,0}) = \sum_{s=1}^{E} f(\bar{x}_{t-1,s}) - f(\bar{x}_{t-1,s-1}) \tag{51a}
$$

$$
\leq \sum_{s=1}^{E} \left(-\langle \nabla f(\bar{x}_{t-1,s-1}), \bar{x}_{t-1,s-1} - \bar{x}_{t-1,s} \rangle + \frac{L_{\max}}{2} \|\bar{x}_{t-1,s} - \bar{x}_{t-1,s-1}\|^2 \right) \tag{51b}
$$

$$
= \sum_{s=1}^{E} \left(-\gamma \langle \nabla f(\bar{x}_{t-1,s-1}), \frac{1}{n} \sum_{i=1}^{n} g_{t-1,s}^i \rangle + \frac{\gamma^2 L_{\max}}{2} \left\| \frac{1}{n} \sum_{i=1}^{n} g_{t-1,s}^i \right\|^2 \right), \tag{51c}
$$

where the inequality is due to the smoothness assumption. Taking expectation over the mini-batch gradient noise $g_{t-1,s}^1, ..., g_{t-1,s}^n$, for the first terms in (51c), we obtain

$$
\mathbb{E}\left[-\langle \nabla f(\bar{x}_{t-1,s-1}), \frac{1}{n} \sum_{i=1}^{n} g_{t-1,s}^i \rangle \right] = -\langle \nabla f(\bar{x}_{t-1,s-1}), \frac{1}{n} \sum_{i=1}^{n} \nabla f_i(x_{t-1,s-1}^i) \rangle \tag{52a}
$$

$$
= -\frac{1}{2} \|\nabla f(\bar{x}_{t-1,s-1})\|^2 - \frac{1}{2} \left\| \frac{1}{n} \sum_{i=1}^{n} \nabla f_i(x_{t-1,s-1}^i) \right\|^2 \tag{52b}
$$

$$
+ \frac{1}{2} \left\| \nabla f(\bar{x}_{t-1,s-1}) - \frac{1}{n} \sum_{i=1}^{n} \nabla f_i(x_{t-1,s-1}^i) \right\|^2. \tag{52c}
$$

For the second terms in (51c), we have

$$
\mathbb{E}\left[\left\|\frac{1}{n}\sum_{i=1}^{n}g_{t-1,s}^{i}\right\|^{2}\right] = \mathbb{E}\left[\left\|\frac{1}{n}\sum_{i=1}^{n}g_{t-1,s}^{i} - \frac{1}{n}\sum_{i=1}^{n}\nabla f_{i}(x_{t-1,s-1}^{i}) + \frac{1}{n}\sum_{i=1}^{n}\nabla f_{i}(x_{t-1,s-1}^{i})\right\|^{2}\right]
$$

$$
\stackrel{(a)}{=} \mathbb{E}\left[\left\|\frac{1}{n}\sum_{i=1}^{n}g_{t-1,s}^{i} - \frac{1}{n}\sum_{i=1}^{n}\nabla f_{i}(x_{t-1,s-1}^{i})\right\|^{2}\right] + \left\|\frac{1}{n}\sum_{i=1}^{n}\nabla f_{i}(x_{t-1,s-1}^{i})\right\|^{2}
$$

$$
\stackrel{(b)}{=} \frac{1}{n^{2}}\sum_{i=1}^{n}\mathbb{E}\left[\left\|g_{t-1,s}^{i} - \frac{1}{n}\sum_{i=1}^{n}\nabla f_{i}(x_{t-1,s-1}^{i})\right\|^{2}\right] + \left\|\frac{1}{n}\sum_{i=1}^{n}\nabla f_{i}(x_{t-1,s-1}^{i})\right\|^{2}
$$

$$
\stackrel{(c)}{\leq} \frac{\zeta^{2}}{n} + \left\|\frac{1}{n}\sum_{i=1}^{n}\nabla f_{i}(x_{t-1,s-1}^{i})\right\|^{2}, \tag{53}
$$

where equalities (a) and (b) are true because the mini-batch gradient noise is independent, and inequality (c) is due to A.1 of Assumption 1.

Notice that owing to the function smoothness, we have for arbitrary $x, y \in \mathbb{R}^{d}$,

$$
f(y) \leq \langle \nabla f(x), y - x \rangle + \frac{L_{\max}}{2}\|y - x\|^{2}, \tag{54}
$$

which is equivalent to

$$
\|\nabla f(x) - \nabla f(y)\| \leq L_{\max}\|y - x\|. \tag{55}
$$

Now to bound the term in (52c), for every s, we have

$$
\left\|\nabla f(\bar{x}_{t-1,s-1}) - \frac{1}{n}\sum_{i=1}^{n}\nabla f_{i}(x_{t-1,s-1}^{i})\right\|^{2}
$$

$$
= \left\|\frac{1}{n}\sum_{i=1}^{n}\nabla f_{i}(\bar{x}_{t-1,s-1}) - \frac{1}{n}\sum_{i=1}^{n}\nabla f_{i}(x_{t-1,s-1}^{i})\right\|^{2}
$$

$$
\leq \frac{L^{2}}{n}\sum_{i=1}^{n}\|\bar{x}_{t-1,s-1} - x_{t-1,s-1}^{i}\|^{2}
$$

$$
= \frac{\gamma^{2}L_{\max}^{2}}{n}\sum_{i=1}^{n}\left\|\sum_{q=1}^{s-1}\left(\frac{1}{n}\sum_{j=1}^{n}g_{t-1,q}^{j} - g_{t-1,q}^{i}\right)\right\|^{2}
$$

$$
\leq \frac{(s-1)\gamma^{2}L_{\max}^{2}}{n}\sum_{i=1}^{n}\sum_{q=1}^{s-1}\left\|\frac{1}{n}\sum_{j=1}^{n}g_{t-1,q}^{j} - g_{t-1,q}^{i}\right\|^{2}
$$

$$
\leq \frac{2(s-1)\gamma^{2}L_{\max}^{2}}{n}\sum_{i=1}^{n}\sum_{q=1}^{s-1}\left(\left\|\frac{1}{n}\sum_{j=1}^{n}g_{t-1,q}^{j}\right\|^{2} + \left\|g_{t-1,q}^{i}\right\|^{2}\right)
$$

$$
\leq \frac{2(s-1)\gamma^{2}L_{\max}^{2}}{n}\sum_{i=1}^{n}\sum_{q=1}^{s-1}\left(\frac{1}{n}\sum_{j=1}^{n}\left\|g_{t-1,q}^{j}\right\|^{2} + \left\|g_{t-1,q}^{i}\right\|^{2}\right). \tag{56}
$$

For any $t = 1, ..., T$, $i = 1, ..., n$ and $q = 1, ..., s - 1$, taking expectation over mini-batch gradient noise, we have

$$
\mathbb{E}\left[\left\|g_{t-1,q}^{j}\right\|^{2}\right] = \mathbb{E}\left[\left\|g_{t-1,q}^{i} - \nabla f_{i}(x_{t-1,q-1}^{i}) + \nabla f_{i}(x_{t-1,q-1}^{i})\right\|^{2}\right]
$$

$$
\leq \mathbb{E}\left[\left\|g_{t-1,q}^{i} - \nabla f_{i}(x_{t-1,q-1}^{i})\right\|^{2}\right] + \left\|\nabla f_{i}(x_{t-1,q-1}^{i})\right\|^{2}
$$

$$
\leq \zeta^{2} + G^{2}. \tag{57}
$$

Substituting (57) into (56), we have

$$\left\| \nabla f(\bar{x}_{t-1,s-1}) - \frac{1}{n} \sum_{i=1}^{n} \nabla f_i(x_{t-1,s-1}^i) \right\|^2 \le 4(s-1)^2 \gamma^2 L_{\max}^2 (\zeta^2 + G^2). \tag{58}$$

Further substituting (53), (52) and (58) into (51) and by rearranging the terms, we obtain

$$\mathbb{E}[f(\bar{x}_t) - f(x_{t-1})] \le \sum_{s=1}^{E} \left(-\frac{\gamma}{2} \|\nabla f(\bar{x}_{t-1,s-1})\|^2 + \frac{\gamma^2 L_{\max} - \gamma}{2} \left\| \frac{1}{n} \sum_{i=1}^{n} \nabla f_i(x_{t-1,s-1}^i) \right\|^2 \right)$$

$$+ \sum_{s=1}^{E} \left(\frac{\gamma^2 \zeta^2 L_{\max}}{2n} + \frac{\gamma}{2} \|\nabla f(\bar{x}_{t-1,s-1}) - \frac{1}{n} \sum_{i=1}^{n} \nabla f_i(x_{t-1,s-1}^i)\|^2 \right)$$

$$\overset{(a)}{\le} -\frac{\gamma}{2} \sum_{s=1}^{E} \|\nabla f(\bar{x}_{t-1,s-1})\|^2 + \frac{E\gamma^2 \zeta^2 L_{\max}}{2n}$$

$$+ \sum_{s=1}^{E} 2(s-1)^2 \gamma^3 L_{\max}^2 (\zeta^2 + G^2), \tag{59}$$

where inequality (a) is by $(\gamma^2 L_{\max} - \gamma) \le 0$.

Note that

$$\sum_{s=1}^{E} (s-1)^2 = \frac{(E-1)E(2E-1)}{6} \le \frac{(E-1)E^2}{3}. \tag{60}$$

By applying it to (59), we finally have

$$\mathbb{E}[f(\bar{x}_t) - f(x_{t-1})] \le -\frac{\gamma}{2} \sum_{s=1}^{E} \|\nabla f(\bar{x}_{t-1,s-1})\|^2 + \frac{E\gamma^2 \zeta^2 L_{\max}}{2n} + \frac{2\gamma^3 (E-1)E^2 L_{\max}^2 (\zeta^2 + G^2)}{3}. \tag{61}$$

$\square$

C.4 PROOF OF THEOREM 3

We need a lemma similar to Lemma 4.

Lemma 8. *Suppose that Assumption 1 and 3 hold. For the t-th ($1 \le t \le T$) communication round in Algorithm 1, if $\eta = \sigma$ and $z = +\infty$, and $\sigma > E(G + Q_\infty)$, then*

$$\mathbb{E}[f(x_t) - f(\bar{x}_t)] \le \frac{2\gamma^2 \sigma^2 \sum_{j=1}^{d} L_j}{n}. \tag{62}$$

Following the similar idea as in the proof of Theorem 1, we have

$$\mathbb{E}[f(x_t) - f(x_{t-1})] = \mathbb{E}[f(x_t) - f(\bar{x}_t)] + E[f(\bar{x}_t) - f(x_{t-1})]$$

$$\le -\frac{\gamma}{2} \sum_{s=1}^{E} \|\nabla f(\bar{x}_{t-1,s-1})\|^2 + \frac{E\gamma^2 \zeta^2 L_{\max}}{2n}$$

$$+ \frac{2\gamma^3 (E-1)E^2 L_{\max}^2 (\zeta^2 + G^2)}{3} + \frac{2\gamma^2 \sigma^2 \sum_{j=1}^{d} L_j}{n}. \tag{63}$$

Rearranging the terms, we have

$$\frac{1}{E} \sum_{s=1}^{E} \|\nabla f(\bar{x}_{t-1,s-1})\|^2 \le \frac{2\mathbb{E}[f(x_{t-1}) - f(x_t)]}{E\gamma} + \frac{\gamma \zeta^2 L_{\max}}{n}$$

$$+ \frac{4\gamma^2 (E-1)E L_{\max}^2 (\zeta^2 + G^2)}{3} + \frac{4\gamma \sigma^2 \sum_{j=1}^{d} L_j}{En}. \tag{64}$$

Form the telescopic sum, we obtain

$$\mathbb{E}\left[\frac{1}{TE}\sum_{t=1}^{T}\sum_{s=1}^{E}\|\nabla f(\bar{x}_{t-1,s-1})\|^2\right] \leq \frac{2\mathbb{E}[f(x_0)-f^*]}{TE\gamma} + \frac{\gamma\zeta^2 L_{\max}}{n}$$
$$+ \frac{4\gamma^2(E-1)EL_{\max}^2(\zeta^2+G^2)}{3} + \frac{4\gamma\sigma^2\sum_{j=1}^{d}L_j}{En}. \quad (65)$$

Here we provide a simple example to show that when $\sigma < E(G + Q_\infty)$, the algorithm cannot converge. Consider $E = 1$, $Q_\infty = 0$ and the problem

$$\min_{x\in\mathbb{R}}(x - A)^2 + (x + A)^2,$$

where $A > 0$ is some positive number. If we choose the initial to be $x_0 = \frac{A}{2}$. As one can see, the gradient at x_0 for the two parts of the objective function are $-A$ and $3A$, respectively. We denote that ξ_∞ as the random noise following uniform distribution at $[-1, 1]$. If now $\sigma < A$, we have

$$\text{Sign}(-A + \sigma\xi_\infty) + \text{Sign}(3A + \sigma\xi_\infty) = 0, \quad (66)$$

i.e., this algorithm never update the variable.

Proof of Lemma 8. We first note that, when $z = +\infty$, we have

$$\Psi_\infty(x) = \begin{cases} x & x \in [-1, 1], \\ -1 & x < -1, \\ 1 & x > 1. \end{cases} \quad (67)$$

Again, from the smoothness assumption (A.2 in Assumption 1) we have,

$$f(x_t) - f(\bar{x}_t) \leq \langle\nabla f(\bar{x}_t), x_t - \bar{x}_t\rangle + \frac{\sum_{j=1}^{d}L_j\left(x_t(j) - \bar{x}_t(j)\right)^2}{2}. \quad (68)$$

Taking expectation over ξ_∞,

$$\mathbb{E}_{\xi_\infty}[x_t - \bar{x}_t] = \mathbb{E}_{\xi_\infty}\left[\frac{\gamma}{n}\sum_{i=1}^{n}\left(\sigma\text{Sign}\left(\sum_{s=1}^{E}g_{t,s}^i + \sigma\xi_\infty\right) - \sum_{s=1}^{E}g_{t,s}^i\right)\right]$$
$$\overset{(a)}{=} \frac{\gamma}{n}\sum_{i=1}^{n}\left(\sigma\Psi_\infty\left(\frac{\sum_{s=1}^{E}g_{t,s}^i}{\sigma}\right) - \sum_{s=1}^{E}g_{t,s}^i\right)$$
$$\overset{(b)}{=} \frac{\gamma}{n}\sum_{i=1}^{n}\left(\sum_{s=1}^{E}g_{t,s}^i - \sum_{s=1}^{E}g_{t,s}^i\right) = 0, \quad (69)$$

where equality (a) is because for any $x \in \mathbb{R}^d$, $\mathbb{E}_{\xi_\infty}[\text{Sign}(x + \sigma\xi_\infty)] = \Psi_\infty(x/\sigma)$, equality (b) is due to $\sigma > \|\sum_{s=1}^{E}g_{t,s}^i\|_\infty$ almost surely and the property of the function $\Psi_\infty(\cdot)$ in (67).

For ease of presentation, we define that

$$\mathcal{B}_t^i \overset{\text{def.}}{=} \sigma\text{Sign}\left(\sum_{s=1}^{E}g_{t,s}^i + \sigma\xi_\infty\right). \quad (70)$$

From (69) we have learned that $\mathbb{E}_{\xi_\infty}[\mathcal{B}_t^i] = \sum_{s=1}^E g_{t,s}^i$. Thus, for any $j = 1, ..., d$, we have

$$
\begin{aligned}
\mathbb{E}_{\xi_\infty}[(x_t(j) - \bar{x}_t(j))^2] &\leq \frac{\gamma^2}{n^2}\mathbb{E}_{\xi_\infty}\left[\left(\sum_{i=1}^n \left(\mathcal{B}_t^i(j) - \mathbb{E}_{\xi_\infty}\left[\mathcal{B}_t^i(j)\right]\right)\right)^2\right] \\
&= \frac{\gamma^2}{n^2}\sum_{i=1}^n \mathbb{E}_{\xi_\infty}\left[\left(\mathcal{B}_t^i(j) - \mathbb{E}_{\xi_\infty}\left[\mathcal{B}_t^i(j)\right]\right)^2\right] \\
&\leq \frac{2\gamma^2}{n^2}\sum_{i=1}^n \left(\mathbb{E}_{\xi_\infty}\left[\left(\mathcal{B}_t^i(j)\right)^2\right] + \left(\mathbb{E}_{\xi_\infty}\left[\mathcal{B}_t^i(j)\right]\right)^2\right) \\
&\leq \frac{4\gamma^2\sigma^2}{n}.
\end{aligned}
\tag{71}
$$

Finally, substituting (69) and (71) into (68), and taking the expectation over both ξ_∞ and the mini-batch gradient noise, we have

$$
\begin{aligned}
\mathbb{E}[f(x_t) - f(\bar{x}_t)] &\leq \mathbb{E}[\langle \nabla f(\bar{x}_t), x_t - \bar{x}_t \rangle] + \mathbb{E}\left[\frac{\sum_{j=1}^d L_j \left(x_t(j) - \bar{x}_t(j)\right)^2}{2}\right] \\
&\leq \frac{2\gamma^2\sigma^2 \sum_{j=1}^d L_j}{n}.
\end{aligned}
\tag{72}
$$

$\square$

D DIFFERENTIALLY PRIVATE SIGN-BASED FEDERATED AVERAGING

In this section, we describe the differential private version of Algorithm 1. The algorithm is summarized in Algorithm 2. Compared to Algorithm 1, we consider the use of Gaussian noise only ($z = 1$) in order to fulfill the DP requirement. To obtain the user-level privacy guarantee, we adopt the privacy accounting method in (Mironov et al., 2019).

Algorithm 2 DP-SignFedAvg

Require: Total communication rounds T, Number of local steps E, Number of clients n, Client sampling ratio q, Clients stepsize γ, Server stepsize η, Noise coefficient σ, Norm clipping coefficient C.

1: Initialize x_0 and for $i = 1, ..., n$.
2: **for** $t = 1$ to T **do**
3:     Sample a set of clients $\mathcal{S}$ with size qn for current round.
4:     **On Clients:**
5:     **for** i in $\mathcal{S}$ **do**
6:         $x_{t-1,0}^i = x_{t-1}$
7:         **for** $s = 1$ to E **do**
8:             $g_{t-1,s}^i = g_i(x_{t-1,s-1}^i)$, where $g_i(\cdot)$ is the mini-batch gradient oracle of the i-th client.
9:             $x_{t-1,s}^i = x_{t-1,s-1}^i - \gamma g_{t-1,s}^i$.
10:        **end for**
11:        $\Delta_{t-1}^i = \text{Sign}\left(\frac{x_{t-1} - x_{t-1,E}^i}{\max\{1, \|x_{t-1} - x_{t-1,E}^i\|/C\}} + \mathcal{N}(0, \sigma^2 C^2 I)\right)$.
12:        Send Δ_{t-1}^i to the server.
13:     **end for**
14:     **On Server:**
15:     $x_t = x_{t-1} - \eta\frac{1}{n}\sum_{i=1}^n \Delta_{t-1}^i$.
16:     Broadcast x_t to clients.
17: **end for**
18: **return** x_T.

E   EXPERIMENT DETAILS

E.1   DETAILS FOR THE EXPERIMENT IN SECTION 4.2

In Table 3, we provide the tuned hyperparameters for all the tested algorithms on non-i.i.d MNIST. Specifically, we tuned the hyperparameters via grid search: $[0.1, 0.05, 0.01, 0.005]$ for stepsize, $[0, 0.3, 0.5, 0.7, 0.9]$ for the momentum coefficient, and $[0, 0.02, 0.05, 0.01, 0.03, 0.05, 0.1, 0.3, 0.5]$ for the noise scale.

Algorithm	Stepsize	Momentum coefficient	Noise scale
SGDwM	0.05	0.9	
EF-SignSGDwM	0.05	0.9	
Sto-SignSGDwM	0.01	0.9	
SignSGD	0.01	0	0
1-SignSGD	0.01	0	0.05
∞-SignSGD	0.01	0	0.05

Table 3: Hyperparameters used for FL on non-i.i.d MNIST.

In Figure 7, we visualize the performance of 1-SignSGD and ∞-SignSGD under different noise scales. As we can see, the results for 1-SignSGD and ∞-SignSGD are almost the same, except that the ∞-SignSGD is slightly better than 1-SignSGD when the noise scale is large.

(a) Training Loss:1-SignSGD

(b) Test Accuracy:1-SignSGD

(c) Training Loss:∞-SignSGD

(d) Test Accuracy:∞-SignSGD

Figure 7: z-SignFedAvg under different noise scales on non-i.i.d MNIST

E.2   DETAILS FOR THE EXPERIMENT IN SECTION 4.3

We denote the noiseless case, i.e., Algorithm 1 with $\sigma = 0$ as SignFedAvg.

EMNIST: For the experiment on EMNIST, we fixed the client stepsize as 0.05. We tuned the server stepsize, noise scales via grid search: $[1, 0.5, 0.1, 0.05, 0.01, 0.005]$ for stepsize, $[0, 0.005, 0.02, 0.05, 0.01, 0.03, 0.05, 0.1, 0.2]$ for noise scale. The comparison between 1-SignFedAvg and ∞-SignFedAvg on EMNIST is shown in Figure 8. The used hyperparameter in the Figure 4 and 8 are summarized in Table 4. We also visualize the performance of 1-SignFedAvg and ∞-SignFedAvg under various noise scales and local steps in Figure 9 and Figure 10.

CIFAR-10: For the experiment on CIFAR-10, we fixed the client stepsize as 0.1. We tuned the server stepsize, noise scales via grid search: $[10^0, 10^{-0.5}, 10^{-1}, 10^{-1.5}, 10^{-2}, 10^{-2.5}, 10^{-3}]$ for the stepsize, $[0, 0.0001, 0.0005, 0.001, 0.005]$ for the noise scale. The comparison between 1-SignFedAvg and ∞-SignFedAvg on CIFAR-10 is displayed in Figure 11. The used hyperparameter in the Figure 5 and 11 are summarized in Table 5. We also visualize the performance of 1-SignFedAvg and ∞-SignFedAvg under various noise scales and different numbers of local steps in Figure 12 and Figure 13. An interesting phenomenon in Figure 12 amd Figure 13 is that the more local steps are, the less impact the additive noise has on the convergence performance.

(a) Training Loss   (b) Test Accuracy   (c) Test Accuracy w.r.t bits

Figure 8: Performance of 1-SignFedAvg and ∞-SignFedAvg on EMNIST dataset.

Algorithm	Server stepsize	Noise scale
1-SignFedAvg	0.03	0.01
∞-SignFedAvg	0.03	0.01
SignFedAvg	0.03	0

Table 4: Hyperparameters for tested Algorithms on EMNIST.

(a) $E = 2$ (b) $E = 5$ (c) $E = 10$ (d) $E = 20$

(e) $E = 2$ (f) $E = 5$ (g) $E = 10$ (h) $E = 20$

Figure 9: EMNIST: 1-SignFedAvg under different noise scales and different numbers of local steps

Figure 10: EMNIST: ∞-SignFedAvg under different noise scales and different numbers of local steps

Algorithm	Server stepsize	Noise scale
1-SignFedAvg	0.0032	0.0005
∞-SignFedAvg	0.0032	0.0005
SignFedAvg	0.0032	0

Table 5: Hyperparameters for tested Algorithms on CIFAR-10.

Figure 11: Performance of 1-SignFedAvg and ∞-SignFedAvg on CIFAR-10 dataset.

Figure 12: CIFAR-10: 1-SignFedAvg under different noise scales and different numbers of local steps

Figure 13: CIFAR-10: ∞-SignFedAvg under different noise scales and different numbers of local steps

E.3   DETAILS FOR THE EXPERIMENT IN SECTION 4.4

Similar to (Kairouz et al., 2021), we run the experiments under the privacy budgets $\varepsilon = [1, 2, 4, 6, 8, 10]$. In Table 6, we provide the hyperparameter for DP-FedAvg and DP-SignFedAvg for all levels of privacy budgets. Unlike previous experiments, the noise scales used in this experiment were determined by the privacy budget and the privacy accounting method in (Mironov et al., 2019).

Privacy budget	η for DP-FedAvg	η for DP-SignFedAvg	Noise scale
1.0029	1	0.03	2.77
2.0171	2	0.05	1.57
4.0459	5	0.05	1.02
6.0135	5	0.05	0.845
8.0336	5	0.05	0.75
9.9996	5	0.05	0.685

Table 6: Hyperparameters for DP Algorithms on EMNIST.